




Figure 7-12: CDMA periodic ranging

for WirelessMAN-SC, where rain fade is the biggest physical degradation culprit, the BS generally needs to receive something from an SS every 80 or so milliseconds; otherwise, it may drop back to the most robust burst profile to ensure it can be heard. This monitoring constraint is a small burden, but the actual change is easy. Since each allocation in a UL MAP specifies the SS and the UIUC, the BS commands a change by simply allocating bandwidth for the SS using a new UIUC, from the set previously defined in the UCD message, in the UL MAP.

The DL can be more complicated. In the DL, while the SS has the advantage (except in certain AAS cases) of always hearing the broadcast portion of the DL, it constantly updates its measure of the DL quality from its point of view. The problem is informing the BS of a need for a change. Typically, the SS will request a change via either a downlink burst profile change (DBPC) message, if it has bandwidth allocated on the UL, or using an RNG-REQ message in a ranging interval, if it does not have its own UL allocation. For some situations with some PHYs, the BS may also periodically request PHY metrics from the SS to fine-tune such issues as which subchannels to use. For MAP efficiency purposes, the DL MAP, unlike the UL MAP, for most IEEE 802.16 PHYs does not direct a DL interval to an individual SS. The SS merely decodes all data that are as robust or more robust than the last negotiated DL burst profile. This is an important point. It allows the BS to send data to the SS using a more robust burst profile before first communicating its intent to switch, as shown in Figure 7-13. It also allows the BS to tell the SS to start listening to a less robust burst profile and then immediately begin sending data with that profile, as shown in Figure 7-14. This avoids complicated synchronization of the messages and the burst profile changes. In some cases, with some PHYs, the DL bursts are identified in the DL MAP as being directed to a specific SS. In these cases, the process works much like the UL process.




Figure 7-13: Transition to more robust burst profile




Figure 7-14: Transition to less robust burst profile

QoS AND SERVICE FLOWS

Dynamic service establishment and deletion

Besides the BS-initiated DSA described in the network entry and initialization section at the beginning of this chapter, other mechanisms are defined for SS-initiated DSA, as illustrated in Figure 7-15.




Figure 7-15: DSA message flow—SS initiated

The standard does not go into details on what actually triggers the DSA; triggering is just assumed to happen, stimulated by the upper layers when needed. For example, a nomadic device may be powered on in a network, similar to Wi-Fi networks that might be found in an airport or other public place today. The SS, being unknown to the network, asks for service. Authentication includes validating the user's credit card. Looking forward to IEEE Std 802.16e and mobility, another example would be a mobile VoIP call initiated at the MS.

One noteworthy detail in the procedure is the DSX-RVD (dynamic service addition, change, or deletion received) message that only acknowledges the reception of the DSA-REQ (dynamic service addition request) message by the BS. This allows the BS to take its time determining whether to admit the service flow without triggering unnecessary retransmissions of the DSA-REQ.

There may also be a need to change the parameters and state of the existing service flow in response to external circumstances. This can be done with the dynamic service change (DSC) procedure that is almost identical to the DSA.

Service flows are deleted using the DSD-REQ (dynamic service deletion request) message and the DSD-RSP (dynamic service deletion response) message. Deletion can be initiated by either BS or SS. Only one service flow can be deleted per message exchange.

QoS model

When IEEE Std 802.16 was in its early stages, the primary focus was from companies targeting last-mile extension of fiber and the PMP backhaul of cellular sites. At that time, IP core networks were considered interesting, but ATM core networks were the norm. Furthermore, ATM was highly advanced in its QoS support. The result was that QoS in IEEE Std 802.16 was modeled after ATM. Some of the concepts were modified based on input from proprietary system proposals and based on proposals for “wireless DOCSIS.” As it turned out, ATM, DOCSIS, and the proprietary systems are compatible in their QoS concepts.

While extension of ATM networks was an early market driver, IP was considered to be the future, and the developers of IEEE Std 802.16 did not want to tie the standard too closely to ATM. DOCSIS, as it turned out, was forward-looking in its application of QoS and traffic parameters and was compatible with both ATM and IP services. Because of this, the QoS description and naming conventions from DOCSIS were chosen as the basis for describing QoS in IEEE Std 802.16. Other parts of the DOCSIS model were adopted as well, including the three-state model in which a service can be provisioned, admitted, or active. The state impacts the actual reservation state of the resources necessary for the service.

In order for QoS and traffic parameters to be fully applied to services, IEEE Std 802.16 MAPs services, including connectionless services, to an IEEE 802.16 MAC connection. This is done in basically the same manner as in ATM and in the UL of DOCSIS. Similar concepts are employed in Ethernet virtual circuits in metro Ethernet. Typically, a service is bidirectional,

resulting in the mapping to separate UL and DL IEEE 802.16 MAC connections.

The benefit of connection-oriented mapping of services is that it provides a “handle” with which the MAC, in particular the scheduler and QoS engines, can associate a packet with the full realm of QoS and traffic parameters, instead of just simple individual packet parameters such as a priority. Since no packets are expected until a service is active and no resources are reserved until a service is at least admitted, services in the provisioned state are not mapped to IEEE 802.16 connections. The services are mapped only when they become admitted or active.

QoS and traffic parameters

A number of QoS and traffic parameters, which the IEEE 802.16 standard calls *service flow encodings*, are available to help in the implementation of QoS within an IEEE 802.16 system.

SFID and CID

The SFID and CID are important concepts at the foundation of IEEE 802.16 QoS. The SFID identifies a service, which in turn identifies the right of an IEEE 802.16 SS to certain system resources, and also defines which of a user’s packets will be mapped to the corresponding IEEE 802.16 MAC connection. The CID is then used internally in the IEEE 802.16 MAC for determining which SS receives the data on the DL, which service it maps to on the UL, and, most importantly, what QoS and traffic parameters are associated with the traffic. The mapping of potentially connectionless traffic to MAC connections is called *classification*. It typically involves some amount of packet inspection and can work much like a combination of a router and a bridge. Classification of IP, VLAN, Ethernet, and ATM to IEEE 802.16 MAC CIDs is currently defined in the standard.

Service class name

The service class name is a parameter that implies a predefined set of other QoS parameters. There is not much demand to define such common service

types yet. Once specific methods for handling certain services is agreed upon (if ever) by industry, service classes will most likely be used as an efficient shorthand for sets of parameters.

QoS parameter set type

The QoS parameter set type indicates whether the current set of parameters is the provisioned, admitted, or active set, as shown in Figure 7-16 and Figure 7-17.




Figure 7-16: Provisioned authorization model

The differences between parameter sets are as follows:

1. The provisioned set is one that is allowed; i.e., when a service-level agreement (SLA) was set up, this is what the users paid for. But the provisioned set is neither reserved nor allocated. Depending on the implementation, the provisioned set may be ignored by the BS's call admission control (CAC) function. For instance, in a mobile system, the users have paid for a service and have a right to certain resources. However, if their phones are turned off, they have no resources allocated, and the BSs ignore them from a CAC point of view because they may never turn on or roam into their field of view.




Figure 7-17: Dynamic authorization model

2. The admitted set is one that is allocated but not being used. IEEE Std 802.16 is a bandwidth-on-demand system in which users get their guaranteed bandwidth only if they ask for it. Allocated but unused bandwidth will cause CAC to keep the resources for this service in reserve so they are available, but will allow other services that are peaking above their guaranteed bandwidth to use the resources on a BE basis. This could be useful in a handover situation, with the necessary resources "admitted" on the new BS prior to the handover.
3. The active set is one that is currently reserved and being used by a service. For bursty services, there is little to distinguish it from the admitted set, since they both consume resources from a CAC point of view, but bandwidth is not used until requested. Technically, the service can't ask for the bandwidth until it transitions to the active state; therefore, the admitted set would rarely be used for bursty services.

These parameters have some interesting potential above and beyond simple resource reservation. For instance, SIP-based VoIP could be modeled as a low-bandwidth (but guaranteed), bursty, nonreal-time polling service (nrtPS) for the SIP signaling, coupled with a fixed-bandwidth UGS [more likely extended real-time polling service (rtPS) in IEEE Std 802.16e] that toggles between provisioned and active, where the active bandwidth may be modified from the provisioned due to choice of codec.

Traffic priority

Traffic priority is a value from 0 to 7 that describes the priority of traffic. Priority alone, in a situation of frequent congestion, does not provide QoS but rather causes starvation. Therefore, this parameter should be used sparingly. It should not override the minimum reserved traffic rate of a connection. It can be useful for determining how to distribute excess bandwidth among connections that peak above their minimum reserved traffic rate. Since the parameter is on a service-by-service basis, rather than a packet-by-packet basis, it cannot be used to differentiate between two packets from the same service for the purpose of discard on congestion.

Maximum sustained traffic rate

The maximum sustained traffic rate is the peak data transmission rate allowed for a service. In the absence of bandwidth demands from other services, a service would expect to be able to transmit at this rate continuously. Since the time base over which this is statistically guaranteed is not specified, it is left to vendor design to determine how smoothly this is guaranteed. It is expected that client devices will police traffic at the ingress and not request more bandwidth than the maximum sustained traffic rate, again statistically determined over some period. BSs can generally assume that the traffic has been policed before it is received across the backhaul from the core network. If the bandwidth demand is greater than the link can bear, services should first receive their minimum reserved traffic rate. Excess bandwidth above the sum of the minimum reserved traffic rate should be distributed proportional to the difference between the minimum reserved traffic rate and the maximum sustained traffic rate. Traffic between the minimum reserved traffic rate and

the maximum sustained traffic rate is not guaranteed to be transmitted and may be discarded. Intelligent discard algorithms that understand the relative importance of individual packets of a service can enhance the QoS perception over general discard methods like weighted random early detection.

Maximum traffic burst

The maximum traffic burst is the largest burst expected at the ingress port for the service. Its main purpose is to ensure adequate buffering in case of temporary congestion or delays between receiving user traffic on the ingress and transmission over the air.

Minimum reserved traffic rate

The minimum reserved traffic rate is statistically guaranteed to a service over time. QoS algorithms should be designed to give services their minimum reserved traffic rate before any services receive bandwidth in excess of their minimum reserved traffic rate, even if they are a higher class of service (CoS) and the traffic is within the bounds of their maximum sustained traffic rate. This parameter is used to prevent starvation of data from connections that are less real-time than others but have guaranteed rates as part of their SLA. Some systems may choose to oversubscribe the minimum reserved traffic rates when performing CAC, assuming that not all services will request bandwidth simultaneously. Typical QoS algorithms use either a credit or a debit scheme with some finite duration memory in determining the bandwidth available to a service under this parameter. For instance, a service that is idle for hours typically cannot expect to wake up and instantly transmit data equivalent to the minimum reserved traffic rate accumulated during those hours.

Minimum tolerable traffic rate

The minimum tolerable traffic rate is related to the Minimum reserved traffic rate. For certain services, it may be convenient to discuss the service paid for—the minimum reserved traffic rate—and the worst service the user will tolerate—the minimum tolerable traffic rate. While CAC should normally use the minimum reserved traffic rate, there may be circumstances in which resource availability changes after a call has been admitted. For instance, the

signal quality may degrade due to some interference or, in a mobile system, due to the client moving to an area of degraded coverage (e.g., farther away or indoors). Alternatively, a mobile call accepted in one cell may move into the neighboring cell that may already be at capacity with respect to minimum reserved traffic rates. The minimum tolerable traffic rate allows calls to be retained at a degraded level even when the call would not normally be accepted by the CAC algorithm.

Vendor-specific QoS parameters

The vendor-specific QoS parameters provide a QoS backdoor allowing two devices to share proprietary information with the expectation that they can do a better job distributing bandwidth without using general algorithms based on generic QoS and traffic parameters. Care must be taken, however, to maintain the ability to interoperate with devices from other manufacturers that do not use the same parameters. In general, an unknown device is handled by dropping back to exclusive use of the parameters defined in the IEEE 802.16 standard.

Service flow scheduling type

The service flow scheduling type defines the CoS.

Converted to ATM terminology, UGS is equivalent to constant bit rate (CBR) and usually has a fixed packet size and periodicity. The BS allocates bandwidth at the desired rate automatically, without any BW request from the client device. Keep in mind that the BS may “clump” the allocation into a portion of the PHY frame (unavoidable for TDD links), increasing the jitter and possibly causing the need for jitter buffering.

Real-time polling service (rtPS), nonreal-time polling service (nrtPS), and best-effort (BE) service are all variable-rate packet-based service classes. The main reason for differentiation is that there are different rules governing how a client device is allowed to request bandwidth for the different CoS. Also, when resources are tight, rtPSs may receive their minimum reserved traffic rate in preference to nrtPSs, which in turn may have priority over BE services.

CoS may impact the allocation of bandwidth above the minimum rate (generally policed to the maximum sustained traffic rate).

Generally, a UGS will have minimum reserved traffic rate set equal to maximum sustained traffic rate. A BE service will have its minimum reserved traffic rate set to zero, but have a nonzero maximum sustained traffic rate. rtPSs and nrtPSs will generally have nonzero minimum reserved traffic rates that are less than, but not equal to, their maximum sustained traffic rates.

Request/transmission policy

The request/transmission policy parameter is slightly misplaced in being considered part of the service flow encodings. While these parameters can be set on a per-service basis, most are really device capabilities and would normally be set to the same values for all services of the same CoS to or from an individual client device. They include the use of broadcast BW request opportunities, piggybacked requests, fragmentation, PHS, packing, and MAC CRC.

Tolerated jitter

The tolerated jitter parameter indicates the jitter that is allowed for a given service. It is quite often assumed that the receiving application has jitter buffering or other means to mitigate the problem. It is not clear from the IEEE 802.16 standard whether the tolerated jitter is meant to be total jitter from all sources or that due to the IEEE 802.16 link of the data's path. It could be used as the basis of jitter buffering but, if other points on the path do jitter buffering as well, unnecessary delay can result. This is a worrisome parameter because certification bodies may impose tests that would require jitter buffers where they may be of little value in the end-to-end system.

Maximum latency

Maximum latency is the maximum delay between receipt of a packet from the network and forwarding it on the air interface. A system is generally designed to minimize latency anyway. This parameter can, however, be used in times of congestion to give packets of similar CoS/QoS relative priority with respect to

each other. Since the other QoS and traffic parameters have more influence on which packets are transmitted and when, it can also be used to age out old packets.

Fixed-length vs variable-length SDU indicator

The fixed-length vs variable-length SDU indicator specifies whether the service carries fixed-length SDUs (like ATM cells) or variable-length SDUs (like IP packets). This parameter is usually meaningful only for QoS in the case of UGS connections, where the periodic grants should be a multiple of the natural fixed packet length of the CBR service, such as an ATM T1. It can, however, be useful in applying packing and fragmentation more intelligently for variable-rate services that use a fixed packet size.

SDU size

If the fixed-length vs variable-length SDU indicator parameter is set to fixed, the SDU size must be used to indicate the size, allowing scheduling algorithms to take advantage of the known fixed size in whatever way is appropriate.

One interesting omission in IEEE Std 802.16 is the equivalent of the cell loss ratio (CLR) of ATM systems. This omission probably stems from the fact that this parameter is used not so much in the scheduling aspects of QoS, but in the link quality aspects. Typical systems would calculate and report a BER or PER that could be used to determine the need to transition to a more robust PHY mode if and when the loss rate is too great for the ToS. Unfortunately, without a parameter, this decision is left to the vendor or to vendor-specific parameters.

A common fallacy is that IEEE Std 802.16 describes only UL QoS. This is an unfortunate artifact of the naming conventions for services and the QoS model description coming from DOCSIS. DOCSIS assumed that since the head end (the cable modem equivalent of a BS) was in control, the cable modem didn't need to know how QoS was handled on the DL. This works in general but, for some issues like jitter, it's best if the receiving end knows what's going on as well. Unlike in DOCSIS, service setup in IEEE Std 802.16

associates QoS and traffic parameters with the DL as well. Therefore, even though IEEE Std 802.16 uses service names like "rtPS," the QoS concepts apply equally to the DL and the UL.

Interactions between QoS, CAC, and adaptive PHY

Determining available bandwidth

BWA systems are normally intended to provide very reliable service, as an extension of fiber optics or some other high-reliability network. When BWA systems are installed, frequency planning is normally performed to minimize interference while maximizing frequency reuse and, therefore, available bandwidth. Cell sizes are chosen based on some availability goal such as 99.99% or 99.999% (often referred to a "four 9's" or "five 9's").

Furthermore, in systems with a subscriber-level adaptive PHY, each SS can be assigned a "planned" PHY mode. The SS is expected to be able to operate at or above the target BER of the system using the planned PHY mode, or a more efficient one, a fraction of time equal to or exceeding the desired availability. For example, if the system availability goal is 99.99% and an SS's planned PHY mode is 16-QAM, then the SS is expected to operate at 16-QAM or 64-QAM the entire year except for 52 min and 33.6 s. The choice of planned PHY mode for a given availability is generally a function of the distance from an SS to the BS and the LOS conditions. Additionally, certain SSs, such as those at the edges of sectors, may be capped so that they cannot use certain more efficient PHY modes due to interference issues.

As a system operates, the physical environment may also change. Most of the time, most SSs will be able to operate in both the UL and DL in not just their planned PHY mode but also in a more efficient one. For LOS systems in the 10-66 GHz frequency range, rain fade is the main variable in link quality. During rain, an SS may not be able to operate above its planned PHY mode. In fact, during heavy rains, an SS may need to drop to a PHY mode more robust than its planned PHY mode to maintain sufficient link quality to communicate with the BS. For lower frequency systems, multipath variation, due for instance to moving objects such as vehicles, is the main culprit.

The CAC algorithm for modern, third-generation BWA systems must deal with the issues created by these dynamic environments. Many fixed BWA services are established as permanent connections and remain active (in operation) for a long time—months and sometimes years. Rain fades, on the other hand, tend to be relatively short in duration. Therefore, the BWA CAC need not consider short-term changes in system capacity. Those are best handled by the queuing, scheduling, and discard algorithm. CAC must, however, consider the planned PHY modes of the SSs, as these determine the amount of bandwidth that can be guaranteed while still meeting the system's availability goals. The BWA CAC algorithm must address three issues:

- What aspects of a service's QoS and traffic parameters are mapped to the bandwidth availability determined by planned PHY modes to guarantee contractual and QoS requirements?
- What should be done with the additional bandwidth available when a terminal can operate at a more efficient PHY mode, which may be most of the time?
- What should be done when a terminal is unable to operate at its planned PHY mode and must use a less efficient one?

Bandwidth on demand setting the basis for CAC

The solutions to the first two of the problems above are based on the concept of bandwidth on demand. While some BWA systems will be expected to carry legacy T1/E1 TDM voice traffic, demand for variable-rate, bursty services such as Internet access is growing. Even for voice, there is a growing interest in using compressed voice, which results in variable bit rate rather than CBR used by traditional TDM connections. These variable-bit-rate services allow more users and more voice calls to be multiplexed into the same bandwidth by taking advantage of not only compression but also statistical multiplexing.

While third-generation BWA systems can interface to a plethora of user services, such as Ethernet, IP, TDM voice, and ATM, it is ATM that currently has the most mature concept of QoS and the richest QoS and traffic parameter terminology. Therefore, while the concepts apply equally well to IP-based systems, they will be explained using ATM terminology and mapped to the more generic WirelessMAN terminology.

The ATM service architecture defines six CoSs, as shown in Table 7-1:

- **CBR:** Constant-bit-rate services require a static amount of bandwidth that is available for the lifetime of the connection and impose stringent control on delay and jitter. CBR services are intended to emulate legacy TDM services, such as voice and video, and do not generally support statistical multiplexing.
- **rtVBR:** Real-time variable-bit-rate services are bursty, but like CBR also require tight control of delay and jitter. rtVBR services are a good choice for VoIP or streaming video. Because of the bursty nature of rtVBR services, statistical multiplexing may be supported.
- **nrtVBR, GFR, UBR, and ABR:** Nonreal-time variable bit rate, guaranteed frame rate, unspecified bit rate, and available bit rate are categorized as nonreal-time services. These services may be very bursty and have a large difference between average and peak usage rates. GFR, nrtVBR, and ABR offer a minimum guaranteed rate while UBR is simply a BE service.

Table 7-1: Mapping of ATM CoS concepts to WirelessMAN

ATM CoS	WirelessMAN CoS
CBR	UGS (unsolicited grant service)
rtVBR	rtPS (real-time polling service)
nrtVBR, GFR, ABR	nrtPS (nonreal-time polling service)
UBR	BE (best-effort service)

These service categories relate traffic descriptions and QoS parameters to network resources. Queuing, scheduling, and CAC are structured differently for each service category. The purpose of CAC is to ensure that the system has the necessary resources (e.g., bandwidth and buffers) to support a new connection without impacting any preexisting connections. CAC uses the following QoS parameters and traffic descriptors to calculate resource availability.

- **QoS parameters**

- **End-to-End Transit Delay:** This parameter is the amount of delay the service can tolerate. Information delayed longer than the specified delay is considered to be less useful to the application and thus may be discarded by the network. In WirelessMAN, this is the maximum latency parameter.
- **Peak-to-peak delay variation (or jitter):** This parameter is used to size buffers at various multiplexing points within the system. It also impacts the overall delay experienced by the application. In WirelessMAN, this is the tolerated jitter parameter.
- **CLR:** The cell loss ratio parameter is used in sizing the buffers allocated to the connection and in the level of statistical multiplexing gain that can be supported by the BWA system.

It should be noted that each BWA system has inherent end-to-end transit delay and peak-to-peak delay variation characteristics that are directly related to system design choices.

- **Traffic description parameters**

- **PCR:** Peak cell rate (or peak bit rate for non-ATM systems) is the maximum data rate allowed for the service. In WirelessMAN, this is the maximum sustained traffic rate parameter.
- **SCR:** Sustained cell rate is the average data rate expected to be available to the service. The minimum cell rate of the GFR service would map to this as well. In WirelessMAN, this is the minimum reserved traffic rate parameter.
- **MBS:** Maximum burst size is used in buffer allocation and statistical multiplexing calculation. In WirelessMAN, this is the maximum traffic burst parameter.

The focus of this section is the impact of adaptive PHYs on CAC. Therefore, we will ignore for clarity and brevity the impact of CLR and MBS, since they affect mostly buffer allocation calculations. Likewise, as long as a system is not oversubscribed, the delay requirements of a service are impacted much more by the bandwidth allocation scheme and the implementation of fairness algorithms.

So what does it mean for a system with a subscriber-level adaptive PHY to not be oversubscribed? The answer to this question lies in the definition of what is guaranteed to a service. For a CAC algorithm to work, certain rules should be obeyed. In particular, policing should be performed at the ingress point to the network. Services should not, in general, be allowed to transmit more data than their maximum sustained traffic rate. Granted, this must be done in a constructive way, since the service should not be penalized for the fact that the physical line rate of its input port is greater than its maximum sustained traffic rate. For BE services, it is not uncommon for the maximum sustained traffic rate to equal the line rate of the port.

SLAs typically stipulate the grade of service the end customer is getting from the service provider. The SLA's attribute that is of interest to CAC is the minimum reserved traffic rate. The customer is typically guaranteed that this rate will be available. This guarantee is, however, a statistical guarantee, meaning that, over time, the customer will get the minimum reserved traffic rate, but that there may be short periods in which that rate is not available. In general, the following holds:

- For UGSs, minimum reserved traffic rate = maximum sustained traffic rate.
- For rtPSs, minimum reserved traffic rate < maximum sustained traffic rate.
- For nrtPSs, minimum reserved traffic rate << maximum sustained traffic rate.
- For BE services, minimum reserved traffic rate = 0.

Bandwidth demands in excess of the minimum reserved traffic rate can be viewed as not guaranteed and are candidates for statistical multiplexing of services. For instance, as any cable modem user knows, BE customers can be continually added until they complain.

CAC can determine whether the minimum reserved traffic rate of a service can be guaranteed, by comparing that rate against the bandwidth available in the airlink after subtracting the minimum reserved traffic rates of the other services already admitted. This is easier said than done. First, there is the issue of jitter. If a service is at all bursty, even if it uses exactly its minimum reserved traffic rate, it will need less at one instance and more at another.

Therefore, some additional bandwidth may be necessary to compensate for jitter. Alternatively, an operator's policy may be to oversubscribe somewhat the minimum reserved traffic rate. Therefore, CAC should base a service's guaranteed bandwidth on a function of minimum reserved traffic rate and jitter. The actual function used can be tailored to take into account oversubscription policy and may also account for the responsiveness of the bandwidth allocation algorithm in the BS, since this can affect jitter.

Second, there is the issue of the adaptive PHY. The same minimum reserved traffic rate for two different services, each to a different SS, may use substantially different resources. For instance, an SS operating at QPSK will use three times as much physical airlink resources for the same amount of data as a terminal operating at 64-QAM and the same FEC. Therefore, the CAC algorithm must be aware of the planned PHY mode of each SS and normalize the bandwidth requirements of services to common units to determine actual PHY resources consumed. The planned PHY mode is used because the CAC algorithm is concerned with guarantees, and it guarantees that contractual obligations can be met, but only within the bounds of system availability. The planned PHY modes dictate the bandwidth guaranteed available a sufficient fraction of the time to meet the operator's availability goals.

Since SSs quite often have environmental conditions allowing them to operate above their planned modulation (just not often enough to meet availability goals), there is quite often more airlink bandwidth available than CAC uses in admitting services. This bandwidth can be used for BE traffic. It can serve this purpose in two ways. For rtPS and nrtPS connections, this excess bandwidth is normally available to service demands in excess of the minimum reserved traffic rate, up to the maximum sustained traffic rate. Similarly, the excess bandwidth is available for BE services. The high probability of excess bandwidth in the system allows for substantial oversubscription of maximum sustained traffic rate. This can be especially useful for selling services that can peak at their port rate (for example, 100BaseT Ethernet) if bandwidth is available.

Adaptive CAC philosophies for adverse conditions

Once a function is determined for allowing services into the system based on the planned PHY modes of the terminals, there remains a need for a plan of action for when the system is faced with adverse conditions, e.g., when it rains hard enough for terminals to drop below their planned PHY modes to more robust but less efficient PHY modes.

First, it must be determined whether a terminal dropping to a more robust PHY mode actually causes oversubscription. The airlink on which the terminal operates may not be fully subscribed (in the sense defined in the previous section) with guaranteed traffic. Also, if the terminal in question has only BE services, there is no change in the ability to accommodate the guaranteed traffic within the system. Finally, especially in uncorrelated fades, some other terminals may be operating at more efficient PHY modes, offsetting any bandwidth availability problem.

Second, if it is determined that the actual PHY mode dropback causes an oversubscription problem, some action must be taken to retain some amount of services at adequate QoS. This allows the system to maximize the benefit of one of the major features of adaptive PHYs—the ability to still retain the link, albeit with reduced capacity, even in severe weather conditions.

Care must be taken in maintaining QoS and system stability on the temporarily oversubscribed airlink. Initially, it might be tempting to just let the system run with reduced capacity, increased delay, and reduced QoS because this condition may exist only a few minutes a year. In systems with no UGS or rtPS, this extremely simple approach may be very reasonable. Customers can be taught to accept slower response during extreme weather. But UGS, and to some extent rtPS, is very intolerant to change. If the system has a high enough ratio of UGSs, the T1/E1 TDM systems will start alarming due to insufficient bandwidth. A minor oversubscription situation could ultimately bring down all the phone lines in the sector. Obviously, this is not good.

Another simple approach is to temporarily suspend the services with guaranteed bandwidth for the terminal that is below its planned PHY mode (keeping in mind that, for VBR connections, suspending may be merely

reducing the SCR). After all, the reason it is in this predicament is that it's raining hard enough to be in the 52 min a year (four 9's) when it's not guaranteed to be available anyway. This works and meets contractual obligations; in fact, the system may not need to suspend all of the services at that terminal, but just enough to resolve the oversubscription situation. That effectively gives the remaining services an availability slightly higher than the system goal.

This concept can be taken further and can lead to system availability greater than the goal, or it can be traded off for additional capacity by slightly increasing the size of the higher PHY mode regions within a sector. This is especially true in light of the fact that, while affecting only the services on the SS at lower modulation meets contractual guarantees, it's not really fair.

There are two main points that make this simple solution unfair. First, consider that the oversubscription situation may have come into being not because of this single SS, but because a sequence of SSs dropped below the planned modulation. This one just happens to push the system below the oversubscription threshold. Why should its customers be the ones to suffer? The second reason the solution is unfair is best explained pictorially.

In Figure 7-18, two SSs within the same sector have the same planned PHY mode. SS 1 is not quite close enough to the BS to have a more efficient PHY mode and still meet availability goals. SS 2 is in the opposite situation; it is barely close enough to the BS to meet availability with its planned PHY mode. In this situation, SS 2 will normally need to drop to a more robust PHY mode. In this situation, SS 2 will normally need to drop to a more robust PHY mode long before SS 1. In fact, SS 1 may never need to drop to a more robust PHY mode. With the previous simple solution to the temporary oversubscription problem, SS 1 will be unfairly penalized for its relative geographical proximity to the BS.

There are numerous methods to make the situation fairer. In applying them, the CAC algorithm can rely on the fact that the availability of services has a minimum, as expressed by the availability goal, but that many terminals actually enjoy much greater availability. So the algorithm can "spread the pain," keeping the average availability the same while decreasing the worst-case availability. One method is to randomly, or in a round-robin fashion, suspend services with guaranteed bandwidth until the oversubscription




Figure 7-18: Two terminals with same planned PHY mode

problem is alleviated. This is more fair than the previous approach, and it exceeds the availability goals of the system. However, it has the drawback that some of the suspended services may have been critical.

The problem of critical services can be handled by assigning services that have guaranteed bandwidth a precedence level relative to each other. Those with lower precedence are suspended first until the oversubscription problem is alleviated. Within a precedence level, the random or round-robin suspension algorithms may be used. The term *precedence* is used intentionally and should not be confused with CoS or QoS. It may not be acceptable, for instance, to suspend nrtPS first, followed by rtPS, with UGSs getting the axe last. Take, for instance, the business with both its phone lines and its point-of-sale (PoS) transactions going over the BWA system. While maintaining some phone lines during severe weather may be necessary, it is probably more acceptable to have reduced phone capability while retaining PoS capability than to retain all phone lines at the expense of PoS.

Multicast connections

The IEEE 802.16 standard supports multicast connections that allow a service on the DL to be transmitted to multiple SSs on the same airlink without duplicating the transmission to each subscriber. The transmission would be performed at the lowest common denominator of the PHY modes currently used on the DL for the set of subscribers receiving the service.

Multicast introduces an additional complication regarding security. IEEE Std 802.16 typically uses a pair of encryption keys per client so that one client's data cannot be read by another client on the same airlink. For multicast data, e.g., a TV program being broadcast to a number of subscribers simultaneously, this policy of one set of keys per client would effectively require the service to be transmitted individually to each client so it could be individually encrypted for each client. The IEEE 802.16 standard, however, allows per-service encryption keys shared by all recipients of the service, allowing the service to be broadcast once and received by many, but still by only those who subscribe. Clients that support this must be able to have multiple SAs. The target security association identifier (SAID) parameter associated with the service is used to determine which set of keys and which encryption method to use. The SSs' control and any unicast services must use the SA unique to the client. Any multicast or broadcast services are mapped to SAs unique to the service.

Multicast connections also have a unique interaction with ARQ. For multicast service, per-service MAC ARQ is not allowed. Further, since PHY HARQ is on a per-client basis, SSs receiving a multicast connection must be configured to not enable HARQ.

BW request/grant

The BW request/grant mechanism for the IEEE 802.16 standard was chosen to be efficient, low-latency, and flexible and to dovetail with QoS. Requests are made on a per-connection basis to ensure they can be properly used in fairness algorithms in the BS's UL scheduler. But grants are made to the SS, not to the connection. This increases efficiency; e.g., the MAPs are smaller due to an entry for the terminal, rather than each of the terminal's connections. Latency can also be reduced. The terminal can use the bandwidth for the best current need rather than for a reason dictated by the BS. For instance, if an SS asked for bandwidth for a BE connection, but an urgent need to go to a more robust DL PHY mode arises, the SS can use the bandwidth to send a DBPC-REQ (DL burst profile change request) message. This very important message is sent with lower latency than if the SS needed to wait for bandwidth explicitly granted for that purpose.

Also, there are no explicit acknowledgments (positive or negative) of requests. Either the SS gets a grant, or it does not. This saves the bandwidth that would have been used for the acknowledgments. Latency is reduced because the SS does not need to wait for an acknowledgment, just for a grant.

Giving grants to SSs rather than connections can result in inconsistent behavior. Even if the SS does not intentionally use the bandwidth differently from its requests, an SS with multiple services does not know exactly how much of a grant the BS intended for one service vs the other. Additionally, the lack of acknowledgments can cause the BS's perception of the SS's queue status to deviate from the actual situation.

The reality at the SS and the perception at the BS can get out of sync for a number of reasons:

- The BS does not hear a BW request (unrecoverable PHY error).
- The SS does not hear the allocation in the MAP (unrecoverable PHY error).
- The BS scheduler decides it does not have bandwidth right now for the particular service for which the SS requested bandwidth.
- The SS used bandwidth for a purpose different from that originally requested.

To rectify any discrepancy between the SS's reality and the BS's perception, the BW request/grant scheme is designed to be self-correcting. After a period, potentially based on the QoS of the service in question, if the SS still needs bandwidth for a service, it simply asks again. To avoid the BS's perception becoming further askew from reality by duplicate requests, the SS issues an *aggregate request*. An aggregate request tells the BS that this is the current state of the SS's queue for that service, allowing the BS to reset its perception of that service's needs.

Aggregate requests are necessary to guarantee the self-correcting nature of the request/grant scheme. However, there is a chance that a repeated aggregate request crosses the grant for that same bandwidth in the same frame. While this is very unlikely to happen with any regularity, it can, if the request is large, cause wasted allocations to the SS that would have been better served going to a different SS. Therefore, while aggregate requests are both

necessary and sufficient for the request/grant mechanism to operate,⁴ there is a potential waste that can be easily avoided by adding the concept of *incremental requests*. With an incremental request, the SS is simply saying "I need more bandwidth" for a particular service. The BS would add this BW request to its current perception of the bandwidth needs for that service rather than using the BW request to reset its perception of the services needs. In general, the airlink should be reliable. Therefore, most BW requests typically would be incremental, with only periodic aggregate requests to ensure the BS does not deviate too far from reality.

If a BS does happen to allocate bandwidth to an SS without a need, the SS can be polite and send an aggregate request for zero bandwidth. This deterministically informs the BS that the SS does not need bandwidth. Alternatively, the SS can just send fill bytes. The BS can key into the presence of fill bytes to modify its perception of the SS's bandwidth needs. Obviously, keying in on fill bytes can be dangerous if the SS implementation can generate fill bytes when the SS has data queued. But, then again, the request/grant scheme is self-correcting, and this situation will correct itself as well.

A few other BW request options exist as well. For UGS connections, which would typically be used for such services as legacy TDM voice, there is no need for BW requests since both parties know the recurring bandwidth needs of the service. However, clock skew can be a problem. To address this, if the SS sees UGS data starting to back up, it can set the SI bit in the GMSH, thereby requesting the BS to slightly increase the rate at which it automatically allocates bandwidth to the SS. This increase would continue until the SS stops setting the SI bit.

If an SS needs more bandwidth for a connection that is currently granted some over the airlink, the SS can piggyback an embedded incremental BW request in a GMSH of an MPDU for that connection.

Similarly, if the SS is receiving bandwidth that is sufficient only for its UGS connections, the SS can request to be polled, indicating it has a bandwidth

⁴ ETSI BRAN HiperACCESS uses the same request/grant scheme, but with only aggregate requests.

need on another connection, by setting the PM bit in the GMSH of an MPDU of a UGS connection. When the BS sees the PM bit set, it knows the SS needs to make a BW request and may choose to short-circuit its polling cycle for that SS and poll it immediately. In fact, if an SS has bandwidth needs for its UGSs sufficient large that it receives an unsolicited allocation every frame, the BS can refrain from polling the SS until it sets the PM bit, saving UL bandwidth.

Scheduling

Scheduling algorithms were intentionally left outside the scope of the IEEE 802.16 standard. The set of service offerings combined with scheduling algorithms is a major area for vendor differentiation. However, some concepts are common to all implementations, and some ideas were intended even while not explicitly made a part of the standard.

An IEEE 802.16 system has three main scheduling points. The most obvious one, and the one that most often comes to mind first, is the scheduling of the UL by the BS. The BS receives requests from SSs, processes those requests, and then creates and distributes UL MAP messages. This process must consider not only the outstanding BW requests but also polling, PHY maintenance needs, and the current UL PHY mode for each SS. The current UL PHY modes impact the amount of bandwidth, from a data rate perspective, available in the UL.

But, as previously mentioned, the UL MAP messages allocate bandwidth to SSs, not connections. This leads to the second scheduling point. Once the SS receives an allocation, it must decide which of its data to transmit during that allocation. To do this, it runs a scheduling algorithm analogous to that in the BS, but limited in scope to its own services, MAC management messages, and its individual allocation at its current UL PHY mode.

The third major scheduling point is the creation by the BS of the DL subframe. Like the BS scheduling of the UL, this task must take into consideration not only the DL data awaiting transmission but also the current DL PHY mode of each SS. DL MAC management messages must be included in this scheduling. The end product of this scheduling point is a DL subframe, complete with a DL MAP message indicating PHY mode transitions within

the DL subframe, and the UL MAP message resulting from the BS UL scheduling.

The intent of IEEE Std 802.16 was that the DL MAP and UL MAP messages be transmitted using the most robust modulation currently in use on the airlink. This aids new SSs entering the network, and it guarantees that the MAP will be received with a low likelihood of error. Since the DL MAP is of variable length, it needs to be relevant to the current PHY frame; i.e., the frame containing it. If it instead mapped the PHY mode transitions of the next frame, it would need to know the length of the next DL MAP so it could map the first PHY transition. This is a nondeterministic problem. It requires an FEC structure for transmitting the MAPs that guarantees that the first DL PHY mode transition is contained in an FEC block that is not the last FEC block of the initial PHY mode. This guarantees at least one FEC block buffer for processing the first DL PHY transition. For most practical implementations, this will require the DL MAP to be processed in hardware or firmware rather than software.

For TDD systems, the UL MAP message can be for either the current frame or the next frame, as shown in Figure 4-7 and Figure 4-8 (in Chapter 4). The BS must choose one of these at the start and not change its choice. When the UL MAP is for the current frame, the latency of the request/grant cycle is reduced. This comes at an expense, however. The UL MAP cannot be for any earlier than the round-trip delay of the first SS scheduled in the UL plus the time required to be allotted for processing the MAP. This bounds the minimum DL subframe duration, reducing flexibility compared to when the UL MAP is for the following frame.

For FDD systems, the UL MAP can map allocations starting as early as the start of the current frame plus the time allotted for processing the MAP plus the round-trip delay. Alternatively, it can map allocations starting with the following frame. Anything within these two extremes is possible, as shown in Figure 4-9 and Figure 4-10 (in Chapter 4).

When an SS has UGSs, it does not need to request bandwidth for those services. In fact, it should not make BW requests for those services. The BS already knows the bandwidth need of the UGSs and allocates the bandwidth unsolicited, hence the name *unsolicited grant* services. Based on the frame

duration and the maximum sustained traffic rate parameter, which should be the same as the minimum reserved traffic rate parameter for UGSs, the BS can determine how much periodic bandwidth the SS will need each frame. In granting the allocations, the BS must also take into account the ToS being offered and other parameters of the service.

For example, assume a WirelessMAN-SC backhaul for a cell site of a global system for mobile communications (GSM) network in the United States. The IEEE 802.16 system would most likely be backhauling TDM voice circuits and using a 1 ms PHY frame. A convenient way to backhaul such cell sites is with an ATM adaptation layer virtual circuit. There are various modes for such a circuit, but a popular mode generates 4192 ATM cells per second. Therefore, the circuit needs bandwidth equivalent to 4.192 ATM cells each PHY frame. Since the ATM CS does not allow ATM cells to be fragmented, the BS must, over the course of each second, allocate the SS at least 4 ATM cells in 808 frames and at least 5 ATM cells in the other 192 frames. How the BS distributes these allocations is implementation-dependent and outside the scope of the IEEE 802.16 standard, but it should be obvious that doing a better or worse job can have a big impact on jitter and on buffer requirements at the SS. In general, the BS should try to distribute the allocation of the fifth cell evenly across time.

Even with very good bandwidth allocation algorithms at the BS, extra care must be taken with UGS connections. For instance, the bandwidth allocation for a UGS connection will likely be grouped into a single burst for each UL subframe rather than distributed across the frame. There are a number of reasons for this:

- Reduced complexity of SSs that need to transmit only once per frame.
- Reduced overhead of a single burst rather than multiple smaller bursts (e.g., packing, burst preambles).
- The fact that, unless all you're doing is nailing up T1s or E1s, the scheduling algorithm will never be able to perfectly distribute the allocations within a frame if there is more than one SS in the system.
- The fact that, in TDD systems, the allocations must be compressed into a partial frame anyway.

The “clumping” that results is really the equivalent of adding one PHY frame duration of jitter into the connection. In our example, this is 1 ms. Jitter buffers at both ends of the airlink should be sufficient to remove at least one PHY frame duration of jitter. Be careful, however, because the way to eliminate jitter is to turn it into delay.

Since UGS connections are the preferred choice for transferring constant data rate services, it is important to provide mechanisms for each side to maintain synchronization. Potential problems may arise. The clock used by the BS for PHY frame generation may drift with respect to the clocks used by the network to clock the UGS data. This can lead to data in the UGS queues at the SS building up at a faster rate than the allocations to the SS can drain the queues. When this situation happens, the SS notices that its UGS queues are above an implementation-dependent threshold. The SS then sets the SI bit in a GMSH, indicating that, due to a clock mismatch, the BS should grant it slightly more bandwidth than agreed. Additionally, many types of UGSs need their clock at the SS to match the network clock used for the service on the backhaul. The SS has the airlink clock available, but this may not be locked to the network clock. Whenever the BS is providing UGSs, it also provides the CLK-CMP ([SS network] clock compare) message, which allows the SSs to derive the network clock, or multiple clocks, from the airlink timing. The method for deriving the network clock is described later in this chapter.

rtPS, nrtPS, and BE service all differ from UGSs in that they do not expect continuous, constant bandwidth allocations. They typically carry bursty traffic such as web browsing or VoIP. From the end user’s point of view, they may be the aggregation of multiple bursty services. For instance, a single IEEE 802.16 rtPS may allow some number of simultaneous VoIP calls. For rtPS and nrtPS, the minimum reserved traffic rate should be statistically guaranteed. The parameters of such a guarantee are outside the scope of the IEEE 802.16 standard; but in general, if a service is requesting its minimum guarantee, it should receive it. On the other hand, if a service does not use its guaranteed minimum for some period of time, it should not build up an infinite credit. Care must be taken to strike a balance between guaranteeing a minimum rate on average for bursty traffic and building up too much credit, which could starve other services.

The main difference between rtPS and nrtPS is the expected response time. This is especially true once a service becomes active. For instance, a VoIP service may tolerate greater delay during initial setup of a call than during the life of the call. BE services, however, differ from rtPS and nrtPS in that they have no minimum reserved traffic rate. Depending on the CAC, fairness, and scheduling algorithms used, the guaranteed part of other CoSs could effectively starve BE services. If this condition is more than an infrequent transient phenomenon, the system is oversubscribed, and more channels should be made available if possible.

Along with satisfying minimum guarantees and distributing bandwidth in excess of guarantees, another aspect of scheduling is policing. In some networks, services may be sold under agreement guaranteeing some (or no) minimum rate, bursting to some peak rate. Network operators may not want to allow users to become accustomed to having access to all the system’s bandwidth if no one else is using it. UGSs typically have a fixed data rate, but rtPS, nrtPS, and BE service can burst with a peak rate equivalent to the line rate of their input port to the SS. For instance, a service connected to the SS via a 100BaseT port can burst data upwards of 96 Mbit/s. At ingress points to the network, policing algorithms should use a function of the maximum sustained traffic rate and the maximum traffic burst parameters to allow instantaneous bursts at the line rate of the input port while statistically limiting the traffic over time to at most the maximum sustained traffic rate. Obviously, if it is desired to have no upper limit on the bandwidth a service can use when available, the maximum sustained traffic rate can be set greater than or equal to the line rate of the port or the maximum rate of the airlink.

Unicast polling

The first thing to understand about unicast polling in IEEE Std 802.16 is exactly what it means. The basic intention of unicast polling is to give the SS a contention-free opportunity to tell the BS that it needs bandwidth for one or more connections. Since the IEEE 802.16 bandwidth allocation scheme allows the SS to use any bandwidth allocation as it sees fit, the SS simply sees extra, unsolicited bandwidth. If the bandwidth is available, unicast polling is generally preferred to broadcast or multicast polling. It can be used to minimize delay and jitter as well as to provide more deterministic delay and

jitter than broadcast and multicast polling, both of which have the potential for collision between two BW requests.

In keeping with the main purpose of the unicast poll, the BS has two primary options for how much additional bandwidth to give an SS. Which option a BS uses is a function of many things, including the SS's service mix, the connection activity, and the complexity of the BS's polling algorithms. If an SS has only a single, active connection, the BS may opt to give the SS only the additional 2 bytes necessary to piggyback a BW request in a GMSH. Alternatively, if the SS has no outstanding BW request or if it has multiple connections, the BS could opt to allocate the 6 bytes necessary for a BW request header. These two options represent the minimum necessary unsolicited allocations for unicast polling. The BS is free to grant more unsolicited bandwidth to an SS. This could allow the SS to transmit multiple BW requests for different services. There are additional reasons why the BS may want to vary the unsolicited grant size. These additional reasons will become more clear when discussing the circumstances that may stimulate the BS to grant unsolicited bandwidth.

In keeping with the main purpose of unicast polling, the BS would periodically grant unsolicited bandwidth at a rate it deems sufficient for the QoS requirements of the SS's services. The frequency can depend on many factors. The BS could merely grant unsolicited bandwidth on a periodic basis, such as every n frames. Alternatively, the BS could consider the CoS of the SS's services. For instance, an SS with an rtPS may be polled more frequently than one that has only nrtPS or BE service. Another factor that could be considered is activity. A BE service that has been idle for a few hours has much less likelihood of needing bandwidth soon than one that has transmitted data within the last second. The BS is free to take into consideration all these issues and any others the implementor thinks are important.

There are a few secondary purposes of unicast polling. First, for MAC management message exchanges on the basic or primary MAC management connections, the BS can predict the SS's need for response bandwidth. Such a predictive ability can greatly speed up MAC management protocols. Of course, the SS has the freedom to either use the bandwidth for its part of the protocol exchange or request bandwidth for its part of the exchange. The

timing of these unsolicited allocations depends on the MAC management exchanges in which the BS and SS are engaged.

Additionally, since IEEE 802.16 systems have subscriber-level adaptive PHYs, the BS needs to periodically assess the UL quality from each SS individually. Periodic ranging is used for this purpose. Any unicast bandwidth allocation is considered a PHY maintenance opportunity for periodic ranging. Because the SS must transmit at least filler, even when it has no other data or requests to transmit, any unicast allocation gives the BS an opportunity to measure the receive signal quality of the SS's UL transmissions. Additionally, the SS may use any UL allocation to transmit a DBPC-REQ message for maintenance of the DL. Therefore, the BS must periodically send a unicast poll to the SS for the purpose of PHY maintenance. The frequency of this type of unicast poll is PHY-dependent. For example, to ensure proper PHY maintenance with 10 dB/s fading in a WirelessMAN-SC system, the BS should give the SS a PHY maintenance opportunity about once every 80 ms. If the SS's services are idle, this PHY maintenance opportunity takes the form of a unicast poll.

Finally, at the BS's discretion, any unused UL bandwidth in a frame may simply be allocated to various SSs, effectively polling them in a unicast fashion. This can be particularly effective as a semipredictive way of reducing the acknowledgment latency of TCP/IP transfers, resulting in better response time, such as faster File Transfer Protocol (FTP) transfer rates.

Broadcast polling

During times of congestion, it may be better for certain CoSs to reduce the UL overhead associated with unicast polling and poll SSs on a contention basis as groups. This is especially true of any SS that has only BE connections. Additionally, SSs whose services have been idle for some period would be good candidates for being polled as a group. When an SS enters the network, it is automatically part of the broadcast polling group. At the discretion of the BS scheduling algorithm, the BS may choose to provide contention-based BW request opportunities open to the entire set of SSs on the channel. These opportunities appear in the UL MAP as a special DIUC indicating a BW request opportunity, addressed to the Broadcast CID 0xFFFF.

The method of sending a BW request in such an allocation, common to all PHYs, is the transmission of the BW request header. However, for the OFDM and OFDMA PHYs, an additional anonymous BW request method exists, for which the allocation must be separately provided by the BS. Different techniques are used in OFDM and OFDMA to support anonymous BW requests. However, in both cases, in addition to the BW requests being anonymous, the techniques allow the transmission of simultaneous BW requests from multiple SSs in the same UL allocation.

For OFDM, this so-called *focused contention BW request* (as compared to the full BW request, which uses the BW request header) is achieved by sending a randomly selected 4-bit code on four out of all data subcarriers for the duration of two OFDM symbols, while sending no energy on all other subcarriers. A random selection of a group of four subcarriers by multiple SSs allows a low probability of collision within the same BW request opportunity. For OFDMA, this so-called *contention-based CDMA BW request* is achieved by modulating a randomly selected spreading sequence over the ranging subchannel in the traditional CDMA fashion.

Upon reception of these codes or sequences, the BS can provide UL allocations; however, since the originator is unknown, it indicates in the allocation the received code or sequence and the BW request opportunity in which it was received rather than the Basic CID of the requesting SS. One drawback of this method is that SSs may sometimes select the same code or sequence during the same BW request allocation, resulting in a collision within the resulting UL allocation. Another is that it is not possible to indicate the size of the UL allocation needed in the code or sequence. These drawbacks are offset by the efficiency of the requests themselves.

Multicast polling groups

Sometimes it may be desirable to use contention-based opportunities for groups of SSs, but the entire group may be large enough that the possibility of collision is too high. For situations such as this, SSs can be divided up into multicast polling groups. Multicast polling groups should not be confused with multicast connections. Multicast connections, as described in Chapter 6, are DL connections that are received by multiple SSs simultaneously, without

duplicate transmissions on the same airlink channel. Multicast polling groups are groups of SSs that may respond to a BW request addressed to their multicast polling group address. Effectively, it is the same as the broadcast poll, but only selected SSs are members. This allows the BS to limit the number of SSs that may respond to a contention-based poll, which it may do for a variety of reasons.

- To reduce the possibility of collisions.
- To group SSs by like services, allowing certain groups to be polled more frequently than others, thus maintaining some determinism in QoS while still taking advantage of group polling.
- To provide the BS with a smaller set of SSs that it may decide to poll individually upon detection (assuming the BS has this capability) of a collision.

CLOCK COMPARISON

The clock compare function arose from the need to be able to support services that transferred data synchronously. In particular, synchronous T1s and E1s, while gradually being supplanted by asynchronous T1s and E1s, were relatively common when IEEE Std 802.16 was first approved and are still used today for certain voice backhaul applications. Also, the standard's developers noted that, since synchronous data transfer is generally faster, some future applications are likely to require synchronous transport. Such applications may include the streaming of audio to multiple devices. However, it is difficult to ensure that the clocks needed for synchronizing services across a network and the clocks used for generating the wireless transmission are the same or even synchronized with each other.

In TDD systems and in FDD systems that allow H-FDD devices, information is not provided continuously from a transmitter to the receiver, further aggravating the problem of synchronization of services. In IEEE Std 802.16, we add sophisticated PHY burst profile usage and MAC scheduling that can further disrupt the continuity desired by synchronous services.

Usually, but not always, the synchronous data are synchronized to the network clock that is also used to generate the backhaul. Theoretically, the symbol

clock for the wireless link could be generated from the network clock, but this is typically not done for a variety of reasons:

- The airlink typically needs a stratum 1 reference. While the network clock is probably of high quality, there is no guarantee that the network clock is better than stratum 3 because it may have accumulated errors through the network.
- Especially in TDD systems, it is advantageous to synchronize BSs within a network. Depending on the network, the backhauls to and from each BS may not be synchronized among themselves.
- Rather than build a variety of backhaul synchronization means, it is easier for BS vendors to design airlink synchronization around a known, readily available stratum 1 clock source, such as a global positioning system (GPS).

This creates a situation such as shown in Figure 7-19. In this example, the BS is synchronized to the 10 MHz reference typically provided by a GPS collocated with the BS. It may further use the 1 pps (pulse per second) reference typical of a GPS receiver to synchronize PHY frame boundaries, but this is immaterial to the clock compare discussion. The BS generates the symbol clock for the airlink synchronized to the 10 MHz reference. The SS synchronizes its symbol clock to the airlink, effectively synchronizing to the 10 MHz reference from GPS.




Figure 7-19: Clock comparison

However, any network clocks derivable from the backhaul or services on the backhaul are not guaranteed to be synchronized with GPS. They could be synchronized to a stratum 1 rubidium oscillator clock generator somewhere in the network or to some other clock generator of similar or worse quality, or they could be synchronized to GPS, but with accumulated errors. But, regardless of its quality or its relationship to GPS, one of these network clocks is the one to which the T1/E1 recreated by the SS must be synchronized.

The SS must regenerate the network clock for the service from the airlink clock. By itself, there is insufficient information to do this with accuracy sufficient to prevent bit slips on a synchronous T1 or E1. Therefore, the BS helps out. Every 50 ms, the BS notes the difference between the 10 MHz reference used to generate the airlink and an 8.192 MHz clock generated from the desired network clock. In the clock compare algorithm, 10 MHz was chosen due to the predominance of GPS as the choice for BS reference, and 8.192 MHz was chosen since it is a commonly occurring divisor of most network clocks.

Now the SS can quantify the difference between the two clocks at known intervals. The SS then adjusts the network clock it is regenerating so that the difference between the 8.192 MHz reference it creates for the network clock and the 10 MHz reference it generates from the airlink symbol clock tracks the difference between the two source clocks at the BS. This can be done with sufficient accuracy to prevent bit slips on a synchronous T1 or E1. It has applicability to any synchronously clocked services carried over the airlink.

ARQ OPERATION

ARQ parameters and timers

This section describes the set of parameters and timers required for ARQ operation. Table 7-2 provides the basic IEEE 802.16 ARQ parameters and their usage. An ARQ implementation may also define additional parameters. For example, an ARQ block may have a maximum retry limitation in addition to its lifetime. The acknowledgment generation at the receiver may also be controlled by an acknowledgment frequency parameter (specifying how often to generate ARQ feedback) and/or a maximum ARQ feedback size.

Table 7-2: ARQ parameters and timers

Parameter	Description
ARQ_BSN_MODULUS	The maximum number of unique BSN values ($= 2^{11}$)
ARQ_WINDOW_SIZE	The maximum number of consecutive ARQ blocks in the sliding window maintained by the transmitter and receiver. In order for the SR ARQ algorithm to work correctly, this window size cannot be greater than half of the ARQ_BSN_MODULUS. The transmitter and receiver state machines use the following additional variables to manage the ARQ blocks within their respective sliding windows: • ARQ_TX_WINDOW_START: transmitter variable—All ARQ blocks with BSNs up to one less than this value have been acknowledged by the receiver. Therefore, this is the BSN of the first (unacknowledged or not yet transmitted or not yet available for transmission) ARQ block in its sliding window. • ARQ_TX_NEXT_BSN: transmitter variable—The BSN of the next ARQ block to send. Therefore, $ARQ_TX_WINDOW_START \leq ARQ_TX_NEXT_BSN \leq (ARQ_TX_WINDOW_START + ARQ_WINDOW_SIZE)$ • ARQ_RX_WINDOW_START: receiver variable—All ARQ blocks with BSNs one less than this value have been successfully received. • ARQ_RX_HIGHEST_BSN: receiver variable—The BSN of the highest ARQ block successfully received, plus one. This variable is related to the window size as follows: $ARQ_RX_WINDOW_START \leq ARQ_RX_HIGHEST_BSN \leq (ARQ_RX_WINDOW_START + ARQ_WINDOW_SIZE)$
ARQ_BLOCK_SIZE	The ARQ block size negotiated during connection setup.

Table 7-2: ARQ parameters and timers (Continued)

Parameter	Description
ARQ_BLOCK_LIFETIME	The maximum amount of time an ARQ block will be held by the transmitter after the initial transmission of the block. A timer with this value is typically set for every ARQ block after the first transmission. If the block is successfully transmitted before its lifetime expires (i.e., upon reception of an acknowledgment), this timer is cancelled. If the transmitter is unable to successfully transmit the block within its lifetime subject to retransmissions, the ARQ block is discarded.
ARQ_RETRY_TIMEOUT	The minimum time between a transmission (or retransmission) and a subsequent retransmission of an ARQ block. A block is retransmitted if no acknowledgment is received within this timeout and the ARQ block is still eligible for retransmission.
ARQ_SYNC_LOSS_TIMEOUT	The maximum time the transmitter or receiver keeps its respective TX/RX_WINDOW_START variables at the same value (i.e., sliding window remains fixed) before declaring a loss of synchronization between the transmitter and receiver. This timeout is meaningful only if the connection is actively transferring data and the TX/RX_WINDOW_START has not moved. The transmitter and receiver have their own way of determining whether a connection is actively transferring data.
ARQ_RX_PURGE_TIMEOUT	The maximum time interval the receiver waits after successfully receiving an ARQ block that did not advance the ARQ_RX_WINDOW_START. After this timeout, the ARQ_RX_WINDOW_START is advanced by the receiver.
ARQ_DELIVER_IN_ORDER	If enabled, the ARQ receiver must deliver the MSDUs to the upper layers in order. If disabled, MSDUs may be delivered to the upper layer out of order.

ARQ protocol messages

Apart from a stand-alone message to transport the ARQ feedback, as described in Chapter 6, a few additional MAC management messages are necessary to exchange state information between the transmitter and receiver and keep their ARQ states in sync. These messages are transported in a management connection using the TLV format.

ARQ Feedback management message

The ARQ Feedback management message (Type 33) may carry any size of ARQ feedback up to the maximum allowed by the connection. It is used by the receiver when no other piggybacking opportunities are available to transport the ARQ feedback payload.

ARQ Discard management message

The ARQ Discard management message (Type 34) is used by the transmitter to instruct the receiver to skip a certain number of ARQ blocks. This message, of fixed size, carries the CID and BSN, where the BSN indicates the last ARQ block that the transmitter wants to discard. The receiver should skip up to the indicated BSN and update its sliding window variables accordingly. For an ARQ receiver, the reception of an ARQ Discard management message is equivalent to the successful reception of the ARQ blocks up to the specified BSN. Therefore, in response, the receiver generates an ARQ Feedback IE with the appropriate acknowledgment (i.e., cumulative acknowledgment with the BSN from the discard message).

ARQ Reset management message

The ARQ Reset management message may be sent by the transmitter or the receiver to reset the transmitter and receiver state machines. This message, which resets all variables in the transmitter and receiver to zero, is used when all other attempts to synchronize the state machines fail. The reset message carries the CID, a two-bit Type field, and a two-bit Direction field. The Type field indicates whether the reset message is the original reset message from the initiator, the acknowledgment from the responder, or the confirmation

from initiator. A three-way handshake is necessary to complete the reset operation. The Direction field indicates whether the CID in the message refers to an UL or DL CID. For transport connections, the Direction field is reserved. However, for the secondary management connection, the same CID is used in both the UL and DL for a specific SS. Therefore, if ARQ is enabled for the secondary management connection, the Direction field is used to identify the source of the reset message.

BSN comparison

Both the transmitter and receiver ARQ state machines need to take actions based on comparison of BSNs (e.g., comparing the BSN from a message or received MPDU with a locally maintained value). Since a simple numerical comparison is inaccurate, due to the size of the BSN space and sliding window and the rolling over of BSN values, the BSN values need to be normalized prior to comparison. The normalized BSN, BSN', is defined as $BSN' = [(BSN - BSN_Base) \bmod ARQ_BSN_MODULUS]$, where BSN_base is ARQ_TX_WINDOW_START for the transmitter and ARQ_RX_WINDOW_START for the receiver.

ARQ transmitter

The primary functions of the ARQ transmitter are the following:

1. Determining whether one or more ARQ blocks are qualified for transmission and whether any ARQ blocks need to be retransmitted.
2. Processing ARQ feedback, extracting acknowledgment information, and updating the local state variables, including the ARQ_TX_WINDOW_START, if necessary.
3. Generating a discard message when an ARQ block's lifetime is expired without a successful transmission.
4. Generating a reset message whenever the ARQ_SYNC_LOSS_TIMEOUT is expired.
5. Processing reset messages from the receiver.

The first three functions of the transmitter state machine can be best illustrated using the state transition of ARQ blocks. Figure 7-20 shows the ARQ block states at the transmitter.




Figure 7-20: ARQ block states at the transmitter

As described in Chapter 6, an MSDU received from the CS is divided into one or more ARQ blocks based on the block size negotiated during the connection setup. An ARQ block starts at the *not-sent* state. An entity outside of the ARQ transmitter, typically the scheduler, is responsible for determining transmit opportunities for a specific connection, based on the QoS requirements and the number of queued ARQ blocks. The exact interface between the scheduler and ARQ is not defined in the IEEE 802.16 standard.

Based on the maximum number of ARQ blocks that can be transmitted for a given opportunity, the ARQ transmitter builds an MPDU of ARQ blocks comprising first transmissions and/or retransmissions. The ARQ transmitter has to follow the packing and fragmentation rules defined for this connection in constructing the MPDU. In order to qualify an ARQ block in not-sent state for transmission, the ARQ transmitter must make sure that the block falls within its window size. Once a block is qualified, it is assigned the ARQ_TX_NEXT_BSN as described in Table 7-2 and the ARQ_TX_NEXT_BSN is incremented by one.

Once an MPDU is constructed and sent for transmission, the ARQ blocks carried in that MPDU become outstanding, i.e., enter the *outstanding* state. Once in the outstanding state, the ARQ block remains in that state until one of the following four events occurs, whichever happens first: (1) Positive acknowledgment (ACK) is received, (2) Negative acknowledgment (NACK) is received, (3) ARQ_RETRY_TIMEOUT is exceeded, 4) ARQ_BLOCK_LIFETIME is exceeded. If a negative acknowledgment is received or an ARQ_RETRY_TIMEOUT occurs, the ARQ block is placed in *waiting-for-retransmission* state. If the ARQ_BLOCK_LIFETIME expires, the ARQ block is moved to the *discarded* state, irrespective of the current state (i.e., outstanding or waiting-for-retransmission).

Similarly, if an acknowledgment is received, irrespective of the current state, the ARQ block is considered successfully delivered. If the BSN of this block is equal to the ARQ_TX_WINDOW_START, then the ARQ_TX_WINDOW_START is advanced by one. Whenever the ARQ transmitter has the opportunity to build a new MPDU, it must give preference for retransmissions, i.e., blocks in the waiting-for-retransmission state must be transmitted before attempting to transmit any blocks in the not-sent state. If there is more than one ARQ block in the waiting-for-retransmission state, the block with the lowest BSN must be transmitted first.

Whenever an ARQ block is marked as discarded (i.e., ARQ_BLOCK_LIFETIME expires), the transmitter sends an ARQ Discard management message to the receiver. This message can be cumulative; therefore, multiple consecutive discard orders can be aggregated into a single discard message that includes the highest BSN to discard. Since it is still possible to receive an acknowledgment while in discarded state and the receiver waits up to ARQ_RX_PURGE_TIMEOUT before advancing a stagnant ARQ_RX_WINDOW_START (i.e., deciding to discard on its own), a discard message may be delayed up to (ARQ_RX_PURGE_TIMEOUT + ARQ_RETRY_TIMEOUT). In order to quickly recover from possible out-of-sync or other disconnects between the transmitter and receiver, the transmitter repeats discard orders at ARQ_RETRY_TIMEOUT intervals until an acknowledgment is received for the discarded BSN.

ARQ feedback processing

Whenever an ARQ feedback (ACK or NACK) is received for a specific BSN, the transmitter checks to see whether the BSN falls within its window and whether it is less than ARQ_TX_NEXT_BSN. If either of those conditions is not met, the positive or negative acknowledgment is ignored as invalid.

All the acknowledgment types supported by the IEEE 802.16 standard can be decoded into a cumulative and/or selective acknowledgment. For example, the selective with cumulative acknowledgment and the sequence acknowledgment messages can be decoded into two separate acknowledgments: a cumulative and a selective.

Whenever a valid cumulative acknowledgment is received, the ARQ_TX_WINDOW_START is set to BSN + 1 of the cumulative acknowledgment. For a selective acknowledgment bitmap, the ARQ_TX_WINDOW_START is advanced for every bit with a positive acknowledgment, whose BSN is equal to ARQ_TX_WINDOW_START.

There may be a delay between the reception of ARQ blocks at the receiver and the actual transmission of the ARQ feedback to the transmitter. This may create a situation in which the transmitter receives a negative acknowledgment for an ARQ block just after it was transmitted and successfully received by the receiver. In order to address this problem, an optional parameter RECEIVER_ARQ_ACK_PROCESSING_TIME (specified in milliseconds) is defined. This parameter may be provided by the receiver (BS or SS) to the transmitter during connection setup or change. The transmitter may use this information to intelligently interpret ARQ feedback and make retransmission decisions.

ARQ receiver

The primary functions of the ARQ receiver are as follows:

1. Receiving ARQ blocks within its receive window and updating the appropriate state machine variables and timeouts.
2. Generating ARQ feedback (ACKs and NACKs) whenever necessary.

3. Generating a reset message whenever the ARQ_SYNC_LOSS_TIMEOUT is expired.
4. Processing discard messages and generating acknowledgment (ARQ feedback) in response to indicate to the transmitter the reception of the discard message.
5. Processing reset messages from the transmitter.

Figure 7-21 shows the ARQ block reception procedure. As described earlier, the CRC-32 is mandatory for ARQ connections. If the CRC check fails, all the ARQ blocks in that MPDU are considered invalid. The CRC check is typically performed outside of the ARQ receiver, and only ARQ blocks that passed the CRC check are handed over to the ARQ receiver. If the MPDU is packed, it needs to be unpacked prior to the examination of ARQ blocks. The reassembly occurs after all the blocks for a specific MSDU are received correctly.




Figure 7-21: ARQ block reception

The first step after the reception of an ARQ block is to add the BSN to the list of BSNs to be acknowledged and to determine whether its BSN is within the ARQ receive window. The ARQ receiver also checks to see whether this block is a duplicate block and discards duplicate blocks after resetting the ARQ_RX_PURGE_TIMEOUT timer corresponding to that BSN. If this is not a duplicate block, then the BSN is checked against the ARQ_RX_HIGHEST_BSN. If the BSN is greater than ARQ_RX_HIGHEST_BSN, then ARQ_RX_HIGHEST_BSN is set to BSN + 1. Then the receiver checks to see whether the BSN advances the ARQ_RX_WINDOW_START. If it is equal to the ARQ_RX_WINDOW_START, then the value is updated and ARQ_SYNC_LOSS_TIMEOUT timer is reset.

Whenever an ARQ block that did not advance ARQ_RX_WINDOW_START is received, an ARQ_RX_PURGE_TIMEOUT is started for that block. Every time an ARQ_RX_PURGE_TIMEOUT expires, the ARQ_RX_WINDOW_START is set to the BSN of the next block that has not yet been received. When an ARQ block advances the ARQ_RX_WINDOW_START, all ARQ_RX_PURGE_TIMEOUT timers set for BSNs lower than this BSN (i.e., outside the receive window) are cancelled.

Only if the ARQ receiver has all blocks corresponding to complete MSDUs is the reassembled SDU delivered to upper layers. If only partial blocks are available for an SDU and the ARQ_RX_WINDOW_START has already moved past the required BSNs, all ARQ blocks in the incomplete SDU are discarded. The receiver also discards all blocks up to the BSN specified in an ARQ Discard management message and advances the ARQ_RX_WINDOW_START to the first BSN not yet received after the BSN specified in the discard message.

If ARQ_DELIVER_IN_ORDER is enabled, the reassembled MSDUs must be delivered in order. This requires that all ARQ blocks of all previous MSDUs have been either delivered to the upper layers or discarded due to a timeout or the reception of a discard message. When ARQ_DELIVER_IN_ORDER is disabled, an MSDU may be delivered as soon as all its ARQ blocks are received correctly, irrespective of the state of previous ARQ blocks and MSDUs. Most higher layer protocols and applications require in-order delivery, although some may be able to accept out-of-order delivery.

ARQ feedback generation

The frequency of acknowledgment generation is not defined in the IEEE 802.16 standard. It is up to implementations to define a frequency or other innovative algorithms to decide when to generate an acknowledgment. However, all received ARQ blocks must be acknowledged.

All acknowledgments outside the receive window must be cumulative, irrespective of whether those blocks were actually received correctly. As described in earlier subsections, the ARQ_RX_WINDOW_START may be advanced for a variety of reasons: (1) the reception of an ARQ block with BSN equal to ARQ_RX_WINDOW_START, (2) the reception of a discard message, or (3) a purge timeout. In all of these cases, the ARQ receiver generates an ARQ Feedback IE with cumulative acknowledgment at least once to indicate the reception of all ARQ blocks less than ARQ_RX_WINDOW_START. For all other ARQ blocks received that fall within the receiver window, the generated acknowledgments may be cumulative (if applicable), or selective, or a combination of both.

ARQ state machine reset and resynchronization

The ARQ reset mechanism is used to recover from an out-of-sync state, with the transmitter and receiver having lost synchronization due to a sequence of lost messages or an incorrect implementation. The reset operation may be initiated by the transmitter or the receiver.

- **Transmitter-initiated reset:** A reset is initiated by the transmitter when the ARQ_TX_WINDOW_START has not moved for ARQ_SYNC_LOSS_TIMEOUT while the ARQ connection is active. The process of transmitter-initiated reset, along with the actions taken by the receiver, is given in Figure 7-22. The timer T22 used in Figure 7-22 is defined in the IEEE 802.16 standard as the "Wait for ARQ-reset" timer, with the default value of 0.5 s.




Figure 7-22: Transmitter-initiated reset

- **Receiver-initiated reset:** The receiver, like the transmitter, can initiate an ARQ reset. It does so when the ARQ_RX_WINDOW_START has not moved for ARQ_SYNC_LOSS_TIMEOUT while the ARQ connection is active. Figure 7-23 shows the process of receiver-initiated reset. The timer T22 used here is the same timer used in transmitter-initiated reset.

Both the reset procedures take into account the case where both the transmitter and receiver independently initiate a reset. In the case of an ARQ reset error, the SS should reinitialize its MAC. The behavior of the BS is undefined, and it is left to the implementation to take the appropriate action when an ARQ reset error occurs.




Figure 7-23: Receiver-initiated reset

Interaction with scheduler

The interactions between a scheduler and ARQ are not defined in the IEEE 802.16 standard. It is up to the implantation to define the exact behavior, including the following:

- **How to count retransmissions?** The ARQ protocol requires that the retransmissions be given preference over first transmissions. However, a MAC-level QoS scheduler has to decide whether to fully or partially count the retransmissions or count only the first transmissions toward the connection's specified limit. For a higher layer protocol or application,

only the successfully delivered MSDUs count toward its perception of QoS. Moreover, delay and jitter management also become challenging with retransmissions.

- *How to allocate bandwidth for ARQ feedback?* Although ARQ Feedback IEs may be piggybacked on another connection, such opportunities are not always available or sufficient. In such cases, bandwidth may need to be allocated in the opposite direction exclusively for carrying ARQ feedback. A BS may be able to allocate and transmit ARQ feedback going toward an SS on demand from the ARQ receiver. However, for transporting ARQ Feedback IEs from an SS to the BS, either an SS has to make an explicit BW request or the BS has to proactively and periodically allocate bandwidth for this purpose when ARQ connections are active.

HARQ OPERATION

HARQ parameters

The following HARQ parameters are defined:

- **SPID:** Subpacket identifier for the four subpackets of the encoder packet, which has a predefined range of 0b00 to 0x11.
- **ACID:** ARQ channel identifier, which specifies the subchannel for the subpacket transmission.
- **AISN:** ARQ identifier sequence number, which is toggled between 0 and 1 on successful transmission of an encoder packet.

The following subsections describe the usage of these parameters by HARQ protocol. The HARQ Control IE in the DL MAP or UL MAP is used to signal these parameters for a specific DL or UL HARQ burst.

Subpacket transmission and acknowledgment generation

When HARQ is enabled, the MAC delivers the constructed MPDUs to the HARQ PHY module responsible for concatenation, encoding, and subpacket generation. Since HARQ operates at the FEC level, the FEC encoder is responsible for generating the subpackets. Once generated, the subpacket with SPID 0b00 is always transmitted first. Subsequently, any one of the

subpackets with SPID 0b00, 0b01, 0b10, or 0b11 may be transmitted based on the positive or negative acknowledgment feedback from the receiver. A subpacket may be transmitted more than once, and any subpacket may be skipped, with the exception of the subpacket with SPID 0b00.

Upon receiving a subpacket, the receiver's FEC decoder attempts to decode the original encoder packet. If the original is successfully decoded, a positive acknowledgment is sent to the transmitter; otherwise, a negative acknowledgment is sent. The transmitter stops sending additional subpackets from the same encoder packet if a positive acknowledgment is received. The transmitter may transmit one of the other subpackets if a negative acknowledgment is received, and this process may continue until the receiver successfully decodes the original encoder packet. A 1-bit HARQ AISN, toggled between 0 and 1, is used to indicate a new encoder packet transmission on the same HARQ channel. Therefore, upon successful decoding of an encoder packet, the transmitter toggles this bit to indicate this fact to the receiver of subpackets belonging to the next encoder packet.

As described in Chapter 6, the synchronous HARQ positive and negative acknowledgment signaling makes use of a dedicated subchannel in the UL and a compact DL MAP with acknowledgment bitmap in the DL. However, the BS has full control over both UL and DL and may decide not to send an acknowledgment bitmap at a fixed frame offset. If no acknowledgment bitmap is present in the expected frame, the SS retains the HARQ burst and the corresponding subpackets. The BS may explicitly request a retransmission later, using the HARQ Control IE in the Compact MAP IE.

The maximum number of HARQ retransmissions in the UL and DL is advertised in UCD and DCD messages, respectively. The default maximum number of HARQ retransmissions in both DL and UL is set to four.

Performance and QoS implications

As described in Chapter 6, the stop-and-wait HARQ protocol uses synchronous acknowledgments⁵ that are sent after a fixed delay specified in

⁵ The BS may optionally decide not to send a synchronous acknowledgment and request a retransmission using an HARQ Control IE.

frame offset in both UL and DL. However, the number of subpacket transmissions required for successful decoding may vary, based on channel conditions. Moreover, the transmission/retransmission of the subpackets is not synchronous. The ability to support multiple HARQ channels per terminal does offer some additional performance, as multiple encoder packets may be pending at any instant. The ACID, carried in the MAPs, uniquely identifies the channels.

While HARQ may offer some performance improvements due to SNR gain and coding gain by incremental redundancy, the lack of control from the MAC and the inherent limitations of stop-and-wait ARQ may affect the type of QoS that can be guaranteed for an HARQ-enabled SS.

Chapter 8 Security

PKM protocol and cryptographic methods

The IEEE 802.16 standard defines security mechanisms affording privacy to subscribers and protecting operators from theft of service. These objectives are achieved by encrypting the data between the BS and SS, by utilizing digital certificate-based authentication of the SS, and by employing an authenticated client-server key management protocol called *privacy key management* (PKM). The PKM protocol allows the BS, as server, to control the distribution of keying material to the SSs. The security protocols of IEEE Std 802.16-2004 [B20] do not offer authentication of the BS. This leaves open the possibility of an SS associating with a malicious BS. However, for a fixed wireless system operating in licensed bands, this should not be a grave concern since the BS equipment may not be readily available; furthermore, operation of a malicious BS can be easily detected by a legitimate operator. Nevertheless, BS authentication has been specified in IEEE Std 802.16e.

SECURITY ASSOCIATIONS (SAs) AND CRYPTOGRAPHIC SUITES

The packet data encryption function in IEEE 802.16 resides in the security sublayer between the MAC CPS and PHY, as shown in Figure 4-1 (in Chapter 4). In the transmitter, the MPDUs are mapped to an SA, which dictates the processing to be applied to a given plaintext MPDU. The receiver uses the CID to determine the correct SA and applies the corresponding processing to the received MPDU.

The SA is a set of security-related information that is shared between the transmitter and receiver, with help from the PKM protocol. Each SA contains information on the cryptographic suite used for that SA. The SA may also contain keys, such as the traffic encryption keys (TEKs), along with their lifetimes and other associated state information. The exact content of the SA depends on the algorithm for encrypting and authenticating the MPDUs and

on the algorithm used for TEK exchange specified in the cryptographic suite. IEEE Std 802.16 defines two main cryptographic suites, as described in more detail below.

An SS entering a network will set up at least one SA, called the *primary SA*, with the BS. The BS may also set up a number of static and dynamic SAs. Static SAs are provisioned at the BS, while dynamic SAs are set up and torn down along with opening and closing service flows. In contrast to the primary SA, the static and dynamic SAs can be shared by the BS and multiple SSs.

Encrypted MPDUs

Only the payload part of an MPDU (which, as defined in the IEEE 802.16 standard, includes the MAC subheaders) is encrypted. The generic MAC header is always sent in cleartext. The cleartext header contains the two EKS bits indicating the LSBs of the TEK sequence number of the key that was used to encrypt the PDU. This allows smooth key transitions in both directions.

Data encryption with DES in CBC mode

One of the two main cryptographic suites defined in the standard specifies data encryption with DES in CBC mode. The MPDU data authenticity is not checked when using this method. The exchange of the 64-bit TEK is performed using 3DES in code book mode. During the TEK exchange, the BS delivers parameter CBC-IV, which acts as the basis for calculating the IV required for encryption processing. The encryption process involves the following steps:

1. The IV is derived by calculating the XOR of the CBC-IV and the frame number in which the MPDU transmission takes place. For UL transmissions, the XOR is taken between the frame number in which the UL MAP allocating the transmission was received and the CBC-IV.
2. The IV is XORed with the first 8 bytes of plaintext MPDU payload, and the result is then DES-encrypted to get the first 8 bytes of ciphered payload.

3. The ciphertext from the previous step is XORed with the next 8 bytes of plaintext payload and DES-encrypted to get the next 8 bytes of ciphered payload.
4. Step 3 above is repeated until less than 64 bits of payload remain unciphered. To cipher the n residual bits, the previously attained ciphertext is DES-encrypted once more. The XOR between the n MSBs of this encrypted result and the n plaintext bits is then computed. The n last bits of ciphered payload are made up of the result of this calculation.

In the receiver, the plaintext is recovered by performing a DES decryption of the ciphertext block and XORing it with the previous ciphertext block (the IV in case of the first 8 bytes). To recover the residual bits, the last full ciphertext block is encrypted once more, and the relevant part of result (the n MSBs) is XORed with the ciphered residual to get the plaintext.

The level of security provided by this suite is not very strong. DES uses keys that are considered by security experts to be too short to be secure. Also, there are some issues with the predictable way in which the cipher chain is initialized. Furthermore, the lack of MPDU authentication can be considered a weakness of the protocol. However, this suite has the benefit of not introducing any data expansion. If the weaker security of this mode is a concern, then the AES-CCM suite described below should be employed instead.

AES-CCM

The advanced encryption standard (AES) is the replacement for DES and considered to be state of the art. The AES is a block cipher with a block length of 128 bits. The keys can be 128 or 256 bits long. IEEE Std 802.16 defines a cryptographic suite that utilizes the AES algorithm in the counter with CBC-MAC (CCM) (see [B40]) mode with 128-bit keys. In addition to data privacy, the suite provides integrity protection for the MPDUs. The encryption method is the same as the one used in IEEE Std 802.11i⁶. The TEKs are exchanged

⁶ IEEE Std 802.11 and IEEE Std 802.16 construct data fields differently. Also, IEEE Std 802.11i defines its own protocol for key exchange.

using AES in code book mode. The confidentiality and data integrity protection provided by the AES-CCM is considered very strong.

The AES-CCM processing adds two fields to the MPDU payload: a 4-byte packet number (PN) and an 8-byte message authentication code. The MPDU payload before and after processing is shown in Figure 8-1.




Figure 8-1: Encrypted payload format in AES-CCM mode

The PN space is split in two—the range 0-7FFFFFFF is used for DL and the remainder for UL—because only one MPDU payload should be encrypted with a given key and PN.

The message authentication code is calculated using AES in CBC mode, with counter mode encryption. The steps of the AES encryption process are described below:

1. A set of blocks $B_0, \dots, B_r$ are formed from the MPDU.
2. A temporary CBC checksum T is calculated over these blocks.
3. Using the nonce (see Figure 8-2) and a counter incremented by one for each block, a set of counter blocks (see Figure 8-3) $S_0, \dots, S_m$ is formed.
4. The first counter block S_0 is encrypted and stored.

5. Block S_1 is encrypted, and the XOR with the first 128 bits of the MPDU payload is calculated to gain the first 128 bits of encrypted MAC payload. The same is done for the subsequent blocks, if any. If the length MPDU payload is not a multiple of 16 bytes, the last block is shortened.
6. The message authentication code is derived by calculating $T \text{ XOR } S_0$ and keeping only the eight most significant bytes.
7. The PN, the encrypted payload, and the message authentication code are concatenated to form the encrypted MPDU payload.

The initial block B_0 used in the CBC calculation is shown in Figure 8-2. By including the generic MAC header (save the redundant HCS) in the nonce, the header also will be afforded integrity protection. The remaining blocks are formed by splitting the plaintext MPDU payload in 16-byte blocks (padding with zeros to the next 16-byte boundary, if necessary).




Figure 8-2: Initial CBC block and nonce

The counter blocks are shown in Figure 8-3, where the nonce is the same as above.



Figure 8-3: Counter blocks

The processing in the receiver is similar to that in the transmitter, but the order of operations is different. The receiver starts by generating the encrypted counter blocks and decrypts the payload. After decryption, it calculates the

CBC checksum and compares this against the message authentication code. If the check fails, the receiver discards the MPDU.

KEY MANAGEMENT

Key management is handled by the authorization and TEK state machines in the SS. The authorization state machine, initialized on SS power up, handles the authorization state and AK management. In the Authorization Reply message, the SS receives the AK and the list of SAs from the BS. For each SA, the SS starts an instance of the TEK state machine that handles the key management of that SA. A TEK state machine is also instantiated upon reception of the SA Add message that creates a dynamic SA.

AK management

The AK is always accompanied by its associated lifetime. Upon reception of an AK, the SS starts a timer to measure its remaining lifetime. At the instant named "AK grace time," which occurs before the expiration of the AK lifetime, the SS initiates a reauthorization procedure to acquire a new AK. The reauthorization is almost identical to the initial authorization, but the Authorization Information message is omitted. In the BS, assuming the SS continues to be authorized, the Authorization Request message will result in a new AK being activated with a lifetime that extends beyond the lifetime of the AK that is about to expire. In this transition period, the BS will have two active AKs for an SS. The transition period and key usage are illustrated in Figure 8-4. The AK is used to derive keys for MAC management message authentication and TEK exchange. As soon as the new AK is activated, the BS starts using the keys derived from the new AK.




Figure 8-4: AK management in BS and SS

TEK management

As mentioned above, the establishment of a new SA either during initial authorization or after reception of the SA Add message will instantiate a new TEK state machine. The TEK state machine will trigger the SS to send a Key Request message to the BS to obtain the keying material for the cryptographic suite used for the SA. Two TEKs with overlapping lifetimes are maintained to prevent interruptions in data transfer due to key expiration. The scheme is illustrated in Figure 8-5. There are certain rules that the BS and SS have to follow for this scheme to work. These rules are summarized below:

- The SS is capable of decrypting DL transmissions using either TEK.
- The SS always uses the newer TEK for UL transmissions. Once it sees the SS use the newer TEK, the BS uses this information as an implicit acknowledgment that the SS has the new keying information.
- The BS uses the older TEK to encrypt data in the DL and starts using the new key only when the old one expires.
- The BS is capable of decrypting UL transmissions using either TEK.

As previously mentioned, the two LSBs of the sequence number of the TEK are carried in the generic MAC header to aid the receiver in the TEK selection for data received on a given MAC connection using a given SA.

In IEEE Std 802.16, the TEKs are usually exchanged using the same block cipher used for the data encryption; in the case of DES, the cipher is run three times with different keys. The symmetric methods are favored over key exchange using RSA, as they consume less computational resources than the RSA method, which is also specified as an option in the IEEE 802.16 standard. The symmetric methods use the key encryption key (KEK) derived from the AK using the Secure Hash Algorithm 1 (SHA-1).




Figure 8-5: TEK management in BS and SS

Chapter 9 Mesh

MAC and PHY extensions for mesh

INTRODUCTION

The concept of mesh radio systems, as an alternative to PMP, has for the last decade been a hot topic for commercial communications, evolving from earlier military work done by the Defense Advanced Research Projects Agency (DARPA) in the United States. Beyond the fixed mesh specification already available in IEEE Std 802.16-2004 [B20], the IEEE 802.16 Working Group proposed in January 2005 the development of an amendment to facilitate mobile multihop relays for fixed and mobile infrastructure. The difference between mesh and infrastructure relay is that a mesh network allows connectivity between any set of end-user and infrastructure devices without manual intervention, where the number and location of end-user devices will fluctuate. An infrastructure relay, on the other hand, is topologically limited to a tree structure with a BS at its root and infrastructure relays as branches.

Mesh is of interest not only to the IEEE 802.16 community but also to the IEEE 802.11 and IEEE 802.15 communities. In particular, the IEEE 802.11s Task Group is currently developing a mesh amendment for WLANs, and the IEEE 802.15 Task Group 5 is currently developing a mesh amendment for WPANs.

The typical reasons for designing or deploying mesh include the following (see [B52]):

- **Communication within a local community:** This is where mesh performs best, but it is not a very typical scenario.
- **Capacity increase:** When the ingress and egress of traffic is distributed throughout a mesh network, the capacity increase is easy to comprehend as traffic can be sent simultaneously over different links due to the spatially

distributed nature of a mesh network. However, when most of the traffic within the mesh is being aggregated to a very limited number of egress points (such as the core network connection), then increased capacity can be difficult to achieve. Compared to the PMP, the capacity of a mesh network represents a balance of increased overhead to schedule the mesh traffic and forwarding of data over multiple links, both of which reduce capacity, vs the substantially increased capacity of each individual link with the mesh network resulting from shorter links and the ability to route around links severely degraded by obstacles in the transmission path.

- **Alternative paths:** Mesh systems that can provide alternative paths add resilience against link failures in the network.
- **Cost-effective range extension:** Because the nodes of a mesh are typically at least an order of magnitude less expensive than a BS and comparable in cost to PMP SS devices, mesh can be a cost-effective method of range extension of a traditional PMP network when the user population is too sparse to justify the extra BSs. Keep in mind that, if the node density decreases beyond a certain point, the mesh becomes ineffective. This is shown in Figure 9-1 and Figure 9-2. The typical mesh deployment hence requires so-called “seeding” to ensure an initial minimum coverage of the area.
- **Cost-effective deployment:** In fixed deployments, coverage is typically inadequate to allow a PMP SS to be installed in an arbitrary location. In some cases, a directional antenna must be installed and aligned, at substantial cost. For logical mesh networks, coverage is omnidirectional, and user self-installation may be enabled.

These tradeoffs can determine whether PMP, a true mesh, or something like a multihop relay is most appropriate.

Two general categories of mesh systems, *logical* and *physical*, are considered here. Logical mesh uses broad-beam or omnidirectional antennas to form logical links to neighbors. These links are considered logical because the hardware configuration does not change for different links. Physical mesh, by contrast, uses substantially directional antennas to create physical links. Links are considered physical because the hardware configuration (via beam forming or via switching, for example) changes to form different links with different neighbors. Both varieties have challenges and benefits.




Figure 9-1: Three BSs required for full coverage




Figure 9-2: Two BSs required with mesh SS

IEEE Std 802.16 includes both concepts to some extent. The logical mesh is completely specified, whereas hooks are in place for the physical mesh, known in the standard as *directed mesh*. Although it was never fully specified in the standard, it is worth spending further discussion here on the topic, especially since some of the concepts may be reused in the proposed mobile multihop relay amendment.

LOGICAL MESH

Since the logical mesh was incorporated into the IEEE 802.16 standard primarily by the proponents of the OFDM PHY, this mode was defined to function only with the WirelessMAN-OFDM PHY. Despite the fact that the mesh MAC uses many of the same messages used by the PMP MAC (there are only five mesh-specific MAC message formats), specifically in the upper MAC, the two architectures are not interoperable.

The logical mesh architecture is based on the concept of neighborhood, where distinction is made among the following:

- **Node:** A device participating in the mesh network. Although some devices may have a connection to the core network and some may be assigned special functions such as centralized schedule controller (Mesh BS) or master clock, all devices are equal, and all connectivity is peer to peer at the most fundamental connectivity level of the network.
- **Immediate neighborhood:** The collection of nodes with which the station of reference is capable of establishing direct physical connection. These nodes are also referred to as *one-hop neighbors*.
- **Extended neighborhood:** The collection of nodes with which the nodes in the immediate neighborhood can establish direct physical connection. Stations in the extended neighborhood that are not immediate neighbors are referred to as *two-hop neighbors*.
- **Cell:** The collection of nodes that are associated with the same coordinated (distributed and/or centralized) scheduler. Between cells, only uncoordinated distributed scheduling can take place. A node that has an interface to the core network or controls the centralized scheduler is

termed *Mesh BS*. Typically these nodes include both functionalities. All other nodes are also termed SSs for the sake of simplicity.

- **Network:** A collection of cells where nodes may arbitrarily associate with the cell of choice and where synchronization takes place between the cells.

This concept is graphically depicted in Figure 9-3.




Figure 9-3: Neighborhood definitions

The definition of the mesh architecture consists of essentially four aspects that are different from PMP: PHY frame format, network entry, network configuration/maintenance, and scheduling of data exchanges. The first aspect is dealt with in Chapter 11; the others are explored below.

Mesh connections and addressing

Beyond these aspects, the single most substantial difference between logical mesh and PMP is the usage of the concept of CIDs. In PMP, each 16-bit CID represents a unique, logically numbered connection to an SS with a defined set of QoS parameters. In a logical mesh network, the CID is used to convey a Link ID, unique only in the local neighborhood, and a set of broadcast/unicast service parameters. To uniquely identify the destination node, a 16-bit Node ID, unique within the network, is appended to the MAC header. The mesh system is hence not connection-oriented, but applies priority on a packet-by-packet basis. As a packet moves through the network, the Link ID in the CID will change with each transmission, whereas the service parameters typically do not. The mesh CID and mesh Broadcast CID are shown in Figure 9-4.




Figure 9-4: Mesh CIDs

Network configuration

Network configuration is achieved by means of broadcasting the MSH-NCFG (mesh network configuration) message. It contains both physical information of the device itself, such as the transmit power as well as network time-synchronization information, nearness to known Mesh BSs, a list of all known neighbors with which connections exist, and information about the next transmission of the MSH-NCFG from the node. MSH-NCFG is also used to assist with network entry, which is explained later.

The time-synchronization information consists of frame number, the control slot number, and the synchronization hop count. Because control slots have a fixed length, nodes are able to determine from this number when the frame must have started. Fine time synchronization is not done with this method; for this, the PHY is responsible. The synchronization hop count provides the number of hops by which the node is removed from the master synchronization node, which is typically a Mesh BS. Nodes will defer in their synchronization timing to nodes with a lower synchronization hop count. In a system that consists of multiple cells, it is possible to have only one master synchronization node so that all cells are synchronized.

Nearness to a Mesh BS is computed with two metrics. The first is a straightforward hop-count, which for any node is the lowest value reported by any of its physical neighbors, plus one. The second metric is the required energy per bit across all hops to the BS, which is computed by all nodes as the minimum of the value reported by its physical neighbors plus the ratio of the transmit power and achievable physical data rate to that neighbor. This second metric allows a better capacity tradeoff as it balances the number of hops vs the data rates over those hops.

Connections are split into two categories: *physical* and *logical*. A physical connection exists merely by means of being able to decode the MSH-NCFG message of the other nodes. Neighbors with which only a physical connection exists cannot be addressed for data transmissions. Logical connections require an underlying physical connection and are addressable for data exchanges.

When listing its physical neighbors with the MSH-NCFG message, a node indicates, for each neighbor, whether a logical link is present. It can also flag that, for this link, a logical link is desired, or, when a neighbor put up such a request flag, that the request is accepted. The physical connection information also contains schedule information for the next transmission opportunity as reported by the neighbor. For logical connections, the list also contains information such as link quality, used burst profile, and transmit power.

Transmissions of MSH-NCFG are scheduled in a distributed fashion. A substantial computational burden would result if, in a single control slot, all nodes compete to transmit a MSH-NCFG. Therefore, a method is provided to limit the control slots in which a node can compete as well as the number of

nodes that can compete in any particular slot. This method depends on the broadcasting by each node of two values, *Xmt Holdoff Exponent* (XHE) and *Next Xmt Mx* (NXM), and on reporting these values to each neighbor within the physical neighborhood so that the entire two-hop neighborhood of a node has access to the values for this node.

Xmt Holdoff Exponent is used to compute the number of control slots following the next MSH-NCFG transmission during which the node will not be eligible to transmit another MSH-NCFG as being $2^{XHE} + 4$. Both *Xmt Holdoff Exponent* and *Next Xmt Mx* are used to compute the eligibility interval for the next MSH-NCFG as

$$2^{XHE}(NXM) < \text{Next Xmt Time} \leq 2^{XHE}(NXM + 1)$$

For any control slot that falls within an eligibility interval, a node computes the list of nodes in its two-hop neighborhood whose eligibility intervals also contain this control slot. Each node then applies an algorithm to see whether it wins the election among this list of nodes. This guarantees that nodes transmitting MSH-NCFG simultaneously are at least three hops apart, which is generally enough to avoid mutual interference.

Network entry

Network entry for mesh devices consists of five steps:

- Scanning for active networks and coarse synchronization.
- Obtaining network parameters.
- Opening sponsor channel.
- Negotiating basic capabilities.
- Performing node authorization, registration, IP connectivity establishment, time-of-day establishment, and operational parameters transfer.

The first three are PHY and lower MAC functions that are substantially different from PMP behavior and are described below. The capabilities negotiation is identical to that performed under the PMP architecture, with the new node sending the SBC-REQ to the sponsor node (the node assisting the new node with network entrance). This capability exchange will be performed

with any node with which a new logical connection is established (contrary to the entire network entry process, which is performed only once). The last step is similar to behavior under the PMP architecture, with the main difference being that the new node tunnels the message exchanges over UDP between itself and the mesh BS through the sponsor node. Because this process is transparent to the sponsor node, the sponsor node cannot determine when the upper MAC initialization is successful; therefore, it is the new node that, as shown in Figure 9-5, indicates completion of this phase to its sponsor node.

Scanning for active networks and coarse synchronization

Scanning is a lower PHY functionality and hence architecture independent. A node will listen to the medium cycling through all available channels until it detects energy and a strong correlation between the known preamble sequence and the received signal. This correlation allows the PHY to synchronize itself to the timing of the start of that burst. The new node will then continue listening to subsequent bursts until its MAC detects MSH-NCFG messages. This synchronization process is termed *coarse synchronization* and should not be confused with the coarse and fine timing synchronizing the lower PHY performs when synchronizing the PHY to the burst itself.

Obtaining network parameters

A new node is required to continue monitoring the channel for MSH-NCFG messages until it hears the same node at least twice, ensuring that the new node has collected a reasonable subset of potential neighbors. It also will have to wait until it receives at least one MSH-NCFG with a Network Descriptor subfield, which is one of the five defined subfields to the MSH-NCFG. The network descriptor contains such parameters as the number of control slots, the scheduling methods used, information on used channels, and criteria for the use of burst profiles as well as the Operator ID; and it is only occasionally attached to the MSH-NCFG by each node. The entire process of obtaining network parameters may take seconds, but in a fixed system, it is required only when the system is turned on (the neighbor list and network parameters can be maintained across losses of synchronization that make reentry necessary).

Opening sponsor channel

Once the collection of network parameters is completed, the node starts its request to join the network, as outlined in Figure 9–5.




Figure 9–5: Mesh network entry: Opening a sponsor channel

For the purpose of joining the network, the node selects any of its neighboring nodes that are not currently assisting another node in network entry and transmits a MSH-NENT (mesh network entry) message with the NetEntryRequest subframe in the control slot reserved for network entry (see Chapter 11). The solicited node indicates its acceptance of the request by

setting the new node's MAC address in the next MSH-NCFG and publishing an arranged schedule for data transfer in the data portion of the frame to this new node; the solicited node then takes on the role of sponsor. (A solicited node that is currently assisting another candidate node in network entry will signal this fact by setting that candidate's MAC address in its MSH-NCFG messages until its role as sponsor is terminated.) Upon reception of the MSH-NCFG and schedule, the new node confirms the schedule with a MSH-NENT message with the NetEntryAck subfield and proceeds with the fifth step of network entry by use of the facilitated schedule. Upon completion of this fifth step, an exchange of MSH-NENT messages with NetEntryAck, initiated by the new node, terminates the sponsor's role and adds the new node into the network. Due to the tunneling, this last exchange is initiated by the new node.

Distributed scheduling


Distributed scheduling is also based on the assumption that if a node is not part of the extended neighborhood, the probability of interference is sufficiently low to be irrelevant. The distributed scheduling mechanism, therefore, ensures that the entire two-hop neighborhood is aware of the pending data transmission to ensure a near-collision-free transmission. The distributed scheduling protocol uses only the MSH-DSCH (mesh distributed scheduling) message format to execute a three-way handshake for exchanging: requests (in which data slots in which the medium is free to fill those requests are indicated), grants, and grant confirmations. This handshake occurs in the control portion of the frame, which is collision-free using the distributed algorithm also used for MSH-NCFG, with the two parameters (as for MSH-NCFG) sent with every coordinated MSH-DSCH message. The transmitting party sends out a request, consisting of a demand level and a persistence ranging from 1 to 128 frames, and the status of the medium of which it is aware. The status consists of "busy," "free for transmission and reception," "free for transmission," or "free for reception." This effectively notifies its immediate neighbors that the medium will be busy during the time indicated as free for the indicated direction of the transmission and during the time indicated as busy due to other known scheduled transmissions among the one-hop neighbors. The receiving party responds with a grant in some or all of

the requester's indicated free time, effectively notifying its immediate neighbors that the medium is reserved for the particular transmission during that period, which those neighbors will then mark as busy in their own schedules. The requester then confirms the indicated grant. The free medium time is computed as the period that none of the immediate neighbors has indicated as busy.

The only difference between coordinated and uncoordinated distributed scheduling is that for uncoordinated distributed scheduling, the handshake takes place in the data portion of the frame, making it susceptible to collisions due to attempts by other stations to set up an uncoordinated schedule.

The method is depicted in Figure 9-6, where node 1 is the node requesting the schedule, and node 2 is the node at which the request is directed. Node 3 is an immediate neighbor of node 1, but not of node 2; node 4 is an immediate neighbor of node 2, but not of node 1. Node 5 is a two-hop neighbor (i.e., within the extended neighborhood) of node 1.

When node 1 issues the request including an indication of potential free slots for the allocation to meet the request, it is received both by node 2 and node 3. Until it receives the grant confirmation sent by node 1, node 3 will assume the request will be granted in the explicitly indicated free slots and mark those temporarily as busy in its schedule. Node 2 will reply to node 1 with a grant in some or all of the indicated free slots, which also notifies node 4 of the allocation, and node 4 will mark those free slots as busy in its own schedule. The grant confirmation sent by node 1 finalizes the handshake between node 1 and node 2 and also serves to notify node 3 of the exact slots being used, as a result of which node 3 may mark the unused slots as free again. Because node 3 will advertise its availability before node 1 sends its grant confirmation (because of the cyclic way the control schedule is designed), node 5 (and any other node in the two-hop neighborhood) will effectively avoid any transmissions within the two-hop neighborhood during the same slots because they know from the free slots advertised by the one-hop nodes that those slots are being used by one of their two-hop neighbors.



- I - Immediate/one-hop neighbors of either transmit or receive node
- T - Two-hop neighbor
- M - Multihop neighbor

Figure 9-6: Distributed scheduling

Centralized scheduling

The concept of centralized mesh is based on the notion that most traffic passes the gateway into the core network and that the node immediately connected to this core network, the Mesh BS, determines the flow of traffic throughout the entire cell. To achieve this, the BS dynamically splits the mesh-connected nodes up into a tree structure, which, by means of a schedule decided by the BS, is then used to arrange upstream and downstream traffic allocations. In a pure OSI model, knowledge of the routing tree would exist only at the routing layer. However, the IEEE 802.16 mesh specification defines knowledge of the tree at the MAC, which enables higher MAC efficiency.

To be able to decide how to update the tree structure (which at network initiation consists only of the BS itself), the current tree structure is used for a fixed schedule to pass down the tree MSH-CSCF (mesh centralized scheduling configuration) messages, which contain the number of nodes attached to the BS and for each of those nodes its ID and the IDs of all its child nodes. An example of a MSH-CSCF list is shown on the right-hand side in Figure 9-7, where the ID of each node is indicated with a single character, and the burst profile indicators in both directions are omitted. The order in which the nodes are listed in the MSH-CSCF is irrelevant, but it is used to indicate the child-parent relationship from which each node can reconstruct the entire tree.




Figure 9-7: Centralized scheduling

The transmission rule for MSH-CSCF is that the BS transmits it first, followed by all its immediate children in list order, followed by the children of the first listed child in list order, etc. In the example in Figure 9-7, the transmission order is, therefore, identical to the list order; note that nodes without children do not rebroadcast the schedule. Due to its overhead burden, MSH-CSCF is used only occasionally, depending on the volatility of the network, whereas incremental changes can be distributed through the frequently sent MSH-CSCH (mesh centralized scheduling) message.

The MSH-CSCH messages serves three purposes:

- To distribute BW requests and grants up and down the tree, respectively. The requested and granted bandwidth is indicated as a function of instantaneous bits per second. The BS and all other nodes use their knowledge of the burst profile on each branch of the tree to translate this into an allocation of time. To facilitate the requests, each node uses a table the size of its branch in the MSH-CSCF list and fills, in MSH-CSCF list order, the BW requests for itself and all nodes down its branch. For example, in Figure 9-7, node K transmits a table with six entries, containing the BW requests of itself and the five nodes (I, D, G, J, and H) in its branch. The list order within the table is dictated by the list order in the MSH-CSCF, shown also in Figure 9-7, which all nodes including node K received from the BS. The transmission order for the requests, shown on the left side of Figure 9-7 starting with node H, is the reverse of the MSH-CSCF message, resulting in the table growing in size until the BS finally combines the pieces of the table into the full table. In their own request (for example, the entry for node K in the request table sent by node K), nodes indicate only the bandwidth needed for traffic that terminates in the node itself, not the cumulative traffic from the nodes downstream. In Figure 9-7, the upstream order of transmissions for MSH-CSCH with the request content of each transmission is shown on the left-hand side.
- To allow a node to request the BS to facilitate bandwidth to add a new node to the cell. The node initiating the request is termed a *sponsor node*.
- To enable the BS to notify the nodes of changes to the tree structure or changes in burst profile, which may be necessitated by changes in the propagation conditions. In this case, nodes and their new parent (or old parent, if only the burst profile changes) are identified with their respective list number in the last MSH-CSCF, which are 1-byte IDs.

Note that MSH-CSCH currently does not allow a node to send up a request for a downstream flow starting in the node, as the indication for this is limited to grants (which are issued by the Mesh BS). Hence, this requires that all downstream traffic be routed through the Mesh BS. As a result, the Mesh BS would need to inspect traffic to predict the required downstream flow grants,

and, although this need does not break the specification, it is impractical. This should, therefore, be considered an error in the specification, which is correctable by the removal of a single "if" statement in the MSH-CSCH frame format.

Note also that there is no facility for nodes to pass up changes to the tree except for the facilitation to add new nodes. This is done because deciding the tree structure is primarily a routing layer function, and hence the indication of the parameter set used by the Mesh BS to decide the tree is left to this layer. In other words, in practice, if a node loses the physical connection with its parent node in the tree, it would have to use the distributed scheduling mechanism using MSH-DSCH to achieve an update to the tree through another neighbor.

DIRECTED MESH AND POINT-TO-POINT (PTP)

Directed mesh in IEEE Std 802.16 can be thought of to some extent as transient PtP links from devices that could act as repeaters for the BS. The hooks for both directed mesh and PtP have been added for systems that use the WirelessMAN-SC PHY, but neither has been completely developed in the standard.

While a BS talking to a single SS in PMP mode is in principle a PtP link, it carries a significant amount of MAC overhead that is essential in the PMP case, but simply adds inefficiency to PtP operation. Furthermore, PtP range can be quite long through the use of highly directional antennas. This concept is shown in Figure 9-8.

The basic PtP link illustrated is a single-path link between the BS and an SS. With directed mesh, the concept is expanded; the SS has some ability to repeat all or some of the BS's transmission on another beam, in a different direction, and possibly on a different frequency. Such a system might appear as shown in Figure 9-9.

Physical or directed mesh can have many benefits. The reduced beam width can significantly improve the carrier to interference ratio (C/I) and improve frequency reuse. This gives high spectral efficiency. Conversely, network entry is greatly complicated, and the antenna systems are more expensive than with a standard PtP SS.




Figure 9-8: Addition of PtP

Interference impact on reuse reduced due to a smaller arc of impact




Figure 9-9: Physical or directed mesh

Chapter 10 PHY: WirelessMAN-SC

Single-carrier PHY for 10–66 GHz

The WirelessMAN-SC PHY specification is intended for operation in the 10–66 GHz frequency range. At these frequencies, LOS operation is a practical necessity due to the propagation characteristics. This makes mobility infeasible. While radios operating at these frequencies are typically expensive, highly directional antennas of practical size are available; therefore, given a LOS, multipath propagation can be negligible. This allows for a low-complexity, single-carrier PHY with good performance, even over a broadband channel. This is compatible with the large spectrum allocations in these frequency bands and the user data rates necessary to justify the radio costs with today's technologies.

As the original IEEE 802.16 PHY specification, WirelessMAN-SC set some precedents. For instance, both TDD and FDD configurations are supported in order to allow operation in worldwide spectrum allocations. Care was taken to make the FDD and TDD systems as similar as possible to minimize the impact of implementing both variants. Both have the same basic frame structure supporting adaptive burst profiling. The main difference is whether the DL subframe and UL subframe are sequential or simultaneous in time. The FDD case looks very much like the TDD case, but with the DL and UL subframes "stretched" toward each other so that they overlap. The FDD configuration also has special features to support half-duplex SSs.

The allocation of channel time (generally known in the IEEE 802.16 standard as *bandwidth allocation*) at the PHY is based on a combination of time division multiple access (TDMA) and demand-assigned multiple access (DAMA). In the UL, the channel is divided into a number of time slots (i.e., PSs) that are assigned to various purposes on a frame-by-frame basis by the BS MAC, based on demand. Time slots are available for ranging, contention-based BW requests, and user traffic. In the DL, the data bound for each SS are

multiplexed in a TDM fashion into a single stream of data and available for reception by all SSs within the same sector. This stream may change its PHY burst profile on QAM symbol boundaries within the frame to allow a tradeoff of robustness for efficiency. To support H-FDD SSs, provisions are made for resynchronization to the DL in midframe.

FRAME STRUCTURE

The WirelessMAN-SC PHY, like the other IEEE 802.16 PHYs, operates in a framed format. The frame structure eases the task of PHY synchronization. Within each frame, in the TDD case, are a DL subframe and an UL subframe. The DL subframe begins with information necessary for frame synchronization and control. While the DL data PDUs are addressed to individual SSs or to a broadcast address, the DL MAPs describing the DL merely indicate the occurrences of DL PHY burst profile changes; they do not indicate to which SS a series of time slots is directed. So each SS attempts to receive all portions of the DL except for the bursts whose profiles either are not implemented by the SS or are less robust than its current operational DL burst profile. The SS filters the data by CID, retaining only the data intended for it. Encryption ensures it cannot make use of data destined for other SSs anyway.

The WirelessMAN-SC PHY allows three different frame durations: 0.5 ms, 1 ms, and 2 ms. While not strictly required, the different frame durations are typically associated with different channel bandwidths, allowing a tradeoff of overhead vs protocol latency, with 1 ms frames being the most typical. Frame durations of 0.5 ms might typically be used for large channel bandwidths of 50 MHz or 56 MHz, while 2 ms frame durations might be preferred for channel bandwidth less than 20 MHz.

To keep the MAPs compact and to ensure that allocations are on byte boundaries, the building blocks for allocation are PSs of four QAM symbols each, yielding 1, 2, or 3 bytes, respectively, for QPSK, 16-QAM, and 64-QAM modulations. In the DL, the allocations are at this PS granularity. Because the number of QAM symbols in a 2 ms frame on a 56 MHz wide channel is greater than can be represented by the fields in the UL MAP (a 2 ms frame on a 56 MHz channel is allowed, but not recommended), the

granularity of the UL allocations are 2^m PSs (m ranging from 0 to 7). The typical value for m is 0 (1 PS granularity).

The basic structure for the DL subframe is taken from the TDD configuration of the system and is shown in Figure 10-1. The DL subframe starts with a frame start preamble used by the PHY for synchronization and equalization. This is followed by the frame control section, consisting of the DL MAP and UL MAP, broadcast to all SSs indicating the PSs at which the various bursts begin. The frame control section is followed by a TDM section carrying data and organized into burst profiles ordered by decreasing burst robustness. For example, assuming the FEC parameters do not change, data transmission begins with QPSK modulation, followed by 16-QAM, followed by 64-QAM. In the case of TDD, a TTG follows the DL subframe, allowing time for the BS to switch from transmit to receive and for the first SS of the UL to switch from receive to transmit mode.




Figure 10-1: TDD DL subframe structure

The structure of the DL subframe for the FDD case can be quite similar to that of TDD operation, but becomes more complex with the introduction of H-FDD SSs. In the FDD case, the BS is full-duplex, but both full-duplex and half-duplex SSs are allowed. Although a full-duplex SS is capable of functioning as a half-duplex device, the IEEE 802.16 standard assumes that H-FDD SSs differ in being incapable of receiving while transmitting. This assumption allows for simplicity and cost savings in designing the H-FDD SS. When only full-duplex SSs are used, the FDD DL subframe is identical in structure to the TDD DL subframe except for the lack of a TTG. H-FDD SSs complicate matters, however, because whenever they are directed to transmit in the UL, they potentially lose synchronization (in particular, phase synchronization) with the DL. This makes it difficult or impossible for them to receive more DL data until resynchronized. As discussed below, a special preamble is specified for this purpose.

The FDD DL subframe structure is shown in Figure 10-2. As can be seen, the initial TDM portion is identical in structure to that of the TDD DL subframe. During this portion of the DL subframe, the BS can transmit data to the following:

- Full-duplex SSs.
- H-FDD SSs scheduled to transmit on the UL later in the frame than when they receive in the DL (the SSs that do not lose synchronization).
- H-FDD SSs not scheduled to transmit on the UL in this frame.

Unfortunately, in a system that has primarily H-FDD SSs, use of only the TDM portion could waste upwards of half the channel bandwidth, due to SS loss of synchronization.

To allow H-FDD SSs to transmit earlier than they receive in a frame, a TDMA section was introduced that differs from the TDM section in two important respects. First, extra preambles are inserted to allow resynchronization with the DL. The positions of these are described in the DL MAP. Second, given the extra preambles for resynchronization, there is no longer a need to smoothly transition through progressively less robust PHY burst profiles; therefore, the burst profiles used may occur in any order convenient to the BS's scheduling algorithm.




Figure 10-2: FDD DL subframe structure

Since the H-FDD SSs are nearly synchronized with the BS, the resynchronization preambles are shorter than the frame start preamble. The frame start preamble is 32 bits, created from the repetition of a 16-bit constant amplitude zero autocorrelation (CAZAC) sequence. The resynchronization preambles are 16 bits, created from the repetition of an 8-bit CAZAC sequence.

For WirelessMAN-SC, the frame control section of the DL always contains a DL MAP and a UL MAP, encoded with an especially robust well-known modulation/FEC combination (using QPSK). The DL MAP and UL MAP are structured so that the frame control section is always at least two FEC blocks in duration, but the first DL PHY transition will always be identified in the first FEC block of the frame, even if the DL MAP message does not terminate

in that block. This ensures that the SS will be warned of the upcoming PHY burst change at least one FEC block in advance.

While the frame control section is transmitted with a well-known burst profile, the remainder of the burst profiles used can be any of the over 4000 possible combinations of modulation and FEC allowed by the WirelessMAN-SC PHY. Since a practical number of PHY burst profiles is closer to four than to 4000, and also to avoid ballooning the DL MAP with numerous PHY parameters, the frame control section periodically contains DCD messages that describe the four or so (up to 13) burst profiles used in the DL. These burst profile descriptions contain all necessary information, such as FEC, modulation, SNR thresholds, etc. These parameter sets are then identified by a 4-bit DIUC. This 4-bit value is used in the DL MAP as a shorthand for the numerous bytes of data that would otherwise be required to describe each PHY burst.

Similarly, for the UL, the UCD message appears periodically in the frame control section of the DL. It describes the parameters of the UL PHY burst profiles in use and identifies them by a 4-bit UIUC that appears in the UL MAP as a shorthand for the actual parameter sets describing the burst profiles.

DL CHANNEL ENCODING

The DL data sections are used to transmit data and control messages to specific SSs. The data are always FEC coded and are transmitted at the current DL operating modulation of each SS. In the TDM portion of the DL subframe, the data are transmitted in decreasing order of burst profile robustness. Within a particular burst, the data transmitted at a given burst profile may contain data for multiple SSs multiplexed together. It is the responsibility of the SS to extract its data from data destined for other SSs sharing a common operational DL burst profile. In the TDMA section, the data are grouped in separate burst profiles that need not be in order of robustness. The BS may, but is not required to, segregate the data by SS as well as by burst profile. However, the DL MAP generally does not indicate the target SS; therefore, SSs listen to all bursts for which they are capable.

While a new DL burst always starts on a PS boundary, the choice of FEC parameters and modulation may cause FEC blocks to end in the middle of a PS or even in the middle of a QAM symbol. However, they always end on bit boundaries. The next FEC block starts on the next available bit, without padding to the next symbol or PS boundary. The last data for a burst may not be sufficient to fully fill an FEC block. In this case, the last FEC block of the burst may be shortened. Unused bits in an unshortened FEC block or the bits used to allow realignment of the next DL burst to a PS boundary are padded with all ones. Figure 10-3 illustrates the allocation of data to a DL burst. If the burst contains a preamble, as is the case for the frame control section and TDMA bursts, the preamble is considered part of the burst and precedes the first FEC block of the burst.




Figure 10-3: DL MAP usage with shortened FEC blocks—TDM case

Within each FEC block, additional information is added to help resynchronize the MAC to the next MPDU within the bit stream in the case of an unrecoverable error in an FEC block. This capability is handled by the transmission CS. Since MPDUs are variable in length, while the FEC blocks of a burst are of fixed length, it is common for MPDUs to begin or end in the middle of an FEC block. The MAC header contains the length of the MPDU, which is required for extracting the MPDUs from the received bit stream. Unfortunately, if an FEC block has unrecoverable errors, this length information may be lost or erroneous, causing difficulty in finding the start of the next MPDU. To avoid the risk of the SS losing all data until the end of the PHY burst, each FEC block uses the first byte of its payload not for data but for a field indicating where, if anywhere, within the FEC block the next MPDU starts. This allows the SS to quickly resynchronize to the next MPDU rather than losing the remainder of the burst. This FEC payload structure is shown in Figure 10-4. The same mechanism is employed in the UL.




Figure 10-4: Format of DL transmission CS PDU

In addition to FEC and modulation, the data go through a randomization process and pulse shaping. The processing chains for transmit and receive are shown in Figure 10-5.




Figure 10-5: Conceptual block diagram of DL PHY

There are four basic types of FEC used in WirelessMAN-SC. These can be further parameterized to give many possible combinations.

The first type, which is specified as mandatory, is a Reed-Solomon (RS) outer code over Galois field (GF) 256 with no inner code. It is generally used for user data except when, even with QPSK modulation, a stronger coding is desired. It can be parameterized with the information block length K variable from 6 to 255 and with error correction capability to correct errors from $T = 0$ to 16 bytes, depending on the number of parity bytes $R = 2T$.

The second type of FEC, also mandatory, is used for the frame control section and for transmissions that need to be very robust. The RS is used with an inner (24, 16) block convolutional code (BCC) derived from a four-state, nonsystematic punctured (7, 5) convolutional code. In this case, the number of information bytes K for the outer RS code must be an even number so that the total size $(K + R)$ is also even, since the inner BCC operates on pairs of bytes. In the frame control section, the parameters are set to $K = 26$ and $R = 20$.

The third FEC type is optional and combines the RS outer code with a (9, 8) parity check code. In this case, a parity bit is calculated for each RS symbol individually and inserted as the LSB of the resulting 9-bit word. The parity bit is the XOR of all 8 bits in the symbol.

The fourth and final FEC type is an optional block turbo code (BTC). If implemented, both $(39, 32) \times (39, 32)$ and $(53, 46) \times (51, 44)$ codes are required. Shortening can apply to the last FEC block of a BTC-encoded burst, as in the RS case.

To maximize the spectral efficiency of the airlink, the WirelessMAN-SC PHY uses a multilevel modulation scheme. The modulation is optimized for each SS based on the quality of the RF channel. If link conditions permit, a more efficient modulation is used to maximize the tradeoff between bandwidth and robustness. If the RF quality degrades, the BS changes to a more robust modulation for that subscriber. If it improves, it changes to a more efficient modulation.

The WirelessMAN-SC PHY supports QPSK, 16-QAM, and 64-QAM providing 2 bits, 4 bits, and 6 bits per QAM symbol, respectively. Two power adjustment rules can be used when transitioning from one modulation to another: *constant peak power* and *constant average power*. In the constant peak power scheme, corner points are transmitted at equal power levels regardless of modulation. In the constant average power scheme, the signal is transmitted at constant average power regardless of modulation. The power adjustment rule is communicated via the DCD message. If a burst at a specific modulation does not end exactly on a PS boundary, the remainder of the burst is filled with zero bits.

Prior to modulation, the I and Q signals are filtered by square-root raised cosine filters with the excess bandwidth factor α set to 0.25.

UL CHANNEL ENCODING

In the WirelessMAN-SC PHY, three types of bursts may be transmitted in the UL subframe:

- Contention-based initial ranging bursts.

- Contention-based multicast or broadcast BW requests.
- Dedicated data bursts in response to unicast bandwidth grants allocated to individual SSs.

In a given UL subframe, any of these burst types may be present (or absent) and may occur in any order and quantity. The scheduler at the BS indicates which bursts are present via the UL MAP message. The bursts are separated by subscriber station transition gaps (SSTGs), allowing for the ramping down of the previous burst and the ramping up and preamble of the next burst. The preamble allows the BS to fine-tune its synchronization to the transmission of the individual SS. As in the DL, the preambles may be 16- or 32-bit repetitions of 8- or 16-bit CAZAC sequences. The UCD message communicates the gap and preamble lengths. Figure 10-6 illustrates an example of the UL subframe structure.




Figure 10-6: UL subframe structure

Request bursts always use UIUC = 1, which always uses QPSK modulation and FEC type 1 or type 2 as defined for the DL. Request bursts are always at

least as robust as the most robust unicast UL data bursts. Initial ranging bursts always use UIUC = 2, which specifies burst characteristics identical to those used in the DL in the frame control section. The UL MAP entries of WirelessMAN-SC are directed to the Basic CID (or multicast group or Broadcast CID) of a specific SS and are relative to the previous MAP entry. They specify the start of the burst, but the next MAP entry implies the end of the burst. The last burst of a UL subframe has an end symbol indicated by an end-of-MAP entry allocated to CID = 0 with UIUC = 10 (decimal).

The UL uses the same FEC and the same transmission convergence subframe as the DL. Also, like the DL, in addition to FEC and modulation, the UL data go through a randomization process and pulse shaping. The processing chains for transmit and receive are shown in Figure 10-7.




Figure 10-7: Conceptual block diagram of UL PHY

As in the DL, the I and Q signals, prior to modulation, are filtered by square-root raised cosine filters with the excess bandwidth factor α set to 0.25.

This 0.25 roll-off factor defines the symbol rate, which, for a 25 MHz channel, would be 20 Mbd. This would give bit rates for QPSK, 16-QAM, and 64-QAM of 40 Mbit/s, 80 Mbit/s, and 120 Mbit/s, respectively. Other channel sizes scale linearly. For example, a 28 MHz channel has a 22.4 Mbd symbol rate.

CONTROL MECHANISMS

The DL demodulator must provide an output reference clock derived from the DL symbol clock. This reference is then used by the SS to provide timing-critical interfaces. One would expect that the BS reference is locked to an accurate (stratum 1) reference such as GPS. This highly accurate timing is used to provide frequency tuning to within $\pm 10 \times 10^{-6}$.

The WirelessMAN-SC PHY requires accurate UL time-slot synchronization and UL transmit time advance to ensure that multiple users do not interfere with each other's transmissions. The ranging procedure outlined in Chapter 7 allows the fine-tuning of timing required for robust operation with efficient burst profiles.

For WirelessMAN-SC, the predominant dynamic impairment is rain fade. The typical extent of the fade varies geographically based on rain region and is affected by both carrier frequency and range. For a desired link availability and given set of transmission parameters, the rain region dictates the maximum cell radius. Additionally, uncorrelated rain fade between an interfering signal and the desired signal may also affect cell radius.

Power control is applied statically in the DL to effectively set cell size and dynamically in the UL to account for fading due to rain and foliage. This dynamic UL power control must handle fades of up to 20 dB/s with dynamic range of at least 40 dB. The specific algorithm is left for vendor differentiation. The BS's EIRP spectral density is capped by +28.5 dBm/MHz or a lower limit if established by local regulations. The SS is limited to an EIRP spectral density of +39.5 dBm/MHz or local regulation.

Received signal strength indicator (RSSI) and CINR signal quality measurements and associated statistics are used in burst profile selection. RSSI measurements do not necessarily require receiver demodulation lock

and are, therefore, used for measurement of low signal levels. CINR requires receiver lock, but provides better information on the actual operating condition of the receiver, including interference and noise levels as well as signal strength.

WIRELESSMAN-SCA

This chapter concludes with a brief description of the WirelessMAN-SCa PHY specification, which is targeted at operation below 11 GHz. In many respects, it is very similar to the WirelessMAN-SC PHY. It was originally added to the standard in IEEE Std 802.16a-2003, with the tacit assumption that it would be used in conjunction with frequency-domain equalization. It has not found subsequent industry support and, at this time, appears to be an orphan.

The WirelessMAN-SCa FEC specification is similar to, but slightly different from, WirelessMAN-SC. The basic FEC is a concatenated FEC, with an outer RS code derived from a systematic RS ($N = 255$, $K = 239$) code using GF(256). The block may be shortened. An inner trellis-coded modulation (TCM) code derived from a $K = 7$, rate 1/2 convolutional code is used. Optionally, an interleaver may be placed between the inner and outer codes.

In addition to QPSK, 16-QAM, and 64-QAM, the WirelessMAN-SCa PHY also requires the implementation of spread binary phase shift keying (BPSK) and BPSK modulations. 256-QAM modulation is optional. Block turbo codes (BTC) and convolutional turbo codes (CTC) are also optional. When ARQ is implemented, the FEC can be disabled (through the "no FEC" option), and the ARQ can be used as a sole method for error correction.

Like WirelessMAN-SC, the WirelessMAN-SCa PHY is defined for both FDD and TDD operation. The WirelessMAN-SCa PHY includes explicit support for beam forming.

The system must handle fade rates of 30 dB/s with depths of 10 dB. Both RSSI and CINR are used for measurements of signal quality. Frequency accuracy must be within $\pm 15 \times 10^{-6}$.

Chapter 11 PHY: WirelessMAN-OFDM

Multicarrier PHY for frequencies below 11 GHz

WirelessMAN-OFDM is one of the three PHY specifications defined in IEEE 802.16 for applications below 11 GHz. For brevity and convenience, the PHY of a WirelessMAN-OFDM system is abbreviated as the "OFDM PHY."

WAVEFORM CONSTRUCTION

Selection of the OFDM waveform

The choice of OFDM for use below 11 GHz was in general based on two considerations. The first of these was that, among the IEEE 802.16 members, a fair number had experience with OFDM systems due to the approval of the IEEE 802.11a amendment in 1999. In addition, a small number of participants were involved with companies developing proprietary OFDM-based systems for BWA. Selecting OFDM was for these members a natural choice. Aside from these external issues, however, OFDM was supported because of its favorable technical characteristics.

As noted in Chapter 3, robust BWA systems in spectrum below 11 GHz must deal with multipath without resorting to highly directional antennas, which would make deployment costly. As noted, one approach is to use redundant samples preceding transmitted symbols to ensure that any received samples affected by energy from the previous symbol can be discarded. This process is efficient only if the duration of the transmitted symbols is considerably longer than that of the expected multipath; otherwise, the redundancy would be constituting an unacceptably large relative overhead. In addition, the method used to modulate data onto these large symbols must be computationally simple. This is important because the number of bits per symbol will have to be very large to maintain a given data rate.

The data rate, in bits per second, can be expressed as $[(\text{bits/symbol}) \times (\text{symbol/s})]$. The symbol rate, (symbol/s), is the inverse of the symbol duration so that increasing the symbol duration requires modulating more bits per symbol to maintain the data rate (assuming a given channel bandwidth).

The preferred method of creating such symbols is the use of the IFFT, which effectively transforms a set of orthogonal narrowband transmissions into a single waveform. An additional advantage of the IFFT is that it is cyclical in the time domain so that when the redundant samples are copied from its tail, the transmitted symbol remains continuous in phase. OFDM provides for the subcarriers to be orthogonal and separable. When the subcarrier spacing is sufficiently small, the channel characteristics can be safely assumed to be constant across the subcarrier. This assumption drastically simplifies channel estimation because it can be performed independently for each subcarrier and, for each subcarrier, the channel can be represented by a single amplitude and phase.

Selection of FFT size

The FFT size is a critical parameter with implications in the time domain as well as the frequency domain. The designer must take into consideration an extraordinarily wide range of system factors, including the multipath propagation environment, the cost of precision electronics, and the nature of the network traffic. This job requires system-level thinking; it is not for narrow specialists.

The most fundamental frequency domain characteristic is the channel bandwidth. IEEE Std 802.16 is designed to accommodate a number of channel bandwidths, depending on the local regulatory environment and the operator requirements. For the purpose of this discussion, we will assume that the channel bandwidth is fixed.

In a given channel bandwidth, the subcarrier spacing is inversely proportional to the number of subcarriers and, therefore, to the FFT size. Meanwhile, the duration of the OFDM symbol is set to be the inverse of the subcarrier spacing. This setting is the necessary and sufficient condition to ensure that the subcarriers are orthogonal. As a result, the OFDM symbol duration is proportional to the FFT size.

The choice of FFT size is inextricably tied to assumptions about the physical environment in which the propagation takes place. This is because, to ensure that multipath propagation does not corrupt the received signal, a copy of the last T_g s of the symbol waveform with duration T_b is prefixed to the symbol before transmission (see Figure 11-1). This copy is termed the *cyclic prefix*. The receiver will sample only an interval T_b within this extended interval $T_b + T_g$. The prefix has no impact on the received symbol due to the cyclic nature of the FFT. Multipath components shorter than T_g s need not negatively affect the performance as long as the sampling interval is chosen correctly. How much smaller the multipath components need to be depends on the accuracy of sampling timing and the symbol windowing used because both negatively affect the protection against multipath. Multipath components in excess of the effective multipath protection duration, however, will significantly degrade the performance (see [B55]). It is, therefore, desirable to choose the cyclic prefix large enough to encompass the expected multipath of the application.




Figure 11-1: OFDM symbol structure

The addition of the cyclic prefix adds overhead due to the redundancy. It also increases the energy per symbol, resulting in an SNR drop of $10 \log_{10}(1 - T_g / (T_b + T_g))$ dB. With the duration of the cyclic prefix dictated by the multipath, choosing a shorter OFDM symbol duration hence increases the proportion of time and energy lost on the cyclic prefix.

The designer must also consider the network traffic requirements. To understand why, begin with the fact that the FFT size determines the number of available subcarriers. Each subcarrier is modulated to carry data. For this discussion, assume QAM modulation, with each subcarrier delivering one QAM symbol during the duration of the OFDM symbol. The total number of bits carried in one OFDM symbol by all the subcarriers, therefore, scales with the FFT size (as does the symbol duration). This is where the network factors enter the problem. As the data capacity per symbol gets larger, the granularity may grow too coarse to efficiently carry variable-length data packets, particularly when the traffic consists of many small data packets that do not fill the symbol. For instance, if the UL is transmitting a few small packets, as typically found in VoIP and most other IP traffic, without a sufficient packet rate to take advantage of packing, then large symbols may need to be transmitted without a full load of data. In this case, a shorter symbol would be more efficient.

Finally, a longer OFDM symbol duration translates into narrower subcarriers in the frequency domain. This closer spacing makes the receiver performance more susceptible to phase noise, which corrupts the orthogonality of the subcarriers. With current technologies, the phase noise requirements have a direct and substantial impact on the cost of the system.

The above considerations all came into play during the discussions on the FFT size N_{FFT} , an issue complicated substantially by the targeted support of a large range of bandwidths (up to 28 MHz). In the early stages of development, the IEEE 802.16 Working Group considered many different FFT sizes, particularly 64 and 256 for OFDM and both 2048 and 4096 for OFDMA. Although it was realized that 64-FFT was suitable only to short links due to its low multipath protection capabilities, the opportunity to reuse IEEE 802.11a implementations was a strong consideration for many participants. Eventually, the 64-FFT option was dropped as an OFDM alternative, as performance issues outweighed issues regarding the reuse of legacy components; and OFDMA was restricted to 2048. With the IEEE 802.16e amendment, additional sizes of 128, 512, and 1024 were added for OFDMA. To provision in a more optimum fashion for deployments with short links and deployments with relatively little multipath, the IEEE 802.16 standard allows for several different cyclic prefix durations.

The OFDM waveform

The OFDM waveform as a function of time can be described as follows:

$$s(t) = \text{Re} \left\{ e^{j2\pi f_c t} \sum_{\substack{k = -N_{\text{used}}/2 \\ k \neq 0}}^{N_{\text{used}}/2} c_k \cdot e^{j2\pi \cdot k \cdot \frac{n \cdot BW}{N_{\text{FFT}}} \cdot (t - T_g)} \right\} \quad 0 < t < T_s$$

where

- c_k is a data point out of the modulation constellation to be mapped onto the frequency offset index k
- f_c is the RF
- BW is the transmission bandwidth
- n is the oversampling factor
- N_{used} is the number of nonsuppressed subcarriers

In the early stages of the development of the OFDM and OFDMA PHYs, the working group attempted to maintain as much commonality between the two specifications as possible. This, along with the fact that IEEE Std 802.11a used 48 data subcarriers per OFDM symbol and the fact that 48 data subcarriers conveniently allowed mapping whole bytes to a single OFDM symbol for almost all modulations, led to a symbol structure containing a multiple of 48 data subcarriers. For the case of the 256-FFT, the working group settled on 192 data subcarriers. Eight additional “pilot subcarriers” are used mainly to track phase changes during a burst, making for a total of $N_{\text{used}} = 200$ subcarriers. The resulting frequency domain description is shown in Figure 11-2.




Figure 11-2: OFDM frequency description

At this point, it would have been possible to use the 200 subcarriers, along with a dc subcarrier in the center and guard subcarriers on either side (28 on one side and 27 on the other). However, the resulting spectral shape would end up unnecessarily conservative with regards to spectral masks established by relevant regulatory agencies; the result would be akin to a waste of spectrum. To take advantage of the opportunity to fully utilize the spectrum within the mask, the sampling factor n was introduced to create a sampling bandwidth somewhat larger than the actual bandwidth BW . This stretches the spectral shape of the signal to more fully fill the space with the spectral mask, shortening the symbol duration and hence leading to slightly higher throughput. The allowed values of n are as follows:

- 8/7 for BW multiples of 1.75 MHz
- 86/75 for BW multiples of 1.5 MHz
- 144/125 for BW multiples of 1.25 MHz
- 316/275 for BW multiples of 2.75 MHz
- 57/50 for BW multiples of 2 MHz
- And again 8/7 for any other bandwidth

These specific values ensure that there is an integer number of samples per frame for all likely bandwidths less than 28 MHz.

Subchannelization

The access method for the OFDM PHY is TDMA. This is, however, not an entirely complete description, as the PHY also provides an integrated optional OFDMA component. To avoid confusion between this component and the OFDMA PHY described in Chapter 12, the OFDMA component in the OFDM PHY is referred to as *subchannelization*.

In late 2002, the IEEE 802.16 Working Group was completing the IEEE 802.16a amendment, which added the new PHY specifications for frequencies below 11 GHz. The working group recognized the importance of specifying profiles as the basis of compliance testing for these alternatives, but the group was anxious to complete IEEE Std 802.16a. Therefore, it decided to develop an amendment, IEEE P802.16d, to add the missing profiles; the same project could be used to address any errors identified in

IEEE Std 802.16a. At about the same time, the working group, following formal study group activity, was initiating activities to expand IEEE Std 802.16 from a fixed-only to a fixed-and-mobile system, beginning with the opening of the IEEE P802.16e PAR in late 2002. Within the IEEE 802.16e effort, it was soon realized that the OFDM PHY as defined did not provision sufficient UL link budget to move from a fixed deployment with relatively large SS antenna gain to a mobile platform with typically very low SS antenna gain, while maintaining a reasonable cell size. Subchannelization was a known tool to extend the link budget. While it made sense for mobile terminals, the working group began to accept the idea that it would be applicable to fixed terminals also.

Another important factor in introducing subchannelization into the IEEE 802.16 OFDM PHY was the ETSI BRAN HiperMAN project. ETSI BRAN HiperMAN, insisting on the need to minimize alternatives in the standard, had at one point reached agreement on a standard that was fully compatible with WirelessMAN-OFDM. However, as IEEE Std 802.16a concluded, ETSI BRAN HiperMAN continue to progress with the introduction and development of subchannelization, even though ETSI BRAN HiperMAN was not chartered to consider mobile operation. The desire to maintain compatibility with ETSI BRAN HiperMAN was one reason that the IEEE 802.16 Working Group sought to introduce the feature. In 2003, the amendment project IEEE P802.16d was converted into a full revision project. This expanded the scope of the work and allowed for the introduction of features like subchannelization.

After the idea of adding subchannelization gained acceptance, the main contention point was how many subchannels to use. Some sought small subchannels to maximize the link-budget gain, while others sought larger subchannels due to concerns with the minimal achievable throughput per subchannel, losses due to the scrambling and encoding blocks getting very small, and the general increase in receiver complexity.

Eventually, the number of subchannels was chosen to be 16, each consisting of 12 data subcarriers. Subchannels may be combined in a predetermined fashion so that an SS can be allocated all of the data subcarriers or one-half, one-fourth, one-eighth, or one-sixteenth of them. Only eight pilot subcarriers

are available for all of the subchannels. Therefore, for allocations of one-sixteenth of the data subcarriers, phase estimation must rely solely on data-driven approaches. The subchannel structure is shown in Figure 11-3.




Figure 11-3: Subchannel subcarrier allocations

The OFDM PHY can be applied to make use of the increased UL link budget provisioned by subchannelization, by limiting the maximum number of subchannels that are assigned in the UL to a given SS. This increased link budget is available from subchannelization because an SS can distribute its available power to fewer subcarriers, achieving a power gain per subcarrier (and hence link budget) of 3 dB every time the number of excited data

subcarriers is halved. With a division into 16 subchannels, a total gain of 12 dB is hence possible (although implementation losses will somewhat reduce this gain). To exploit this opportunity, an SS with insufficient link budget to establish a link using full bandwidth can establish a link using less than the full bandwidth at the cost of peak throughput (but not at the cost of system capacity). To support this, special provisions allow efficient initial ranging and BW requesting for these cases. In order to make full use of this feature, however, sufficient link budget must be achieved on the DL, generally through the use of a higher gain BS amplifier, to enable establishment of a connection. Especially in license-exempt bands, where allowed EIRP may be fairly restrictive, this may not be possible.

Aside from link range extension, subchannelization may additionally be used to exploit the lower overhead of the subchannelized preamble and to increase the modulation/coding efficiency. This may be easily understood from a simple example. A full bandwidth transmission of data filling x OFDM symbols requires $x + 1$ OFDM symbols (the extra OFDM symbol resulting from the preamble). The overhead ratio is hence $1/(x + 1)$. Transmitting that same data over eight subchannels (one-half the bandwidth) using the same data rate results in an overhead ratio of $1/(2x + 1)$ within those subchannels because the data now occupy eight subchannels of twice as many OFDM symbols, but the preamble only occupies eight subchannels of a single OFDM symbol. Because the remaining eight subchannels remain free for another SS, no loss of system capacity occurs (in fact, the reduced overhead slightly increases the system capacity). Because of the 3 dB gain achieved by using only half the subchannels, the SS may additionally be able to increase the data rate by increasing the modulation/coding efficiency, requiring less OFDM symbols (e.g., $1.6x$) to transmit the data. The total system resources used is then $(1 + 1.6x)/2 = 0.5 + 0.8x$, compared to the full-bandwidth $1 + x$.

The data subcarriers assigned to a single subchannel are distributed over the entire OFDM symbol, in four blocks of three subcarriers each. This spreading was introduced as a frequency diversity technique to reduce the susceptibility to partial band fading, whereas the grouping in blocks of three subcarriers results in slightly lower phase noise and frequency offset sensitivity. The allocation of blocks is such that combining subchannels still results in an evenly spread allocation of subcarriers. During a single OFDM symbol

interval, it is possible to assign different numbers of subchannels to individual SSs as long as the frequency offset indices of the subchannels do not overlap.

One of the four major changes introduced in WirelessMAN-OFDM by the IEEE 802.16e amendment is the capability for provisioning subchannelization in the DL (the other three changes are the additions of private MAPs, private initial ranging opportunities, and open-loop power control). This DL subchannelization is provided as a separate zone, similar to the zone concept of the OFDMA PHY (see Chapter 12), with its own subchanneled preamble, FCH, and MAPs so that it is completely independent of the remainder of the frame. The DL subchannelization is restricted to the use of quadruple subchannel allocations (see Figure 11-3). The DL MAP in this construct provides allocations only for future frames, not for the current one, as it is assumed that mobile devices do not have the computational power necessary to decode this MAP quickly enough to efficiently avoid receiving data not intended for the station itself; this would unnecessarily drain the battery.

The addition of DL subchannelization is motivated by the desire for a larger coverage area for mobile devices, which have comparatively low antenna gain.

Preambles

The OFDM PHY specifies two 200-element sequences from which all preambles are derived. One sequence is used for all DL preambles and full-bandwidth UL preambles; the other is for UL allocations spanning less than the full channel. These two sequences are termed *mother sequences*. Computing an actual preamble from a mother sequence involves operations no more complex than multiplication with a constant, conjugation, and puncturing. This makes it practical to store only the two mother sequences.

All preambles are one OFDM symbol long, with exception of the DL preamble, initial ranging preambles, and mesh preamble, which consist of two OFDM symbols.

The first symbol of the two-symbol preambles, shown in Figure 11-4, consists of a cyclic prefix (CP) followed by four repetitions of a frequency domain derivative of the first mother code. Each repetition is said to be

length 64, which means that it contains 64 samples and has a duration four times shorter than that of the 256-FFT OFDM symbol. This symbol primarily allows the receiver to perform large-gain adjustments of its amplifier, as well as coarse frequency and time correction. This is necessary on the DL to allow new SSs to properly track and adjust to the BS signal. On the UL, it is necessary for initial ranging, as the new SS's transmit gain and frequency/timing offsets have not yet been adjusted to within an acceptable range for the BS receiver. For other transmissions in the UL, the BS directs each SS to adjust its transmit power and frequency/timing offsets to within a desired range so that the preamble need not facilitate this functionality for these transmissions.




Figure 11-4: DL and network entry preamble structure

The second symbol of the long preambles as well as all of the one-symbol (short) preambles consists of a cyclic prefix followed by two repetitions of a length 128 frequency domain derivative of the mother codes, which is transmitted on the even subcarriers. Special cases exist for the DL STC-encoded region and for DL AAS transmissions. For the former, alternate subcarriers are transmitted from the two different antennas. For the latter, two identical "regular" OFDM symbols (each with cyclic prefix) are transmitted, where each beam (not each antenna) transmits on every fourth carrier. If a BS has more than four simultaneously active beams, the fifth beam transmits the same symbol as the first antenna, etc. This is possible because of the spatial separation.

For UL allocations smaller than the full bandwidth, subcarriers not part of the allocated subchannels are not excited when transmitting the preamble. If midambles are transmitted, they are identical to the short preamble or the second symbol of the long preamble that was used for the burst. Midambles are generally not necessary in fixed deployment, but the OFDM PHY

provisions them to enable extension to mobile applications as defined in IEEE Std 802.16e. The purpose of the short preamble and the second symbol of the long preamble is to allow fine frequency/time estimation and channel estimation.

In the UL, SSs can be ordered through the UL MAP to cyclicly rotate the preamble by a given factor between 0 and 255. The idea behind this is to allow better simultaneous detection of preambles by AAS-enabled BSs. This is achieved by the concept that, if preambles are sufficiently rotated, correlation of the received signal with the nonrotated preamble and with the rotated preamble will result in two better estimates due to low cross-correlation of the preambles. Because this shift must be substantially larger than the main multipath components of any of the channels of involved SSs, the number of shift possibilities is limited. For the UL, the BS has a receiving beam in the direction of the individual SSs, which suppresses signals from other simultaneously transmitting SSs with substantially different angles of arrival (AoAs). However, this feature is only marginally useful for SSs that have relatively similar AoAs. Despite the fact that the cyclic shift method is a mandatory specification, it is of little use for non-AAS devices.

FRAME STRUCTURE

The OFDM PHY supports two noncompatible frame structures: a mandatory one for PMP architectures and an optional one for mesh-based architectures. Either frame structure allows for a number of frame durations between 2.5 ms and 20 ms.

Point-to-multipoint (PMP)

For PMP architectures, the duplexing method may be either TDD or FDD (with H-FDD SSs supported), except in license-exempt bands where only TDD is provisioned to ensure better coexistence with other IEEE 802 standards.

The TDD structure for PMP architectures is shown in Figure 11-5. The FDD structure is similar, except that TTG and RTG are omitted and the DL and UL subframes exist in parallel on different frequencies.




Figure 11-5: Example OFDM structure with TDD

The DL PHY PDU is initiated by the DL frame preamble, as previously described, followed by the FCH, which only contains the DLFP. The DLFP contains the lower 4 bits of the BS ID and the frame number (the full fields are present in the following DL MAP); this helps SSs with synchronization and identification of the right burst. The DLFP also contains a list of up to four DL bursts, indicating for each burst the DIUC (indicating, among other parameters, the modulation and coding methods), the existence of a preamble, and the length of each burst in OFDM symbols. For the first burst (Burst #0), the DIUC field is replaced by the Rate ID, which indicates only the modulation and coding method. Lastly, the DLFP contains an HCS to identify errors in the FCH. It may also contain the start time of an STC-encoded region, if present, which lasts till the end of the DL frame. The FCH uses the most robust modulation method and coding (BPSK-1/2). The FCH hence allows the SS to individually demodulate each DL burst correctly.




Figure 11-6: DL burst and MPDU mapping

The first DL burst subsequently contains the DL MAP, the UL MAP, the DCD, and the UCD. Transmission of each of the messages is optional (although insertion of DL MAP and DCD is mandated periodically to ensure that synchronization is maintained); but, when any of these four messages is present, the order is mandatory. The DL MAP may also contain markers to indicate that, from a certain starting point until the end of the DL subframes, STC, AAS, or DL subchannelization is enabled. These are the so-called *STC*, *AAS*, and *DL subchannelization zones*, respectively. If these zones are used to extend the cell range for devices, then all broadcast messages must be transmitted in these zones as well. Specifically, in the case of AAS, which has no broadcast PHY method, the FCH and unicast versions of the broadcast messages must be repeated on as many beams as necessary to reach all SSs. Similarly, in the UL, separate allocations must be inserted in these zones for the contention-based methods (ranging and BW requests).

The remainder of the first DL burst, as well as any subsequent DL burst within the frame, carries other MPDUs as indicated by the DL MAP.

The UL may contain contention slots for initial ranging and full and focused BW requests (explained later in this chapter). UL bursts may be received in parallel on nonoverlapping sets of subchannels (or on overlapping sets when exploiting the space division component through an antenna array). The main

difference between the allocation mapping on the DL and UL is that on the DL, the duration of a burst is implicit from the start time of the next burst, whereas on the UL, the duration is explicitly stated. This was introduced to avoid the need to derive the duration from multiple parallel subchannelized subsequent allocations (i.e., the duration of an allocation could be derived from the earliest subsequent start time of any other allocation in any of the subchannels assigned to the allocation).

Mesh

For the mesh architecture, only TDD is specified. Each frame consists of two configurable fixed-duration subframes. The first period is the control subframe, which is used for network and schedule control, whereas the second is used for data transfer.

As illustrated in Figure 11-7, network and schedule control are fully separated, in that one out every few control subframes is dedicated to network control, whereas the remaining control subframes are dedicated to scheduling. Each control subframe consists of a number of transmission slots.

The first slot of a network control subframe is dedicated to contention-based network entry. The message used for network entry (MSH-NENT) is substantially shorter than the duration of the slot. This provides robustness with respect to timing errors due to unknown propagation durations, similar to the technique discussed later in this chapter for initial ranging (and is only used in PMP architectures). The remainder of the slot in the network control subframe is used for contentionless distribution of network configuration parameters (including neighbor lists) by the devices already part of the mesh network.

Three different messages are used in the scheduling control subframe, which manage the scheduling of bursts in the data subframe. The MSH-CSCF message is used to distribute the connectivity tree for centralized scheduling, whereas the MSH-CSCH contains the actual centralized transmission schedule. MSH-CSCF and MSH-CSCH messages are not bound by slot boundaries. MSH-DSCH is used to establish distributed schedules. MSH-DSCH may also occur during the data subframe to establish contention-based schedules.




Figure 11-7: Mesh frame structure

Each control message is terminated by a guard period. This is because, although all devices are synchronized, propagation durations will still vary between devices. The additional symbol avoids the end of a burst received over a long link suffering interference by the start of a subsequent burst received over a short link. Relying only on the cyclic prefix of the OFDM symbol for this would not have been sufficient.

Each of the (broadcast) control message formats, not only the network entry message, starts with a long preamble. This is because a device may,

contention-free, conclude whether it is its time to transmit, but it cannot always determine who has the right to transmit otherwise. This is handled differently in the data subframe, where the transmission schedule is known. Although they use the long preamble by default, links can establish use of the short preamble in the data subframe.

The mesh architecture cannot make use of the subchannelization functionality. Although there is principally no obstruction to its use, the complexity of the scheduler would be prohibitive with current technology. The architecture does allow the use of patch antennas or antenna arrays, either with up to eight distinguishable directions. This allows for a substantially higher spacial reuse and hence substantial system capacity increases during the data subframe, at the cost of higher scheduling complexity. Extending link range through AAS as previously defined is, however, not possible due to the reliance on broadcasting for network control.

BW requesting is performed by use of the scheduling messages. The contention-based methods as described earlier are hence not used when using the mesh architecture.

CHANNEL ENCODING

The OFDM PHY channel encoding, which precedes the IFFT, consists of four steps; randomization, FEC, interleaving, and modulation.

Randomization

A specific sequence of data modulated on an OFDM symbol results in a given peak to average power ratio (PAPR) for that symbol. With a small probability of occurrence, this PAPR can be quite large (e.g., more than 7 dB). It is generally inefficient to back the transmitter power amplifier off far enough to avoid unrecoverable nonlinear distortion at the worst possible PAPR. Practical designs instead back off the amplifier only far enough to keep the probability of unrecoverable distortion acceptably low. However, retransmitting a data sequence with a high PAPR would result in a repeated receiver error. To avoid such persistent errors, the data are passed through a randomizer at the transmitter.

Randomization is performed by passing the block of data to be transmitted through a pseudo-random binary sequence (PRBS) with polynomial $1 + x^{14} + x^{15}$. For every data burst, the initial state of the PRBS memory is reset with a combination of the BS ID, the IUC for the allocation, and the frame number, except at the start of the frame, where it is reset with a fixed value, and on the first DL burst (i.e., the burst following the FCH), where it is not reset at all. Due to the fact that the FCH is fixed in duration, the state of the PRBS will always have the same value at the start of the first DL burst. Hence not resetting the PRBS at this point is equivalent to resetting it with a fixed value.

Forward error correction (FEC)

The OFDM PHY specified three methods of channel coding: Reed-Solomon concatenated with convolutional coding (RS-CC), block turbo coding (BTC), and convolutional turbo coding (CTC). RS-CC is mandatory, whereas BTC and CTC are optional. Although BTC and CTC generally provide on the order of 2 dB to 3 dB better coding gain, their substantial complexity made them less attractive as a mandatory requirement. The performance of BTC and CTC relative to each other varies slightly as a function of the coding rate and the size of the data to be encoded.

Reed-Solomon concatenated with convolutional coding (RS-CC)

The RS-CC encoding consists of a systematic RS(255,239,8) code over $GF(2^8)$, which can be shortened and punctured to appropriate block sizes followed by a native rate 1/2 constraint-length 7 convolutional encoder (identical to the encoder defined in IEEE Std 802.11a), which can be punctured as well.

The randomized burst of data to be encoded is first appended by a byte of zeroes, as shown in Figure 11–8, in order to facilitate zero-tail termination of the CC encoder. Given the constraint length of 7, the usage of 6 tail bits would suffice (the last 2 bits will always remain zero after encoding). However, since data are generally passed to the PHY in whole bytes, the byte appendage is simpler. During development of the IEEE 802.16 standard, the use of tail-biting, which does not require the tail-byte overhead, in combination with per-OFDM symbol encoding, was favored. However, the disadvantage of having

to process a substantial portion of the data twice was deemed to outweigh the incurred zero-tailing overhead. A separate RS block is computed for each OFDM symbol. The parity bits for each block are sent to the CC encoder before the block itself, ensuring that the added tail byte is passed last to the CC encoder. The CC encoder is employed over the entire burst. The RS encoder is bypassed entirely when less than the entire channel is allocated (i.e., when eight or fewer subchannels are allocated). This avoids performance deterioration due to the weakness of RS codes for small blocks.




Figure 11–8: RS-CC encoding process

Block turbo codes (BTCs)

Unlike RS-CC, where the data are treated as a long string, BTC encodes the data in block form, where the block is filled row by row. Subsequently, a code polynomial is used to encode each row, with check bits added to the row. Subsequently, another code polynomial is used to encode each column, including the columns consisting of the row check bits. The polynomials are selected from a set of three extended Hamming codes and three parity check codes. The block (see Figure 11–9) may be shortened by not filling the first I_x rows, I_y columns, and B bits and zero-filling the Q bits until the next byte boundary. An encoding is hence fully described by its two constituent codes and the four parameters I_x , I_y , B , and Q . To specify blocks that fit into each of the five possible allocation sizes per OFDM symbol (see Figure 11–3), each of the four possible modulations and each of the two code rates per modulation—a total of thirty different encodings—are provided. The performance of BTC for an allocation of only a few subchannels was never thoroughly studied during the development of the subchannelization option. The performance may turn out to be problematic due to the small block sizes.




Figure 11-9: BTC encoding block

Convolutional turbo codes (CTCs)

The CTC encoder is most easily described from its depiction in Figure 11-10.




Figure 11-10: CTC encoder

Bits are alternately fed into A and B (MSB first), with the switch in position 1 as shown. The encoding process must be performed twice: one with the

memory elements initialized to 0b000 with the switch in position 1 and one with the memory elements initialized with a value computed by passing the final value of the first run through a lookup table and the switch in position 2.

The final encoded stream is achieved by the sequence of alternated bits from A and B, followed by all punctured parity bits from the first encoding (switch position 1), followed by all punctured parity bits from the second encoding (switch position 2).

Interleaving

The interleaver is defined by a two-step permutation. The first ensures that adjacent coded bits are mapped onto nonadjacent subcarriers. The second permutation ensures that adjacent coded bits are mapped alternately onto less or more significant bits of the constellation, thus avoiding long runs of low-reliability bits. The interleaver is virtually identical to that used in IEEE Std 802.11a and IEEE Std 802.11gTM, except that it uses 12 as computational base, rather than 16. The reason for this is that each subchannel has 12 data subcarriers. A base-12 permutation hence ensures that adjacent bits are mapped not only to different subcarriers but to different subchannels as well (if multiple subchannels are allocated).

Block sizes for the interleaver are defined so that the number of bits in a block fits into all allocated subchannels within an OFDM symbol. There is hence exactly one interleaving block per OFDM symbol for each transmitter.

Modulation

The OFDM PHY mandates BPSK as well as Gray-mapped 4-QAM (QPSK), 16-QAM, and 64-QAM constellations. The Gray-mapped 64-QAM constellation is optional for license-exempt bands, mostly to allow the use of IEEE 802.11 RF components that would typically not meet the 64-QAM performance requirements of IEEE Std 802.16.

Pilot tones are modulated with a BPSK signal. The values to be used are derived from passing fixed initialization sequences (one each for UL and DL) through a PRBS with polynomial $x^{11} + x^9 + 1$ clocked with the OFDM symbol rate. The values of the individual pilots within a single OFDM symbol

are then defined as being either equal or the negative of the BPSK-modulated PRBS output.

CONTROL MECHANISMS

Of all control mechanisms that are available to the BS to control SS behavior, three have special provisions in the PHY: ranging, BW request, and power control.

Ranging

Ranging consists of two types: *initial* and *maintenance*. The first serves to initiate registration (or re-registration) of an SS with a BS. The second serves to periodically readjust PHY parameters of the SS and to verify that the SS is still on line.

Maintenance ranging is predominantly a MAC process, for which the PHY makes no special provisions in terms of scheduling or waveform creation. From the PHY's perspective, maintenance ranging is treated like any other data exchange.

Initial ranging is different in this respect in that it is, by necessity, a contention-based protocol with a nonzero probability of collision. The time period scheduled for initial ranging must be at least the total duration of the round-trip propagation delay and the transmission time of the initial ranging message, as a new SS is not yet able to correct its clock for propagation delays. The round-trip propagation delay is a function of the maximum cell size. An initial ranging attempt uses the long preamble. The initial ranging data fit in one OFDM data symbol (using the most robust modulation/coding) so that the total duration of an initial ranging allocation must be at least $3 + \lceil (n \cdot BW) / (256(1 + T_g/T_b)) \cdot (2r)/c \rceil$ OFDM symbols, where r is the cell radius in meters and c the speed of light. For typical deployments, this turns out to be a four-OFDM-symbol allocation. In fixed systems, contrary to mobile applications, registration is a relatively rare occurrence. It is, therefore, not necessary to facilitate initial ranging slots in every frame, and, as a result, the incurred overhead is negligible. The different initial ranging formats are shown in Figure 11–11.




Figure 11–11: Initial ranging formats

As mentioned before, the PHY provides special provisions to allow SSs with insufficient link budget to use less than the full bandwidth. As a consequence of this design, a method is specified for these stations to start initial ranging with a slightly different method than the one described above. When an SS deduces, from estimating the required transmit power (for which the BS provides the necessary data in the UCD message), that it will not be able to close the link or when it has failed initial ranging attempts multiple times, it may replace the RNG-REQ message with the subchannelization preamble on one random subchannel so that the total initial ranging burst consists of the long preamble followed by the subchannelized preamble. The long preamble has sufficient inherent gain to be detected, whereas only an energy detect is needed to establish on which subchannel the subchannelization preamble was sent. Because the same total power is used, the spectral density of the single subchannel preamble will be roughly 12 dB higher, further improving the accuracy of the energy detect. Upon detection, the BS can issue a subchannelized UL allocation referencing the SS by the ranging slot and subchannel. For efficiency, SSs using the full bandwidth as well as those requiring a subchannelized initial ranging are using the same ranging opportunities. This avoids duplication of allocations.

An exception to this exists when the BS operates using AAS. Under the assumption that the cell range for AAS devices may be much larger than that of non-AAS devices, it cannot be assumed that AAS-enabled SSs can receive the broadcast DL MAP. They may, therefore, have no knowledge of the UL schedule, including initial ranging slots. To get around this problem, a BS must schedule an AAS initial ranging slot of eight OFDM symbols, the first symbol of which the BS uses to transmit the AAS network entry preamble,

which has sufficient gain to be detected by AAS-enabled SSs. Following a TTG, an AAS-enabled SS may then transmit the long preamble and RNG-REQ message. The sum of SSRTG and round-trip delay may hence not exceed four OFDM symbols.

One of the few changes provided by the IEEE 802.16e amendment for the OFDM PHY is, as mentioned previously, the capability of the BS to allocate an SS-specific (and hence noncollision-based) initial ranging opportunity. This feature is useful when the BS receives notice (for example, from a network controller) that a MS will be attempting a handover to the BS in question. This shortens the handover time and avoids the possibility that many collision-based initial ranging opportunities need to be allocated because of handover frequency.

BW requests

There are multiple ways in which bandwidth can be requested: through polling, through piggybacking, and through two contention-based methods. From the PHY perspective, only the latter two are of interest. These two methods, of which only the first is mandatory, are *full contention* and *focused contention*.

Full contention may be used both with full bandwidth allocations and with subchannelized allocations. The only difference is that, using full bandwidth, the request is limited to two OFDM symbols to be filled with the short preamble and one data symbol containing the BW request, whereas using subchannelization, the width (in subchannels) and length (in OFDM symbols) is announced in the UCD. The BS may provide multiple request opportunities within a single allocation. The BS can identify the SS by the Basic CID in the BW request.

Focused contention is an optional feature. To request bandwidth using focused contention, an SS selects randomly a contention channel index out of the 48 available. This maps to four unique data subcarriers. These are arranged to form three sets of contention channels within each subchannel. On these four subcarriers, the SS transmits one of eight BPSK contention codes. On the following OFDM symbol, the SS again transmits the same contention code on the same subcarriers, with the difference that, for all subcarriers with

contention element -1, the phase is inverted. The BS is now able to identify the SS by the contention channel index and contention code and can issue an UL allocation on that basis. The advantage of this scheme is that many SSs can simultaneously indicate a need for bandwidth with a low probability of collision (same contention channel) and an even lower probability of undetectable collisions (same contention channel and same contention code). A minor drawback of this scheme is that it introduces a single frame of delay, as the focused contention indication does not provide the BS with any knowledge about the size of the bandwidth needed. When a BS supports subchannelization, it may indicate through the UCD that a certain amount of the contention channel indices are reserved to indicate the SS needs a subchannelized allocation. In the case that it receives one of these codes, the BS does not know the identity of the requesting SS; therefore, it has no choice but to allocate the lowest number of subchannels required by any of its associated SSs.

Power control

Power control is needed and specified only in the UL, where it serves to ensure that the received signal power density at the BS falls within a narrow range. The SS transmit power level is adjusted under control of the BS. To allow this, each SS reports, during initialization, its current transmit power level and the maximum transmit power level for each of the modulations as part of its basic capabilities. This allows the BS to compute the feasibility of an SS changing its power level for full bandwidth allocations with the current modulation. It also allows the BS to compute the effects of a change in modulation and subchannelization. This can be used to improve bandwidth efficiency.

The BS can use both the maintenance ranging and fast power control MAC messages to force an SS to adjust its power levels. The SS must be capable of changing power at a rate of at least 30 dB/s.

An SS must maintain the same power spectral density when changing between transmissions with different numbers of subchannels. In other words, if the number of subchannels is double that of the previous allocation, the total transmit power, when feasible, must be doubled. Reciprocally, if the number of subchannels is halved compared to the previous allocation, the total transmit power, when feasible, must be halved.

Chapter 12 PHY: WirelessMAN-OFDMA

Multicarrier PHY for frequencies below 11 GHz

WirelessMAN-OFDMA is one of the three PHY specifications defined in IEEE Std 802.16 for applications below 11 GHz. This PHY has attracted much attraction in the past few years, particularly because of the expansion of the scope of the IEEE 802.16 standard, through the IEEE 802.16e amendment, to include mobile stations (MSs). IEEE Std 802.16e includes the expansion of all three of the lower frequency PHY specifications into the mobile arena (WirelessMAN-SC is excluded due the IEEE 802.16e upper limit of 6 GHz). However, the primary interest has centered around WirelessMAN-OFDMA, which is abbreviated as the "OFDMA PHY."

WirelessMAN-OFDMA uses orthogonal frequency-division multiple access (OFMDA), which is an extension of orthogonal frequency-division multiplexing (OFDM). The multiple access feature makes OFDMA considerably more complex. In OFDM, all of the transmitter's subcarriers are, at any given time, addressed to a single receiver; multiple access is provided solely by TDMA time slotting. OFDMA divides the subcarrier set into subsets, each of which can address a different receiver at any given time. This provides for a number of performance advantages, as discussed below, at the cost of considerable complexity. The complexity comes not only in the air interface, as defined in the IEEE 802.16 standard, but also in the control functionality outside the standard. For example, the design and optimization of an efficient scheduler will prove an interesting engineering challenge.

The description of WirelessMAN-OFDMA here is less comprehensive than those of the other PHYs. This is due to the large number of features and options present in the specification, as well as by the substantial changes and additions that have recently been added through IEEE Std 802.16e (which, as published, also includes an approved corrigendum to the base standard). This book is not intended to thoroughly cover IEEE Std 802.16e, but, on the other

hand, neither do we wish to spend time explaining features that have changed significantly by virtue of that amendment. Therefore, while this chapter excludes a substantial number of features, mainly optional and mobility features added in IEEE Std 802.16e, care has been taken to ensure that the features described here are consistent with the changes in IEEE Std 802.16e.

INTRODUCTION

Selection of OFDMA waveform

As compared to the OFDM case discussed in the previous chapter, OFDMA involves different considerations regarding the complexity and implementation cost tradeoffs. Although WirelessMAN-OFDM has a limited capability for OFDMA through its subchannelization feature, its basic premise is TDMA with fairly large intercarrier spacing, which allows for an implementation hardly more challenging than the well-known Wi-Fi IEEE 802.11a or IEEE 802.11g OFDM products that have been readily available in the market since 2001. Those IEEE 802.11 amendments are based on a 64-FFT. Recall that WirelessMAN-OFDM uses a 256-FFT. WirelessMAN-OFDMA, as defined in IEEE Std 802.16-2004 [B20], uses a 2048-FFT. Therefore, for a given channel bandwidth, the OFDMA PHY presumes smaller intercarrier spacing and places more stringent demands on the hardware.

The issue of intercarrier spacing is made more complex by the decision, embedded in IEEE Std 802.16e, to move toward a “scalable” OFDMA providing for multiple FFT sizes: 2048, 1024, 512, and 128 (leaving out 256 presumably to maintain distinctiveness from WirelessMAN-OFDM). The idea of scalability is to match the FFT size to the channel bandwidth (i.e., larger FFT size with larger bandwidth), optimizing the subcarrier spacing. This idea of scalability was discussed earlier in the IEEE 802.16 Working Group, during the early Task Group 3 development of IEEE Std 802.16a-2003, but was rejected in order to simplify the interoperability problem. The IEEE 802.16 standard is rather ambiguous about channel bandwidth, as it is about carrier frequency, because of the lack of specific, harmonized worldwide spectrum in which to deploy.

In the remainder of this chapter, the 2048-FFT will be assumed, unless stated otherwise.

The OFDMA PHY using 2048-FFT is slightly more efficient than the OFDM PHY under the same conditions because the larger FFT size allows for a relatively smaller cyclic prefix (T_g/T_s).

The number of subchannels within the OFDMA PHY depends both on the FFT size and the time-frequency mapping (discussed below). As shown in Table 12–1, the number of data carriers per subchannel (per OFDM symbol) varies with the permutation method (discussed later in this chapter) and is 48 for full usage of subchannels (FUSC), optional full usage of subchannels (O-FUSC), and adaptive modulation and coding (AMC) and on average 24 and 16 for partial usage of subchannels (PUSC) and optional partial usage of subchannels (O-PUSC).

Table 12–1: Subchannel allocations

Method / FFT size	2048	1024	512	128
DL PUSC	60	30	15	3
UL PUSC	70	34	17	4
UL O-PUSC	96	48	24	6
DL FUSC	32	16	8	2
DL O-FUSC	32	16	8	2
AMC	32	16	8	2

As can be seen from Table 12–1, the power concentration that can be achieved, which is easily computed as $10 \cdot \log_{10}(\text{subchannels})$, varies widely with the time-frequency mapping and FFT size selected.

Time-frequency mapping

In the OFDMA PHY, the mapping of data to physical subcarriers occurs in two steps. In the first step, dictated by the scheduler, data are mapped to one or more data slots (in the time domain) on one or more logical subchannels. In the second step, for each data slot, each logical subchannel is then mapped to a number of physical subcarriers (in the frequency domain), with a mapping that may vary from one OFDM symbol to the next.

The first step, the logical mapping, makes use of certain basic terms in its description:

- **Slot:** The smallest unit of allocation in the time-frequency domain (except for mini-subchannels, which split a UL subchannel allocation further into two, three, or six pieces in the frequency domain). A slot always consists of a single subchannel, but, depending on the physical mapping, consists of one to three OFDM symbols.
- **Data region:** A contiguous allocation of slots in the time-frequency domain.
- **Subchannel group:** A single set of contiguous subchannels. The allocation of subchannels to subchannel groups is fixed.
- **Segment:** One or more subchannel groups that are controlled by a single instance of the BS MAC. As an example, a BS might segment the available subchannels among different sectors. There can be up to three segments where segment 0 must always contain subchannel group 0; segment 1, when present, must always contain subchannel group 2; and segment 2, when present, must always contain subchannel group 4.

Figure 12-1 displays these concepts in an example for 1024-FFT DL PUSC with three segments.




Figure 12-1: Schematic indication of logical mapping elements

The second step, the mapping of logical subchannels to physical subcarriers, is termed *permutation*. The OFDMA PHY specifies seven permutation mechanisms: FUSC, PUSC, O-FUSC, O-PUSC, AMC, TUSC1, and TUSC2. A set of OFDM symbols over which the same permutation method is used (using more than one method in an OFDM symbol is not possible) is termed a *permutation zone*. A single frame may contain one or more permutation zones. These permutation alternatives are described below.

- **FUSC (DL only):** FUSC consists of a single segment containing all subchannel groups. Each subchannel is mapped onto physical subcarriers distributed throughout the entire physical channel as a function of IDCell (a number specific to the sector or cell). This mapping changes with each OFDM symbol. An example of this mapping is shown in the next section. Besides IDCell, which is used for the first DL zone in a frame, the BS may alter the permutations through the use of the PermutationBase parameter. A data slot consists of one subchannel over one OFDM symbol.

The concept behind this method is that of interference mitigation through classical frequency hopping. Under light load, this allows the FEC to correct the few subcarriers on which a collision has occurred. As with classical frequency hopping, this scheme starts to lose its effectiveness if roughly one-third or more of the subchannels become occupied. The efficiency is hence roughly equal to that of system with frequency reuse of 3 (although some claim that it is comparable to a frequency reuse of 1), but the allocation of the instantaneous capacity (i.e., subchannels) to the individual sectors is more flexible. The disadvantage is that the BS needs to obtain a reasonable understanding (through network intelligence or channel measurements) of instantaneous load on other BSs, as throughput degradations are not a measure of only system load, but also of many other factors.

- **PUSC:** On the DL, each physical channel is split into clusters of fourteen subcarriers, which are then mapped to six major groups as a function of the IDCell. Subsequently, up to three segments are created out of these major groups. Within each group, pilots are allocated to each cluster in fixed locations that differ for odd and even symbols. The mapping of the remaining physical subcarriers within each major group to subchannels is similar to that of the FUSC case. A DL slot is defined as one subchannel over two OFDM symbols. On the UL, the subcarriers are split into groups of four consecutive physical subcarriers over a period of three OFDM symbols. Such a group is termed a *tile*. Six of those tiles are allocated to one subchannel, after which a UL slot is defined as one subchannel over that period of three OFDM symbols. The corners of each time-frequency tile are fixed for use as pilots. Except for subchannels allocated to UIUC 12 (CDMA BW request/CDMA ranging) and UIUC 13 (PAPR

reduction allocation/safety zone), the mapping between subchannels and slots on the UL is rotated by a fixed number of slots every slot duration within each segment. A UL mini-subchannel is mapped to either one, two, or three tiles for the duration of the slot.

PUSC is in effect a compromise between the above, completely flexible subchannel allocation and the traditional frequency reuse schemes. It has as disadvantages both the load-balancing intelligence requirement and a somewhat large granularity in capacity allocation. This flexible method is hence valuable mostly when frequent, large shifts in capacity demand from one sector to the next are expected (which for WirelessMAN systems may not be typical) or when the deployment necessitates permanent unequal capacity per segment. PUSC is also claimed by some to be equivalent to a frequency reuse of 1, but segmenting the channel in three is similar in deployment to having a traditional reuse of 3 with one-third of the channel size. PUSC is, however, substantially advantageous over such a scheme due to the lack of need for guard bands between the segments.

- **O(optional)-FUSC (DL only):** O-FUSC differs from FUSC solely in the manner by which pilots are allocated. Whereas FUSC's pilots are distributed in a pseudo-random way throughout the frame (after which the data subcarriers are pseudo-randomly allocated to subchannels), O-FUSC spaces the pilots always eight data subcarriers apart, rotating the locations three subcarriers for each OFDM symbol. After this, the data subcarriers are pseudo-randomly allocated to subchannels with the same algorithm used by FUSC. In synchronized networks, this setup has the effect of completely colliding the pilots when the same logical subchannel is used in nearby sectors.
- **O-PUSC (UL only):** O-PUSC differs from PUSC solely in the size of the tile and the allocation of pilots within it. PUSC in the UL has tiles sized four subcarriers by three OFDM symbols, where the four tile corners are used as pilots. O-PUSC instead uses tiles sized three subcarriers by three OFDM symbols, where only the center is allocated as a pilot.
- **AMC (AAS only):** The abbreviation AMC is not defined in the IEEE 802.16 standard, but it appears to have been derived from *adaptive modulation and coding*. It is also called *adjacent subcarrier permutation*. Using AMC, the entire channel is split in nonoverlapping

groups of nine contiguous physical subcarriers. Subchannels are then mapped to a single such group over six contiguous OFDM symbols or to two such contiguous groups over three contiguous OFDM symbols. The middle subcarrier of each group is used as a pilot in each of the symbols. The allocation of physical subcarriers to these groups is the same on each OFDM symbol. Because AMC is used only with AAS, which inherently provides interference mitigation due to directionality, having such larger groups of carriers susceptible to group collision should not cause any degradation as compared to the use of smaller groups (where group collision would be substantially less recoverable by the FEC).

AMC allows for a somewhat simpler transceiver design than PUSC or FUSC. It is tailored specifically to AAS, where one can easily calculate a single weight per group, rather than having to compute individual weights for each carrier.

- **TUSC1 & TUSC2 (DL AAS only):** TUSC1 and TUSC2 (i.e., variations of tile usage of subchannels) are both optional and are similar to DL PUSC and O-PUSC, respectively. The sole difference is that pseudo-random allocation of subcarriers to subchannels follows a different equation.

The above permutation methods can in principle be combined at random into a single frame by indicating switches between permutation methods in the DL MAP (which, together with the FCH preceding, it is always transmitted with PUSC permutation).

Permutation examples

Because the above permutation mappings may be hard to visualize, a few example allocations are depicted. The allocation is derived for 128-FFT.

FUSC

The example given below assumes $IDCell = 0$, $PermutationBase_0 = [1\ 0]$, and $SymbolNumber = 0$.

1. Map physical carriers to logical data carriers by removing from the physical list all DC carriers, guard carriers, and pilots. Note that the pilots are specified relative to the first nonguard carrier. In Figure 12-2, the mapping of the first 40 physical carriers is shown.

2. Partition logical data carriers into subchannels using the $subcarrier(k,s)$ formula. In Figure 12-2, the mapping is shown for the second subchannel ($s = 1$)
3. Map the logical data carriers k of the subchannels to physical carriers by combining step 1 and step 2. In Figure 12-2, the mapping of the logical indices k of subchannel 1 are shown for the first 40 physical carriers. It shows, for example, that physical subcarrier 12 is the 35th logical subcarrier of subchannel 1 because physical subcarrier 12 is logical subcarrier 0, which is the 35th element of $subcarrier(k,1)$.
4. Repeat step 1 through step 3 for the next OFDM symbol. The different allocation for $SymbolNumber = 1$ is shown as the last subplot in Figure 12-2, which is the result of the variable pilots being located in different places for odd and even symbols.




Figure 12-2: FUSC mapping example

PUSC, DL

The example given below assumes that this is the first DL zone and that there is only one segment. It also assumes that the $PermutationBase_3 = [0,1,2]$ since this parameter is not specified in the relevant table in the IEEE 802.16 standard.

1. Map the physical clusters consisting of 14 consecutive carriers to logical clusters, which are then assigned to the major groups and from there assigned to segments. The principle is shown in Figure 12-3. However, it is irrelevant to the subsequent mapping, as only one segment is used in this example containing all clusters.
2. Partition logical data carriers within the segment into subchannels, by use of the $subcarrier(k,s)$ formula. In Figure 12-3, the mapping is shown for the second subchannel ($s = 1$).
3. Map the logical data carriers k of the subchannels to physical carriers by combining step 1 and step 2. In Figure 12-3, the mapping of the logical indices k of subchannel 1 is shown for the first 57 physical carriers. It shows, for example, that physical subcarrier 24 is the 11th logical subcarrier of subchannel 1 because physical subcarrier 24 is logical subcarrier 1, which is the 11th element of $subcarrier(k,1)$.
4. Repeat step 1 through step 3 for the next OFDM symbol. The different allocation for $SymbolNumber = 1$ is shown as the last subplot in Figure 12-3, which is the result of the variable pilots being located in different places for odd and even symbols




Figure 12-3: PUSC DL mapping example

PUSC, UL

The example given below assumes $UL_PermBase = 0$.

1. Map the physical tiles consisting of four consecutive carriers to per-subchannel logical tiles. The principle is shown in Figure 12-4, in which the carriers belonging to a single physical tile are stacked vertically. As shown, subchannel 1's six logical tile indexes 1 through 5 point to physical tiles 2, 4, 11, 13, 18, and 20, respectively.
2. Allocate the pilots within each tile and sequentially number the logical data carriers, starting with the lowest carrier in the lowest numbered logical tile in the earliest OFDM symbol. Number all carriers within that tile in the same OFDM symbol, and then do the same in the next to lowest logical tile. Repeat until all data carriers within that OFDM symbol for that subchannel have a logical number, and then repeat for the other two OFDM symbols in the slot. The resulting numbering is shown in the second subplot of Figure 12-4, where crossed-out locations are pilot locations.
3. The last step is the mapping of data symbols. Rather than mapping the first data modulation symbol to logical subcarrier 0, an offset of 13 times the subchannel number is applied. This data mapping rotation is shown in the third subplot of Figure 12-4.
4. Repeat step 1 through step 3 for the next slot. The different data mapping for $SymbolNumber = \{3, 4, 5\}$ is shown as the last subplot in Figure 12-4. This is the sole result of the data subchannel rotation mechanism that must be applied on the UL, which in this case results in the previous subchannel 0 being renumbered subchannel 1.




Figure 12-4: PUSC UL mapping example

FRAME STRUCTURE

Point-to-multipoint (PMP)

The only network configuration currently supported for the OFDMA PHY is PMP. It is, however, likely that the amendment project IEEE P802.16j, on mobile multihop relay (see Chapter 9), will target WirelessMAN-OFDMA only.

An example of the logical layout of a frame is shown in Figure 12-5, where the segment spans logical subchannels s through $s + L$. As in the OFDM PHY, the FCH, which has a fixed location and duration in the frame and contains only the DLFP, follows the DL preamble. The DLFP specifies the subchannel groups of which the segment is constructed, the length of the DL MAP, how much repetition coding is used on the DL MAP, and whether there is any change to the ranging allocation from the previous frame.

The MAPs in this example specify, among other things, that the frame spans two permutation zones on the DL, the first of which (PUSC) is mandatory. The MAPs also specify the location and content of all bursts (including burst profile; destination, if applicable; and so on).

As in the OFDM PHY, UL and DL bursts are separated by RTGs and TTGs to ensure that the transceiver at the BS has the time required to switch between receive and transmit. Furthermore (also as in the OFDM PHY), when establishing the MAPs, the BS must take into account the SSTTG and SSRTG, which is the minimum time in which an SS can switch between receive and transmit. Using Figure 12-5 as an example, the BS may be prohibited from providing an allocation to the station addressed in burst #6, as its SSTTG may exceed the BS's TTG. Similarly, the BS may be prohibited from addressing, in the next frame's DL, the station addressed in UL burst #1, as its SSRTG may exceed the BS's RTG, making it impossible for the SS to receive the necessary preamble of the following frame. Problems like these may result from the use of inexpensive SSs. The inability to address some SSs in a DL frame must be taken into account when scheduling broadcast messages.




Figure 12-5: Frame structure (TDD)

Preambles

In order to enable channel estimation at the receiver, two steps are taken:

- Preceding each burst with a preamble, as in the OFDM PHY
- Embedding pilots in the data stream, as in the DVB-RCT standard [B16]

In comparison to the OFDM PHY, therefore, the OFDMA PHY pilots are more abundant because they are not intended only for phase tracking.

To generate the preambles, the OFDMA PHY uses a series of 114 binary PN sequences of length 568. The sequence to be used is decided by the segment number and the *IDCell*. It is mapped to every third subcarrier except the DC carrier, starting with the subcarrier that equals the segment in number. In each

segment, the SS can derive the complete channel response by interpolation and can augment this by updating the estimate with information derived from the constant and variable location pilots.

Each DL burst must be initiated with such a preamble. However, on the UL, no preambles are used except during AAS zones. In that direction, the BS derives the needed channel information solely from the pilots embedded in each tile.

CHANNEL ENCODING

The OFDMA PHY channel encoding consists of randomization, FEC, interleaving, and modulation.

Randomization

The randomization process is, apart from initialization, identical in definition to that of the OFDM PHY. The only notable difference is that, for each FEC block, the same fixed initialization value is used. Regardless of when and from where it is transmitted, the result for a given input sequence is hence always the same. The remnant value of the randomizer specified in this fashion is, therefore, limited. It is, however, worth noting that the PAPR concerns that stimulate the traditional use of randomizers is substantially mitigated in the OFDMA PHY due to the logical to physical subcarrier permutations and the different time-frequency allocation that may be used when retransmitting the data. Also note that a fixed randomizer seed is necessary with the use of HARQ to allow prerandomizer combining. When using chase combining, the transmitted bursts are hence necessarily identical. When incremental redundancy is used, the transmitted bursts are naturally different.

Forward error correction (FEC)

The OFDMA PHY specifies five methods of channel coding: convolutional coding (CC) with tail-biting, block turbo coding (BTC), convolutional turbo coding (CTC), low-density parity check coding (LDPC), and CC with zero-tailing. Tail-biting CC is mandatory; the others are optional.

Convolutional coding (CC)

The CC encoder is identical to that used in the OFDM PHY and the IEEE 802.11a amendment. In the optional zero-tailing case, a single byte 0x00 is appended before encoding, as in the OFDM PHY. In the mandatory tail-biting case, the input data are used cyclically in that the first 6 data bits are fed into the encoder a second time to compute the last 6 output bits. This practice avoids the 1 byte of tail overhead employed by optional zero-tailing; however, the decoder needs to compute a substantial portion of the received sequence twice, mandating a faster decoder. This is an unusual example in that the optional specification is less complex than the mandatory implementation, but requires (slightly more) overhead. The motivation to specify this option is not entirely obvious.

In the IEEE 802.16a specification, the mandatory implementation required concatenation of RS-CC as in WirelessMAN-OFDM. However, it requires the use of tail-biting, rather than the zero-tailing used in the OFDM PHY. The small blocks into which the IEEE 802.16e amendment evolved the OFDMA specification made this concatenation less attractive due to the poor performance of small RS code words.

BTCs and CTCs

The BTC and CTC specifications in the OFDMA PHY are very similar to those in the OFDM PHY, with the minor differences stemming from the need to enable a finer granularity of blocks.

LDPC

The low-density parity check (LDPC) is a coding method that has received substantial attention in the past few years, both academically and in industry. It is no surprise then that LDPC codes were also introduced into the OFDMA PHY through the IEEE 802.16e amendment. Some industry groups, however, appear to be leaning toward the CTC encoder as the primary optional codec.

The LDPC encoding process is the equivalent of the encoding of a data vector of size $n - m$ so that parity check matrix H multiplied by the resultant code word equals an all-zero vector. H is of size $m \times n$, where n is the length of

the code and m indicates the number of parity bits. This results in a code rate of m/n . The matrix $\mathbf{H}$ is constructed out of submatrices of size $(n/24) \times (n/24)$, each of which is identified by a single rotation index. A value of -1 indicates an all-zero submatrix, whereas any larger value indicates an identity matrix right-rotated by the indicated number of times equal to the index. The IEEE 802.16 standard hence provides specifications of the $\mathbf{H}$ matrix by means of the reduced size $(m/24) \times 24$ rotation index matrix, also commonly termed the *shift index matrix*.

Specifically, the standard indicates the shift index matrix for the largest possible block size $n = 2304$. The shift index matrix for smaller block sizes $n^\dagger$ is obtained by replacing each non-negative rotation index $p(i, j)$ by $\lfloor p(i, j) \cdot n^\dagger / n \rfloor$ for all but one particular index matrix (for rate 2/3, code A) where $\text{mod}(p(i, j), (n^\dagger/24))$ is used. The standard specifies five index matrices; one for rate 1/2 and two each for rate 2/3 and rate 3/4. The required dual implementation of index matrices for a particular rate has no technical advantages; it is purely a result of the political process.

The shift index matrix has the general structure shown in Figure 12-6.

[illegible]

Figure 12–6: General shift index matrix structure

Whereas the left side of the matrix may have almost any entries (subject only to column and row weight preferences), the remaining portions are strictly structured. The right side of the matrix consists of a so-called *dual diagonal staircase construction*, where the 0 indexes (which indicate identity submatrices) and the “-1” indexes (which indicate all-zero matrices, as previously explained) create an all-zero section in the $\mathbf{H}$ with two all-unity off-diagonals. The column in the shift index matrix preceding this section is defined so that the first and last indices (indicated by x) are identical, with

only one non-“1” entry (indicated by y) in the remainder of the column. This construction results in the last column in the H identified by this column in the shift matrix being of weight three.

The purpose of this strict general definition of the shift matrix (and hence of the $\mathbf{H}$ matrix) is that, for encoding schemes based on the general Richardson-Urbanke method (some specific implementations of which are explained as informative in the IEEE 802.16e amendment), a matrix that requires inversion results in the identity, making the inversion unnecessary.

Interleaving

The mandatory interleaver follows the IEEE 802.11a/g interleaver, with the identical base 16 (unlike WirelessMAN-OFDM, which uses base 12).

Because, as explained in the previous chapter, the interleaver's first step is intended to map adjacent coded bits to nonadjacent subcarriers, this does create an additional permutation on top of the logical to physical carrier mapping. In the late stages of the development of the IEEE 802.16e amendment, it was discovered (see [B12]) that the net effect of this combination of permutations could result in a performance loss as high as 5 dB. To resolve this problem, an optional interleaver was added. It has the same structure, but it uses as its base 16 times the number of slots per FEC block.

Modulation

As for the WirelessMAN-OFDM PHY, the modulation of the OFDMA PHY consists of square BPSK through 64-QAM constellations for all data. Exceptions exist for special channel feedback messages, which are encoded with various forms of circular constellations.

CONTROL MECHANISMS

Fast-feedback

The OFDMA defines two fast-feedback methods for the UL. These can be used to relate time-critical PHY parameters. Parameters for which this feedback is defined are SNR, specific MIMO coefficients for two antennas, and MIMO configuration parameters [space-time transmit diversity (STTD) vs spatial multiplexing, open- vs closed-loop spatial multiplexing, the permutation type, antenna selection, and precoding matrix selection]. Fast-feedback subchannels can be allocated by the use of a special MAC subheader or by the use of various DL MAP IEs.

The data to be transmitted within the fast-feedback channel are not encapsulated in an ordinary PDU message, but are instead in an orthogonal encoding of only a few bits of data using QPSK modulation. Each of the possible bit combinations is mapped to a sequence with one octal value per tile in the subchannel. This octal value represents a QPSK sequence for each of the eight data carriers per tile.

The specification allows for both full- and half-subchannel fast-feedback channels. The full subchannel can transfer 4 bits or 6 bits, depending on whether the fast-feedback is regular or enhanced. The half subchannel transfers 3 bits of data per slot. Although the IEEE 802.16 standard does not explicitly state so, the orthogonality of this setup allows for multiple SSs to transfer parameters during the same slot.

CDMA ranging and BW requests

To allow for initial ranging, maintenance ranging, handover ranging, and BW requests, the OFDMA PHY provides a collision-based method using PN sequences. The mandatory ranging allocation (called *ranging channel*) consists of six (and optionally eight) contiguous subchannels. Multiple channels may be allocated contiguously as well. The ranging and bandwidth channel are specified in the UL MAP.

Note that the specification of a minimum of six subchannels for initial ranging makes operation of this PHY with 128-FFT currently impossible, as, for 128-FFT, only four subchannels are defined in the uplink.

The initial ranging and handover ranging transmission may, on instruction from the BS, span either two or four OFDM symbols. When the two-symbol type is to be used, the transmission follows the depiction of Figure 12-7. This depicts the dual transmission of the same BPSK-modulated PN sequence, with the cyclic prefix (CP) and cyclic postfix replacement as indicated.




Figure 12-7: Single-slot initial ranging transmission for OFDMA

The transmission of the PN sequence in this fashion results in a phase-contiguous symbol and provides an addition gain on top of the spreading gain due to the repetition. To provide even more gain, the BS can instruct the use of the four-symbol alternative, in which the SS transmits two of the above symbols built from consecutive PN sequences out of the list of available sequences (in which the first PN sequence must be an even-numbered choice). Due to the spreading gain, this method can resolve multiple initial ranging transmissions simultaneously and is hence called *CDMA ranging*. In contrast to traditional CDMA, the PN sequences are modulated on the carriers in the frequency domain, rather than transmitted sequentially in the time domain.

For periodic (maintenance) ranging and BW requests, the same ranging channel is used, but the symbols are transmitted with the regular cyclic prefix instead of by the method shown in Figure 12-7. For these two methods, the transmission may be one or three OFDM symbols in duration (remember that a UL slot is three OFDM symbols in duration), but in the case of BW requests, three consecutive PN sequences must be used.

All PN sequences are created by a PRBS with generator polynomial $1 + x + x^4 + x^7 + x^{15}$ and an initial state that is partially fixed and partially consists of the IDcell so that different BSs can distinguish between the sequences. This PRBS results in 256 unique PN sequences, each 144 bits in length, a consecutive set of which is allocated to a BS through configuration. The BS can then divide its allocated sequences among the four functions (initial ranging, periodic ranging, BW requests, and handover ranging) by means of the UCD message.

Because the sequences for these methods are known, they can be used not only to identify the transmitting SS by the received sequence but also as a preamble, allowing extraction of (among other things) channel response for the used subchannels and timing and frequency offset information. Specifically, in response to an initial ranging sequence, the BS can immediately provide power, timing, and frequency offset corrections in its response.

PAPR reduction/safety zone

As discussed previously, a PAPR that exceeds the backoff of the amplifier results in nonlinear distortion at the transmitter that is unrecoverable at the receiver. Typically, this is tolerated by randomizing the data and backing the amplifier off until the error probabilities are tolerable. WirelessMAN-OFDMA also provides another method to minimize PAPR and allow for reduced backoff (and, therefore, higher average power or less expensive amplifiers). This method consists of allocating of subchannels, both in the DL and UL, in which the BS and SSs, respectively, can modulate arbitrary data to reduce the overall PAPR of their transmissions. These subchannels are filled with, in effect, random energy that can be freely ignored by the receiver. Naturally, this method comes with a cost: the transmitting party must first

pass the data to be transmitted through the IFFT, compute the PAPR, and determine additional data that, when transmitted in the PAPR reduction subchannel, will ensure a low overall PAPR.

Note that the specification does not preclude the use of other PAPR reduction mechanisms, such as windowing and time-domain peak cancellation (see, for example, [B55]) as long as the transmitter relative constellation error does not exceed the required values.

The BS may also provide safety zones. These are gaps in the UL and DL schedule. To be used, they must be explicitly indicated because the MAPs specify only the duration of an allocation, with the remaining positioning information being implicit from the sequence of allocation. Gaps can be specified in coordination with other BSs to reduce interference on the indicated subchannels for the other BS or BSs.

HARQ support

To support HARQ feedback, the BS may allocate one or multiple pairs of UL acknowledgment channels, each of which consists of the even- or odd-numbered tiles that make up half a subchannel. As with the fast-feedback channel, data are QPSK-modulated directly on the channel, without packetization. The data consist of only a NACK or ACK bit, each of which is expanded to a specific orthogonal sequence to fill the three tiles. The location in the acknowledgment channels in which an HARQ-enabled SS returns its positive or negative acknowledgment is determined by the number of preceding SSs in the DL MAP that are to return such a signal.

HARQ is defined to support chase combining (implying simple retransmission of the data) for all coding methods as well as incremental redundancy methods for both the CC and CTC codec. For CC, the incremental redundancy is achieved through retransmission of the data using a different puncturing sequence.

Chapter 13 Multiple antenna systems

Support for advanced antennas

For operations below 11 GHz, the IEEE 802.16 standard provides support for advanced multi-element antenna systems, including adaptive antenna systems (AAS), space-time coding (STC), and multiple-input, multiple-output (MIMO) systems. These techniques are not supported above 11 GHz as they exploit spatial diversity not substantially present above 11 GHz. This chapter provides an overview of the IEEE 802.16 MAC and PHY support for these multiple antenna systems. This chapter subsequently discusses AAS, open-loop transmit diversity methods (i.e., all methods not requiring feedback), and closed-loop transmit diversity methods (i.e., all methods requiring feedback). AAS is also a closed-loop method, but it is described separately in this chapter, due to the fact that its use has, unlike all other methods, systemwide consequences.

The descriptions in this chapter refer to specific numbers of antenna elements, but should not be construed as limiting the number of physical antennas a system may have. A system may use more than the specified number of physical antennas as long as the resultant signal waveform meets the standard's specification. It is, for example, possible for a compliant system to use cyclic delay diversity (CDD) with multiple transmit antennas, resulting in a signal comparable to a single antenna's signal passed through a multipath channel. On the receive side, the number of antennas beyond the minimum (for example, four in the case of 4x4 MIMO) is completely transparent to the air interface and hence permissible as well.

ADAPTIVE ANTENNA SYSTEMS (AAS)

AAS technology, popularly known as a smart antennas (see [B2], [B32], and [B37]), accommodates the spatially diverse location of energy sources by discriminating signals based on their angles of arrival (AoAs) and angles of departure (AoDs) at an antenna array. In very general terms, the

discrimination of signals, which is outside the scope of the IEEE 802.16 standard, is achieved by computing a complex weighted sum of the signals of all antenna elements, where the weights may be computed according to various metrics.

Through the AAS options, the IEEE 802.16 standard supports the use of smart antennas to perform beam forming. Beam forming can effectively create a narrower signal beam, resulting in increased gain and, therefore, higher range. This in turn increases capacity by increasing the range at which a particular PHY burst profile can be received. In addition, if a BS is capable of multiple simultaneous beams, capacity can be increased through spatial diversity. Theoretically, the spectral efficiency can be increased linearly with the number of antenna elements at the BS. This can lead to an in-cell frequency reuse proportional to the number of antennas.

AAS also allows for the suppression of noise sources, improving the SNR at the receiver; and discrimination on the AoD allows energy to be concentrated in the direction of the intended recipient, enabling larger cell ranges. In addition, nulls can be steered in particular directions, enhancing the interference resistance of the system. An example beam-forming network is shown in Figure 13-1. Obviously, beam forming toward mobile devices adds challenges.




Figure 13-1: Example beam-forming network

Drawbacks of these approaches include the increased system complexity and the inability to broadcast messages, reducing the spectral efficiency due to repetition of broadcast MAC messages to the various recipients.

AAS support in IEEE Std 802.16

While the AAS option requires some AAS-specific capabilities in an SS, the actual beam forming is defined only at the BS side of the link. Therefore, AAS systems in the context of the IEEE 802.16 standard are discussed purely as a BS feature, with both DL and UL AAS components. This limits the complexity of the AAS requirements in the SS to such functions as understanding the AAS zones, implementing AAS-specific preambles and permutations, and using AAS-specific messaging such as private DL MAPs and UL MAPs. At the BS, the algorithms and hardware designs necessary for AAS support are implementation-specific and left to vendor differentiation.

An AAS-enabled SS is an SS capable of establishing and maintaining connectivity with a BS that is actively using an antenna array. This predominantly requires synchronization and MAC capabilities. It does not pose any requirements on the number of SS antenna elements. An SS may also employ an antenna array, and could do so transparently from the standard's perspective, but SS arrays are unlikely due to complexity and size constraints. If AAS is used to extend the range of the cell, both the SS and BS need to be prepared to take additional steps to allow the SS to enter the network. The frame start preamble is a repetitive, well-known pattern. The SS may take advantage of processing gain associated with that preamble to synchronize with the DL in time and frequency, even if it is receiving the DL too weakly to decode the DL MAP and DCD messages.

The AAS option supported by IEEE Std 802.16 is defined so that a single BS can support both AAS-enabled and non-AAS SSs simultaneously. The key difference between pure PMP and AAS is that some AAS SSs may be outside the coverage area of some beams of an AAS BS. The basic framing needs to be modified to accommodate this; a single broadcast cannot be used to communicate information to all AAS SSs. For an IEEE 802.16 system, this results in a challenge, as IEEE Std 802.16 relies on broadcast data (UCD, DCD, DL MAP, UL MAP) to communicate the transmission schedules and to

schedule contention slots. These messages must either be repeated to each individual SS or repeated to SS clusters in the same general direction, although the MAPs need contain only the schedule elements relevant for the targeted SS(s).

As AAS is optional, the BS must always support non-AAS SSs and, therefore, support broadcast transmissions. The coexistence of AAS and non-AAS SSs is achieved by partitioning the IEEE 802.16 frame in time into AAS and non-AAS zones, where the AAS zone is dedicated to AAS-capable SSs. In the AAS zone, AAS-capable SSs receive or transmit, knowing that the BS is directing a beam in their direction. This partitioning can be adjusted dynamically by the BS, as with dynamically asymmetric TDD. The IEEE 802.16 MAC and PHY also support additional functions necessary to support and manage AAS SSs, such as the ability to dynamically choose the best “beams” for each AAS SS and to support ranging of AAS-capable SSs. Since the AAS zone of the frame is explicitly indicated in the broadcast MAP by the BS, non-AAS SSs would not be confused by AAS-specific messages sent in the AAS zone.

We noted above that AAS in the IEEE 802.16 context has both a DL and UL component and provides range extension. However, the structure of the UL MAP allows for scheduling simultaneous or time-overlapping transmissions on the UL, as each scheduled transmission has both a start time and duration. Therefore, a BS may exploit this property to achieve spatial division multiple access (SDMA) transmissions in the UL. This approach can be used to substantially increase the UL capacity, with or without an increase in the range. Strictly speaking, these simultaneous transmissions can be achieved with non-AAS SSs, as it does not require the use of AAS zones or any other AAS-specific messages. On the DL, however, this is not possible, as each allocation implicitly ends with the start of the next allocation.

DL and UL framing

Figure 13-2 shows the TDD framing with AAS support, with both non-AAS and AAS zones. In the OFDM case, the AAS DL zone starts with an AAS-specific preamble; and, in the UL, all SSs require a separate preamble. Also,

again in the OFDM case, the allocation start time in the UL MAP transmitted in an AAS zone is always relative to the start of that AAS zone.

It should be noted that the UL MAPs transmitted in the mandatory broadcast and in the AAS zone may overlap. Whenever such overlap occurs, the most recently received UL MAP with overlapping IE takes precedence.




Figure 13-2: TDD framing for AAS Systems

The partitioning concept is very similar for FDD systems. Figure 13-3 shows the FDD framing of AAS systems.




Figure 13-3: FDD framing for AAS systems

MAC service and control functions

The IEEE 802.16 MAC supports the following functions for AAS-capable SSs:

- The ability to transmit private management messages (such as UL MAP, DL MAP, UCD, and DCD) that may be sent directly to the AAS SS Basic CID, instead of to the Broadcast CID as in generic PMP. It is still possible for an AAS SS to receive broadcast information in certain deployments. During the initial ranging process, the AAS SS communicates to the BS its ability to receive broadcasts.
- Dynamic allocation of specific regions within the frame for initial ranging and BW requests for AAS SSs. The initial AAS ranging is achieved using a separate CID in order to avoid conflicts with the regular Initial Ranging CID used by non-AAS SSs.
- A set of AAS MAC management messages, such as those required for obtaining feedback from an AAS SS for channel estimation and for selecting the most optimal beam for an AAS SS.

AAS MAC management messages

The following AAS MAC management messages are defined:

- The AAS-FBCK-REQ (AAS feedback request) message is used to request channel measurement for a specific frequency. This may be used to adjust the direction of the adaptive array.
- The AAS-FBCK-RSP (AAS feedback response) message is sent in response to AAS-FBCK-REQ and contains the channel measurements.
- The AAS_Beam_Select (AAS beam select) message is used by an AAS-capable SS to indicate the preferred beam. The BS may use this information in deciding on the optimal beam for communication with this SS.
- The AAS_BEAM_REQ (AAS beam request) message is used to request channel measurement for a specific beam in order to adjust the adaptive array at the BS.

- The AAS_BEAM_RSP (AAS beam response) message is sent by an SS in response to an AAS_BEAM_REQ.

Channel state information

The adaptive array operation depends on the estimation of the channel state in both directions. The BS can estimate the UL channel state directly. In TDD systems, the BS may use this UL channel information to estimate the DL channel. However, for FDD systems this method is not accurate due to the different frequencies used for UL and DL. Therefore, for the FDD case, an AAS-FBCK-REQ message is used by the BS to instruct the SS to measure and send channel state estimation using an AAS-FBCK-RSP message. The BS may automatically allocate UL slots for transmitting AAS-FBCK-RSP messages after the measurement period.

AAS DL synchronization and initial ranging

Since a new SS trying to join the system may lie outside all beams, special measures are required to support DL synchronization of AAS SSs. Some SSs with high processing gain may be able to decode the broadcast DL frame boundaries for timing and frequency synchronization. The BS may also periodically perform active scanning by aiming at different directions or may use some PHY-specific diversity methods to support DL synchronization of such SSs.

An AAS-enabled SS that is outside broadcast range and wants to perform initial ranging has no information on the BS. It must, therefore, wait until it receives the AAS network entry preamble, which provides substantial processing gain, and respond immediately. The cell range in which SSs can join the BS is, therefore, limited by the directional gain of the AAS, which is related to the number of antenna elements, by the broadcast link budget, and by the processing gain of the AAS network entry preamble.

As with DL synchronization, some AAS stations may be able to decode MAP and channel descriptor information from the broadcast frame. If an SS is able to reliably decode this information, the initial ranging process can be performed as in the non-AAS case. Adjustments to the adaptive arrays can be made by the BS during this process. In order to support SSs that cannot decode the broadcast portion of the frame, a BS may use PHY-specific predefined AAS contention regions for the various general directions in order to allow AAS SSs to alert the BS of their presence. This approach has substantially higher overhead.

The SS always attempts initial ranging by trying to decode the broadcast DL MAPs and DCD. If it is unable to decode that broadcast, it tries the AAS slots. These AAS alert slots are similar to the regular contention slots for initial ranging. However, an AAS SS uses all contention slots, as opposed to just one slot used by a regular SS, so that the BS has sufficient time and processing gain to aim the beam at the SS's direction. If the BS is able to receive the alert message with sufficient processing gain, it may focus a beam on the SS and transmit the MAPs and channel descriptors. If the SS receives the DL parameters, it continues with the rest of the network entry process. If no DL MAP and DCD are received, the AAS SS performs an exponential backoff identical to the non-AAS case to select the next frame to send the alert.

AAS BW requests

An SS that wants to request bandwidth may lie outside a beam. When an SS performs ranging, its ability to receive broadcast allocations is communicated in the RNG-REQ message. The BS can instruct the SS to use broadcast allocations for BW requests, just like non-AAS SSs. If the SS is not capable of receiving broadcast or if the BS does not want the SS to use broadcast allocation, the BS is responsible for polling in the general direction of the SS to allow BW requests. The BS may modify the BW request method dynamically by instructing the SS in a RNG-RSP.

AAS support in OFDM PHY

Similar to DL subchannelization, AAS is supported in a zone logically separated from the remainder of the frame. Within the AAS zone, the BS can create what can be conceptualized as parallel instances of the PHY and lower MAC, each active on one or more beams in both SDM(A) and TDM(A) fashion. Each instance has its own preambles, FCH (termed *AAS-FCH*), and MAPs, with periodic use of a dedicated UCD and DCD. The IEEE 802.16e addition of private MAPs is particularly useful for this feature. Within each AAS-FCH, the BS transmits an AAS-DLFP that is different from the regular DLFP in that some of the functionality of the MAPs, such as provisioning UL allocations and contention-based opportunities, is embedded in it.

Two MAC management messages are specified to support the AAS PHY. The first allows the exchange of channel feedback information, which consists of CINR, RSSI, and the complex channel coefficient for a regularly spaced (on either side of the DC carrier) set of carriers with intervals of 4, 8, 16, or 32 carriers, depending on the request. The measurements are to be performed on a specific indicated burst. The second message is a similar exchange of channel information except that measurement information is requested and provided on one or more beams.

For initial ranging, two separate messages are provided, one to be used with full channel AAS initial ranging opportunities and one to be used with subchannelized AAS initial ranging opportunities. Both messages violate the IEEE 802.16 MAC architecture in that they have no MAC header. It is unclear whether this omission is by design or by error; but, because they are the only responses allowed in the respective allocation, it is not a fatal violation.

The full channel initial ranging message allows the SS to provide the BS with measured amplitude values of up to four beams, providing the BS with an initial indication of which beam may best be used for the SS in question. The subchannelized initial ranging message, which may be used only if full channel initial ranging repeatedly failed, must be filled with the measured phase offset of three beams relative to a first beam (i.e., four beams total), providing the BS a measure of directionality for the SS and the average RSSI over those beams. In both messages, the SS sets a randomly selected network entry code, which the BS will use in its response to identify the SS.

AAS support in OFDMA PHY

AAS is supported by the OFDMA PHY for FFT sizes larger than 128 by means of the creation of an AAS diversity MAP zone (DMZ). The AAS DMZ can be allocated only on a specific set of subchannels of the DL: the highest two numbered subchannels in the segment ($N-1$ and N) for FUSC and PUSC; and the fourth and $(N-4)^{\text{th}}$ subchannel for AMC. The reason for this difference is that FUSC and PUSC provide frequency diversity through their permutations (logical subchannel to physical subcarrier mapping), whereas AMC does not.

The AAS DMZ contains pairs of the AAS DL preamble followed by the AAS-DLFP, each sent on a (directional) beam. The AAS-DLFP contains some configuration information (the beam used and type and presence of preambles) as well as a pointer to an initial ranging opportunity and a pointer to a DL allocation. The latter pointer may point to the broadcast DL MAP or to a private DL MAP or may constitute a private DL MAP in the form of a single allocation depending on the CID and DIUC in the pointer.

In addition to provisioning AAS as a zone within the general frame, the OFDMA PHY allows the use of so-called *superframes*. A superframe is a period of up to 1 s that must meet the following requirements:

- It must start with at least 20 regular frames, each containing UCD, DCD, UL MAP, and DL MAP, and ranging channel.
- It contains AAS-only periods no longer than 200 ms followed by at least one regular frame containing UCD, DCD, and DL MAP.

The motivation for this construct is that it allows the BS to spend up to 95.2% of its time in AAS-only mode, which is advantageous from a capacity and range perspective, without violating the timeout limitations on synchronization, which are defined as the ability to receive the DL MAP and the DCD. Because those timeouts have a maximum limit of 600 ms, the superframe construct provides at least three synchronization opportunities in that period and provides at least 20 regular frames to reacquire synchronization and network entry for non-AAS devices.

In terms of MAC support, the OFDMA PHY makes use of the same channel feedback message as discussed in regard to the OFDM PHY.

OPEN-LOOP TRANSMIT DIVERSITY

An “open-loop” transmit diversity method exploits the diversity provided by multiple antennas, but requires no knowledge at the transmitter of the channel. These methods require no MAC support.

The OFDM PHY specifies STC as its sole open-loop transmit diversity scheme. The OFDMA PHY, on the other hand, specifies three such methods. Although the IEEE 802.16 standard describes all these methods broadly as STC, a distinction is made in the proceeding between actual STC, *frequency-hopped diversity coding* (FHDC), and *spatial multiplexing* (SM), which is more popularly known as *open-loop MIMO*. The basic transforms for these methods are summarized in Figure 13-4.

	OFDM symbol $k \quad k+1$	OFDM symbol k	subchannel $k \quad k+1$	OFDM symbol $k \quad k+1 \quad k+2$
antenna 0	$\begin{bmatrix} s_0 & -s_1^* \end{bmatrix}$	$\begin{bmatrix} s_0 \end{bmatrix}$	$\begin{bmatrix} s_0 & -s_1^* \end{bmatrix}$	$\begin{bmatrix} 0 & s_2 & p \\ s_0 & s_3 & s_6 \\ s_1 & s_4 & s_7 \\ p & s_5 & 0 \end{bmatrix}$
antenna 1	$\begin{bmatrix} s_1 & s_0^* \end{bmatrix}$	$\begin{bmatrix} s_1 \end{bmatrix}$	$\begin{bmatrix} s_1 & s_0^* \end{bmatrix}$	$\begin{bmatrix} p & -s_3^* & 0 \\ -s_1^* & s_2^* & -s_7^* \\ s_0^* & -s_5^* & s_6^* \\ 0 & s_4^* & p \end{bmatrix}$
	rate 1 STC	rate 2 SM	rate 1 FHDC	rate 1 UL STC

Figure 13-4: Open-loop transmit diversity schemes

Each of the methods shown in Figure 13-4 requires two antenna elements at the transmitter or, if the BS is sectorized, two elements per sector.

STC uses the optimal space-time block code presented by Alamouti [B1], which achieves channel capacity (see [B44]). This STC is also known by the abbreviations *STTD* (space-time transmit diversity) or *STBC* (space-time block coding) and is, for example, also defined as part of the wideband CDMA (W-CDMA) standard [B17] (although in transposed form, which does not change its properties). This method requires that the channel be constant during the two-symbol interval over which the code is defined.

STC support in OFDM PHY

In the OFDM PHY, STC specifications are provided only for the DL.

The method is applied as follows: Data for two subsequent OFDM symbols s_0 and s_1 are collected after the modulation stage, where the pilot modulations are copied from the first symbol to the second. During the first OFDM symbol of the STC block, s_0 is transmitted from the first antenna and s_1 from the second antenna. During the second OFDM symbol of the STC block, the first antenna transmits $-s_1^*$ and the second antenna s_0^* .

The SS will hence receive $r_0 = h_0 \cdot s_0 + h_1 \cdot s_1$ during the first OFDM symbol, where h_0 and h_1 are the channel responses from antenna 0 and 1 to the SS antenna, respectively, and $r_1 = -h_0 \cdot s_1^* + h_1 \cdot s_0^*$.

The reception of this post modulation transform can be denoted as follows:

$$\begin{bmatrix} r_0 \\ r_1 \end{bmatrix} = \begin{bmatrix} s_0 & s_1 \\ -s_1^* & s_0^* \end{bmatrix} \begin{bmatrix} h_0 \\ h_1 \end{bmatrix}$$

Because the preamble for this PDU is transmitted on alternate subcarriers from the two antennas (even subcarriers for antenna 0 and odd subcarriers for antenna 1), the SS has knowledge of the channel responses $\hat{h}_0$ and $\hat{h}_1$ through simple frequency interpolation.

The receiver then applies the following transform to achieve the estimates $\{\hat{s}_0, \hat{s}_1\}$ using the channel estimates:

$$\begin{bmatrix} \hat{s}_0 \\ \hat{s}_1 \end{bmatrix} = \begin{bmatrix} \hat{h}_0^* & \hat{h}_1 \\ \hat{h}_1^* & -\hat{h}_0 \end{bmatrix} \begin{bmatrix} r_0 \\ r_1 \end{bmatrix} = \begin{bmatrix} \hat{h}_0^* \cdot h_0 + \hat{h}_1 \cdot h_1^* & \hat{h}_0^* \cdot h_1 - \hat{h}_1 \cdot h_0^* \\ \hat{h}_1^* \cdot h_0 - \hat{h}_0 \cdot h_1^* & \hat{h}_1^* \cdot h_1 + \hat{h}_0 \cdot h_0^* \end{bmatrix} \begin{bmatrix} s_0 \\ s_1 \end{bmatrix}$$

The above equation shows the diversity combining on the diagonal terms and shows that the off-diagonal interference terms go to zero if the channel estimates are accurate. Note that this transform is also used for the modulated pilots.

The STC codec gain can be used to increase modulation/coding efficiency within the broadcast range. Also, to extend the cell range beyond the

broadcast range, a separate STC zone is allocated, in which the BS sends an STC-encoded preamble and FCH as well as the MAPs and DCD/UCD, as needed. The inclusion of broadcast messages in the STC zone is necessary since a station outside broadcast range will be unable to decode the FCH and MAPs outside the STC zone.

STC, FHDC, and MIMO support in OFDMA PHY

The OFDMA PHY provides the same method of STC as the OFDM PHY for deployments in which the BS has two antennas (or four, where the second pair transmit the same signal as the first pair but with a respective phase rotation received through the fast-feedback mechanism so that directional gain is achieved). The method is defined only for FUSC and PUSC.

Using FUSC, the permutation during an STC zone changes only once per two OFDM symbols; an FUSC slot using STC can, therefore, be said to last two OFDM symbols. Within those two symbols, data are modulated from both antennas, as described for the OFDM PHY. For the pilots, different sequences apply to odd and even OFDM symbols, but the pilots are placed on the same subcarriers in both symbols. This method can be represented by the transfer matrix shown on the left in Figure 13-4. Because it encodes two data symbols over two OFDM symbols, this method is classified as a rate one encoding method.

Another method allowed by the OFDMA PHY is spatial multiplexing, in which a separate data symbol is transmitted from each antenna without repetitions in the subsequent OFDM symbol. Spatial multiplexing provides increased capacity, but provides no diversity gain and requires a more complex receiver including multiple receiver chains.

Another variant allowed is FHDC, which is conceptually the same as STC, but with encoding over two subchannels instead of over two OFDM symbols.

Unlike in the case of the OFDM PHY, STC and SM are also defined for the UL, specifically for PUSC. Recall that a tile for UL PUSC is defined as four contiguous carriers over a span of three OFDM symbols, with the corners reserved for pilots. Using STC and SM on the UL, this tile definition is slightly modified so that the pilots on the diagonal are not transmitted on

antenna 0 and the pilots on the cross-diagonal are not transmitted on antenna 1. The STC encoding is subsequently applied per two subcarriers within the same OFDM symbol, as shown in Figure 13-4, where each vector indicates the encoding of the four subcarriers within the tile for a specific OFDM symbol per antenna.

PUSC also allows what is termed *virtual MIMO*, in which antenna 0 and antenna 1 belong not to the same SS but to completely different SSs. This allows SSs to transmit simultaneously with near certainty of the channels being uncorrelated and without requiring any additional complexity.

Lastly, a provision is established for STC and SM where the transmitter has four antennas, the matrices for which are shown in Figure 13-5.

	OFDM symbol k $k+1$ $k+2$ $k+3$				OFDM symbol k $k+1$ $k+2$ $k+3$				OFDM symbol k	
antenna 0	s_0	$-s_1^*$	0	0	s_0	$-s_1^*$	s_4	$-s_6^*$	s_1	
antenna 1	s_1	s_0^*	0	0	s_1	s_0^*	s_5	$-s_7^*$	s_2	
antenna 2	0	0	s_2	$-s_3^*$	s_2	$-s_3^*$	s_6	s_4^*	s_3	
antenna 3	0	0	s_3	s_2^*	s_3	s_2^*	s_7	s_5^*	s_4	
	rate 1 FHDC				rate 2 FHDC				rate 4 FHDC	

Figure 13-5: Four-antenna STC and SM

CLOSED-LOOP TRANSMIT DIVERSITY

In addition to the open-loop schemes, the IEEE 802.16e amendment adds closed-loop transmit diversity methods for the OFDMA PHY. These methods rely on channel state information sent back by the SS on command from the BS. For this purpose, the BS uses the UL_Sounding_Command_IE, which provides a large array of possibilities for how the SS should parse the measurements it made.

Precoding

One of the closed-loop methods is so-called *precoding*, which is similar in application and motivation to STC but exploits knowledge of the channel. The coding in this case maps the orthogonal MIMO streams to the physical antennas.

There are principally two methods of conveying, from the SS to the BS, which precoding matrix to use. Using the first method, the SS simply returns quantized versions of the channel metrics. In the second method, both sides of the link have access to a set of so-called *codebooks*, each containing an indexed set of coding matrices. For each channel rank, which never exceeds the number of transmit antennas and dictates the number of spatial streams the channel can support, a different codebook is specified in the standard. The receiving station computes a precoding matrix to optimize throughput for the current channel rank, finds the nearest matrix in the codebook of the current channel rank, and sends the index of the selected matrix as well as the channel rank back to the transmitting station.

For each rank, the codebooks are designed so that the chordal distance between the code matrices is maximal. They are specified with 3-bit indexes (8 code matrices per codebook) and 6-bit indexes (128 code matrices per codebook). The choice allows the implementer a trade-off between complexity and performance. The receiver's decision about which index to select is implementation-dependent and may make use of various distance metrics between the computed optimal matrix and the available matrices in the codebook.

With the introduction of high-speed mobility as a consideration during the development of IEEE Std 802.16e, it was observed that, despite the use of the fast-feedback channel as discussed in Chapter 12, the protocol delays could in some cases exceed the coherence time of the channel. This would make the instantaneous channel metrics outdated by the time they were applied. To resolve this issue, a method was introduced to feed back not only the instantaneous channel metrics but also (long-term) first- and second-order statistics of the channel. The first-order statistic used is the LOS component of the Ricean fading channel approximation. The second-order statistics consist

of the channel's spatial correlation information. These statistics may be used to improve the estimate of the channel condition at the time of transmission.

Antenna selection

Using antenna selection, the receiving SS can use the fast-feedback channel to identify the group of antennas it prefers the transmitting BS to use for full-rate transmissions. The spatial multiplexing is performed by the selection of a single vector (similar to the rate 4 FDHC shown in Figure 13–5) where one or more elements are nulled (the vector being of a length equal to the number of transmit antennas, wherein the number of non-nulled elements is equal to the number of spatial streams desired). Antennas for which the element reads null are not used during the transmission. This method is defined only for systems with three or four transmit antennas.

Antenna grouping

The antenna grouping method uses the methods described in the open-loop section of this chapter. These methods are less than full-rate. Instead of disabling antennas as with antenna selection, the antenna grouping method groups antennas into STC pairs. This may be most trivially visualized as row permutations of the space-time coding matrix. For example, for four transmit antennas, these are row permutations of the rate 1 and rate 2 FHDC shown in Figure 13–5. The receiving SS uses the fast-feedback channel to indicate the index of the preferred permutation to use. This method is also defined only for systems with three or four transmit antennas.

Chapter 14 Performance analysis

MAC and PHY performance and throughput

INTRODUCTION

This chapter reviews several published simulations that assess the performance of WirelessMAN systems. Such simulations are complex and depend on a vast number of parameters, assumptions, and algorithms that are typically not fully detailed in the publications. However, due to the great interest among both industry and academia in the WirelessMAN technology, the research base is growing as the community has more time to study and evaluate the IEEE 802.16 standard. As more research becomes available, confidence in the results will begin to grow.

Due to the complexity of the simulations and the time required to run them, most studies chose to treat certain aspects of the system in a general way, while modeling other aspects in great detail. While simulation results may indicate potential performance, they cannot do so definitively.

WIRELESSMAN-OFDM, FIXED OPERATION

Capacity analysis

A 2005 paper by Ghosh, et al., [B18] reports the performance of the WirelessMAN-OFDM system with different frequency reuse patterns and cell sectorization. Figure 14–1, reproduced from that paper, illustrates the aggregate MAC-level throughput with a 3 km cell radius and a 50 W BS transmitter. The traffic model is not detailed, but the marginal differences between the PHY and MAC throughput presented suggest a full-buffer model. The calculations use three and six sectors per cell, with reuse factors 1 and 3. The reuse factor in this case is defined from cell to cell; for example, with six sectors per cell and a reuse factor of 3, a set of six channels, chosen from among three available sets of six channels, is used at each cell. According to

the paper, the results show the “average throughput over an entire cell per 5 MHz carrier.” However, it appears that, in calculating the average, the throughput has been divided by the number of channels per cell, not the total number in all cells. This is suggested by the paper’s conclusion that “if at all possible, 1/1 reuse (frequencies reused every cell) should be employed since the gain from going to 1/3 reuse (frequencies reused every third cell) does not come close to compensating for the associated tripling of consumed bandwidth.” To calculate the throughput per channel used in the system, it appears that the bars labeled “1/3 reuse” in Figure 14–1 should be divided by a factor 3.




Figure 14–1: WirelessMAN-OFDM throughput per 5 MHz channel

The figure also shows the effect of adding a second receiver in the SS, with half a wavelength (7 cm) separation.

The performance of the system can also be improved by the use of STC. The paper shows that, in the three-sector case (with 1/1 reuse) and one receive antenna, adding STC with a second transmit antenna provides performance similar to the six-sector single-in, single-out (SISO) case, but with only half the channels.

Figure 14–2 shows the outage relative to 1.5 Mbit/s; that is, the fraction of cell area with maximum data rate less than this value. This figure indicates that narrower sectorization cuts down drastically on bad channel conditions and interference. Also the use of receive diversity improves the outage substantially.




Figure 14–2: WirelessMAN-OFDM outage relative to 1.5 Mbit/s

MAC performance

MAC performance is assessed under more realistic traffic conditions (although less realistic environmental conditions) in a 2006 paper by Cicconetti, et al., [B10]. It considers an interference-free FDD WirelessMAN-OFDM system with 7 MHz bandwidth and 10 ms frame duration. The UL allocation start time is chosen to be 10 ms, meaning that all UL allocations point at a minimum to the next frame. This introduces a minimum delay of 10 ms, but it provisions terminals with very low processing power. The analysis is performed on a single cell (i.e., no interference) and assumes no transmission errors apart from contention-based collisions. The authors assumed that the SSs employ the following modulation methods and coding rates, which are evenly partitioned among SSs: QPSK 3/4, 16-QAM 3/4, and 64-QAM 3/4.

Two scenarios are studied in the paper. In the residential scenario, the authors consider offering broadband Internet access. The Internet traffic is modeled as a Web traffic source (see [B39]). Packet sizes are drawn from a Pareto distribution with cutoff (shape factor = 1.1, mode = 4.5 kB, cutoff threshold = 2 MB), while packet interarrival times are distributed exponentially (average = 5 s), which yields an average load of 25 kB/s. The resulting throughput delay curves are shown in Figure 14-3. In addition to the residential scenario, the paper covers a small- and medium-enterprise scenario. For details, please consult the paper.




Figure 14-3: Average throughput delay vs offered load

The following sections deal with previously unpublished results generated by the authors of the previously discussed paper using the same simulator. The assumption for these results are, however, slightly different. In this set of results, a frame duration of 5 ms was used. The allocation start time was set to be equal to the length of the frame. The channel bandwidth is 7 + 7 MHz.

The system is loaded with a number of applications spanning all four defined service types (UGS, rtPS, nrtPS, BE) and resulting in eight connections in each direction:

- DL

MPEG video: 128 kbit/s

IP traffic: 200 kbit/s [10% gaming, 9% mail, 9% FTP, 4.5% Telnet, and 67.5% Hypertext Transfer Protocol (HTTP)]

Videoconference: 80 kbit/s

VoIP: 16 kbit/s

- UL

MPEG video: 128 kbit/s

IP traffic: 50 kbit/s (same mix as DL)

Videoconference: 80 kbit/s

VoIP: 16 kbit/s

The UL allocation start time is chosen to be 5 ms, meaning that all UL allocations point at a minimum to the next frame. This introduces a minimum delay of 5 ms, but it provisions terminals with very low processing power. The analysis is performed on a single cell (i.e., no interference) and assumes no transmission errors apart from contention-based collisions (except in the ARQ analysis, where a fixed 10^{-6} BER is assumed on each link).

Full-duplex with single burst profile

The SSs in this example are all full-duplex, and all use the same 64-QAM-5/6 burst profile, which implies a 28.23 Mbit/s raw PHY data rate. The DLFP and MAPs are transmitted at their required rates.

The most interesting delay curve is that for the IP traffic. Because this traffic is BE, it provides a good indicator of behavior as a function of load. This is because an increase in load increases the demand for the other services and hence reduces the capacity left over for BE traffic. In Figure 14-4 and Figure 14-5, an example of this performance is shown for the DL and UL, respectively.




Figure 14-4: DL, IP traffic mean transfer delay




Figure 14-5: UL, IP traffic mean transfer delay

Besides the data transfer, the UL must carry contention-based request transmit opportunities. The absolute number of these, as well as the utilization (S) and load (G) of request transmit opportunity ($UIUC = 2$), is shown in Figure 14-6 and Figure 14-7, respectively. Notice that only the mandatory full contention method is used.




Figure 14-6: UL, Average transmit opportunities per frame

Lastly, the MAC overhead within a frame is of interest. This overhead, which consists of the FCH and MAPs, is shown in Figure 14-8. It can be seen that the overhead increases to 4.7% (7 OFDM symbols per frame) when supporting 400 connections (50 SSs) in both directions.

The loads of the DL and UL are roughly linear with the number of SSs. For 50 SSs, the load on the DL is roughly 75%, whereas the load on the UL approaches 90%, driving the UL faster into saturation than the DL, despite carrying only two thirds the net throughput.




Figure 14-7: UL load and utilization of transmit opportunities




Figure 14-8: FCH + MAP overhead

Mixed full-duplex/half-duplex with burst profiles case

In this scenario, the DIUC and UIUC span the QPSK-1/2 to 64-QAM-5/6 range. Performance is evaluated for SSs having the same DIUC and UIUC, respectively. Half the SSs are full-duplex, and half are half-duplex. As the average PHY rate is substantially lower (on average around 10.8 Mbit/s) than in the previous case, simulations are limited to 30 SSs. Because the overhead is not depended on the used IUC and whether an SS is full-duplex or half-duplex, the overhead shown in Figure 14-8 remains valid for these cases.

Figure 14-9 and Figure 14-10 show the difference between full-duplex and half-duplex SSs with regard to the transfer delay for the VoIP application. It shows that the transfer delay for half-duplex SSs is around 20% higher than that of full-duplex devices, which is predictable as the uplink cannot be used by these devices while actively listening to the DL and during SSRTG and SSTTG.




Figure 14-9: UL, full-duplex SSs, VoIP mean transfer delay




Figure 14-10: UL, half-duplex SSs, VoIP mean transfer delay

Figure 14-11 and Figure 14-12 show the transfer delay difference between DL and UL for the same best effort HTTP service. Figure 14-11 shows that, on the DL, the traffic is on average allocated either to the immediately following frame or to the next frame after that. On the UL, shown in Figure 14-12, an SS may first have to use a contention slot to request bandwidth or, if it has other data scheduled for transmission, can use piggy-backing. The allocation for the burst will then appear in the DL MAP no sooner than the next frame with an allocation for the frame following that. Because of this, the average transfer delay for any service will typically exceed 10 ms. Lastly, in Figure 14-13, the same scenario is shown with ARQ enabled, assuming a 10^{-6} BER on each link. It can be seen that the transfer delay roughly doubles, which is to be expected from retransmissions and the increase in system load. For 30 SSs, the UL can be seen to go rapidly into saturation.




Figure 14-11: DL, half-duplex SSs, HTTP mean transfer delay




Figure 14-12: UL, half-duplex SSs, HTTP mean transfer delay




Figure 14-13: UL, half-duplex SSs, HTTP mean transfer delay w/ARQ

WIRELESSMAN-OFDM, MOBILE OPERATION

Basic PHY performance

In this section, we present unpublished calculations regarding the WirelessMAN-OFDM performance with limited mobility. Figure 14-14 shows the coded block error rate (CBLER) for WirelessMAN-OFDM using the ITU Vehicular A (VehA) 3 km/h channel model [B30]. These results include all of the synchronization loss, which comes to 1 dB to 2 dB.




Figure 14-14: OFDM CBLERs—ITU VehA 3 km/h

Figure 14-15 shows the CBLER as a function of OFDM symbol index and SNR using the ITU VehA 30 km/h channel model with QPSK modulation and 1/2 rate coding. The symbol index is the count of data OFDM symbols following the preamble within the same burst, and the CBLER is computed individually over each OFDM symbol (as the outer RS code is a per-OFDM-symbol block code). Due to the rapidly varying channel condition, the channel estimate computed from the preamble will be increasingly less accurately matched to the instantaneous channel condition for the OFDM symbol as the OFDM symbol index in the burst increases. For BPSK 1/2, the degradation will be slower, while for higher order modulations, it will be more severe. This figure shows that, even at this modest speed, the degradation is severe due to the changing channel conditions. For this reason, the nonsubchannelized bursts in mobile operation must be relatively short. To address the problem, midambles, for subchannelized operation, have been added through IEEE Std 802.16e. The degradation can also partially be mitigated by updating the channel estimates by means of data-driven decision feedback, which is not included in Figure 14-15.




Figure 14-15: OFDM CBLERs—ITU VehA 30 km/h

Capacity analysis

In a 2005 paper, Ball, et al., [B5] report a study of a mobile network using WirelessMAN-OFDM in a 3.5 MHz channel at 3.5 GHz with cell radius of 300 m. The 2 W BS uses three sectors with 17.5 dBi antennas. The analysis considers a full-buffer FTP model with up to 300 randomly distributed nomadic clients per sector. The analysis is performed with reuse factors of both 1 and 3.

Figure 14-16 depicts the channel utilization of each sector utilization as a function of the offered load, showing a limit of around 3 Mbit/s for a reuse factor of 1 and at 4.25 Mbit/s for a reuse factor of 3. This corroborates the findings of Ghosh, et al., [B18] that the spectral efficiency is higher with a reuse factor of 1. Figure 14-17 shows, as a function of the offered load (which is varied identically in each cell), the fraction of SSs served with each modulation/coding rate in this simulation. For reuse factor 1, the modulation/coding rate efficiency is substantially lower due to the increased

interference (lower C/I); roughly 80% of the SSs are using modulation/coding no more efficient than QPSK-3/4.




Figure 14-16: Channel utilization as function of offered load




Figure 14-17: Modulation/coding utilization as function of offered load

The Ball paper further analyzes (see Figure 14–18) the occurrence of call blocking (i.e., rejection by admission control due to insufficient C/I). In the reuse factor 1 scenario, a cell load of 1 Mbit/s results in 10% of call blocking, whereas the reuse factor 3 scenario experiences no substantial call blocking up to the channel utilization limit shown in Figure 14–16. The spectral efficiency is hence $1 \text{ Mbit/s} / 3.5 \text{ MHz} = 0.29 \text{ (bit/s)/Hz}$ per sector for the reuse factor 1 case and $4.25 \text{ Mbit/s} / (3 * 3.5 \text{ MHz}) = 0.40 \text{ (bit/s)/Hz}$ per sector for reuse factor 3. The reuse factor 3 scenario hence provides higher spectral efficiency when both channel utilization and call blocking limitations are observed. It should be noted that the analysis considers none of the optional WirelessMAN-OFDM features to improve C/I performance, such as STC, diversity techniques, advanced coding, and subchannelization. Applying these options would likely provide a substantial performance improvement, particularly for the reuse factor 1 scenario.




Figure 14–18: Call blocking (C/I < 1 dB) as function of offered load

WIRELESSMAN-OFDMA, MOBILE OPERATION

Overhead and capacity

In a 2005 paper, Lee, et al., [B35] report on studies of a system considered for “WiBro” services. The system studied is “somewhat similar” to a draft of IEEE Std 802.16e at some stage prior to approval. According to the paper, the differences include “the structure and performance of preamble” and “subcarrier permutation in FCH/DL MAP.” The results may shed some light on WirelessMAN-OFDMA performance. Recall that WirelessMAN-OFDMA is defined in IEEE Std 802.16-2004 [B20] using a 2048-FFT. The system under study uses a 1024-FFT, which is an option for WirelessMAN-OFDMA in IEEE Std 802.16e.

The system studied uses a channel of 8.447 MHz and a 10 MHz sampling bandwidth. The system is TDD, with a 2/1 DL/UL ratio. The overhead, including all PHY overhead as well as control subchannels for channel quality information (channel feedback), acknowledgment, and initial ranging, was found to be between 22% and 31%.

This paper also analyzes performance as a function of cell radius. It assumes a fixed modulation/coding and maximizes the number of subchannels to satisfy the CINR required to achieve a 1% PER. Figure 14–19, redrawn from the published data, illustrates the results. Combining the results by selecting the maximum capacity at a given range, the solid line in Figure 14–19 shows the DL sector capacity if the only modulation/coding options available for the link adaptation algorithm to choose were the three indicated in this figure. Introducing the remaining modulation/coding combinations would have the effect of largely removing the jaggedness of the curves.

Figure 14–20 is the parallel to Figure 14–19 for the UL.

Figure 14–19 and Figure 14–20 suggest that, in order to guarantee a single user 512 kbit/s DL and 256 kbit/s UL, the cell radius must be limited to 2.3 km.

Using the same approach with an outdoor-to-indoor channel model, Figure 14–21 and Figure 14–22 show the 512 kbit/s DL / 256 kbit/s UL cell radius to be limited to approximately 0.7 km.




Figure 14-19: DL sector capacity per cell radius—ITU VehA (60 km/h)




Figure 14-20: UL sector capacity per cell radius—ITU VehA (60 km/h)




Figure 14-21: DL sector capacity per cell radius (ITU outdoor-indoor)




Figure 14-22: UL sector capacity per cell radius (ITU outdoor-indoor)

A 2005 paper by Kwon, et al., [B34] presents an alternative study of the system capacity. The modeled system is TDD using a 1024-FFT, 9 MHz bandwidth, 5 ms frame duration, and a 2/1 DL/UL frame split. The network is loaded with a number of applications spanning all four service types (UGS, rtPS, nrtPS, and BE) defined in IEEE Std 802.16-2004 as well as the extended rtPS (ertPS) introduced in IEEE Std 802.16e for real-time flows generating variable packet sizes on a periodic basis, such as VoIP with silence suppression. The traffic load per user is as follows:

- DL

Video: 32 kbit/s, 10 frames/s

IP traffic: ~90 kbit/s FTP and ~15 kbit/s HTTP traffic (according to 1xEV-DV traffic models; see [B8])

VoIP: 9.6 kbit/s with 0.403 activity factor

- UL

VoIP: 9.6 kbit/s with 0.403 activity factor

IP traffic: As needed to support UL FTP, HTTP, and video traffic

The analysis is performed in a hexagonal cellular environment considering interference from first and second tier cells with identical traffic distributions. Figure 14-23 shows the delay in transmitting VoIP data using rtPS, UGS, and ertPS. On the DL, the number of VoIP calls is limited to 92 when the delay limit is 60 ms. This figure shows that the introduction of ertPS in IEEE Std 802.16e is justified for voice with silence suppression since the call limit is similar to the DL limit using ertPS, but is significantly lower using rtPS and UGS.




Figure 14-23: Delay for VoIP using rtPS, UGS, and ertPS

Figure 14-24 shows the average cell throughput both for UL and DL using various scheduling mechanisms, permutations, and feedback.




Figure 14-24: Average cell throughput for various schemes

WirelessMAN-OFDMA vs high-speed DL packet access (HSDPA)

A 2005 paper by Shin, et al., [B48] compares the capacity of a WiBro-compatible version of WirelessMAN-OFDMA (based on a preapproved draft of IEEE Std 802.16e) with that of HSDPA. The study concludes that the OFDMA approach has “much better performance.” In particular, it finds that the spectral efficiency of WirelessMAN-OFDMA is close to double that of HSDPA for the ITU VehA channel model and also for the ITU Pedestrian A (PedA) channel at 10 km/h [B30]. For the ITU PedA channel model at 3 km/h, the spectral efficiency of WirelessMAN-OFDMA is found to be about one third greater than that of HSDPA. The authors ascribe the WirelessMAN-OFDMA advantage to two main factors:

- **TDD vs FDD:** Both systems work within a system bandwidth of 10 MHz. However, the OFDMA system under study uses TDD (with a fixed 2/1 DL/UL ratio) with signal bandwidth of 8.3 MHz. HSDPA uses FDD carried in two 5 MHz channels, but its effective signal bandwidth is just 3.84 MHz times two. The wider bandwidth of OFDMA is naturally not all positive, as it can result in a shrinkage of the coverage area due to the 3.4 dB higher thermal noise. In a noise-limited scenario, this coverage shrink is estimated at 19%, but the real situation may be interference-limited in both cases.
- **Multipath performance:** As discussed in Chapter 3 and Chapter 11, OFDM is very robust to multipath due to the use of the cyclic prefix and the cyclical nature of the FFT. Multipath channels that do not exceed the cyclic prefix duration will not significantly deteriorate the system performance (provided the sampling is adequate). CDMA, on the other hand, typically makes use of a rake receiver to extract the multipath energy. This results in deteriorated performance. The paper by Shin reports as much as 40% HSDPA capacity loss going from a single-path (multipath-free) channel to a three-path channel. Naturally, the move away from conventional rake receivers to more advanced receiver designs provides a means to reduce that capacity loss.

Basic WirelessMAN-OFDMA PHY performance

This section reports on unpublished studies of the basic WirelessMAN-OFDMA PHY performance. It assumes 10 MHz channelization at 2.5 GHz with a 1024-FFT; a 1/8 cyclic prefix; and practical levels of phase noise, mixer I/Q imbalance, and frequency offset. The reported $E_s N_0$ is equivalent to the SNR per subcarrier. For the repetition codes, postdetection combining of soft decisions is employed. All simulations shown use the mandatory CC.

Figure 14-25 and Figure 14-26 present the CBLER for the OFDMA modulation using the ITU VehA 3 km/h channel model. The first figure represents ideal synchronization and channel estimation, whereas the second represents a practical system of moderate complexity. The poor performance of QPSK-3/4 is a result of the mandatory interleaver problem discussed in Chapter 12.




Figure 14-25: CBLER, UL PUSC, ITU VehA 3 km/h, CC, ideal




Figure 14-26: CBLER, UL PUSC, ITU VehA 3 km/h, CC, estimated

Figure 14-27 and Figure 14-28 provide similar data using the ITU VehA 120 km/h channel model. The ideal performance suffers only moderately as a result of the higher speeds, even for the higher modulation orders. However, the practical challenges of synchronization and channel estimation cause the performance at the higher modulation orders to degrade substantially, with error floors developing. For the lower order modulations, including the omitted repetition rates, the PHY is fairly robust to the rapidly changing channel.

Similar analysis for VehA 30 km/h channel shows no significant degradation compared to the VehA 3 km/h model, showing that the OFDMA PHY is substantially robust to practical speeds. On the other hand, the performance degrades substantially using the VehB 10 km/h model due the insufficient cyclic prefix duration compared to the impulse response in that model.




Figure 14-27: CBLER, UL PUSC, ITU VehA 120 Km/h, CC, ideal




Figure 14-28: CBLER, UL PUSC, ITU VehA 120 km/h, CC, estimated

Figure 14-29 shows the ideal performance using the optional CTC codec, which is the optional codec of choice within the WiMAX profiles. The improvement over the CC codec varies from 1 dB to 1.5 dB although it need be noted that in this analysis only the longest code word is used. Use of shorter code words can result in a loss of up to 2 dB (compared to the longest code word).




Figure 14-29: CBLER, UL PUSC, ITU VehA 3 km/h, CTC, ideal

Figure 14-30 shows the ideal performance of the DL modulations, including that of the DLFP. It is best to protect the DLFP since it constitutes a single point of failure within the frame.




Figure 14-30: CBLER, DL PUSC, ITU VehA 3 km/h, CC, ideal

In Figure 14-31, the performance of the DL repetition coding as a function of channel impulse response (CIR) is shown. This result is important to determine which repetition code can be used at the cell edge. As may be observed from the figure, the use of QPSK-1/4 (QPSK-1/2, repetition rate 2) or QPSK-1/8 (QPSK-1/2, repetition rate 4) has sufficient CIR performance to make usage at the cell edge feasible. The large gap between the solid (ideal synchronization) and dashed (practical synchronization) curves is the result of the general difficulty of achieving good synchronization under low signal to noise-plus-interference ratio, regardless of the method used.




Figure 14-31: CBLER, DL PUSC, ITU VehA 3 km/h, CC, ideal

Finally, Table 14-1 shows the cell ranges that may be achieved with the DL modulations with a 20 W transmitter, 10 dB backoff, 15 dB antenna gain, and a 10 dB noise figure. For this case, the mobile is assumed to have two antennas on which it performs MRC. Achievable cell ranges are shown both with and without a 10 dB shadowing margin using the Cost 231 Hata channel model [B11].

Table 14-1: Cell-ranges DL PUSC

Modulation/ code rate	Max. PHY throughput (Mbit/s)	SNR @ 0.01 CBLER (dB)	Cell range (m)	Cell range with fade margin (m)
QPSK-1/12	1.19	-1.1	1586	825
QPSK-1/8	1.79	0.7	1410	733
QPSK-1/4	3.57	2.0	1259	674
QPSK-1/2	7.14	6.0	997	512
QPSK-3/4	10.71	9.2	809	421
16-QAM-1/2	14.28	10.3	753	392
16-QAM-3/4	21.42	14.9	557	290
64-QAM-1/2	21.42	15.5	536	279
64-QAM-2/3	28.56	19.0	426	222
64-QAM-3/4	32.13	21.2	369	192

MIMO capacity

This section discusses the capacity gain achieved by the use of MIMO. The capacity is analyzed at link level for a full-buffer FTP stream in an OFDMA network with 19 cells, each having three sectors, using 10 MHz bandwidth at 2.5 GHz. The channel models are a mix of stationary/pedestrian, pedestrian, mobile, and highly mobile models in analogue to the 1xEV-DV evaluation methodology (see [B8]). Some capacity results, in megabits per second, are shown in Table 14-2, where the notation $m \times n$ indicates m transmitter chains and n on the receiver. Note that the results are indicative only of the relative capacity gain, as a full-buffer FTP analysis provides an overly optimistic result for achievable capacity. The use of 2x1 STC on the DL, for which no simulation data were available for this specific scenario, would be expected to result in values between those of 1x1 SISO and 2x2 MIMO, but relatively closer to the 2x2 MIMO results.

Table 14-2: Relative performance benefit of MIMO and virtual MIMO^a

DL/UL ratio	DL				UL		
	Reuse	1x1	2x2 MIMO	2x4 MIMO	1x2 MRC	1x2 V-MIMO	2x2 MIMO
1/2	1	3.80	7.97	11.76	3.20	7.04	6.72
	3	1.52	3.98	7.06			
1/1	1	5.75	12.08	17.83	2.40	5.28	5.04
	3	2.30	6.04	10.70			
2/1	1	7.67	14.00	20.67	1.60	2.40	3.36
	3	3.07	7.00	12.40			

^a Data courtesy of Nortel Networks.

In Table 14-3, the spectral efficiency and capacity are shown for various antenna configurations in the same system, with DL/UL ratio of 2/1 and using the ITU PedA 3 km/h channel model.

Table 14-3: Performance using MIMO^a

	1x1	1x2	2x2	2x4	4x2	4x4
(bit/s)/Hz per sector	1.2	1.8	2.8	4.4	3.7	5.1
Aggregate sector throughput (Mbit/s)	7.6	11.6	17.8	27.7	23.6	32.6

^a Data courtesy of Nortel Networks.

Chapter 15 Conformance and interoperability

Conformance standards and testing

In this chapter, we discuss the IEEE 802.16 conformance standards and the WiMAX Forum[®] interoperability and certification procedures. The conformance standards are essentially comprehensive test plans to evaluate whether a particular vendor's implementation meets the requirements defined in IEEE Std 802.16. The WiMAX Forum is an industry alliance, analogous to the Wi-Fi Alliance for IEEE Std 802.11, that defines interoperability tests and certifies IEEE 802.16 BSs and SSs that pass these tests.

THE WiMAX FORUM

By the end of 2000, even before the original IEEE Std 802.16-2001 was approved, it became clear that the standard would include a plethora of options. For instance, the high-frequency WirelessMAN-SC mode has literally more than 4000 possible combinations of FEC and modulation alternatives, while in practice four or five would suffice. While most options have at least one corresponding proponent who can argue for its benefits under certain circumstances, implementing all of the options would clearly be an onerous and expensive task. Conversely, if equipment vendors independently chose which options to implement, full interoperability would be precluded, and IEEE Std 802.16 would be a standard in name only. Systems would be, for all intents and purposes, proprietary through the choice of options. In March of 2001, the outline of Clause 12 was added to the IEEE 802.16 draft standard.

It also became clear that full interoperability would require proper conformance testing, lest two vendors pick the same profile but interpret it differently. In IEEE 802, standards rarely include test specifications; in most cases, they stop with functional specifications. In the 2000 time frame, intense

debate surrounded IEEE Std 802.16 versus ETSI BRAN HiperACCESS as the standard of choice for PMP broadband wireless access above 10 GHz. ETSI BRAN HiperACCESS was a simpler but less efficient standard than IEEE 802.16 WirelessMAN-SC. ETSI BRAN HiperACCESS advocates criticized IEEE Std 802.16, citing the plethora of options and the impact on interoperability. They also cited the ETSI mandate for a full set of test documentation based on the ISO/IEC 9646 standards series (identical to the ITU x.290 series) specifying test documentation. In response, several companies involved in IEEE Std 802.16 were determined to eliminate this as a source of discredit to IEEE Std 802.16 so the two standards could be compared on a head-to-head technical basis.

These companies decided to take the concept a step further and initiate a certification body and process modeled as a hybrid of Wi-Fi and GSM type approval. In April 2001, representatives of Nokia, Ensemble Communications, Harris Corporation, and Crosspan (a division of Raytheon) met in Antibes, France, alongside an ETSI BRAN HiperACCESS meeting in neighboring Sophia Antipolis; and the WiMAX Forum was born. Unlike the WiMAX Forum of today, the original group was concerned with single-carrier systems above 11 GHz. This was due to the facts that this aspect of IEEE Std 802.16 was much further developed than the lower frequency specifications and that it was ETSI BRAN HiperACCESS to which they were reacting.

By the way, “WiMAX” is derived from the expression *worldwide interoperability for microwave access*. Jay Klein, who chaired the WirelessMAN-SC PHY Task Group, has been credited with creating the name.

The initial task of the early WiMAX Forum was to develop system profiles for WirelessMAN-SC operation. These were submitted during the development of IEEE Std 802.16c, which specified detailed system profiles in Clause 12. Following draft development and balloting, these profiles, with minor changes, were approved; and IEEE Std 802.16c was approved in December 2002. The WirelessMAN-SC profiles are shown in Table 15–1.

Table 15–1: WirelessMAN-SC system profiles

Identifier	Description
profM1	Basic ATM MAC profile
profM2	Basic packet MAC profile
profP1	25 MHz channel PHY profile
profP1f	25 MHz channel PHY profile—FDD
profP1t	25 MHz channel PHY profile—TDD
profP2	28 MHz channel PHY profile
profP2f	28 MHz channel PHY profile—FDD
profP2t	28 MHz channel PHY profile—TDD

Once this task was accomplished, the next step was to deal with the issue of test specifications. With the aid of other companies such as Nera, Intracom, Hewlett-Packard, and Hughes Network Systems, the founders of the WiMAX Forum started to create the test specification necessary to be on par with the ETSI test specifications. Four documents were identified:

1. Protocol implementation conformance statement (PICS) proforma: A document that serves two purposes. First, it lists the features that are mandatory, optional, conditionally mandatory, forbidden, etc., for each of the system profiles. Second, it serves as a form that vendors fill out to specify which features they implement and for what sets or ranges of allowed values.
2. Test suite structure and test purposes (TSS&TP): A test plan for covering the features outlined in the PICS proforma.
3. Abstract test suite (ATS): Equipment-independent test procedures for implementing the tests identified in the TSS&TP.
4. Radio conformance test (RCT) specification: Tests for the radio portion of the system that could not be specified as protocol tests.

CONFORMANCE TEST STANDARDS FOR WIRELESSMAN-SC

The WiMAX Forum played a key role in the development of PICS proforma, TSS&TP, and RCT documents in IEEE Std 802.16. In each case, a new IEEE 802.16 project was proposed and initiated for each test specification, each to lead to an independent published standard. Once the project was underway, an open call for contributions was issued; in each case, a single proposal, developed within the WiMAX Forum, was received.

These proposals were unchallenged primarily because of the involvement of the same participants in both the WiMAX Forum and the IEEE 802.16 Working Group. Nonetheless, the documents proceeded through the official IEEE 802 process of working group review, working group letter ballot, and sponsor ballot, with comments addressed along the way. The result was three official IEEE standards: IEEE Std 802.16/Conformance01-2003 [B21], IEEE Std 802.16/Conformance02-2003 [B22], and IEEE Std 802.16/Conformance03-2004 [B23], each in accordance with ISO/IEC 9646.

By the time the RCT document was initiated, relations between companies participating only in ETSI BRAN HiperACCESS and those interested in both ETSI BRAN HiperACCESS and IEEE Std 802.16 had improved, and the ETSI BRAN HiperACCESS RCT was used as the foundation of the WirelessMAN-SC RCT document. Unfortunately, before the ATS document could be initiated, the bottom fell out of the market for high-frequency broadband wireless access equipment. Consequently, the WirelessMAN-SC ATS standards project was never initiated.

THE WiMAX FORUM'S MOVE TO LOWER FREQUENCIES

In April 2002, as the specifications for systems below 11 GHz were solidifying, entities interested in operation below 11 GHz began to join the WiMAX Forum. The first was the OFDM Forum in April, followed by Wi-LAN and Fujitsu in November 2002. Then, in January of 2003, the WiMAX Forum jumped to twelve "charter member" companies and, fueled by the efforts of Intel Corp., started expanding rapidly. The WiMAX Forum, with well over 300 member companies, is now certifying fixed-access WirelessMAN-OFDM systems through independent laboratory conformance

testing and overseeing interoperability "plug-fests." The WiMAX Forum is devoting great energy to the development of system profiles and test specifications for mobile systems based on the enhancements in IEEE Std 802.16e.

LOWER FREQUENCY PROFILES AND TEST SPECIFICATIONS

The WirelessMAN-OFDM, WirelessMAN-OFDMA, and WirelessMAN-SC PHY specifications were the first foray of IEEE Std 802.16 into the lower frequencies (less than 11 GHz). These were first defined in IEEE Std 802.16a. In late 2002, as IEEE Std 802.16a was nearing completion, the IEEE 802.16 Working Group opened the amendment project IEEE P802.16d, which was intended to develop profiles in support of the low-frequency modes. Eventually, IEEE P802.16d was dropped as a project to amend IEEE Std 802.16, replaced by a broader revision project that eventually led to IEEE Std 802.16-2004 [B20]. That revised standard does include the low-frequency profiles.

IEEE Std 802.16-2004 specifies profiles for all three PHY mode alternatives. However, for this fixed-access case, WirelessMAN-OFDM was of the greatest interest for two reasons:

1. The parallel ETSI BRAN HiperMAN standard initially supported a mode compatible with WirelessMAN-OFDM only.
2. The WiMAX Forum contributed only to the development of the WirelessMAN-OFDM and developed fixed-access interoperability tests only for that mode.

The low-frequency profiles are considerably more complex set than those for WirelessMAN-SC. In the case of WirelessMAN-OFDM, a system profile consists of four components: a MAC profile, a PHY profile, a duplexing selection, and a power class. The IEEE 802.16 standard defines two MAC profiles (PMP and mesh), six PHY profiles (1.75, 3.5, 7, 3, 5.5, and 10 MHz channel bandwidth, with the last one specified in the license-exempt case only), two duplexing alternatives (TDD and FDD), and five power classes.

In the case of WirelessMAN-OFDMA, only one MAC profile (PMP-based) is specified, along with nine PHY profiles (1.25, 3.5, 7, 8.75, 14, 17.5, 28,

10, and 20 MHz channel bandwidth, with the last two specified in the license-exempt case only), two duplexing alternatives (TDD and FDD), and four power classes.

The ATM CS is not included in either the WirelessMAN-OFDM or the WirelessMAN-OFDMA profiles. In both cases, RF profiles are mentioned, but not specified except in the license-exempt case.

The IEEE P802.16/Conformance04 project, to specify PICS proforma for the low-frequency modes, was initiated in March 2004. Draft 6, which entered IEEE-SA sponsor ballot in January 2006, includes no specification for WirelessMAN-SCa, which had lost support by the time the project got underway. The draft does include a detailed PICS specification for WirelessMAN-OFDMA. It should be noted that this PICS proforma concerns only fixed systems, not any mobile systems. In the case of WirelessMAN-OFDM, the draft simply makes normative reference to ETSI 102 385-1 V1.2.1, entitled "Broadband Radio Access Networks (BRAN); HiperMAN; Conformance testing for the Data Link Control Layer (DLC); Part 1: Protocol Implementation Conformance Statement (PICS) proforma." Since ETSI BRAN HiperMAN has long supported a PHY compatible with WirelessMAN-OFDM and since ETSI is recognized for its expertise in conformance test specifications, it is natural to defer to the ETSI standard on this issue. It is worth noting, however, that ETSI defers to IEEE standards as well. In fact, the ETSI test specifications have, in many cases, pointed not to ETSI air interface standards but to IEEE Std 802.16 for their references.

WiMAX FORUM CONFORMANCE TESTING FOR FIXED ACCESS

The only publicized industry activities related to the testing of conformance to IEEE Std 802.16 have been developed in the WiMAX Forum. In January 2006, the WiMAX Forum announced that four products (two BSs, one BS "solution," and one SS "solution") had been certified for 3.5 GHz operation following testing at its laboratory in Malaga, Spain. It also announced plans to test an additional 26 products. Protocol conformance, radio conformance, and basic interoperability were certified. Some additional capabilities, including QoS and security, were not tested. Certification testing of these features is

expected later in 2006. Testing of systems operating in the 5.8 GHz bands is also in development.

WiMAX FORUM AND MOBILE BROADBAND WIRELESS ACCESS

With the progress of the amendment project IEEE P802.16e, the WiMAX Forum developed an interest in this work also. The WiMAX Forum eventually came to the conclusion that it would strongly support the evolution of the IEEE 802.16 standard from fixed to mobile applications and would commit itself to the development of test specifications for mobile systems defined in IEEE Std 802.16e. Most of the WiMAX Forum effort on mobility has been directed at the WirelessMAN-OFDMA mode. Work to create the test specifications is well underway. This work is being undertaken jointly between ETSI and the WiMAX Forum based on agreement between the two. An activity related to the mobile enhancement of WirelessMAN-OFDM is also underway, but this has seen considerably less support among the member companies of the WiMAX Forum.

Chapter 16 Related standards

Other wireless standards with similar applications

This chapter opens by comparing the IEEE 802.16 (WirelessMAN) standard to the IEEE 802.11 (WLAN) standard. It next overviews progress in two IEEE 802 working groups, IEEE 802.20 and IEEE 802.22, that are engaged in developing standards, but have not at this time completed any. The chapter reviews some history and the status of related projects in ETSI's BRAN activity, briefly adding reports on the relation between the IEEE 802.16 Working Group and two other regional standardization activities: the Korean Telecommunication Technology Association (TTA) and the China Communications Standards Association (CCSA). We close the chapter with a review of the important relationships between IEEE Std 802.16 and the ITU, particularly those leading to the international recommendation of IEEE Std 802.16 through the ITU.

IEEE Std 802.11

The IEEE 802.11 standard defines MAC, PHY, and management protocols for WLANs. A LAN typically has a range on the order of 100 m and serves a space the size of a home, an office building, or a small campus. The distinction between LANs and MANs is especially important in the wireless case because the choices for MAC and PHY protocols and parameters essentially dictate the type of network that can be built. WLANs and wireless MANs have widely different requirements, and a MAC or PHY designed for one type of network may be unsuitable for the other.

Since its initial ratification in 1997, IEEE Std 802.11, and its later amendments, have become the foundation for a large and growing market. WLANs based on IEEE Std 802.11 are an essential network technology. With their standardization and subsequent widespread adoption in homes and enterprises, IEEE 802.11 devices—known as *Wi-Fi* to the general public, due

to the certification mark of the Wi-Fi Alliance—have become commodities in recent years. The following subsections summarize the IEEE 802.11 MAC and PHY and discuss the similarities and differences between IEEE Std 802.11 and IEEE Std 802.16.

IEEE 802.11 MAC

Medium access control layer (MAC)

The IEEE 802.11 MAC is based on the carrier sense multiple access with collision avoidance (CSMA/CA) protocol, in which IEEE 802.11 devices primarily follow a “listen before talk” rule, with random backoff to avoid collisions. The fundamental premise of CSMA is that all devices sharing the channel can hear each other. Most IEEE 802.11 devices have omnidirectional antennas and, in the local area of primary application, can hear each other. Some mechanisms [e.g., the request to send and clear to send (RTS/CTS) mechanism] do exist, albeit at a higher overhead, to partially address the “hidden node” case in which some nodes are within range of the AP (analogous to an IEEE 802.16 BS), but not within range of each other.

The IEEE 802.11 CSMA/CA protocol is similar to the CSMA/CD protocol of Ethernet. In the wireless case, carrier sensing is possible, except in the hidden node situation. However, collision detection (the “CD” of Ethernet) is not. An Ethernet node continues to sense the medium during transmission and is thereby able to detect collisions. IEEE 802.11 devices are half-duplex and, therefore, cannot listen while transmitting. In fact, given the fact that IEEE Std 802.11 uses the same frequency for UL and DL, it would be a significant challenge to design an IEEE 802.11 device that could accurately sense the medium for collisions during transmission.

In lieu of collision detection, IEEE 802.11’s collision avoidance process uses a physical carrier sense and a virtual carrier sense mechanism are used to avoid potential collisions. The physical carrier sense mechanism listens for the presence of any other transmissions on the channel before attempting a transmission of its own. The virtual carrier sense mechanism utilizes the explicit indication from another transmitter that essentially reserves the channel for a specific amount of time.

Since CSMA/CA is a fully distributed scheme with no central coordinator, collisions are still possible. The absence of collision detection makes it essential to use an acknowledgment scheme to ensure successful reception. IEEE Std 802.11 uses immediate MAC acknowledgments to confirm that an IEEE 802.11 frame has reached its destination. This is essentially a stop-and-wait ARQ scheme with synchronous acknowledgment, where the transmitter waits for the acknowledgment before attempting the next transmission or repeating the previous one. In the IEEE 802.11 MAC, the immediate acknowledgment is mandatory for all unicast frames⁷. Note that, in IEEE Std 802.11, the word *frame* is used in both the MAC sense (as a single MAC PDU, carrying data, management, or control content) and in the PHY sense (as a unit of PHY transmission) because each PHY frame carries one MAC frame. In contrast, IEEE Std 802.16 uses *frame* only as a PHY transmission unit; an IEEE 802.16 frame may carry one or more MAC PDUs or partial MAC PDUs. Although IEEE Std 802.11 supports fragmentation, it is optional and seldom implemented by IEEE 802.11 devices. The optional fragmentation is not dynamic and uses a fixed, configurable fragment size.

The duplexing method used in IEEE Std 802.11 is TDD, which is half-duplex by definition. However, in IEEE Std 802.11, no centralized coordinator allocates time slots; instead, transmission decisions are taken independently at each transmitter. The IEEE 802.11 AP, which is analogous to the IEEE 802.16 BS, has no special rules for accessing the media. The AP has to contend for the media just like any other IEEE 802.11 client communicating with it.

MAC overhead

The IEEE 802.11 MAC requires a minimum of 24 bytes of MAC header information per frame. Note that an IEEE 802.11 MAC frame can carry only one higher layer SDU; i.e., multiple higher layer SDUs such as IP packets cannot be packed into a single MAC frame. For example, each 40 byte TCP acknowledgment would require at least 42 bytes of MAC overhead (24 bytes of MAC header + 4 bytes of CRC + 14 bytes of acknowledgment) in addition to the per-frame PHY overhead. The PHY rates must be considered in this

⁷ IEEE Std 802.11e™-2005 includes an option to omit immediate acknowledgments in favor of delayed acknowledgments.

MAC discussion because the IEEE 802.11 acknowledgment is typically sent at one of the more robust PHY rates. A large frame sent at a lower rate can occupy the channel for a significant amount of time.

The transmission rate to be used is also chosen independently by the transmitters. The standard does not specify an algorithm to choose the transmission rate, and vendors implement their own rate-selection algorithm. However, an IEEE 802.11 AP can restrict the number of transmission rates that can be used in the network.

The IEEE 802.11 MAC supports two alternative channel access modes, the distributed coordination function (DCF) and the optional point coordination function (PCF). The DCF is the fully distributed scheme discussed in the previous paragraphs. PCF offers some centralized polling, although it is not scalable and the polling does not take the frame size or transmission rate into account. For these reasons, PCF is not widely supported and is rarely used.

MAC summary

The CSMA/CA protocol with DCF works reasonably well in a WLAN environment. However, it is not without problems in some situations. The following is a partial list of concerns in CSMA/CA WLAN:

- **Nondeterminism:** CSMA/CA is nondeterministic, and the stop-and-wait ARQ can make successful reception significantly unpredictable if frames need to be resent often. The situation can become drastically worse as the network load increases. Deterministic behavior is required for many QoS-sensitive applications.
- **Hidden nodes:** Two CSMA devices that cannot hear each other may simultaneously initiate transmission. A collision will result. Retransmission will take time and waste future transmission opportunities. This problem is somewhat addressed by the RTS/CTS-based reservation protocol, but its effectiveness declines with a large number of hidden nodes.
- **Near-far problem:** The near-far problem refers to a scenario in which devices closer to an IEEE 802.11 AP can overpower devices farther away, thus unfairly affecting the performance of those devices.

- **Slowest node:** Since transmission decisions are taken independently, one or more nodes choosing to transmit at the lowest rate will, by using a less efficient communication scheme, occupy a disproportionate fraction of airtime. This adversely affects other devices that can communicate at a higher rate.
- **Capture effect:** The capture effect is a fundamental problem in any CSMA protocol, including wired networks such as Ethernet. Since the CSMA devices make independent decisions on transmissions and backoff, the device that successfully completes a transmission resets its contention window and starts afresh for the next contention. This provides an unfair advantage to the device with a successful transmission when multiple devices are contending for access.
- **Overhead:** In general, the IEEE 802.11 MAC has high overhead, especially for smaller frames such as voice or TCP acknowledgments.

IEEE 802.11 PHY

IEEE Std 802.11 has standardized several PHY modes, including the following:

- Frequency-hopping spread spectrum (FHSS), up to 2 Mbit/s
- Direct sequence spread spectrum, up to 11 Mbit/s, in IEEE Std 802.11b™
- OFDM, up to 54 Mbit/s, in IEEE Std 802.11a™ and IEEE Std 802.11g™

The quoted data rates are raw PHY rates. For instance, the maximum IEEE 802.11a PHY rate is 54 Mbit/s, but the highest actual UDP throughput with maximum packet size is only about 30 Mbit/s due to the MAC and PHY overheads.

The OFDM PHY of IEEE Std 802.11a and IEEE Std 802.11g is based on a 64-FFT. The channel size is approximately 20 MHz. The maximum delay spread is about 800 ns, which is sufficient for a LAN with reasonable multipath.

IEEE 802.11 extensions

The IEEE 802.11 Working Group has recently developed and is currently developing many amendment projects, including the following:

- **IEEE Std 802.11e:** IEEE Std 802.11e-2005 defines MAC extensions to CSMA/CA in order to improve QoS. Some MAC efficiency improvements are also included. The QoS extensions improve both DCF and PCF by defining a new hybrid coordination function (HCF), which includes enhanced distributed channel access (EDCA) and the HCF coordinated channel access (HCCA) functions. Both EDCA and HCCA schemes are backward compatible with IEEE 802.11 DCF and frame formats. HCCA offers some centralized scheduled functions. Some of the efficiency improvements include the option of not having immediate acknowledgments and allowing block (i.e., delayed) acknowledgments. IEEE Std 802.11e works for any of the underlying PHY modes.
- **IEEE P802.11n:** The primary objective of the amendment project IEEE P802.11n is to improve the throughput of IEEE Std 802.11 beyond 100 Mbit/s, using techniques such as SDMA and MIMO. Both PHY and MAC enhancements are under consideration. This project is expected to make use of most of the IEEE 802.11e features and to define additional efficiency mechanisms. The project is expected to achieve most of the throughput improvements by doubling the channel size. Completion of the standard is expected in 2007.
- **IEEE P802.11p:** The objective of the amendment project IEEE P802.11p is to support communication between vehicles, and from vehicles to the roadside, while operating at speeds up to 200 km/h for communication ranges up to 1000 m. This is specifically targeted for the 5 GHz bands and in all forms of surface transportation. Both MAC and PHY enhancements are being considered, including a smaller channel size of 10 MHz.
- **IEEE P802.11s:** The amendment project IEEE P802.11s is working on defining a mesh MAC extension to IEEE Std 802.11. The objective is to use the existing IEEE 802.11 addressing format (especially the four-address format) to fully define a multihop network with autoconfiguration capabilities.

Using IEEE Std 802.11 as a MAN

Although IEEE Std 802.11 and its extensions were designed to operate in a LAN environment, many IEEE 802.11 systems, sometimes with modifications, are being operated in long-range outdoor MAN environments. To extend the range, most of these systems make use of high-gain directional antennas to support clients communicating with a (standard or modified) IEEE 802.11 AP. This situation massively exacerbates the hidden node problem, forcing every terminal to be hidden from every other. MAC customization becomes particularly important. Many proprietary and nonstandard extensions to IEEE Std 802.11 have been applied, including the following:

- **IEEE 802.16-like MAC over IEEE 802.11 PHY:** Some IEEE 802.11 chipsets allow an implementor to use the IEEE 802.11 PHY, but bypass the IEEE 802.11 MAC. Some vendors have used such an approach to implement a TDMA scheme. However, the PHY overhead and some of the MAC overhead cannot be eliminated using this approach. Similarly, the limitations of the IEEE 802.11 PHYs, such as the limited ability to address the delay spread typical of long-range outdoor environments, cannot be eliminated either.
- **Modified IEEE 802.11 MAC:** Some of the proprietary modifications include modification of basic IEEE 802.11 timing or channel access parameters, the turning off of acknowledgments, and modification of the acknowledgment timeout. The IEEE 802.11 standard requires that the immediate acknowledgment be received within a specific time. This time is sufficient to deal with smaller propagation delays in a LAN. However, long-range communication such as a MAC requires longer propagation delays.
- **FDD:** Some systems use an FDD-like approach, with communications in opposite directions using different IEEE 802.11 channels.

Quantitative comparison of IEEE Std 802.11 and IEEE Std 802.16

In general, the IEEE 802.11 and IEEE 802.16 technologies are complementary, as one is targeted for LANs and the other for MANs. However, we need to summarize the differences between the two standards in

order to stress the differences in the target markets, which is reflected in the design choices made. Table 16-1 shows some of these differences.

Table 16-1: Comparison of IEEE Std 802.11 and IEEE Std 802.16

Feature	IEEE Std 802.11	IEEE Std 802.16
Medium access	CSMA/CA Some TDMA-like functions in IEEE Std 802.11e	TDM/TDMA OFDMA (optional)
Channel size	~22 MHz (IEEE Std 802.11b) 20 MHz (IEEE Std 802.11a and IEEE Std 802.11g) 10 MHz (IEEE Std 802.11j™)	1.25–28 MHz
Maximum PHY data rate	54 Mbit/s	72 Mbit/s (10 MHz channel)
Maximum (bit/s)/Hz	~2.7	~5
Delay spread tolerance	Up to 800 ns	Up to 10 μ s
Minimum MAC overhead	28 bytes (header + CRC)	6 bytes
QoS	Limited QoS support (up to eight priorities per system) in IEEE Std 802.11e	Per-connection QoS

Although IEEE Std 802.11e supports a form of QoS, with eight priorities (or classes), the addition of QoS to IEEE Std 802.11 is an afterthought. On the other hand, the IEEE 802.16 MAC is a QoS-centric MAC that has been designed with QoS as an integral part of the MAC functions. Moreover, the IEEE 802.16 MAC is much more efficient than IEEE Std 802.11 for outdoor applications, with packing, ARQ, dynamic fragmentation, and smaller header overhead. The problems associated with the IEEE 802.11 CSMA/CA protocol, such as hidden nodes, capture effect, and the near-far problem, are eliminated by the use of a centrally scheduled IEEE 802.16 MAC with TDM/TDMA (and optionally OFDMA).

Ultimately, IEEE Std 802.11 and IEEE Std 802.16 are two parts of a team that can form the basis of a flexible network with an extensive range of applicability.

IEEE 802.20 WORKING GROUP

The IEEE 802.20 Working Group, chartered to develop a standard for mobile broadband access supporting vehicular speeds, first met formally in March 2003. The goal is to support operation in licensed bands below 3.5 GHz allocated to the mobile service. The main performance targets given in the IEEE P802.20 PAR are shown in Table 16-2.

Table 16-2: IEEE 802.20 performance targets

Characteristic	Target value
Mobility	Vehicular mobility classes up to 250 km/h (as defined in ITU-R M.1034-1)
Sustained spectral efficiency	>1 (bit/s)/Hz per cell
Peak user data rate	> 1 Mbit/s in paired 1.25 MHz channel
Peak aggregate data rate per cell in the DL	>4 Mbit/s in 1.25 MHz channel
Peak aggregate data rate per cell in the UL	> 800 kbit/s 1.25 MHz channel
Airlink MAC round-trip time	< 10 ms
Duplex	FDD, TDD
Channel bandwidth	1.25 MHz, 5 MHz

At the moment, very little can be said about the technology itself, and whether it meets the targets, as the group has addressed mostly the technology selection process and system requirements rather than developing draft specifications. The working group first considered proposals for draft text in

November 2005, but the process is in its early stages. It is too soon to speculate on the content of the future standard.

IEEE 802.22 WORKING GROUP

The IEEE P802.22 PAR on wireless regional area networks (WRANs) was approved in September 2004. The PAR covers “Cognitive Wireless RAN Medium Access Control (MAC) and Physical Layer (PHY) specifications of fixed point-to-multipoint wireless regional area networks operating in the VHF/UHF TV broadcast bands between 54 MHz and 862 MHz.” This range of operation is based on U.S. frequency allocations and implies 6 MHz channelization. For other scenarios, the broader frequency range of 41 MHz to 910 MHz may be considered a target, with 6 MHz, 7 MHz, or 8 MHz channelization. However, the PAR specially addresses U.S. rules promulgated by the FCC.

The aim of the project is to develop a fixed broadband access standard for use in licensed but unused broadcast television spectra. Such a network is envisioned to have a long range, yet prevent interference with incumbent licensed services within the same spectrum. A primary objective is to provide rural, low-population markets with performance levels similar to those of broadband access technologies servicing urban and suburban areas. The WRAN must support QoS, enabling simultaneous support for data, voice, and audio/video applications, and must be available 99.9% of the time.

The target markets to be addressed by such a system are residential, small office/home office (SOHO), small business, multitenant dwellings, and campuses. IEEE P802.22 is intended to provide these customers with capabilities similar to those provided by digital subscriber line (ADSL) and cable modems, but more economically in sparsely populated rural settings. The system is expected to have a typical range of 33 km, with a maximum range of 100 km. The minimum peak throughput at cell edge is required to be 1.5 Mbit/s per subscriber in the DL and 384 kbit/s per user in the UL. To achieve this, the PAR proposes a spectral efficiency goal of 5 (bit/s)/Hz.

Use of the VHF/UHF TV broadcast frequency range is possible in near-LOS and NLOS situations. In the rural settings targeted, operation may include

partial or complete blockage by foliage, contributing to multipath and attenuation of the signal. We may expect that macrodiversity, repeaters, and other techniques will be combined with the natural propagation characteristics of the frequency band to solve the issues of range, multipath, and blockage.

The problems faced by systems operating in this spectrum are compounded by the fact that they are operating in an license-exempt mode in spectrum that technically is licensed to other uses. These other uses are not limited to broadcast TV services that would be relatively easy to map and avoid. They also include FCC Part 74 devices, such as licensed wireless microphones, wireless intercoms, etc. Regulations require that license-exempt users detect these licensed users and avoid interfering with them by moving to a different frequency. This may, however, be very challenging because some of the licensed users are transient and low power in nature.

To better ensure the proper avoidance of incumbents, designers envision that subscriber devices (and repeaters) will be in a master-slave relationship with the BS, with the BS providing centralized power and spectrum management and centralized scheduling control. They also imagine distributed sensing of the RF environment by the subscriber devices for the purpose of detecting incumbents, with the sensing also controlled by the BS.

In terms of services supported, the clear intent of the IEEE P802.22 functional requirements document (see [B46]) is to support variable-length IP-based services with some level of QoS.

There is currently some interest in using a version of IEEE Std 802.16, modified to provide the intended detection and avoidance of incumbents, in order to meet the needs of the IEEE P802.22 PAR.

ETSI BRAN

Within the European Telecommunications Standards Institute (ETSI), the Broadband Radio Access Networks (BRAN) Technical Committee has been active since 1997. Its three primary activities include ETSI BRAN HiperLAN/2 (a WLAN standard that is, in effect, defunct) and two broadband wireless access standards: ETSI BRAN HiperACCESS and ETSI BRAN HiperMAN.

The IEEE 802.16 Working Group has had an active liaison relationship with ETSI BRAN since 1999; for example, the two groups have exchanged over 60 documents and reports. The initial collaboration strove for harmonization between the WirelessMAN-SC and ETSI BRAN HiperACCESS projects, in which ETSI was the first mover. Although this effort made some progress, it ultimately failed. Later, the attention turned to the lower frequency work, in which IEEE Std 802.16 went first. In this case, the harmonization results were remarkably successful. ETSI BRAN HiperMAN, as discussed below, is compatible with the WirelessMAN-OFDM and WirelessMAN-OFDMA modes in IEEE Std 802.16.

ETSI BRAN HiperACCESS

ETSI BRAN HiperACCESS defines PMP broadband wireless for use in the frequency bands between 11 GHz and 66 GHz. In this respect, it attempts to fill the same niche as IEEE 802.16 WirelessMAN-SC.

The ETSI BRAN HiperACCESS standard was developed by many of the same participants involved in creating WirelessMAN-SC. Some parties, however, participated in only one. The result was less harmonization than would ultimately have been desirable. Both standards assume LOS operation and specify a single-carrier PHY. Many other similarities exist also. However, the two also have significant differences and are not compatible.

ETSI BRAN HiperACCESS shares the following features with IEEE 802.16 WirelessMAN-SC:

- Single-carrier modulation, with QPSK, 16-QAM, and 64-QAM
- Similar FEC
- Same basic request/grant scheme
- Same CoSs and QoS concepts
- Same basic ranging, power control, and PHY maintenance
- Similar UL and DL MAP structure
- Similar frame structure, including support for TDD, FDD, and H-FDD
- Similar RCT specification

ETSI BRAN HiperACCESS differs from IEEE 802.16 WirelessMAN-SC in the following ways:

- Fixed-length packet ATM cell transport only
- No packing
- No fragmentation
- Far fewer options of FEC combinations (a few options are defined, tailored for the size of an ATM cell)
- No incremental BW requests
- No piggybacked BW requests

The result was a standard that is simpler to implement than WirelessMAN-SC, but considerably less efficient (even for ATM cells) and not forward looking to IP as the preferred network protocol.

ETSI BRAN HiperMAN

When ETSI BRAN initiated the HiperMAN activity to consider fixed broadband wireless access below 11 GHz, the amendment project IEEE P802.16a was well on its way to adding the new PHY specifications WirelessMAN-OFDM, WirelessMAN-OFDMA, and WirelessMAN-SCa, all operating under the IEEE 802.16 MAC, first defined in IEEE Std 802.16-2001. Thanks to active cooperation between the IEEE 802.16 Working Group and the ETSI BRAN HiperMAN activity, a unified solution was obtained. One key player in this success was Mariana Goldhamer, who served as the IEEE 802.16 Working Group's liaison official to ETSI BRAN while also chairing the ETSI BRAN HiperMAN activity and later serving as vice chair of the ETSI BRAN Technical Committee. Another key player was Nico van Waes, the technical editor of the IEEE 802.16a and ETSI BRAN HiperMAN drafts as well as the area coordinator (ETSI terminology for chair) of ETSI BRAN HiperMAN during that period.

Rather than adapting the MAC from ETSI BRAN HiperACCESS, the ETSI BRAN HiperMAN group came to the conclusion that it would instead adopt the IEEE 802.16 MAC. However, it sought a single PHY solution, rather than three of them. It came to choose WirelessMAN-OFDM, eventually supporting a standard that was a subset of WirelessMAN-OFDM. The ETSI project was

not passive in the collaboration; it contributed ideas and comments to IEEE Std 802.16 during the refinement of that standard. Notably, ETSI moved first to specify UL subchannelization; this was not added into WirelessMAN-OFDM until IEEE Std 802.16-2004 [B20].

More recently, in 2005, the scope of the ETSI BRAN HiperMAN project was extended to include nomadic wireless access. At this stage, ETSI BRAN HiperMAN moved to extend its support of IEEE Std 802.16 and incorporated not only WirelessMAN-OFDM but also WirelessMAN-OFDMA.

As discussed in Chapter 15, ETSI is very active in the development of conformance test specifications for IEEE Std 802.16, particularly through its agreement with the WiMAX Forum. ETSI conformance test documents have referenced IEEE Std 802.16 as their source standards. IEEE Std 802.16 has already moved to accept the notion of making normative reference to ETSI conformance test documentation.

OTHER REGIONAL STANDARDS ACTIVITIES

Beyond its active relationship with ETSI, the IEEE 802.16 Working Group has developed and maintained relationships with some other regional organizations that are interested in broadband wireless access standardization.

Korean Telecommunication Technology Association (TTA) and WiBro

The Korean TTA approached the IEEE 802.16 Working Group in January 2004 with information concerning its effort to develop a parallel standard in the PG05 project, later renamed PG302. Unlike the ETSI BRAN interest, which was on fixed access, the TTA focus was on mobile access. Also, in contrast to ETSI BRAN HiperMAN's interest in WirelessMAN-OFDM, it was clear that the TTA focus was on WirelessMAN-OFDMA. Early in the process, it appeared that the TTA was headed toward a standard similar to, but different from, the WirelessMAN-OFDMA that was eventually approved in IEEE Std 802.16e. However, a number of letters and reports were exchanged, and meetings were held to coordinate activity. Eventually, the two projects began to see significant alignment.

In July 2004, the Korean Ministry of Information and Communication announced that service in the 2.3 GHz spectrum, which had been set aside for portable Internet service, "must comply with IEEE 802.16-2004 and IEEE 802.16e/Draft3 or later versions." The Korean regulations also stipulate some additional specifications, including use of the WirelessMAN-OFDMA mode with a 1024-FFT. The Korean government named this service *WiBro*, for wireless broadband. It is important to understand that WiBro is a service, not a technology. The regulations required that the technology be WirelessMAN-OFDMA.

In retrospect, the IEEE 802.16 Working Group's decision to support multiple modes turns out to have been well justified. The working group, in trying to develop a single standard for worldwide use, had a major challenge because the world includes many diverse interests. In this case, the Europeans leaned toward an OFDM solution and the Koreans toward OFDMA. The multimode decision included in IEEE Std 802.16a formed a basis to satisfy both.

China Communications Standards Association (CCSA)

The CCSA has been pursuing broadband wireless access standards through Working Group 3 of its Technical Committee 5. CCSA has been communicating actively with the IEEE 802.16 Working Group since IEEE Std 802.16's Session #31, which was held in Shenzhen, China, in May 2004. Since then, the organizations have remained in contact through letters, reports, and liaison exchanges. In November 2005, CCSA reported a number of standards projects in fixed access related to IEEE Std 802.16, including test specifications. Work regarding mobile broadband wireless access was at an earlier stage.

INTERNATIONAL TELECOMMUNICATIONS UNION (ITU)

Historically, some of the IEEE 802 standards have been entered into the more formal arena of "international" standardization through IEEE 802's engagement with Joint Technical Committee 1 (JTC1), the committee on information technology standards administered by two private Geneva-based organizations, the International Organization for Standardization (ISO) and the International Electrotechnical Commission (IEC). Although the original

collaborations covered only wired networks, the partnership was extended to wireless networks also by the adoption of IEEE Std 802.11 as ISO/IEC 8802-1 in 1999.

In spite of the successful relationship between IEEE 802 and ISO/IEC JTC1, the IEEE 802.16 Working Group has never shown an interest in following that precedent. The working group has always recognized the value of engaging with the formal international process in Geneva. However, instead of ISO/IEC, IEEE Std 802.16 looks to partner with the ITU, particularly the ITU Radiocommunications Sector (ITU-R). This is partly because IEEE Std 802.16 is the only IEEE 802 standard expected to operate significantly in licensed spectra, the administration of which is significantly dependent on the ITU. It is also because the ITU has always been a focal point of the telecommunications industry. IEEE Std 802.16 is a convergent technology, drawing significantly from the data communications community, but targeting applications that have historically been supported by the telecommunications establishment. Many of the potential customers for IEEE 802.16 systems have a natural home in ITU. The IEEE 802.16 community naturally seeks to engage that community and encourage its participation.

From the beginning, IEEE Std 802.16 has looked to engage with ITU. The original IEEE 802.16 PAR, submitted in March 1999, in answering the question "Is this standard planned for adoption by another international organization?" responded "Yes," referencing ITU. Since then, IEEE 802.16 PARs have done so consistently.

Central to building the IEEE 802.16 Working Group's relationship with ITU-R was Dr. José Costa, who has served since Session #1 in 1999 as the working group's ITU-R liaison official. Dr. Costa originally helped to connect the working group with ITU-R's Joint Rapporteurs Group 8A/9B, on Wireless Access Systems, where Dr. Costa served as one of two principle rapporteurs.

The relationship strengthened significantly in October 2003, when ITU-R named IEEE as a Sector Member, under the same membership classification as ISO. Shortly before, the ITU-R's Strategy and Policy Unit had published its seminal document *The Birth of Broadband* [B28], which made numerous references to the role of IEEE Std 802.16, particularly regarding the expansion of Internet access in rural and developing areas. ITU, perhaps as a

consequence, invited the IEEE 802.16 Working Group chair to speak at its major conference, ITU Telecom World, in Geneva during October 2003. During that meeting, the working group chair, with the assistance of ITU-R Counsellor Fabio Leite, met with staff and various study group officials, discussing opportunities to develop the relationship and, in particular, on drafting new ITU-R recommendations based on the IEEE 802.16 standard and its amendments, which were seen to be valuable because of ITU-R's "global approach and visibility." Following those discussions, the working group began to pursue contacts with several ITU study groups, including some in ITU's Telecommunications Bureau (related to network access and cable modem technology).

In November 2003, the IEEE 802.16 Working Group followed up these discussions with a letter to ITU-R indicating its support for the idea of developing ITU-R recommendations referring to IEEE Std 802.16. This work was slightly delayed by the termination of Joint Rapporteurs Group 8A/9B. However, with the assistance of Dr. Costa (who had assumed the chairmanship of Working Party 8A), the work progressed. IEEE, using its ITU-R membership, contributed a series of documents to Working Party 9B, coordinated with ETSI, on the development of a recommendation on "radio interface standards for broadband wireless access (BWA) systems in the fixed service operating below 66 GHz," pointing to IEEE Std 802.16 and the compatible ETSI BRAN HiperMAN standard. After many discussions and coordination actions, Study Group 9 approved this recommendation in December 2005. The ITU-R recommendation awaits a formal written consultation of the member administration in mid-2006.

In March 2005, the IEEE contributed a parallel proposal to ITU-R Working Party 8A, proposing a preliminary draft new recommendation on "radio interface standards for broadband wireless access systems in the mobile service operating below 6 GHz." The proposal would point to IEEE Std 802.16, including the IEEE 802.16e mobility amendment. The proposal has not progressed rapidly in Working Party 8A, mainly because supporters of a number of alternative technologies have become vocal. It is far from certain where this will lead.

Appendix A IEEE 802.16 headers, subheaders, and management messages

The list of IEEE 802.16 MAC headers, subheaders, and MAC management messages is provided here for quick reference. Table A-1 shows the list of MAC headers, subheaders, and special payloads.

Table A-1: MAC headers, subheaders and special payloads

Description	Size in bytes
Generic MAC header	6
BW request header	6
Fragmentation subheader (FSH)	1
FSH (ARQ)	2
FSH (Extended)	2
Grant management subheader (GMSH)	2
Packing subheader (PSH)	2
PSH (ARQ)	3
PSH (Extended)	3
Mesh subheader (MSH)	2
Fast-feedback allocation subheader (FFSH)	1

Table A-2 lists the management messages and the type of connections that may be used to send them.

Table A-2: Management messages

Type	Name	Description	Connection
0	UCD	UL channel descriptor	Fragmentable Broadcast
1	DCD	DL channel descriptor	Fragmentable Broadcast
2	DL-MAP	Downlink access definition	Broadcast
3	UL-MAP	Uplink access definition	Broadcast
4	RNG-REQ	Ranging request	Initial Ranging or Basic
5	RNG-RSP	Ranging response	Initial Ranging or Basic
6	REG-REQ	Registration request	Primary Management
7	REG-RSP	Registration response	Primary Management
8		Reserved	
9	PKM-REQ	Privacy key management request	Primary Management
10	PKM-RSP	Privacy key management response	Primary Management
11	DSA-REQ	Dynamic service addition request	Primary Management
12	DSA-RSP	Dynamic service addition response	Primary Management
13	DSA-ACK	Dynamic service addition acknowledgment	Primary Management
14	DSC-REQ	Dynamic service change request	Primary Management

Table A-2: Management messages (Continued)

Type	Name	Description	Connection
15	DSC-RSP	Dynamic service change response	Primary Management
16	DSC-ACK	Dynamic service change acknowledgment	Primary Management
17	DSD-REQ	Dynamic service deletion request	Primary Management
18	DSD-RSP	Dynamic service deletion response	Primary Management
19		Reserved	
20		Reserved	
21	MCA-REQ	Multicast assignment request	Primary Management
22	MCA-RSP	Multicast assignment response	Primary Management
23	DBPC-REQ	DL burst profile change request	Basic
24	DBPC-RSP	DL burst profile change response	Basic
25	RES-CMD	Reset command	Basic
26	SBC-REQ	SS basic capability request	Basic
27	SBC-RSP	SS basic capability response	Basic
28	CLK-CMP	SS network clock comparison	Broadcast
29	DREG-CMD	De/Re-register Command	Basic
30	DSX-RVD	DSx received message	Primary Management

Table A-2: Management messages (Continued)

Type	Name	Description	Connection
31	TFTP-CPLT	Config file TFTP complete message	Primary Management
32	TFTP-RSP	Config file TFTP complete response	Primary Management
33	ARQ-Feedback	Stand-alone ARQ Feedback	Basic
34	ARQ-Discard	ARQ Discard	Basic
35	ARQ-Reset	ARQ Reset	Basic
36	REP-REQ	Channel measurement report request	Basic
37	REP-RSP	Channel measurement report response	Basic
38	FPC	Fast power control	Broadcast
39	MSH-NCFG	Mesh network configuration	Broadcast
40	MSH-NENT	Mesh network entry	Basic
41	MSH-DSCH	Mesh distributed schedule	Broadcast
42	MSH-CSCH	Mesh centralized schedule	Broadcast
43	MSH-CSCF	Mesh centralized schedule configuration	Broadcast
44	AAS-FBCK-REQ	AAS feedback request	Basic
45	AAS-FBCK-RSP	AAS feedback response	Basic
46	AAS_Beam_Select	AAS beam select	Basic
47	AAS_BEAM_REQ	AAS beam request	Basic
48	AAS_BEAM_RSP	AAS beam response	Basic
49	DREG-REQ SS	SS deregistration message	Basic
50–255		Reserved	

Bibliography

[B1] Alamouti, S. M., "A simple transmit diversity technique for wireless communications," *IEEE Journal on Selected Areas of Communication*, vol. 16, pp. 1451–1458, Oct. 1998.

[B2] Alexiou, A., and Haardt, M., "Smart Antenna Technologies for Future Wireless Systems: Trends and Challenges," *IEEE Communications Magazine*, vol. 42, no. 9, pp. 90–97, Sept. 2004.

[B3] Ayanoglu, E., Eng, K. Y., and Karol, M. J., "Wireless ATM: Limits, Challenges and Proposals," *IEEE Personal Communications*, Aug. 1996.

[B4] Anderson, H. R., *Fixed Broadband Wireless System Design*, John Wiley & Sons, 2003.

[B5] Ball, C. F., Humburg, E., Ivanov, K., and Treml, F., "Performance analysis of IEEE 802.16 based cellular MAN with OFDM-256 in mobile scenarios," *Proceedings of IEEE Vehicular Technology Conference 2005-Spring*, vol. 3, pp. 2061–2066, May 2005.

[B6] Bertsekas, D., and Gallager, R., *Data Networks*, Prentice Hall, 1992.

[B7] Bing, B., *Broadband Wireless Access*, Kluwer Academic Publishers, 2000.

[B8] C50-20010820-026, "1xEV-DV Evaluation Methodology Addendum [V6]," July 2001, (http://ftp.3gpp2.org/TSGC/Working/2001/TSG-C_0108/TSG-C-0801-Portland/WG5/C50-20010820-026%201xEV-DV-Evaluation-Methodology-Addendum-V6.doc).

[B9] Chandran, S. R., "A Selective Repeat ARQ Scheme for Point-to-Multipoint Communications and its Throughput Analysis," *ACM SIGCOMM Conference on Communications Architecture and Protocols*, 1986.

- [B10] Cicconetti, C., Lenzini, L., Mingozzi, E., and Eklund, C., "Quality of Service Support in IEEE 802.16 Networks", *IEEE Network*, March/April 2006.
- [B11] COST Action 231, "Digital mobile radio towards future generation systems, final report," tech. rep., European Communities, EUR 18957, 1999.
- [B12] Doron, A., et al., "Problem in Interleaver and Permutation Combination in OFDMA," *IEEE C802.16maint-05/068r23*, July 2005.
- [B13] Eklund, C., Marks, R. B., Stanwood, K. L., and Wang, S., "IEEE Standard 802.16: A Technical Overview of the WirelessMAN Air Interface for Broadband Wireless Access," *IEEE Communications Magazine*, pp. 98–107, June 2002.
- [B14] ETSI TS 101 761-1 v1.2.1, Broadband Radio Access Networks (BRAN): HIPERLAN Type 2—Data Link Control (DLC) Layer—Part 1: Basic Data Transport Functions, 2000.
- [B15] ETSI TS 101 350 v6.1.0, Digital Cellular telecommunication System (Phase 2+): General Packet Radio Service (GPRS)—Overall description of the GPRS Radio Interface Stage 2, 1998.
- [B16] ETSI EN 301 958 v1.1.1, Digital Video Broadcasting (DVB); Interaction channel for Digital Terrestrial Television (RCT) incorporating Multiple Access OFDM, 2002.
- [B17] ETSI TS 121 101, Universal Mobile Telecommunications System (UMTS); Technical Specifications and Technical Reports for a UTRAN-based 3GPP system.
- [B18] Ghosh, A., Wolter, D. R., Andrews, J. G., and Chen, R., "Broadband wireless access with WiMax/802.16: Current performance benchmarks and future potential," *IEEE Communications Magazine*, vol. 43, no. 2, pp. 129–136, Feb 2005.
- [B19] Housely, R., Polk, W., Ford, W., and Solo, D., "Internet X.509 Public Key Infrastructure Certificate and Certificate Revocation List (CRL) Profile," *RFC 3280*, Apr. 2002.

- [B20] IEEE Std 802.16-2004, IEEE Standard for Local and Metropolitan Area Networks—Part 16: Air Interface for Fixed Broadband Wireless Access Systems.
- [B21] IEEE Std 802.16/Conformance01-2003, IEEE Standard for Conformance to IEEE Std 802.16—Part 1: Protocol Implementation Conformance Statement (PICS) Proforma for 10–66 GHz WirelessMAN-SC Air Interface.
- [B22] IEEE Std 802.16/Conformance02-2003, IEEE Standard for Conformance to IEEE Std 802.16—Part 2: Test Suite Structure and Test Purposes for 10–66 GHz WirelessMAN-SC Air Interface.
- [B23] IEEE Std 802.16/Conformance03-2004, IEEE Standard for Conformance to IEEE Std 802.16—Part 3: Radio Conformance Tests (RCT) for 10–66 GHz WirelessMAN-SC Air Interface.
- [B24] IEEE Std 802.16e-2005, IEEE Standard for Local and Metropolitan Area Networks—Part 16: Air Interface for Fixed and Mobile Broadband Wireless Access Systems—Amendment 2—Physical and Medium Access Control Layers for Combined Fixed and Mobile Operation in Licensed Bands.
- [B25] IEEE Std 802.16f-2005, IEEE Standard for Local and Metropolitan Area Networks—Part 16: Air Interface for Fixed Broadband Wireless Access Systems—Amendment 1—Management Information Base.
- [B26] IEEE Std 802.16.2-2004, IEEE Recommended Practice for Local and metropolitan area networks—Coexistence of Fixed Broadband Wireless Access Systems.
- [B27] Ishimaru, A., *Electromagnetic Waves, Propagation, Radiation and Scattering*, Prentice Hall, 1991.
- [B28] ITU Internet Report, "The Birth of Broadband," ITU Sales Service <<http://www.itu.int/osg/spu>>.
- [B29] ITU-T Recommendation X.200, Information technology—Open Systems Interconnection—Basic Reference Model: The basic model, 1994.
- [B30] ITU-R Recommendation M.1225, "Guidelines for valuation of radio transmission technologies for IMT-2000," 1997.

- [B31] Jeon, W. S., and Jeong, D., "Improved Selective Repeat ARQ Scheme for Mobile Multimedia Communications," *IEEE Communications Letters*, vol. 4, no. 2, 2000.
- [B32] Johnson, D., and Dudgeon, D., *Array Signal Processing*, Prentice Hall, 1993.
- [B33] Keshav, S., *An Engineering Approach to Computer Networking*, Addison-Wesley, 1997.
- [B34] Kwon, T., Lee, H., Choi, S., Kim, J., Cho, D.-H., Cho, S., Yun, S., Park, W.-H., and Kim, K., "Design and implementation of a simulator based on a cross-layer protocol between MAC and PHY layers in a WiBro Compatible IEEE 802.16e OFDMA system", *IEEE Communications Magazine*, pp. 136-146, Dec. 2005.
- [B35] Lee, R., Kim, J., Yu, J., and Lee, J., "Capacity analysis considering channel resource overhead for wireless mobile Internet system," *Proceedings of IEEE Vehicular Technology Conference 2005-Spring*, May 2005.
- [B36] Li, H., Lindskog, J., Malmgren, G., Miklos, G., Nilsson, F., and Rydell, G., "Automatic Repeat Request (ARQ) Mechanism in HIPERLAN/2," *The IEEE Semiannual Vehicular technology Conference - VTC2000*, Spring 2000.
- [B37] Liberti, J. C., and Rappaport, T. S., *Smart Antenna for Wireless Communications*, Prentice Hall, 1999.
- [B38] Marks, R. B., "IEEE Standard 802.16 for Global Broadband Wireless Access," ITU Telecom World 2003, Geneva, Oct. 12-18, 2003.
- [B39] Motorola, "Evaluation Methods for High Speed Downlink Packet Access (HSDPA)," TSG-R1 document, TSGR#14(00)0909, 2000.
- [B40] NIST 800-38C, Recommendation for Block Cipher Modes of Operation: the CCM Mode for Authentication and Confidentiality, May 2004.
- [B41] Pang, Q., Bigloo, A., Leung, V. C., and Scholefield, C., "Performance Evaluation of Retransmission Mechanisms in GPRS Networks," *IEEE WCNC'00*, Sept. 2000.
- [B42] Partridge, C., *Gigabit Networking*, Addison-Wesley, 1993.

- [B43] Rosen, E., Viswanathan, A., and Callon, R., "Multiprotocol Label Switching Architecture," *IETF RFC 3031*, Jan. 2001.
- [B44] Sandhu, S., and Paulraj, A., "Space-time block codes: a capacity perspective," *IEEE Communication Letters*, vol 4, pp. 384-386, 2000.
- [B45] Schneier, B., *Applied Cryptography: Protocol, Algorithms and Source code in C*, 2d ed., John Wiley & Sons, 1994.
- [B46] SCTE DSS 00-05, Radio Frequency Interface Specification, v.1.1, DOCSIS, July 2000.
- [B47] Seybold, J. S., *Introduction to RF Propagation*, John Wiley & Sons, Inc., 2005.
- [B48] Shin, S., Kang, C., Kim, J.-C., and Oh, S.-H., "The Performance Comparison between WiBro and HSDPA," *2nd International Symposium on Wireless Communication Systems*, pp. 346-350, Sept. 2005.
- [B49] Sklar, B., "Rayleigh Fading Channels in Mobile Digital Communication Systems: Part I: Characterization," *IEEE Communications Magazine*, Sept. 1997.
- [B50] Stallings, W., *Data & Computer Communications*, Prentice Hall, 2000.
- [B51] Stallings, W., *Wireless Communications and Networks*, Prentice Hall, 2002.
- [B52] Stanwood, K., and Piggitt, P., "WiMAX and Mesh Networking in the Home," *WiMAX and Mesh Networks Forum*, IEE, Savoy Place, London, June 2005.
- [B53] Stevenson, C. R., Cardeiro, C., Sofer, E., Chouinard, G., "Functional Requirements for the IEEE 802.22 WRAN Standard," *IEEE 802.22 Working Group Document*, IEEE 802.22-05/0007r45, Mar. 2006.
- [B54] Tanenbaum, A. S., *Computer Networks*, Prentice Hall, 1996.
- [B55] Van Nee, R., and Prasad, R., *OFDM for Wireless Multimedia Communications*, Artech House, 2000.

Index

NOTE—When phrases have been abbreviated in the text of this book, the abbreviations have generally been used when creating this index. See the Acronyms and Abbreviations list at the beginning of the book for the complete phrase for each abbreviation.

A

AAS, 45–46, 95, 311–320
 AAS subchannelization zone, 274
 ABR, 183
 ACID, 216, 218
 acknowledgments, 64–65
 active networks, 237
 adaptive CAC, 187–189
 adaptive modulation and coding, 293
 adaptive PHY, interactions with QoS and CAC, 181–189
 adjacent subcarrier permutation, 293
 admission control and provisioning (QoS function), 59
 AES-CCM, 96, 221–224
 aggregate request, 191
 AISN, 216
 AK management, 224
 allocation start time, 161
 AMC, 293
 angle diversity of antennas, 45
 antenna
 adaptive systems of, 45
 basic concepts of, 40–48
 design, 47
 directional and sectorized, 42
 diversity, 42–45
 grouping method, 326
 impact on protocol design, 47
 MIMO, 46
 parameters, 41

selection, 326

ARQ

basic concepts of, 64–66, 90–92, 97
 blocks, 127, 137–139
 BSN, 128
 cumulative acknowledgments, 141
 feedback, 64, 92, 125–126, 134, 143, 210, 213
 fragmentation and, 129–131
 GBN retransmission policy, 65, 91
 immediate acknowledgment, 64
 interaction with scheduler, 215
 packing and, 134
 parameters and timers, 203–205
 piggybacked payload, 125, 134
 protocol messages, 206
 receiver, 210–213
 reset and resynchronization, 213–215
 selective acknowledgments, 141
 SR retransmission policy, 65, 68, 86, 91, 204
 stop-and-wait retransmission policy, 65, 90, 93, 144, 218, 367–368
 transmitter, 207–210
 WirelessMAN-SCa, 260

ARQ Feedback IE, 139

ATDD, 51, 62, 84, 87

ATM CS, 99–101

ATS, 359

authorization, 152

B

bandwidth

allocation, 247
 antenna, 41
 channel, 95
 determining available, 181
 on demand, 182–186

BE service, 97, 178, 183, 185–186, 196–198

beam steering adaptive antenna, 46
 beam width of antenna, 41

- bit ordering, 98
- block-based retransmission, 91–92, 137
- BPSK, 260
- broadcast polling, 199
- BS, 71–73
- BSN comparison, 207
- BTC, 256, 260, 279, 302–303
- burst profile, 75, 84, 167–170, 248, 331–338
- BW request
 - AAS, 318
 - CDMA, 96, 292
 - contention-based CDMA, 200
 - focused contention, 96, 200, 284
 - full contention, 284
 - header, 96, 114
 - piggyback, 97, 111, 122, 192, 198
 - WirelessMAN-OFDM, 284
 - WirelessMAN-OFDMA, 306–308
- BW request/grant mechanism, 190–193
- byte-based retransmission, 91
- C**
 - CAC, 174, 181–189
 - CBC, 89, 220
 - CBR, 183
 - CCSA, 379
 - CDMA, 55, 96, 167, 200, 292, 306–308, 348
 - channel bandwidth, 95
 - channel descriptors and MAPs, 156–163
 - channel encoding
 - WirelessMAN-OFDM, 277–282
 - WirelessMAN-OFDMA, 302–305
 - channel state information for AAS, 317
 - channels, frequency, 30, 50–52
 - chip rate, 55
 - CID
 - AAS Initial Ranging, 111, 113
 - Basic, 108, 110, 113, 145–147, 149, 316
 - basic concepts of, 70, 107–113, 173
 - Broadcast, 112–113, 146, 199
 - CSs and, 99, 102
 - Fragmentable Broadcast, 112–113
 - header field, 115–117
 - Initial Ranging, 108–109, 113
 - mesh, 234
 - Multicast Polling, 111, 146
 - Padding, 111, 113
 - Primary Management, 110, 113, 149
 - Secondary Management, 110, 113
 - Transport, 110, 113
 - classification, 97, 102–104, 173
 - classifiers, 73
 - clock comparison, 201–203
 - clock skew, 192
 - closed-loop transmit diversity, 324–326
 - coarse synchronization, 237
 - coarse-grain QoS, 61
 - coexistence, 27, 32, 314
 - Compact MAP IE, 144
 - concatenation, 135
 - constant average power, 256
 - constant peak power, 256
 - continuous PHY, 85
 - control mechanisms
 - WirelessMAN-OFDM, 282–286
 - WirelessMAN-OFDMA, 306–309
 - WirelessMAN-SC, 259
 - control plane, 69
 - CPE, 71
 - CPS, 69
 - CRC, 96, 136
 - CS, 69–70, 97
 - CSMA, 47, 52, 366
 - CSMA/CA, 86
 - CTC, 260, 280, 302–303
 - cyclic prefix, 38, 94, 263, 270, 307, 348
- D**
 - DAMA, 247
 - data/control plane, 68
 - DCD, 75, 78, 144, 163
 - delay, 58
 - DES, 89, 96, 220
 - DFS, 31, 96
 - differentiated services, 69
 - directed mesh, 88, 244
 - discarded state, 209

- DIUC, 75, 156, 163, 199, 252, 273, 335
- diversity of antennas, 42–45
- DL and UL framing for AAS, 314
- DL burst, 78
- DL channel encoding, 252–256
- DL MAP, 75, 77–78, 248
- DL subchannelization zone, 274
- DL subframe, 77–78
- DL synchronization for AAS, 317
- Doppler frequency, 40
- DSA, 154, 171
- DSC, 172
- DSCP, 69
- dual diagonal staircase construction, 304
- duplexing, 50–52, 74–83, 95
- dynamic fragmentation, 62, 129
- dynamic service, 154, 171
- E**
 - EGC, 44
 - encryption, 96, 219–224
 - equalization, 39
 - equalizer, 38–39, 49, 93–94
 - error correction methods. See ARQ, FEC
 - ertPS, 346
 - Ethernet CS, 70
 - ETSI's BRAN activity, 267, 358, 375–378
- F**
 - fading, 39–40
 - fast-feedback control mechanism, 306, 323, 326
 - fast-receive diversity, 44
 - FDD
 - basic concepts of, 50–52, 74, 158–162, 194
 - framing, 78–80, 250
 - half-duplex, 158
 - WirelessMAN-SC, 247, 250
 - FDE, 93
 - FDM, 52
 - FDMA, 53
 - FEC
 - basic concepts of, 48
 - WirelessMAN-OFDM, 278–281
 - WirelessMAN-OFDMA, 302
 - WirelessMAN-SC, 252–258
 - WirelessMAN-SCa, 260
 - feedback, ARQ, 64, 92, 125–126, 134, 210, 213
 - FFSH, 118, 124, 127, 383
 - FFT, 95, 262–264
 - FHDC, 323
 - fine-grain QoS, 61
 - fixed access and WiMAX Forum, 362
 - fixed TDD, 84
 - fixed wireless networks, 33
 - fixed-length SDU and packing, 131
 - focused contention BW request, 96, 200, 284
 - fragmentation, 56, 62–64, 87, 97, 129–132
 - fragment-based retransmission, 91
 - frame duration, 95
 - framed PHY, 85
 - framing, 74–83
 - frequency bands, 30–33
 - frequency diversity of antennas, 43
 - Fresnel zone, 36
 - FSDD, 50
 - FSH, 118, 120, 126–127, 383
 - full contention BW request, 284
 - full-duplex. See duplexing
 - FUSC, 292, 294
- G**
 - gain, antenna, 41
 - GBN retransmission policy, 65, 91
 - GFR, 183
 - GMSH, 97, 118, 122, 127, 383
 - granularity, 60, 76, 248, 264, 293, 303
 - guard interval, 95
- H**
 - half-duplex. See duplexing
 - HARQ
 - acknowledgments, 147, 216
 - Compact MAP IE, 144
 - overview, 92–93, 97, 143
 - packet construction, 145
 - parameters, 216

performance and QoS implications, 217
 RCID, 145–147
 subpacket transmission, 216
 WirelessMAN-OFDMA, 309
 HARQ Control IE, 144, 216
 head-of-line blocking problem, 63
 H-FDD, 50–51, 79–80, 95, 250–251
 hidden nodes, 368
 HiperACCESS, ETSI BRAN, 358, 360, 376
 HiperMAN, ETSI BRAN, 267, 361, 377,
 381
 HSDPA, 348

I

IEEE 802.20 Working Group, 373
 IEEE P802.22 Working Group, 374
 IEEE Std 802.11, 365–373
 incremental request, 192
 initial ranging, 149–150, 283, 317
 interleaving, 85, 281, 305
 IP connectivity, 153
 IP CS, 70
 ISI, 39, 49
 ISO/IEC JTC1 and IEEE Std 802.16, 379
 ITU and IEEE Std 802.16, 379–381
 IUC, 84, 278

J

jitter, 58, 179

K

key, security, 152, 224
 Korean TTA, 378

L

latency, 58
 LDPCC, 303–305
 licensed spectrum, 9, 30
 license-exempt spectrum, 9, 30
 light licensing, 31
 logical mesh, 232–244
 LOS, 36, 38
 loss, 58

M**MAC**

address basics, 107
 connections, 383–386
 CPS, 70
 CS, 70
 efficiency, 85–87
 headers, subheaders, and special
 payloads, 113–124, 383
 management, 136
 management messages, 316, 383–386
 service and control functions for AAS,
 316

management plane, 68, 71
 mandatory IEEE 802.16 components, 94–97
 MAPs and channel descriptors, 156–163
 master-slave relationship, 71
 maximum latency, 179
 maximum sustained traffic rate, 176
 maximum traffic burst, 177
 MBS, 184
 medium access overhead, 86
 mesh

antennas, 42
 centralized scheduling, 241–244
 connections and addressing, 234
 directed, 88, 244
 distributed scheduling, 239
 logical, 232–244
 network configuration, 234–236
 network entry, 236–239
 overview, 35, 87, 97, 229–232
 WirelessMAN-OFDM, 275–277

midamble, 271
 MIMO, 46, 323, 355
 minimum reserved traffic rate, 177
 minimum tolerable traffic rate, 177
 mini-slots, 76
 mobile broadband wireless access, 363
 mobile networks, 33
 modulation, 39, 96, 281, 305
 mother sequences, 270
 MPDU, 70, 86, 107, 116, 125–126
 MPDU header, 86–87, 115
 MPLS, 101

MRC, 44, 46
 MSDU, 70
 MSH, 118, 123, 127, 383
 multicast connections, 189
 multicast polling group, 200
 multihop networks, 35
 multipath

basic concepts of, 38
 delay spread, 39
 fading, 38
 mitigation, 94
 propagation, 38
 multiple access, 52
 multiplexing, 52

N

near-far problem, 368
 NLOS, 36, 38
 nomadic service, 34
 not-sent state, 208
 nrtPS, 97, 178, 183, 185–186, 196–198
 nrtVBR, 183

O

OFDM. See WirelessMAN-OFDM
 OFDMA. See WirelessMAN-OFDMA
 O-FUSC, 293
 open-loop transmit diversity, 321–324
 optimum combining antenna, 46
 optional IEEE 802.16 components, 94–97
 O-PUS, 293
 outstanding state, 209

P

packing, 56, 63, 87, 97, 101, 121, 131–134
 PAPR, 49, 277, 308
 path loss, 39
 PCR, 184
 PCS, 101–105
 PDU, 56
 per-class QoS, 60
 per-flow QoS, 60
 periodic ranging, 163–167
 permutations for WirelessMAN-OFDMA,
 291–299

PHS, 70, 97, 104–105

PHSI field, 101

PHY

maintenance, 155–170
 overview, 93–94
 PICS, 27
 PICS proforma, 27, 359, 362
 piggyback BW request, 97, 111, 122, 192,
 198

PKM, 89, 152, 219

PM bit, 123, 193

PMP network, 35, 42, 97, 272, 300

polarization diversity of antennas, 44

polarization, antenna, 41

policing, shaping and (QoS function), 60

polling

broadcast, 199
 multicast, 200
 unicast, 197–199

portable networks, 34

power control, 285

preamble

WirelessMAN-OFDM, 270–272
 WirelessMAN-OFDMA, 301

precoding, 325

provisioning, admission control and (QoS
 function), 59

PS, 76

PSH, 91, 118, 121, 126, 383

PtP and directed mesh, 244

PtP network, 34, 42

PUSC, 292, 296–299

Q

QAM, 76

QoS

basic concepts of, 57–62, 88–89
 DOCSIS model, 172
 fragmentation and, 63
 interactions with CAC and adaptive
 PHY, 181–189
 model, 172
 parameters, 173–181, 184
 per-class/flow, 60
 service flows and, 171–201

wireless, 61–62
QoS parameter set type, 174–176

R

radiation pattern, antenna, 41
randomization, 277, 302
ranging
 CDMA, 306–308
 channel, 306
 initial, 149–150, 283, 317
 periodic, 163–167
 WirelessMAN-OFDM, 282–284
RCID, 145–147
RCT, 27, 359
reassembly, 97
receiver-initiated reset, 214
registration, 153
request/transmission policy, 179
retransmission, 65, 86, 91
RS-CC, 278
RTG, 77, 156
rtPS, 97, 178, 183, 185–186, 196–198, 346
rtVBR, 183

S

SA, 152, 219–224
SAP, 56
SC. See WirelessMAN-SC
SCa. See WirelessMAN-SCa
scheduling
 centralized, 241–244
 distributed, 239
 generally, 193–197
SCR, 184
SDU, 56, 131–132, 180
security, 62
 AES-CCM, 221–224
 encryption, 219–224
 key management, 224–227
 sublayer, 69–70, 89–90, 97
See also DIUC, UIUC
service class name, 173
service flow
 basic concepts of, 109

dynamic, 96
encodings, 173
QoS and, 171–201
 scheduling type, 178
SFID, 70, 109, 173
shadowing, 40
shaping and policing (QoS function), 60
shift index matrix, 304
SI bit, 123, 192, 196
single-hop networks, 35
SM, 321, 323
small-scale fading, 38
SNR, 44
spatial diversity of antennas, 43–44
SPID, 92, 216
sponsor channel, 238
sponsor node, 243
spreading codes, 55
SR retransmission policy, 65, 68, 86, 91, 204
SS, 71–73
SS basic capability negotiation, 150–152
SSRTG, 79
SSTTG, 79
static provisioning, 59
STBC, 321
STC, 95, 321–324
STC subchannelization zone, 274
stop-and-wait retransmission policy, 65, 90, 93, 144, 218, 367–368
STTD, 321
subchannelization, 95, 266–270
subframes, 76, 78
subheader
 fast-feedback allocation, 124
 fragmentation, 120
 grant management, 122
 MAC, 119, 383
 mesh, 123
 ordering of, 126
 packing, 121
sublayers, 69
switched beam adaptive antenna, 45

T

tail-biting method, 278
TDD
 basic concepts of, 50–52, 74, 157, 161, 194
 framing, 76–78, 248–250
 WirelessMAN-SC, 247–250
TDM, 52, 78, 86, 157, 248
TDMA, 53, 78, 86, 247
TEK, 153, 226
temporal diversity of antennas, 43
throughput, 58
time relevance, 81–83, 161–162
time-frequency mapping, 290–294
TLV-encoded information, 136
tolerated jitter, 179
Tproc, 157, 162
traffic
 classification (QoS function), 59
 parameters, 173–181, 184
 priority, 176
 scheduling (QoS function), 60
transmission CS, 135
transmitter-initiated reset, 213
TSS&TP, 27, 359
TTG, 77, 156, 250
turbo code, 96
TUSC1 and TUSC2, 294

U

UBR, 183
UCD, 75, 78, 144, 163, 257
UGS, 97, 123, 178, 180, 183, 185, 187, 192, 194–197, 346
UIUC, 75, 156, 163, 169, 252, 257, 335
UL burst, 78
UL channel encoding, 256–259
UL MAP, 76–78, 150
UL subframe, 78
unicast polling, 197–199
unlicensed spectrum, 30
unpacking, 97
unsolicited grant, 164

V

variable-length SDU and packing, 132
VCI, 99–101
vendor-specific QoS parameters, 178
VPI, 99–101

W


waiting-for-retransmission state, 209
waveform
 WirelessMAN-OFDM, 261–272
 WirelessMAN-OFDMA, 288
W-CDMA, 321
WiBro, 378
WiMAX Forum, 357–363
wireless QoS, 61–62
WirelessMAN-OFDM
 AAS, 319
 BW requests, 284
 channel encoding, 277–282
 conformance, 361
 control mechanisms, 282–286
 FEC, 278–281
 FFT size, 262–264
 fixed operation, 327–338
 frame structure, 272–277
 interleaving, 281
 mesh, 275–277
 mobile operation, 338–342
 modulation, 281
 overview, 54
 PMP network, 272
 power control, 285
 preambles, 270–272
 ranging, 282–284
 STC, 322
 subchannelization, 266–270
 waveform, 261–272
WirelessMAN-OFDMA
 AAS, 320
 BTC, 303
 CC, 303
 channel encoding, 302–305
 conformance, 361
 control mechanisms, 306–309
 CTC, 303

- FEC, 302
- FHDC, 323
- frame structure, 300–302
- interleaving, 305
- LDPCC, 303–305
- MIMO, 323
- mobile operation, 343–356
- modulation, 305
- overview, 53, 287
- permutations, 291–299
- PMP network, 300
- preambles, 301
- STC, 323
- time-frequency mapping, 290–294
- waveform, 288
- WirelessMAN-SC
 - conformance, 360–361
 - control mechanisms, 259
 - DL channel encoding, 252–256
 - frame structure, 248–252
 - overview, 93, 247
 - profiles, 358
 - UL channel encoding, 256–259
- WirelessMAN-SCa, 93, 260

Additional Books in the IEEE Standards Wireless Networks Series



This is the second edition of Bob O'Hara and Al Petrick's **IEEE 802.11 Handbook**. It has been referred to as the "LAN Bible". The new edition covers IEEE 802.11d, 802.11e, 802.11f, 802.11g, 802.11h, 802.11i, 802.11j, 802.11n, and more! The book is 365 pages, includes a Preface written by Stuart J. Kerry, Chairman of 802.11, a comprehensive list of abbreviations and acronyms, and handy index.



This handy pocket guide provides over 250 definitions for the jargon used in today's wireless industry. Written by Dr. James P.K. Gilb, Technical Editor of IEEE 802.15™, the dictionary is the perfect companion to the other handbooks in our Standards Wireless Networks Series and to the IEEE 802 wireless standards. Individuals who need to have a broad view of the wireless landscape will find that this book covers the most important topics and terms in today's market.*



Wireless Communications Standards: A Study of IEEE 802.11™, 802.15™, and 802.16™ is the only IEEE book of its kind that covers all of the current 802 wireless standards.*

*The authors of these books are also teaching courses based on IEEE wireless standards. For a deeper understanding of IEEE 802.16™, consider attending DoceoTech's instructor-led course called, "WiMAX and 802.16: Broadband Wireless Access." For more information, see <http://www.doceotech.com>.

<http://standards.ieee.org/standardspress/>

More Titles in the IEEE Standards Wireless Networks Series



Wireless Multimedia: A Handbook to the IEEE 802.15.3™ Standard clarifies the IEEE 802.15.3 standard for individuals who are implementing compliant devices and shows how the standard can be used to develop wireless multimedia applications.*



Low-Rate Wireless Personal Area Networks: Enabling Wireless Sensors with IEEE 802.15.4™ is an excellent companion to the standard for those interested in the field of "simple" wireless connectivity with a further focus on wireless sensors and actuators for the industry in general.

Please visit

<http://standards.ieee.org/standardspress/>

- Learn more about our products and authors
- Sign up to peer review future publications
- Submit a proposal and become an IEEE Author yourself!

WirelessMAN®

Inside the IEEE 802.16™ Standard for Wireless Metropolitan Area Networks

WirelessMAN®: Inside the IEEE 802.16™ Standard for Wireless Metropolitan Area Networks is the resource for understanding and navigating through the IEEE 802.16 standard, which serves as the basis of all WiMAX broadband wireless access systems.

Written by the 802.16 Working Group's Chair, Dr. Roger B. Marks, and Vice Chair, Kenneth L. Stanwood, along with Working Group participants Carl Eklund, Subbu Ponnuswamy, and Dr. Nico J.M. van Waes, the book provides a thorough understanding of the standard from an insider's perspective not found elsewhere.

Inside:

- Find detailed descriptions of the medium access control (MAC) and physical layer (PHY) operation up through IEEE 802.16-2004, with an introduction to the technologies introduced in IEEE 802.16e.
- See why certain design choices were made and how recent technological developments, real-world experience, and lessons learned from previous projects were used to make critical tradeoffs.
- Get details on OFDM, OFDMA, multiple antenna systems, security, and mesh technologies.
- See performance simulations and learn about current conformance and interoperability activities.
- Read a summary of ongoing projects, related standards, and future extensions.

WirelessMAN is a must-read for anyone wishing to understand the IEEE 802.16 standard and its operation. This book will immediately benefit designers, engineers, students, and deployment professionals who need to rapidly understand the fundamentals of the standard. The book is a self-contained companion to the standard, and no specific knowledge of any other wireless protocols is assumed. It can be used for self-study, as a reference, or as a designer's handbook.

Look for other books in the series at:

<http://standards.ieee.org>



0738148423 (123456)
**WirelessMAN: Inside the IEEE
802.16 Standard for Wireless
Metropolitan Area Networks**