


## Read direction — '608 Patent (EX1001) Figures 16 & 15

FIG. 15 illustrates a DQS routing circuit 620 according to an embodiment. As shown, the DQS routing circuit 620 includes a first DQS pin 1501 that is coupled to a corresponding DQS signal line 324, a second DQS pin 1502A that is coupled to a corresponding module DQS line  $YA_{DQS}$ , a third DQS pin 1502B that is coupled to a corresponding module DQS line  $YB_{DQS}$ . The DQS routing circuit 620 further includes a first write strobe path coupled between the first DQS pin 1501 and the second DQS pin 1502A and a second write strobe path coupled between the first DQS pin 1501 and the third DQS pin 1502B. The first write strobe path includes a write strobe buffer 1510 that buffers a write strobe, a write strobe receiver 1520 that samples the write strobe according to the buffered module signal CK0. The sampled write strobe is provided to the DQ routing circuits 320 as the write strobe WDQS. The first write strobe path further includes a first write strobe transmitter 1530A that transmits the write strobe to one or more memory devices 112 coupled to the module strobe line  $YA_{DQS}$ . The second write strobe path includes the write strobe buffer 1510, the write strobe receiver 1520, and a second write strobe transmitter 1530B that transmits the write strobe to one or more memory devices 112 coupled to the module strobe line  $YB_{DQS}$ . The first and second write strobe transmitters, 1530A and 1530B, are controlled by two enable signals, ENA and ENB, respectively, such that the first write strobe path and the second write strobe path can be selectively enabled/disabled by the enable signals, ENA and ENB.

The DQS routing circuit further includes a read strobe path coupled between the first DQS pin 1501 and a selected one of the second and third DQS pins 1502A and 1502B. In the read strobe path, a select circuit 1550 (e.g., a multiplexor) selects either a read strobe signal received via DQS pin 1502A or a read strobe signal received via DQS pin 1502B based on one or both of the enable signals ENA or ENB. The selected read strobe signal is delayed in a delay circuit 1560 by an amount controlled by the delay signal DS, and sampled by a sampler circuit 1570 according to the buffered module clock signal CK0. The sampled read strobe is provided to the DQ routing circuits 320 as the read strobe RDQS and is transmitted by transmitter 1580 onto the corresponding strobe signal line 324 via the first DQS pin 1501.

FIG. 16 illustrates a DQ routing circuit 320 according to an embodiment. As shown, the DQ routing circuit 320 includes a first DQ pin 1601 that is coupled to a corresponding DQ signal line 130, a second DQ pin 1602A that is coupled to a corresponding module DQ line  $YA_{DQ}$ , a third DQ pin 1602B that is coupled to a corresponding module DQ line  $YB_{DQ}$ . The DQ routing circuit 320 further includes a first write data path coupled between the first DQ pin 1601 and the second DQ pin 1602A and a second write data path coupled between the first DQ pin 1601 and the third DQ pin 1602B. The first write data path includes a write data buffer 1610, a write data receiver 1620 that samples write data according to the write strobe WDQS from the DQS routing circuit 620, and a first write data transmitter 1630A that transmits the write data to one or more memory devices 112 coupled to the module data line  $YA_{DQ}$ . The second write data path includes the write data buffer 1610, the write data receiver 1620, and a second write data transmitter 1630B that transmits the write data to one or more memory devices 112 coupled to the module data line  $YB_{DQ}$ . The first and second write data transmitters, 1630A and 1630B, are controlled by two enable signals, ENA and ENB, respectively. Thus, the first write data path and the second write data path can be selectively enabled/disabled by the enable signals, ENA and ENB.

The DQ routing circuit further includes a read data path coupled between the first DQ pin 1601 and a selected one of the second and third DQ pins 1602A and 1602B. In the read data path, a select circuit 1650 (e.g., a multiplexor) selects either a read data signal received via DQ pin 1602A or a read data signal received via DQ pin 1602B based on one or both of the enable signals ENA or ENB. The selected read data signal is delayed in a delay circuit 1660 by an amount controlled by the delay signal DS. The delayed read data signal is then sampled by a receiver circuit 1670 according to the read strobe RDQS from the DQS routing circuit 620, and transmitted by transmitter 1680 onto the corresponding data signal line 130 via the first DQ pin 1601.



## Write direction — '608 Patent (EX1001) Figures 16 & 15

