

(12) **EUROPEAN PATENT SPECIFICATION**

(45) Date of publication and mention
of the grant of the patent:
20.05.1998 Bulletin 1998/21

(51) Int Cl.⁶: **H03H 21/00**

(21) Application number: **94301499.3**

(22) Date of filing: **02.03.1994**

(54) **Low-delay subband adaptive filter**

Adaptives Subbandfilter mit geringer Verzögerung

Filtre adaptatif en sous-bandes à faible retard

(84) Designated Contracting States:
DE FR GB

(30) Priority: **12.03.1993 US 30931**

(43) Date of publication of application:
14.09.1994 Bulletin 1994/37

(73) Proprietor: **AT&T Corp.**
New York, NY 10013-2412 (US)

(72) Inventors:
• **Morgan, Dennis B.**
Morristown, New Jersey 07960 (US)
• **Thi, James Chi Huu**
Montgomery, Maryland 20877 (US)

(74) Representative:
Buckley, Christopher Simon Thirsk et al
Lucent Technologies (UK) Ltd,
5 Mornington Road
Woodford Green, Essex IG8 0TU (GB)

(56) References cited:
WO-A-88/03341

- **1990 INT SYMP ON CIRCUITS AND SYSTEMS;**
1-3/5/90; NEW ORLEANS (US); P279-282; E.
HÄNSLER: ADAPTIVE ECHOCOMPENSATION
APPLIED TO THE HANDS-FREE TELEPHONE
PROBLEM
- **PROC OF EUSIPCO-92, 24-27/8/92, BRUSSELS**
(BE); G. EGELMEERS et al: RELATION
BETWEEN REDUCED DIMENSION TIME AND
FREQUENCY DOMAIN ADATIVE ALGORITHM;
P1065-1068.

Note: Within nine months from the publication of the mention of the grant of the European patent, any person may give notice to the European Patent Office of opposition to the European patent granted. Notice of opposition shall be filed in a written reasoned statement. It shall not be deemed to have been filed until the opposition fee has been paid. (Art. 99(1) European Patent Convention).

EP 0 615 340 B1

Description

Field of the Invention

The present invention relates generally to the field of adaptive filtering techniques and specifically to the use of such techniques for adaptive noise cancellation.

Background of the Invention

Adaptive filtering techniques are now in widespread use for a number of applications such as adaptive arrays, adaptive line enhancement, adaptive modeling and system identification, adaptive equalization, and adaptive noise cancellation, including acoustic echo cancellation and active noise control.

In particular, the adaptive noise cancellation problem typically involves the generation of a signal which reflects an estimate of a disturbance (i.e., noise) which is to be reduced or eliminated (i.e., cancelled) from a primary source signal. Once determined, this estimate signal may then be subtracted from this primary source signal to reduce the effect of the disturbance. Active noise control in particular involves the generation of a secondary signal (e.g., sound) for the purpose of counteracting the effect of a preexisting noise disturbance. Adaptive filtering techniques are advantageously employed in the context of adaptive noise cancellation because a source signal from which a disturbance has been partially removed may be iteratively tested and processed to further reduce (e.g., minimize) the presence of the disturbance (see e.g. the document WO-A-88 03341).

Certain adaptive filtering applications involve adaptive filter lengths with hundreds of taps. Examples of such applications include wideband active noise control for complex mechanical structures and acoustic echo cancellation, both of which are characterized by long impulse responses. The computational burden associated with these long adaptive filters precludes their use for many low-cost applications. In addition to computational complexity, adaptive filters with many taps may also suffer from long convergence times, especially if the reference signal spectrum has a large dynamic range.

A technique that involves the use of subbands has been recently exploited to address the above problems (see e.g. the document 1990 Int. Symposium on Circuits and Systems; 1-3/5190; New Orleans (US); pp. 279-282; E. Hänsler: "Adaptive Echo Compensation Applied to the Hands-Free Telephone Problem"). Processing the signals in subbands has a twofold advantage. First, the computational burden is reduced by approximately the number of subbands, since both the tap length and weight update rate can be decimated in each subband. Second, faster convergence is possible because the spectral dynamic range within each subband is greatly reduced as compared to the overall spectral range.

One disadvantage of existing subband adaptive filters, however, is that a delay is necessitated by virtue of the bandpass filters used to derive subband signals. This delay presents a problem for some applications. In active noise control applications, for example, delay seriously limits the bandwidth over which good cancellation can be achieved. For acoustic echo cancellation applications, some transmission systems mandate a very low signal path delay. Thus, conventional subband adaptive filtering techniques may be precluded for applications requiring low delay.

Summary of the Invention

A technique is provided for generating a disturbance estimate signal for use in, for example, adaptive noise cancellation. According to an illustrative embodiment of the invention, a signal reflecting reference information is filtered by a plurality of subband filters to produce a plurality of subband reference signals. A signal reflecting a disturbance is filtered by a corresponding plurality of subband filters to produce a plurality of subband disturbance reflecting signals. Then, a plurality of sets of time domain subband weighting coefficients are generated, each set being derived based on a corresponding subband reference signal and a corresponding subband disturbance reflecting signal. Each set of time domain subband weighting coefficients is transformed into a set of frequency domain subband weighting coefficients. The frequency domain subband weighting coefficients are combined into a combined set of frequency domain weighting coefficients. The coefficients of this combined set are then transformed back into the time domain. This resultant set of combined time domain weighting coefficients is then supplied to a programmable filter which filters the reference signal accordingly in order to produce the disturbance estimate signal.

Brief Description of the Drawing

Fig. 1 shows a block diagram of a low-delay subband adaptive filter according to a first embodiment of the present invention.

Fig. 2 shows a block diagram of each conventional LMS processor of the system of Fig. 1.

Fig. 3 shows the frequency response of subband filters in accordance with an illustrative example of the system of Fig. 1.

Fig. 4 shows the process of frequency stacking in accordance with the illustrative example of the system of Fig. 1.

Fig. 5 shows the system of Fig. 1 without a cancellation path filter.

Fig. 6 shows a block diagram of a low-delay subband adaptive filter according to a second embodiment of the present invention.

Fig. 7 shows a block diagram of each conventional

LMS processor of the system of Fig. 6.

Fig. 8 illustrates the application of active noise control techniques to address an acoustic noise problem.

Fig. 9 shows the system of Fig. 1 as applied in the context of the technique of active noise control as illustrated in Fig. 8.

Fig. 10 shows the system of Fig. 1 as applied to the problem of acoustic echo cancellation.

Detailed Description

Fig. 1 shows a block diagram of a low-delay sub-band adaptive filter for use in adaptive noise cancellation according to a first embodiment of the present invention. A disturbance signal $d(t)$ reflects a disturbance to be reduced or eliminated. The reference signal $x(t)$ is a signal reflecting reference information which is correlated with the disturbance to be reduced. For example, in an acoustic echo cancellation application it may be desirable to cancel certain components of a microphone's output signal. These components may be generated as a result of the microphone's proximity to a loudspeaker. Such an application is presented by a conventional speakerphone. In such a case, $d(t)$ may represent the microphone's output signal (which includes a disturbance) and $x(t)$ may represent the loudspeaker's input signal (upon which the disturbance is based). Note that signal $d(t)$ may or may not include that part of a source signal which is not part of a disturbance. The embodiment of the present invention will remove from the microphone output signal those portions of the signal which are correlated with the disturbance. (See the discussion of Fig. 2 below.)

According to the first embodiment, reference signal $x(t)$ is filtered by programmable filter 12 having a transfer function W . This transfer function is derived iteratively, and is based on a set of MN (i.e., M times N) weights (or coefficients), w , supplied by inverse FFT processor 24. The resulting filtered signal, which reflects an estimate of the disturbance signal, is filtered in turn by cancellation path filter 26 (having a transfer function C). The result is a disturbance estimate signal $\hat{d}(t)$. Disturbance estimate signal $\hat{d}(t)$ like the signal output from programmable filter 12, reflects an estimate of the disturbance to be removed from disturbance signal $d(t)$. Removal of $\hat{d}(t)$ from $d(t)$ is accomplished by summation 14.

Illustratively, cancellation path filter 26 may represent an inherent transfer function applied by the environment to the signal generated by programmable filter 12. In an active noise control application, for example, it may be desired to create a "zone of silence" in a particular physical location by producing sound from a loudspeaker which will cancel the effect of a given preexisting disturbance. In this case, transfer function C of cancellation path filter 26 may reflect the effect on the loudspeaker's input signal by the loudspeaker itself, as well as the effect of air (or other medium through which the sound may travel) between the loudspeaker and the in-

tended "zone of silence". In other words, even though the active noise control system may generate a given signal to be provided to a loudspeaker (i.e., the output of programmable filter 12), the actual cancellation result achieved will be based on the generated signal as "filtered" by the effects of the loudspeaker and the air. Thus, C represents the electroacoustic (or electromechanical) transfer function from the input of the loudspeaker to the location of the intended zone of silence.

In other cases, such as in the acoustic echo cancellation application described above, there may be no cancellation path filter 26, since direct access to summation 14 is available. That is, the output signal of programmable filter 12 may be directly subtracted from disturbance signal $d(t)$ by an electrical implementation of summation 14.

Summation 14 removes the disturbance estimate from the disturbance signal by subtracting signal $\hat{d}(t)$ from signal $d(t)$ to produce residual error signal $e(t)$. Thus, residual error signal $e(t)$ is based on disturbance signal $d(t)$. Since signal $d(t)$ reflects a disturbance, signal $e(t)$ is therefore also a signal which reflects a disturbance. The operation of summation 14 may be effectuated by the physical environment (as in the active noise control case) or by an electrical component (as in the acoustic echo cancellation case). Note that residual error signal $e(t)$ may or may not include a desirable part of a source signal which is not part of a disturbance (depending on whether disturbance signal $d(t)$ does or does not include the desirable part of a source signal). However, that portion of residual error signal $e(t)$ which is part of a disturbance represents the actual residual disturbance (residual error) which is to be reduced (minimized). In other words, the actual residual error is the remaining portion of $e(t)$ which is correlated with the disturbance signal (and thus with reference signal $x(t)$). The operation of the illustrative embodiments involves an iterative adjustment of the coefficients w of programmable filter 12 such that the mean square residual error is reduced.

The technique used for adapting the coefficients of programmable filter 12 employs a conventional modification of the complex LMS (least-mean-squared) process well known in the art. The modification compensates for the effect of cancellation path transfer function C by initially filtering reference signal $x(t)$ by cancellation path estimate filter 28 to produce filtered reference signal $y(t)$. Filtered reference signal $y(t)$, like reference signal $x(t)$, reflects reference information which is correlated with the disturbance. Cancellation path estimate filter 28 has a transfer function $\hat{C}$, which is an estimate of transfer function C of cancellation path filter 26. In this manner, the choice of coefficients to be applied by programmable filter 12 will appropriately compensate for the effect of cancellation path filter 26. This technique is commonly known in the art as the "filtered-x" LMS (or FXLMS) process. Of course, in the case where there is no cancellation path filter 26 (e.g., in the acoustic echo cancellation

case) there will also be no need for cancellation path estimate filter **28**. In such a case, both transfer functions C and $\hat{C}$ may be viewed as equalling one (the identity function).

According to the embodiment of the present invention, filtered reference signal $y(t)$ is decomposed into a set of subband reference signals $y_0, y_1, \dots$ and y_M by the application of a set of $M + 1$ single-sideband bandpass filters. These bandpass filters, subband filters **16-0**, **16-1** ... and **16-M** (hereafter subband filters **16-m**) have transfer functions $H_0, H_1, \dots$ and H_M , respectively. Similarly, residual error signal $e(t)$ is decomposed into a set of subband residual error signals $e_0, e_1, \dots$ and e_M by the application of a corresponding set of $M + 1$ single-sideband bandpass filters. These bandpass filters, subband filters **18-0**, **18-1**, ... and **18-M** (hereafter subband filters **18-m**), also have (identical) transfer functions $H_0, H_1, \dots$ and H_M , respectively. These subband filters span the frequency range from zero to the sampling rate. In each subband, both the subband reference signals and the subband residual error signals are appropriately decimated (i.e., downsampled) by subband filters **16-m** and **18-m**, respectively, to reflect the reduced frequency range. Such downsampling is conventional in subband processing techniques. Illustratively, M may be 32.

Once signals $y(t)$ and $e(t)$ have been decomposed into sets of corresponding subband signals, a set of N adaptive weights (i.e., filter coefficients) is computed for each subband individually. As described above, a conventional complex LMS process is used, implemented by LMS processors **20-0**, **20-1**, ... and **20-M** (hereafter LMS processors **20-m**), respectively. In particular, LMS processor **20-0** generates a set w_0 comprising N coefficients, LMS processor **20-1** generates a set w_1 comprising N coefficients, ... and LMS processor **20-M** generates a set w_M comprising N coefficients. The detailed function of each LMS processor is illustrated in Fig. 2, and discussed below. Illustratively, N may be 32.

After each LMS processor **20-m** has generated adaptive weights $w_0, w_1, \dots, w_M$ (hereafter w_m), respectively, for each subband, these sets of coefficients are then transformed into the frequency domain by FFT processors **22-0**, **22-1**, ... and **22-M** (hereafter FFT processor **22-m**), respectively. Specifically, each FFT processor **22-m** produces a set of N frequency domain coefficients. These FFT processors may be implemented by conventional fast fourier transformation techniques.

Next, the $M + 1$ sets of frequency domain coefficients are appropriately stacked and inverse transformed by inverse FFT processor **24** to obtain the (time domain) filter coefficients w for programmable filter **12** (i.e., the coefficients of the transfer function W). Inverse FFT processor **24** may be implemented by a conventional inverse fast fourier transformation technique. An illustrative example of frequency stacking is illustrated in Fig. 7 and described below. Note that because the (wideband) filter coefficients are real, only half of the sampling band is actually processed, corresponding to

the positive frequency components of the wideband filter response. The other half of the response is formed in complex conjugate symmetry.

The FFTs and the inverse FFT need not be performed at the decimated sample rate. A substantial reduction in computation can be realized if they are computed only once every several decimated samples, with a corresponding moderate time lag in convergence. It is further noted that the wideband filter convolution can be more efficiently computed either by using a vector coprocessor or by using orthogonal transform techniques. A vector coprocessor is a conventional specialized hardware device that is dedicated to fast convolution. Alternatively, fast convolution can be realized using conventional orthogonal transform techniques such as the FFT. However, some care must be taken to insure that no delay is introduced into the signal path. Usually, a fast FFT convolution will entail a block delay in throughput. However, this can be avoided by splitting the wideband filter coefficients into segments of equal length. Then processing with the first segment may be implemented by direct convolution while the remaining segments may be processed by fast convolutions in time sequence. In this way, the fast convolution part may be started ahead of time by the number of samples in the direct convolution so that the output is available when needed. Thus, the total number of computations for the wideband convolution may be reduced by approximately the number of segments (neglecting the fast part of the computation).

Fig. 2 illustrates the detailed operation of each conventional LMS processor **20-m**. Each LMS processor takes as input a corresponding subband reference signal $y_m(t)$ and a corresponding subband residual error signal $e_m(t)$, and produces a set w_m of N adaptive weights (coefficients) for the given subband. Note that except for shift register **30**, each of the illustrated devices in Fig. 2 is to be replicated N times in each LMS processor **20-m**. Specifically, subband reference signal $y_m(t)$ is processed by shift register **30**, a tap delay line having N taps, to produce a set y_m of N values. The complex conjugate of each of these values is computed, as indicated by the asterisk (*) in the illustration, and a product of each of these resulting N values and subband residual error signal $e_m(t)$ is computed by multiplier **32**. Finally, each of the N values which result from this multiplication is passed through amplifier **34** (having gain μ) and integrated by adder **36** and delay **38**, to produce a corresponding one of the N adaptive weights of set w_m . This process ensures that only that part of the subband residual error signal which is correlated with the subband reference signal will be removed by the adaptive filtering process of the system of Fig. 1. Therefore, if disturbance signal $d(t)$ includes a source signal which is not part of a disturbance, the technique of the present invention will advantageously only remove those portions of the signal which are, in fact, correlated with the disturbance.

Illustratively, the low-delay subband adaptive filter of Fig. 1 assumes $M = 32$ and $N = 32$. A wideband filter of $MN/2 = 512$ taps may then be selected for programmable filter **12** and a 32-subband filter bank may be designed using a conventional polyphase FFT technique with twice-critical sampling (i.e., decimation by a factor of 16). Note that the subband filter bank actually comprises 33 ($M + 1$) subband filters, where the first and last filters reflect two halves of the same subband. Fig. 3 illustrates the frequency response of the first $M/2 + 1 = 17$ filters, which are the only ones processed due to the complex conjugate symmetry in accordance with this illustrative example. Each subband spans the 512 tap impulse response using $N = 32$ taps. Each of the sets $\mathbf{w}_m$ of subband adaptive weights are transformed by a corresponding 32-point FFT processor **22-m** to obtain 32 frequencies per subband. These frequencies are then stacked in the manner illustrated in Fig. 4 to form points 0 to 255 of a 512 point spectrum. In particular, the frequencies from subband 0 are assigned first, followed by those from subband 1, and so forth. Note that only the middle half (16) of the $N = 32$ frequencies are used for the odd numbered subbands, and only the upper and lower quarters of the 32 frequencies (i.e., the upper 8 and the lower 8) are used for the even numbered subbands. Moreover, these upper and lower quarters of the frequencies in the even subbands are transposed before assembly. The array is then completed by setting point 256 to zero and by using the complex conjugates of points 1 to 255 in reverse order to fill in points 257 to 511. Finally, the 512 point spectrum is then transformed by 512-point inverse FFT processor **24** to obtain the wideband filter weights $\mathbf{w}$ for programmable filter **12**. Note that the above example is described for illustrative purposes only. The technique according to the present invention can accommodate an arbitrary number of taps, number of subbands, decimation factor, etc., all of which may be optimized for a particular application.

A special case of the system of Fig. 1 results when $C = 1$, that is, when there is no cancellation path filter **26** (or cancellation path estimate filter **28**). In this case, the system of Fig. 1 reduces to the low-delay subband LMS system illustrated in Fig. 5. This special case concerns the acoustic echo cancellation problem, where $x(t)$ is an electrical line input signal, $d(t)$ is a microphone signal, and summation **14** is an electronic subtraction circuit that derives the output signal $e(t)$. As with the case of Fig. 1, signal $\hat{d}(t)$ output from programmable filter **12** reflects an estimate of the disturbance signal $d(t)$.

The low-delay subband systems of Figs. 1 and 5 can be characterized as closed-loop systems since the output residual error signal is fed back to the subband residual error filter bank. An alternative embodiment is possible for the special case of the low-delay subband system of Fig. 5 (where there is no cancellation path transfer function). Such an alternative, second embodiment of the present invention may be characterized as an open-loop system, and is illustrated by the system

shown in Fig. 6.

Specifically, in the open-loop system of Fig. 6, LMS processors **20-0**, **20-1**,... and **20-M** are replaced by alternate LMS processors **40-0**, **40-1**,... and **40-M** (hereafter **40-m**), respectively. In addition to generating a corresponding set $\mathbf{w}_m$ of N adaptive weights, each of these substitute LMS processors also generates subband disturbance estimate signals $\hat{d}_0, \hat{d}_1, \dots$ and $\hat{d}_M$ (hereafter $\hat{d}_m$), respectively, which are used to derive corresponding "local" subband residual error signals $e_0, e_1, \dots$ and e_M (hereafter e_m), respectively. Each of these local subband residual error signals is, in turn, supplied back to the corresponding LMS processor. Specifically, subband filters **18-m** decompose disturbance signal $d(t)$, which reflects a disturbance, into a plurality of subband signals $d_0, d_1, \dots$ and d_M (hereafter d_m). This is, of course, in contrast to the system of Fig. 5, in which subband filters **18-m** decompose residual error signal $e(t)$ (which also reflects a disturbance) into subband residual error signals e_m . Then, in the system of Fig. 6, each subband summation **42-0**, **42-1**,... and **42-M** (hereafter **42-m**) computes the corresponding local subband residual error signal e_m to be supplied to the corresponding LMS processor **40-m**. Ultimately, programmable filter **12** generates disturbance estimate signal $\hat{d}(t)$, which reflects an estimate of the disturbance, based on the outputs of LMS processors **40-m**. Since the (wideband) residual error signal $e(t)$ is not fed back to the subband weight calculation, the system of Fig. 6 can be characterized as an open-loop version of the system of Fig. 5.

Fig. 7 illustrates the detailed operation of each conventional LMS processor **40-m** of the system shown in Fig. 4. The operation of LMS processor **40-m** is nearly identical to that of LMS processor **20-m** as illustrated in Fig. 2 and described above. The difference is that multiplier **44** has been added to LMS processor **40-m** to generate subband disturbance estimate signal $\hat{d}_m(t)$ for the purpose as described above in connection with the operation of the system of Fig. 4.

The convergence of an open-loop system such as the one illustrated in Fig. 4 may be initially quicker than that of the closed-loop system of Fig. 3. However, after an initial convergence phase, the closed-loop system may continue to converge at a faster rate than the open-loop system. For this reason, it may be advantageous to provide a system incorporating both techniques. In such an embodiment of the present invention, the open-loop technique may be used initially, followed by a switch over to the closed-loop technique. For example, (electrical) switches may be provided at the inputs and the outputs of subband filters **18-m**. The input switches may be designed to supply either disturbance signal $d(t)$ or residual error signal $e(t)$ to each subband filter. The output switches may be designed to supply the output of each subband filter either to a corresponding subband summation **42-m** or directly to a corresponding LMS processor **40-m**. In this manner, an embodiment having combined convergence characteristics may be ob-

tained.

Fig. 8 illustrates the application of active noise control to address an acoustic noise problem. Primary disturbance source **50** generates acoustic noise in an enclosed room. Specifically, it is desired to create a "zone of silence" around microphone **46** by controlling loudspeaker **45** to produce a canceling acoustic signal. Microphone **46**, therefore, obtains the residual error signal $e(t)$ which is to be minimized. The reference signal $x(t)$ is derived from microphone **48**, which is in close proximity to primary disturbance source **50**. Thus, reference signal $x(t)$ may be reasonably assumed to be highly correlated with the disturbance which is to be eliminated from the intended zone of silence. The acoustic transfer functions H_d , H_x , and C are transfer functions over which no control exists, as they are inherent in the environment (i.e., resulting from the acoustics of the room). These transfer functions are described below in the discussion of Fig. 9.

Fig. 9 shows the system of Fig. 1 as applied to the problem of active noise control as illustrated in Fig. 8. The components of the system contained in (dashed) box **56** represent that part of the environment over which no direct access or control is available, except for the reference signal and residual error "observation" ports $x(t)$ and $e(t)$, respectively, and the control input (the output of programmable filter **12**) which is to be supplied in accordance with the technique of the present invention. Specifically, filter **52**, having transfer function H_x , reflects the effect of the environment on disturbance source **50** as it travels through the room and is captured by microphone **48** to generate reference signal $x(t)$. Filter **54**, having transfer function H_d , reflects the effect of the environment on disturbance source **50** as it travels through the room to the intended zone of silence surrounding microphone **46**. Cancellation path filter **26**, having transfer function C , reflects the effect of the environment (and of loudspeaker **45** itself) on the signal generated by programmable filter **12** for the purpose of cancelling disturbance source **50** (as filtered by filter **54**). And summing circuit **14** reflects the inherent process of the acoustic combination of these acoustic signals which occurs at the intended zone of silence. Therefore, by minimizing residual error signal $e(t)$ through the generation of filter weights w which control programmable filter **12**, the zone of silence may be quieted. Note that programmable filter **12** advantageously has a sufficient number of taps to span the combined length of transfer functions H_d and $(H_x C)^{-1}$.

Fig. 10 illustrates the system of Fig. 1 as applied to the problem of acoustic echo cancellation. In this case, reference signal $x(t)$ may be interpreted as a "far-end" received signal, H may be interpreted as an acoustic echo path transfer function (effectuated by filter **58**), and residual error signal $e(t)$ may be interpreted as a de-echoed return signal (to which the desired "near-end" source signal may be added). Thus, by minimizing residual error signal $e(t)$, the echo effect in the resultant

combined signal (i.e., the source signal plus the residual error signal) will be appropriately reduced. Note that the open-loop embodiment of the system of Fig. 4 may also be used in an analogous manner to address the problem of acoustic echo cancellation.

For clarity of explanation, the illustrative embodiments of the present invention have been presented as comprising individual functional blocks (including functional blocks labeled as "processors"). The functions these blocks represent may be provided through the use of either shared or dedicated hardware, including, but not limited to, hardware capable of executing software. For example, the functions of processors presented in the figures may be provided by a single shared processor. (Use of the term "processor" should not be construed to refer exclusively to hardware capable of executing software.)

Illustrative embodiments may comprise digital signal processor (DSP) hardware, such as the AT&T DSP16 or DSP32C, read-only memory (ROM) for storing software performing the operations discussed below, and random access memory (RAM) for storing DSP results. Very large scale integration (VLSI) hardware embodiments, as well as custom VLSI circuitry in combination with a general purpose DSP circuit, may also be provided.

Although a number of specific embodiments of this invention have been shown and described herein, it is to be understood that these embodiments are merely illustrative of the many possible specific arrangements which can be devised in application of the principles of the invention. Numerous and varied other arrangements can be devised in accordance with these principles by those of ordinary skill in the art without departing from the scope of the invention as defined in the appended claims.

Claims

1. A method for generating a signal reflecting an estimate of a disturbance, the method comprising the steps of

filtering a signal reflecting reference information with a plurality of subband filters to produce a plurality of subband reference reflecting signals;

filtering a signal reflecting a disturbance with a plurality of subband filters to produce a plurality of subband disturbance reflecting signals;
generating a plurality of sets of time domain subband weighting signals based on said subband reference reflecting signals and said subband disturbance reflecting signals;
combining said plurality of sets of time domain subband weighting signals to form a set of combined time domain weighting signals; and

- filtering said reference signal with use of said set of combined time domain weighting signals to produce the signal reflecting an estimate of a disturbance.
- 5
2. The method according to claim 1 wherein said signal reflecting reference information is correlated with said disturbance signal.
- 10
3. The method according to claim 1 wherein said generating step comprises use of a complex LMS process.
- 15
4. The method according to claim 1 wherein said step of combining said plurality of sets of time domain subband weighting signals comprises the steps of
- transforming said plurality of sets of time domain subband weighting signals to a plurality of sets of frequency domain subband weighting signals;
- 20 combining said plurality of sets of frequency domain subband weighting signals to form a combined set of frequency domain weighting signals; and
- 25 transforming said combined set of frequency domain weighting signals to a set of combined time domain weighting signals.
- 30
5. The method according to claim 4 wherein said step of transforming said plurality of sets of time domain subband weighting signals comprises use of a Fourier Transform process.
- 35
6. The method according to claim 5 wherein said step of transforming said combined set of frequency domain weighting signals comprises use of an inverse Fourier Transform process.
- 40
7. The method according to claim 1 wherein said signal reflecting reference information comprises a reference signal.
- 45
8. The method according to claim 1 wherein said signal reflecting reference information is generated by filtering a reference signal.
- 50
9. The method according to claim 1 wherein said signal reflecting a disturbance further reflects said signal reflecting an estimate of a disturbance.
- 55
10. An adaptive filter for generating a signal reflecting an estimate of a disturbance, the apparatus comprising
- a plurality of subband filters (16-O,...,16-M) for generating a plurality of subband reference reflecting signals based on a signal reflecting reference information;
- a plurality of subband filters (18-O,...,18-M) for generating a plurality of subband disturbance reflecting signals based on a signal reflecting a disturbance;
- means (20-O,..., 20-M) for generating a plurality of sets of time domain subband weighting signals based on said subband reference reflecting signals and said subband disturbance reflecting signals;
- means (24) for combining said plurality of sets of time domain subband weighting signals to form a combined set of time domain weighting signals; and
- a programmable filter (12) for filtering said reference signal with use of said set of combined time domain weighting signals to produce the signal reflecting an estimate of a disturbance.
11. The apparatus according to claim 10 wherein said signal reflecting reference information is correlated with said disturbance signal.
12. The apparatus according to claim 10 wherein said generating means (20-O,...,20-M) comprises use of a complex LMS process.
13. The apparatus according to claim 10 wherein said means (24) for combining said plurality of sets of time domain subband weighting signals comprises
- means (22-O,...,22-M) for transforming said plurality of sets of time domain subband weighting signals to a plurality of sets of frequency domain subband weighting signals;
- means (24) for combining said plurality of sets of frequency domain subband weighting signals to form a combined set of frequency domain weighting signals; and
- means (24) for transforming said combined set of frequency domain weighting signals to a set of combined time domain weighting signals.
14. The apparatus according to claim 13 wherein said means (24) for transforming said plurality of sets of time domain subband weighting signals comprises means for performing a Fourier Transform.
15. The apparatus according to claim 14 wherein said means (24) for transforming said combined set of frequency domain weighting signals comprises means for performing an inverse Fourier Transform.
16. The apparatus according to claim 10 wherein said signal reflecting reference information comprises a reference signal.
17. The apparatus according to claim 10 further com-

prising a filter (28) for generating said signal reflecting reference information based on a reference signal.

18. The apparatus according to claim 10 wherein said signal reflecting a disturbance further reflects said signal reflecting an estimate of a disturbance.

Patentansprüche

1. Verfahren zur Erzeugung eines einen Schätzwert einer Störung widerspiegelnden Signals mit folgenden Schritten:

Filtern eines Bezugsinformationen widerspiegelnden Signals mit einer Mehrzahl von Teilbandfiltern zur Erzeugung einer Mehrzahl von einem Teilbandbezugswert widerspiegelnden Signale;
Filtern eines eine Störung widerspiegelnden Signals mit einer Mehrzahl von Teilbandfiltern zur Erzeugung einer Mehrzahl von eine Teilbandstörung widerspiegelnden Signalen;
Erzeugen einer Mehrzahl von Mengen von Teilbandgewichtungssignalen im Zeitbereich auf Grundlage der besagten den Teilbandbezugswert widerspiegelnden Signale und besagten die Teilbandstörung widerspiegelnden Signale;
Kombinieren der besagten Mehrzahl von Mengen von Teilbandgewichtungssignalen im Zeitbereich zum Bilden einer Menge kombinierter Gewichtungssignale im Zeitbereich; und
Filtern des besagten Bezugssignals unter Verwendung der besagten Menge kombinierter Gewichtungssignale im Zeitbereich zur Erzeugung des einen Schätzwert einer Störung widerspiegelnden Signals.

2. Verfahren nach Anspruch 1, wobei das besagte die Bezugsinformationen widerspiegelnde Signal mit dem besagten Störungssignal korreliert ist.

3. Verfahren nach Anspruch 1, wobei der besagte Schritt des Erzeugens die Verwendung eines komplexen Verfahrens der kleinsten Fehlerquadrate umfaßt.

4. Verfahren nach Anspruch 1, wobei der besagte Schritt des Kombinierens der besagten Mehrzahl von Mengen von Teilbandgewichtungssignalen im Zeitbereich folgende Schritte umfaßt:

Umformen der besagten Mehrzahl von Mengen von Teilbandgewichtungssignalen im Zeitbereich in eine Mehrzahl von Mengen von Teilbandgewichtungssignalen im Frequenzbereich;

Kombinieren der besagten Mehrzahl von Mengen von Teilbandgewichtungssignalen im Frequenzbereich zum Bilden einer kombinierten Menge von Gewichtungssignalen im Frequenzbereich; und
Umformen der besagten kombinierten Menge von Gewichtungssignalen im Frequenzbereich in eine Menge von kombinierten Gewichtungssignalen im Zeitbereich.

5. Verfahren nach Anspruch 4, wobei der besagte Schritt des Umformens der besagten Mehrzahl von Mengen von Teilbandgewichtungssignalen im Zeitbereich die Verwendung eines Fourier-Transformationsvorgangs umfaßt.

6. Verfahren nach Anspruch 5, wobei der besagte Schritt des Umformens der besagten kombinierten Menge von Gewichtungssignalen im Frequenzbereich die Verwendung eines Fourier-Rücktransformationsvorgangs umfaßt.

7. Verfahren nach Anspruch 1, wobei das besagte Bezugsinformationen widerspiegelnde Signal ein Bezugssignal umfaßt.

8. Verfahren nach Anspruch 1, wobei das besagte Bezugsinformationen widerspiegelnde Signal durch Filtern eines Bezugssignals erzeugt wird.

9. Verfahren nach Anspruch 1, wobei das besagte eine Störung widerspiegelnde Signal weiterhin das besagte einen Schätzwert einer Störung widerspiegelnde Signal widerspiegelt.

10. Adaptives Filter zur Erzeugung eines einen Schätzwert einer Störung widerspiegelnden Signals mit folgenden:

einer Mehrzahl von Teilbandfiltern (16-0, ..., 16-M) zur Erzeugung einer Mehrzahl von einem Teilbandbezugswert widerspiegelnden Signalen auf Basis eines Bezugsinformationen widerspiegelnden Signals;
einer Mehrzahl von Teilbandfiltern (18-0, ..., 18-M) zur Erzeugung einer Mehrzahl von eine Teilbandstörung widerspiegelnden Signalen auf Basis eines eine Störung widerspiegelnden Signals;
Mitteln (20-0, ..., 20-M) zur Erzeugung einer Mehrzahl von Mengen von Teilbandgewichtungssignalen im Zeitbereich auf Basis der besagten einen Teilbandbezugswert widerspiegelnden Signale und besagten eine Teilbandstörung widerspiegelnden Signale;
Mitteln (24) zum Kombinieren der besagten Mehrzahl von Mengen von Teilbandgewichtungssignalen im Zeitbereich zum Bilden einer

- kombinierten Menge von Gewichtungssignalen im Zeitbereich; und einem programmierbaren Filter (12) zum Filtern des besagten Bezugssignals unter Verwendung der besagten Menge kombinierter Gewichtungssignale im Zeitbereich zur Erzeugung des einen Schätzwert einer Störung widerspiegelnden Signals.
11. Vorrichtung nach Anspruch 10, wobei das besagte Bezugsinformationen widerspiegelnde Signal mit dem besagten Störungssignal korreliert ist.
12. Vorrichtung nach Anspruch 10, wobei die besagten Erzeugungsmittel (20-0, ..., 20-M) die Verwendung eines komplexen Verfahrens der kleinsten Fehlerquadrate umfassen.
13. Vorrichtung nach Anspruch 10, wobei die besagten Mittel (24) zum Kombinieren der besagten Mehrzahl von Mengen von Teilbandgewichtungssignalen im Zeitbereich folgendes umfassen:
- Mittel (22-0, ..., 22-M) zum Umformen der besagten Mehrzahl von Mengen von Teilbandgewichtungssignalen im Zeitbereich in eine Mehrzahl von Mengen von Teilbandgewichtungssignalen im Frequenzbereich;
- Mittel (24) zum Kombinieren der besagten Mehrzahl von Mengen von Teilbandgewichtungssignalen im Frequenzbereich zum Bilden einer kombinierten Menge von Gewichtungssignalen im Frequenzbereich; und
- Mittel (24) zum Umformen der besagten kombinierten Menge von Gewichtungssignalen im Frequenzbereich in eine Menge von kombinierten Gewichtungssignalen im Zeitbereich.
14. Vorrichtung nach Anspruch 13, wobei die besagten Mittel (24) zum Umformen der besagten Mehrzahl von Mengen von Teilbandgewichtungssignalen im Zeitbereich Mittel zum Durchführen einer Fourier-Transformation umfassen.
15. Vorrichtung nach Anspruch 14, wobei die besagten Mittel (24) zum Umformen der besagten kombinierten Menge von Gewichtungssignalen im Frequenzbereich Mittel zum Durchführen einer Fourier-Rücktransformation umfassen.
16. Vorrichtung nach Anspruch 10, wobei das besagte Bezugsinformationen widerspiegelnde Signal ein Bezugssignal umfaßt.
17. Vorrichtung nach Anspruch 10, weiterhin mit einem Filter (28) zur Erzeugung des besagten Bezugsinformationen widerspiegelnden Signals auf Basis eines Bezugssignals.
18. Vorrichtung nach Anspruch 10, wobei das besagte eine Störung widerspiegelnde Signal weiterhin das besagte, einen Schätzwert einer Störung widerspiegelnde Signal widerspiegelt.

Revendications

1. Procédé de génération d'un signal représentant une estimation d'une perturbation, le procédé comprenant les étapes de

filtrage d'un signal représentatif d'informations de référence avec une pluralité de filtres de sous-bandes pour produire une pluralité de signaux représentatifs de références de sous-bandes;

filtrage d'un signal représentatif d'une perturbation avec une pluralité de filtres de sous-bandes pour produire une pluralité de signaux représentatifs de perturbations de sous-bandes;

génération d'une pluralité d'ensembles de signaux de pondération de sous-bandes dans le domaine temporel sur la base desdits signaux représentatifs de références de sous-bandes et desdits signaux représentatifs de perturbations de sous-bandes;

combinaison de ladite pluralité d'ensembles de signaux de pondération de sous-bandes dans le domaine temporel pour former un ensemble de signaux de pondération dans le domaine temporel combinés; et

filtrage dudit signal de référence en utilisant ledit ensemble de signaux de pondération dans le domaine temporel combinés pour produire le signal représentatif d'une estimation d'une perturbation.

2. Procédé selon la revendication 1, dans lequel ledit signal représentatif d'informations de référence est mis en corrélation avec ledit signal de perturbation.
3. Procédé selon la revendication 1, dans lequel ladite étape de génération comprend l'utilisation d'un processus complexe des moindres carrés moyens.
4. Procédé selon la revendication 1, dans lequel ladite étape de combinaison de ladite pluralité d'ensembles de signaux de pondération de sous-bandes dans le domaine temporel comprend les étapes de

transformation de ladite pluralité d'ensembles de signaux de pondération de sous-bandes dans le domaine temporel en une pluralité d'ensembles de signaux de pondération de sous-bandes dans le domaine de fréquence;

combinaison de ladite pluralité d'ensembles de signaux de pondération de sous-bandes dans

- le domaine de fréquence pour former un ensemble combiné de signaux de pondération dans le domaine de fréquence; et transformation dudit ensemble combiné de signaux de pondération dans le domaine de fréquence en un ensemble de signaux de pondération dans le domaine temporel combinés. 5
5. Procédé selon la revendication 4, dans lequel ladite étape de transformation de ladite pluralité d'ensembles de signaux de pondération de sous-bandes dans le domaine temporel comprend l'utilisation d'un processus de Transformée de Fourier. 10
6. Procédé selon la revendication 5, dans lequel ladite étape de transformation dudit ensemble combiné de signaux de pondération dans le domaine de fréquence comprend l'utilisation d'un processus de Transformée de Fourier inverse. 15
7. Procédé selon la revendication 1, dans lequel ledit signal représentatif d'informations de référence comprend un signal de référence. 20
8. Procédé selon la revendication 1, dans lequel ledit signal représentatif d'informations de référence est généré en filtrant un signal de référence. 25
9. Procédé selon la revendication 1, dans lequel ledit signal représentatif d'une perturbation représente en outre ledit signal représentatif d'une estimation d'une perturbation. 30
10. Filtre adaptatif pour générer un signal représentatif d'une estimation d'une perturbation, l'appareil comprenant 35
- une pluralité de filtres de sous-bandes (16-0, ..., 16-M) pour générer une pluralité de signaux représentatifs de références de sous-bandes sur la base d'un signal représentatif d'informations de référence; 40
- une pluralité de filtres de sous-bandes (18-0, ..., 18-M) pour générer une pluralité de signaux représentatifs de perturbations de sous-bandes sur la base d'un signal représentatif d'une perturbation; 45
- un moyen (20-0, ..., 20-M) pour générer une pluralité d'ensembles de signaux de pondération de sous-bandes dans le domaine temporel sur la base desdits signaux représentatifs de références de sous-bandes et desdits signaux représentatifs de perturbations de sous-bandes; 50
- un moyen (24) pour combiner ladite pluralité d'ensembles de signaux de pondération de sous-bandes dans le domaine temporel pour former un ensemble combiné de signaux de pondération dans le domaine temporel; et 55
- un filtre programmable (12) pour filtrer ledit signal de référence en utilisant ledit ensemble de signaux de pondération dans le domaine temporel combinés pour produire le signal représentatif d'une estimation d'une perturbation.
11. Appareil selon la revendication 10, dans lequel ledit signal représentatif d'informations de référence est mis en corrélation avec ledit signal de perturbation.
12. Appareil selon la revendication 10, dans lequel ledit moyen de génération (20-0, ..., 20-M) comprend l'utilisation d'un processus complexe des moindres carrés moyens.
13. Appareil selon la revendication 10, dans lequel ledit moyen (24) de combinaison de ladite pluralité d'ensembles de signaux de pondération de sous-bandes dans le domaine temporel comprend 20
- un moyen (22-0, ..., 22-M) pour transformer ladite pluralité d'ensembles de signaux de pondération de sous-bandes dans le domaine temporel en une pluralité d'ensembles de signaux de pondération de sous-bandes dans le domaine de fréquence; 25
- un moyen (24) pour combiner ladite pluralité d'ensembles de signaux de pondération de sous-bandes dans le domaine de fréquence pour former un ensemble combiné de signaux de pondération dans le domaine de fréquence; 30
- et 35
- un moyen (24) pour transformer ledit ensemble combiné de signaux de pondération dans le domaine de fréquence en un ensemble de signaux de pondération dans le domaine temporel combinés.
14. Appareil selon la revendication 13, dans lequel ledit moyen (24) pour transformer ladite pluralité d'ensembles de signaux de pondération de sous-bandes dans le domaine temporel comprend un moyen pour effectuer une Transformée de Fourier.
15. Procédé selon la revendication 14, dans lequel ledit moyen (24) pour transformer ledit ensemble combiné de signaux de pondération dans le domaine de fréquence comprend un moyen pour effectuer une Transformée de Fourier inverse.
16. Appareil selon la revendication 10, dans lequel ledit signal représentatif d'informations de référence comprend un signal de référence.
17. Appareil selon la revendication 10, comprenant en outre un filtre (28) pour générer ledit signal représentatif d'informations de référence sur la base d'un

signal de référence.

18. Appareil selon la revendication 10, dans lequel ledit signal représentatif d'une perturbation représente en plus ledit signal représentatif d'une estimation d'une perturbation. 5

10

15

20

25

30

35

40

45

50

55

11

FIG. 1



FIG. 2
(PRIOR ART)

FIG. 3







FIG. 4

FIG. 5

FIG. 7
(PRIOR ART)




FIG. 8
(PRIOR ART)




FIG. 9




FIG. 10

