




US 20080116818A1

(19) **United States**(12) **Patent Application Publication**
Shteynberg et al.(10) **Pub. No.: US 2008/0116818 A1**(43) **Pub. Date: May 22, 2008**(54) **TIME DIVISION MODULATION WITH
AVERAGE CURRENT REGULATION FOR
INDEPENDENT CONTROL OF ARRAYS OF
LIGHT EMITTING DIODES**(75) Inventors: **Anatoly Shteynberg**, San Jose, CA
(US); **Harry Rodriguez**, Gilroy,
CA (US)

Correspondence Address:

GAMBURD LAW GROUP LLC
600 WEST JACKSON BLVD., SUITE 625
CHICAGO, IL 60661(73) Assignee: **Exclara Inc.**, San Jose, CA (US)(21) Appl. No.: **11/603,689**(22) Filed: **Nov. 21, 2006****Publication Classification**(51) **Int. Cl.**
H05B 37/02 (2006.01)(52) **U.S. Cl. 315/192**(57) **ABSTRACT**

Exemplary apparatus, method and system embodiments provide for separately and independently sourcing current to a series of light emitting diodes of a plurality of series of light-emitting diodes. An exemplary apparatus comprises a power converter which generates a current, a first multiplexer, and a controller. The controller provides for sequential and separate switching of the current through the first multiplexer to each of the series of light-emitting diodes for a corresponding period of time. An average current provided by the power converter is determined as substantially equal to a sum of the corresponding currents through the plurality of series of light-emitting diodes. A total period for switching current to all of the series of light-emitting diodes is also determined. A corresponding time period for switching current to a selected corresponding series of light-emitting diodes is substantially equal to a proportion of the total period determined as a ratio of the corresponding current for the selected corresponding series of light-emitting diodes to the average current provided by the power converter.






FIG. 2
(PRIOR ART)




FIG. 3




FIG. 4




FIG. 5




FIG. 6




FIG. 7





FIG. 8







FIG. 11




FIG. 12




FIG. 13




FIG. 14A





FIG. 14B

TIME DIVISION MODULATION WITH AVERAGE CURRENT REGULATION FOR INDEPENDENT CONTROL OF ARRAYS OF LIGHT EMITTING DIODES

FIELD OF THE INVENTION

[0001] The present invention in general is related to converters and regulators used for driving and controlling arrays of light emitting diodes and, in particular, is related to an apparatus, system and method for time division modulation with average current regulation for independent control of arrays of light emitting diodes.

BACKGROUND OF THE INVENTION

[0002] Arrays of light emitting diodes ("LEDs") are utilized for a wide variety of applications, including for ambient lighting. To achieve emission of light perceived as white light, LED arrays typically utilize a combination of red, green and blue ("RGB") LEDs (and, occasionally, amber LEDs), usually as a first series connection (a first "string") of a plurality of red LEDs, a second series connection (a second string) of a plurality of green LEDs, and a third series connection (a third string) of a plurality of blue LEDs, typically which are referred to as "multistring LEDs".

[0003] For driving an array of LEDs, electronic circuits typically employ a converter to transform an AC input voltage (e.g., "AC mains") and provide a DC voltage source, with a linear regulator then used to regulate LED current. For example, in Mueller et al., U.S. Pat. No. 6,016,038, entitled "Multicolored LED Lighting Method and Apparatus", the LEDs may be controlled by a processor to alter the brightness and/or color of the generated light, such as by using pulse-width modulated ("PWM") signals.

[0004] Multistring LED Drivers with PWM regulation are known, e.g., Subramanian Muthu, Frank J. P. Schuurmans, and Michael D. Pashly "Red, Blue, and Green LED for White Light Illumination", *IEEE Journal on Selected Topics in Quantum Electronics*, Vol. 8, No. 2, March/April 2002, pp. 333-338. Such prior art multistring LED drivers typically require redundant drivers for every LED string. For example, in the prior art system illustrated in FIG. 1, three separate and independent flyback converters **10** operating at a constant switching frequency of 100 kHz drive a corresponding string of an RGB LED light source **15**, with a PWM **20** driving scheme operating at a frequency of 120 Hz. Each flyback converter **10** contains a current loop to maintain a constant peak current for the PWM pulses. The color control system is implemented in a DSP controller **25** (TMS320F240), which supplies the PWM turn-on and turn off signals for the power supply.

[0005] A similar prior art approach using redundant drivers for multistring LEDs is suggested in Chang et al., U.S. Pat. No. 6,369,525, entitled "White Light-Emitting-Diode Lamp Driver Based on Multiple Output Converter with Output Current Mode Control", which utilizes a white LED array driver circuit with a multiple output flyback (or forward) converters with output current mode control, as illustrated in FIG. 2. The circuit **40** comprises a power supply source, and a transformer having a primary winding **41** and multiple secondary windings **42**, with each light-emitting-diode string coupled in the circuit to one of the secondary windings. A main controller **43** is coupled to a first of the light-emitting-diode strings **46** and is configured to control a flow of current to the primary

transformer winding **41**. The circuit also comprises an additional plurality of secondary controllers **44**, **45**, each of which is correspondingly coupled to another light-emitting-diode string **47**, **48** to control a flow of current to its corresponding light-emitting-diode string.

[0006] An analog implementation of this teaching can be found in the AS3691 product from Austriamicrosystems (LEDs Magazine 2005). The AS3691 includes four independent high precision current sources each capable of sinking 400 mA. The operating current per LED channel can be set via an external resistor, while the LED brightness is controlled by four independent pulse width modulated inputs. The AS3691 integrates four independent current sinks per chip, enabling it to drive either four white LEDs each sinking 400 mA or a single white LED with up to 1.6 A.

[0007] Another prior art method utilizes multiple, separate linear regulators, with each regulator separately coupled to an LED string of an LED array. For example, an AC-to-DC converter, for transforming AC input voltage into a DC voltage source, is coupled to multiple, dedicated linear regulators, with one regulator coupled to each LED string to regulate the current in that corresponding LED string. This approach represents a multistage power system with low efficiency of power conversion, in addition to already low efficiency of series pass current regulators, particularly when the DC voltage is constant and does not depend on current. This prior art method of multiple and separate linear regulators is illustrated in the following U.S. Pat. No. 7,064,498 Light-Emitting Diode Based Products; U.S. Pat. No. 7,038,399 Methods And Apparatus For Providing Power To Lighting; U.S. Pat. No. 6,965,205 Light Emitting Diode Based Products; U.S. Pat. No. 6,806,659 Multicolored LED Lighting Method And Apparatus; U.S. Pat. No. 6,801,003 Systems And Methods For Synchronizing Lighting Effects; U.S. Pat. No. 6,788,011 Multicolored LED Lighting Method And Apparatus; U.S. Pat. No. 6,720,745 Data Delivery Track; U.S. Pat. No. 6,636,003 Apparatus And Method For Adjusting The Color Temperature Of White Semiconductor Light Emitters; U.S. Pat. No. 6,624,597 Systems And Methods For Providing Illumination In Machine Vision Systems; U.S. Pat. No. 6,548,967 Universal Lighting Network Methods And Systems; U.S. Pat. No. 6,528,954 Smart Light Bulb; U.S. Pat. No. 6,459,919 Precision Illumination; U.S. Pat. No. 6,340,868 Illumination Components; U.S. Pat. No. 6,292,901 Power/Data Protocol; U.S. Pat. No. 6,211,626 Illumination Components; U.S. Pat. No. 6,166,496 Lighting Entertainment System; and U.S. Pat. No. 6,150,774 Multicolored LED Lighting Method And Apparatus.

[0008] Similarly, in U.S. Pat. No. 6,016,038, entitled "Multicolored LED Lighting Method and Apparatus", each LED string of the LED array is controlled by a separate current regulator with a processor, to alter the brightness and/or color of the generated light using pulse-width modulated signals. In this case, an additional, current sink stage is added in series with each LED string current regulator, resulting in a further decrease in efficiency, particularly when the current sink is used to bypass the LED current to ground when the LED should be off. This multistage power system, with dedicated current converters and controllers in each LED channel, in addition to low efficiency, has a large size, many expensive components, and is expensive to manufacture.

[0009] Lastly, in Archenhold et al. U.S. Pat. No. 6,963,175, entitled "Illumination Control System", a light emitting diode illumination control system is disclosed for driving a current

circuit for energizing one or more LED light sources. The system comprises a control system including a microprocessor, arranged to control a pulse amplitude modulated (PAM) voltage controlled current circuit, and may employ a monitor for monitoring at least one ambient condition and a microprocessor operable to control the current circuit to response to the monitored conditions. This proposal has several significant problems: (1) the system is very complex, inefficient (for power conversion), has many expensive components, and is expensive to manufacture; (2) the current to emission (color) transfer function in emitting diodes is substantially nonlinear, leading to a poor color control or requiring additional, undisclosed technical means for compensation of this nonlinearity (not suggested in the patent); and (3) the disclosed current source operates poorly, suffering from thermal dependency and requiring correction by a microprocessor.

[0010] The referenced prior art with multi-output or separate power converters and controllers for each LED string of an LED array increases the cost and size of the LED driver, and reduces the functionality and efficiency of the driver. Accordingly, a need remains for a multistring LED driver which utilizes a single power converter and controller for an entire LED array and does not utilize these multiple, separate power converters and controllers for each LED string. Such a multistring LED driver should provide for independent current control for each LED string of the array, for corresponding effective color and brightness control. In addition, such an LED array driver should provide for local LED regulation, providing local compensation of LED emission due to age and drift of functional parameters, temperature changes of the LED junction, LED production characteristics variation, and variations of devices produced by different manufacturers. Such an LED array driver also should be backwards-compatible with legacy LED control systems.

SUMMARY OF THE INVENTION

[0011] As discussed in greater detail below, the various embodiments of the invention provide innumerable advantages for energizing a plurality of series (strings) of LEDs, using a single power converter and controller for an entire LED array, and does not utilize multiple, separate power converters and controllers for each LED string. The exemplary embodiments provide a multistring LED driver which controls current independently for each series of LEDs of the array, for corresponding effective color and brightness control, among other features. In addition, the exemplary LED array drivers provide for local LED regulation, achieving local compensation of LED emission due to age and drift of functional parameters, temperature changes of the LED junction, LED production characteristics variation, and variations of devices produced by different manufacturers. The exemplary LED array drivers are also backwards-compatible with legacy LED control systems.

[0012] Providing such local regulation of LED arrays is a significant advance compared to the prior art use of a central, overall system (or host) computer or microprocessor for certain types of remote regulation. The local regulation provided by the present invention enables a significantly faster response time, without requiring the prior art communication protocols, and further provides a more comprehensive approach for maintaining selected color and brightness levels throughout the life span of the LEDs and corresponding changes in their functional parameters. Exemplary embodiments also may be implemented using comparatively lower

cost controllers. When the exemplary embodiments are further implemented to be backwards-compatible with legacy control systems, the present invention frees the host computer for other tasks and allows such host computers to be utilized for other types of system regulation.

[0013] An exemplary apparatus embodiment, for providing current independently to a series of light emitting diodes of a plurality of series of light-emitting diodes, comprises a power converter, a first multiplexer, and a controller. The power converter is couplable to the plurality of series of light-emitting diodes, and the power converter is adapted to generate a current. The first multiplexer is also couplable to the plurality of series of light-emitting diodes. The controller is coupled to the power converter and to the first multiplexer, and the controller is adapted to provide for sequential and separate switching of the current through the first multiplexer to each of the series of light-emitting diodes, of the plurality of series of light-emitting diodes, for a corresponding period of time. The controller is further adapted to provide for no switching of current through the first multiplexer to all remaining series of light-emitting diodes while current is switched to a selected series of light-emitting diodes of the plurality of series of light-emitting diodes.

[0014] In exemplary embodiments, the controller is further adapted to determine an average current provided by the power converter as substantially or about equal to a sum of a plurality of corresponding currents through the plurality of series of light-emitting diodes, and to determine a total period for switching current to all of the series of light-emitting diodes of the plurality of series of light-emitting diodes. The controller may also be adapted to determine a corresponding time period for switching current to a selected corresponding series of light-emitting diodes as substantially (or about) equal to a proportion of the total period determined as a ratio of the corresponding current for the selected corresponding series of light-emitting diodes to the average current provided by the power converter.

[0015] An exemplary apparatus embodiment may further include a memory coupled to the controller, with the memory adapted to store, as a look up table, a plurality of parameters corresponding to the plurality of series of light-emitting diodes. In exemplary embodiments, the controller is further adapted to predict an output voltage across a selected series of light-emitting diodes based on the device parameters stored in memory and to revise the predicted output voltage based upon a measured output voltage across a selected series of light-emitting diodes.

[0016] The power converter may further comprise a first voltage divider, with the controller being further adapted to determine an input voltage across the first voltage divider. Similarly, the power converter may further comprise a current sensor, with the controller being further adapted to determine a peak input current through the current sensor. In addition, exemplary embodiments may also include a plurality of capacitors, with each capacitor of the plurality of capacitors couplable to a corresponding series of light-emitting diodes of the plurality of series of light-emitting diodes.

[0017] An exemplary apparatus embodiment may further include a plurality of second voltage dividers, with each second voltage divider couplable in parallel to a corresponding series of light-emitting diodes of the plurality of series of light-emitting diodes, with the controller being further adapted to determine a corresponding output voltage across the corresponding second voltage divider of the plurality of

second voltage dividers. In exemplary embodiments, a second multiplexer may be coupled to the plurality of second voltage dividers and the controller, with the controller being further adapted to control switching of the second multiplexer to a selected second voltage divider of the plurality of second voltage dividers. Also in exemplary embodiments, a third multiplexer may be coupleable to the plurality of series of light-emitting diodes and coupled to the controller, with the controller being further adapted to control switching of the third multiplexer to a selected series of light-emitting diodes of the plurality of series of light-emitting diodes for measuring a corresponding current through the selected series of light-emitting diodes.

[0018] In various exemplary embodiments, the controller may be further adapted to determine the corresponding period of time for switching of current to a selected series of light-emitting diodes based on a comparison of the measured corresponding current to a predetermined current level for the selected series of light-emitting diodes. In other embodiments, the controller may be further adapted to determine the corresponding period of time for switching of current to a selected series of light-emitting diodes based on an integer multiple of a period of switching of the power converter, and may be further adapted to control switching of the first multiplexer to a selected series of light-emitting diodes of the plurality of series of light-emitting diodes when current through the power converter is substantially (or about) zero.

[0019] In various exemplary embodiments, the controller may be further adapted, in response to a first input, to adjust an output brightness of the plurality of series of light-emitting diodes by modifying each corresponding period of time of current switching to each of the series of light-emitting diodes. In addition, the controller may be further adapted, in response to a second input, to adjust an output color of the plurality of series of light-emitting diodes by modifying at least one corresponding period of time of current switching to at least one of the series of light-emitting diodes of the plurality of series of light-emitting diodes.

[0020] In exemplary embodiments, the first multiplexer may comprise a plurality of switches, with each switch of the plurality of switches correspondingly coupleable to a first, high side of a corresponding series of light-emitting diodes of the plurality of series of light-emitting diodes, or coupleable to a second, low side of a corresponding series of light-emitting diodes of the plurality of series of light-emitting diodes. In other embodiments, the first multiplexer may comprise a plurality of first switches, with each switch of the plurality of first switches correspondingly coupleable to a first, high side of a corresponding series of light-emitting diodes of the plurality of series of light-emitting diodes; and a plurality of second switches, with each switch of the plurality of second switches correspondingly coupleable to a second, low side of a corresponding series of light-emitting diodes of the plurality of series of light-emitting diodes. In yet other embodiments, the first multiplexer may comprise a plurality of first switches, with each switch of the plurality of first switches correspondingly coupleable to a first, high side of a corresponding series of light-emitting diodes of the plurality of series of light-emitting diodes; and a second switch coupleable to the plurality of capacitors.

[0021] In exemplary embodiments, a lighting system comprises a plurality of series of light-emitting diodes, a power converter, a first multiplexer, and a controller. The power converter is coupled to the plurality of series of light-emitting

diodes and is adapted to generate a current. The first multiplexer is coupled to the plurality of series of light-emitting diodes. The controller is coupled to the power converter and to the first multiplexer, and the controller is adapted to provide for sequential and separate switching of the current through the first multiplexer to each of the series of light-emitting diodes, of the plurality of series of light-emitting diodes, for a corresponding period of time.

[0022] The exemplary embodiments further provide a method of selectively and independently providing power to a series of light emitting diodes of a plurality of series of light-emitting diodes. The method comprises generating an input DC current having a first average level; and sequentially and separately switching the DC current to each of the series of light-emitting diodes, of the plurality of series of light-emitting diodes, for a corresponding period of time. The exemplary method may further include switching no current to all remaining series of light-emitting diodes while switching the DC current to a selected series of light-emitting diodes of the plurality of series of light-emitting diodes.

[0023] In exemplary embodiments, the method may also include determining the first average level of DC current as substantially or about equal to a sum of a plurality of corresponding currents through the plurality of series of light-emitting diodes, determining a total period for switching current to all of the series of light-emitting diodes of the plurality of series of light-emitting diodes, and determining a corresponding time period for switching current to a selected corresponding series of light-emitting diodes as substantially or about equal to a proportion of the total period determined as a ratio of the corresponding current for the selected corresponding series of light-emitting diodes to the average current provided by the power converter. An exemplary method may also include storing, as a look up table, a plurality of parameters corresponding to the plurality of series of light-emitting diodes, and predicting an output voltage across a selected series of light-emitting diodes, of the plurality of series of light-emitting diodes, based on the stored device parameters. The exemplary method may further include measuring a corresponding output voltage for each series of light emitting diodes of the plurality of series of light-emitting diodes; updating the predicted output voltage across a selected series of light-emitting diodes, of the plurality of series of light-emitting diodes, based on a corresponding measured output voltage; determining an input voltage; determining a peak input DC current; determining a corresponding output voltage for each series of light emitting diodes of the plurality of series of light-emitting diodes; and/or measuring a corresponding current through each series of light-emitting diodes of the plurality of series of light-emitting diodes.

[0024] In other exemplary embodiments, the method may include determining the corresponding period of time for switching of current to a selected series of light-emitting diodes based on a comparison of the measured corresponding current to a predetermined current level for the selected series of light-emitting diodes, and/or determining the corresponding period of time for switching of current to a selected series of light-emitting diodes based on an integer multiple of a period of switching of a power converter. In addition, the method may include switching current to a selected series of light-emitting diodes of the plurality of series of light-emitting diodes when the input DC current is substantially (or about) zero.

[0025] Another exemplary embodiment provides an apparatus for providing current independently to a series of light emitting diodes of a plurality of series of light-emitting diodes, with the apparatus comprising a power converter, a first multiplexer, a memory, and a controller. The power converter is couplable to the plurality of series of light-emitting diodes and is adapted to generate a current. The first multiplexer is also couplable to the plurality of series of light-emitting diodes. The memory is adapted to store, as a look up table, a plurality of parameters corresponding to the plurality of series of light-emitting diodes. The controller is coupled to the power converter, to the first multiplexer and to the memory, with the controller being adapted to provide for sequential and separate switching of the current through the first multiplexer to each of the series of light-emitting diodes, of the plurality of series of light-emitting diodes, for a corresponding period of time; the controller further adapted to determine an average current provided by the power converter as substantially or about equal to a sum of a plurality of corresponding currents through the plurality of series of light-emitting diodes, to determine a total period for switching current to all of the series of light-emitting diodes of the plurality of series of light-emitting diodes, and to determine a corresponding time period for switching current to a selected corresponding series of light-emitting diodes as substantially or about equal to a proportion of the total period determined as a ratio of the corresponding current for the selected corresponding series of light-emitting diodes to the average current provided by the power converter.

[0026] Numerous other advantages and features of the present invention will become readily apparent from the following detailed description of the invention and the embodiments thereof, from the claims and from the accompanying drawings.

BRIEF DESCRIPTION OF THE DRAWINGS

[0027] The objects, features and advantages of the present invention will be more readily appreciated upon reference to the following disclosure when considered in conjunction with the accompanying drawings, wherein like reference numerals are used to identify identical components in the various views, and wherein reference numerals with alphabetic characters (with or without subscripts) are utilized to identify particular instantiations of a corresponding type of selected component in the various views, in which:

[0028] FIG. 1 (or FIG. 1) is a prior art LED array driver.

[0029] FIG. 2 (or FIG. 2) is a prior art LED array driver.

[0030] FIG. 3 (or FIG. 3) is a circuit and block diagram illustrating a first exemplary LED array driver circuit in accordance with the teachings of the present invention.

[0031] FIG. 4 (or FIG. 4) is a timing diagram for a first exemplary LED array driver circuit in accordance with the teachings of the present invention.

[0032] FIG. 5 (or FIG. 5) is a diagram illustrating continuous current in an inductor in a first exemplary LED array driver circuit in accordance with the teachings of the present invention.

[0033] FIG. 6 (or FIG. 6) is a diagram illustrating discontinuous current in an inductor in a first exemplary LED array driver circuit in accordance with the teachings of the present invention.

[0034] FIG. 7 (or FIG. 7) is a circuit and block diagram illustrating a second exemplary LED array driver circuit in accordance with the teachings of the present invention.

[0035] FIG. 8 (or FIG. 8) is a circuit diagram illustrating high side driving and low side sensing of a series of LEDs in accordance with the teachings of the present invention.

[0036] FIG. 9 (or FIG. 9) is a circuit diagram illustrating differential high side sensing and low side driving of a series of LEDs in accordance with the teachings of the present invention.

[0037] FIG. 10 (or FIG. 10) is a graphical diagram illustrating simulation of a boost LED array driver circuit, for three series of LEDs, in accordance with the teachings of the present invention.

[0038] FIG. 11 (or FIG. 11) is a circuit diagram illustrating a first configuration of an LED array for independent time division modulation in accordance with the teachings of the present invention.

[0039] FIG. 12 (or FIG. 12) is a circuit diagram illustrating a second configuration of an LED array for common time division modulation in accordance with the teachings of the present invention.

[0040] FIG. 13 (or FIG. 13) is a graphical diagram illustrating simulation of LED current in a boost LED array driver circuit, for three LED strings, in accordance with the teachings of the present invention.

[0041] FIG. 14 (or FIG. 14) is a flow diagram illustrating an exemplary method in accordance with the teachings of the present invention.

DETAILED DESCRIPTION OF EXEMPLARY EMBODIMENTS

[0042] While the present invention is susceptible of embodiment in many different forms, there are shown in the drawings and will be described herein in detail specific exemplary embodiments thereof, with the understanding that the present disclosure is to be considered as an exemplification of the principles of the invention and is not intended to limit the invention to the specific embodiments illustrated. In this respect, before explaining at least one embodiment consistent with the present invention in detail, it is to be understood that the invention is not limited in its application to the details of construction and to the arrangements of components set forth above and below, or as described and illustrated in the drawings. Apparatuses consistent with the present invention are capable of other embodiments and of being practiced and carried out in various ways. Also, it is to be understood that the phraseology and terminology employed herein, as well as the abstract included below, are for the purposes of description and should not be regarded as limiting.

[0043] Referring now to the Figures, wherein like reference numerals are used to identify identical components in the various views, and wherein reference numerals with alphabetic characters (with or without subscripts) are utilized to identify particular instantiations of a corresponding type of selected component in the various views, FIG. 3 is a circuit and block diagram illustrating a first exemplary LED array driver circuit 100 in accordance with the teachings of the present invention. The first exemplary LED array driver circuit 100 comprises a (switching) power converter 120, a parallel array of LEDs 110, a multiplexer (or other array of power switches) 150 (typically referred to as a first, time-division multiplexer 150), a controller 125, and a memory 175. In exemplary embodiments, the exemplary LED array driver circuit 100 also comprises one or more sensors 185, discussed in greater detail below.

[0044] The parallel array of LEDs **110** comprises a plurality of series-connected LEDs, i.e., independent series or “strings” of LEDs, illustrated as “N” individual series of LEDs **110₁**, **110₂**, **110₃**, through **110_N**. Each such series of LEDs **110₁**, **110₂**, **110₃**, through **110_N** may be referred to equivalently herein as a “channel”, namely, channel one, channel two, channel three, through channel “N”, respectively. The “channel” connotation is particularly appropriate for the present invention which, as discussed in greater detail below, provides for independently energizing each series of LEDs **110₁**, **110₂**, **110₃**, through **110_N** using time-division modulation (“TDM”, or equivalently, time-division multiplexing).

[0045] Each series of LEDs **110₁**, **110₂**, **110₃**, through **110_N** may have either the same or different types of LEDs. For purposes of explanation and understanding of the present invention, and without limitation as to the scope of the invention, however, it may be assumed that each series of LEDs **110₁**, **110₂**, **110₃**, through **110_N** have similar characteristics, such as by being fabricated by the same manufacturer and having only production or other manufacturing variations or tolerances. LEDs **110₁**, **110₂**, **110₃**, through **110_N** having different characteristics, such as by being produced from different manufacturers, may still be modeled appropriately, with corresponding information stored in the memory **175**, and with all such variations considered equivalent and within the scope of the invention. As discussed in greater detail below, various models of LED operation and device characteristics are created and stored in memory **175**, which may be any type or form of memory, and which further may comprise a look up table structure or a database **180** structure, for example and without limitation.

[0046] Each such channel may also comprise a corresponding bypass filter capacitor **115** connected in parallel with each series of LEDs **110₁**, **110₂**, **110₃**, through **110_N**, illustrated as corresponding capacitors **115₁**, **115₂**, **115₃**, through **115_N**. The selection of the value of each corresponding capacitance, or the inclusion of any of the capacitors **115₁**, **115₂**, **115₃**, through **115_N** altogether, is discussed in greater detail below.

[0047] The exemplary LED array driver circuit **100** further comprises a first, time-division or “energizing” multiplexer (or other array of power switches) **150**, which provides for individually and selectively allowing current to flow through each of the series of LEDs **110₁**, **110₂**, **110₃**, through **110_N**, i.e., turning on or off any selected series of LEDs **110₁**, **110₂**, **110₃**, through **110_N**. Under the control of the controller **125**, the multiplexer **150** is configured to allow current through one or more of the series of LEDs **110₁**, **110₂**, **110₃**, through **110_N** in any combination, and for any selected duration (time period or time slot), such as one series of LEDs **110**, two series of LEDs **110**, none of the series of LEDs **110**, or all of the series of LEDs **110**, for example.

[0048] The illustrated exemplary power converter **120** comprises a DC voltage source **105**, a filter capacitor **135**, an inductor **130**, a switch **140**, a peak current sense resistor (**R1**) **155**, and the controller **125**. The power converter **120** may be of any topology which is capable of or adapted to deliver a controlled current level to a load, such as a current having a controlled peak to average current ratio, and may be isolated or non-isolated, including a Buck, Boost, Buck-Boost, or Flyback configuration or topology. The DC voltage source **105** may be a battery element or an AC/DC converter (not separately illustrated), such as a diode bridge or rectifier, or a more complex, off line switching power supply with power

factor correction, for example. Also for example, the DC voltage source **105** also may be an AC/DC converter connected to phase modulation AC device (typically wall dimmer) via an impedance matching block, not separately illustrated. The power converter **120** may operate in a continuous mode of operation (illustrated in FIG. 5) or a discontinuous mode of operation (illustrated in FIG. 6).

[0049] The controller **125** may receive input from a wide variety of sources, including open or closed-loop feedback of various signals and measurements from within the LED array driver circuit **100**, as discussed in greater detail below. Not separately illustrated, the controller **125** may be coupled within a larger system, such as a computer-controlled lighting system in a building, and may interface with other computing elements using a wide variety of data transmission protocols, such as DMX 512, DALI, IC squared, etc.

[0050] The memory **175**, which may include a data repository (or database) **180**, may be embodied in any number of forms, including within any computer or other machine-readable data storage medium, memory device or other storage or communication device for storage or communication of information, currently known or which becomes available in the future, including, but not limited to, a memory integrated circuit (“IC”), or memory portion of an integrated circuit (such as the resident memory within a controller **125** or processor IC), whether volatile or non-volatile, whether removable or non-removable, including without limitation RAM, FLASH, DRAM, SDRAM, SRAM, MRAM, FeRAM, ROM, EPROM or E²PROM, or any other form of memory device, such as a magnetic hard drive, an optical drive, a magnetic disk or tape drive, a hard disk drive, other machine-readable storage or memory media such as a floppy disk, a CDROM, a CD-RW, digital versatile disk (DVD) or other optical memory, or any other type of memory, storage medium, or data storage apparatus or circuit, which is known or which becomes known, depending upon the selected embodiment. In addition, such computer readable media includes any form of communication media which embodies computer readable instructions, data structures, program modules or other data in a data signal or modulated signal, such as an electromagnetic or optical carrier wave or other transport mechanism, including any information delivery media, which may encode data or other information in a signal, wired or wirelessly, including electromagnetic, optical, acoustic, RF or infrared signals, and so on. The memory **175** is adapted to store various look up tables, parameters, coefficients, other information and data, programs or instructions (of the software of the present invention), and other types of tables such as database tables, discussed below.

[0051] The controller **125** may be any type of controller or processor, and may be embodied as one or more controllers **125**, adapted to perform the functionality discussed below. As the term controller or processor is used herein, a controller **125** may include use of a single integrated circuit (“IC”), or may include use of a plurality of integrated circuits or other components connected, arranged or grouped together, such as controllers, microprocessors, digital signal processors (“DSPs”), parallel processors, multiple core processors, custom ICs, application specific integrated circuits (“ASICs”), field programmable gate arrays (“FPGAs”), adaptive computing ICs, associated memory (such as RAM, DRAM and ROM), and other ICs and components. As a consequence, as used herein, the term controller (or processor) should be understood to equivalently mean and include a single IC, or

arrangement of custom ICs, ASICs, processors, microprocessors, controllers, FPGAs, adaptive computing ICs, or some other grouping of integrated circuits which perform the functions discussed below, with associated memory, such as microprocessor memory or additional RAM, DRAM, SDRAM, SRAM, MRAM, ROM, FLASH, EPROM or E²PROM. A controller (or processor) (such as controller 125), with its associated memory, may be adapted or configured (via programming, FPGA interconnection, or hard-wiring) to perform the methodology of the invention, as discussed below. For example, the methodology may be programmed and stored, in a controller 125 with its associated memory (and/or memory 175) and other equivalent components, as a set of program instructions or other code (or equivalent configuration or other program) for subsequent execution when the processor is operative (i.e., powered on and functioning). Equivalently, when the controller 125 may be implemented in whole or part as FPGAs, custom ICs and/or ASICs, the FPGAs, custom ICs or ASICs also may be designed, configured and/or hard-wired to implement the methodology of the invention. For example, the controller 125 may be implemented as an arrangement of controllers, microprocessors, DSPs and/or ASICs, collectively referred to as a "controller", which are respectively programmed, designed, adapted or configured to implement the methodology of the invention, in conjunction with a memory 175.

[0052] As indicated above, the controller 125 is programmed, using software and data structures of the invention, for example, to perform the methodology of the present invention. As a consequence, the system and method of the present invention may be embodied as software which provides such programming or other instructions, such as a set of instructions and/or metadata embodied within a computer readable medium, discussed above. In addition, metadata may also be utilized to define the various data structures of a look up table or a database 180. Such software may be in the form of source or object code, by way of example and without limitation. Source code further may be compiled into some form of instructions or object code (including assembly language instructions or configuration information). The software, source code or metadata of the present invention may be embodied as any type of code, such as C, C++, SystemC, LISA, XML, Java, Brew, SQL and its variations (e.g., SQL 99 or proprietary versions of SQL), DB2, Oracle, or any other type of programming language which performs the functionality discussed herein, including various hardware definition or hardware modeling languages (e.g., Verilog, VHDL, RTL) and resulting database files (e.g., GDSII). As a consequence, a "construct", "program construct", "software construct" or "software", as used equivalently herein, means and refers to any programming language, of any kind, with any syntax or signatures, which provides or can be interpreted to provide the associated functionality or methodology specified (when instantiated or loaded into a processor or computer and executed, including the controller 125, for example).

[0053] The software, metadata, or other source code of the present invention and any resulting bit file (object code, database, or look up table) may be embodied within any tangible storage medium, such as any of the computer or other machine-readable data storage media, as computer-readable instructions, data structures, program modules or other data, such as discussed above with respect to the memory 175, e.g., a floppy disk, a CDROM, a CD-RW, a DVD, a magnetic hard

drive, an optical drive, or any other type of data storage apparatus or medium, as mentioned above.

[0054] FIG. 4 is a timing diagram for a first exemplary LED array driver circuit 100, and illustrates the time division modulation for current regulation in accordance with the teachings of the present invention. As illustrated, each series of LEDs 110₁, 110₂, 110₃, through 110_N will be provided with a selected and independent current level, through control (by controller 125) of the switching state of each channel (via multiplexer 150), for a selected time period (or duration), illustrated as first time period T_{Q1} for series of LEDs 110₁, second time period T_{Q2} for series of LEDs 110₂, third time period T_{Q3} for series of LEDs 110₃, fourth time period T_{Q4} for series of LEDs 110₄, through "Nth" time period T_{QN} for series of LEDs 110_N. The total time period for providing current to all of the series of LEDs 110₁, 110₂, 110₃, through 110_N is referred to herein as "T_c". Each of these time periods may be selected and varied during operation of the LED array driver circuit 100, providing time division modulation. Each energizing time period may be provided in any order or combination; for example, series of LEDs 110₃ may be provided with current for third time period T_{Q3}, followed by series of LEDs 110₂ being provided with current for second time period T_{Q2}, followed by both series of LEDs 110₁ and series of LEDs 110_N being provided with selected current levels for corresponding first and Nth time periods T_{Q1} and T_{QN}, respectively. In addition, the corresponding current levels provided during these time periods to each series of LEDs 110₁, 110₂, 110₃, through 110_N may be selected and varied during operation of the LED array driver circuit 100, as discussed in greater detail below, additionally providing for the average current regulation of the present invention. The intervals or time periods (illustrated as T_A, T_B, and T_C) between successive energizing time periods T_{Q1}, T_{Q2} through T_{QN} may also be selected and varied, depending upon the selected embodiment.

[0055] Referring to the average DC current in each channel (series of LEDs 110₁, 110₂, 110₃, through 110_N) as I_{ci}, (i.e., average DC current I_{C1} for series of LEDs 110₁, average DC current I_{C2} for series of LEDs 110₂, average DC current I_{C3} for series of LEDs 110₃, through average DC current I_{CN} for series of LEDs 110_N), then the average current I_c provided by the current source (in this case, power converter 120) is equal to

$$I_c = \sum_{i=1}^{i=N} I_{ci}.$$

With a period of time "T_c" to provide current (energize) all of the LED channels (all of the series of LEDs 110₁, 110₂, 110₃, through 110_N), then the time of energizing each channel (series of LEDs 110) will be

[0056]

$$T_{Qi} = \frac{I_{ci} T_c}{I_c}.$$

Referring to the switching cycle of power converter **120** as “T”, then

[0057]

$$T_{Qi} = m_i T,$$

where m_i is the number of cycles of the power converter **120** per channel (series of LEDs **110**). In exemplary embodiments, although not required, the period of time T_c and the cycle time T is selected such that m_i is an integer.

EXAMPLE 1

[0058] For a system having three series of LEDs **110**₁, **110**₂, and **110**₃, with average channel currents are initially set as I_{c1} =500 mA, I_{c2} =520 mA, and I_{c3} =480 mA, then $I_{c500+520+480}$ =1500 mA. Assuming T_c =1000 μs and T =1 μs, under the control of the controller **125** directing switching through multiplexer **150**, the power converter **120** will supply to each channel a current of 150 mA for the run times

$$T_{Q1} = \frac{500 \cdot 1000}{1500} = 333 \text{ } \mu\text{s},$$

$$T_{Q2} = \frac{520 \cdot 1000}{1500} = 347 \text{ } \mu\text{s}, \text{ and}$$

$$T_{Q3} = \frac{480 \cdot 1000}{1500} = 320 \text{ } \mu\text{s}$$

which will result in the following number of cycles of the power converter **120**: m_1 =333, m_2 =347, and m_3 =320.

[0059] Continuing with the example, we may now suppose that for any of various reasons, such as a change in junction temperature, a change in color output, etc., the current in channel one (series of LEDs **110**₁) only is to be adjusted to 275 mA, while the previous current levels are to be maintained in the remaining channels **2** and **3** (series of LEDs **110**₂ and series of LEDs **110**₃). Accordingly, the total average DC current to be provided by the power converter **120** is now I_c =275+520+480=1275 mA, resulting in:

$$T_{Q1} = \frac{275 \cdot 1000}{1275} = 216 \text{ } \mu\text{s},$$

$$T_{Q2} = \frac{520 \cdot 1000}{1275} = 408 \text{ } \mu\text{s}, \text{ and}$$

$$T_{Q3} = \frac{480 \cdot 1000}{1275} = 376 \text{ } \mu\text{s},$$

with m_1 = 216, m_2 = 408, and m_3 = 376.

[0060] An exemplary boost converter may be utilized to generate the required average current I_c in every channel. In addition to those illustrated below in the Examples, those skilled in the art may derive similar equations for other power converter (or current source) topologies.

EXAMPLE 2

[0061] For a continuous conduction mode (“CCM”), as illustrated in FIG. 5,

$$I_c = \frac{I_{p1i} + I_{p2i}}{2} \cdot \frac{t_{r1}}{T},$$

where

[0062] I_{p1i} —First peak current, Channel i;

[0063] I_{p2i} —Second peak current, Channel i; and

[0064] t_{ri} —reset time, Channel i.

Two variables are introduced for ease of explanation and derivation of equations, as follows:

$$a_i = \frac{I_{p2i}}{I_{p1i}},$$

namely, the ratio of the second peak current to the first peak current for a selected ith channel, and

$$b_i = \frac{t_{ri}}{T},$$

namely, the ratio of the switch **140** reset time (i.e., off or open time) to the total cycle time, resulting in a first peak current for an ith channel of:

$$I_{p1i} = \frac{2I_c}{(1 + a_i)b_i}.$$

[0065] Another expression for the first peak current I_{p1i} is:

$$I_{p1i} = I_{p2i} + \frac{V_{in} \cdot t_{oni}}{L}$$

where

[0066] V_{in} —Input voltage from DC voltage source **105**;

[0067] t_{oni} —on time, Channel i; and

[0068] L —inductance value of inductor **130**.

With substitutions

[0069]

$$I_{p1i} = \frac{V_{in} \cdot t_{oni}}{(1 - a_i)L}$$

then one more expression for I_{p1i} current is

$$I_{p1i} = I_{p2i} + \frac{(V_{out} - V_{in}) \cdot t_{ri}}{L}$$

where

[0070] V_{outi} —output voltage, ith channel;
or

$$I_{pli} = \frac{(V_{outi} - V_{in}) \cdot t_{ri}}{(1 - a_i)L}$$

From FIG. 5, for the continuous mode, we also have $T = t_{oni} + t_{ri}$, and the cycle time T is the same for all channels. Solving the above system of equations provides:

$$b_i = \frac{V_{in}}{V_{outi}}$$

and

$$a_i = \frac{2I_c \cdot L - (V_{outi} - V_{in})b_i^2 T}{2I_c L + (V_{outi} - V_{in})b_i^2 T}$$

[0071] As will be apparent from the derivation above, constant values may be known or selected for the inductance L of inductor 130, the cycle time T for the power converter 120, and the average DC current I_c , with corresponding values stored in memory 175. Using coefficients a_i and b_i , as an example, allows the computation (by controller 125) of the values of the first and second peak currents per channel, I_{p1i} and I_{p2i} , for operation of the power converter 120, provided the input and output voltages are known. Input voltage V_{in} (from DC voltage source 105) can be measured (e.g., through a sensor 185), selected or otherwise predetermined, with a value stored in memory 175. Initially, however, the output voltage V_{outi} across an individual series of LEDs 110 cannot be measured, because the computations occur before the power converter 120 provides current to the series of LEDs 110. In accordance with the present invention, therefore, the output voltage for a channel V_{outi} is initially predicted by employing digital models of the LEDs 110, with such models (as parameters) stored in memory 175 and utilized by the controller 125. Knowing the DC current through a selected series of LEDs 110, I_c , and using device specifications, data sheets, or other data provided by the LED device manufacturer, the output voltage (i.e., voltage drop) across each of the series of LEDs 110, as function of forward current, may be determined and provided in the form of a look up table stored in memory 175, in graphical form, or any in other form known to those skilled in the digital electronics design arts.

[0072] This more theoretical prediction, however, may have an error component, due to manufacturing tolerances, age, junction temperature related drift, or any other physical parameter or variable of LED performance, leading to a forward voltage change. In accordance with the exemplary embodiments of the present invention, the actual output voltage across each series of LEDs 110₁, 110₂, 110₃, through 110_N is measured, also using a sensor 185. Corresponding to such measurements, compensation coefficients are introduced, stored in memory 175, and utilized for subsequent output voltage prediction by the controller 125, for use in successive iterations (i.e. successive time periods “ T_c ”), as discussed above. These compensation coefficients can be saved and stored for each channel, and may be updated peri-

odically (comparatively infrequently), as they are associated with LED 110 device parameters which change comparatively slowly.

EXAMPLE 3

[0073] For a discontinuous conduction mode (“DCM”), as illustrated in FIG. 6, peak current I_{p1i} is defined as

$$I_{p1i} = \frac{2I_c T}{t_{ri}}$$

Also, for a boost configuration using DCM:

[0074]

$$I_{p1i} = \frac{V_{in} \cdot t_{oni}}{L}$$

and volt-seconds balance across inductor 130 is:

$$V_{in} \cdot t_{oni} = (V_{outi} - V_{in}) \cdot t_{ri}$$

The peak current I_{p1i} is then:

$$I_{p1i} = \frac{2I_c \cdot V_{outi}}{V_{in}}$$

[0075] The technique of generating the value of the output voltage V_{outi} is the same as described above for CCM of operation. The boundary between CCM and DCM may be found analytically by solving the following equation, or by determining if the actual cycle time, after current discharge by the inductor 130 is completed, is equal to the set cycle time T :

$$T = \frac{2I_c L V_{outi}^2}{V_{in}^2 (V_{outi} - V_{in})}$$

[0076] The amplitude of voltage ripple ΔV_i in a selected channel i is given by the following relationship, from which the capacitance values of capacitors 115 may be determined:

$$\Delta V_i = \frac{I_c \cdot T_{Qi}^2}{C_i \cdot T_c}$$

[0077] Referring again to FIG. 3, the controller 125 receives one or more inputs from any of various sources, such as from one or more sensors 185, or from other systems, such as a master lighting controller or control system (not separately illustrated), using any type of communication protocol, such as accommodating a standard interface between digital controllers such as DMX512, DALI, IC squared, radio frequency, Ethernet and many other communication protocols and/or interfaces, as known or becomes known in the art.

[0078] The various sensors 185 may be analog and/or digital, and will be coupled to corresponding input ports of the controller 125. For example, an analog peak current may be measured (e.g., across resistor 155, which functions as a peak

current sensor), and converted (utilizing an analog to digital converter, not separately illustrated), to provide a digital value of peak current for storage in memory 175. Such a measured peak current value may be compared within controller 125, such as through a comparator (not separately illustrated), with corresponding control provided by the controller 125 to the DC voltage source 105 and/or switch 140 to adjust peak current levels. As indicated above, LED models, other parameters, specifications, coefficients, etc., are stored in digital form in memory 175. The controller 125 also generally includes buffer (or other driver) circuits to provide the switching control for the multiplexer (or other power switches) 150 and the switching (of switch 140) of the exemplary LED array driver circuit 100.

[0079] The various sensors 185 providing input to analog and/or digital ports of the controller 125 generate sense signals from each channel, the exemplary LED array driver circuit 100 environment, and potentially the larger lighting system environment. Exemplary sensors 185, for example and without limitation, may be sensors for: electrical (output voltage, string current), optical (brightness, wavelengths emission, color temperature, chromaticity, radiant power, luminous power in), thermal (junction temperature, ambient temperature), environmental (ambient lighting), mechanical (displacement, angular, strain, velocity, acceleration), magnetic, hall sensors, and more specific sensors providing signals related to the functional purposes of the system (e.g., residential illumination, architectural, signage, automotive lighting, backlighting, emergency lighting, naval lighting and others).

[0080] In exemplary embodiments, the controller 125 receives input control signals and feedback (or sensed) signals to generate the average DC currents to be set for each channel I_{ci} and the duty cycle for the time-division modulation average current control of the exemplary LED array driver circuit 100 in accordance with the present invention. For example, in an exemplary embodiment, DC currents I_{ci} for each channel may be determined by control signals coming from an overall system controller, such as based upon the type or manufacture of LEDs used in the LED array 110 (series of LEDs 110₁, 110₂, 110₃, through 110_N). In another exemplary embodiment, DC currents I_{ci} for each channel may be determined as a result of specific algorithms, with the controller 125 processing LED feedback (or sensed) information and adjusting the amplitude of average currents I_{ci} to compensate for unwanted changes and age drift of the LED system in any area of electrical, optical, thermal and functional performance. The controller 125 also utilizes the digital models of electrical behavior for each string of LEDs (series of LEDs 110₁, 110₂, 110₃, through 110_N) by supplying forward current using the models and determining error coefficients for each model by comparing the actual output voltages across each series of LEDs 110 (measured and fed back) with the predicted output voltages, as discussed above.

[0081] The controller 125 is also the functional controller of the converter 120, selecting the cycle time “T” of the converter 120 and determining the peak current for each channel I_{pis} , based on its input signals, discussed above. The controller 125 also synchronizes this set value of the peak current with one of the active LED channels (series of LEDs 110), computes the energizing time periods or durations (on times or run times) of the channels, T_{Qi} , and controls the status of the multiplexer 150 switching according to these required energizing time periods (on times or run times) T_{Qi} ,

synchronizing such switching with the corresponding set values of I_{pis} for each series of LEDs 110₁, 110₂, 110₃, through 110_N.

[0082] FIG. 7 is a circuit and block diagram illustrating a second exemplary LED array driver circuit 200, implemented as a boost-type converter, in accordance with the teachings of the present invention. The second exemplary LED array driver circuit 200 comprises a (switching) power converter 220, a parallel array of LEDs 110 (series of LEDs 110₁, 110₂, 110₃, through 110_N) with corresponding bypass filter capacitors 115 and voltage dividers 230 (discussed below), a first, time-division multiplexer (or other array of power switches) 150, a second, current sense multiplexer 250, a third, voltage sense multiplexer 210, a controller 225, a memory 175, and a plurality of resistors 265 in series with each channel (illustrated as corresponding resistors 265₁, 265₂, 265₃, through 265_N). In exemplary embodiments, the second exemplary LED array driver circuit 200 one or more of the sensors 185 are implemented, for example, utilizing voltage divider 240 and voltage dividers 230₁, 230₂, 230₃, through 230_N.

[0083] In addition to the features previously discussed for power converter 120, the power converter 220 further comprises a voltage divider 240, a (total) current sense resistor 255, and corresponding blocking (Schottky) diodes 145 (for each series of LEDs 110₁, 110₂, 110₃, through 110_N). In addition, the switch 140 is implemented as a MOSFET 140₁, having its drain connected to inductor 130 and its source connected to the current sense resistor 255.

[0084] The parallel array of LEDs 110 also comprises a plurality of series-connected LEDs, i.e., independent series or “strings” of LEDs, illustrated as “N” individual series of LEDs 110₁, 110₂, 110₃, through 110_N, as previously discussed. Each such channel may also comprise a corresponding bypass filter capacitor 115 connected in parallel with each series of LEDs 110₁, 110₂, 110₃, through 110_N, illustrated as corresponding capacitors 115₁, 115₂, 115₃, through 115_N, as previously discussed. Each such channel also comprises a corresponding voltage divider 230 also connected in parallel with each series of LEDs 110₁, 110₂, 110₃, through 110_N, illustrated as corresponding voltage dividers 230₁, 230₂, 230₃, through 230_N. A plurality of corresponding output current sense resistors (265₁, 265₂, 265₃, through 265_N) are also utilized, as illustrated.

[0085] The controller 225 has all of the functionality of the controller 125 previously discussed, plus the additional functionality discussed below. In addition to the time-division multiplexer (or other array of power switches) 150 and switch 140, the voltage sense multiplexer 210 and current sense multiplexer 250 are also under the control of the controller 225. As discussed above, the exemplary LED array driver circuit 200 further comprises a first, time-division or “energizing” multiplexer (or other array of power switches) 150, which provides for individually and selectively allowing current to flow through each of the series of LEDs 110₁, 110₂, 110₃, through 110_N, i.e., turning on or off any selected series of LEDs 110₁, 110₂, 110₃, through 110_N. Under the control of the controller 225, when the time division multiplexer 150 is switched to a selected LED series 110 (of the plurality of series of LEDs 110₁, 110₂, 110₃, through 110_N) for allowing current to flow through that selected LED series 110 for a selected period of time (T_{QN}), the voltage sense multiplexer 210 and current sense multiplexer 250 are concurrently switched for corresponding sensing of the voltage and current levels for the same selected LED series 110, as follows: (1)

the voltage sense multiplexer **210** is concurrently switched to the voltage divider **230** which is coupled in parallel to the same selected LED series **110**, for output voltage detection (sensing) for that selected channel; and (2) the current sense multiplexer **250** is also switched to the same selected LED series **110** for detection (sensing) of the current flowing through the selected LED series **110**.

[0086] Functional blocks of the controller **225** are also illustrated in FIG. 7, including one or more analog-to-digital (A/D) converters **205**, one or more comparators **215**, control logic **235**, and switching buffers (or drivers) **245** (for controlling the switching of the various multiplexers **150**, **210**, **250** for the time-division modulation of the present invention. As illustrated, corresponding voltages, representing: (1) input voltage (from voltage divider **240**), (2) an output voltage across a selected series of LEDs **110₁**, **110₂**, **110₃**, through **110_N** (from the corresponding voltage divider **230**) selected via voltage sense multiplexer **210**, (3) peak current (from current sense resistor **255**), and (4) output current through a selected series of LEDs **110₁**, **110₂**, **110₃**, through **110_N** (across output current sense resistors (**265₁**, **265₂**, **265₃**, through **265_N**) selected via current sense multiplexer **250**), are provided to corresponding A/D converters **205**, and are then correspondingly compared in comparators **215**, with the corresponding results provided to control logic **235**, for use in determining the current to be provided to each channel (driving the various multiplexers **150**, **210** and **250** via switching buffers **245**) for the corresponding time duration (T_{ON}) for the time-division modulation of the present invention, as discussed above. Not separately illustrated, the controller **225** may also include an oscillator (for clocking the various components) and a voltage regulator.

[0087] In this exemplary LED array driver circuit **200**, using corresponding comparators **215** and control logic **235**: (1) actual peak current (from current sense resistor **255**) may be compared to the set or predetermined peak current (from an input or stored in memory **175**), and if sufficiently different, adjusted accordingly; (2) actual output current through a selected series of LEDs **110₁**, **110₂**, **110₃**, through **110_N** (across output current sense resistors (**265₁**, **265₂**, **265₃**, through **265_N**) may be compared to the corresponding set or predetermined output current (from an input or stored in memory **175**), and if sufficiently different, adjusted accordingly; (3) input voltage (from voltage divider **240**) may be compared to the set or predetermined input voltage level (from an input or stored in memory **175**), and if sufficiently different, adjusted accordingly; and (4) an output voltage across a selected series of LEDs **110₁**, **110₂**, **110₃**, through **110_N** (from the corresponding voltage divider **230**) may be compared to the corresponding set or predetermined output voltage level (from an input or stored in memory **175**), and if sufficiently different, adjusted accordingly.

[0088] The exemplary LED array driver circuit **200** is implemented based on the following hysteretic process of time-division modulation, consisting of the following steps, implemented in the controller **225** and the other specified components:

[0089] (1) Setting values of DC currents in each channel, based on input signal.

[0090] (2) Calculating the source DC current I_c as substantially or about equal to sum of each channel DC current I_{ci} :

$$I_c = \sum_{i=1}^{i=n} I_{ci}.$$

[0091] (3) Monitoring current in the inductor **130** of the power converter **220** and when this current is equal to zero, sequentially turning on the power switch of a selected series of LEDs **110₁**, **110₂**, **110₃**, through **110_N** (the "active" string) via the time-division multiplexer **150**, while keeping the rest of the power switches in an off state, also via the time-division multiplexer **150**.

[0092] (4) Correspondingly and synchronously turning on the switches within voltage sense multiplexer **210** and current sense multiplexer **250**, corresponding to the active string LEDs **110** (the selected series of LEDs **110₁**, **110₂**, **110₃**, through **110_N**), for the corresponding time-division modulation periods or durations.

[0093] (5) Monitoring the DC current level in the active string, and (a) if the current is higher than the corresponding predetermined or set value, deactivate the current series of LEDs **110** and activating the next series of LEDs **110** in the sequence; or (b) if the DC current level is less than the corresponding predetermined or set value, continuing the process of energizing the selected active series of LEDs **110**.

[0094] (6) Measuring the operating input DC Voltage (across voltage divider **240**).

[0095] (7) Measuring operating output voltage of the selected, active series of LEDs **110**, (across a corresponding voltage divider **230**).

[0096] (8) Calculating peak current of the power converter **220** according to

$$I_{pli} = \frac{2I_c \cdot V_{outi}}{V_{in}}.$$

[0097] (9) Alternatively the last three steps (6, 7 and 8 above) can be implemented by measuring the reset time t_r ; measuring actual cycle time T ; and calculating the peak current of the converter **220** as

$$I_{pli} = \frac{2I_c T}{t_r}.$$

[0098] (10) Running converter **220** in constant peak current mode in the DCM mode with preselected constant cycle time and peak current value calculated separately for each string.

[0099] (11) Monitoring DC current in the active, selected series of LEDs **110₁**, **110₂**, **110₃**, through **110_N**: when DC current reaches the corresponding predetermined or set value, terminating the switching cycle of the converter **220**, and if the switch **140₁** is currently in an off state, waiting until current in the inductor **130** drops to about zero before starting the process of energizing of the next selected series of LEDs **110₁**, **110₂**, **110₃**, through **110_N**; or if the switch **140₁** is currently in an on state, turning the switch **140₁** off (e.g., immediately) and then waiting until current in the inductor **130** drops to about zero before starting the process of energizing of the next selected series of LEDs **110₁**, **110₂**, **110₃**, through **110_N**.

[0100] (12) At the end of sequence of energizing each of the series of LEDs **110₁**, **110₂**, **110₃**, through **110_N**, updating all parameters of the operation and driving of the exemplary LED array driver circuit **200** for each channel, and starting the next driving cycle of the exemplary LED array driver circuit **200**.

[0101] The required DC current level of each series of LEDs **110₁**, **110₂**, **110₃**, through **110_N** is supplied as input to control logic **235**. The control logic **235** calculates the total equivalent DC current of the converter **220** for the total period T which will include a sequential activation of all series of LEDs **110**. The peak current is adjusted for each series of LEDs **110** by measuring input voltage via voltage divider **240** and one of the A/D converters **205**. Output voltage of the active, selected series of LEDs **110₁**, **110₂**, **110₃**, through **110_N** is sensed by the corresponding voltage divider **230**, selected via voltage sense multiplexer **210** and input to one of the A/D converters **205**. The selection by the voltage sense multiplexer **210** is synchronized with the time division multiplexer **150**, so only active series of LEDs **110** (power switch is on) is selected for voltage sensing. The switch **140₁** of the boost converter **220** is controlled by the switching buffers **245**, based on determinations by the control logic **235**, comparing the sensed peak current across resistor **255** with the predetermined or set value for each series of LEDs **110**. The set value of peak current may be different for each series of LEDs **110**, depending on its DC voltage and is determined by comparisons performed by control logic **235**. Via switching buffers **245**, the control logic **235** controls the switching status, switching selections, and switching synchronization of the time division multiplexer **150**, the current sense multiplexer **250**, and the voltage sense multiplexer **210**, such that only the active series of LEDs **110** is sensed.

[0102] In this embodiment, the time periods for each of the series of LEDs **110** for the time division modulation is not required to be analytically determined. Because the DC current supplied by a boost converter **220** is much higher than any required DC current of the selected series of LEDs **110**, the actual DC current in the active series of LEDs **110** will always be ramping up. Based on the monitored DC current in the active series of LEDs **110**, when comparator **215** and/or control logic **235** identifies that the DC current in the active series of LEDs **110** is equal to the predetermined or set current value for the selected series of LEDs **110**, that selected series of LEDs **110** will be deactivated. For example, threshold levels of the comparator **215** may be set to a unique value for each series of LEDs **110**.

[0103] Additional configurations for switching and sensing, for the exemplary LED array driver circuits **100**, **200** are illustrated in FIGS. **8**, **9**, **11** and **12**. FIG. **8** is a circuit **300** diagram illustrating high side driving (**301**), as an exemplary switching implementation of a time-division multiplexer **150₁**, with low side sensing (**302**), for a series of LEDs **110_N** in accordance with the teachings of the present invention. FIG. **9** is a circuit diagram illustrating differential high side sensing (**303**) and low side driving (**304**), as an exemplary switching implementation of a time-division multiplexer **150₂**, for a series of LEDs **110_N** in accordance with the teachings of the present invention. As illustrated, the switching through the time division multiplexer **150** may be provided on either the high (**150₁**) or low (**150₂**) sides of each series of LEDs **110₁**, **110₂**, **110₃**, through **110_N**. High side switching (FIG. **8**) may be slightly more expensive and slower than low side switching, but may provide greater accuracy. Accord-

ingly, if the speed of system performance over its accuracy is more important, then high side sensing and low side switching may be selected. Those of skill in the art will recognize that different combinations of low and high side switching (drivers) and sensing circuits may be utilized to achieve the best performance of an LED array driver circuit **100**, **200**.

[0104] FIG. **10** is a graphical diagram illustrating simulation of a boost LED array driver circuit, for three series of LEDs, in accordance with the teachings of the present invention. FIG. **10** is illustrated for a V_{in} of 5 V, a filter **115** capacitance of 2.2 μ F, a first series of three LEDs (LEDs₁) having a current setting of 50 mA, a second series of four LEDs (LEDs₂) having a current setting of 40 mA, and a third series of five LEDs (LEDs₃) having a current setting of 30 mA, with dimming to 50% at 100 μ s and returning back to 100% after 240 μ s. DC current ripple may be adjusted by a selection of appropriate values of filter capacitors **115**. In turn, this selection depends on the switching frequency of the switch **140**, **140₁** and the cycle time of time division multiplexer **150**, with a higher switching frequency and smaller cycle time T_c enabling a smaller filter **115** capacitance to achieve the same ripple current. As illustrated in FIG. **10**, time division modulation creates a relatively poor response, based on the time required to discharge or charge filter capacitors **115**. If duty cycle of switching (of switch **140**, **140₁**) is small and cycle time T_c is small, that may considerably affect the response of the system to the required accuracy and speed of change of lighting intensity, color temperature adjustments, or creating color effects.

[0105] FIGS. **11** and **12** are circuit diagrams illustrating a first circuit **310** configuration and a second circuit **330** configuration, respectively, of an LED array for independent time division modulation. FIG. **13** is a graphical diagram illustrating simulation of LED current in a boost LED array driver circuit, for three LED strings implemented according to the configuration of circuit **310** of FIG. **11**, with simultaneous switching as illustrated for a first series of three LEDs (LEDs₁) having a current setting of 50 mA, a second series of four LEDs (LEDs₂) having a current setting of 40 mA, and a third series of five LEDs (LEDs₃) having a current setting of 30 mA.

[0106] As illustrated in FIG. **11**, the time division multiplexer **150** is implemented in a distributed manner, as the illustrated time division multiplexer **150₃** having corresponding switches on both the high and low sides of each series of LEDs **110₁**, **110₂**, **110₃**, through **110_N**. As illustrated in FIG. **12**, the time division multiplexer **150** is also implemented in a distributed manner, as the illustrated time division multiplexer **150₄** having corresponding switches on the high side of each series of LEDs **110₁**, **110₂**, **110₃**, through **110_N** and one switch on the low side of filter capacitors **115**.

[0107] Also as illustrated in FIG. **11**, the configuration of circuit **310** provides for fast switching speeds for the time division modulation, allowing independent time division modulation for each series of LEDs **110₁**, **110₂**, **110₃**, through **110_N** by substantially simultaneously turning on/off corresponding pairs of switches **315_{2A}** and **315_B** of the time division multiplexer **150₃** for each series of LEDs **110₁**, **110₂**, **110₃**, through **110_N**, illustrated as corresponding switching pairs **315_{1A}** and **315_{1B}**, **315_{2A}** and **315_{2B}**, through **315_{NA}** and **315_{NB}**. The edges of current pulses through the LEDs **110** may be very fast, on the order of tens to hundreds of nanoseconds, unless specifically slowed down to curtail electromagnetic interference (EMI). The switches **315_{1A}** and **315_{1B}**,

through **315_{NA}** and **315_{NB}**, may be unidirectional (like MOSFETs with body diode conducting when capacitors **115** are being charged). For less power dissipation a Schottky diode **329** may be connected in parallel with the MOSFET body diode.

[0108] When individual time division modulation of each series of LEDs **110₁**, **110₂**, **110₃**, through **110_N** is not required, such as for energizing one or more of the series of LEDs at substantially the same time, such as in various groups, the time division multiplexer **150** may be simplified by having a corresponding plurality of high side switches **315_A** and only one low side switch **315_B** comprising time division multiplexer **150₄**, as illustrated in FIG. **12**. This configuration of circuit **330** operates similarly to circuit **310**, except for simultaneous connection or disconnection of filter capacitors **115** from series of LEDs **110₁**, **110₂**, **110₃**, through **110_N**. The current in the series of LEDs **110₁**, **110₂**, **110₃**, through **110_N** is completely disabled when all switches **315** are turned off synchronously. To enable current flow in a selected series of LEDs **110₁**, **110₂**, **110₃**, through **110_N**, the switch **315_B** and one of the switches **315_{1A}**, **315_{2A}**, through **315_{NA}** (corresponding to the selected series of LEDs **110**) are turned on.

[0109] Continuing to refer to FIGS. **11** and **12**, each series, or any selected series of LEDs **110₁**, **110₂**, **110₃**, through **110_N**, may be separately and independently energized as follows, for each such series of LEDs **110**: (1) establish DC current in each series of LEDs **110** by DC current regulation, keeping the one of the switches **315_{1A}**, **315_{2A}**, through **315_{NA}** of the time division multiplexer **150₃** or time division multiplexer **150₄** in an on or off state as required to regulate the DC level of the current through the selected series of LEDs **110₁**, **110₂**, **110₃**, through **110_N**, and keeping one of the corresponding filter capacitor switches **315_{1B}**, **315_{2B}**, through **315_{NB}** in a corresponding on or off state (or keeping the single switch **315_B** in an on state continuously); (2) determining the corresponding time period (or duty ratio) for time-division modulation for each series of LEDs **110₁**, **110₂**, **110₃**, through **110_N** (a duty ratio 100% will mean that string is permanently on DC current regulation); (3) for each series of LEDs **110₁**, **110₂**, **110₃**, through **110_N**, monitoring elapsed time and/or counting the number of cycles “m” of the switching of the power converter, and when either is substantially equal to the corresponding predetermined or set value, monitoring the current in inductor **130** of the converter, and when the inductor **130** current is substantially zero, turning off the corresponding switch **315_{1A}**, **315_{2A}**, through **315_{NA}** of the time division multiplexer **150₃** or time division multiplexer **150₄** and turning off the corresponding filter capacitor switches **315_{1B}**, **315_{2B}**, through **315_{NB}** or turning off the single switch **315_B** of a series of LEDs **110** to be disabled; (4) optionally determining the converter peak current I_{pi} based on source current I_c and parameters of the active series of LEDs **110**; and (5) at the end of the particular switching cycle of the converter, turning on the next one of the switches **315_{1A}**, **315_{2A}**, through **315_{NA}** and corresponding filter capacitor switches **315_{1B}**, **315_{2B}**, through **315_{NB}** (or the single switch **315_B**) to energize the next selected series of LEDs **110₁**, **110₂**, **110₃**, through **110_N**.

[0110] FIG. **14** is a flow diagram illustrating an exemplary method of time-division modulation for separately and independently energizing a selected series of LEDs **110₁**, **110₂**, **110₃**, through **110_N** in accordance with the teachings of the present invention, and provides a useful summary of exemplary features of the present invention. The method begins, start step **400**, with determining corresponding values or lev-

els of a DC current for each series (or channel) of LEDs **110₁**, **110₂**, **110₃**, through **110_N**, step **405**. The method calculates the source DC current I_c , to be provided by the converter **120**, **220**, step **410**, as substantially or about equal to the sum of each channel DC current I_{ci} , namely,

$$I_c = \sum_{i=1}^{i=n} I_{ci}.$$

A total period “T” is determined for switching current to all of the series of LEDs **110₁**, **110₂**, **110₃**, through **110_N**, and a corresponding time period for energizing each selected series of LEDs **110₁**, **110₂**, **110₃**, through **110_N** is determined, step **415**, as substantially equal to a proportion of the total period (for switching current to all of the series of light-emitting diodes of the plurality of series of light-emitting diodes), determined as a ratio of the corresponding current for the selected corresponding series of light-emitting diodes to the total (average) current provided by the power converter, namely,

$$T_{Qi} = \frac{I_{ci} T_c}{I_c}.$$

The operating mode of the converter is selected, namely, whether operating in continuous or discontinuous current mode, and a switching frequency of the power converter **120**, **220** may also be selected (based on whether the power converter **120**, **220** is to be operated in discontinuous or continuous current mode), step **420**. Those of skill in the art will appreciate that steps **405**, **410**, **415** and **420** may occur in any order or concurrently, and also may be performed in advance of the operation of the system or apparatus.

[0111] Continuing to refer to FIG. **14**, during operation of the system or apparatus, step **425**, the operating input DC voltage of the converter **120**, **220** is measured, such as across a voltage divider **240**. In step **430**, the output DC voltage for each series of LEDs **110** is predicted initially, such as by using various models or device parameters, and is then updated subsequently (using the error coefficients) based on measurements of the corresponding output voltage across the selected series of LEDs **110₁**, **110₂**, **110₃**, through **110_N**, typically determined as a corresponding voltage across a voltage divider **230**. A first peak current is also calculated for CCM or a peak current for DCM, step **435**. Those of skill in the art will also appreciate that the prediction step **430**, and determination step **435** may occur in any order or concurrently, and also may be performed in advance of the operation of the system or apparatus (for an initial prediction).

[0112] As previously mentioned, the prediction of the output voltage across each series of LEDs **110₁**, **110₂**, **110₃**, through **110_N** is typically based on device parameters, such as a manufacturer’s specification of a forward voltage drop as function of a forward current of LED and the number of LEDs in series, for a selected series of LEDs **110₁**, **110₂**, **110₃**, through **110_N**. The output voltage of each selected series of LEDs **110₁**, **110₂**, **110₃**, through **110_N** is also measured periodically to determine and/or update an error coefficient, such that the output voltage prediction is updated based on multiplying the predicted value by the error coefficient, for a more accurate output voltage prediction. This comparison of the

predicted and measured voltages allows compensation for any effects of manufacturing production variations and tolerances, LED junction temperature variations, age drift and other factors, any and all of which can contribute to changes of the electrical characteristics of LEDs 110.

[0113] The power converter 120, 220 is then operated with the constant peak current, constant cycle time and constant DC current I_c , step 440, and with driving each selected series of LEDs 110₁, 110₂, 110₃, through 110_N for the corresponding time-division T_{ON} time period or until the corresponding predetermined current level is reached, step 445, by switching each selected series of LEDs 110₁, 110₂, 110₃, through 110_N on and off, i.e., coupling to and uncoupling from the output of power converter 120, 220, generally at times when the power converter 120, 220 is building current in the inductor 130 and not supplying current to the output load (i.e., when the inductor 130 current is substantially zero). When monitoring of corresponding current levels is utilized in step 445 to implement the time-division multiplexing of the present invention, those having skill in the art will recognize that all or part of step 415 may be omitted from the methodology. Following each energizing of a selected series of LEDs 110₁, 110₂, 110₃, through 110_N, or following the energizing of all of the series of LEDs 110₁, 110₂, 110₃, through 110_N (e.g., at the end of a period “T”), all parameters of power converter 120, 220 operation and driving parameters for each series of LEDs 110₁, 110₂, 110₃, through 110_N are updated (e.g., such as for use in predicting corresponding output voltages), step 450. When the energizing of the series of LEDs 110₁, 110₂, 110₃, through 110_N is to be continued, step 455, the method returns to step 405 and iterates, and otherwise the method may end, returns step 460.

[0114] The apparatus, system and method of driving a single or plurality of series of LEDs 110₁, 110₂, 110₃, through 110_N may be used for controlling the performance of an LED system, for example, controlling brightness, color temperature, color control or dimming. Another significant and effective use of this method comprises local compensation of the drift of LED parameters due to junction temperature changes, age, manufacturing variations and tolerances, and other characteristics and parameters.

[0115] Another variation of the above time-division modulation may also be implemented. Rather than changing a duty ratio of each switching cycle of a power converter 120, 220, as is done with pulse-width modulation, the time-division modulation may also be implemented in DCM by skipping cycles of the power converter 120, 220, i.e., by shutting down the power converter 120, 220 for a predetermined number of cycles. For example, the number of cycles to be skipped is calculated, based on a full number of cycles m_i and the required time periods T_{ON} of the time-division modulation. The power converter 120, 220 is run in discontinuous current mode, with time-division modulation implemented by shutting down the power converter 120, 220 for a complete number of skipped cycles during one total period “T”. In this embodiment, there are fewer switching events than a driver with standard PWM, thus reducing EMI and simplifying power converter 120, 220 design for controlling EMI.

[0116] The above description of the power converter 120, 220 and regulator is exemplary. Those skilled in the art will recognize that any topology of power converter 120, 220 may be utilized, such as buck, buck boost, or flyback. A direct conversion of AC input into a controlled current source may also be achieved by different AC/DC topologies. Any number

of series of LEDs 110₁, 110₂, 110₃, through 110_N may be implemented, using a corresponding number of switches and/or multiplexers. Also, if the actual output voltage across each of the series of LEDs 110₁, 110₂, 110₃, through 110_N is expected to be the same, the output voltage may be measured for one selected series, rather than all, of LEDs 110₁, 110₂, 110₃, through 110_N.

[0117] Numerous advantages of the present invention are readily apparent. The various embodiments of the invention provide innumerable advantages for energizing a plurality of series (strings) of LEDs, using a single power converter and controller for an entire LED array, and does not utilize multiple, separate power converters and controllers for each LED string. The exemplary embodiments provide a multistring LED driver which controls current independently for each series of LEDs of the array, for corresponding effective color and brightness control, among other features, throughout the life span of the LEDs and corresponding changes in their functional parameters. In addition, the exemplary LED array drivers provide for local, faster and comprehensive LED regulation, providing local compensation of LED emission due to age and drift of such functional parameters, temperature changes of the LED junction, LED production characteristics variation, and variations of devices produced by different manufacturers. The exemplary LED array drivers are also backwards-compatible with legacy LED control systems, frees the legacy host computer for other tasks and allows such host computers to be utilized for other types of system regulation.

[0118] Although the invention has been described with respect to specific embodiments thereof, these embodiments are merely illustrative and not restrictive of the invention. In the description herein, numerous specific details are provided, such as examples of electronic and electrical components, materials, and structural variations, to provide a thorough understanding of embodiments of the present invention. One skilled in the relevant art will recognize, however, that an embodiment of the invention can be practiced without one or more of the specific details, or with other apparatus, systems, assemblies, components, materials, parts, etc. In other instances, well-known structures, materials, or operations are not specifically shown or described in detail to avoid obscuring aspects of embodiments of the present invention.

[0119] Reference throughout this specification to “one embodiment”, “an embodiment”, or a specific “embodiment” means that a particular feature, structure, or characteristic described in connection with the embodiment is included in at least one embodiment of the present invention and not necessarily in all embodiments, and further, are not necessarily referring to the same embodiment. Furthermore, the particular features, structures, or characteristics of any specific embodiment of the present invention may be combined in any suitable manner and in any suitable combination with one or more other embodiments, including the use of selected features without corresponding use of other features. In addition, many modifications may be made to adapt a particular application, situation or material to the essential scope and spirit of the present invention. It is to be understood that other variations and modifications of the embodiments of the present invention described and illustrated herein are possible in light of the teachings herein and are to be considered part of the spirit and scope of the present invention.

[0120] It will also be appreciated that one or more of the elements depicted in the Figures can also be implemented in

a more separate or integrated manner, or even removed or rendered inoperable in certain cases, as may be useful in accordance with a particular application. Integrally formed combinations of components are also within the scope of the invention, particularly for embodiments in which a separation or combination of discrete components is unclear or indiscernible. In addition, use of the term “coupled” herein, including in its various forms such as coupling or couplable, means and includes any direct or indirect structural, electrical or magnetic coupling, connection or attachment, or adaptation or capability for such a direct or indirect structural, electrical or magnetic coupling, connection or attachment, including integrally formed components and components which are coupled via or through another component. Furthermore, the disjunctive term “or”, as used herein and throughout the claims that follow, is generally intended to mean “and/or”, having both conjunctive and disjunctive meanings (and is not confined to an “exclusive or” meaning), unless otherwise indicated. As used in the description herein and throughout the claims that follow, “a”, “an”, and “the” include plural references unless the context clearly dictates otherwise. Also as used in the description herein and throughout the claims that follow, the meaning or “in” includes “in” and “on” unless the context clearly dictates otherwise.

[0121] The foregoing description of illustrated embodiments of the present invention, including what is described in the summary or in the abstract, is not intended to be exhaustive or to limit the invention to the precise forms disclosed herein. From the foregoing, it will be observed that numerous variations, modifications and substitutions are intended and may be effected without departing from the spirit and scope of the novel concept of the invention. It is to be understood that no limitation with respect to the specific methods and apparatus illustrated herein is intended or should be inferred. It is, of course, intended to cover by the appended claims all such modifications as fall within the scope of the claims.

It is claimed:

1. An apparatus for providing current independently to a series of light emitting diodes of a plurality of series of light-emitting diodes, the apparatus comprising:

- a power converter couplable to the plurality of series of light-emitting diodes, the power converter adapted to generate a current;
- a first multiplexer couplable to the plurality of series of light-emitting diodes; and
- a controller coupled to the power converter and to the first multiplexer, the controller adapted to provide for sequential and separate switching of the current through the first multiplexer to each of the series of light-emitting diodes, of the plurality of series of light-emitting diodes, for a corresponding period of time.

2. The apparatus of claim 1, wherein the controller is further adapted to provide for no switching of current through the first multiplexer to all remaining series of light-emitting diodes while current is switched to a selected series of light-emitting diodes of the plurality of series of light-emitting diodes.

3. The apparatus of claim 1, wherein the controller is further adapted to determine an average current provided by the power converter as about equal to a sum of a plurality of corresponding currents through the plurality of series of light-emitting diodes.

4. The apparatus of claim 3, wherein the controller is further adapted to determine a total period for switching current

to all of the series of light-emitting diodes of the plurality of series of light-emitting diodes.

5. The apparatus of claim 4, wherein the controller is further adapted to determine a corresponding time period for switching current to a selected corresponding series of light-emitting diodes as substantially equal to a proportion of the total period determined as a ratio of the corresponding current for the selected corresponding series of light-emitting diodes to the average current provided by the power converter.

6. The apparatus of claim 1, further comprising:

- a memory coupled to the controller, the memory adapted to store, as a look up table, a plurality of parameters corresponding to the plurality of series of light-emitting diodes.

7. The apparatus of claim 6, wherein the controller is further adapted to predict an output voltage across a selected series of light-emitting diodes based on the device parameters stored in memory and to revise the predicted output voltage based upon a measured output voltage across a selected series of light-emitting diodes.

8. The apparatus of claim 1, wherein the power converter further comprises a first voltage divider, and wherein the controller is further adapted to determine an input voltage across the first voltage divider.

9. The apparatus of claim 1, wherein the power converter further comprises a current sensor, and wherein the controller is further adapted to determine a peak input current through the current sensor.

10. The apparatus of claim 1, further comprising a plurality of second voltage dividers, each second voltage divider couplable in parallel to a corresponding series of light-emitting diodes of the plurality of series of light-emitting diodes, and wherein the controller is further adapted to determine a corresponding output voltage across the corresponding second voltage divider of the plurality of second voltage dividers.

11. The apparatus of claim 10, further comprising:

- a second multiplexer coupled to the plurality of second voltage dividers and the controller, and wherein the controller is further adapted to control switching of the second multiplexer to a selected second voltage divider of the plurality of second voltage dividers.

12. The apparatus of claim 1, further comprising:

- a third multiplexer couplable to the plurality of series of light-emitting diodes and coupled to the controller, and wherein the controller is further adapted to control switching of the third multiplexer to a selected series of light-emitting diodes of the plurality of series of light-emitting diodes for measuring a corresponding current through the selected series of light-emitting diodes.

13. The apparatus of claim 12, wherein the controller is further adapted to determine the corresponding period of time for switching of current to a selected series of light-emitting diodes based on a comparison of the measured corresponding current to a predetermined current level for the selected series of light-emitting diodes.

14. The apparatus of claim 1, wherein the first multiplexer further comprises:

- a plurality of switches, each switch of the plurality of switches correspondingly couplable to a first, high side of a corresponding series of light-emitting diodes of the plurality of series of light-emitting diodes.

15. The apparatus of claim 1, wherein the first multiplexer further comprises:

- a plurality of switches, each switch of the plurality of switches correspondingly couplable to a second, low side of a corresponding series of light-emitting diodes of the plurality of series of light-emitting diodes.

16. The apparatus of claim 1, wherein the first multiplexer further comprises:

- a plurality of first switches, each switch of the plurality of first switches correspondingly couplable to a first, high side of a corresponding series of light-emitting diodes of the plurality of series of light-emitting diodes; and
- a plurality of second switches, each switch of the plurality of second switches correspondingly couplable to a second, low side of a corresponding series of light-emitting diodes of the plurality of series of light-emitting diodes.

17. The apparatus of claim 1, further comprising:

- a plurality of capacitors, each capacitor of the plurality of capacitors couplable to a corresponding series of light-emitting diodes of the plurality of series of light-emitting diodes.

18. The apparatus of claim 17, wherein the first multiplexer further comprises:

- a plurality of first switches, each switch of the plurality of first switches correspondingly couplable to a first, high side of a corresponding series of light-emitting diodes of the plurality of series of light-emitting diodes; and
- a second switch couplable to the plurality of capacitors.

19. The apparatus of claim 1, wherein the controller is further adapted to determine the corresponding period of time for switching of current to a selected series of light-emitting diodes based on an integer multiple of a period of switching of the power converter.

20. The apparatus of claim 1, wherein the controller is further adapted to control switching of the first multiplexer to a selected series of light-emitting diodes of the plurality of series of light-emitting diodes when current through the power converter is substantially zero.

21. The apparatus of claim 1, wherein the controller is further adapted, in response to a first input, to adjust an output brightness of the plurality of series of light-emitting diodes by modifying each corresponding period of time of current switching to each of the series of light-emitting diodes.

22. The apparatus of claim 1, wherein the controller is further adapted, in response to a second input, to adjust an output color of the plurality of series of light-emitting diodes by modifying at least one corresponding period of time of current switching to at least one of the series of light-emitting diodes of the plurality of series of light-emitting diodes.

23. A lighting system, comprising:

- a plurality of series of light-emitting diodes;
- a power converter coupled to the plurality of series of light-emitting diodes, the power converter adapted to generate a current;
- a first multiplexer coupled to the plurality of series of light-emitting diodes; and
- a controller coupled to the power converter and to the first multiplexer, the controller adapted to provide for sequential and separate switching of the current through the first multiplexer to each of the series of light-emitting diodes, of the plurality of series of light-emitting diodes, for a corresponding period of time.

24. The system of claim 23, wherein the controller is further adapted to provide for no switching of current through

the first multiplexer to all remaining series of light-emitting diodes while current is switched to a selected series of light-emitting diodes of the plurality of series of light-emitting diodes.

25. The system of claim 23, wherein the controller is further adapted to determine an average current provided by the power converter as substantially equal to a sum of a plurality of corresponding currents through the plurality of series of light-emitting diodes.

26. The system of claim 25, wherein the controller is further adapted to determine a total period for switching current to all of the series of light-emitting diodes of the plurality of series of light-emitting diodes.

27. The system of claim 26, wherein the controller is further adapted to determine a corresponding time period for switching current to a selected corresponding series of light-emitting diodes as substantially equal to a proportion of the total period determined as a ratio of the corresponding current for the selected corresponding series of light-emitting diodes to the average current provided by the power converter.

28. The system of claim 23, further comprising:

- a memory coupled to the controller, the memory adapted to store, as a look up table, a plurality of parameters corresponding to the plurality of series of light-emitting diodes.

29. The system of claim 28, wherein the controller is further adapted to predict an output voltage across a selected series of light-emitting diodes based on the device parameters stored in memory and to revise the predicted output voltage based upon a measured output voltage across a selected series of light-emitting diodes.

30. The system of claim 23, wherein the power converter further comprises a first voltage divider, and wherein the controller is further adapted to determine an input voltage across the first voltage divider.

31. The system of claim 23, wherein the power converter further comprises a current sensor, and wherein the controller is further adapted to determine a peak input current through the current sensor.

32. The system of claim 23, further comprising a plurality of second voltage dividers, each second voltage divider coupled in parallel to a corresponding series of light-emitting diodes of the plurality of series of light-emitting diodes, and wherein the controller is further adapted to determine a corresponding output voltage across the corresponding second voltage divider of the plurality of second voltage dividers.

33. The system of claim 32, further comprising:

- a second multiplexer coupled to the plurality of second voltage dividers and the controller, and wherein the controller is further adapted to control switching of the second multiplexer to a selected second voltage divider of the plurality of second voltage dividers.

34. The system of claim 23, further comprising:

- a third multiplexer coupled to the plurality of series of light-emitting diodes and to the controller, and wherein the controller is further adapted to control switching of the third multiplexer to a selected series of light-emitting diodes of the plurality of series of light-emitting diodes for measuring a corresponding current through the selected series of light-emitting diodes.

35. The system of claim 34, wherein the controller is further adapted to determine the corresponding period of time for switching of current to a selected series of light-emitting

diodes based on a comparison of the measured corresponding current to a predetermined current level for the selected series of light-emitting diodes.

36. The system of claim **23**, wherein the first multiplexer further comprises:

a plurality of switches, each switch of the plurality of switches correspondingly coupled to a first, high side of a corresponding series of light-emitting diodes of the plurality of series of light-emitting diodes.

37. The system of claim **23**, wherein the first multiplexer further comprises:

a plurality of switches, each switch of the plurality of switches correspondingly coupled to a second, low side of a corresponding series of light-emitting diodes of the plurality of series of light-emitting diodes.

38. The system of claim **23**, wherein the first multiplexer further comprises:

a plurality of first switches, each switch of the plurality of first switches correspondingly coupled to a first, high side of a corresponding series of light-emitting diodes of the plurality of series of light-emitting diodes; and

a plurality of second switches, each switch of the plurality of second switches correspondingly coupled to a second, low side of a corresponding series of light-emitting diodes of the plurality of series of light-emitting diodes.

39. The system of claim **23**, further comprising:

a plurality of capacitors, each capacitor of the plurality of capacitors coupled to a corresponding series of light-emitting diodes of the plurality of series of light-emitting diodes.

40. The apparatus of claim **39**, wherein the first multiplexer further comprises:

a plurality of first switches, each switch of the plurality of first switches correspondingly coupled to a first, high side of a corresponding series of light-emitting diodes of the plurality of series of light-emitting diodes; and
a second switch coupled to the plurality of capacitors.

41. The system of claim **23**, wherein the controller is further adapted to determine the corresponding period of time for switching of current to a selected series of light-emitting diodes based on an integer multiple of a period of switching of the power converter.

42. The system of claim **23**, wherein the controller is further adapted to control switching of the first multiplexer to a selected series of light-emitting diodes of the plurality of series of light-emitting diodes when current through the power converter is substantially zero.

43. The system of claim **23**, wherein the controller is further adapted, in response to a first input, to adjust an output brightness of the plurality of series of light-emitting diodes by modifying each corresponding period of time of current switching to each of the series of light-emitting diodes.

44. The system of claim **23**, wherein the controller is further adapted, in response to a second input, to adjust an output color of the plurality of series of light-emitting diodes by modifying at least one corresponding period of time of current switching to at least one of the series of light-emitting diodes of the plurality of series of light-emitting diodes.

45. A method of selectively and independently providing power to a series of light emitting diodes of a plurality of series of light-emitting diodes, the method comprising:

generating an input DC current having a first average level; and

sequentially and separately switching the DC current to each of the series of light-emitting diodes, of the plurality of series of light-emitting diodes, for a corresponding period of time.

46. The method of claim **45**, further comprising:

switching no current to all remaining series of light-emitting diodes while switching the DC current to a selected series of light-emitting diodes of the plurality of series of light-emitting diodes.

47. The method of claim **45**, further comprising:

determining the first average level of DC current as substantially equal to a sum of a plurality of corresponding currents through the plurality of series of light-emitting diodes.

48. The method of claim **47**, further comprising:

determining a total period for switching current to all of the series of light-emitting diodes of the plurality of series of light-emitting diodes.

49. The method of claim **48**, further comprising:

determining a corresponding time period for switching current to a selected corresponding series of light-emitting diodes as substantially equal to a proportion of the total period determined as a ratio of the corresponding current for the selected corresponding series of light-emitting diodes to the average current provided by the power converter.

50. The method of claim **45**, further comprising:

storing, as a look up table, a plurality of parameters corresponding to the plurality of series of light-emitting diodes.

51. The method of claim **50**, further comprising:

predicting an output voltage across a selected series of light-emitting diodes, of the plurality of series of light-emitting diodes, based on the stored device parameters.

52. The method of claim **51**, further comprising:

measuring a corresponding output voltage for each series of light emitting diodes of the plurality of series of light-emitting diodes.

53. The method of claim **52**, further comprising:

updating the predicted output voltage across a selected series of light-emitting diodes, of the plurality of series of light-emitting diodes, based on a corresponding measured output voltage.

54. The method of claim **45**, further comprising:

determining an input voltage.

55. The method of claim **45**, further comprising:

determining a peak input DC current.

56. The method of claim **45**, further comprising:

determining a corresponding output voltage for each series of light emitting diodes of the plurality of series of light-emitting diodes.

57. The method of claim **45**, further comprising:

measuring a corresponding current through each series of light-emitting diodes of the plurality of series of light-emitting diodes.

58. The method of claim **45**, further comprising:

determining the corresponding period of time for switching of current to a selected series of light-emitting diodes based on a comparison of the measured corresponding current to a predetermined current level for the selected series of light-emitting diodes.

59. The method of claim 45, further comprising:
determining the corresponding period of time for switching of current to a selected series of light-emitting diodes based on an integer multiple of a period of switching of a power converter.
60. The method of claim 45, further comprising:
switching current to a selected series of light-emitting diodes of the plurality of series of light-emitting diodes when the input DC current is substantially zero.
61. The method of claim 45, further comprising:
in response to a first input, adjusting an output brightness of the plurality of series of light-emitting diodes by modifying each corresponding period of time of current switching to each of the series of light-emitting diodes.
62. The method of claim 45, further comprising:
in response to a second input, adjusting an output color of the plurality of series of light-emitting diodes by modifying at least one corresponding period of time of current switching to at least one of the series of light-emitting diodes of the plurality of series of light-emitting diodes.
63. An apparatus for providing current independently to a series of light emitting diodes of a plurality of series of light-emitting diodes, the apparatus comprising:
a power converter couplable to the plurality of series of light-emitting diodes, the power converter adapted to generate a current;
a first multiplexer couplable to the plurality of series of light-emitting diodes;
a memory adapted to store, as a look up table, a plurality of parameters corresponding to the plurality of series of light-emitting diodes; and
a controller coupled to the power converter, to the first multiplexer and to the memory, the controller adapted to provide for sequential and separate switching of the current through the first multiplexer to each of the series of light-emitting diodes, of the plurality of series of light-emitting diodes, for a corresponding period of time; the controller further adapted to determine an average current provided by the power converter as a substantially equal to sum of a plurality of corresponding currents through the plurality of series of light-emitting diodes, to determine a total period for switching current to all of the series of light-emitting diodes of the plurality of series of light-emitting diodes, and to determine a corresponding time period for switching current to a selected corresponding series of light-emitting diodes as substantially equal to a proportion of the total period determined as a ratio of the corresponding current for the selected corresponding series of light-emitting diodes to the average current provided by the power converter.
64. The apparatus of claim 63, wherein the controller is further adapted to predict an output voltage across a selected series of light-emitting diodes based on the device parameters stored in memory and to revise the predicted output voltage based upon a measured output voltage across a selected series of light-emitting diodes.
65. The apparatus of claim 63, further comprising:
a plurality of second voltage dividers, each second voltage divider couplable in parallel to a corresponding series of light-emitting diodes of the plurality of series of light-emitting diodes;
a second multiplexer coupled to the plurality of second voltage dividers and the controller; and
wherein the controller is further adapted to control switching of the second multiplexer to a selected second voltage divider of the plurality of second voltage dividers and to determine a corresponding output voltage across the corresponding second voltage divider of the plurality of second voltage dividers.
66. The apparatus of claim 63, further comprising:
a third multiplexer couplable to the plurality of series of light-emitting diodes and coupled to the controller; and
wherein the controller is further adapted to control switching of the third multiplexer to a selected series of light-emitting diodes of the plurality of series of light-emitting diodes for measuring a corresponding current through the selected series of light-emitting diodes.
67. The apparatus of claim 63, wherein the controller is further adapted to determine the corresponding period of time for switching of current to a selected series of light-emitting diodes based on a comparison of the measured corresponding current to a predetermined current level for the selected series of light-emitting diodes.
68. The apparatus of claim 63, wherein the controller is further adapted to determine the corresponding period of time for switching of current to a selected series of light-emitting diodes based on an integer multiple of a period of switching of the power converter.
69. The apparatus of claim 63, wherein the controller is further adapted, in response to a first input, to adjust an output brightness of the plurality of series of light-emitting diodes by modifying each corresponding period of time of current switching to each of the series of light-emitting diodes.
70. The apparatus of claim 63, wherein the controller is further adapted, in response to a second input, to adjust an output color of the plurality of series of light-emitting diodes by modifying at least one corresponding period of time of current switching to at least one of the series of light-emitting diodes of the plurality of series of light-emitting diodes.
- * * * * *