



US 20060220938A1

(19) **United States**(12) **Patent Application Publication****Leung et al.**(10) **Pub. No.: US 2006/0220938 A1**(43) **Pub. Date:****Oct. 5, 2006**(54) **DIGITAL PWM CONTROLLER**(52) **U.S. Cl. 341/155**

(76) Inventors: **Ka Y. Leung**, Austin, TX (US); **Kafai Leung**, Austin, TX (US); **Jinwen Xaio**, Austin, TX (US); **Chia-Ling Wei**, Austin, TX (US); **Alvin C. Storvik II**, Austin, TX (US); **Biranchinath Sahu**, Austin, TX (US); **Donald Alfano**, Round Rock, TX (US)


Correspondence Address:
HOWISON & ARNOTT, L.L.P
P.O. BOX 741715
DALLAS, TX 75374-1715 (US)



(21) Appl. No.: **11/096,597**(22) Filed: **Mar. 31, 2005****Publication Classification**

(51) **Int. Cl.**
H03M 1/12 (2006.01)

(57) **ABSTRACT**

A digital controller for controlling the operation of a DC-DC switching converter is disclosed. A digital feedback control system is provided for receiving an analog input voltage representing the output of the switching converter and digitally processing the analog input voltage by comparing it to a reference voltage and then determining analog drive signals to control the operation of the switching converter to provide a regulated output. The digital feedback control system operates in accordance with predetermined operating parametrics. The digital feedback control system also has monitoring inputs and control inputs. A microcontroller monitors the operation of the digital feedback control system and is able to change the operating parametrics under certain predetermined conditions.








FIG. 3









FIG. 4




















FIG. 12










FIG. 18




FIG. 20a







FIG. 20b












FIG. 23b








FIG. 28a




FIG. 28b




FIG. 29




FIG. 31




FIG. 30

FIG. 32





FIG. 33








FIG. 34








FIG. 36b







FIG. 37

FIG. 38








FIG. 45




FIG. 46




FIG. 42





FIG. 43








FIG. 47







FIG. 48





DIGITAL PWM CONTROLLER

CROSS-REFERENCE TO RELATED APPLICATIONS

[0001] This application is related to U.S. patent application Ser. No. _____, filed of even date herewith, and entitled "PID BASED CONTROLLER FOR DC-DC CONVERTER WITH POST-PROCESSING FILTERS" (Atty. Dkt. CYGL 27,105) and U.S. patent application Ser. No. _____, filed of even date herewith, and entitled "DIGITAL POWER SUPPLY CONTROLLER WITH VOLTAGE POSITIONING" (Atty. Dkt. No. CYGL-27,111), both of which are incorporated herein by reference in their entirety and claims priority in Provisional Application No. 60/591,463, filed Jul. 27, 2004, which is incorporated herein by reference in its entirety.

TECHNICAL FIELD OF THE INVENTION

[0002] The present invention pertains in general to DC-DC power converters and, more particularly, to a digital controller for a DC-DC power converter.

BACKGROUND OF THE INVENTION

Background of the Invention

[0003] DC-DC power converters are utilized in situations where one DC voltage is converted to another DC voltage. In one application, that associated with PC based systems, the processor requires a fairly low voltage and a fairly high current. Rather than convert an incoming AC voltage down to a very low DC voltage and then route the low DC voltage across a PC board, a higher DC voltage is output by the power supply, routed around to the various components on the PC board and then, proximate to the processor, the voltage is down converted to a very low level on the order of 1.0 V. This requires a conversion device to be disposed proximate to one or more high current integrated circuits on the board.

[0004] Typical DC-DC converters are fabricated using a switching supply that utilizes a switched inductor or capacitor configuration with the input DC voltage switched to the input thereof with a periodically waveform operating at a preset switching frequency with a varying duty cycle. By sensing the output voltage and comparing it with a desired voltage, the duty cycle of the waveform can be adjusted to control the amount of current supplied to the reactive components. This control is facilitated with a negative feedback control loop.

[0005] There are two types of feedback loops, an analog feedback loop and a digital feedback loop. The analog feedback loop is well understood and provides some advantages over the other type of feedback loop, the digital feedback loop. Each of the feedback loops has associated therewith a voltage sense input for sensing the supply output voltage and a pulse width modulator (PWM) for generating switching pulses for driving switches. The sensed voltage is compared in the analog domain to a desired operating DC voltage to generate an error voltage that is reduced to essentially zero volts at regulation. To compensate for loop phase shift, there is provided a compensator. This provides some phase lead in the feedback loop for the purpose of loop stability. The digital controller portion of the digital feed-

back loop is similar to the analog feedback loop. The voltage signal sense input utilizes an analog-to-digital converter (ADC) to convert the output voltage to a digital value and then compare this to a desired voltage to determine the difference voltage as an error voltage. A digital compensator then provides some phase lead to the feedback to maintain stability in the control loop. This digital error voltage is then converted into a varying pulse width for output to the driving switches on the switching converter. This in effect is a digital-to-analog converter. Typical switching converters such as buck converters can utilize single or multiple phases to facilitate the switching operation.

SUMMARY OF THE INVENTION

[0006] The present invention disclosed and claimed herein, in one aspect thereof, comprises a digital controller for controlling the operation of a DC-DC switching converter. A digital feedback control system is provided for receiving an analog input voltage representing the output of the switching converter and digitally processing the analog input voltage by comparing it to a reference voltage and then generating analog drive signals to control the operation of the switching converter to provide a regulated output. The digital feedback control system operates in accordance with predetermined operating parametrics. The digital feedback control system also has monitoring inputs and control inputs. A microcontroller monitors the operation of the digital feedback control system and is able to change the operating parametrics under certain predetermined conditions.

BRIEF DESCRIPTION OF THE DRAWINGS

[0007] For a more complete understanding of the present invention and the advantages thereof, reference is now made to the following description taken in conjunction with the accompanying Drawings in which:

[0008] **FIG. 1** illustrates an overall block diagram of a switching power supply;

[0009] **FIG. 2** illustrates a schematic diagram of the switching portion of a half-bridge power supply;

[0010] **FIG. 3** illustrates the timing diagram for the control pulses to the switching power supply;

[0011] **FIG. 4** illustrates a diagrammatic view of the digital controller utilized in conjunction with a buck converter;

[0012] **FIG. 5** illustrates a more detailed view of the digital controller;

[0013] **FIG. 6** illustrates a block diagram of the microcontroller portion of the digital controller;

[0014] **FIG. 6a** illustrates a diagrammatic view of a monolithic solution utilizing the embodiments of **FIGS. 4, 5 and 6**;

[0015] **FIG. 7** illustrates an overall block diagram of the Flash ADC;

[0016] **FIG. 8** illustrates a prior art Flash ADC;

[0017] **FIG. 9** illustrates a more detailed diagram of the comparator portion of the Flash ADC of the present disclosure;

[0018] **FIGS. 10 and 10a** illustrate a block diagram of a comparator string;

[0019] **FIG. 11** illustrates a timing diagram for the operation of the compare operation;

[0020] **FIG. 12** illustrates a schematic diagram of the bias circuitry for the resistor ladder;

[0021] **FIG. 13** illustrates a schematic diagram for the first comparator section;

[0022] **FIG. 14** illustrates a schematic diagram for the second comparator section;

[0023] **FIG. 15** illustrates a schematic diagram for the reconfigurable latch;

[0024] **FIG. 16** illustrates a gain response curve for the reconfigurable latch;

[0025] **FIG. 17** illustrates a schematic diagram for the dynamic latch;

[0026] **FIG. 18** illustrates a simplified block diagram of the PID;

[0027] **FIG. 19** illustrates a more detailed block diagram of the PID;

[0028] **FIGS. 20a and 20b** illustrate a z-domain plot of amplitude and phase;

[0029] **FIG. 21** illustrates a frequency plot of a low pass filter;

[0030] **FIG. 22** illustrates a frequency response of the sinc filter;

[0031] **FIG. 23** illustrates a block diagram of one implementation of the PID;

[0032] **FIG. 24** illustrates a Bode plot of the overall digital compensator comprised of the PID and LPF;

[0033] **FIG. 25** illustrates a more detailed waveform of the sinc filter;

[0034] **FIG. 26** illustrates a plot of the voltage response in a prior art system to positive and negative transients;

[0035] **FIGS. 27a and 27b** illustrate voltage plots for transients in the presence of voltage positioning for both low and high current, respectively;

[0036] **FIGS. 28a and 28b** illustrate the relationship between the voltage set point and the current level;

[0037] **FIG. 29** illustrates a flow chart depicting the operation of voltage positioning;

[0038] **FIG. 30** illustrates a block diagram of the voltage positioning in the current sensing operation utilizing two current sensors;

[0039] **FIG. 31** illustrates a schematic diagram of the circuitry for determining the inductor current;

[0040] **FIG. 32** illustrates a schematic diagram of the method for determining the capacitor current;

[0041] **FIG. 33** illustrates a diagrammatic view of the method for measuring the total load current without Hall sensors;

[0042] **FIG. 34** illustrates a diagrammatic view of the DPWM;

[0043] **FIG. 35** illustrates a more detailed diagrammatic view of the DPWM;

[0044] **FIG. 36** illustrates a block diagram of the trim and limit sub-system;

[0045] **FIG. 37** illustrates a block diagram of the DPWM timing register program model;

[0046] **FIG. 38** illustrates a block diagram of the shut-down sources;

[0047] **FIG. 39** illustrates a timing diagram for the sync operation;

[0048] **FIG. 40** illustrates a timing diagram for the frame skipping operation;

[0049] **FIG. 41** illustrates a simplified block diagram of the bypass logic;

[0050] **FIG. 42** illustrates a flow chart for the operation of the pattern generator for creation of the edges of the various phases;

[0051] **FIG. 43** illustrates a flow chart for the operation of the u(n) selection;

[0052] **FIG. 44a** is a functional block diagram of over current protection circuitry;

[0053] **FIG. 44b** illustrates an integrator hold circuit responsive to the primary interrupt;

[0054] **FIG. 44c** is a flow diagram illustrating the operation of the integrator hold circuit of **FIG. 44b**;

[0055] **FIG. 45** is a timing diagram illustrating the operation of a phase output of the digital pulse width modulator responsive to an over current detection signal;

[0056] **FIG. 46** is a timing diagram illustrating the use of a blanking pulse;

[0057] **FIG. 47** is a flow diagram illustrating the generation of primary and secondary interrupts by the over current protection circuitry;

[0058] **FIG. 48** is a flow diagram illustrating the operation of the reset circuitry of the over current protection circuitry;

[0059] **FIG. 49** is a functional block diagram illustrating the circuitry for providing over voltage and over temperature protections for a digital pulse width modulator;

[0060] **FIG. 50** is a flow diagram illustrating the method for providing over voltage and over temperature protections; and

[0061] **FIG. 51** illustrates a diagrammatic view of the PLL.

DETAILED DESCRIPTION OF THE INVENTION

[0062] Referring now to **FIG. 1**, there is illustrated a top level schematic diagram for the switching power supply of the present embodiment, which in this Fig. is illustrated as a half bridge power supply. The main portion of the power supply comprises a primary switch group **102** that is operable to receive an input voltage on a node **104**, this being a

DC voltage, and ground on a node 106. The primary switch group 102 is coupled through an isolation transformer 108 to a secondary switch group 110. The secondary switch group 110 is operable to drive an output voltage node 112 that is connected to one terminal of a load 114, the secondary switch group 110 also having a ground connection on a node 116, the load 114 disposed between the node 112 and the node 116. The two switch groups 102 and 110 are operable to operate in conjunction with various pulse inputs on a control bus 118 associated with the primary switch group 102 and with various pulse inputs on a control bus 126 associated with the secondary switch group 110.

[0063] A digital control circuit 124 is provided which is operable to control the operation of the primary switch group 102 and the secondary switch group 110. The nodes 104 and 106 are provided as inputs to the digital control circuit 124 for sensing the voltage and current on the primary, the digital control circuit 124 generating the information on the bus 118 for control of the primary switch group 102. The control circuit 124 must be isolated from the secondary switch group 110. This is facilitated by driving a bus 126 through an isolation circuit 128, such as an optoisolator, to drive the bus 120. Similarly, the control circuit 124 is operable to sense the voltage and current levels on the output node 112 through sense lines 130 which are also connected through an isolation circuit 132 to the digital control circuit 124. The digital control circuit 124 is also interfaced to a bus 136 to receive external control/configuration information. This can be facilitated with a serial data bus such as an SMB serial data bus.

[0064] Referring now to FIG. 2, there is illustrated a detailed schematic diagram of the primary switch group 102, isolation transformer 108 and secondary switch group 110. The node 104 is connected to one side of the source-drain path of a power switching transistor 202, the other side thereof connected to a node 204. Node 204 is connected to one side of the primary of isolation transformer 108, a primary 206. The other side of primary 206 is connected to a node 208. Node 208 is coupled to node 104 through a capacitor 210. Node 106 is coupled to one side of the source-drain path of a switching transistor 212, the other side thereof connected to node 204. Node 208 is coupled through a capacitor 214 to node 106. A diode 218 has the anode thereof connected to node 208 and the cathode thereof connected to a node 220, node 220 connected to one side of the source-drain path of a switching transistor 222, the other side thereof connected to node 204.

[0065] Switching transistor 212 is controlled by a switching pulse P1, the gate of switching transistor 202 controlled by a switching pulse P2 and the gate of switching transistor 222 controlled by switching pulse P3. Switching pulses P1, P2 and P3 all form part of the bus 118.

[0066] The secondary switch group 110 is comprised of a switching transistor 230 having the source-drain path thereof connected between the node 116 and a node 232, the gate thereof controlled by a switching pulse P5. Node 232 is connected to one side of a winding 234 which forms part of the secondary of the isolation transformer 108. The other side of winding 234 is connected to a center tap node 236, node 236 connected to one side of a winding 238, the other side thereof connected to a node 240. Winding 238 and winding 234 form the secondary of transformer 108.

[0067] Node 240 is connected to one side of the source-drain path of a switching transistor 242, the other side thereof connected to node 116 and the gate thereof connected to a switching pulse P4. An inductor 244 is connected between node 236 and the output node 112. The output node 112 is coupled to the ground node 116 through a capacitor 246 which is connected proximate to the other side of the source-drain path of transistor 230 and coupled through a capacitor 248 to node 116 proximate to the other side of the source-drain path of switching transistor 242.

[0068] Referring now to FIG. 3, there is illustrated a timing diagram for generating the switching pulses to operate the switch of FIG. 2. The switching pulse P1 is a pulse-width modulated switching pulse having a rising edge 320. The rising edge 320 changes the level to a high level 322 which then returns to the low level at a falling edge 324. The switching pulse P2 is delayed from the falling edge 324 by a delay t_{d1} . The rising edge 326 changes the level of switching pulse P2 to a high level 328 followed by a change back to a low level having a falling edge 330. The switching pulse P3 goes from a low level to a high level ahead of the falling edge of P2 by delay time t_{d2} . The switching pulse P3 returns to the low level at a falling edge 336.

[0069] In the output switch, the switching pulse P4 goes from a low level to a high level 336 at a rising edge 338. The rising edge 338 is delayed from the rising edge 320 by a delay t_{d3} . The switching pulse P4 returns to a low level ahead of the falling edge of P1 by delay time t_{d3} . The switching pulse P5 goes from a low level to a high level 342 at a rising edge 344 which is delayed from edge 326 of switching pulse P2 by a delay t_{d3} . Switching pulse P5 returns to a low level ahead of the rising edge of P3 by delay t_{d3} .

[0070] It can be seen that the switches 202 and 212 in FIG. 2 are controlled by switching pulses P1 and P2. The delay t_{d1} is the duration of time required for transistor 212 to go from a conducting state to a non-conducting state and prior to transistor 202 going to a conducting state. The delay t_{d1} is a delay that is required in order to ensure that the switches are completely off such that connecting the node 204 to the ground node 106 does not cause current to flow through transistor 202. This could result in a "shoot-through" current spike. Depending upon the circuit components and operating frequency, it may be necessary to vary this delay. Similarly, transistor 222 will be turned on prior to turning off switch 202 with the delay t_{d2} allowing the diode 218 to be placed in parallel with the primary 206 prior to turning off transistor 202. Similarly, on the output switch, it is necessary that transistor 242 is maintained in a non-conducting state until transistor 212 is fully turned on and node 204 is sufficiently grounded. Further, it is necessary that the falling edge 346 be delayed until the transistor 222 has fully turned on, which requires the delay t_{d3} . This timing is conventional and, depending upon the application, the various delays will be adjusted, these adjustments due to the size of the load, circuit characteristics and operating frequency.

Digital Controller—Overall

[0071] Referring now to FIG. 4, there is illustrated a block diagram of the digital controller 124 of FIG. 1. As described hereinabove, the switching converter is generally realized with a half bridge converter, but a simpler buck converter 402 is illustrated in this figure. This requires a plurality of phases 404 for controlling the switches internal to the buck

converter 402. This will allow a DC input voltage to be converted to a DC output voltage on output 406. The digital controller senses the output voltage on the output 406 as a sense voltage, V_{SENSE} , and inputs this to one input of a differential analog-to-digital converter (ADC) 408. The other input of the ADC 408 is connected to an analog or reference voltage generated by a V_{REF} generator 410 that, as will be described hereinbelow, comprises a digital-to-analog converter (DAC).

[0072] The output of the ADC 408 is a digital output that represents the difference between the analog output voltage on the DC output 406 and the “set point” generated by V_{REF} generator 410. The output of the V_{REF} generator 410 is typically the desired output voltage. As such, the operation of the control loop at regulation will typically result in a “0” output from the ADC 408. As will be described hereinbelow, this is the “0” code for the ADC 408. This is input to a digital compensator 412, which is operable to provide some phase lead in the loop. The buck converter 402 is comprised of a combination of a series inductor and shunt capacitor that forms an LC network, which provides a phase lag of 180° . The control loop will typically be provided by a negative feedback loop and will result in an additional negative phase shift of 180° . If the loop were allowed to operate in this manner, this would result in a 0° total phase change which would be an unstable loop. As such, the digital compensator 412 provides some phase lead to stabilize the loop. The output of digital compensator 412 provides the digital control value $u(n)$ on a digital output bus 414 for input to a digital pulse width modulator (DPWM) 416. This provides the various clock signals which provide the switching phases 404 to the buck converter 402 (or to a half bridge converter described herein above).

[0073] The ADC 408, digital compensator 412 and DPWM 416 are realized in hardware such that they provide relatively fast digital response and, once operating, operate in a fixed manner. However, each of the ADC 408, digital compensator 412, DPWM 416 and V_{REF} generator 410 are operable to be configured and have the operation thereof monitored. The V_{REF} generator 410 has a configuration block 420 associated therewith for configuring the operation thereof such that the voltage of the V_{REF} generator 410 can be controlled. Additionally, a monitoring circuit 422 is provided for monitoring the operation thereof. Similarly, the ADC 408 has a configuration block 424 for configuring the operation thereof and a monitoring block 426 for monitoring the operation thereof. The digital compensator 412 has a configuration block 428 for configuring the operation thereof and a monitoring block 430 for monitoring the operation thereof. The DPWM 416 has a configuration block 432 for configuring the operation thereof and a monitoring block 436 for monitoring the operation thereof.

[0074] As will be described hereinbelow, the ADC 408 is a parallel data converter that is configured with a Flash ADC topology. The digital compensator 412 is configured with a proportional-integral-derivative (PID) compensator with post processing filtering and DPWM 416 is realized with a state machine. The PID compensator is a discrete compensation network that is operable to apply a discrete time PID control law to the signal. The operation of each of these blocks is controlled through the associated configuration and monitoring blocks with a microcontroller 440. The microcontroller 440 is an instruction based engine that operates on

instructions that can be downloaded to Flash memory 442, which is non-volatile memory. A serial data input 442 allows instructions to be input to the microcontroller 440 for storage in the memory 442 and for various debug and control operations. Additionally, error handling is provided by a block 446 that basically provides for over current protection and over voltage protection to prevent damage to the buck converter 402 under certain conditions, as will be described in more detail hereinbelow.

[0075] By providing a digital controller that, when operating and configured, operates independent of the programmable microcontroller 440, the functionality of the digital controller is embedded primarily within the circuitry of the primary block involving the ADC block 408, the digital compensator block 412 and the DPWM block 416. The microcontroller 440 basically is the “housekeeper” for the digital controller which is operable to monitor the operation thereof. When the digital controller is operating at voltage regulation and once configured, very few actions need to be taken by the microcontroller 440. However, when the digital controller is originally configured, depending upon the environment, the type of switching converter utilized, etc., the digital controller will be configured by the microcontroller 440 for a specific application. Even for the given application, there are certain transients that occur, such as when the converter is powered up, when short circuits occur, when transient loads are applied, etc. and, thus, certain parameters of the various blocks need to be varied to accommodate such during the operation of the DC-DC converter. By providing an instruction based engine such as the microcontroller 440 in a monitoring mode and configuration mode, the operation of the digital controller can be monitored and then the parameters thereof changed temporarily, if necessary, to account for this change. To implement the entire digital controller in an instruction-based engine such as a DSP would require a large amount of programming operations. By providing a hardware based digital controller as the primary block, the functionality has been embedded within the hardware by the chip designer. The DSP solution, on the other hand, typically utilizes a general purpose DSP and the value or functionality of the digital controller is facilitated through programming, which can be complex and typically is utilized only for very high-end digital controllers. Further, the implementation of the primary digital control in hardware provides for a more efficient design that utilizes the circuitry and is more power efficient, which is important in low power DC-DC converters, without sacrificing the benefits of digital control.

[0076] Referring now to FIG. 5, there is illustrated a more detailed block diagram of the digital controller. The ADC 408 is a differential Flash ADC that is operable to determine as a digital value the difference between the voltage on the DC output node 406, that being the V_{SENSE} voltage, and a reference voltage on a node 502. This analog reference voltage on node 502 is generated by the V_{REF} generator 410. This is comprised of an analog reference voltage generator 504 which is operable to generate a fixed analog reference voltage based on an internal reference such as a bandgap generator. The bandgap generator is a conventional circuit that is utilized to generate temperature and process stable voltages. This is not shown in the illustration of FIG. 5. The V_{REF} generator 504 will generate this reference voltage and provide it as a reference input to a conventional reference digital-to-analog converter 506 (reference DAC). This is a

scaling DAC that is operable to receive a digital word on a bus 508 from a reference DAC control block 510 that is controlled by the microcontroller 440. This is basically a register that can be written to for the purpose of generating the reference DAC voltage. The reference DAC 506 is operable to convert this digital value on bus 508 to an analog voltage on node 502 for input to one of the differential inputs of the ADC 408. Typically, the voltage generated by V_{REF} generator 504 is a 1.25 V analog voltage. The output of the reference DAC 506 comprises the desired voltage of the DC-DC converter. In one embodiment, this is approximately 1.0 V, a conventional processor voltage. The reference voltage on node 502 is compared with the V_{SENSE} voltage on node 406 and, when regulated, this should essentially be zero. In the test mode of operation, there is provided a switch 512 which is operable to short the two inputs together. This will be described hereinbelow.

[0077] The ADC 408, as will be described hereinbelow, is a parallel ADC of the Flash type. It is a window ADC that is operable to generate a zero voltage output when the differential input is "0." An ADC control block 514 is operable to provide a control input to the ADC 408. The control block 514 provides a variable LSB input to the ADC 408 for use with some of various features thereof. The ADC operates on an ADC CK clock signal and also generates an end of conversion cycle interrupt, EOC1 IRQ. This provides an indication of when a data conversion operation is complete on a given sample and digital data associated with the analog sample is ready to be output. The data is output through an inverter circuit 516 for input to one input of a 4-input digital multiplexer 518, which is part of the input interface to the digital compensator 412.

[0078] The digital compensator 412, in addition to receiving the output of the ADC 408 through the inverter 516, is also operable to receive a ground input on a digital input bus 520, ADC data from a register 522 through a bus 524 for digitally generated ADC data, primarily for test purposes, and also a "raw" data input on a bus 526. In one mode of operation, primarily associated with start-up and the such, the sensed voltage, V_{SENSE} , is determined by another ADC, which is described hereinbelow, which is a SAR ADC. This is a slower ADC and the output thereof is stored in a special function register, $V_{SENSE/SFR}$, the output of which is provided on a bus 528. The difference between the digital representation of the V_{SENSE} voltage and the actual input to reference DAC 506 on the bus 508 is determined by a digital subtraction block 530, the output of which comprises the bus 526. Therefore, a single-ended SAR can be utilized to bypass the ADC 408 and determine a value for input to the digital compensator 412 during start-up and the such, this providing the differential operation in the digital domain. However, during regulation, the ADC 408 is the preferred input data converter.

[0079] The output of the multiplexer 518 is input to a PID controller block, which provides a proportional, integral, derivative (PID) control algorithm. One difficulty associated with designing a controller arises from the LC resonance of a buck converter. An open-loop frequency-response analysis exhibits a resonant peak at the cutoff frequency of the LC filter. A sharp peak, quantified by the quality factor (Q), is desirable for efficient power conversion for lossless power conversion. For a simple integral control, this resonant peak must be kept below unity gain in the open-loop frequency

response to ensure stability. Such a controller configuration has a low loop bandwidth and leads to slow transit response characteristic. This PID block 540 provides the requisite loop stability without sacrificing bandwidth and improves the loop's transient response. The proportional and derivative control blocks, as will be described hereinbelow, introduce compensation zeros that push unity-gain beyond the resonant peak and eliminates the bandwidth limitation otherwise imposed by the resonant nature of the buck converter. There is provided a PID control block 542 that controls the operation of the PID 540 by providing, as will be set forth hereinbelow, gain constants for the operation thereof. The operation is clocked with a filter clock, FILTCLK, on a clock input 544. The input to the PID 540 is determined by the output of multiplexer 518, which is controlled by a PID input control block 546. The clock rate is around 10 MHz, wherein the switching frequency of the power supply is around 500 kHz.

[0080] The analog corollary to the digital controller has one inherent benefit in that the overall operation of the analog controller has an inherent low pass filter function associated therewith. The PID 540, on the other hand, has an amplitude and phase response that increases with increasing frequency such that the gain thereof becomes relatively high at higher frequencies and the phase also increases in an ever increasing phase leading manner. To accommodate the frequency response of the PID, post processing filtering is required. This is facilitated in the present embodiment with either a low pass filter, represented by an LPF filter block 550 or a sinc filter block 552. The output of the PID 540 is input to both of these blocks 550 and 552 and the outputs thereof selected with a two-input digital multiplexer 554. The sinc filter operation 552 provides for a plurality of "notches" which are controlled by a sinc control block 556, the sinc filter block 552 clocked by the FILTCLK clock signal. The LPF filter block 550 also utilizes variable poles and zeros that are set by an LPF control block 558. The LPF filter block 550 is also clocked by the filter clock, FILTCLK. The output of multiplexer 554 provides the output from the digital compensator 412, the output selected by the multiplexer 554 controlled by a filter select block 560.

[0081] The output of the multiplexer 554 from the digital compensator 412 is provided on a digital data bus 562. This is input to a PID data register 564 for the purpose of monitoring the operation thereof, such that the output of the digital compensator block 412 can be monitored. The output of the multiplexer 554 is also input to the input of a two-input digital multiplexer 566, the other input thereof receiving data from the PID data block 564, such that the operation of the compensator 412 can be bypassed. The multiplexer 566 is controlled by a DPWM input control block 568. The output of the multiplexer 566 provides the $u(n)$ error signal, which is output on a bus 570 to the DPWM 416. The DPWM 416, as set forth hereinabove, is a state machine and is controlled by a DPWM control block 572. The DPWM block, as will be described hereinbelow, is operable to receive various control signals from the DPWM control block 572 from the microcontroller 442 and is also operable to generate a plurality of interrupts (not shown) and receive various interrupts. For example, at the end of a given frame, there will be an EOFIRQ interrupt generated, and the DPWM 416 will also receive various interrupts from the error handling block 446 to indicate either over current situations or over voltage situations.

[0082] Referring now to **FIG. 6**, there is illustrated a detailed block diagram of the microcontroller **440**. This microcontroller **440** is an 8051 instruction-based engine which is substantially disclosed in U.S. patent application Ser. No. 10/244,344, filed on Sep. 16, 2002 and entitled "Precision Oscillator for an Asynchronous Transmission System," which is incorporated herein in its entirety by reference for all purposes whatsoever. At the center of the microcontroller **440** is a processing core **602** which is an 8051 microprocessor engine. This is an instruction-based engine. There is provided a 32 K byte Flash memory block **604**, 256 byte IRAM block **606** and a 1K byte XRAM block **608**, providing memory for the processing core **602**. Clock signals are provided to the core **602** in the form of a system clock, SYSCLK, on a clock line **610**. This is provided on the output of a multiplexer **612**. The multiplexer is operable to receive the input thereof from a 20 MHz boot oscillator block **614**, an input from an 80 kHz low frequency oscillator block **616** to provide an 80 kHz clock for use in a sleep mode, or a higher frequency clock in the form of a divided down 25 MHz oscillator **618**. The 25 MHz oscillator is the primary oscillator at the operating frequency of the core **602**, as the core **602** operates at high frequency or at low frequency. However, at low frequency, the processing of instructions occurs at a much slower rate and this mode is typically used in a sleep mode. In the normal operating mode, typically the higher frequency clock oscillator is utilized. This clock is a non-crystal based clock and has an accuracy of approximately 2%. The output of the clock **618** is input through a two-input multiplexer **620** to the multiplexer **612**, the output of multiplexer **620** passed through a divide block **622** in order to divide the frequency of the clock, if necessary. Additionally, an external clock is input to the other input of multiplexer **620**, such that either the internally generated 25 MHz clock can be utilized or an external clock can be utilized. A phase lock loop **624** is provided which is controlled by a PLL control block **626** and this utilizes the 25 MHz clock **618** as a reference and then multiplies this clock up to as high as 400 kHz. This provides an output to one end of the multiplexer **612** for selection as the SYSCLK. This PLL **624** is operable to generate the other clocks associated with the operation of a digital controller, the clock for the DPWM **416**, PWMCK, the filter clock, FILTCLK, and the ADC clock, ADCCLK. This will be described hereinbelow.

[0083] The core **602** is also operable to receive a Reset signal on a block **630**, which is operable to generate a reset when it is not in a debug operating mode. In a debug operating mode, the Reset input on a node **631** is input to the clock input of a debug hardware block **634** to provide a clock signal thereto, the other input being a serial data input on a line **635**. This is a two-wire serial data port that allows for very low clocked data to be input to the core **602** during a debug mode. In the reset mode, the reset block **630** provides the reset signal to the core **602**.

[0084] The core **602** is interfaced through a special function register (SFR) bus **630** to various I/O blocks. In the embodiment illustrated herein, four timers **632** are provided. Each of these timers is operable to have the parameters thereof set, and initiated and each of them generates various timer interrupts, TMRXX IRQ, signals. Additionally, there are provided a number of serial bus configurations for allowing for various formats of a serial data interface. One of these is the SM Bus/I2C format, in a block **634**. This is

a conventional serial data format. Additionally, there is provided a UART functionality in a block **636**. There is provided a programmable counter/timer array (PCA) block **638** and a plurality of port latches **640** for interfacing with a port "0" block **642** and a port "1" block **644** for transmitting and receiving data therefrom. All of the blocks **632-640** are interfaced through a crossbar matrix block **646**, which is disclosed in U.S. Pat. No. 6,738,858, issued May 18, 2004, which is incorporated herein by reference. The crossbar matrix is operable to selectively connect any of the outputs of the blocks **632-640** to any of a plurality of output pins associated with the port driver **642** and **644**, there being eight pins **650** associated with the port "0" driver **642** and eight pins **652** associated with the port "1" driver. These pins can function as digital outputs, digital inputs or analog inputs.

[0085] For analog sensing, all of the eight pins **652** associated with the port "1" driver are connectable to analog inputs of a multiple input analog multiplexer **656** which is operable to receive eight analog inputs, AIN0, AIN1, . . . , AIN7, a V_{SENSE} input and a Temperature input. The input voltage is connected to the AIN0 input for sensing thereof. A separate dedicated pin is provided for the V_{SENSE} input for input to the multiplexer **656**. An additional input is provided by an internal temperature sensor **658**, which senses the chip temperature, which basically constitutes the environmental temperature, this being an input to the analog multiplexer **656**. The output of the analog multiplexer **656** is input to the input of a 12-bit SAR ADC **660**, operating at a sampling clock of 500 Ksps. This is a single-ended ADC that provides the digital output on a bus **662**. The control for the ADC **660** is provided by the ADC control block **664**. The analog multiplexer **656** is controlled by an auto scan block **666**, which is operable to scan through all of the inputs in a cyclical manner. At the end of each conversion cycle, there is generated an interrupt EOC0 IRQ indicating the end of the conversion cycle for the ADC **660**. This is input to the auto scan block **666** which will then increment the select control on the multiplexer to the next input to initiate a second or subsequent conversion operation. For each scan step, the output of the ADC **660** is "steered" or directed toward an associated special function register (SFR)/limiter (LIM). Each of these SFR/LIM blocks is operable to store the associated output, compare it with an internal fixed upper and/or lower limit, which can be varied upon power-up, and then output an interrupt if it exceeds the limit(s). In the first five SFR/LIMs, there is provided an ADC window interrupt in an SFR/LIM block **668**, an SFR/LIM block for the V_{SENSE} output **670**, an SFR/LIM block **672** for the AIN0 output, an SFR/LIM block **674** for the AIN1 input, and an SFR/LIM block **676** for the AIN2 input. Each of these blocks **668-676** provide an associated interrupt, ADC0WINTIRQ, V_{SENSE} IRQ, AIN0VIN IRQ, AIN1 IRQ, and AIN2 IRQ. Since the core **602** can only handle a certain number of interrupts, the remaining inputs, AIN3-AIN7 and TEMP are associated with respective SFR/LIM blocks **678**. The output of each block **678** provides an associated interrupt to an OR gate **681**. The output of the OR gate **680** provides an interrupt, which when recognized by the core **602**, requires that the core **602** then "poll" the outputs of the SFR/LIM blocks **678**, it being recognized that each of the SFR/LIM blocks occupies a unique address in the address space of the core **602**, such that the contents thereof can be read, or in certain circumstances, written to. Whenever an

interrupt is generated, the core 602 initiates an interrupt sub-routine for servicing that particular interrupt, as is the case with any interrupt generated.

[0086] There is also provided a comparator function for generating a comparator interrupt. A comparator block 680 is provided which is operable to have one compare input interface with the even ones of the pin 652 and a second input interface with the odd inputs thereto. This is a four comparator block, which is controlled by a comparator control block 682 and will generate a comparator interrupt whenever any of the respective inputs exceeds the threshold set therein.

[0087] Referring now to FIG. 6a, there is illustrated a diagrammatic view of an integrated circuit 690, which is operable to provide all of the functions for the digital control operation in a single integrated circuit. This integrated circuit 690 requires only connections from V_{SENSE} on a pin 692, switching control signals on output pins 693, a power supply input on a power supply pin 694 and a ground connection on a pin 695. With these minimal number of pins, the entire digital control operation can be facilitated. This assumes that a program is provided in the memory 442. If the program is not "hard coded," some type of serial connection on at least one pin 696 is required, but it should be understood that other pins in the system can be multiplexed for use in programming, since programming is facilitated in a nonoperating mode. Further, there are provided a plurality of pins 697 that are operable to receive other sense analog input voltages. However, for the straightforward operation of the digital controller, all that is required is the V_{SENSE} input. The other inputs are required for such things as over voltage protection and over current protection and for detecting the peak current for the purposes of voltage positioning, as will be described hereinbelow.

[0088] As set forth hereinabove, the digital control section is a hardware digital control section comprised of the ADC 408, the digital compensation network 412 and the DPWM 416. Once these blocks are parameterized, they will provide the control function associated therewith. The internal reference generator 410 is operable to provide the internal reference, for conversion to an analog signal by the DAC 506. Thus, all the voltage reference information is contained in the integrated circuit 690. The on chip self-contained microcontroller provides the monitoring and control functions such as over current protection, voltage positioning, etc. and, in general, provides all housekeeping functions to monitor the operation of the hardware digital control stream. The self-contained clock and on-board memory provide for the timing functions and the instructions for use by the microcontroller, respectively. Therefore, it can be seen that the system of the present disclosure provides for a single monolithic solution that is low power due to the use of a state machine-driven digital controller without requiring the power overhead of an instruction based system, but still retains the intelligence of an instruction based system in the monitoring and reparameterizing aspect provided by the microcontroller 440.

Flash ADC

[0089] Referring now to FIG. 7, there is illustrated a logic diagram of the window ADC 408. A first reference voltage is generated by an on-chip bandgap generator, a voltage V_{BG} . The bandgap generator is a conventional circuit that

combines a very stable voltage that is stable over temperature. This voltage is input to the voltage follower circuit comprised of an amplifier 702, the output thereof driving the gate of a p-channel transistor 704. The source/drain path of the transistor 704 is connected between V_{DD} and a node 708. Node 708 is connected to the other input of amplifier 702, such that the amplifier 702 and transistor 704 provide a source follower configuration. Node 708 is connected to a string 710 of resistors of value "5R." The output of amplifier 702 also drives a current mirror, such that the current through resistor string 710 is mirrored over to the current mirror. The current mirror is comprised of a p-channel transistor 712 and the gate thereof connected to a node 714, node 714 connected to the output of amplifier 702. The source/drain of transistor 712 is connected between V_{DD} and a node 728. Node 728 is connected to one side of the source/drain path of an n-channel transistor 716, the other side thereof connected to ground. The gate and drain transistor 716 are connected together to node 728 to form a diode-connected configuration. Node 714 is also connected to a variable width p-channel transistor 718, the source/drain path thereof connected between V_{DD} and a node 720. Transistor 718, as will be described herein below, is comprised of a plurality of parallel connected binary-weighted transistors, the connection thereof being programmable, such that one or all of the parallel connected transistors can be connected in parallel on a selective basis.

[0090] Node 720 is connected on one side thereof to a resistor string comprised of a plurality of resistors 722. There are provided sixty four of these resistors 722 having a total resistive value of "R," each having a voltage disposed there across equal to the voltage of a least significant bit (LSB) of the ADC. This will be described in more detail herein below. The bottom of the resistor string of resistors 722 is connected to a node 724, which is connected on one side thereof to the drain of a variable n-channel transistor 726, the source thereof connected to ground, and the gate thereof connected to the gate of transistor 716 on a node 728. Transistor 726 is substantially identical to transistor 718 and is also programmable to allow selection of the number of transistors connected together, which will be described in more detail herein below.

[0091] A voltage input on an input node 730 represents the negative input voltage. This is input to one input of a unity gain amplifier 732, which has the other input thereof connected to the output on a node 734. Node 734 represents the mid-point of the resistor string of resistors 722, such that there are an equal number of resistors above as below. Thus, for the disclosed embodiment of sixty four resistors 722, there will be thirty two resistors above and thirty two resistors below the point 734. The unity gain amplifier 732 provides the drive voltage node 734 and isolates the input voltage on node 730 therefrom.

[0092] The current through resistor string 710 is ratiometrically related to the current through transistors 718 and 726 and all of the resistors 722. Thus, the current through resistors 722 is set by the current through resistor string 710, which current is set by the voltage on the input to amplifier 702, voltage V_{BG} , such that the current is $V_{BG}/5R$. The only way to vary the current of the resistors 722 is through the ratio of the size of the transistors 718 and 726 to the size of the transistor 704. This will be described in more detail herein below.

[0093] Each of resistors 722, at the bottom thereof, is connected to one of sixty four comparators on one input thereof of comparators 740, on one input thereof. (It is noted that the number sixty four defines a "window," but any number of comparators could be utilized to represent the entire Flash ADC window). The other input of each of the comparators 740 is connected to a node 742, which is connected to the positive input voltage V_{IN+} . Therefore, the output of each of the respective comparators will be a "0" if the input voltage is below the resistor tap voltage and a "1" if the input voltage is above the associated tap voltage. The outputs of all of the comparators 740 having the reference input connected to resistor taps below the input voltage will have a "1" on the output thereof. This, therefore, represents a thermometer code on the output thereof. This is input to a decoder 746 to decode the thermometer code and provide the digital output therefrom.

[0094] The output voltage from decoder 746, D_{OUT} represents the difference voltage between the voltage on node 742 and the voltage on node 730, $V_{IN+}-V_{IN-}$. By comparing the positive input voltage on node 742 to the negative input voltage on node 730, the output voltage, V_{OUT} , will have a resolution defined by the voltage across each of the resistors 722, this being the LSB of voltage. This overall circuit provides the circuitry of the Flash ADC, this being a "window" Flash ADC as opposed to an absolute value ADC. When the difference between the voltage on positive input voltage node 742 and negative input voltage node 730 is "0," the comparators 740 below the node 734 will have a "1" on the output thereof and the comparator 740 having the reference input thereof connected to node 734 will have a "0" on the output thereof. This, as will be described herein below, represents the "0" code for the Flash ADC, this being a differential input ADC. As the size of the transistors 718 and 726 is varied, this will vary the current through the resistors 722 and, therefore, vary the size of the LSB. However, the "0" code will not vary. In effect, the negative input voltage on node 730 represents the reference voltage input of the ADC whereas the positive input voltage on node 742 represents the analog input voltage.

[0095] To distinguish the current architecture of the Flash ADC with a conventional architecture, the prior art Flash ADC of FIG. 8 will be described. In FIG. 8, a four comparator Flash ADC is described. A reference voltage is defined that is variable, this being for the purpose of varying the size of the LSBs. This reference voltage is provided on a node 802 at the top of a resistor ladder comprised of a plurality of tapped resistors 804. At each of the taps, there is an output provided to the reference input of an associated comparator 806. The other input on each of the comparators 806 is connected to an input node 808. For a single ended input, the reference voltage on node 802 will typically be connected to the supply voltage and resistor 804 adjusted such that the full rail-to-rail voltage could be provided. In this example, this would only provide a resolution of $1/4$ of the supply voltage. Typically, a very large number of comparators 806 will be provided associated with a large number of resistors. For a 16-bit Flash ADC, this would require 2^{16} comparators and a corresponding number of resistors. This results in a significant power consumption for each of the comparators. However, for a differential input signal, it is only necessary to resolve the difference between a positive and negative input signal over a defined range. Thus, a smaller reference voltage can be utilized which is divided by

a predetermined number of resistors in the corresponding comparator 806. In a prior art embodiment, the differential input voltage is determined by a differential amplifier 810 receiving the positive and negative input voltage and outputting a differential voltage on node 808. This differential voltage is then input to the input of each of the comparators 806. Of course, in order to utilize the full range, the output of the amplifier 810 must be centered around some common node voltage which is equal to $V_{REF}/2$. In one alternate embodiment, the prior art system of FIG. 8 can have the LSB is changed by a factor of, for example, $10\times$, which will require the common mode voltage, $V_{CM}=V_{REF}/2$, to change by a factor of $10\times$. Although this will provide a stable zero code, the common mode voltage, V_{CM} , of the amplifier 810 should be around $V_{CM}/2$ in order to have a large voltage swing.

[0096] It can be seen that, if the LSB size is varied through a variation of the reference voltage, this will cause the reference voltage on the zero-code node to change. If, for example, a node 820 associated with the second from the top comparator 806 on the reference input thereof represents the zero-code wherein the positive input voltage equals the negative input voltage, then, when the positive input voltage equals the negative input voltage, this comparator will have a "0" on the output thereof, comparators above will have a "0" output and comparators below will have a "1" output. As long as the voltage difference is "0," and the reference voltage is not varied, then the zero-code will not change but, if the voltage V_{REF} is changed, the size of the LSB will change and the zero code will also change, since the zero-code is now "coupled" to the value of V_{REF} . Therefore, if the LSB is required to be changed, then the tap associated with the resistor string that defines the zero-code may change. This will be described in more detail herein below.

[0097] Associated with each of the inputs of the comparator 806, is a distributed capacitance, which distributed capacitance would sum up to a total capacitance of C_T , represented by capacitor 814. It can be seen that the amplifier 810 must drive the capacitance 814 during a conversion operation. By reducing the number of comparators in the "window," the value of C_T can be reduced, in addition to the power consumption. However, the amplifier 810 must still drive this input with a capacitance.

[0098] Referring now to FIG. 9, there is illustrated a simplified diagram of the disclosed ADC of FIG. 7, which is utilized for comparison therewith to the prior art embodiment of FIG. 8. In this embodiment, it can be seen that the resistive string comprised of the resistors 722 are driven by an upper current source 902 from the supply voltage, V_{DD} , and the bottom of the resistive string is driven with a lower current source 904. Both of these current sources provide a current I_{REF} , which is variable. This variable current source varies the current through the resistors 722 and, therefore, sets the size of the LSB or, more specifically, the resolution of the ADC. The voltage on the node 734 is a negative input voltage and this provides the center reference voltage of the window with the current sources 902 and 904 in conjunction with the current through the resistors, providing the LSB voltage increments increasing toward current source 902 and decreasing toward current source 904. As the voltage on node 734 varies, the voltage across node resistors 722 does not vary, as that voltage is controlled by the current sources

902 and **904**. However, if the current value of the current sources **902** and **904** is varied, then the size of the LSB voltage will vary.

[0099] As will be described herein below, each of the current sources **902** and **904** are identical and are comprised of four separate parallel connected current sources, each having a binary-weighted current there through, such that a binary word can be input thereto for defining the value thereof. In the disclosed embodiment, there are provided four current sources, a 1× current source, a 2× current source, a 4× current source and an 8× current source, associated with a 4-bit word. This, however, is not meant to be limiting in that any number of current sources could be utilized, and any type of variable method for varying the current source could be utilized.

[0100] The output voltage, V_{OUT} is defined in the following equation:

$$D_{OUT} = (V_{IN+} - V_{IN-})G$$

[0101] The value of G is related to the inverse of LSB as follows:

$$G = \frac{1}{LSB \text{ size}}$$

The current through the resistor string is a ratiometric current such that it is the current through the resistor string **710** multiplied by a ratio metric factor α . Thus, the current through the resistor string of resistors **722** provided by transistors **718** and **726** is:

$$\frac{V_{BG}}{5R} \alpha$$

where:

R is the total value of the sixty four resistors **722** in the ladder; and

α is a scaling or ratiometric factor.

Thus, the LSB is defined as the current through a given resistor and it will be multiplied by the current through the resistor string multiplied by the value of resistor, R, as follows:

$$\left(\frac{V_{BG}}{5R} \alpha \right) \frac{R}{K} = \frac{V_{BG}}{5K} \alpha$$

where:

K is a factor representing the number of resistors **722** in the resistor string, there being sixty four in the disclosed embodiment.

[0102] As noted herein above, the ratio metric multiplier is a binary weighted multiplier that, in the disclosed embodi-

ment, utilizes a 4-bit word. This will be defined by the following relationship:

$$LSB = \left(\frac{V_{BG}}{5K} \right) \cdot \left(\frac{2^3 \cdot b_3 + 2^2 \cdot b_2 + 2^1 \cdot b_1 + 2^0 \cdot b_0}{2} \right)$$

where:

$$\alpha = \left(\frac{2^3 \cdot b_3 + 2^2 \cdot b_2 + 2^1 \cdot b_1 + 2^0 \cdot b_0}{2} \right)$$

Thus, it can be seen that the value of R is removed from the equation such that temperature and process variations therein do not affect the value of the LSB. All that is necessary is to have a stable voltage, this provided by the bandgap voltage generator.

[0103] Referring now to **FIGS. 10 and 10a**, there is illustrated a logic diagram for a comparator bank, each comparator bank representing each of the comparators **740**. This comparator string is a differential comparator having a positive input and a negative input. The positive input is connected to the positive input voltage on the node **742** which is connected to the voltage V_{IN+} . The other input is connected to a node **1002** which is the tap voltage V_{TAP} , this reference input to the comparator. There is provided a first comparator **1004** having a reference voltage input on node **1006** and a primary input on a node **1008**. Node **1002** is connected to one side of a switch **1010**, the other side thereof connected to node **1006**. Similarly, the node **742** is connected through one side of a switch **1012**, the other side thereof connected to node **1008**. Node **1002** is also connected to one side of two switches **1014** and **1016**, the other sides thereof connected to the nodes **1008** and **1006**, respectively. Switches **1010** and **1012** are controlled by the clock signal $\Phi 1$ and the switches **1014** and **1016** are controlled by the clock signal $\Phi 2$.

[0104] The output of comparator **1004** is provided on differential outputs **1020** and **1022**. Output **1020** is connected to one side of a sample capacitor **1024** and the node **1022** is connected to one side of a sample capacitor **1026**, both having a value of "C." The other side of the capacitor **1024** is connected to a node **1028**, which comprises one input of a second comparator **1030**. The other side of capacitor **1026** is connected to a node **1032**, which is connected to the other input of the comparator **1030**, the comparator **1030** being a differential input comparator. Node **1028** is connected to one side of a switch **1034**, and the other side thereof is connected to a differential output node **1036** of comparator **1030**. Similarly, node **1032** is connected to one side of a switch **1038**, the other side thereof connected to a second differential output node **1040** of differential comparator **1030**. Nodes **1036** and **1040** are connected to the differential inputs of a reconfigurable latch **1042**. Switches **1034** and **1038** are controlled by a clock signal $\Phi 1'$. The reconfigurable latch **1042** is controlled by a clock signal $\Phi 3$. The reconfigurable latch **1042** is operable to provide a latched output on differential outputs **1044** and **1046** for input to the dynamic latch **1048**, which is controlled by a clock signal $\Phi 4$. This provides a latched output for input to a T-latch **1046**, which is clocked by a clock signal to provide a data output, this being the output of the overall comparator **740**.

[0105] Referring now to FIG. 11, there are illustrated timing diagrams for the clock signals associated with the embodiment of FIG. 10. The operation of the comparator bank will be described with reference to these clock signals. When $\Phi 1$ goes high, as denoted by an edge 1102, the switches 1012 and 1010 will close, resulting in the output of the respective voltage on the respective nodes 1020 and 1022. Shortly thereafter, the clock signal $\Phi 1'$ will go high at an edge 1104. This will result in switches 1034 and 1038 closing, thus reducing the gain of the comparator 1030 such that the voltage on nodes 1036 and 1040 is substantially the same. At this time, the switches 1014 and 1016 are open, since the clock $\Phi 2$ is low at this time. This is the sampling operation. Thereafter, $\Phi 1$ goes low at an edge 1106 and $\Phi 2$ goes high at an edge 1108, thus opening switches 742 and 1010 and closing switches 1014 and 1016. This, in effect, disposes the nodes 1020 and 1022 at the same voltage or substantially the same voltage, thus "boosting" the other side of capacitors 1024 and 1026 to the voltages that were previously on the nodes 1020 and 1022. In general, the voltage on the input to the comparator 1004 on nodes 1008, 1006 comprises the difference voltage $V_{IN+}-V_{TAP}$. The output voltage of the comparator 1004 will have an offset voltage V_{OS1} associated therewith. This offset voltage and difference voltage will be multiplied by the gain of comparator 1004, a gain A_1 . Therefore, the output voltage on nodes 1020 and 1022 will be $A_1(V_{IN+}-V_{TAP}+V_{OS1})$. When $\Phi 2$ goes high at 1108, this represents the "hold" operation. Therefore, this represents a sample and hold operation. However, when switches 1014 and 1016 are closed, the voltage across nodes 1020 and 1022 is V_{OS1} and, therefore, the voltage across nodes 1028 and 1032 will now be $(V_{IN+}-V_{TAP})$, such that the offset voltage associated with the comparator 1004 is effectively removed in the hold operation.

[0106] It can further be seen that the capacitors 1024 and 1026 are isolated from nodes 742 and 1002. Thus, the analog input voltage that is input on node 742 will not be required to drive a large capacitance. The amplifier 732 isolates the negative input voltage on node 730 from node 734 and from all the subsequent tap voltages. However, the input voltage on node 742 is required to drive the inputs of each of the multiple comparators 740. The sampling operation requires a larger capacitance for the purpose of holding the charge for a predetermined amount of time. Since this larger capacitor is disposed on the opposite side of comparator 1004, it can be seen that the need for driving a very large capacitance and holding the voltage on that large capacitance is reduced, as the charge driven to the capacitor is driven from internal circuitry to the comparator 1004, as opposed to a driving circuit associated with the node 742. Thus, the drive of the sampling capacitors is distributed among all of the comparators 740.

[0107] Referring now to FIG. 12, there is illustrated a schematic diagram of the transistors 718 and 726. The transistor 718 is comprised of four binary weighted transistors 1202, 1204, 1206 and 1208, each of these being a p-channel transistor having the source/drain path thereof connected on one side thereof to the supply voltage V_{DD} . The other side of the source/drain path thereof is connected to the node 720. The gate of transistor 1202 is connected through the source/drain path of a p-channel transistor 1210 to node 714, the gate thereof connected to bit b0-Bar. The gate of transistor 1204 is connected to node 714 through the

source/drain path of a p-channel transistor 1212, the gate thereof connected to bit b1-Bar. The gate of transistor 1206 is connected to node 714 through the source/drain path of a p-channel transistor 1214, the gate thereof connected to bit b2-Bar. The gate of transistor 1208 is connected to node 714 through the source/drain path of a p-channel transistor 1216, the gate thereof connected to bit b3-Bar. Therefore, when the respective bits are a logic "high," then the respective gate transistors 1210-1216 will connect the gate of the respective transistors 1202-1208 to node 714. Transistors 1202-1208 are binary weighted in size. The transistor 1202 has a size of, for reference purposes, 1x, transistor 1204 has a size of 2x, transistor 1206 has a size of 4x and transistor 1208 has a size of 8x. Therefore, the amount of current that will flow through the transistors is correspondingly larger. This provides the binary weighting, a fairly conventional weighted current scheme.

[0108] When the transistors 1202-1208 are deselected, their gates will be pulled high. A pull-up p-channel transistor 1220 has the source/drain path thereof connected between the gate of transistor 1202 and a supply voltage V_{DD} , and the gate thereof connected to bit b0. A pull-up p-channel transistor 1222 has the source/drain path thereof connected between V_{DD} and the gate of transistor 1204 and the gate thereof connected to bit b1. A pull-up p-channel transistor 1224 has the source/drain path thereof connected between V_{DD} and the gate of transistor 1206 and the gate thereof connected to bit b2. A pull-up p-channel transistor 1226 has the source/drain path thereof connected between V_{DD} and the gate of transistor 1208 and the gate thereof connected to bit b3.

[0109] The transistor 726 is comprised of four n-channel transistors 1230, 1232, 1234 and 1236 having the source/drain paths thereof connected between node 724 and ground and sized in a binary weighted manner similar to transistors 1202-1208, such that they are respectively identical thereto in size. The gate of transistor 1230 is connected to node 728 through an n-channel transistor 1238, the gate thereof connected to bit b0. The gate of transistor 1232 is connected through an n-channel gate transistor 1240 to node 728, the gate thereof connected to bit b1. The gate of transistors 1234 is connected through an n-channel gate transistor 1242 to node 728, the gate thereof connected to bit b2. The gate of transistor 1236 is connected through an n-channel gate transistor 1244 to node 728, the gate thereof connected to the bit b3. Thus, by selecting the ones of the gated transistors 1238-1244, the binary weighted transistors 1230-1236 can be selectively connected between node 724 and ground. When not selected, the gates thereof are pulled low through the source/drain paths of pull-down n-channel transistors 1246, 1248, 1250 and 1252, respectively. The gates of transistors 1246-1252 are connected to bits b0-Bar, b1-Bar, b2-Bar and b3-Bar, respectively.

[0110] Referring now to FIG. 13, there is illustrated a schematic diagram of the comparator 1004. This is a differential input comparator that is comprised of two differential input n-channel transistors 1302 and 1304 having the sources thereof connected in a common source configuration to a common source node 1306. Node 1306 is connected through the source/drain path of an n-channel transistor 1305 to ground, the gate thereof connected to a bias voltage on a node 1308. A diode connected n-channel transistor 1310 has the source/drain path thereof connected between node

1308 and ground and the gate thereof connected to node **1308**. This provides the bias for the node **1306** for the transistor **1305**. The drain of transistor **1302** is connected to a negative output node **1312** and the drain of transistor **1304** is connected to a node **1314**, the positive output node. A cross coupled p-channel transistor pair comprised of a p-channel transistor **1316** connected between V_{DD} and node **1312** at a p-channel transistor **1318** connected between V_{DD} and node **1314** is configured such that the gate of transistor **1316** is connected to the opposite node, node **1314**, and the gate of transistor **1318** is connected to the opposite node, node **1312**. A diode connected p-channel transistor **1320** is connected between V_{DD} and node **1312**, the gate thereof connected to node **1312**. A diode connected p-channel transistor **1324** is connected between V_{DD} and node **1314**, the gate thereof connected to node **1314**. The gate of transistor **1302** is the positive input and the gate of transistor **1304** is the negative input.

[0111] Referring now to **FIG. 14**, there is illustrated a schematic diagram of the comparator **1030**. This is a differential input comparator that is comprised of two differential input n-channel transistors **1402** and **1404** having the sources thereof connected in a common source configuration to a common source node **1406**. Node **1406** is connected through the source/drain path of an n-channel transistor **1405** to ground, the gate thereof connected to a bias voltage on a node **1408**. A diode connected n-channel transistor **1410** has the source/drain path thereof connected between node **1408** and ground and the gate thereof connected to node **1408**. This provides the bias for the node **1406** for the transistor **1405**. The drain of transistor **1402** is connected to a negative output node **1412** and the drain of transistor **1404** is connected to a node **1414**, the positive output node. A cross coupled p-channel transistor pair comprised of a p-channel transistor **1416** connected between V_{DD} and node **1412** and a p-channel transistor **1418** connected between V_{DD} and node **1414** is configured such that the gate of transistor **1416** is connected to the opposite node, node **1414**, and the gate of transistor **1418** is connected to the opposite node, node **1412**. A diode connected p-channel transistor **1420** is connected between V_{DD} and node **1412**, the gate thereof connected to node **1412**. A diode connected p-channel transistor **1424** is connected between V_{DD} and node **1414**, the gate thereof connected to node **1414**. The gate of transistor **1402** is a positive input and the gate of transistor **1404** is the negative input. This is a conventional design.

[0112] A p-channel transistor **1440** that has the source/drain path thereof connected between nodes **1412** and **1414** and provides a short circuit for a short duration of time prior to the leading edge of $\Phi 1'$ to prevent kickback. The gate of transistor **1440** is connected to a clock signal $\Phi 1_{pre}$, such that, when activated, the gain of the comparator stage **1030** is substantially reduced. This clock signal is not shown in **FIG. 11**.

[0113] Referring now to **FIG. 15**, there is illustrated a schematic diagram of the reconfigurable latch **1042**. This latch has two modes of operation. In the first mode, the gain is set at a relatively low gain and, in a second mode, the gain is increased substantially. The input is provided by a common source pair of differential input n-channel transistors **1502** and **1504**, having the source thereof connected to a common source node **1506**. The n-channel transistor **1510** is

connected between node **1506** and ground with the gate thereof connected to a bias voltage on a node **1508**. The drain of transistor **1502** is connected to a negative output node **1512** and the drain of transistor **1504** is connected to a node **1514**, the positive output node. A cross-coupled pair of p-channel transistors **1516** and **1518** is provided, with the source/drain path of transistor **1516** connected between V_{DD} and node **1512** and the source/drain path of transistor **1518** connected between V_{DD} and node **1514**. The gate of transistor **1516** is connected to node **1514** and the gate of transistor **1518** is connected to node **1512**. A p-channel transistor **1520** has the source/drain path thereof connected between nodes **1514** and **1512** and the gate thereof connected to a node **1524**. A diode connected p-channel transistor **1526** is connected between V_{DD} and a node **1528** (p-channel), the gate thereof connected to node **1528**. A second diode connected p-channel transistor **1530** is connected between node **1528** and node **1524**, the gate thereof connected to node **1524**. An n-channel transistor **1532** is connected between node **1524** and ground, the gate thereof connected to the bias voltage on node **1508**. A p-channel transistor **1534** has the source/drain path thereof connected between V_{DD} and node **1524**, the gate thereof connected to the clock signal $\Phi 3$. In general, the transistor **1520** is operated in the triode region and, therefore, when turned on, constitutes a resistor. The input impedance looking into the source of transistor **1516** and into the source of transistor **1518** is equal to $-1/g_m$. When transistor **1520** is turned on, it provides a resistance, R_{1520} , that is disposed in parallel with this impedance. Initially, this is a negative impedance until a transistor is turned on, at which time it is impedance above zero, which, when turned on, results in a relatively low gain. When turned off, the gain goes high. Thus, when $\Phi 3$ goes high, node **1524** is biased to place the transistor **1520** in the triode region. This occurs at an edge **910** on the waveform $\Phi 3$ in **FIG. 11**. This occurs prior to the switches **1014** and **1016** closing in response to $\Phi 2$ going high at the edge **1108**. Thus, prior to the sample operation, the latch **1042** is configured for a low gain operation. When $\Phi 2$ goes high at edge **1108**, the reconfigurable latch **1042** will evaluate the difference voltage at the gates of transistors **1502** and **1504** which will result in a difference voltage generated across the output nodes **1512** and **1514** with a gain of two. When $\Phi 3$ goes low at an edge **1112**, this value will be latched on the outputs.

[0114] Referring now to **FIG. 16**, there is illustrated a plot of gain of the reconfigurable latch when $\Phi 3$ is high. It can be seen that the gain varies from a value of 4.5 at a substantially zero voltage input to a value of 1.5 at a voltage of 100 millivolts and a voltage of 1.0 at a value of 200 millivolts on the input.

[0115] Referring now to **FIG. 17**, there is illustrated a schematic diagram of the dynamic latch **1048**. There are provided two n-channel gate transistors **1702** and **1704** for connecting the positive and negative inputs associated therewith to respective nodes **1706** and **1708**, the gates of transistors **1702** and **1704** gated by the $\Phi 2$ clock signal. Two common source n-channel transistors **1710** and **1712** have the sources thereof connected to a common source node **1714** and the drains thereof connected respectively to nodes **1706** and **1708**. An n-channel transistor **1716** is connected between node **1714** and ground and controlled by the $\Phi 4$ clock signal. Therefore, the sources of transistors **1710** and **1712** will be connected to ground when $\Phi 4$ is a logic "high."

Node **1706** is associated with a positive output and node **1708** is associated with a negative output. Two cross-coupled p-channel transistors **1720** and **1722** are provided, transistor **1720** connected between a node **1724** and node **1706** and transistor **1722** connected between node **1724** and node **1708**. The gate of transistor **1720** is connected to node **1708** and the gate of transistor **1722** is connected to node **1706**. A p-channel gate transistor **1726** is provided for connection between V_{DD} and node **1724** and the gate thereof connected to the clock signal $\Phi 4$ -Bar. Thus, when transistor **1726** is turned on, node **1724** is connected to V_{DD} .

[0116] In operation, when the clock signal $\Phi 2$ goes high, the differential output of the reconfigurable latch is connected to nodes **1706** and **1708**. However, this latch is essentially powered down until the evaluation phase is complete and $\Phi 4$ goes high at an edge **114**, the same time that $\Phi 2$ goes low at a negative falling edge **116**. Thus, the output of the reconfigurable latch which is provided at the falling edge of $\Phi 3$, falling edge **112**, will be disposed on nodes **1706**, and **1708** while the latch **1048** is powered down. When transistors **1702** and **1704** are turned off, then the voltage on nodes **1706** and **1708** is "latched" into the latch **1048** by turning on transistors **1716** and **1726**. This provides an output to the transmit latch **846**.

Digital Compensator

[0117] Referring now to **FIG. 18**, there is illustrated a simplified diagrammatic view of the digital controller and the digital compensator **412**. The PID block **540** is comprised of three paths that are summed with a summing junction **1802**. The first path provides a proportional relationship with a block **1804**, the second path provides an integration function with an integration block **1806** and the third block provides a differentiation path with a block **1808**. As noted hereinabove, this is referred to as a PID controller. The proportional block **1804** has a steady state proportional gain, K_p , and provides zero phase lag. The integral path and integration block **1806** has an integral gain, K_i , which generally reduces the steady state error. There is some phase lag associated with this. The differentiation path associated with the differentiation block **1808** has a derivative gain, K_d , which provides some phase lead by anticipating future operations. Thus, the overall PID block **540** provides phase compensation for the overall control loop.

[0118] The output of the summing junction **1802** is input to, as described hereinabove, either a low pass filter **550** or a sinc filter **552**. The low pass filter **550** is comprised of a block **1810** that has associated therewith a low pass filter frequency response with two poles. This is passed through an amplification stage **1812** with another coefficient associated with the amplification, this being the coefficient that is controlled by the microcontroller **440**. Thus, there are three coefficients, a_1 , a_2 and a_3 that control the operation of the low pass filter function, these being the coefficients of the low pass filter. The sinc filter **552** is basically comprised of a summing block or an accumulation block **1814**, which is operable to sum over a range of delay values, this being a decimation type sinc filter. A gain factor is provided by an amplification stage **1816** which has a coefficient a_0 associated therewith. This a_0 will set the position of the sinc filter notch, as will be described hereinbelow. A multiplexer **1818** is operable to select between the output of amplification stage **1812** and the amplification stage **1816** for input to the DPWM **406**.

[0119] Referring now to **FIG. 19**, there is illustrated a more detailed block diagram of the PID **540** and the low pass filter **550** and the sinc filter **552**. The proportional path of the block **1804** has a gain stage **1902** associated therewith with the gain factor K_p . This is controlled by the PID control block **542**. The integral block has a gain block **1904** associated therewith with the integral gain factor K_i . The output of this is passed through a transfer function $1/(1-z^{-1})$ in a block **1906**. The output of this block is input to the summing junction **1802**. The integration path and the block **1808** are comprised of a gain block **1908** with a differential gain K_d . The output of this gain block **1908** is input to a delay block **1910** to provide the delay $(1-z^{-1})$. The output of block **1910** is input to the summing junction **1802**. Additionally, there is provided a multiplexer **1970** having one input thereof connected to the input **1901** and the other input connected to a digital word with a value of "0." The output of the multiplexer **1970** is input to the input of the gain block **1904**. In that error condition, the "0" value can be selected such that the integration path is on hold. This will be described in more detail hereinbelow.

[0120] The low pass filter is configured with an input summing junction **1912**, the output thereof connected to a delay block **1914** with a delay of z^{-1} . The output of delay block **1914** is connected to a node **1916**, which node **1916** has a signal associated therewith fed back through a coefficient block **1918** with a coefficient a_2 , the output thereof input to the summing block **1912**. Node **1916** is also input to one input of a summing junction **1918**, the output thereof connected to the input of a coefficient block **1920**, the output thereof providing the output of the low pass filter on a node **1922**. The input to delay block **1914** is also input to summing junction **1912**. Node **1916** is input through a delay block **1924** with a delay z^{-1} , the output thereof input through a coefficient block **1926** with a coefficient a_1 to another input of the summing junction **1912**. The low pass filter control block **558** sets the coefficients a_1 , a_2 and a_3 . In general, this is a Butterworth configuration low pass filter, a fairly conventional digital filter.

[0121] The sinc filter is comprised of an input summing junction **1930**, the output thereof input through a delay block **1932** with a delay of z^{-1} , the output thereof input to a coefficient block **1934**, the output thereof providing the output of the sinc filter **552**, coefficient block **1934** having the coefficient a_0 associated therewith, this coefficient provided by the sinc control block **556**. The output of delay block **1932** is also fed back to the input of summing junction **1930** to provide the accumulation operation. This delay block **1932** has a reset input associated therewith which is reset at a predetermined time. As noted hereinabove, this is a decimation type sinc filter. The output of both the low pass filter and the sinc filter are input to respective inputs of the multiplexer **554**. This provides the $u(n)$ error signal. The low pass filter or the sinc filter can be selected, depending upon the particular application and the desire of the applications engineer.

[0122] Referring now to **FIGS. 20a** and **20b**, the frequency response of the PID **540** will be described. First, the mathematics associated with the PID will be set forth as follows:

$$\begin{aligned}
 H(z)_{PID} &= K_p + \frac{K_i}{1-z^{-1}} + K_d(1-z^{-1}) \\
 &= \frac{K_p(1-z^{-1}) + K_i + K_d(1-z^{-1})^2}{1-z^{-1}} \\
 &= \frac{(K_p + K_i + K_d) + (-K_p - 2K_d)z^{-1} + z^{-2}}{1-z^{-1}}
 \end{aligned}$$

It can be seen from the above equations that there is a single pole at DC and that there are two zeros. Further, it can be seen that the value of the zeros is the function of the constants K_p , K_i and K_d . By selecting these constants, the value of the zeros can be varied.

[0123] Referring now to FIGS. 20a and 20b, there is illustrated frequency and phase plots for the response over frequency of the PID. It can be seen that there is a single pole at DC and the response will roll off until the first zero, at which time the response will flatten out until the second zero. At the second zero, the response changes in a positive manner, this due primarily to the differentiator term. However, it can be seen that without some type of filtering, the gain at high frequencies will be fairly high. This is the difference between a digital controller and an analog controller wherein the analog controller has an inherent low pass filter at the higher frequencies. It can be seen that the phase also exhibits a similar property wherein the phase is initially 90° and falls slightly to the first zero where it goes positive and then at the second zero continues to increase. At high frequencies, the phase is significantly leading in nature. With the use of a low pass filter, as set forth in FIG. 21, the high frequency portion of the PID response can be controlled. However, the corner frequency of the low pass filter cannot be too low or the phase associated therewith will cause instability in the loop. Typically, the switching frequency is around 500 KHz. It will be desirable to filter any noise associated with the switching frequency and, therefore, it will be desirable from a filtering standpoint to move the corner frequency of the low pass filter at or below this frequency. However, this would cause significant phase instability in the control loop. This is where the sinc filter will be beneficial. The sinc filter, with the response shown in FIG. 22, results in a plurality of “notches” at multiples of the sampling frequency, such that a notch can be placed at the switching frequency of the power supply.

[0124] As noted hereinabove, the sinc filter is a decimation type filter. The decimation ratio is defined as the ratio of the sampling frequency of the controller divided by the switching frequency of the power supply, the desired notch. If the sampling frequency f_s is set at 10 MHz and the switching frequency of the power supply, f_{sw} , is equal to 500 kHz, that summation ratio would be equal to f_s/f_{sw} , which results in zeros at integer multiples of the switching frequency. This is equal to $(10 \times 10^6)/(500 \times 10^3)$, which results in a decimation ratio of 20. Therefore, a notch would exist at 500 kHz, 1 MHz, 1.5 MHz and finally at 5 MHz, $f_s/2$. Therefore, the accumulator would accumulate 20 samples and then be reset, at which time it would provide an output.

[0125] Referring now to FIG. 23, there is illustrated a more detailed implementational diagram of the digital compensator 412. The input 1901 of the PID is input along three

paths, as noted hereinabove. The proportional path utilizes a multiplier 2302 having one input connected to the node 1901 and the other input thereof for receiving the digital value of K_p and providing on the output the result for input to a first summing junction 2304. The integral path has a multiplier 2306 associated therewith having one input thereof connected to the input 1901 and the other input thereof for multiplication with the output of an AND gate 2308. One input of the AND gate is connected through an inverter node to an integrate hold enable signal, INTHLDEN, and the other input thereof connected to the K_i integral constant. The output of multiplier 2306 is fed to the input of a summing junction 2308 for summing with the output of a feedback delay block 2310 which is operable to feedback the output from a node 2312. The output of the summing junction 2308 is passed through a saturation block 2314 to a node 2312. Node 2312 is input to the other input of the summing junction 2304. The output of summing junction 2304 is input to a summing junction 2316. The differentiator block has a summing node 2318 for receiving on the one input thereof the value on the node 1901 and on the other input thereof the value on node 1901 delayed by delay block 2320, this input to a negative input such that the block 2318 is a difference block. The output of the difference block 2318 is input to a multiplication block 2322 for multiplication of the output of the summing block 2318 with the constant case K_d . The output of multiplication block 2322 is input to the summing block 2316. The summing block 2316 is input to a summing block 2324, this operable to receive on the input thereof a programmable dither signal, generated by a programmable dither register 2326. By changing the value of this programmable dither, the value output by the summing junction 2316 can be varied.

[0126] The output of the summing junction 2324 comprises the PID output. This is input to the two filters. The low pass filter is configured with an AND gate 2330, one input connected to the PID output and the other input thereof connected to the filter select signal, FILTERSEL-EAR. The output of the enable gate 2330 is input to a summing junction 2332. The output of summing junction 2332 is input to the input of a summing junction 2334, the output thereof connected through a saturate block 2336 to a node 2338 for input to a delay block 2340, the output thereof connected to a node 2342. Node 2342 is input to one input of a multiplication block 2344, the other input thereof connected to the coefficient a_1 for multiplication therewith. The output of multiplication block 2344 is passed through a truncation block 2346 to truncate the value output therefrom for input to the other input of the summing junction 2334 on a negative input thereof to provide a subtraction operation with the summing junction 2334. The output of node 2342 is also input through a delay block 2348 to the input of a multiplication block 2350 for multiplication with the a_2 coefficient. The output of multiplication block 2350 is truncated with a truncation block 2352 for input to a negative input on the summing junction 2332 such that a subtraction operation is performed by the summing junction 2332. A summing junction 2358 is operable to the sum of the output of node 2342 and the output of node 2338, the output thereof input to a multiplication block 2360 for multiplication with the a_3 coefficient. The output of multiplication block 2360 is input to a block 2362 for saturation of truncation and then to the input of the multiplexer 554.

[0127] The sinc filter is facilitated with an input selection AND gate 2364 having one input connected to the PID output and the other input connected to the filter select signal, FILTERSEL. The output of the gate 2364, the enable gate, is input to one input of a summing junction 2366, the output thereof connected through a saturate block 2368 to a node 2370. Node 2370 is connected through a delay block 2372 to an input of an AND gate 2374. The output of AND gate 2374 is input to the other input of the summing junction 2366. Node 2370 is also input to a multiplication block 2376 for multiplication with the sinc filter coefficient, a_0 , the output thereof connected to a saturate and truncation block 2378 for output to the other input of the multiplexer 554.

[0128] When the sinc filter is selected, a different clock signal is utilized for delaying the output. A delay 2380 is provided on the output of the multiplexer 554. A multiplexer 2382 selects the control signal for the delay 2380 to adjust the delay thereof. This either can be the raw clock signal or the raw clock signal divided by a factor of "N," with a divide block 2384. The clock signal is input to one input of the multiplexer 2380 and to the other input thereof through the divide block 2384 to provide the divide down clock signal. The divide down clock signal also provides the second input to the enable gate 2374 through inverting node thereon. Thus, the divide ratio provides the "reset" for the accumulation operation, the accumulation operation operating at the filter clock rate. The divide down "N" ratio sets the number of accumulations that will be allowed to occur before the reset, at which time the data output will be provided.

[0129] Referring now to FIG. 24, there is illustrated a Bode plot of the digital compensator with a low pass filter. It can be seen that, at DC, there is a pole and the first zero of the PID occurs at Fz1 and the second zero occurs at Fz2. The response will increase at the second zero until the first pole of the low pass filter occurs, at Fp1, and the second pole occurs later at a pole Fp2. Thus, it can be seen that by moving the corner frequency of the low pass filter out from the switching frequency and the zeros of the PID, there will be some increase in the signal output by the PID. Of course, the two zeros of the PID could be identical and the two poles of the low pass filter could be closer together.

[0130] Referring now to FIG. 25, there is illustrated a frequency plot of the sinc filter operation in the frequency domain. It can be seen that, in this embodiment set forth hereinabove with respect to the example where the sampling frequency of the filter is 10 MHz and the switching frequency of the power supply is 500 kHz, there will be a notch 2502 placed proximate to the 500 kHz switching frequency. It is noted that this notch is programmable to the use of the coefficients utilized to realize the sinc filter, the decimation ratio, the sampling frequency and the switching frequency. By adjusting these values, the notch can be programmed for placement at the switching frequency of the power supply. This will result in a very quiet power supply, such that the switching frequency is effectively filtered out of the control loop.

Voltage Positioning

[0131] Referring now to FIG. 26, there is illustrated a prior art voltage plot of the voltage output in the presence of positive and negative transients. The power supply is typically given some type of specification for the regulation, i.e., the regulation must be within predetermined limits. There is

a high limit and a low limit. The reason that the voltage may go outside of the limits is due to ripple or due to transient responses. The ripple is typically very tightly controlled. However, transient current surges can cause the voltage to increase or decrease. In FIG. 26, there are illustrated a positive transient and a negative transient. A positive transient will occur whenever a load is quickly removed from the output of the power supply and a negative transient will occur when a load is applied. When a load is applied, for example, there will be a large inrush of current. This current will have a tendency to pull the power supply voltage low and out of regulation shortly until it can be brought back into regulation. However, it may be that the current rush will pull the voltage down below a lower limit, thus falling outside of the specification. The way the prior art systems have accommodated this transient is to provide for a larger capacitor on the output node. This larger capacitor will tend to reduce the effect of the transient and maintain it within the limit. The problem with large capacitors is that they are expensive and large. There are two types of capacitors that can be utilized, ceramic capacitors or electrolytic capacitors. The ceramic capacitors have a relatively small equivalent series resistance (ESR), but they do not accommodate large capacitor values at economic costs. A typical value of a capacitor to accommodate transients would be 100 microfarads. For this size of a capacitor, a single discrete capacitor would typically utilize an electrolytic capacitor. However, these electrolytic capacitors have high ESRs. For any inductor current ripple, there would be a commensurate amount of power dissipated in the ESR of the capacitor. For DC voltages, there would be no dissipation, but, for even a small ripple, there would be some heating of the capacitor. This heating could cause failure of the capacitor, which is why ceramic capacitors are favored. Thus, even though the ceramic capacitor has a relatively small value, power supply manufacturers utilize a plurality of the power supply capacitors disposed in parallel. Thus, for large capacitors, there can be a large part count and, therefore, it is desirable to reduce this part count.

[0132] In the present disclosed embodiment, it is possible through the control of the reference DAC 506 that is part of the reference generator 410, to be controlled to reposition the set point for the reference input to the ADC 408. For situations where low current is present, well below the rated current of the power supply, it is anticipated that any transient would be a negative transient due to a sub increase in the load. Thus, the set point is positioned higher than median voltage and closer to the higher limit than the low limit. Thus, when a transient occurs, it has the full range between the high and low limit or substantially the full range, within which to pull the voltage down on the output of the power supply. This is illustrated in FIG. 27a, wherein the regulated DC voltage is disposed proximate the high limit. When high current is present, the set point is disposed proximate to the lower limit of the power supply specifications. When the load is removed, which would be expected, then a positive transient would occur and, with the embodiment illustrated in FIG. 27b, the transient can have a magnitude that is approximately equal to the difference between the high and low limits in the specification.

[0133] In order to appropriately set the value output by the reference DAC 506, it is necessary to determine the current level and then set the reference voltage level accordingly. FIGS. 28a and 28b illustrate this aspect. For low currents,

the voltage is positioned proximate the high limit and for the high currents, the voltage is positioned proximate the lower limit. Illustrated in **FIG. 28a** is the current and **28b** is the output voltage position, i.e., the set point. Superimposed on the current in phantom at the low current level is a current transient **2802**. This results in a transient in the voltage in the transient **2804** in voltage that is negative going. However, since the voltage is positioned proximate the high limit, this transient has more room than if it were disposed at the midpoint between the high and low limits. Very similarly, when the current is high, there is illustrated a negative current transient **2806** in phantom. This would result in the regulated voltage experiencing a high voltage transient **2808**. It can be seen that, since the voltage is repositioned for the higher current, that more room is allowed for the voltage mediation. The result of utilizing the voltage positioning is that a smaller capacitor can be utilized on the output, which can significantly reduce the part count.

[0134] Referring now to **FIG. 29**, there is illustrated a flow chart for the voltage positioning operation. This is initiated at a start block **2902** and the proceeds to a block **2904** to sense the current. The current is sensed with a Hall effect sensor **460** which generates a voltage output proportional to the current, these being conventional devices. This current is sensed and input to one of analog inputs to the chip and converted to a digital voltage with the SAR ADC converter **660**. This is stored in the associated SFR/LIM register and can be examined by the core processor **602**. Of course, any time the current exceeds the internal limit, this is accommodated by other circuitry. Once the current is sensed, then the value of V_{REF} output by the reference DAC **506** is then set. This is set in accordance with a look-up table that can be stored in the memory or any other manner to set the values of the steps, including a simple algorithm. It could be that the voltage is positioned at three points, one when the voltage is above a threshold, one when it is below a threshold and one when it is between the thresholds. However, even finer graduations could be facilitated through the use of a look-up table.

[0135] Referring now to **FIG. 30**, there is illustrated a block diagram of a method for determining the total current. Hall sensors are fairly expensive and, therefore, a different technique is disclosed for measuring the currents and determining the change to the reference voltage to be made. As noted hereinabove with respect to **FIG. 1**, there is provided a half bridge power supply section **3002**, which includes on the output side a series inductor **3004**. Associated with this series inductor **3004** is an internal resistance **3006** with a resistive value. The current through the resistor **3006** is determined with a current detector **3008**, which will be described in more detail hereinbelow. This provides the inductor current to the output node **3010** wherein the output voltage V_O is provided. The output current, I_{OUT} , is output therefrom. Disposed between this output node and ground is the load capacitor **3012**, C_{OUT} . This has associated therewith an internal resistance **3040**. A current detector **3014** is disposed between the bottom plate of the capacitor **3012** and ground. The current detected by the current source **3008** is multiplied by a gain factor and input to a summing junction **3016**. Similarly, the current detected by the current detector **3014** is multiplied by a factor and input to the summing junction **3016**. In general, the ratio between the two internal resistors **3006** and **3014** determines what the multiplication factor is in both of the current detect legs. Additionally, the

output voltage V_O is input to the summing junction **3016**. The output of the summing junction **3016** is an intermediate voltage V_I . The output of each of the current detect legs after the amplification stage is provided by the following equations:

$$V_I = V_O + I_L R_{ESR2} + I_C R_{ESR2}$$

$$V_I = V_O + I_{OUT} R_{ESR2}$$

The output of the summing junction is then input to a summing junction **3018** to subtract the term $I_{OUT} R_{ESR2}$ from the value of V_{REF} to provide the error voltage. This is input to a control block **3020** for input to the half bridge **3002**. This is one implementation, but it indicates that the current can be determined from looking at particular voltages associated with the operation of the inductor and the capacitor. Once the currents are known, then a factor can be determined, such as the voltage across the resistor, and this can be utilized to perform the voltage positioning. Alternatively, the absolute value of the current can be determined and a look-up table utilized.

[0136] Referring now to **FIG. 31**, there is illustrated a schematic of the technique for measuring the current across the resistor without utilizing a Hall sensor. This is facilitated by disposing a series R_C network between one side of the inductor **3004** and the other side of the internal resistor **3006**. This is comprised of a resistor **3102** and a capacitor **3104** labeled R_O and C_O . This is a monitoring circuit. If, for example, V_O were equal to "0," then the following relationship would exist:

$$V_I = I_{OUT}(sL + R_{ESR2})$$

$$V_x = \frac{\frac{1}{C_O s}}{R_O + \frac{1}{C_O s}} = \frac{1}{1 + sR_O C_O} V_I$$

By combining the last two equations, the following exists:

$$I_{OUT}(sL + R_{ESR1}) \left(\frac{1}{1 + sR_O C_O} \right) = V_x$$

$$I_{OUT} = V_x \frac{1 + sR_O C_O}{R_{ESR1} + sL}$$

$$I_{OUT} = \frac{V_x}{R_{ESR1}} \left(\frac{1 + sR_O C_O}{1 + \frac{sL}{R_{ESR1}}} \right)$$

By matching the poles and zeros of the above function, i.e., setting $R_O C_O = L/R_{ESR1}$ or $R_O R_{ESR1} C_O = L$, then $I_{OUT} = B_x / R_{ESR1}$. The output of V_x is then equal to I_{OUT} multiplied by the value of R_{ESR1} .

[0137] Referring now to **FIG. 32**, there is illustrated a diagrammatic view of the technique for determining the current through the capacitor. The capacitor is illustrated with an output capacitor **3202**, the large filter output capacitor which has the internal resistance **3204**. By providing a parallel series RC component comprised of a series resistor **3206** and series capacitor **3208**, it is possible to determine at a junction between the resistor **3206** and capacitor **3208** a

voltage which represents the voltage across resistor **3206**. This is scaled such that the voltage across resistor **3206** is correlated with the voltage across resistor **3204** and current therefrom can be measured. The relationship is as follows:

$$\begin{aligned} V_O &= -I_C R_{ESR} - \frac{I_C}{sC_O} \\ V_O &= -I_C \left(\frac{1 + s R_{ESR} C_O}{sC_O} \right) \\ V_{CO} &= \frac{-I_C}{sC_O} \left(\frac{1 + s R_{ESR} C_O}{1 + s R_1 C_1} \right) \\ R_1 C_1 &= R_{ESR} C_O \\ V_{CO} &= \frac{I_C}{sC_O} \\ V_{CO} &= V_O + I_C R_{ESR} \end{aligned}$$

Thus, it can be seen that the voltage at the junction between resistor **3206** and capacitor **3208** directly relates to the current through the capacitor **3202**.

[0138] Referring now to **FIG. 33**, there is illustrated an embodiment illustrating the current sensing of the inductor current and the capacitor current of the embodiments of **FIGS. 31 and 32**. The voltage V_x from the junction between resistor **3102** and capacitor **3104** is input to one side of a summing junction **3302**, the other side connected to the output voltage V_O . The voltage V_{CO} from the junction between resistor **3206** and resistor **3208** is input to a summing junction **3304**. Both summing junctions **3302** and **3304** are operable to subtract the voltage V_{CO} and V_x from the output voltage. The output of the summing junction **3302** is normalized to R_{ESR} by multiplying by the function of R_{ESR}/R_1 , where R_1 is the value of resistor **3006**. Thus, this output can be summed with a summing junction **3306** with the output of summing junction **3304** to provide the voltage V_i , the intermediate voltage. This represents the voltage across the resistor **3014**, which can then be utilized to determine current, as this voltage represents the current I_{OUT} through a resistor of a value R_{ESR} . From an implementation standpoint, the voltage V_x on the junction between resistors **3102** and **3104** is provided as an input to one of the analog inputs on the pin **652** for input to the multiplexer **656**. The V_{CO} output at the junction between resistors **3206** and **3208** is also provided as analog input. All the microcontroller requires is knowledge of the values of the resistor **3006** and the resistor **3014** in order to determine the current through the inductor and capacitor, respectively. The functions R_{ESR}/R_1 is a constant that can be determined from known values and this utilized in the microcontroller to perform the operations of the summing junctions **3302**, **3304** and **3306** and the normalization stage.

DPWM

[0139] Referring now to **FIG. 34**, there is illustrated a general block diagram of the DPWM **416**. As noted hereinabove, the DPWM **416** is a state machine that is operable to generate up to six phases for use in driving external drivers that will control switches on the switching power converter. Each of these phases will be defined by a leading edge and a trailing edge, either leading or trailing edge being rising or falling. Either the $u(n)$ signal from the digital

compensator **412** or a microcontroller generated PID value from the register **564** is provided on the bus **570** as an input to the DPWM **416**. The DPWM **416** provides for highly flexible operation, which is operable to accommodate various pulse width and phase modulation schemes. Phase-to-phase timing can be programmed for fixed (or zero) dead time, or the microcontroller **440** can dynamically control dead time during converter operation. The DPWM **416** may be clocked at 200 MHz (5 nS resolution) or 50 MHz (20 nS resolution), depending on the setting associated therewith, these clocks generated by the PLL. It is noted that the DPWM is a state machine, such that, for each clock cycle, there is a result output by the state machine, as compared to an instruction based microprocessor or a DSP solution.

[0140] There are provided two paths from the input bus **570**. The first path is associated with a Symmetry Lock logic block **3402**, which is operable to interface with a Symmetry Lock SFR in the microcontroller **440**. As noted hereinabove, there are a plurality of SFRs, some of which are not illustrated, each of these SFRs occupying a portion of the address space of the microcontroller **440**, such that they can be written to or read from. The Symmetry Lock logic block **3402** is operable to latch each value output by the multiplexer **566** upon receiving a Data Ready signal. Since the digital compensator **412** operates at a clock rate of 10 MHz with a switching frequency of 500 kHz, for example, there will be many more samples of $u(n)$ during a particular switching frame than may be required. However, $u(n)$ can be changing and there may be modulation schemes and phase schemes that require an edge of the pulse to be sent based upon current data. The block **3402** latches each value and, upon the occurrence of a predetermined lock condition, the data will be "locked" into the logic block **3402**. This situation occurs when, for example, the trailing edge of PH1 requires current data to determine the position thereof. Once the trailing edge occurs on PH1, a system may be set up that, for example, the leading edge of PH1, a relative edge to the trailing edge of PH1, calculates its position relative to PH1 based upon the locked data in the logic block **3402**.

[0141] There are provided two separate paths output from the logic block **3402**, a first path associated with a summation block **3404** and a second path associated with a summation block **3406**. Each of the summation blocks **3404** and **3406** is operable to receive a 2's complement correction data value from a correction data SFR, labeled TLCD0 and TLCD1, respectively, which basically each provide an offset. There may be situations where the designer needs to compensate the mismatch of the components in the power supply. As such, it may be desirable to increase or decrease the value of $u(n)$. Once corrected, each of the paths flows to an associated limit block **3408** and **3410**, respectively, which will provide a corrected $u(n)$. The limit block **3408** is associated with the summation block **3404** and receives high and low limits, TLGT0 and TLLT0, wherein the limit block **3410** associated with the summation block **3406** receives high and low limits TLGT1 and TLLT1, these limits associated with respective SFRs. By providing two correction paths for each Symmetry Lock logic block, this allows a first edge to be defined based upon currently changing data and then subjected to two different correction factors and two different limit factors.

[0142] There is provided a second Symmetry Lock logic path associated with a logic block **3412**, having associated

therewith two paths associated with, in the first path, a summation block **3414** and the limit block **3416**. The second path has associated therewith a summation block **3418** and a limit block **3420**. These blocks have associated correction data and associated high/low limit values. This will provide two additional corrected $u(n)$ values which can both be locked.

[0143] Each of the four corrected $u(n)$ values form the blocks **3408**, **3410**, **3416** and **3420** are input to a timing generator **3422** which generates the phase values for output to a timing generator bypass logic block **3424**. The length of a switching cycle can be defined by signal SWC_CYC and there is also provided via control of the microcontroller **440** a start of cycle signal DPWM_EN. The polarity of the initial pulse edge, rising or falling, is determined by PH_POL.

[0144] Referring now to **FIG. 35**, there is illustrated a more detailed block diagram of the Symmetry Lock logic circuit. When enabled, the two Symmetry Lock logic blocks **3402** and **3412** store the value of $u(n)$ once per switching cycle at a time specified by a register **3502**, DPWMULOCK. The two latch $u(n)$ values are paired with two trim and limit functions, resulting in four unique corrected $u(n)$ functions, resulting in four unique corrected $u(n)$ functions that can be mapped to any of the PHn outputs in any combination. The value of $u(n)$ on the databus **570** is input to a data input of two latches **3504** and **3506** at the data input thereof. Each of the latches has a clock input. The clock input of latch **3504** is connected to the output of a leading/trailing edge select block **3508** which is controlled by the bit ULCK0_EDG bit of the register **3502**. This is operable to select either the leading or trailing edge of one of the six phases PH1-PH6 that are selected by a multiplexer **3510**. This is controlled by the first three bits of the register **3502**. As noted, the latch is operable to latch each value of the $u(n)$ data therein. The output of the latch **3504** is input to the trim and limit blocks **3512** and **3514**, associated with the blocks **3404**, **3408**, **3406** and **3410** of **FIG. 34**. Similarly, there is provided in the second Symmetry Lock logic path a multiplexer **3516** controlled by the bits 4-6 of register **3502** for selecting one of the six phases and inputting that to a leading/trailing edge select block **3518**, the output thereof driving the clock input of the latch **3506**. The latch **3506** is associated with two trim and limit blocks **3520** and **3522** that correspond to blocks **3414** and **3416**, and blocks **3418** and **3420**.

[0145] The timing generator **3422** is comprised of a plurality of multiplexers and phase generators. Each path has a multiplexer **3526** associated therewith and a phase generator **3528**, each of these being a pattern generator. Each multiplexer **3526** is operable to receive all four of the corrected $u(n)$ values and, depending upon which one is mapped to the particular phase path, input that to the associated pattern generator **3528**.

[0146] Referring now to **FIG. 36**, there is illustrated a more detailed diagram of the trim and limit sub-system, illustrating the registers and how they interface with various function blocks. A multiplexer **3630** is operable to be disposed between each of the outputs of the limiters **3408**, **3410**, **3416** and **3420** for forcing the operand to "0" such that the duty cycle of the output PH1-PH6 will be terminated when ICYC IRQ happens. This provides protection to the system from exposure to long term over current conditions.

Note that, although the multiplexer **3630** is illustrated as a single multiplexer, there is actually a separate multiplexer for each $cu(n)$ output.

[0147] Referring now to **FIG. 37**, there is illustrated a more detailed block diagram of the pattern generator **3528** for one of the phases. Each of the phase generators is divided into two sections, one for processing the leading edge and one for processing a trailing edge. As will be described hereinbelow, each phase generator is based upon a leading or trailing edge. It is the generation and positioning of this edge that is handled by the state machine. Each edge is associated with a specific timing type. The timing type is an absolute time, wherein edge is defined as one that unconditionally occurs at a specific time-tick. Relative time is associated with an edge that occurs a prescribed time after its reference edge transitions. For example, normally PH1 has a leading edge that occurs at time-tick #1 with a pulse width that is defined as a finite value of the $u(n)$. The leading edge of PH2 is a relative edge, in some power converters, wherein the leading edge thereof occurs a number of time-ticks after the falling edge of PH1. Another is hardware modulation timing, which is associated with an edge that occurs at a time specified by the value of one of the four corrected $u(n)$ modulation terms.

[0148] Each of the leading edge and trailing edge functionalities have associated therewith a portion of the multiplexer **3526**. The leading edge portion has a multiplexer **3702** associated therewith which is operable to select one of the four corrected $u(n)$ values, or a "relative" or a "absolute" input. These inputs are provided by the PHn_CNTL as one register for the lowermost eight bits and a ninth bit from the PHn_CNTL0 register. These are SFR control registers. This provides a leading edge control value for the leading edge portion. Configuration data is provided that is the select input to the multiplexer **3702** and is provided by the three lowermost bits of a PHn_CNTL0 SFR. The information in these three bits is also input, along with the output of the multiplexer **3702**, to a phase bit logic block **3704** that is operable to carry out the operations associated with defining the leading edge and defining the trailing edge. Thus, a control value is what is provided by the multiplexer **3702**. The reference phases are provided by multiplexer **3706** that selects between one of the six phases as a reference phase in the event that this is a relative edge created. This multiplexer is controlled by the four lowermost bits of the PHn_CNTL0 SFR.

[0149] The trailing edge is handled in a similar manner to the leading edge in that a multiplexer **3710** is provided for receiving the four corrected $u(n)$ values and also Relative and Absolute inputs from the PHn_CNTL3 control register and the eighth bit from the PHn_CNTL2 register. This provides a trailing edge control. A multiplexer **3712**, similar to the multiplexer **3706**, selects one of the PH1-PH6 phases as the reference phase when a relative edge is being generated, and this is controlled by the four lowermost bits of the PHn_CNTL2 register.

[0150] The contents of the PHn_CNTL0 and CNTL2 registers is set forth in Tables 1 and 2.

TABLE 1

PHn_CNTL0: Phase n Leading Edge Control Register 0	
Bit 7	PHnL(8): PHn Leading Edge Timing Data Bit 8 This is bit 9 (MSB) of the PHn_CNTL1 register
Bit 6-4	PHnL_SEL2 - 0: Phase 3 Leading Edge Control Bits 000: PHn Leading Edge Timing Determined by u(n)0 001: PHn Leading Edge Timing Determined by u(n)1 010: PHn Leading Edge Timing Determined by u(n)2 011: PHn Leading Edge Timing Determined by u(n)3 100: PHn Leading Edge Timing is Relative to Another Timing Edge 101: PHn Leading Edge Timing is Relative to Another Timing Edge 110: PHn Leading Edge Timing is Relative to Another Timing Edge 111: PHn Leading Edge Timing is Absolute
Bit 3	PHnL_EDGE: Relative Training Reference Edge Leading/Trailing Edge Select 0: Relative Timing is Referenced to Leading Edge 1: Relative Timing is Referenced to Trailing Edge
Bit 2-0	PHnL_PHN - 0: PHn Leading Edge Relative Timing Reference Edge 001: PHn Leading Edge Timing Relative to PH1 010: PHn Leading Edge Timing Relative to PH2 011: PHn Leading Edge Timing Relative to PH3 100: PHn Leading Edge Timing Relative to PH4 101: PHn Leading Edge Timing Relative to PH5 110: PHn Leading Edge Timing Relative to PH6

[0151]

TABLE 2

PHn_CNTL2: Phase n Trailing Edge Control Register 2	
Bit 7	PHnT(8): PHn Trailing Edge Timing Data Bit 8 This is bit 9 (MSB) of the PHn_CNTL1 register
Bit 6-4	PHnT_SELn - 0: Phase 2 Trailing Edge Control Bits 000: PHn Trailing Edge Timing Determined by u(n)0 001: PHn Trailing Edge Timing Determined by u(n)1 010: PHn Trailing Edge Timing Determined by u(n)2 011: PHn Trailing Edge Timing Determined by u(n)3 100: PHn Trailing Edge Timing is Relative to Another Timing Edge 101: PHn Trailing Edge Timing is Relative to Another Timing Edge 110: PHn Trailing Edge Timing is Relative to Another Timing Edge 111: PHn Trailing Edge Timing is Absolute
Bit 3	PHnT_EDGE: Relative Training Reference Edge Leading/Trailing Edge Select 0: Relative Timing is Referenced to Leading Edge 1: Relative Timing is Referenced to Trailing Edge
Bit 2-0	PHnT_PHN - 0: PHn Trailing Edge Relative Timing Reference Edge 001: PHn Trailing Edge Timing Relative to PH1 010: PHn Trailing Edge Timing Relative to PH2 011: PHn Trailing Edge Timing Relative to PH3 100: PHn Trailing Edge Timing Relative to PH4 101: PHn Trailing Edge Timing Relative to PH5 110: PHn Trailing Edge Timing Relative to PH6

[0152] Referring now to FIG. 38, there is illustrated a diagrammatic view of the bypass logic block 3424. The bypass logic is operable to safeguard the power supply system by forcing each PH output into user-defined “safe” states during supply shutdown. The embodiment of FIG. 38 shows the bypass logic for each phase. An output multiplexer 3802 is operable to select, on one input, the output of the DPWM pattern generator 3422, the default output, or one of three static pre-defined states contained in the Soft-

ware Bypass (SWBP_OUT) SFR 3806, the over-current protection fault (OCP_OUT) SFR 3808, or the Enable (ENABX_OUT) bypass SFR 3810. Therefore, the three shutdown sources, in priority, are the enable input, the over-current protection fault and the software bypass (noting that the software bypass is initiated by the microcontroller 440). Both the ENABLE input and the OCP are hardware shutdowns and are enabled by setting a bit in the DPWMCN register to a logic “1” which bit is the HWBP_EN bit. When enabled, a supply shutdown occurs when either the enable input pin is forced to its off state or the over-current protection interrupt (OCPIRQ) interrupts are asserted. If both occur simultaneously, the higher priority ENABLE interrupt will prevail. The lowest priority shutdown source is software bypass, which is invoked by the microcontroller 440 by setting an SWBP bit in the DPWMCN register to a logic “1.” This is all facilitated with a priority encoder 3812 wherein the DPWMCN SFR is connected to the highest priority input through an AND gate 3814 on one input thereof, the ENABIRQ interrupt connected to the other input. The DPWMCN HWBP_EN bit is also input to one input of an AND gate 3816, which has the output thereof connected to the second priority input, with the other input of AND gate 3816 connected to the OCPIRQ interrupt. The SWBP bit of the DPWMCN register is connected to one input of an AND gate 3818, the output thereof connected to the lowest priority input of the encoder 3812, the other inputs of the AND gate 3818 connected to the SWBP_PHNnEN bit associated with the particular phase. The transition from DPWM output to any of the three-defined states can be programmed to occur on switching frame boundaries, or instantaneously by setting the EMGY_EN bit of the DPWMCN register to a “1.” This is input to a control input of a multiplexer 3820, which selects either the direct output of the priority encoder 3812 or the output of an end-of-frame synchronizer block 3824 disposed between the other input of multiplexer 3820 and the output of the priority encoder 3812. The frame synchronizer block 3824 is controlled by the EOFIRQ, the end-of-frame interrupt. For this end-of-frame synchronizing, this indicates that all operations, the generation of all leading and trailing edges for all phases, will occur prior to the bypass mode. With the use of the bypass safeguards, the state of each of the phases can be predetermined. In this manner, it can be insured that a transistor will not be closed and power being directed toward an inductor to basically destroy the transistor or other parts of the power converter.

[0153] Referring now to FIG. 39, there is illustrated a timing diagram depicting the Sync Mode of operation. This mode allows the start of each switching cycle to be synchronized with an external clock. The user enables sync mode by assigning the SYNC input to the port I/O pins by setting a sync enable signal, SYNCEN, in the XBAR0 SFR and the SYNC_EN bit in the DPWMCN to a logic “1.” A logic level sync pulse is applied to the SYNC input of the integrated circuit, the positive edge of which triggers (or re-triggers) the start of a new switching operation, shown in FIG. 39. It can be seen that when the SYNC input goes high, at an edge 3902, the switching cycle will terminate. The SYNC pulse must return low a minimum of three clock cycles of the DPWM prior to the next positive transition, as illustrated in the associated detail. The switching cycle in execution is unconditionally terminated and the new switching cycle initiated on the positive edge 3902 of the SYNC

pulse. In non-sync mode, SWC_CYC in SFR register defines the switching cycle period.

[0154] Referring now to FIG. 40, there is illustrated a timing diagram for the operation of frame skipping, with FIG. 41 illustrating a detail of the bypass operation of FIG. 38. In the illustration of FIG. 41, the SWBP_PHNEN bit of the SWBP_OUTEN SFR is input to one input of an AND gate 4102, the other input thereof connected to the SWBP bit of the DPWMCN register. For frame skipping, even at a minimum PWM duty cycle, system losses at minimum may be insufficient to prevent V_{OUT} from rising above its specified maximum. Frame skipping reduces the effect of energy transferred to the load by momentarily shutting the supply output off on alternate cycles. It is analogous to pure skipping, but applies to all PH outputs. In reference to the timing diagram of FIG. 40, it can be seen that each PHn bit has a corresponding PHn enable bit in SWBP_OUTEN and a SWBP bit in SWBP_OUT. The end-of-frame interrupt interrupts the microcontroller 440 at the end of each switching cycle. When this occurs, the microcontroller 440 will clear the SWBP bit in DPWMCN register, forcing the output multiplexer 3802 for each PH output to pass either the DPWM output (active switching cycle), or the OFF state contained in SWBP_OUT. Frame skipping can be configured to skip any number of cycles. Normal (continuous active frame) load resumes when firmware detects an increase in output loading.

[0155] Referring now to FIG. 42, there is illustrated a flow chart depicting the operation of creating an edge in a driving pulse in the pattern generator. Each edge is created similar to another edge by this procedure, such that the pattern generator is operable to operate on edges, such that all that needs to be defined by the power supply designer is the parameters of an edge, whether it is an absolute edge, a relative edge, how many ticks to wait before generating the edge, whether it is a leading edge or a trailing edge and whether it is falling or rising. The program is initiated at a block 4202 wherein the referenced edge is selected in the appropriate phase, i.e., either the leading edge or the trailing edge. The program then flows to a decision block 4204 to determine if it is an absolute edge. An absolute edge, as described hereinabove, is one that has a defined starting point from the edge of the initiation of the frame. If so, the program flows along the "Y" path to a function block 4206 to reset the base to a value of "0." If it is not an absolute edge, then the program flows along the "N" path to a function block 4208 to monitor for the reference edge, i.e., to determine when the reference edge has occurred. This program flows to a decision block 4210 to determine if it has been triggered and it will maintain itself in a loop until such time, at which time it will flow along the "Y" path to a function block 4212 to latch the value of the DPWM counter as the base value. This basically sets the reference edge as the base. The program then flows to a decision block 4214 to determine if the corrected value of $u(n)$ is selected. This is also the point in the program to which the function block 4206 flows. If the corrected $u(n)$ is selected, the program flows along the "Y" path to a function block 4216 to select the corrected $u(n)$ as the operand. If not, the program flows along the "N" path to a function block 4218 to select the value from the SFR register as the operand, this being a fixed value. Both function blocks 4216 and 4218 flow to a function block 4220 to set the expected value equal to the base value plus the value of the operand. The program then

flows to a function block 4222 wherein the result is compared with the DPWM counter value. A decision block 4224 determines when the expected value is greater than or equal to the DPWM counter value, at which time it will flow along a "N" path to a function block 4226 to trigger the edge, i.e., create the edge. The program then flows to a function block 4228 to monitor for the end of frame interrupt and, if it occurs, the program will flow from a decision block 4230 along a "Y" path to a function block 4232 in order to reset the edge and the state machine, at which time the program will flow back to the input of function block 4202.

[0156] Referring now to FIG. 43, there is illustrated a flow chart depicting the operation of selecting the value of $u(n)$ from either the PID or the SFR. The program is initiated at a block 4302 and then proceeds to a block 4304 to monitor if the corrected $u(n)$ value is ready for latching. As described hereinabove, the data is ready after it has been processed through the conversion cycle of the ADC and then passes through the digital compensator. At the digital compensator, for example, the sinc filter may take longer to process due to the decimation aspect thereof. The program then flows to a decision block 4306 to determine if a new $u(n)$ is ready and, if not, it loops back to function block 4304. When ready, the program flows to a decision block 4308 to determine if the Symmetry Lock edge has been triggered such that Symmetry Lock is present. If so, this indicates that the new $u(n)$ should not be processed and the program flows back to the input of the function block 4304. If not, the program then flows to a function block 4310 to latch the new $u(n)$ into the register and then to a function block 4312 to correct the value of $u(n)$ by the offset to provide a corrected value thereof. The program then flows to a decision block 4314 to determine if a corrected value of $u(n)$ is less than the minimum limit and, if so, then it flows to a function block 4316 to set the corrected value of $u(n)$ to the minimum limit. If not, then the program flows to a decision block 4318 to determine if the corrected value of $u(n)$ is greater than the maximum and, if so, the program flows to a function block 4320 to set the corrected value of $u(n)$ to the maximum limit. If neither limit has been breached, the program flows to a function block 4322 to leave the corrected value of $u(n)$ unchanged and then to a decision block 4324 to determine if the ICYC interrupt has occurred. If so, the program flows to a function block 4326 to set the corrected value of $u(n)$ to "0" and, if the interrupt has not occurred, the program flows to a function block 4328 to leave the corrected value of $u(n)$ unchanged.

[0157] Referring now to FIG. 44a, there is more fully illustrated the over current protection circuitry 4400 of the digital pulse width modulator circuit 416 contained within block 446 (FIG. 4). The over current protection circuitry 4400 has provided thereto a voltage related to the output current IPK of the buck converter 402. The output current IPK is measured via a hall sensor which provides the measured current output. The voltage related to the output current IPK is provided to the positive input of a comparator 4402 via input line 4404. The switch 4406 on the input line 4404 is associated with the leading edge blanker circuit 4408 which will be more fully discussed herein below. The negative input of the comparator 4402 is connected to the output of a 4-bit programmable digital to analog controller (DAC) 4410. The 4-bit programmable DAC 4410 provides a voltage related to the threshold current I_{TH} to the negative input of comparator 4402. The 4-bit programmable DAC

4410 is programmed to provide a desired threshold by a control register **4412** having a control value stored therein. The comparator **4402** compares the provided voltage related to the output current IPK of the buck converter **402** with the programmed voltage related to the threshold current I_{TH} and when the voltage related to IPK exceeds the voltage related to the threshold current I_{TH} , a primary interrupt (ICYCIRQ) is generated on line **4414** from the output of comparator **4402**. The value to which the voltage related to the I_{TH} current is programmed by the digital to analog controller **4410** is based upon the limits of the buck converter **402** to which the DPWM is connected. Hysteresis for the comparator **4402** is controlled from hysteresis control values from a control register **4416**. The primary interrupt (ICYCIRQ) is provided to a clock input of 5-bit counter **4418**. The primary interrupt (ICYCIRQ) is also provided to the input of reset logic **4420**. The primary interrupt is output via line **4422** to the DPWM **416**, the controller **440** and to the integrator stage of the PID **540**.

[0158] The 5-bit control register **4418** monitors the number of occurrences of the primary interrupt. The present count for the number of occurrences is provided as an output on line **4424**. The present primary interrupt count is stored within a control register **4426** called ICYC count. The present ICYC count on line **4424** is compared at a comparator **4428** with an over current protection count limit provided from register **4430**. The OCP current limit comprises the maximum number of occurrences of primary interrupt ICYCIRQ in consecutive frames that may occur. The present ICYC count from the 5-bit counter **4418** is compared with the OCP count limit, which is stored in register **4430**, at comparator **4428**, and if the ICYC count from the 5-bit counter **4418** equals the OCP count limit, a secondary interrupt OCPIRQ is generated from the comparator **4428** on output line **4432**. The secondary over current interrupt is provided to the DPWM **416** to indicate the occurrence of a serious over current condition.

[0159] The primary over protection interrupt ICYCIRQ provides an indication of over current conditions which may or may not fix themselves in a next frame period. The occurrence of consecutive primary interrupt conditions are monitored by the 5-bit counter **4418** such that when a predetermined number of primary interrupts have occurred, the secondary interrupt OCPIRQ may be generated to indicate a more serious over current problem such as a dead short. The primary interrupt ICYCIRQ performs a number of functions within the switch power supply device described with respect to FIG. 1. The primary interrupt ICYCIRQ is provided to the DPWM **416** such that each of the switches connected to the phase outputs of the DPWM **416** are turned off. Additionally, the primary interrupt ICYCIRQ is provided to the PID **540** to hold the integrator to prevent it from overloading.

[0160] Referring now to FIG. 44b, there is illustrated the circuit for providing the integrated hold to the PID **540**. The primary interrupt ICYCIRQ is applied to a first input of OR gate **4470**. The second input of OR gate **4470** is connected to the integrator hold output from a latch **4472**. The output comprises the Q output of the latch **4472**. The output of OR gate **4470** is applied to an input of AND gate **4474**. The other input of AND gate **4474** is an inverted input of the end of frame interrupt EOFIRQ. The output of AND gate **4474** is

connected to the D input of latch **4472**. A clock signal PWMCK is applied to the clock input of the latch **4472**.

[0161] FIG. 44c describes the operation of the circuit of FIG. 44b. At step **4480**, the integrator hold circuit monitors for the primary interrupt ICYCIRQ. Inquiry step **4482** determines if the ICYCIRQ interrupt has been detected. If not, control passes back to step **4480**. Once the primary interrupt is detected, the integrator hold circuit is initiated at step **4484**. Once the integrator hold circuit has been initiated, inquiry step **4486** determines if the end of frame interrupt has been received. If not, the integrator hold circuit remains active at step **4484**. Once the end of frame interrupt is detected, the integrator hold circuit is released at step **4488**.

[0162] This is more fully illustrated in FIG. 45 where there is shown the pulsed output **4502** associated with PH X which could be any phase outputs of the DPWM **416**, and the primary interrupt signal ICYCIRQ provided from the output of the comparator **4402**. FIG. 45 illustrates three separate frame periods. Occurring from times T_0 to T_1 is a first frame **4506a**, from time T_1 to time T_2 is a second frame **4506b** and from time period T_2 to time period T_3 is a third frame **4506c**. During time frame **4506a**, a switch connected to the output of PH X would be turned on by the rising pulse edge **4508**. Upon detection of a pulse indicating a primary interrupt at rising edge **4510**, the switch connected with output PH X would be turned off by the signal being driven low at **4512** by the DPWM **416**. Likewise, in frame **4506b**, the switch associated with DPWM output PH X would be turned on at **4514** and turned off at **4516** responsive to detection of the primary interrupt ICYCIRQ at **4518**. The turning off of a switch in response to detection of the ICYC interrupt occurs similarly in frame **4506c**.

[0163] If the over current condition continues over multiple frames and the secondary interrupt OCPIRQ is generated, this signal is provided to the DPWM **416** which then has the option of immediately stopping operation of the DPWM upon receipt of the secondary interrupt OCPIRQ, or alternatively, may wait to cease operation of the DPWM at the end of the next frame. Whether the DPWM ceases operation right away or at the end of the frame is programmable by the user.

[0164] Referring now back to FIG. 44a, the reset logic **4422** is responsive to the primary interrupt ICYCIRQ and the end of frame interrupt EOFIRQ provided from the DPWM **416** to reset the 5-bit counter to "0" when pulses of the primary interrupt ICYCIRQ are no longer received in consecutive frames. Thus, if the reset logic **4420** within a previous frame has detected occurrence of a primary interrupt ICYCIRQ, and in the next frame, as indicated by the occurrence of the end of frame interrupt EOFIRQ, there is detected no occurrence of the primary interrupt ICYCIRQ, the reset logic **4420** provides a signal to the reset input of the 5-bit counter **4418** via line **4440** to reset the 5-bit counter to "0." The end of frame interrupt EOFIRQ is additionally provided as an input to the 5-bit counter **4418**. This enables the 5-bit counter to only count a single occurrence of the primary interrupt ICYCIRQ within a particular frame. If the 5-bit counter **4418** had already counted the occurrence of a primary interrupt ICYCIRQ during a single frame period and receives a second primary interrupt pulse, the counter **4418** will not count this pulse since the counter had not received an end of frame interrupt since receiving the last ICYCIRQ primary interrupt.

[0165] The leading edge blanker circuit 4408 mentioned herein above receives an input from the leading edge blanker select register 4442. The leading edge blanker select register 4442 provides a control input for actuating or not actuating the leading edge blanker circuit 4408. The leading edge blanker select register 4442 also provides an indication to the phase selector 4443 of the phase output of the DPWM 416 that is to be blanked. The phase selector 4443 is connected to receive each of the PH1-PH6 outputs of the DPWM 416, such that the leading edge blanker circuit may know when to actuate a leading edge blanker output via output 4444 to switch 4406 corresponding to a leading edge on one of these phase outputs. The leading edge blanker select register 4442 also provides the length of the blanking time of the blanking pulse. Additionally, the leading edge blanker circuit 4408 receives an input from the end of frame interrupt EOFIRQ to indicate when a frame has ended. This enables the leading edge blanker circuit 4408 to know when to begin looking for a next leading edge pulse. Finally, the PWMCK is a clock input clocking operations of the leading edge blanker circuit 4408. The output of the leading edge blanker circuit 4408 is provided to switch 4406 to provide an open switch condition at switch 4406 to keep the input of the comparator 4402 from seeing a spiked current output on the IPK line. This is more fully illustrated in FIG. 46.

[0166] FIG. 46 illustrates the output of one of the phase outputs 4602 from the DPWM 416, the output current IPK 4604 and the blanking signal 4606. Within a first frame 4608, the phase output of one of the outputs of the DPWM circuit 416 goes high at 4610. This comprises the leading edge of this switching pulse. In response to the output 4602 going high at 4610, a current spike 4612 due to parasitic capacitance is created at the current output IPK. If the voltage related to the current spike 4612 were applied to the input of the comparator 4402, the comparator 4402 might inadvertently register an over current condition responsive to the current spike even though no over current condition actually existed. A blanking pulse is provided from the leading edge blanker circuit 4408 via the output 4444 to the blanking switch 4406 to set the switch to an open condition to keep the comparator 4402 from monitoring the current spike on IPK. The current blanking pulse 4614 will only open the blanking switch 4406 during the time of current spike 4612. The remainder of the time the switch is closed enabling the comparator 4402 to compare the output current to the threshold current. The operation of the blanking signal 4606 in the following frame 4616 occurs in a similar fashion. The phase blanked by the leading edge blanker circuit 4408 and the length of the blanking pulse 4614 are each programmable by the user through the LEB select register 4442. The blanking circuit 4408 may also detect a falling edge signal that comprises a leading edge signal.

[0167] Referring now to FIG. 47, there is illustrated a flow diagram describing the operation of the over current protection circuitry in the manner for generating both the primary interrupt ICYCIRQ and the secondary interrupt OCPIRQ. The leading edge blanker circuit initially monitors at step 4702 the output current IPK. The output current IPK is compared at step 4704 with the threshold current ITH to determine whether the output current exceeds the threshold current. If inquiry step 4706 determines that the output current does not exceed the threshold current, control passes back to monitoring step 4702.

[0168] Once the inquiry step 4706 determines that the output current has exceeded the threshold current, a primary interrupt ICYCIRQ is generated at step 4708. Inquiry step 4710 determines if the interrupt is occurring within a new frame. If not, control passes back to monitoring step 4702 to continue to monitor for the occurrence of a primary interrupt in a new frame. If inquiry step 4710 determines that the primary interrupt has occurred within a new frame, the interrupt count is incremented at step 4710.

[0169] Next, at inquiry step 4714, a determination is made if the interrupt count has reached the count limit. If not, control returns to monitoring step 4702 to begin monitoring for a next interrupt pulse. If the interrupt count limit has been equaled, a secondary interrupt OCPIRQ is generated at step 4716. The controller 440 will reset the OCPIRQ when the OCP condition is removed, and process flow returns to monitoring step 4702 to continue monitoring the output current.

[0170] Referring now to FIG. 48, there is illustrated the process of operation of the reset logic 4420. The reset logic 4420 monitors at step 4802 the occurrence of the primary interrupt from the comparator 4402. If inquiry step 4804 detects an interrupt, control passes back to monitoring step 4802. If no interrupt is detected, inquiry step 4806 determines if an end of frame interrupt has been received by the reset logic 4420. If no end of frame interrupt has been received, control passes back to step 4802 to continue monitoring the primary interrupt output. When inquiry step 4806 detects an occurrence of an end of frame interrupt and no primary interrupt has been detected within that frame, the counter 4418 is reset at step 4808. Control then returns to monitoring step 4802 to repeat the process.

[0171] Referring now to FIG. 49, there is illustrated the circuitry for providing both over voltage and temperature protection for the DPWM 416 contained within block 446 (FIG. 4). A number of analog signals are applied to the input of a multiplexor 4902. These signals are provided from various analog outputs and include a V_{SENSE} input sensing the output voltage of the switched power supply and an AIN0/VIN input which is monitoring the input voltage of the switched power supply. Also, a TEMP signal is provided by a temperature sensor 4904 that measures the temperature of the device. These signals are multiplexed to the output 4906 of the multiplexor 4902 and provided to the input of a 12 bit analog to digital converter (ADC) 4910. The 12 bit ADC 4910 is controlled from values from an ADC control register 4912. The output of the 12 bit ADC is a digital output which is applied to the input of a special function register/limit (SFR/LIM) register set. There are a number of SFR/LIM register sets associated with output of the ADC 4910. Each of the SFR/LIM register sets are associated with one of the input analog signals provided to the multiplexor 4902. The SFR/LIM register sets have stored therein a limit value. The SFR/LIM register set compares a provided input from the ADC 4910 to this limit value, and if the limit value is exceeded, generates an associated interrupt signal at the output of the SFR/LIM register set.

[0172] Thus, when the V_{SENSE} signal is applied to the input of the 12 bit ADC 4910, a digital V_{SENSE} signal is applied to the input of SFR/LIM register set 4920. The SFR/LIM register set 4920 compares the provided digital value of V_{SENSE} to the predetermined value stored within the

register set 4920. If the provided value exceeds the stored value, a VSENSEIRQ is generated at output 4922. If the provided value does not exceed the stored limit value in register set 4920, no VSENSEIRQ is generated. Likewise, if the VIN value is applied to the input of the 12 bit ADC 4910, the digitized value is applied to the input of SFR/LIM 4924. If the provided digital value of the VIN exceeds the stored limit value in the register set 4924, a AIN0/VINIRQ is generated at output 4926. The remaining SFR/LIM register sets operate in a similar manner responsive to a digital input that is compared to a limit value stored within the register set. When the limit value is exceeded an appropriate interrupt is generated.

[0173] When the temperature value is applied to the input of 12 bit ADC 4910, the digitized temperature signal is applied to the input of the TEMP SFR/LIM register set 4930. As described previously, this value is compared with a temperature limit value in the register set 4930, and if this value is exceeded, a TEMP IRQ is generated at output 4932. However, the output of the TEMP SFR/LIM register set 4930 is connected to the input of an OR gate 4934. This is due to the fact that not enough interrupt resources are available for each of the SFR/LIM register set, so a limited number of the register sets have their outputs applied to the input of OR gate 4934. The interrupt provided to the input of OR gate 4934 is also provided at the output 4936 of OR gate 4934. Thus, when the TEMP's IRQ is applied to input 4932, it will also be provided at the output pin 4936. When a digital value is applied to a particular SFR/LIM register set, the remaining SFR/LIM register sets are each disabled. Thus, when a digital signal associated with a particular register set is being applied, that register set is the only register set which is presently enabled.

[0174] Referring now to FIG. 50, there is more fully illustrated the process of operation of the SFR/LIM register sets. Initially, at step 5002 each of the V_{SENSE} input voltage, the input voltage VIN and the temperature are monitored by the above-described circuitry. When a particular SFR/LIM register set determines at inquiry step 5004 that a limit value has been exceeded, the interrupt is generated at step 5006. If inquiry step 5004 determines that no value has been exceeded, control passes back to the monitoring step 5002. Once the interrupt 5006 has been generated and provided to the controller 440 of the switched power supply, the controller will access at step 5008 the special function register set to determine what the present problem may be.

[0175] Referring now to FIG. 51, there is illustrated a block diagram of the PLL block. The reference phase, i.e., an external or internally generated signal, is received on an input 5102 and input to one input of a phase-frequency detector 5104. The output of this is input to a charge pump circuit 5106 which is operable to charge a node from a positive sourcing circuit or to discharge the node to a sinking circuit. This is conventional. The output of the charge pump circuit 5106 is input to a loop filter 5108 to generate a control voltage for a voltage controlled oscillator (VCO) 5110. This output is provided as the upper level frequency of, in this example, 400 MHz. This is input to one input of a multiplexer 5112. This is then output to a divide-by-two circuit 5114, which provides on the output a 200 MHz clock, this being the preferred DPWM clock. The output of block 5114 is then input to another divide-by-two circuit 5116 to provide a 100 MHz clock signal, which is typically unused,

which is then output to a third divide-by-two circuit 5120, which provides a 50 MHz output and then to a divide-by-two block 5122 to provide on the output thereof a 25 MHz signal for input to the other input of the phase-frequency detector 5104. This PLL provides the 200 MHz clock for the DPWM clock. The filter clock is provided by dividing this by a factor of 20.

[0176] In an alternate operation, there is a test mode provided wherein the input 5102 is input to the other input of a multiplexer 5112 for bypassing the PLL operation in the blocks 5104-5110. This allows the dividers to be directly controlled and the frequency of operations to be controlled also.

[0177] Although the preferred embodiment has been described in detail, it should be understood that various changes, substitutions and alterations can be made therein without departing from the scope of the invention as defined by the appended claims.

What is claimed is:

1: A system for controlling a switching power converter operating at a switching frequency, comprising:

a digital controller for receiving an analog signal representing the output DC voltage of the power converter for comparison to a desired output voltage level and generating switching control signals to control the operation of the power supply to regulate the output DC voltage to said desired output voltage level, the operation of the digital controller parameterized by a set of operating parameters; and

a microcontroller for determining the parameters used by said digital controller, said microcontroller operating independent of the operation of said digital controller.

2: The system of claim 1, wherein said digital controller comprises a state machine that is operable generate said switching control signals.

3: The system of claim 2, wherein said state machine is register driven from information contained in a plurality of registers, with the contents of said registers comprising said operating parameters, which said registers are controlled by said microcontroller.

4: The system of claim 2, wherein said state machine is a clocked state machine that is clocked at the switching frequency of the power converter, such that each change in said switching control signals occurs in a single clock cycle of the switching frequency and said state machine.

5: The system of claim 1, wherein said microcontroller is operable to monitor the operating parameters of the operation of said digital controller during control of the power converter.

6: The system of claim 5, wherein said microcontroller is operable to change said parameters as a result of the monitored operating parameters.

7: The system of claim 1, wherein said microcontroller comprises an instruction based engine operating on stored instructions stored in an associated memory, said instruction based engine clocked with a microcontroller clock.

8: The system of claim 1, wherein said digital controller comprises:

- a differential analog-to-digital converter (ADC) for receiving the analog signal and the desired operating voltage and converting the difference therebetween to a digital error signal;
 - a digital compensator for processing of the digital error signal to compensate for loop phase to provide a compensated digital error signal; and
 - a pulse width modulator for generating said switching control signals as a function of said a compensated digital error signal.
- 9:** The system of claim 8, wherein said digital compensator operates in accordance with a proportional-integral-derivative (PID) control law.
- 10:** A system for controlling a switching power converter operating at a switching frequency, comprising:
- a digital controller for receiving an analog DC sense voltage representing the output DC voltage of the power converter and generating switching control signals for controlling the operation of the power switcher to provide a regulated output voltage, said digital controller including:
 - a data converter for converting the analog DC sense voltage to a digital sense signal,
 - a voltage generator for generating a desired reference voltage that represents the desired value of the regulated output voltage,
 - a difference device for determining the difference between said digital sense signal and said desired reference voltage to provide a digital error voltage,
 - a digital pulse width modulator for generating digital pulses with controllable pulse that are varied to control the switching power converter to minimize said digital error signal, and
 - a plurality of parameter control blocks for parameterizing the operation of said digital controller in accordance with predetermined operation parameters that define the operation of at least one of said data converter, said difference device, said voltage generator and said digital pulse width modulator; and
 - a microcontroller for determining the parameters for storage in said parameter control blocks, said microcontroller operating independent of the operation of said digital controller.
- 11:** The system of claim 10, wherein said digital controller and said microcontroller are all fabricated on a single semiconductor substrate to provide a monolithic device.
- 12:** The system of claim 10, wherein said digital pulse width modulator comprises a state machine that is operable generate said digital pulses.
- 13:** The system of claim 12, wherein said parameter plurality of control blocks comprise a plurality of registers for parameterizing said digital pulse width modulator and said state machine is register driven from information contained in said plurality of registers, with the contents of said registers comprising said operating parameters, which said registers are controlled by said microcontroller.
- 14:** The system of claim 12, wherein said state machine is a clocked state machine that is clocked at the switching frequency of the power converter, such that each change in

said switching control signals occurs in a single clock cycle of the switching frequency and said state machine.

15: The system of claim 10, wherein said microcontroller is operable to monitor the operating parameters of the operation of said digital controller during control of the power converter.

16: The system of claim 15, wherein said microcontroller is operable to change said parameters as a result of the monitored operating parameters.

17: The system of claim 10, wherein said microcontroller comprises an instruction based engine operating on stored instructions stored in an associated memory, said instruction based engine clocked with a microcontroller clock.

18: The system of claim 10, wherein said data converter comprises a differential analog-to-digital converter (ADC) for receiving said digital sense signal and said desired reference voltage for converting the difference therebetween to said digital error signal.

19: the system of claim 10, wherein said digital controller further includes a digital compensator for processing of said digital error signal to compensate for loop phase to provide a compensated digital error signal.

20: The system of claim 19, wherein said digital compensator operates in accordance with a proportional-integral-derivative (PID) control law.

21: A digital controller for controlling the operation of a DC-DC switching converter, comprising:

- a digital feedback control system for receiving an analog input voltage representing the output of the switching converter and digitally processing the analog input voltage by comparing it to a reference voltage and generating analog drive signals to control the operation of the switching converter to provide a regulated output, said digital feedback control system operating in accordance with predetermined operating parameters;
- said digital feedback control system having monitoring inputs and control inputs; and
- a microcontroller for monitoring the operation of the digital feedback control system and able to change the operating parameters under certain predetermined conditions.

22: A monolithic integrated circuit for controlling the operation of a DC-DC switching power converter, comprising:

- a sense pin for receiving an analog voltage input representing the DC output voltage of the power converter
- a plurality of switching control outputs for controlling the operation of the power converter with switching control signals to provide a regulated voltage;
- positive and negative power supply inputs for providing operating power to the integrated circuit;
- a voltage reference circuit for generating a reference voltage corresponding to the desired output DC voltage of the power converter;
- a digital control system for receiving the analog voltage input and digitally processing the analog input voltage by comparing it to the reference voltage and generating said switching control signals, said digital feedback control system operating in accordance with predetermined operating parameters;

said digital feedback control system having monitoring inputs and control inputs; and

a microcontroller for monitoring the operation of the digital feedback control system and able to change the operating parameters under certain predetermined conditions through said control inputs.

23: The system of claim 22, wherein said digital control system comprises a state machine that is operable generate said switching control signals.

24: The system of claim 23, wherein said state machine is register driven from information contained in a plurality of registers, with the contents of said registers comprising said operating parameters, which said registers are controlled by said microcontroller and are loaded through said control inputs.

25: The system of claim 23, wherein said state machine is a clocked state machine that is clocked at the switching frequency of the power converter, such that each change in said switching control signals occurs in a single clock cycle of the switching frequency and said state machine.

26: The system of claim 22, wherein said microcontroller is operable to monitor the operating parameters of the operation of said digital control system during control of the power converter through said monitor inputs.

27: The system of claim 26, wherein said microcontroller is operable to change said parameters as a result of the monitored operating parameters.

28: The system of claim 22, wherein said microcontroller comprises an instruction based engine operating on stored instructions stored in an associated memory, said instruction based engine clocked with a microcontroller clock.

29: The system of claim 22, wherein said digital control system comprises:

- a differential analog-to-digital converter (ADC) for receiving the analog voltage signal and the reference voltage and converting the difference therebetween to a digital error signal;

- a digital compensator for processing of the digital error signal to compensate for loop phase to provide a compensated digital error signal; and

- a pulse width modulator for generating said switching control signals as a function of said a compensated digital error signal.

30: The system of claim 29, wherein said digital compensator operates in accordance with a proportional-integral-derivative (PID) control law.

* * * * *