

04-14-00

A

**APPLICATION FOR U.S. PATENT
TRANSMITTAL FORM**

TI-30882

Attorney Docket No.

jc777 U.S. PTO
04/12/00

Assistant Commissioner for Patents
Washington, DC 20231

"EXPRESS MAILING" Mailing Label No. EM490248165US
Date of Deposit: April 12, 2000. I hereby certify that this paper is being deposited with the U.S. Postal Service Express Mail Post Office to Addressee Service under 37 CFR 1.10 on the date shown above and is addressed to the Assistant Commissioner for Patents, Washington, D.C. 20231.

C. Alan McClure
C. Alan McClure

Sir:

Transmitted herewith for filing is the patent application of:

Inventor(s): Mati Amit

For: System and Method for Home Network Communications

Enclosed are:

TEN(10) sheets of informal drawings, forty-eight (48) pages of Specification.
Declaration/Power of Attorney. (UNSIGNED)

FEE CALCULATION					FEE
	NUMBER		NUMBER EXTRA	RATE	BASIC FEE \$ 760.00
Total Claims	15	-20	0	\$ 22	\$ 0.00
Independent Claims	1	3	0	x \$82 =	\$ 0.00
Total Filing Fee					\$0.00
Assignment Recording Fee					\$ N/A
TOTAL FEES					\$760.00

Please charge to the deposit account of Texas Instruments Incorporated, Account No. 20-0668 in the amount of the Total Fees set forth. The Commissioner is hereby authorized to charge to the deposit account of Texas Instruments Incorporated, Account No. 20-0668, any additional fees which may be required, or credit any overpayment. **This form is submitted in triplicate.**

All correspondence related to this application may be addressed to the undersigned at TEXAS INSTRUMENTS INCORPORATED, P.O. Box 655474, MS 3999, Dallas, Texas 75265.

April 12, 2000
Date

C. Alan McClure
C. ALAN MCCLURE
Attorney for Applicant
Registration No. 31,041

jc542 U.S. PTO
09/548048
04/12/00

SYSTEM AND METHODS FOR HOME NETWORK COMMUNICATIONS

This application claims priority under 35 USC §119(e)(1) of Provisional Application Number 60/128,810, filed April 12, 1999.

10 Technical Field of Invention

The present invention relates to communications systems, and more particularly, to system and methods for home network communications.

Background of Invention

Home networking is a key technology for the evolving home infotainment market, and it is expected to become a very large market by itself within the next decade. Home networks will connect between computing devices (personal computers, palm computers, network computers, etc.), entertainment devices (TV, VCR, DVD player, video camera, audio systems, etc.), I/O devices (printer, scanner, head-sets, keyboards, remote controls, mouse, loud-speakers, etc.), home appliances, and modems (such as cable modems, DSL modems, and PSTN modems) that connect the home outsidess. The home network will enable a wide range of application such as internet sharing, peripheral sharing, file and application sharing, and home automation. The home network will distribute the computation power of the computer from the study room to the living rooms.

There are several home networking solutions that have already been proposed, including networking over the existing telephone wiring (e.g. HomePNA), networking over the existing power lines, short range wireless networks (Bluetooth), medium range wireless networks (e.g. HomeRF, IEEE802.11), and solutions that require new wiring, such as IEEE1394 (I.LINK) or CAT 5 Ethernet wiring.

Existing Telephone wiring (HomePNA) generally allows ordinary voice telephone calls to be carried over the wire, while at the same time providing up to several megabits of data throughput.

5 It is also possible to use the normal AC electrical wiring in the home for data transmission. Electrical wiring has been used in the past for low bit-rate data applications (e.g. home automation). Technologies for achieving multi megabit throughput on existing residential electrical wiring are under investigation in the industry.

10 Wireless technologies (Short-range wireless; Bluetooth; HomeRF; IEEE 802.11) technologies provide several megabits of throughput; however, their effectiveness can vary, depending on the size of the house, the proximity of other wireless networks, and other sources of noise.

15 The IEEE 1394 (i.LINK) standard defines a serial interface between digital devices. This inexpensive, easy-to-use and high-speed bus handles multimedia bandwidth requirements and provides a universal interface for a variety of devices. By allowing seamless data exchange between devices such as workstations, personal computers and digital televisions, VCRs, camcorders and set-top boxes, it enables a new generation of computers and consumer electronic devices to operate in a common environment.

 Originally developed as an interface to replace SCSI, IEEE 1394 offers bi-directionality, high data transfer rates and isochronous data transfers. This fire-wire technology required special wires.

20 For new homes, it is anticipated that standard Category 5 wiring can supplement twisted-pair telephone wiring. The added cost of including this extra wiring is low and the benefits reaped can be great, because 100BaseT and other high-speed network types work well over this cable.

 TV wiring that consist of coaxial cables are used to connect the antenna/cable TV output, typically via passive splitters, to the cable outlets at specific points in the home. Typical home TV wiring scenarios are depicted in Figure 1.

25 The signals transmitted over the in-home coaxial TV wiring may include regular video channels, data channels for fast Internet access (using e.g., DOCSIS cable modem), voice channels for telephony over cable, pay-per-view, control signals and more.

30 Technically, to use the in-home TV wiring for home networking applications, one may connect standard cable modems through the cable TV (CATV) system. Data from one cable modem can be transmitted to the other cable modem via the CATV head-end.

- 5 Such configuration has several drawbacks: (1) it loads the system, possibly above the typical headend system capacity; and (2) it introduces large delays that cannot be tolerated by at least some of the applications. Therefore, it is unlikely that cable operators will adopt such configuration.

It should be noted that a cable modem could be used to connect any type of home networking system to external (out of the home) networks, such as the Internet.

- 10 A home networking solution may also be built at a home that does not connect to the cable infrastructure (i.e. a home that is connected to a standard home antenna, a satellite dish, another access network (xDSL), or a wireless local loop).

continued

•
.
.

5 Summary of Invention

The present invention provides a system and methods for communication between subscribers' devices over cable infrastructure designed to carry video signals, using pass-band frequency bands, without transmission through a CATV headend device. A particular application of this system and method is home networking over coaxial TV cables. The disclosed system will allow very high-speed digital and analog communications within the home and from the home to external devices or networks using low cost devices.

The present invention provides home networking solutions that utilize in-home TV wiring for supplying high rate connectivity between any two home networking nodes. The present invention does not load the city cable TV (CATV) network.

In many, if not most, of US residential homes, there are several TV inlets, connected by coaxial (coax) cables to either a municipal CATV network or a TV antenna. This coax cable is an excellent communication medium, as it has a high bandwidth and it is shielded to avoid noise. The present invention provides a method and system which allows home networking over these coax cables, allowing for very high data rates and a low cost implementation. The term Home Cable Network (HomeCN) is used herein for the system of the present invention.

In the prior art (e.g. the DOCSIS 1.0 spec), a CATV infrastructure is utilized for communication between a subscribers' devices (e.g. cable modem) and a headend, thus, two subscribers' devices can communicate via the headend. The system and method of the present invention is based on direct communications between two subscribers' devices, without transferring the data via a headend, and thus allows for high data rates between units in a home without reducing the capacity of the regional CATV network.

In the prior art, coaxial cables have been used for local area networks (LAN) and for analog communications. The system and method of the present invention is designed for cable networks that carry video, or other information, from a headend or an antenna, and thus it is different from prior art LAN over coaxial cables. Furthermore, the method employs a new digital modulation scheme based on pass-band RF signaling, which is fundamentally different than prior art LAN and analog modulation over coaxial cables.

5 The present invention enables installation of modems, connected to different types of nodes of the CATV, to enable communication between these nodes. The present invention provides a way to transfer data between these nodes, when the data is not required to be transferred to the headend.

 The present invention provides a low cost solution, which is very importance to enable a solution for the mass market.

10 A summary of some of the key principles of the disclosed system and methods are noted below.

1. Subscribers' devices may communicate directly (not via the headend) using RF signaling over the coax cable. These signals will typically propagate between the devices via reflections from other devices in the line, e.g. splitters or amplifiers in the line.
2. When the home coaxial cables are connected to a local or regional CATV network, the HomeCN is done in an out-of-band frequency (i.e. band that is not in use, e.g. above 860 MHz), or in part of the downstream band (e.g., within the range of 100-860 MHz) which is allocated (e.g. by the cable operator) for home networking applications.
3. When the home coaxial cables are connected to a local or regional CATV network, there is frequency re-use between portions of the CATV plants (i.e. same frequency range is allocated to different users in a CATV plant), taking into account the isolation between those users due to the attenuation of the cable plant.
4. The frequency re-use can be improved by adding filters within the signal path in the local or regional CATV network. The quality of the signal transmitted by one subscriber device to another subscriber device can be further improved by deliberately using splitters with high reflections.
5. The home devices may also be capable of connecting to the headend, e.g. operate as a DOCSIS or DVB cable modem or set-top box, either simultaneously with connecting to other devices in the home, or in an alternative mode in which a devices switches between cable modem functionality and connecting to the other in home devices. Parts of the device that are capable of connecting to a headend can be used for both home networking and for cable modem functionality, thus reducing the implementation cost of the home networking functionality. An architecture is proposed in which the home network includes only one device, which can operate both as a cable modem and

as a home-networking device. In this architecture, all the other devices can communicate only over the home network, and if one of these devices need to communicate outside the home, it is communicating via the device with the cable modem functionality. Other devices that have home networking and cable modem functionality may also handle a direct connection. The home networking functionality will be implemented in cable modems, and particularly in host-based cable modems, which are installed in personal computers and are using the processor of the personal computer to perform some of the functionality of the cable modem and the home cable networking. More generally, the home networking devices will be installed in various kinds of devices that employ general purpose computers (such as a laptop computer, a network computer, a TV, a DVD device, or even certain cellular phones), and use their general purpose processors to perform home networking functionality, thus reducing the implementation cost of the home networking functionality.

6. In a particular implementation of the method, when the home coaxial cables are connected to a local or regional CATV network, each home device addresses the headend, and the headend is assigning carrier frequency, and bandwidth to each home network, and maximum power levels to each device on the home network. The specific power level is assigned by the home networking devices that exist in each specific sub-network. In another implementation of the method, the devices search for a non occupied frequency sub-band within a band that is pre-assigned for home networking, and once such a sub-band is found they use it for their needs. When a home CN device is initialized it is trying to "join its home network", that is trying to communicate with other devices in the same home and adopt their frequency band and protocol.
7. In a particular implementation of the method, the devices that share a home network are based on the IEEE 802.11 MAC layer. This protocol is in common use and is a collision avoidance multiple access protocol that supports priorities.
8. In a particular embodiment of the present invention, the splitter at the input to the user premises is replaced by a special splitter device that supplies higher quality home networking capabilities or a filter is connected to the splitter. A passive filter connected to the splitter insures that the home networking signals in a specific home will not interfere with or be interfered by other home networks. This passive filter provides a "single home" operational mode that allows for low cost equipment and frequency re-use. A home network splitter that supplies less isolation between the home drops and includes the filter inside is also provided. This home network splitter provides

better performance for the home network. An active device receives signals from a TV antenna or a regional CATV network and receives signals from subscribers' devices via the home coax lines, and functions as a repeater for communications signals between subscribers' devices as well as between subscribers' devices to a headend (in case the home is connected to a regional CATV network), while still allowing transparent transition of video signals from the TV antenna or the regional CATV network into the home.

9. In a particular embodiment of the present invention, the home coax network is connecting portions of the home (e.g. rooms or floors), and its terminals have inputs and outputs for wireless connections within these portions.

10. In a particular embodiment of the present invention, home CN devices have an interface to another communication link, such as IEEE1394 link (I.LINK), thus the home coax network is used to extend the range of the other link.

11. In a particular embodiment of the present invention, home CN devices have an interface to another communication link, such as Bluetooth, thus the home coax network is used to extend the range of Bluetooth coverage by supplying pico-cells that are connected between themselves and cover the required home area.

12. In cases where direct communications between home devices is not feasible (e.g. due to highly balanced splitter that has very low reflections), the home devices may have a fallback option of communicating via a regional CATV headend.

13. The data transmitted in the coax home network may be secured (i.e. encrypted)

As used herein, the term a "home network" means a local network; it does not necessarily have to be in a home. For example, it may be in an office, or in a complex that contains several homes (e.g. an apartment building).

5 Description of Drawings

The preferred embodiments of the invention as well as other features and advantages thereof will be best understood by reference to the detailed description which follows, read in conjunction with the accompanying drawings, wherein:

10 Figure 1 shows a home that has four nodes inside the home and is connected to a regional CATV plant;

Figure 2 shows an example of a preferred embodiment of the home network method and system connected to a regional CATV plant;

Figure 3 shows an example of the present invention, not connected to a CATV;

Figure 4 shows an example of HomeCN with a hub;

15 Figure 5 presents a frequency allocation that may be employed by the present invention;

Figure 6 shows an HFC infrastructure;

Figure 7 shows a network with a notch filter;

Figure 8 shows HCNM interfaces;

Figure 9 shows representative HCN data flows;

20 Figure 10 shows a power supply;

Figure 11 shows a dual frequency architecture;

Figure 12 shows dual frequency components;

Figure 13 shows layer 2 transport;

Figure 14 shows a Bluetooth home network;

25 Figure 15 shows neighborhood wiring;

5

Figure 16 shows building wiring;

Figure 17 and Figure 18 show home wirings;

Figure 19 and Figure 20 depict examples of an HCNM and HNCU.

Figure 16 shows building wiring;

5 Detailed Description

Figure 1 presents the structure of the existing regional CATV network.

The typical home coaxial cable infrastructure consists of a Cable Source [101] which is connected to the home Splitter [102] (the home splitter might be Customer Premises Equipment – CPE). Some wires connect the interfaces at home to the splitter. The components that can connect to the network are TV [103], VCR [104] that is connected to TV.

Cable Modems (CM) [105] (e.g. DOCSIS CM). Cable Telephone Device [106] that connects some phones via the cable infrastructure (e.g. using VoIP protocol over DOCSIS channel).

An amplifier [107] can be added in the entrance of the home / house to increase the signal power. (If CM equipment exists at home, this amplifier should be bi-directional amplifier. That amplifies the signal to home side (DS) in the 100MHz-860MHz frequency range, and amplifies the signal to the headend side (US) in the 5MHz-44MHz frequency range).

There are some major types of HomeCN components (see figure 2):

- **HCNI: Home Cable Networking Interface.**

A sub-component that supply Home Cable Networking interface. This sub-component is a part of specific equipment (e.g. PC, TV, DVD) [204,205].

- **HCNU: Home Cable Networking Unit**

A component that supply connection to the Home Cable Networking. This component is a separate unit that contains one or more interfaces to the home equipment (e.g. 10BaseT, USB, wireless). This component does bridging or routing between the HCN to the other interfaces (networks) [207,212].

- **HCNM: Home Cable Networking Modem**

A component that include HCN-U and cabal modem (e.g. DOCSIS cable modem).

This component supplies a connection to the Home Cable Networking, and a connection to the cabal headend. This component is usually a separate unit that also contains one or more other interfaces (e.g.

5 10BaseT, USB, wireless). This component does routing between the HCN network , the cable network and the other interfaces networks [206].

Figure 2 shows an example of a preferred embodiment of the disclosed method and system.

Figure 2 shows a Home Cable networking (HomeCN/HCN) that has 5 nodes [204-207, 212] of the CATV network, and it is connected to the regional CATV plants via cable [201]. Notch filter [202], is a
 10 band reject filter that does not pass a certain RF range that is used by the home networking devices [204-207, 212] This filter improves the isolation between the home network and other homes as well as the regional network. However, the use of such a filter is optional, as we believe that the disclosed system and method is functional with the isolation levels of the CATV network without the additional notch filtering [202]. RF splitter [203] splits the signal coming from and to the regional CATV plant [201], to the signals
 15 coming to and from units [204-207, 212] respectively. The signals arriving to RF splitter [203] from the home units [204-207, 212] are partially reflected back to these home units [204-207]. It may be recommended to use splitters that deliberately have high reflection levels (although we believe that the method and system can operate with typical commercial splitters). The Video Cassette Recorder (VCR) [204] and TV set [205] include Home Cable Networking Interface (HCNI) devices. The Personal Computer
 20 (PC) [208] is connected to a Home Networking Cable Modem (HNCM) device [206] (That supplies the Home Networking functionality and the Cable Modem functionality). The HCNM is also connected to a phone [215] and supplies the VoIP functionality. A PC that includes HCNI can be connected directly to the HCN. The HCNU + wireless units [207, 212] are connected to the CATV and has a wireless output (e.g. Bluetooth, HomeRF or infra-red) which connects to devices within the vicinity of the device [207], such as
 25 wireless telephone unit [209, 213], and a notebook computer [210]). The HCNU devices are capable of transmitting and receiving digital communications signals between them. These signals propagate in the CATV wires and are reflected by the RF splitter [203]. The HCNM device is further capable of operating as a DOCSIS cable modem and communicating with a headend of a regional CATV plant [201]. The HNCI's, the HCNU's and the HNCM are using Home Cable Network Protocol HCNP.

30 The HomeCN can also be used to supply full home coverage by the Bluetooth network. To enable this coverage some HCNU + Bluetooth components that are connected to HomeCN should be exist in the home [207, 212]. The person that is travel between the rooms with his wireless phone [209, 213] or with his notebook computer [210] can be connected to the appropriate Bluetooth station in the home.

5 We note that the method and system will still be capable to perform home networking if the home coaxial wiring is not connected to a regional CAT plant [201], but connected to TV antenna, or even disconnected. However, in such cases the home network will not allow the capability of connecting the home outside through the CATV, as done by the HMCM unit [206].

10 The HomeCN operation modes are determined according to the existence / not existence of notch filter at the home entrance (see figure 2 [202]).

The notch filter in the entrance of the home is a one of the basic element in the home network design. If this notch filter exists the HomeCN is disconnected from the regional cable network, therefore it design is more simple (single home network). When this filter not exists the home network is part of the regional network, therefore it design is more complicated, and some additional functionality is required.

15 The HomeCN supports two operation modes:

- **Single Home** operation mode – This mode required a Notch filter, or an amplifier that usually supplies similar functionality, or it can be operated in a system that does not connected to the CATV planet.
- **Connected Home** operation mode – This mode does not require a Notch Filter. This mode is more complex and additional functionality. Following some functionality that are required in the *Connected Home* operation mode: Wider frequency operation, frequency selection (FDM), multiple bandwidth, privacy, capability to be managed by the headend.

Notes:

- The notch filter can be passive component or an active component. An active component that also has management can supply some additional functionality. Example to important functionality is answer to the quarry “Is notch filter exist”. This quarry can be used by the HCNP to verify the type of operating mode that should be handled if the components supply the two modes.
- Notch filter adding to the home network design usually reduces the price and increase the performance of the home networking.
- The default operation mode is *Single Home*. The management system configures the components to the appropriate mode after initialization.
- The *Connected Home* operational mode is recommended only if it is managed by the CMTS.

5 Figure 3 presents a Home Networking network that exist at a house that does not connected to the Regional Cable infrastructure. Instead, it is connected to a local antenna [301]. This system is operates in *Single Home* operational mode.

Figure 4 presents HomeCN with a local cable hub. A Local Cable HUB [401] connects the HCNUs and the HCNIs. This system is operates in *Single Home* operational mode.

10 Figure 5 presents a typical channel allocation. This figure is suitable for example to system that supply TV channels, DOCSIS CM (US and DS), and HomeCN channels.

In the present figure, some of the HomeCN channels have a different width.

15 HomeCN components that are work in the single home operation mode (reduced mode) are always using the 900-906.25MHz channel. These components do not support the frequency selection capability, and different channel bandwidth capability.

20 There is an additional mode '*Dual Frequencies Mode*' in this mode there is a different frequency-range to the transmitted information and a different frequency-range to the received information. In this mode a transponder at the entrance of the home that transfer all the signals that are sent in the transmitted frequency-range to the received frequency-range. The major benefit of this method is decreasing the influence of the in home echo (For more details see *Dual Frequencies Mode* appendix).

Note:

- The HomeCN-P is defined by specifying the two lower communication layers: the physical layer and the data link layer.

25 The preferred frequency and the preferred frequency range (bandwidth) are selected according to the operational mode.

	<i>Connected Home</i> operation mode	<i>Single Home</i> operation mode
Frequency range	higher then 860 MHz; usually 900-960MHz	900-906MHz

RF channel spacing (bandwidth)	8 MHz or lower, according to the required rate	6.25 MHz
-----------------------------------	---	----------

- 5 The modulation method is QPSK, QAM 16, QAM 64 or QAM 256 according to the channel conditions, and according to the equipment capabilities.

The modulator of the home networking device **MUST** provide QPSK and QAM 16.

The modulator of the home networking device **MAY** provide QAM 64 and QAM 256.

The modulator **MUST** provide 2,560 ksym/sec.

- 10 The modulator **MAY** provide 160, 320, 640, 1,280, and 5,120 ksym/sec.

FEC (Forward Error Correction) **MUST** support R-S (Reed Salomon) T=0,10.

FEC (Forward Error Correction) **MAY** support R-S (Reed Salomon) T=0,...,10.

The Channel Allocation method is FDM - a specific frequency for each home network.

- 15 The frequency plan is done only in *connected home* operational mode. In this case it done by the management system.

The structure of the HFC is important for understanding the home networking when the system is in *Connected Home* operation mode. This structure is used for enabling frequency reuse.

The HFC system usually contains the following components (see figure 6):

- Headend (CMTS) [601] usually with fiber output.
- 20 • Fibers [602] that exist only in HFC (Hybrid Fiber Coax) environment and connect the Headend to the cabinets (Fiber Nodes) [603]. The cabinets include fiber to coax converters (O-E).
- The coax wires those connect the different components [604, 606, 607, 610, 611...].
- Amplifiers that increase the signal power, and also filter the frequencies that are not amplified [605, 608, 609]. (These amplifiers might include splitters)

- 5 • Splitters that get a single wire as input, and some wires as output. [605, 608, 609, 612, 613, 614, 619, 622].

The splitters are divided into two types: Active splitters that usually include the amplifier inside, and passive splitters, that usually only divide the power between the different ports.

- 10 The active splitters are usually used close to the CMTS (headend) side. The passive splitters are usually used in the house entrance and in the flats (near to the home end equipment).

The Attenuation and Isolation are used for two major subjects:

- Branches calculation - Dividing the HFC Network to Branches. The branches are the key for frequency reuse. Branch calculation should be done before frequency allocation for each HomeCN in the global HFC infrastructure.

- 15 • HomeCN home network – Understanding of the home network conditions.

These aspects are required for the HomeCN component and protocol design.

- 20 The HFC infrastructure is similar to a tree. This tree build with connection points that supplies isolation between the sub-trees. The components that are exist in the network (e.g. Amplifiers, splitters, and filters) supplies attenuation of the signal, except the amplifier that supply amplifying (only if it was designed to amplify the required frequency in this direction). This attenuation is also can be used for isolation between the sub-trees.

The key element for efficient frequency allocation to the HomeCN is frequency reuse.

- 25 To enable calculation of the frequency reuse in a different sub-trees, the term *branch* will be used. Branches' is defined as sub-networks that can use any home networking frequency without interference another sub-network that exist in another 'branch' and reuse the same home networking frequency.

The cable network can be divided to 'branches' because the tree structure supplies attenuation between its branches. The attenuation is granted by the coaxial cables and by components that include filters. Some of the splitters also and provide good isolation between the sub networks that are connected to these components.

5 The HomeCN is based on FDM (see HomeCN protocol), therefore each home gets its own frequency range. The ability to supply reasonable frequency range for each home is based on the network infrastructure and on the ability to reuse the after dividing the network to 'branches'.

10 The size of the 'branches' can be reduced by adding filters. These filters enable increasing of the frequency reuse. These filters are usually passive filters that are relatively small and can be added easily by the cable operator, or by the user at the home entrance. This mechanism of adding low cost filters at the entrance of a home / flat enables a single home / flat branch, and enables the *Single Home* operation mode.

 The frequency resources are limited. To increase the frequency resources one (or more) of the following methods can be used:

- 15 • Frequency Reuse: Enabling simultaneous usage of the same frequency by some customers.
 The 'branches' method is a method to support the isolation of customers group. This method enables reusing of the same frequency in separate groups. This method uses the attenuation characteristic of the existing components. The disadvantage of this method is the management complexity. The operator should be aware to its physical infrastructure attenuation characteristic.
- 20 • Supports wider frequency range.
 This option can be handled by building equipment that supports a wider range. The disadvantage of this method is higher price of the components that are required to support wider range. Because, wider range support increases the complexity of each component.

 The 'branches' method is very cost effective, and it increase the robustness of the home networking solution. Therefore, this document includes a detailed definition of this method.



25 The 'branches' approach enables reuse of the same RF frequencies, witch allows the following benefits:


- It enable the manufactures to reduce the price of the home networking equipment, because home networking equipment can support a smaller range of frequencies.
- 30 • It enables allocating a larger frequency range for each home / flat. This wider range can supply higher network capacity.

- 5 The Attenuation / Isolation calculations can be done by adding the attenuation of each component and the attenuation of the wire in the required pass and in the required direction.

The following table (table 1) presents the typical attenuation of the basic components.

Table 1: Attenuation / Isolation Calculation

Component Type	Signal Attenuation [dB] For frequency range of 900-960MHz
Coaxial Wiring	_0.21dB for meter (RJ 59 type). Notes: The isolation is depended in the wiring quality. Cable attenuation. Depends on cable length and signal frequency.
Passive splitter 	g – Insertion loss: $10\log_{10}(N)$: <i>Theoretical</i> $3_{(N=2)}, 6_{(N=4)}, 9_{(N=8)}$ Example of real values $4.2_{(N=2)}, 8.2_{(N=4)}, 12.5_{(N=8)}$ p - backward attenuation of downstream amplifier: $10\log_{10}(N)$: $3_{(N=2)}, 6_{(N=4)}, 9_{(N=8)}$ r - Isolation: 20-30 corresponding to the quality
Active splitter 	g - downstream amplifier gain: $10\log_{10}(N)$: $3_{(N=2)}, 6_{(N=4)}, 9_{(N=8)}$ (The amplifying functionality should be added). p - backward attenuation of downstream amplifier: ~55dB. (The attenuation is lower when the power supply is disconnected). r - :20-30 corresponding to the quality (higher in better quality)
Notch Filter	g – 40-60dB p – 40-60dB

	$r = 0.5 \text{ dB or } 19\text{dB according to the design.}$
---	---

5

Data Form 1: Components parameters

Components' Parameters

Component	Parameter	Value[dB]				Comments
Wires	<i>dB/meter</i>	RG-59	RG-6	RG-7	RG-11	
		0.21				
Passive splitter	<i>Insertion Loss</i> <i>Isolation</i> <i>Return Loss</i>	<i>N=2</i>	<i>N=4</i>	<i>N=8</i>		20-30
		4.2	8.2	12.5		
		22	25	30		
		11	11	12		
Amplifiers	<i>Amplifying</i> <i>Isolation</i> <i>Return Loss</i>					
Transputer						
Isolator						
Notch Filter	<i>Return Loss</i>	10				

Following some typical calculations based on figure 6 and table 1. These calculations are based on system that does not include notch filter.

Data Form 2: Typical loss between to partments

Loss between two partments

1 Loss between two modems in the same flat sharing the same splitter [from 615 to 616]:

Wires [meaters]	20	4.2
Splitter Isolation (n=4)[612]		25
Total [dB]		29.2

2 Loss between two modems in neighbor homes [from 615 to 617]:

Wires [meaters]	44	9.24	10m[home 612]+2*12m[flat to basment]+10m[home 613]
Insertion Lost (n=4)[612]		8.2	
Splitter Isolation (n=8)[608]		30	Passive splitter
Insertion Lost (n=4)[613]		8.2	
Total [dB]		55.64	

Note:

The loss between two modems that required to pass amplifier is more then 60dB, because the amplifier contains filter for these frequencies for the up stream direction.

The capability to calculate the attenuation between two different flats is important for enabling efficient frequency reuse. The cable operator should do the calculation of the “branches”. The calculation of the ‘branches’ can be done by the following methods:

- **Numerical Calculations** - Calculations that are based on preceding knowledge of the cable operator. The cable operator can do calculations that are based on its network structure and its network components.
- **Defining Basic Rules** – The operator can define some base rules that usually works, and divide the network to brunches according to these rules. E.g. (of rules) a. each port that connects directly to a filter / amplifier unit specify a “branch”; b. Homes / flats that are connected using passive filters will be on the same “branch”.
- **Measurements using special equipment** - The cable operator can use spectrum measurement equipment. This equipment will usually be used to enable the cable operator to define the rules according to its own infrastructure.
- **Measurements using HCNM Branch Calculation Mode** - The cable operator can use a specific mode of the home networking equipment that enables ‘branch’ calculation.

- 5 Each HCNM should have a specific mode that enables the management system to calculate each 'branch' member.

This mode contains the following base features:

- Lock on a specific frequency, and on a specific frequency range.
- Transmit a signal in a specific power for a specific period (The pattern of this signal is known).
- 10 • Measure the power of the input signal (The pattern and the measurement period are known).

The algorithm is based on the structure of the cable infrastructure. A tree data structure is built in the computer memory. This data structure represents the existing infrastructure.

The tree is built according to the following rules:

- Tree nodes are the splitters (the splitters can be active or passive).
- 15 The splitter capability to isolate between two sub-trees is saved as data in these nodes.
- The leaves are the CM, HCNM or HNO.
- The identification of these nodes is saved in these leaves.

The main process is to build the topology database. This process can be done by the following methods:

- 20 • Load the tree structure from the cable operator database.
- This process is simple but it required an updated database.
- Automatic generation of the tree structure based on measurements of the isolations between two components using the *HCNM – Branch Calculation Mode*. These calculations are very complex and are based on prior assumptions.

25 Note:

The base idea in automatic tree building is to calculate the isolation between two leaves. If the some leaves have similar isolation between themselves they can be connected to the same nodes. If there are two leaves with the same isolation, and an additional leaf that has a higher isolation this leave connect to the previous two leaves using additional higher level node.

Note:

10 It is very hard to calculate these numbers when the tree is calculated automatically, and the splitter supplies different isolations between the wires that are connected to the same node.

This 'branch' specification is based on the data structure that was built.

'Branch' is specified by the isolation between this 'branch' to the other "branch". This isolation enable the systems in two different 'branch' to use the same frequency without (or with negligible) interference.

15 A ‘branch’ is defined by specifying a threshold of the minimal isolation between this ‘branch’ to the other ‘branches’. When the isolation value in the tree nodes (or in summary of some layers that does not include leaves) is greater than the specified threshold all the nodes that are member in the specified sub-tree will be defined as nodes in a specific ‘branch’.

Notes:

- 20
- When the system is not occupied as a balanced tree, the ‘branch’ calculation might be less affective. In this case, it might be required to divide the frequency range to some sub-ranges, and define a ‘branch’ for each one of them. The algorithm for these calculations will not be specified in this document, because we do not think that the common network includes such complex structure.
 - The operator can add filters or special splitters to reduce the branches size.

25 To use the *Single Home* operation mode that simplify the equipment, notch filter should be added.
This filter can be added in the following points:

- Adding a filter at the flat / single user home entrance.

The advantage of this method is the ability of the end user to add the filter by himself.

- Replace the house basement splitter that split the signals between the flats to a special splitter.

30 The advantage of this method is the ability of the MSO to change a single splitter to a special splitter that includes internal filter. This splitter enables more affective usage of the home networking for some flats (homes).

The disadvantage of this method exists only if the HomeCN use the notch filter reflection. In this case

5 the attenuation and the delay of the coaxial wire between the flat to the central splitter. This influence is usually negligible.

 The attenuation between two points at home (and the range of these values when there are more than two points) dedicates the quality of the equipment that should be use for HomeCN.

 There are some RF challenges in designing the HomeCN components:

- 10 • The “hidden nodes” problem:
 This “hidden nodes” might exist when the isolation difference between two different nodes is different then the isolation between other two nodes. This problem is usually exist in a home that contains some splitters and a notch filter does not exist.
 i.e. if there are some HCNU the attenuation between two of them might be low, and between each one of them to the 3rd might be high.
 e.g. figure 7: the communication between 703 and 704 might be ‘hidden’ from 701 in particular when the notch filter [707] does not exist.
- 15 • High reflation:
 The reflection from the notch filter is in the power of the signal or it might be higer. When this reflection is higher then the signal we can use this reflection as our main signal.
- 20 • High reflation:

 The following calculations are based on table 1 and figure 7. These calculations are only valid for homes that have notch filter.

Data Form 3: Home Networking Typical Calculations

[illegible][illegible][illegible][illegible][illegible][illegible][illegible][illegible][illegible][illegible]

5 The security that is required in this protocol is the base on IEEE 802.11 or on line privacy plus.
The specification for line privacy plus protocol is presented in DOCSIS 1.1.

The management of the security keys can be done by the CMTS.

Note:
Home networks that works in *connected home* operational mode and are not connected to the CMTS will
10 use a single key.

The priority is integrated in Layer two MAC.

A HCNM has at least two physical interfaces.

- HCNM interface to the cable side.

This single physical interface contain two data channels (that use different frequencies):

15 1. ***Cable Modem Channel.***

The cable modem channel (e.g. DOCSIS), containing two sub-channels: up stream channel (US)
and down stream (DS) channel.

2. ***Home Networking Channel.***

20 The Home Networking channel (a single channel that is used for sending and receiving
information).

- HCNM interface to the home side – ***Home Interface.***

The home interface might be a single interface or it might contain some interfaces. This / these
interface(s) are connected to the equipment at home. This / these interface(s) can be Ethernet
(10/100/1G BaseT) (or some Ethernet ports), USB, Phone connection, Bluetooth, wireless, or other.

25 Notes:

- The HCNU and the HCNI components do not contain the Cable Modem Channel. Except HCNI that
designed as host-based, i.e. a card that inserted into the PC and connected to the PCI bus, in this
special case it might implement the HCNM functionality.
- The HCNM gets the information from these channels/interfaces simultaneously.

- 5 The HCNM bridges messages between the home interface to these cable channels and vice versa. In addition it might support the capability to bridge information between cable modem channel to the home-networking channel and vice versa (This capability is only required when HNO components exists).

The following table describes the bridging requirements for HCNM:

Bridging Type	Description
Cable Modem Channel - Home Interface	According to cable modem standard's specifications.
Home Networking Channel -Home Interface	Bridge the messages between the stations at the home networking and the stations that are connected to the HCNM home interface(s).
Cable Modem Channel - Home Networking Channel	Bridge the messages between the Cable Modem Channel and Home Networking Channel in the following conditions: • This component was configured to do Cable Modem channel -- Home Networking channel bridging; and • The message should be transferred between Cable Modem Headend system and HNO component.

- 10 Figure 9 presents some example of data flow.

Ex.1 and Ex.2: Message from the Cable headend to component no. 1 or component on. 2; and the returned response. These examples are present a standard cable modem protocol.

- Ex.3 and Ex.4: Message from the one component in the home network to another component in the home-network (1 to 3; 3 to 4) and response. The messages form the home equipment is transferred to the splitter, the splitter distributes the energy to the Cable In connector, and to the other output connectors that are connected to the splitter. The destination-component gets the message and returns the response.

- Ex.5: Message from the Cable headend to component 3 through component 1 (that was specified as the front router of the components that exist only in the home networking). The message is arrived to HNCM no. 1, it identifies the destination and its duty as router, and it routs the messages to HCNU no. 3. The response is transferred in the opposite way. (Note: if HNCM no.1 fails, HNCM no.2 can be configured to take its duty automatically).

5 The purpose of the home networking system is to transport Internet Protocol (IP) traffic through the HomeCN system.

The Network Layer protocol is the IP [RFC-791].

The home networking management can be done by two methods:

- 10 • Local management that is done at home.
This method is always used in the Single Home operation mode.
This option can be done when the house is not connected to the cable infrastructure, or when the house has isolation (for the home networking frequency) from the cable network and the headend does not support the home networking management capability.
Local management might not include all the capabilities that the central management supports.
- 15 • Central Management
Management from the headend that is done by the cable operator.
This option is the preferred method for *connected home* operational mode. This method used the standard cable modem interface (e.g. DOCSIS interface). The configurations of the HCNU and HCNI can be done by the headend via HCNM routing capabilities.

20 There are some options for power supply to the HomeCN units. Most of the HomeCN components will use local power supply. The special unit is a HomeCN component that its only interface is wireless (i.e. Bluetooth). For this type of unit, that required very low power consumption, a central home power supply can be added. The central power supply is a special HomeCN splitter that contains inside the following sub units: Notch filter, a passive splitter, and a power supply that enable units to gets its power
25 from the home cable infrastructure (see figure 10).

The present invention provides home networking solutions that utilize the in-home TV wiring, supplying high rate connectivity between any two home networking nodes. The presented solution does not load the city cable TV (CATV) network.

30 The present invention enables installation of modems, connected to different types of nodes of the CATV; to enable communication between these nodes.

The present invention presents solution of transferring the data between these nodes, when the data is not required to be transferred to the headend.

5 • **File and Application Sharing**

Multiple users can easily share applications, move files, or back up data, saving time and money. Automatic software updates are enabled by a network connection.

Other applications enabled by home networking:

• **Entertainment**

10 Easy-to-use home networks will also enable popular multi-player network games, either within the home or over the Internet.

• **Home Automation**

A ubiquitous, easy-to-install home network will also foster home automation applications, such as environmental control and security systems.

15 • **Voice and Video over IP**

New digital voice and video services are being introduced into the home. All these digital services—whether data, voice, or video—need to be accessible anywhere in the home by any device. All digital devices, including PCs, digital televisions, and digital telephones, will require a high-speed connection to the home network.

20 Today, it is estimated that over 15 million of the 100 million homes in the United States have two or more PCs, and 60% of new consumer PC purchases are by families that already have at least one computer. This number is expected to double by the year 2000.

25 Chief among these is the fact that the widely adopted and supported enterprise networking technologies require a technically skilled individual capable of designing and maintaining complex network architecture. Enterprise networks also require the use of high-grade wiring typically not found in most homes.

Also, few home users are willing to master the art of installing and maintaining an Ethernet repeater, learn even the basics about network protocols, or drill holes through their walls to run new network-capable wiring throughout their home.

5 Success in the consumer market requires that a home networking technology be inexpensive, easy to install, and easy to use. To be truly effective and embraced by consumers, a home networking solution must meet these criteria:

1. No new wiring.
Most existing homes are not wired for traditional networking equipment. Rewiring the home is too expensive and a hassle for most consumers.
2. Simple to install and use.
3. Must be low cost to allow the mass market to enjoy the benefits of home networking.
4. The range must be adequate to operate within a typical home.
5. Support high data rate.
- 15 6. The networking capability must grow with user applications without obsoleting existing devices.
7. The network must be secure.
The network data must remain private; it must not be accessible to neighbors or anyone outside the home.
8. The solution must not interfere with other systems, appliances and services.

20 Requirements:

1. The home networking equipment coexists with the other services on the cable network. In particular,

It is spectrally aligned with any combination of television and other signals in the cables; and

It does not cause harmful interference to any other services that are assigned to the cable network in spectrum outside of that allocated to the home networking. Therefore,

 - 25 • The solution should not interfere with the TV/video channels.
 - The solution should not interfere with any cable modem channels.
2. Comply with the general home networking requirements.

- 5 3. Verify that the technology does not limit the number of cable modems or the number of home networking modems. Due to using HNCM technology, each home will include more than a single CM. It is required that the cable headend will support the increased amount of CM's. For example DOCSIS protocol can support high quantity of CM's (up to 8,000 CM's for a MAC chip) in particular DOCSIS1.1.
- 10 4. The Home Networking (HN) is required to supply a scaleable bandwidth range (100Kb-10Mb and more).
5. The number of nodes that are connected to the home network should not be limited by the presented solution. The only limitation should be the identification method in layer two (e.g. the limitation of using MAC address).
- 15 6. The connection method and the connection rate from home to the Internet using any technology (e.g. xDSL, cable modem) should not be influenced by the home networking technology. The only difference may be the ability to use this Internet connection for central management. For example, the Ethernet protocol, as a home networking protocol, complies with this requirement. It does not create any limitations to the protocol that is used for connecting the home to the Internet. The
- 20 HomePNA is a home networking protocol that adds limitations and does not comply with this requirement. HomePNA enables the G.Lite protocol to be used for connecting the home to the Internet, but it does not enable the use of ADSL (10Mbps) or VDSL protocols because it uses the same medium (phone line) and the same frequencies.
- 25 7. The ability to create a component that supplies the functionality of home networking and the functionality of connection to the Internet.

Nice to have:

1. The ability to create a component that supplies the functionality of home networking and does not supply the functionality of connection to the Internet.
2. Home Networking might be able to operate without connection to the headend.
- 30 3. An important point is to define this protocol to use limited "cable" resources. It should not use the limited US (up stream) frequencies. It can use some of the DS (down stream) frequencies or higher frequencies (even if their distance is limited).

5 There are some advantages in using this solution:

- No new wiring is required. Usually there are some ports of the TV cable in each home.
- The capacity of data that can be transferred using this infrastructure is very high.
- There is no radiation. Wire radiation is very low, in particular Coax wires radiation is negligible. (Compared to wireless solutions this point is very important).

10 • Simple to installed and to use.

- It can be low cost to allow the mass market to enjoy the benefits of home networking.
- Supply high data rate.
- It enables a secured network. The network data can remain private; the information can not be accessible to neighbors or anyone outside the home.

15 • The range limitation is negligible compared to the typical home.

- The networking capability grows with user applications without making the existing devices obsolete.
- Total isolation from the home network to the cable infrastructure (filters) can be added, although it is not required.
- It uses the same infrastructure that is used today by the current entertainment equipment (e.g. TV, Video). Therefore, the cabling probably exists. Supporting this protocol only requires minor changes in the equipment.

20


The advantages of using the cable infrastructure:

- No new wiring is required. Usually there are some ports of the TV cable in each home. These ports are usually located in the appropriate location, because one of the major aspects of home networking is to connect your TV environment (that already has some interfaces to the cable infrastructure) to the computer environment (that already has an interface for the current cable modem).

25

- 5
 - The capacity of data that can be transferred using this infrastructure is very high (Order of Gbps).
 - There is no radiation. Wire radiation is very low, in particular Coax wire radiation is negligible. Compared to wireless solutions this point is of great importance.
The coax cables are also not sensitive to external radiation.

The two-frequency mode is existing to eliminate the echo problem that exists in some of the homes in the single frequency mode. The method is transmitting the information in a specific frequency range (e.g. 900-906 MHz) and receiving the information in a different frequency range (e.g. 910-916 MHz). The architecture of this solution appears in the following figure.



In the single frequency mode the information that is transferred from HCNU-2 to HCNU-3 is
15 transferred through Splitter-1 and in addition and echo from Splitter-main also received.

In the Dual Frequencies Mode the Transponder module is required to be added in the entrance to the home. The signal from HCNU-2 is transferred to the transponder module. The transponder module changes the signal frequency from the US frequency to the DS frequency and transmits it to the home. The HCNU-3 received this signal with no echo.

20 The transponder is a simple one that translates the input frequency to another, whether if it is with an up and down conversion or other technique such as conversion to baseband and back.

The HCNU can support the two modes, and according to the configuration the operation mode will be specified. The configuration can be done manually or automatically by verifying is the transponder exits (by sending a signal in the US channel and verifying if the signal arrived in the DS channel).

5 Therefore this module can be inserted in houses were there is a problem with reflection.

There are some additional benefits in the two-frequency mode:

- The transmission path has low insertion loss and negligible reflections.
- The transponder module can be inserted with the notch filter and with an amplifier.

The HN module and transponder modules are:

10 **Note:**

The transponder can be powered down (even remote) and the system returns to the initial model, this ability maybe very important to the cable operator.

This section describes other applications that can be operated using the same physical layer.

These applications are a group of applications that can be built on the same infrastructure.

15 Transporting of variety classes of layer two protocols through the home cable infrastructure. These applications are based on home networking layer one that is described in this document, and used the specific application layer two.

The HomeCN-P is a protocol that includes layer one and two. There are two options to transfer different layer two over this infrastructure:

- 20
- To transfer different layers two using the same layer one.
This method is used in the presented application.
 - To transfer different layers two over the layer two of the HomeCN-P.
This method is not used in this presented solution because the capacity and the delay are not good enough for the presented applications.

25 Following some examples of layer two protocol that can be used:

- USB
- IEEE 1394 (fire-wire)
- Ethernet (10BaseT, 100BaseT)

- 5 • Wireless

This system enables high rate connection between two points at home.

The system contains two Home Networking Bridges (HNB) that are connected through the home cable wiring, each one of them has the same layer two interface e.g. IEEE 1394.

The system structure is presented in the following:

- 10 This structure enables information sending in very high rates (e.g. 40Mbps) for each direction.

Note:

This system does not required burst modulator / demodulator. It can use a “standard” one.

- 15 The Bluetooth technology is design to supply connectivity of components that are located in the same area. The distance between the components should be less then 10 meters (This range probably does not include wall interference). When you build your home network, and your home is larger then a small flat. You need to connect component when the distance between them is larger then 10 meters.

The idea is to build a network at home that connects the Bluetooth sub-networks.

Advantages

- 20 • The benefits of the Bluetooth connectivity can be used.
- You can cover much larger range.
- The location of the cable infrastructure port in the room is going to be less important because all the room is “covered” (connected) by the network using Bluetooth connectivity.
- The Bluetooth CM can be very simple, and cost effective.

Disadvantages

- 25 • Adding Home Networking protocol that connects all the sub-networks of Bluetooth is required.
- You have two types of networks at your home.

- 5
- The rate of Bluetooth is less than 1Mbps. If a higher capacity is required, an additional connector type should be added (HomeCN-P capacity is 10-50Mbps). This additional type might make your network more complex, and will required an appropriate network management.

Notes:

- Figure 5 present an example of network.
- 10
- The HNO-Bluetooth can be a very simple component if the network is required to have at least one component of HCNM + Bluetooth that has the capability to manage the simple HNO-Bluetooth components.
- The management of the Bluetooth sub-networks and the ability to transfer the connection of a network element from one Bluetooth sub-network to another required a specific layer two Bluetooth roaming-in protocol.
- 15
- Adding Power-supply capabilities to the home amplifier enable very simple Bluetooth-CM component. Bluetooth-CM component is required to include the following: Tuner, CM-chip, Bluetooth-chip, and very small CPU (only is the CM-chip and the Bluetooth-chip does not contain CPU). The installation procedure is going to be very simple, Just plug it to the cable interface, no other wire are required. The BOM of this component is going to be very low.
- 20
- When the system is working in a single home operational mode and a notch filter exist, all the management is done local and the requirements from this management system are reduced.
 - When the system is working in a *Connected Home* operation mode, and the system contain a CM channel, the management is done from the headend. This management is much more complex.
- 25
- The following table presents the management functionality:

Table NNN: Management Functionality

Functionality	Description	Operation Mode (ALL or Only - <i>Connected Home</i>)
HCN units identification	Identify all the units that are sharing the same HCN	All

5 The following section describes the frequency planning mechanism.

The configuration for the specific frequency will be done by the management system. The calculation is based on the 'branch' calculation, because the process of frequency allocation is done separately in each "branch".

10 The following are base rules that are used in the calculation of each *home-network frequency-range*.

- The *home-network frequency-range* is specified by the required home-networking bandwidth. The required bandwidth is specified for each home-network separately.

E.g. the required *home-network frequency-range* to transfer 40Mbps is 6MHz.

- The *total frequency-range* is specified by the capability of the home networking equipment.
- 15 E.g. the *total frequency-range* can be 40MHz.

- The *total frequency-range* should be larger than the summaries of the *home-networks frequency-range* of all the home-networks that exist in each "branch".
- If this condition is not met, the cable operator can decrease the bandwidth of its customers, or divide the network into smaller "branches".

- 20 E.g. If a 'branch' contains 16 flats and each one of them ask for the higher bandwidth and the *total frequency-range* is 40MHz, each one of the flats can get $40\text{MHz}/16 = 2.5\text{MHz}$ *home-networks frequency-range*. The operator can also divide the *total frequency-range* in other method, 4 flats will get 5MHz each, and the other 12 flats will get 1.6MHz each.

There are some frequency-ranges that might be used.

- 25 The preferred frequency range is higher than 860 MHz.

Note:

There are some existing chips (low price) that supply two-direction filtering and tuner functionality for the specific 900-1000 MHz frequency-range (Note: These chips were designed for the cellular market).

The following table presents the comparison between these frequency-ranges.

Frequencies Range	Pros	Cons
-------------------	------	------

Frequencies Range	Pros	Cons
< 5 MHz	☐ Not used by DOCSIS and by the TV. ☐ Tuners are not required. • Low attenuation of the Coax Cable enables low power.	☐ The capacity is very low. ☐ The quality of this frequency-range is low. ☐ The cable network contains amplifiers for part of this frequency-range. These amplifiers are designed to amplify in the US direction; therefore the segmentations to 'brunch' are limited. • Low attenuation of the Coax Cable increases the 'brunch' size.
5-42 MHz	☐ Tuners are not required. • Low attenuation of the Coax Cable enables low power.	☐ The DOCSIS channels use this frequency-range. ☐ The frequency-range resource is very limited. ☐ The cable network contains amplifiers for this frequency-range. These amplifiers are designed to amplify in the US direction; therefore the amplifier may be saturated. • Low attenuation of the Coax Cable increases the 'brunch' size.
42-88 MHz	☐ Not used by DOCSIS and by the TV, these rates are the gap between DOCSIS US channels to TV channels and DOCSIS DS channels.	☐ This range is not free all over the world. For example, in the DEVIC standard this range is reduced. ☐ The cable network contains amplifiers for part of this frequency-range. These amplifiers are designed to amplify in the US direction; therefore the amplifier may be saturated.
88-860 MHz	☐ The standard tuner can be used. ☐ The capacity is not limited. ☐ There is good isolation between different home segments; therefore, 'brunch' separation can	☐ The TV channels and the DOCSIS channels use this frequency-range; therefore the cable companies probably prefer to use this resource for the TV channels and DOCSIS channels.

Frequencies Range	Pros	Cons
	be used.	
> 860 MHz	☐ Not used by DOCSIS channels and by the TV channels. ☐ There is a good isolation between different home segments, due to the non -matched impedance (Z_0). ☐ There are some existing chips (low price) that supply two-direction filtering and tuner functionality.	• The attenuation is high; therefore there are some distances limitations in very high frequencies. (Note: The distance limitation is not relevant to home networking). • There are some FCC limitations. These limitation probably not relevant for coaxial wires

5 Modulation Method

Various types of modulation can be used.

The modulation method should comply with the following requirements:

- Can be used in the required frequency range.
- Should support high bandwidth rate (more then 10Mbps).
- Should support bursts with short learning time.

10

The selected modulations that comply with these requirements are QPSK and QAM.

The Channel Allocation method should be FDM - a specific frequency for each home network. This chapter describes the Design Considerations.

- 15 There are some alternatives for channel allocation. The mechanism of channel allocation should answer the problem that a sub-network ("brunch") usually contains some home networks. The number of home networks that should use the same frequency range can be changed according to the physical layer condition i.e. according to the 'brunch' size.

- 5 There are some known methods to allocate channels for each home-network. The following table compares between them. This table does not present methods that are a combination of two base methods, because these combinations are not required (e.g. combination of FDM and TDM) in our simple problem:

Method	Pros	Cons
FDM - Frequency Domain Multiplexing	☐ Simple ☐ The frequency range can be updated according to the number of home-networks that share the same frequency, and according to the required bandwidth. ☐ Can use wide spectrum for the whole solution, when each home is required to use narrow range (less then 6 MHz). ☐ Very efficient, in particular when the number of home-networks in a specific 'brunch' is low. ☐ Does not require synchronization and does not require CMTS for synchronization.	☐ Not efficient in case of many home-networks on the same "brunch". According to our estimations, this case is probably rare. • CBR based; therefore it is not affective when the traffic is not CBR type.
FDM with frequency hopping	• Does not require any configuration. I.e. not required configuration of the frequency that each home should use. • Very efficient when the traffic is ABR type.	• More complex then FDM. • Hard to be managed by the Cable Operator. • It is not efficient when the traffic is CBR type (e.g. digital movie playing on the DVD in the leaving room, when the TV is in the bad room). • It has only disadvantage when the home is the only home on the brunch.
TDM - Time Domain Multiplexing	• The bandwidth allocation can be dynamic – according to the needs.	☐ Requires synchronization, therefore, it require CMTS for synchronization. ☐ Can not use the wide spectrum (more then 10 MHz) in each channel group.

Method	Pros	Cons
		☐ Making Home Cable Networking Unit (HCNU) equipment is very complex, because this equipment is required to get the sync from the cable modem network. • It his similar to FDM, but more complex, when the home is the only home on the brunch.
CDM – Code Domain Multiplexing	• The supplied bandwidth (data rate) can be dynamic – according to the needs.	☐ Very complex • Requires synchronization, therefore, it require CMTS for synchronization. ☐ Making Home Cable Networking Unit (HCNU) equipment is very complex, because this equipment is required to get the sync from the cable modem network. • Can not use wide spectrum (more then 10 MHz) in each channels group. ☐ The performances are low unless you are using complex equipment that supports wide spectrum sampling. • It his similar to FDM, but more complex, when the home is the only home on the brunch.

5

The data link protocol should be the IEEE 802.11 MAC layer CSMA/CA.

Note:

The CSMA/CA can be used with or without ACK protocol. The need for immediate ACK should be verified according to the quality of the infrastructure.

10 Following the design considerations:

There are some options to define the layer two (data link) protocol.

5 The major aspects that should be considered are:

- The number of stations that use the home networking is variable (usually 2-15).
- Station can be added to the network or removed from the network during the home network operation.
- Collision prevention is required, because collision detection in the QAM technology is complex.
- It is preferable that all the components will be similar, so that the home network will not require a special head component.

10

This method usually increases the robustness of the network, and does not require special addition of equipment.

- A standard protocol or protocol that is close to a standard protocol is preferred.

There are some protocols that comply with these requirements, following two examples:

15

- The 802.11 MAC layer CSMA/CA.

This protocol is used today by many vendors, usually, in the wireless LAN equipment. Consider the fact that Bluetooth interface might be required to be exist on the HCNM / HCNU / HCNI components, it would be much simpler to support a single MAC protocol. This protocol also supports priority.

20

- The Token Bus 802.4.

This protocol is not common, and it is very complex. Building a reduced version of this protocol can simplify the protocol, but it will not be a standard protocol.

The system security is done in layer two. This security can be based on to the following standards:

- The DOCSIS standard.

25

- IEEE 802.11 standard.

The preferred option is according to DOCSIS standard because:

- The CMTS headend already manage this security.

- 5 • The standard CM already contains these cores.

Priority should be defined for the two channels separately.

The priority for the cable modem channel:

The need for priority for this channel was investigated. Cable modem protocols such as DOCSIS include this capability for services that require this capability e.g. VoIP.

10 Example:

- The priority mechanism for the DOCSIS standard is well defined in DOCSIS 1.1.

The priority for the Home Networking channel:

The priority for this channel is divided into two aspects:

- 15 • Priority is required in the home-networking channel for applications that are required to be connected to the standard cable modem channel; but they are using the home networking as transport media. The solution for these applications is to use HCNM and not HCNU / HCNI, and to use the cable modem channel directly.

- 20 • Priority is required in the home-networking channel for applications at home. E.g. CBR priority for transferring a video from the DVD reader to the digital TV on another floor, high priority for games, low priority for backup.

The priority requirements for these applications probably will be added soon. But the basic requirements of the home networking does not require priority capabilities, and the data rate of the home networking is high therefore "best effort" is good enough.

25 According to the presented analyses, specifying the priority for the home networking can be handled in the 2nd phase.

The following table compares between the different home networking solutions.

Subject	HomePNA	HomeCN
No new wiring	Use the existing phone interfaces Small advantage for the number of phone jacks	Use the existing TV cable interfaces Advantage in the location for usage of home networking to entertainment (e.g.

Subject	HomePNA	HomeCN
		TV, VCR, DVD)
Installation	Simple to be install and use. Does not required any change in the home wiring.	Simple to be install and use. Usually, does not required any change in the home wiring. In some of the cases it required adding a component in the entrance of the home.
Notch filter adding	Might be required – depend on the VDSL / HomePNA coexistent.	May be require for low cost equipment, or to enable higher bandwidth.
Low cost	The host-based product price is \$79 for 1Mbps (Intel).	The solution can be in similar prices.
Range	Adequate to a typical home.	
User privacy	Does not required. The neighbor can use the cross talk for Eaves dropping (intelligence).	Required, only, when the notch filter (or flat amplifier) not exist, and you are afraid from Eaves dropping (intelligence) from neighbors that are connected to the same building splitter.
Interferes	Interferes with VDSL	No interferes
Available capacity	HomePNA 1 – 1Mbps HomePNA 2 – 10Mbps (This capacity is vary difficult to be achieved because the home phone wiring is in very low quality_.	Single Home low cost version – 20Mbps Higher version can support very high capacity because the coaxial network has very high quality.
Integrated into	DSL (G.Lite), Cable Modems?	Usually - Cable Modems, Bluetooth

5

Following some typical Street / Building wiring

The following describes HCNM.

The 1st chip is designed to be designed in “system on a chip” architecture. The base chip should supports the *Single Home* operation mode to reduce the price. In addition it required supplying a Bluetooth interface.

10

5 Following the components that should be exist on the chip: Burst receiver, Burst Transmitter, 900MHz front end (bi-directional), MAC (based on 802.11) that supports the HomeCN and the Bluetooth, The Bluetooth interface, and CPU core (ARM).

 The chip should support only specific the frequency of 900-906MHz and transmission rate of up to 30Mbps.

10 Note:

- This chip might also include Bluetooth core.
- CATV Cable Television
- CM Cable Modem
- DOCSIS Data Over Cable Service Interface Specifications
- 15 • HCNP Home Cable Networking Protocol
- HCNM Home Cable Networking Modem
- HCNI Home Cable Networking Interface
- HCNU Home Cable Networking Unit
- HomeCN, HCN Home Cable Networking

5 **What is Claimed is:**

1. A communication system, comprising:

a plurality of information processing devices capable of interconnection to exchange information;

a transmission medium including at least one coaxial wire, capable of carrying TV signals;

10 and

at least one communication device, connected to the transmission medium, operative to interconnect the information processing devices.

2. The communication system of claim 1, wherein said devices form a home network.

15 3. The communication system of claim 2, wherein the network employs a specific frequency range that is not used by other signals transferred over the transmission medium.

4. The communication system of claim 2, wherein the network uses a frequency range above 550 MHz.

5. The communication system of claim 4 wherein the frequency range is reusable in different networks.

20 6. The communication system of claims 2, wherein said network uses QPSK or QAM modulation.

7. The communication system of claim 2, wherein said network uses channel allocation according to FDM method.

8. The communication system of to claim 5, wherein each home network has its own data rate.

25 9. The communication system of claim 5, wherein each home network uses its own frequency range.

10. The communication system of claim 2, wherein the network uses bridge or routing protocols selected from the group of IEEE 1394, USB, and/or Ethernet protocols.

5 11. The communication system of claim 10, wherein the bridge function employs a single channel for the two directions or a specific channel for each direction.

12. The communication system of claim 1, wherein a received signal is a reflection of the transmitted signal from either a passive element or an active element.

13. The communication system according to claim 12, wherein the element is a passive splitter.

10 14. The communication system according to claim 12, wherein the element is a notch filter.

15. The communication system according to claim 12, wherein the element is a transponder which converts the signals in an input band to signals in another output band.


TI-30882

5 Abstract:

The present invention provides the ability to use existing cable TV wires for home networking.

TI-30882


Figure 1 – The existing regional CATV network



002T40 540450

TI-30082.

Figure 2 – HomeCN within a regional CATV network



TI-30882

Figure 3 – HomeCN connected to a TV antenna





Figure 4 – HomeCN with a local cable hub



TI-30882

Figure 5 – Frequency Allocation





Figure 6: HFC infrastructure



TI-30882

Figure 7: Example of home wiring that contain notch filter






Figure 8: HCNM Data Channels



TI-30882

Figure 9 – HomeCN data flow examples



TI-30882

Figure 10: Central Power Supply





Figure 11: Dual Frequencies Mode components



TF-32082

Figure 12: Layer Two Transporting over Home Networking




Figure 13: Bluetooth Home Networking Using Cable Infrastructure





Figure 14: Wiring in negherhood that contains some small department buildings



TI-30082

Figure 16: Home - Column instalation




Figure 17: Home - Tree instalation





Figure 15: Wiring in big department building



TI-30882

Figure 18: HCNM Proof Of Concept – Card





Figure 19: HCNU Proof Of Concept – Card



002T10: 81024450

TI-30880

04/12/00

	Class	Subclass
ISSUE CLASSIFICATION		

PATENT NUMBER

U.S. UTILITY Patent Application

O.I.P.E. SCANNED <u>117</u> Q.A. <u>A.G.</u>	PATENT DATE
--	--

APPLICATION NO.	CONT/PRIOR	CLASS	SUBCLASS	ART UNIT	EXAMINER
09/548048	D	~~709~~ 725	37.8	2750 2611	SRIVASTAVA

APPLICANTS

Mati Amit

TITLE

System and methods for home network communications

PTO-2041
12/99

ISSUING CLASSIFICATION

ORIGINAL				CROSS REFERENCE(S)								
CLASS		SUBCLASS		CLASS	SUBCLASS (ONE SUBCLASS PER BLOCK)							
INTERNATIONAL CLASSIFICATION												

☐ Continued on Issue Slip Inside File Jacket

☐ TERMINAL DISCLAIMER	DRAWINGS			CLAIMS ALLOWED	
	Sheets Drwg.	Figs. Drwg.	Print Fig.	Total Claims	Print Claim for O.G.
☐ The term of this patent subsequent to _____ (date) has been disclaimed.	 _____ (Assistant Examiner) (Date)			NOTICE OF ALLOWANCE MAILED	
☐ The term of this patent shall not extend beyond the expiration date of U.S. Patent. No. _____ _____ _____	 _____ (Primary Examiner) (Date)			ISSUE FEE	
				Amount Due	Date Paid
☐ The terminal ____ months of this patent have been disclaimed.	 _____ (Legal Instruments Examiner) (Date)			ISSUE BATCH NUMBER	
WARNING: The information disclosed herein may be restricted. Unauthorized disclosure may be prohibited by the United States Code Title 35, Sections 122, 181 and 368. Possession outside the U.S. Patent & Trademark Office is restricted to authorized employees and contractors only.					

Form PTO-436A
(Rev. 6/99)

FILED WITH: ☒ DISK (CRF) ☐ FICHE ☐ CD-ROM
(Attached in pocket on right inside flap)

(FACE)

Best Available Copy

SEARCHED			
Class	Sub.	Date	Exmr.
725	74, 78	12/13/5	LS
	80, 81	↑	↓
	82, 85		
	111, 110		
	131, 133		
	139, 141		
H04N	151, 153		
	7/15	↓	↓
	2/16		

INTERFERENCE SEARCHED			
Class	Sub.	Date	Exmr.

SEARCH NOTES (INCLUDING SEARCH STRATEGY)		
	Date	Exmr.
EAST	12/13/5	LS

Best Available Copy

(RIGHT OUTSIDE)

ISSUE SLIP STAPLE AREA (for additional cross references)

POSITION	INITIALS	ID NO.	DATE
FEE DETERMINATION	<i>rw</i>	<i>608904</i>	<i>4/22/00</i>
O.I.P.E. CLASSIFIER	<i>J.S.</i>	<i>69134</i>	<i>6-19-00</i>
FORMALITY REVIEW	<i>11</i>	<i>11</i>	<i>8-31-2000</i>
RESPONSE FORMALITY REVIEW			

INDEX OF CLAIMS

✓ Rejected N Non-elected
 = ... Allowed I Interference
 - (Through numeral)..... Canceled A Appeal
 + ... Restricted O Objected

Claim	Date
Final	
Original	
1	
2	
3	
4	
5	
6	
7	
8	
9	
10	
11	
12	
13	
14	
15	
16	
17	
18	
19	
20	
21	
22	
23	
24	
25	
26	
27	
28	
29	
30	
31	
32	
33	
34	
35	
36	
37	
38	
39	
40	
41	
42	
43	
44	
45	
46	
47	
48	
49	
50	

Claim	Date
Final	
Original	
51	
52	
53	
54	
55	
56	
57	
58	
59	
60	
61	
62	
63	
64	
65	
66	
67	
68	
69	
70	
71	
72	
73	
74	
75	
76	
77	
78	
79	
80	
81	
82	
83	
84	
85	
86	
87	
88	
89	
90	
91	
92	
93	
94	
95	
96	
97	
98	
99	
100	

Claim	Date
Final	
Original	
101	
102	
103	
104	
105	
106	
107	
108	
109	
110	
111	
112	
113	
114	
115	
116	
117	
118	
119	
120	
121	
122	
123	
124	
125	
126	
127	
128	
129	
130	
131	
132	
133	
134	
135	
136	
137	
138	
139	
140	
141	
142	
143	
144	
145	
146	
147	
148	
149	
150	

Best Available Copy

If more than 150 claims or 10 actions
staple additional sheet here

(LEFT INSIDE)

04-14-00

APPLICATION FOR U.S. PATENT
TRANSMITTAL FORM

TI-30882

Attorney Docket No.

jc777 U.S. PTO
04/12/00

Assistant Commissioner for Patents
Washington, DC 20231

"EXPRESS MAILING" Mailing Label No. EM490248165US
Date of Deposit: April 12, 2000. I hereby certify that this paper is being deposited with the U.S. Postal Service Express Mail Post Office to Addressee Service under 37 CFR 1.10 on the date shown above and is addressed to the Assistant Commissioner for Patents, Washington, D.C. 20231.

C. Alan McClure
C. Alan McClure

Sir:

Transmitted herewith for filing is the patent application of:

Inventor(s): Mati Amit

For: System and Method for Home Network Communications

Enclosed are:

TEN(10) sheets of informal drawings, forty-eight (48) pages of Specification.
Declaration/Power of Attorney. (UNSIGNED)

FEE CALCULATION					FEE
	NUMBER		NUMBER EXTRA	RATE	BASIC FEE \$ 760.00
Total Claims	15	-20	0	\$ 22	\$ 0.00
Independent Claims	1	3	0	x \$82 =	\$ 0.00
Total Filing Fee					\$0.00
Assignment Recording Fee					\$ N/A
TOTAL FEES					\$760.00


Please charge to the deposit account of Texas Instruments Incorporated, Account No. 20-0668 in the amount of the Total Fees set forth. The Commissioner is hereby authorized to charge to the deposit account of Texas Instruments Incorporated, Account No. 20-0668, any additional fees which may be required, or credit any overpayment. **This form is submitted in triplicate.**

All correspondence related to this application may be addressed to the undersigned at TEXAS INSTRUMENTS INCORPORATED, P.O. Box 655474, MS 3999, Dallas, Texas 75265.

April 12, 2000
Date

C. Alan McClure
C. ALAN MCCLURE
Attorney for Applicant
Registration No. 31,041


Figure 1 – The existing regional CATV network



002740-87034560

TI-30082

Figure 2 – HomeCN within a regional CATV network



002740 84034500

TI-30882

00240-84034560

Figure 3 – HomeCN connected to a TV antenna





Figure 4 – HomeCN with a local cable hub



TI-30082

Figure 5 – Frequency Allocation





Figure 6: HFC infrastructure



TI-30882

Figure 7: Example of home wiring that contain notch filter






Figure 8: HCNM Data Channels



TI-3088.2

Figure 9 – HomeCN data flow examples



TI-30882

Figure Central Power Supply





Figure 11: Dual Frequencies Mode components



TF-30002

Figure 12: Layer Two Transporting over Home Networking




Figure 13: Bluetooth Home Networking Using Cable Infrastructure





Figure 14: Wiring in negherhood that contains some small department buildings



TI-30082

Figure 16: Home - Column instalation




Figure 17: Home - Tree instalation





Figure 15: Wiring in big department building



TI-30882

Figure 18: HCNM Proof Of Concept – Card





Figure 19: HCNM Proof Of Concept – Card



002110-34034900

TI-30882

SYSTEM AND METHODS FOR HOME NETWORK COMMUNICATIONS

This application claims priority under 35 USC §119(e)(1) of Provisional Application Number 60/128,810, filed April 12, 1999.

10 Technical Field of Invention

The present invention relates to communications systems, and more particularly, to systems and methods for home network communications.

Background of Invention

Home networking is a key technology for the evolving home infotainment market, and it is expected to become a very large market by itself within the next decade. Home networks will connect between computing devices (personal computers, palm computers, network computers, etc.), entertainment devices (TV, VCR, DVD player, video camera, audio systems, etc.), I/O devices (printer, scanner, headsets, keyboards, remote controls, mouse, loud-speakers, etc.), home appliances, and modems (such as cable modems, DSL modems, and PSTN modems) that connect the home outside. The home network will enable a wide range of application such as internet sharing, peripheral sharing, file and application sharing, and home automation. The home network will distribute the computation power of the computer from the study room to the living rooms.

There are several home networking solutions that have already been proposed, including networking over the existing telephone wiring (e.g. HomePNA), networking over the existing power lines, short range wireless networks (Bluetooth), medium range wireless networks (e.g. HomeRF, IEEE802.11), and solutions that require new wiring, such as IEEE1394 (I.LINK) or CAT 5 Ethernet wiring.

Existing Telephone wiring (HomePNA) generally allows ordinary voice telephone calls to be carried over the wire, while at the same time providing up to several megabits of data throughput.

5 It is also possible to use the normal AC electrical wiring in the home for data transmission. Electrical wiring has been used in the past for low bit-rate data applications (e.g. home automation). Technologies for achieving multi megabit throughput on existing residential electrical wiring are under investigation in the industry.

2
10 Wireless technologies (Short-range wireless; Bluetooth; HomeRF; IEEE 802.11) ~~technologies~~ provide several megabits of throughput; however, their effectiveness can vary, depending on the size of the house, the proximity of other wireless networks, and other sources of noise.

The IEEE 1394 (i.LINK) standard defines a serial interface between digital devices. This inexpensive, easy-to-use and high-speed bus handles multimedia bandwidth requirements and provides a universal interface for a variety of devices. By allowing seamless data exchange between devices such as
15 workstations, personal computers and digital televisions, VCRs, camcorders and set-top boxes, it enables a new generation of computers and consumer electronic devices to operate in a common environment.

Originally developed as an interface to replace SCSI, IEEE 1394 offers bi-directionality, high data transfer rates and isochronous data transfers. This fire-wire technology required special wires.

For new homes, it is anticipated that standard Category 5 wiring can supplement twisted-pair
20 telephone wiring. The added cost of including this extra wiring is low and the benefits reaped can be great, because 100BaseT and other high-speed network types work well over this cable.

TV wiring that consist of coaxial cables are used to connect the antenna/cable TV output, typically via passive splitters, to the cable outlets at specific points in the home. Typical home TV wiring scenarios are depicted in Figure 1.

25 The signals transmitted over the in-home coaxial TV wiring may include regular video channels, data channels for fast Internet access (using e.g., DOCSIS cable modem), voice channels for telephony over cable, pay-per-view, control signals and more.

Technically, to use the in-home TV wiring for home networking applications, one may connect standard cable modems through the cable TV (CATV) system. Data from one cable modem can be
30 transmitted to the other cable modem via the CATV head-end.

- 5 ^aSuch configuration has several drawbacks: (1) it loads the system, possibly above the typical headend system capacity; and (2) it introduces large delays that cannot be tolerated by at least some of the applications. Therefore, it is unlikely that cable operators will adopt such configuration. ^a

It should be noted that a cable modem could be used to connect any type of home networking system to external (out of the home) networks, such as the Internet.

- 10 A home networking solution may also be built at a home that does not connect to the cable infrastructure (i.e. a home that is connected to a standard home antenna, a satellite dish, another access network (xDSL), or a wireless local loop).

002740-84084560

5 **Summary of Invention**

The present invention provides a system and methods for communication between subscribers' devices over cable infrastructure designed to carry video signals, using pass-band frequency bands, without transmission through a CATV headend device. A particular application of this system and method is home networking over coaxial TV cables. The disclosed system will allow very high-speed digital and analog communications within the home and from the home to external devices or networks using low cost devices.

The present invention provides home networking solutions that utilize in-home TV wiring for supplying high rate connectivity between any two home networking nodes. The present invention does not load the city cable TV (CATV) network.

15 In many, if not most, of US residential homes, there are several TV inlets, connected by coaxial (coax) cables to either a municipal CATV network or a TV antenna. This coax cable is an excellent communication medium, as it has a high bandwidth and it is shielded to avoid noise. The present invention provides a method and system which allows home networking over these coax cables, allowing for very high data rates and a low cost implementation. The term Home Cable Network (HomeCN) is used herein for the system of the present invention.

20 In the prior art (e.g. the DOCSIS 1.0 spec), a CATV infrastructure is utilized for communication between a subscribers' devices (e.g. cable modem) and a headend, thus, two subscribers' devices can communicate via the headend. The system and method of the present invention is based on direct communications between two subscribers' devices, without transferring the data via a headend, ^{allowing} ~~and~~ thus ^{allows} for high data rates between units in a home without reducing the capacity of the regional CATV network.

25 In the prior art, coaxial cables have been used for local area networks (LAN) and for analog communications. The system and method of the present invention is designed for cable networks that carry video, or other information, from a headend or an antenna, and thus it is different from prior art LAN over coaxial cables. Furthermore, the method employs a new digital modulation scheme based on pass-band RF signaling, which is fundamentally different than prior art LAN and analog modulation over coaxial cables.

5 The present invention enables installation of modems, connected to different types of nodes of the CATV, to enable communication between these nodes. The present invention provides a way to transfer data between these nodes, when the data is not required to be transferred to the headend.

2 The present invention provides a low cost solution, which is very ^{important} ~~importance~~ to enable a solution for the mass market.

10 A summary of some of the key principles of the disclosed system and methods are noted below.

1. Subscribers' devices may communicate directly (not via the headend) using RF signaling over the coax cable. These signals will typically propagate between the devices via reflections from other devices in the line, e.g. splitters or amplifiers in the line.
- 15 2. When the home coaxial cables are connected to a local or regional CATV network, the HomeCN is done in an out-of-band frequency (i.e. band that is not in use, e.g. above 860 MHz), or in part of the downstream band (e.g., within the range of 100-860 MHz) which is allocated (e.g. by the cable operator) for home networking applications.
- 20 3. When the home coaxial cables are connected to a local or regional CATV network, there is frequency re-use between portions of the CATV plants (i.e. same frequency range is allocated to different users in a CATV plant), taking into account the isolation between those users due to the attenuation of the cable plant.
4. The frequency re-use can be improved by adding filters within the signal path in the local or regional CATV network. The quality of the signal transmitted by one subscriber device to another subscriber device can be further improved by deliberately using splitters with high reflections.
- 25 5. The home devices may also be capable of connecting to the headend, e.g. operate as a DOCSIS or DVB cable modem or set-top box, either simultaneously with connecting to other devices in the home, or in an alternative mode in which a device ^{switches} ~~switches~~ between cable modem functionality and connecting to the other ⁱⁿ ~~in~~ home devices. Parts of the device that are capable of connecting to a headend can be used for both home networking and for cable modem functionality, thus reducing the implementation cost of the home networking functionality. An architecture is proposed in which the home network includes only one device, which can operate both as a cable modem and
- 30

- 5 as a home-networking device. In this architecture, all the other devices can communicate only over
the home network, and if one of these devices need to communicate outside the home, it ~~is~~
^{Communicates} ~~communicating~~ via the device with the cable modem functionality. Other devices that have home
networking and cable modem functionality may also handle a direct connection. The home
networking functionality will be implemented in cable modems, and particularly in host-based
10 cable modems, which are installed in personal computers and ^{use} ~~are using~~ the processor of the
personal computer to perform some of the functionality of the cable modem and the home cable
networking. More generally, the home networking devices will be installed in various kinds of
devices that employ general purpose computers (such as a laptop computer, a network computer, a
TV, a DVD device, or even certain cellular phones), and use their general purpose processors to
15 perform home networking functionality, thus reducing the implementation cost of the home
networking functionality.
6. In a particular implementation of the method, when the home coaxial cables are connected to a
local or regional CATV network, each home device addresses the headend, and the headend ~~is~~
^{assigns the} ~~assigning~~ carrier frequency, ^{and} ~~and~~ bandwidth to each home network, and maximum power levels to
20 each device on the home network. The specific power level is assigned by the home networking
devices that exist in each specific sub-network. In another implementation of the method, the
devices search for a non-occupied frequency sub-band within a band that is pre-assigned for home
networking, and once such a sub-band is found they use it for their needs. When a home CN
device is initialized it is trying to "join its home network", that is trying to communicate with
25 other devices in the same home and adopt their frequency band and protocol.
7. In a particular implementation of the method, the devices that share a home network are based on
the IEEE 802.11 MAC layer. This protocol is in common use and is a collision avoidance multiple
access protocol that supports priorities.
8. In a particular embodiment of the present invention, the splitter at the input to the user premises is
30 replaced by a special splitter device that supplies higher quality home networking ^{capabilities or} ~~capabilities~~ or a
filter is connected to the splitter. A passive filter connected to the splitter insures that the home
networking signals in a specific home will not interfere with or be interfered by other home
networks. This passive filter provides a "single home" operational mode that allows for low cost
equipment and frequency re-use. A home network splitter that supplies less isolation between the
35 home drops and includes the filter inside is also provided. This home network splitter provides

5 better performance for the home network. An active device receives signals from a TV antenna or
a regional CATV network and receives signals from subscribers' devices via the home coax lines,
and functions as a repeater for communications signals between subscribers' devices as well as
between subscribers' devices to a headend (in case the home is connected to a regional CATV
10 network), while still allowing transparent transition of video signals from the TV antenna or the
regional CATV network into the home.

9. In a particular embodiment of the present invention, the home coax network ^{connects} ~~is connecting~~ portions
of the home (e.g. rooms or floors), and its terminals have inputs and outputs for wireless
connections within these portions.

10. In a particular embodiment of the present invention, home CN devices have an interface to another
communication link, such as IEEE1394 link (I.LINK), thus the home coax network is used to
15 extend the range of the other link.

11. In a particular embodiment of the present invention, home CN devices have an interface to another
communication link, such as Bluetooth, thus the home coax network is used to extend the range of
Bluetooth coverage by supplying pico-cells that are connected between themselves and cover the
20 required home area.

12. In cases where direct communications between home devices is not feasible (e.g. due to ^a highly
balanced splitter that has very low reflections), the home devices may have a fallback option of
communicating via a regional CATV headend.

13. The data transmitted in the coax home network may be secured (i.e. encrypted).

25 As used herein, the term a "home network" means a local network; it does not necessarily have to
be in a home. For example, it may be in an office, or in a complex that contains several homes (e.g. an
apartment building).

5 Description of Drawings

The preferred embodiments of the invention as well as other features and advantages thereof will be best understood by reference to the detailed description which follows, read in conjunction with the accompanying drawings, wherein:

10 Figure 1 shows a home that has four nodes inside the home and is connected to a regional CATV plant;

Figure 2 shows an example of a preferred embodiment of the home network method and system connected to a regional CATV plant;

Figure 3 shows an example of the present invention, not connected to a CATV;

Figure 4 shows an example of HomeCN with a hub;

15 Figure 5 presents a frequency allocation that may be employed by the present invention;

Figure 6 shows an HFC infrastructure;

Figure 7 shows a network with a notch filter;

Figure 8 shows HCNM interfaces;

Figure 9 shows representative HCN data flows;

20 Figure 10 shows a power supply;

Figure 11 shows a dual frequency architecture;

Figure 12 shows dual frequency components;

Figure 13 shows layer 2 transport;

Figure 14 shows a Bluetooth home network;

25 Figure 15 shows neighborhood wiring;

5

Figure 16 shows building wiring;

Figure 17 and Figure 18 show home wirings;

Figure 19 and Figure 20 depict examples of an HCNM and HNEU.

~
Instal)

HCNW

HNEU

002740-2403450

5 Detailed Description

Figure 1 presents the structure of the existing regional CATV network.

The typical home coaxial cable infrastructure consists of a Cable Source [101] which is connected to the home Splitter [102] (the home splitter might be Customer Premises Equipment – CPE). Some wires connect the interfaces at home to the splitter. The components that can connect to the network are TV [103], VCR [104] that is connected to TV.

Cable Modems (CM) [105] (e.g. DOCSIS CM). Cable Telephone Device [106] that connects some phones via the cable infrastructure (e.g. using VoIP protocol over DOCSIS channel).

An amplifier [107] can be added in the entrance of the home / house to increase the signal power. (If CM equipment exists at home, this amplifier should be bi-directional amplifier, ^{that} amplifies the signal to home side (DS) in the 100MHz-860MHz frequency range, and amplifies the signal to the headend side (US) in the 5MHz-44MHz frequency range).

There are some major types of HomeCN components (see figure 2):

- **HCNI:** Home Cable Networking Interface.

A sub-component that supply Home Cable Networking interface. This sub-component is a part of specific equipment (e.g. PC, TV, DVD) [204,205].

- **HCNU:** Home Cable Networking Unit

A component that supply connection to the Home Cable Networking. This component is a separate unit that contains one or more interfaces to the home equipment (e.g. 10BaseT, USB, wireless). This component does bridging or routing between the HCN to the other interfaces (networks) [207,212].

- **HCNM:** Home Cable Networking Modem

A component that include HCN-U and ^{cable} modem (e.g. DOCSIS cable modem).

This component supplies a connection to the Home Cable Networking, and a connection to the cabal headend. This component is usually a separate unit that also contains one or more other interfaces (e.g.

5 10BaseT, USB, wireless). This component does routing between the HCN network , the cable network and the other interfaces networks [206].

Figure 2 shows an example of a preferred embodiment of the disclosed method and system.

2
10 Figure 2 shows a Home Cable networking (HomeCN/HCN) that has 5 nodes [204-207, 212] of the CATV network, and it is connected to the regional CATV plants via cable [201]. Notch filter [202], is a band reject filter that does not pass a certain RF range that is used by the home networking devices [204-207, 212]. This filter improves the isolation between the home network and other homes as well as the regional network. However, the use of such a filter is optional, as we believe that the disclosed system and method is functional with the isolation levels of the CATV network without the additional notch filtering [202]. RF splitter [203] splits the signal coming from and to the regional CATV plant [201], to the signals coming to and from units [204-207, 212] respectively. The signals arriving to RF splitter [203] from the home units [204-207, 212] are partially reflected back to these home units [204-207]. It may be recommended to use splitters that deliberately have high reflection levels (although we believe that the method and system can operate with typical commercial splitters). The Video Cassette Recorder (VCR) [204] and TV set [205] include Home Cable Networking Interface (HCNI) devices. The Personal Computer (PC) [208] is connected to a Home Networking Cable Modem (HNCM) device [206] ^{that} ~~that~~ supplies the Home Networking functionality and the Cable Modem functionality). The HCNM is also connected to a phone [215] and supplies the VoIP functionality. A PC that includes HCNI can be connected directly to the HCN. The HCNU + wireless units [207, 212] are connected to the CATV and has a wireless output (e.g. Bluetooth, HomeRF or infra-red) which connects to devices within the vicinity of the device [207], such as wireless telephone unit [209, 213], and a notebook computer [210]). The HCNU devices are capable of transmitting and receiving digital communications signals between them. These signals propagate in the CATV wires and are reflected by the RF splitter [203]. The HCNM device is further capable of operating as a DOCSIS cable modem and communicating with a headend of a regional CATV plant [201]. The HCNI's, the HCNU's and the HNCM ^{use} ~~are using~~ Home Cable Network Protocol HCNP.

2
25
30

2
The HomeCN can also be used to supply full home coverage by the Bluetooth network. To enable this coverage some HCNU + Bluetooth components that are connected to HomeCN should be exist in the home [207, 212]. The person that is ^{traveling} ~~travel~~ between the rooms with his wireless phone [209, 213] or with his notebook computer [210] can be connected to the appropriate Bluetooth station in the home.

5 We note that the method and system will still be capable to perform home networking if the home coaxial wiring is not connected to a regional CAT plant [201], but connected to TV antenna, or even disconnected. However, in such cases the home network will not allow the capability of connecting the home outside through the CATV, as done by the HCNM unit [206].

10 The HomeCN operation modes are determined according to the existence / not existence of notch filter at the home entrance (see figure 2 [202]).

The notch filter in the entrance of the home is a one of the basic element^s in the home network design. If this notch filter existsⁱⁿ the HomeCN is disconnected from the regional cable network, therefore it's design is more simple (single home network). When this filter not exists^{does} the home network is part of the regional network, therefore its design is more complicated, and some additional functionality is required.

15 The HomeCN supports two operation modes:

- **Single Home** operation mode – This mode required a Notch filter, or an amplifier that usually supplies similar functionality, or it can be operated in a system that ^{is} does not connected to the CATV plant.
- **Connected Home** operation mode – This mode does not require a Notch Filter. This mode is more complex and ^{requires} additional functionality. Following some ^{functionalities} functionality that are required in the **Connected Home** operation mode: Wider frequency operation, frequency selection (FDM), multiple bandwidth, privacy, capability to be managed by the headend.

Notes:

- The notch filter can be passive component or an active component. An active component that also has management can supply some additional functionality. ^{An example of an} Example to important functionality is ^{to} answer to the ^{query} query "Is notch filter exist". This ^{query} query can be used by the HCNP to verify the type of operating mode that should be handled if the components supply the two modes.
- Notch filter adding to the home network design usually reduces the price and increase the performance of the home networking.
- The default operation mode is **Single Home**. The management system configures the components to the appropriate mode after initialization.
- The **Connected Home** operational mode is recommended only if it is managed by the CMTS.

5 Figure 3 presents a Home Networking network that exist at a house that does not connected to the Regional Cable infrastructure. Instead, it is connected to a local antenna [301]. This system is operates in *Single Home* operational mode.

Figure 4 presents HomeCN with a local cable hub. A Local Cable HUB [401] connects the HCNUs and the HCNIs. This system is operates in *Single Home* operational mode.

10 Figure 5 presents a typical channel allocation. This figure is suitable for example to system that ^{supplies} supply TV channels, DOCSIS CM (US and DS), and HomeCN channels.

In the present figure, some of the HomeCN channels have a different width.

15 HomeCN components that are ^{working} work in the single home operation mode (reduced mode) ~~are~~ always ^{use} using the 900-906.25MHz channel. These components do not support the frequency selection capability, and different channel bandwidth capability.

20 There is an additional mode '*Dual Frequencies Mode*' ^{mode'. In this} in this mode there is a different frequency-range to the transmitted information and a different frequency-range to the received information. In this mode a transponder at the entrance of the home ^{transfers} that transfer all the signals that are sent in the transmitted frequency-range to the received frequency-range. The major benefit of this method is decreasing the influence of the in-home echo (For more details see *Dual Frequencies Mode* appendix).

Note:

- The HomeCN-P is defined by specifying the two lower communication layers: the physical layer and the data link layer.

25 The preferred frequency and the preferred frequency range (bandwidth) are selected according to the operational mode.

	<i>Connected Home</i> operation mode	<i>Single Home</i> operation mode
Frequency range	higher ^{than} 860 MHz; usually 900-960MHz	900-906MHz

RF channel spacing (bandwidth)	8 MHz or lower, according to the required rate	6.25 MHz
-----------------------------------	---	----------

- 5 The modulation method is QPSK, QAM 16, QAM 64 or QAM 256 according to the channel conditions, and according to the equipment capabilities.

The modulator of the home networking device **MUST** provide QPSK and QAM 16.

The modulator of the home networking device **MAY** provide QAM 64 and QAM 256.

The modulator **MUST** provide 2,560 ksym/sec.

- 10 The modulator **MAY** provide 160, 320, 640, 1,280, and 5,120 ksym/sec.

FEC (Forward Error Correction) **MUST** support R-S (Reed Salomon) T=0,10.

FEC (Forward Error Correction) **MAY** support R-S (Reed Salomon) T=0,...,10.

The Channel Allocation method is FDM - a specific frequency for each home network.

- 15 The frequency plan is done only in *connected home* operational mode. In this case it done by the management system.

The structure of the HFC is important for understanding the home networking when the system is in *Connected Home* operation mode. This structure is used for enabling frequency reuse.

The HFC system usually contains the following components (see figure 6):

- Headend (CMTS) [601] usually with fiber output.
- 20 • Fibers [602] that exist only in HFC (Hybrid Fiber Coax) environment and connect the Headend to the cabinets (Fiber Nodes) [603]. The cabinets include fiber to coax converters (O-E).
- *Coax wires that*
~~The coax wires that~~ connect the different components [604, 606, 607, 610, 611...].
- Amplifiers that increase the signal power, and also filter the frequencies that are not amplified [605, 608, 609]. (These amplifiers might include splitters)

- 5 • Splitters that get a single wire as input, and some wires as output. [605, 608, 609, 612, 613, 614, 619, 622].

The splitters are divided into two types: Active splitters that usually include the amplifier inside, and passive splitters, that usually only divide the power between the different ports.

10 The active splitters are usually used close to the CMTS (headend) side. The passive splitters are usually used in the house entrance and in the flats (near to the home end equipment).

The Attenuation and Isolation are used for two major subjects:

- Branches*
a *Branches* calculation - Dividing the HFC Network to *Branches*. The *branches* are the key for frequency reuse. *Branch* calculation should be done before frequency allocation for each HomeCN in the global HFC infrastructure.

- 15 • HomeCN home network – Understanding of the home network conditions.

These aspects are required for the HomeCN component and protocol design.

20 The HFC infrastructure is similar to a tree. This tree build with connection points that supplies isolation between the sub-trees. The components *that exist* in the network (e.g. Amplifiers, splitters, and filters) supplies attenuation of the signal, except the amplifier that supply amplifying (only if it was designed to amplify the required frequency in this direction). This attenuation is also can be used for isolation between the sub-trees.

The key element for efficient frequency allocation to the HomeCN is frequency reuse.

- branches are*
a To enable calculation of the frequency reuse in a different sub-trees, the term *branch* will be used. *branch* is defined as sub-networks that can use any home networking frequency without interference another sub-network that exist in another 'branch' and reuse the same home networking frequency.

a The cable network can be divided to 'branches' because the tree structure supplies attenuation between its branches. The attenuation is granted by the coaxial cables and by components that include filters. Some of the splitters also and provide good isolation between the sub networks that are connected to these components.

5 The HomeCN is based on FDM (see HomeCN protocol), therefore each home gets its own frequency range. The ability to supply reasonable frequency range for each home is based on the network infrastructure and on the ability to reuse the after dividing the network to ^{branches} ~~branches~~.

10 The size of the 'branches' can be reduced by adding filters. These filters enable increasing of the frequency reuse. These filters are usually passive filters that are relatively small and can be added easily by the cable operator, or by the user at the home entrance. This mechanism of adding low cost filters at the entrance of a home / flat enables a single home / flat branch; and enables the *Single Home* operation mode.

The frequency resources are limited. To increase the frequency resources one (or more) of the following methods can be used:

- Frequency Reuse: Enabling simultaneous usage of the same frequency by some customers.

15 The 'branches' method is a method to support the isolation of customers group. This method enables reusing of the same frequency in separate groups. This method uses the attenuation characteristic of the existing components. The disadvantage of this method is the management complexity. The operator should be aware ^{of} ~~to~~ its physical infrastructure attenuation characteristic.

- Supports wider frequency range.


20 This option can be handled by building equipment that supports a wider range. The disadvantage of this method is higher price of the components that are required to support wider ^{range, because wider} ~~range. Because, wider~~ range support increases the complexity of each component.

The 'branches' method is very cost effective, and it increase the robustness of the home networking solution. Therefore, this document includes a detailed definition of this method.

25 The 'branches' approach enables reuse of the same RF frequencies, ^{which} ~~which~~ allows the following benefits:

- It enable the manufactures to reduce the price of the home networking equipment, because home networking equipment can support a smaller range of frequencies.
- It enables allocating a larger frequency range for each home / flat. This wider range can supply higher network capacity.

30

	$r = 0.5 \text{ dB or } 19\text{dB}$ according to the design.
---	---

5

Data Form 1: Components parameters

Components' Parameters

Component	Parameter	Value[dB]				Comments
Wires	<i>dB/meter</i>	RG-59	RG-6	RG-7	RG-11	
		0.21				
		<i>N=2</i>	<i>N=4</i>	<i>N=8</i>		
Passive splitter	<i>Insertion Loss</i>	4.2	8.2	12.5		
	<i>Isolation</i>	22	25	30		20-30
	<i>Return Loss</i>	11	11	12		
Amplifiers	<i>Amplifying</i>					
	<i>Isolation</i>					
	<i>Return Loss</i>					
Transmitter						
Transputer						
Isolator						
Notch Filter	<i>Return Loss</i>	10				

Following some typical calculations based on figure 6 and table 1. These calculations are based on a system that does not include notch filter.

These calculations are based on a

Data Form 2: Typical loss between to apartments

002410-34034500

apartments				
Loss between two partments				
1	Loss between two modems in the same flat sharing the same splitter [from 615 to 616]:			
	Wires [meaters]	20	4.2	
	Splitter Isolation (n=4)[612]		25	
	Total [dB]		29.2	
2	Loss between two modems in neighbor homes [from 615 to 617]:			
	Wires [meaters]	44	9.24	10m[home 612]+2*12m[flat to basment]+10m[home 613]
	Insertion Lost (n=4)[612]		8.2	
	Splitter Isolation (n=8)[608]		30	Passive splitter
	Insertion Lost (n=4)[613]		8.2	
5	Total [dB]		55.64	

Note:

The loss between two modems that required to pass amplifier is more then 60dB, because the amplifier contains filter for these frequencies for the up stream direction.

10 The capability to calculate the attenuation between two different flats is important for enabling efficient frequency reuse. The cable operator should do the calculation of the “branches”. The calculation of the ‘branches’ can be done by the following methods:

- **Numerical Calculations** - Calculations that are based on preceding knowledge of the cable operator. The cable operator can do calculations that are based on its network structure and its network components.
- **Defining Basic Rules** – The operator can define some base rules that usually works, and divide the network to branches according to these rules. E.g. (of rules) a. each port that connects directly to a filter / amplifier unit specify a “branch”; b. Homes / flats that are connected using passive filters will be on the same “branch”.
- **Measurements using special equipment** - The cable operator can use spectrum measurement equipment. This equipment will usually be used to enable the cable operator to define the rules according to its own infrastructure.
- **Measurements using HCNM Branch Calculation Mode** - The cable operator can use a specific mode of the home networking equipment that enables ‘branch’ calculation.

- 5 Each HCNM should have a specific mode that enables the management system to calculate each 'branch' member.

This mode contains the following base features:

- Lock on a specific frequency, and on a specific frequency range.
- Transmit a signal in a specific power for a specific period (The pattern of this signal is known).
- 10 • Measure the power of the input signal (The pattern and the measurement period are known).

The algorithm is based on the structure of the cable infrastructure. A tree data structure is built in the computer memory. This data structure represents the existing infrastructure.

The tree is built according to the following rules:

- Tree nodes are the splitters (the splitters can be active or passive).
- 15 The splitter capability to isolate between two sub-trees is saved as data in these nodes.
- The leaves are the CM, HCNM or HNO.
- The identification of these nodes is saved in these leaves.

The main process is to build the topology database. This process can be done by the following methods:

- 20 • Load the tree structure from the cable operator database.
- This process is simple but it required an updated database.
- Automatic generation of the tree structure based on measurements of the isolations between two components using the *HCNM – Branch Calculation Mode*. These calculations are very complex and are based on prior assumptions.

- 25 Note:
- The base idea in automatic tree building is to calculate the isolation between two leaves. If the some leaves have similar isolation between themselves they can be connected to the same nodes. If there are two leaves with the same isolation, and an additional leave that has a higher isolation this leave connect to the previous two leaves using additional higher level node.

5 After building the topology database, it is required to verify that the nodes contain the isolation values. These values are usually loaded in the previous stage, but if this information was not entered, the system can use the *Branch Calculation Mode* to find the isolation of the nodes.

Note:

10 It is very hard to calculate these numbers when the tree is calculated automatically, and the splitter supplies different isolations between the wires that are connected to the same node.

This 'branch' specification is based on the data structure that was built.

'Branch' is specified by the isolation between this 'branch' to the other "branch". This isolation enable the systems in two different 'branch' to use the same frequency without (or with negligible) interference.

15 A 'branch' is defined by specifying a threshold of the minimal isolation between this 'branch' to the other 'branches'. When the isolation value in the tree nodes (or in summary of some layers that does not include leaves) is ^{greater} ~~greater~~ than the specified threshold all the nodes that are member in the specified sub-tree will be defined as nodes in a specific 'branch'.

Notes:

20 • When the system is not occupied as a balanced tree, the 'branch' calculation might be less ^{effective} ~~effective~~. In this case, it might be required to divide the frequency range to some sub-ranges, and define a 'branch' for each one of them. The algorithm for these calculations will not be specified in this document, because we do not think that the common network includes such complex structure.

• The operator can add filters or special splitters to reduce the ^{branches} ~~branches~~ size. ^{Simplifies}

25 To use the *Single Home* operation mode that ^{simplify} ~~simplify~~ the equipment, notch filter should be added. This filter can be added in the following points:

- Adding a filter at the flat / single user home entrance.

The advantage of this method is the ability of the end user to add the filter by himself.

- Replace the house basement splitter that split the signals between the flats to a special splitter.

30 The advantage of this method is the ability of the MSO to change a single splitter to a special splitter that includes internal filter. This splitter enables more ^{effective} ~~effective~~ usage of the home networking for some flats (homes).

The disadvantage of this method exists only if the HomeCN ^{uses} ~~use~~ the notch filter reflection. In this case

- 5 the attenuation and the delay of the coaxial wire between the flat to the central splitter. This influence is usually negligible.

than
then two points) dedicates the quality of the equipment that should be use for HomeCN.

There are some RF challenges in designing the HomeCN components:

- 10 • The “hidden nodes” problem:

This “hidden nodes” might exist when the isolation difference between two different nodes is different than the isolation between other two nodes. This problem is usually exists in a home that contains some splitters and a notch filter does not exist.

i.e. if there are some HCNU the attenuation between two of them might be low, and between each one of them to the 3rd might be high.

e.g. figure 7: the communication between 703 and 704 might be ‘hidden’ from 701 in particular when the notch filter [707] does not exist.

- High reflection:

The reflection from the notch filter is in the power of the signal or it might be higher. When this reflection is higher than the signal we can use this reflection as our main signal.

The following calculations are based on table 1 and figure 7. These calculations are only valid for homes that have notch filter.

Data Form 3: Home Networking Typical Calculations

Loss between two modems in the same flat

1 Connected to the same main filter HCNM1 [701] HCNU2 [702]:

Without Notch Filter

Wires [meters] 20 4.2
 Splitter Isolation [706] 25
Total [dB] 29.2

Echo from the notch filter

Wires [meters] 20 4.2
 Insertion Lost (n=4) [706] 8.2
 Return Loss [707] 10
 Insertion Lost (n=4) [706] 8.2
Total [dB] 30.6

2 Connected to the same minor filter HCNU3 [703] HCNU4 [704]:

Through the nearest splitter

Wires [meters] 8 1.68
 Splitter Isolation [705] 22
Total [dB] 23.68

Echo from the notch filter

Wires [meters] 20 4.2
 Insertion Lost (n=2) [705] 4.2
 Insertion Lost (n=4) [706] 8.2
 Return Loss [707] 10
 Insertion Lost (n=4) [706] 8.2
 Insertion Lost (n=2) [705] 4.2
Total [dB] 39

Echo from Main Splitter

Wires [meters] 20 4.2
 Insertion Lost (n=2) [705] 4.2
 Return Loss [706] 11
 Insertion Lost (n=2) [705] 4.2
Total [dB] 23.6

3 Connected to different filters HCNM1 [701] HCNU2 [704]:

Without Notch Filter

Wires [meters] 20 4.2
 Splitter Isolation [706] 25
 Insertion Lost (n=2) [705] 4.2
Total [dB] 33.4

Echo from the notch filter

Wires [meters] 20 4.2
 Insertion Lost (n=4) [706] 8.2
 Return Loss [707] 10
 Insertion Lost (n=4) [706] 8.2
 Insertion Lost (n=2) [705] 4.2
Total [dB] 34.8

5 Note:

The CSMA/CA can be used with or without ACK protocol. The need for immediate ACK should be verified according to the quality of the infrastructure.

The security is only required in Connected Home operational mode.

5 The security that is required in this protocol is the base on IEEE 802.11 or on line privacy plus.
The specification for line privacy plus protocol is presented in DOCSIS 1.1.

 The management of the security keys can be done by the CMTS.

Note:
10 Home networks that works in *connected home* operational mode and are not connected to the CMTS will
use a single key.

 The priority is integrated in Layer two MAC.

 A HCNM has at least two physical interfaces.

- HCNM interface to the cable side.

 This single physical interface contain two data channels (that use different frequencies):

15 1. ***Cable Modem Channel.***

 The cable modem channel (e.g. DOCSIS), containing two sub-channels: up stream channel (US)
and down stream (DS) channel.

2. ***Home Networking Channel.***

20 The Home Networking channel (a single channel that is used for sending and receiving
information).

- HCNM interface to the home side – ***Home Interface.***

 The home interface might be a single interface or it might contain some interfaces. This / these
interface(s) are connected to the equipment at home. This / these interface(s) can be Ethernet
(10/100/1G BaseT) (or some Ethernet ports), USB, Phone connection, Bluetooth, wireless, or other.

25 Notes:

- The HCNU and the HCNI components do not contain the Cable Modem Channel. Except HCNI that
designed as host-based, i.e. a card that inserted into the PC and connected to the PCI bus, in this
special case it might implement the HCNM functionality.
- The HCNM gets the information from these channels/interfaces simultaneously.

- 5 The HCNM bridges messages between the home interface to these cable channels and vice versa. In addition it might support the capability to bridge information between cable modem channel to the home-networking channel and vice versa (This capability is only required when HNO components exists).

The following table describes the bridging requirements for HCNM:

Bridging Type	Description
Cable Modem Channel - Home Interface	According to cable modem standard's specifications.
Home Networking Channel -Home Interface	Bridge the messages between the stations at the home networking and the stations that are connected to the HCNM home interface(s).
Cable Modem Channel - Home Networking Channel	Bridge the messages between the Cable Modem Channel and Home Networking Channel in the following conditions: - This component was configured to do Cable Modem channel – Home Networking channel bridging; and - The message should be transferred between Cable Modem Headend system and HNO component.

- 10 Figure 9 presents some ^{examples} ~~example~~ of data flow.

Ex.1 and Ex.2: Message from the Cable headend to component no. 1 or component ^{no} ~~on~~ 2; and the returned response. These examples ~~are~~ present a standard cable modem protocol.

Ex.3 and Ex.4: Message from the one component in the home network to another component in the home-network (1 to 3; 3 to 4) and response. The messages ^{from} ~~from~~ the home equipment is transferred to the splitter, the splitter distributes the energy to the Cable In connector, and to the other output connectors that are connected to the splitter. The destination-component gets the message and returns the response.

Ex.5: Message from the Cable headend to component 3 through component 1 (that was specified as the front router of the components that exist only in the home networking). The message is arrived to HNCM no. 1, it identifies the destination and its duty as router, and it ^{routes} ~~route~~ the messages to HCNU no. 3. The response is transferred in the opposite way. (Note: if HNCM no.1 fails, HNCM no.2 can be configured to take its duty automatically).

5 The purpose of the home networking system is to transport Internet Protocol (IP) traffic through the HomeCN system.

The Network Layer protocol is the IP [RFC-791].

The home networking management can be done by two methods:

- Local management that is done at home.
10 This method is always used in the Single Home operation mode.
 This option can be done when the house is not connected to the cable infrastructure, or when the house has isolation (for the home networking frequency) from the cable network and the headend does not support the home networking management capability.
 Local management might not include all the capabilities that the central management supports.

- 15 • Central Management
 Management from the headend that is done by the cable operator.
 This option is the preferred method for *connected home* operational mode. This method used the standard cable modem interface (e.g. DOCSIS interface). The configurations of the HCNU and HCNI can be done by the headend via HCNM routing capabilities.

20 There are some options for power supply to the HomeCN units. Most of the HomeCN components will use local power supply. The special unit is a HomeCN component that its only interface is wireless (i.e. Bluetooth). For this type of unit, that ^{requires} ~~required~~ very low power consumption, a central home power supply can be added. The central power supply is a special HomeCN splitter that contains inside the following sub units: Notch filter, a passive splitter, and a power supply that enable units to gets its power
25 from the home cable infrastructure (see figure 10).

~ The present invention provides home networking solutions that utilize the in-home TV wiring, supplying high rate connectivity between any two home networking nodes. The presented solution does not load the city cable TV (CATV) network.

~ The present invention enables installation of modems, connected to different types of nodes of the
30 CATV, to enable communication between these nodes.

~ The present invention presents ^a ~~a~~ solution of transferring the data between these nodes, when the data is not required to be transferred to the headend.

5

important to enable a solution

10

15

SECRET

- **Internet Sharing**

20

25

30

TI-30882

5 • **File and Application Sharing**

Multiple users can easily share applications, move files, or back up data, saving time and money. Automatic software updates are enabled by a network connection.

Other applications enabled by home networking:

• **Entertainment**

10 Easy-to-use home networks will also enable popular multi-player network games, either within the home or over the Internet.

• **Home Automation**

A ubiquitous, easy-to-install home network will also foster home automation applications, such as environmental control and security systems.

15 • **Voice and Video over IP**

New digital voice and video services are being introduced into the home. All these digital services—whether data, voice, or video—need to be accessible anywhere in the home by any device. All digital devices, including PCs, digital televisions, and digital telephones, will require a high-speed connection to the home network.

20 Today, it is estimated that over 15 million of the 100 million homes in the United States have two or more PCs, and 60% of new consumer PC purchases are by families that already have at least one computer. This number is expected to double by the year 2000.

25 Chief among these is the fact that the widely adopted and supported enterprise networking technologies require a technically skilled individual capable of designing and maintaining complex network architecture. Enterprise networks also require the use of high-grade wiring typically not found in most homes.

Also, few home users are willing to master the art of installing and maintaining an Ethernet repeater, learn even the basics about network protocols, or drill holes through their walls to run new network-capable wiring throughout their home.

5 Success in the consumer market requires that a home networking technology be inexpensive, easy to install, and easy to use. To be truly effective and embraced by consumers, a home networking solution must meet these criteria:

1. No new wiring.

10 Most existing homes are not wired for traditional networking equipment. Rewiring the home is too expensive and a hassle for most consumers.

2. Simple to install and use.

3. Must be low cost to allow the mass market to enjoy the benefits of home networking.

4. The range must be adequate to operate within a typical home.

5. Support high data rate.

- 15 6. The networking capability must grow with user applications without obsoleting existing devices.

7. The network must be secure.

The network data must remain private; it must not be accessible to neighbors or anyone outside the home.

8. The solution must not interfere with other systems, appliances and services.

20 Requirements:

1. The home networking equipment coexists with the other services on the cable network. In particular,

It is spectrally aligned with any combination of television and other signals in the cables; and

It does not cause harmful interference to any other services that are assigned to the cable network in spectrum outside of that allocated to the home networking. Therefore,

- 25
 - The solution should not interfere with the TV/video channels.
 - The solution should not interfere with any cable modem channels.
2. Comply with the general home networking requirements.

002140-3403750

2

- 5 3. Verify that the technology does not limit the number of cable modems or the number of home networking modems. Due to using ^{HFCM} technology, each home will include more than a single CM. It is required that the cable headend will support the increased amount of CM's. For example DOCSIS protocol can support high quantity of CM's (up to 8,000 CM's for a MAC chip) in particular DOCSIS1.1.
- 10 4. The Home Networking (HN) is required to supply a scaleable bandwidth range (100Kb-10Mb and more).
5. The number of nodes that are connected to the home network should not be limited by the presented solution. The only limitation should be the identification method in layer two (e.g. the limitation of using MAC address).
- 15 6. The connection method and the connection rate from home to the Internet using any technology (e.g. xDSL, cable modem) should not be influenced by the home networking technology. The only difference may be the ability to use this Internet connection for central management. For example, the Ethernet protocol, as a home networking protocol, complies with this requirement. It does not create any limitations to the protocol that is used for connecting the home to the Internet. The
- 20 HomePNA is a home networking protocol that adds limitations and does not comply with this requirement. HomePNA enables the G.Lite protocol to be used for connecting the home to the Internet, but it does not enable the use of ADSL (10Mbps) or VDSL protocols because it uses the same medium (phone line) and the same frequencies.
- 25 7. The ability to create a component that supplies the functionality of home networking and the functionality of connection to the Internet.

Nice to have:

1. The ability to create a component that supplies the functionality of home networking and does not supply the functionality of connection to the Internet.
2. Home Networking might be able to operate without connection to the headend.
- 30 3. An important point is to define this protocol to use limited "cable" resources. It should not use the limited US (up stream) frequencies. It can use some of the DS (down stream) frequencies or higher frequencies (even if their distance is limited).

5 There are some advantages in using this solution:

- No new wiring is required. Usually there are some ports of the TV cable in each home.
- The capacity of data that can be transferred using this infrastructure is very high.
- There is no radiation. Wire radiation is very low, in particular Coax wires radiation is negligible. (Compared to wireless solutions this point is very important).

10 • Simple to installed and to use.

- It can be low cost to allow the mass market to enjoy the benefits of home networking.

- Supply high data rate.

- It enables a secured network. The network data can remain private; the information can not be accessible to neighbors or anyone outside the home.

15 • The range limitation is negligible compared to the typical home.

- The networking capability grows with user applications without making the existing devices obsolete.

- Total isolation from the home network to the cable infrastructure (filters) can be added, although it is not required.


20 • It uses the same infrastructure that is used today by the current entertainment equipment (e.g. TV, Video). Therefore, the cabling probably exists. Supporting this protocol only requires minor changes in the equipment.

The advantages of using the cable infrastructure:

- No new wiring is required. Usually there are some ports of the TV cable in each home. These ports are usually located in the appropriate location, because one of the major aspects of home networking is to connect your TV environment (that already has some interfaces to the cable infrastructure) to the computer environment (that already has an interface for the current cable modem).

- 5
- The capacity of data that can be transferred using this infrastructure is very high (Order of Gbps).
 - There is no radiation. Wire radiation is very low, in particular Coax wire radiation is negligible. Compared to wireless solutions this point is of great importance.
- The coax cables are also not sensitive to external radiation.

10 The two-frequency mode ^{exists} is ~~existing~~ to eliminate the echo problem that exists in some of the homes in the single frequency mode. The method is transmitting the information in a specific frequency range (e.g. 900-906 MHz) and receiving the information in a different frequency range (e.g. 910-916 MHz). The architecture of this solution appears in the following figure.



15 In the single frequency mode the information that is transferred from HCNU-2 to HCNU-3 is transferred through Splitter-1 and in addition and echo from Splitter-main also received.

In the Dual Frequencies Mode the Transponder module is required to be added in the entrance to the home. The signal from HCNU-2 is transferred to the transponder module. The transponder module changes the signal frequency from the US frequency to the DS frequency and transmits it to the home. The HCNU-3 received this signal with no echo.

20 The transponder is a simple one that translates the input frequency to another, whether if it is with an up and down conversion or other technique such as conversion to baseband and back.

The HCNU can support the two modes, and according to the configuration the operation mode will be specified. The configuration can be done manually or automatically by verifying ^{if} ~~is~~ the transponder ^{exists} ~~exists~~ (by sending a signal in the US channel and verifying if the signal arrived in the DS channel).

2 5 Therefore this module can be inserted in houses ^{where} ~~were~~ there is a problem with reflection.

There are some additional benefits in the two-frequency mode:

- The transmission path has low insertion loss and negligible reflections.
- The transponder module can be inserted with the notch filter and with an amplifier.

2 ~~The HN module and transponder modules are.~~

10 Note:

The transponder can be powered down (even remote) and the system returns to the initial model, this ability may be very important to the cable operator.

This section describes other applications that can be operated using the same physical layer.

15 ^{transporting} ~~Transporting~~ These applications are a group of applications that can be built on the same infrastructure. These applications are based on home networking layer one that is described in this document, and used the specific application layer two.

The HomeCN-P is a protocol that includes layer one and two. There are two options to transfer different layer two over this infrastructure:

- 20
- To transfer different layers two using the same layer one.
This method is used in the presented application.
 - To transfer different layers two over the layer two of the HomeCN-P.
This method is not used in this presented solution because the capacity and the delay are not good enough for the presented applications.

25 Following some examples of layer two protocol that can be used:

- USB
- IEEE 1394 (fire-wire)
- Ethernet (10BaseT, 100BaseT)

- 5 • Wireless

This system enables high rate connection between two points at home.

The system contains two Home Networking Bridges (HNB) that are connected through the home cable wiring, each one of them has the same layer two interface e.g. IEEE 1394.

The system structure is presented in the following:

- 10 This structure enables information sending in very high rates (e.g. 40Mbps) for each direction.

Note:

This system does not required burst modulator / demodulator. It can use a “standard” one.

- 15 The Bluetooth technology is design to supply connectivity of components that are located in the same area. The distance between the components should be less ^{than} 10 meters (This range probably does not include wall interference). When you build your home network, and your home is larger then a small flat. You need to connect component when the distance between them is larger then 10 meters.

The idea is to build a network at home that connects the Bluetooth sub-networks.

Advantages

- 20 • The benefits of the Bluetooth connectivity can be used.
- You can cover much larger range.
- The location of the cable infrastructure port in the room is going to be less important because all the room is “covered” (connected) by the network using Bluetooth connectivity.
- The Bluetooth CM can be very simple, and cost effective.

Disadvantages

- 25 • Adding Home Networking protocol that connects all the sub-networks of Bluetooth is required.
- You have two types of networks at your home.

a

- 5
- The rate of Bluetooth is less than 1Mbps. If a higher capacity is required, an additional connector type should be added (HomeCN-P capacity is 10-50Mbps). This additional type might make your network more complex, and will required an appropriate network management.

Notes:

- 10
- Figure ¹³ ~~7~~ present an example of ^a network.
- 15
- The HNO-Bluetooth can be a very simple component if the network is required to have at least one component of HCNM + Bluetooth that has the capability to manage the simple HNO-Bluetooth components.
 - The management of the Bluetooth sub-networks and the ability to transfer the connection of a network element from one Bluetooth sub-network to another required a specific layer two Bluetooth roaming-in protocol.
- 20
- Adding Power-supply capabilities to the home amplifier enable very simple Bluetooth-CM component. Bluetooth-CM component is required to include the following: Tuner, CM-chip, Bluetooth-chip, and very small CPU (only is the CM-chip and the Bluetooth-chip does not contain CPU). The installation procedure is going to be very simple, Just plug it to the cable interface, no other wire are required. The BOM of this component is going to be very low.
 - When the system is working in a single home operational mode and a notch filter exist, all the management is done local and the requirements from this management system are reduced.
 - When the system is working in a *Connected Home* operation mode, and the system contain a CM channel, the management is done from the headend. This management is much more complex.
- 25
- The following table presents the management functionality:

Table NNN: Management Functionality

Functionality	Description	Operation Mode (ALL or Only - <i>Connected Home</i>)
HCN units identification	Identify all the units that are sharing the same HCN	All

002110-31031560

5

Ranging	Ranging between each two modems	All
Headend management	Enabling management from the headend.	Only - <i>Connected Home</i>
Frequency Selection And frequency plan	Select the required frequency for HCN and the required frequency range	Only - <i>Connected Home</i>
Security	Management of the BLP (Base Line Privacy) keys	Only - <i>Connected Home</i>
Support ^{branch} Calculation Mode ^{Branch}	Support the ability to measure the signal amplitude according to the command of the headend	Only - <i>Connected Home</i>

a

- 5 The following section describes the frequency planning mechanism.

The configuration for the specific frequency will be ^{done}~~done~~ by the management system. The calculation is based on the 'branch' calculation, because the process of frequency allocation is done separately in each "branch".

- 10 The following are base rules that are used in the calculation of each *home-network frequency-range*.

- The *home-network frequency-range* is specified by the required home-networking bandwidth. The required bandwidth is specified for each home-network separately.

E.g. the required *home-network frequency-range* to transfer 40Mbps is 6MHz.

- The *total frequency-range* is specified by the capability of the home networking equipment.

- 15 E.g. the *total frequency-range* can be 40MHz.

- The *total frequency-range* should be larger ^{than}~~than~~ the summaries of the *home-networks frequency-range* of all the home-networks that ~~are~~ exist in each "branch".

If this condition is not met, the cable operator can decrease the bandwidth of its customers, or divide the network into smaller "branches".

- 20 E.g. If a 'branch' contains 16 flats and each one of them asks for the higher bandwidth and the *total frequency-range* is 40MHz, each one of the flats can get $40\text{MHz}/16 = 2.5\text{MHz}$ *home-networks frequency-range*. The operator can also divide the *total frequency-range* in other method, 4 flats will get 5MHz each, and the other 12 flats will get 1.6MHz each.

There are some frequency-ranges that might be used.

- 25 The preferred frequency range is higher ^{than}~~than~~ 860 MHz.

Note:

There are some existing chips (low price) that supply two-direction filtering and tuner functionality for the specific 900-1000 MHz frequency-range (Note: These chips were designed for the cellular market).

The following table presents the comparison between these frequency-ranges.

Frequencies Range	Pros	Cons
-------------------	------	------

Frequencies Range	Pros	Cons
< 5 MHz	☐ Not used by DOCSIS and by the TV. ☐ Tuners are not required. • Low attenuation of the Coax Cable enables low power.	☐ The capacity is very low. ☐ The quality of this frequency-range is low. ☐ The cable network contains amplifiers for part of this frequency-range. These amplifiers are designed to amplify in the US direction; therefore the segmentations to 'branch' are limited. • Low attenuation of the Coax Cable increases the 'branch' size.
5-42 MHz	☐ Tuners are not required. • Low attenuation of the Coax Cable enables low power.	☐ The DOCSIS channels use this frequency-range. ☐ The frequency-range resource is very limited. ☐ The cable network contains amplifiers for this frequency-range. These amplifiers are designed to amplify in the US direction; therefore the amplifier may be saturated. • Low attenuation of the Coax Cable increases the 'branch' size.
42-88 MHz	☐ Not used by DOCSIS and by the TV, these rates are the gap between DOCSIS US channels to TV channels and DOCSIS DS channels.	☐ This range is not free all over the world. For example, in the DEVIC standard this range is reduced. ☐ The cable network contains amplifiers for part of this frequency-range. These amplifiers are designed to amplify in the US direction; therefore the amplifier may be saturated.
88-860 MHz	☐ The standard tuner can be used. ☐ The capacity is not limited. ☐ There is good isolation between different home segments; therefore, 'branch' separation can	☐ The TV channels and the DOCSIS channels use this frequency-range; therefore the cable companies probably prefer to use this resource for the TV channels and DOCSIS channels.

Frequencies Range	Pros	Cons
	be used.	
> 860 MHz	☐ Not used by DOCSIS channels and by the TV channels. ☐ There is a good isolation between different home segments, due to the non -matched impedance (Z_0). ☐ There are some existing chips (low price) that supply two-direction filtering and tuner functionality.	• The attenuation is high; therefore there are some distances limitations in very high frequencies. (Note: The distance limitation is not relevant to home networking). • There are some FCC limitations. These limitation probably not relevant for coaxial wires

5 Modulation Method

Various types of modulation can be used.

The modulation method should comply with the following requirements:

- Can be used in the required frequency range.
- Should support high bandwidth rate (more then 10Mbps).
- 10 • Should support bursts with short learning time.

The selected modulations that comply with these requirements are QPSK and QAM.

The Channel Allocation method should be FDM - a specific frequency for each home network. This chapter describes the Design Considerations.

- There are some alternatives for channel allocation. The mechanism of channel allocation should answer the problem that a sub-network ("branch") usually contains some home networks. The number of home networks that should use the same frequency range can be changed according to the physical layer condition i.e. according to the 'branch' size.
- 15

5

There are some known methods to allocate channels for each home-network. The following table compares between them. This table does not present methods that are a combination of two base methods, because these combinations are not required (e.g. combination of FDM and TDM) in our simple problem:

Method	Pros	Cons
FDM - Frequency Domain Multiplexing	☐ Simple ☐ The frequency range can be updated according to the number of home-networks that share the same frequency, and according to the required bandwidth. ☐ Can use wide spectrum for the whole solution, when each home is required to use narrow range (less then 6 MHz). ☐ Very efficient, in particular when the number of home-networks in a specific "branch" is low. ☐ Does not require synchronization and does not require CMTS for synchronization.	☐ Not efficient in case of many home-networks on the same "branch". According to our estimations, this case is probably rare. • CBR based; therefore it is not affective when the traffic is not CBR type.
FDM with frequency hopping	• Does not require any configuration. I.e. not required configuration of the frequency that each home should use. • Very efficient when the traffic is ABR type.	• More complex then FDM. • Hard to be managed by the Cable Operator. • It is not efficient when the traffic is CBR type (e.g. digital movie playing on the DVD in the living room, when the TV is in the bad room). • It has only disadvantage when the home is the only home on the "branch".
TDM - Time Domain Multiplexing	• The bandwidth allocation can be dynamic – according to the needs.	☐ Requires synchronization, therefore, it require CMTS for synchronization. ☐ Can not use the wide spectrum (more then 10 MHz) in each channel group.

222740-34034560

Method	Pros	Cons
		□ Making Home Cable Networking Unit (HCNU) equipment is very complex, because this equipment is required to get the sync from the cable modem network. • It ^{is} ~~his~~ similar to FDM, but more complex, when the home is the only home on the ^{branch} ~~branch~~.
CDM – Code Domain Multiplexing	• The supplied bandwidth (data rate) can be dynamic – according to the needs.	□ Very complex • Requires synchronization, therefore, it requires [~] ~~CMTS~~ CMTS for synchronization. □ Making Home Cable Networking Unit (HCNU) equipment is very complex, because this equipment is required to get the sync from the cable modem network. • Can not use wide spectrum (more ^{than} ~~then~~ 10 MHz) in each channels group. □ The performances are low unless you are using complex equipment that supports wide spectrum sampling. • It ^{is} ~~his~~ similar to FDM, but more complex, when the home is the only home on the ^{branch} ~~branch~~.

5

The data link protocol should be the IEEE 802.11 MAC layer CSMA/CA.

Note:

The CSMA/CA can be used with or without ACK protocol. The need for immediate ACK should be verified according to the quality of the infrastructure.

10 Following the design considerations:

There are some options to define the layer two (data link) protocol.

5 The major aspects that should be considered are:

- The number of stations that use the home networking is variable (usually 2-15).
- Station can be added to the network or removed from the network during the home network operation.
- Collision prevention is required, because collision detection in the QAM technology is complex.
- It is preferable that all the components will be similar, so that the home network will not require a special head component.

10

This method usually increases the robustness of the network, and does not require special addition of equipment.

- A standard protocol or protocol that is close to a standard protocol is preferred.

There are some protocols that comply with these requirements, following two examples:

- 15
- The 802.11 MAC layer CSMA/CA.

This protocol is used today by many vendors, usually, in the wireless LAN equipment. Consider the fact that Bluetooth interface might be required to ~~be~~ exist on the HCNM / HCNU / HCNI components, it would be much simpler to support a single MAC protocol. This protocol also supports priority.

- 20
- The Token Bus 802.4.

This protocol is not common, and it is very complex. Building a reduced version of this protocol can simplify the protocol, but it will not be a standard protocol.

The system security is done in layer two. This security can be based on to the following standards:

- The DOCSIS standard.
- 25
- IEEE 802.11 standard.

The preferred option is according to DOCSIS standard because:

- The CMTS headend already ^{manages} ~~manage~~ this security.

- 5 • The standard CM already contains these cores.

Priority should be defined for the two channels separately.

The priority for the cable modem channel:

The need for priority for this channel was investigated. Cable modem protocols such as DOCSIS include this capability for services that require this capability e.g. VoIP.

10 Example:

- The priority mechanism for the DOCSIS standard is well defined in DOCSIS 1.1.

The priority for the Home Networking channel:

The priority for this channel is divided into two aspects:

- 15 • Priority is required in the home-networking channel for applications that are required to be connected to the standard cable modem channel; but they are using the home networking as transport media. The solution for these applications is to use HCNM and not HCNU / HCNI, and to use the cable modem channel directly.

- 20 • Priority is required in the home-networking channel for applications at home. E.g. CBR priority for transferring a video from the DVD reader to the digital TV on another floor, high priority for games, low priority for backup.

The priority requirements for these applications probably will be added soon. But the basic requirements of the home networking does not require priority capabilities, and the data rate of the home networking is high therefore "best effort" is good enough.

25 According to the presented analyses, specifying the priority for the home networking can be handled in the 2nd phase.

The following table compares between the different home networking solutions.

Subject	HomePNA	HomeCN
No new wiring	Use the existing phone interfaces Small advantage for the number of phone jacks	Use the existing TV cable interfaces Advantage in the location for usage of home networking to entertainment (e.g. ~)

Subject	HomePNA	HomeCN
		TV, VCR, DVD)
Installation	Simple to ~~be~~ install and use. Does not required any change in the home wiring.	Simple to be install and use. Usually, does not required any change in the home wiring. In some of the cases it required adding a component in the ~~entrance~~ entrance of the home.
Notch filter adding	Might be required - ^{depends} depend on the VDSL / HomePNA coexistence.	May be require for low cost equipment, or to enable higher bandwidth.
Low cost	The host-based product price is \$79 for 1Mbps (Intel).	The solution can be in similar prices.
Range	Adequate to a typical home.	
User privacy	Does not required. The neighbor can use the cross talk for ~~eavesdropping~~ eavesdropping (intelligence).	Required, only, when the ^{notch} notch filter (or flat amplifier) not exist, and you are afraid from ~~eavesdropping~~ eavesdropping (intelligence) from neighbors that are connected to the same building splitter.
Interferes	Interferes with VDSL	No interferes
Available capacity	HomePNA 1 - 1Mbps HomePNA 2 - 10Mbps (This capacity is ^{very difficult to achieve} very difficult to achieve because the home phone ~~wiring~~ wiring is in very low quality.	Single Home low cost version - 20Mbps Higher version can support very high capacity because the coaxial network has very high quality.
Integrated into	DSL (G.Lite), Cable Modems?	Uaually - Cable Modems, Bluetooth

5

Following some typical Street / Building wiring

The following describes HCNM.

The 1st chip is designed to be designed in "system on a chip" architecture. The base chip should supports the Single Home operation mode to reduce the price. In addition it ^{requires} requires supplying a Bluetooth interface.

5 **What is Claimed is:**

1. A communication system, comprising:
- a plurality of information processing devices capable of interconnection to exchange information;
- a transmission medium including at least one coaxial wire, capable of carrying TV signals;
- 10 and
- at least one communication device, connected to the transmission medium, operative to interconnect the information processing devices.
2. The communication system of claim 1, wherein said devices form a home network.
3. The communication system of claim 2, wherein the network employs a specific frequency
- 15 range that is not used by other signals transferred over the transmission medium.
4. The communication system of claim 2, wherein the network uses a frequency range above 550 MHz.
5. The communication system of claim 4 wherein the frequency range is reusable in different networks.
- 20 6. The communication system of claims 2, wherein said network uses QPSK or QAM modulation.
7. The communication system of claim 2, wherein said network uses channel allocation according to FDM method.
8. The communication system of to claim 5, wherein each home network has its own data rate.
- 25 9. The communication system of claim 5, wherein each home network uses its own frequency range.
10. The communication system of claim 2, wherein the network uses bridge or routing protocols selected from the group of IEEE 1394, USB, and/or Ethernet protocols.

002140-84034560

002140 37037500

- 5 11. The communication system of claim 10, wherein the bridge function employs a single channel for the two directions or a specific channel for each direction.
12. The communication system of claim 1, wherein a received signal is a reflection of the transmitted signal from either a passive element or an active element.
13. The communication system according to claim 12, wherein the element is a passive splitter.
- 10 14. The communication system according to claim 12, wherein the element is a notch filter.
15. The communication system according to claim 12, wherein the element is a transponder which converts the signals in an input band to signals in another output band.

Add
a1

Add
B12

5 **Abstract:**

The present invention provides the ability to use existing cable TV wires for home networking.

00240-84034560



AUG

3

ATTORNEY'S DOCKET NO.


TI-30882

PAGE 1 OF 1

APPLICATION FOR UNITED STATES PATENT DECLARATION AND POWER OF ATTORNEY

As a below named inventor, I declare that my residence, post office address and citizenship are as stated below next to my name; that I verily believe that I am the original, first and sole inventor if only one name is listed below, or an original, first and joint inventor if plural inventors are named below, of the subject matter which is claimed and for which a patent is sought on the invention entitled as set forth below, which is described in the attached specification of **Application Serial No. 09/548,048, filed 04/12/00**; that I have reviewed and understand the contents of the specification, including the claims, as amended by any amendment specifically referred to in the oath or declaration; that no application for patent or inventor's certificate on this invention has been filed by me or my legal representatives or assigns in any country foreign to the United States of America; and that I acknowledge my duty to disclose information which is material to the patentability of this application in accordance with Title 37, Code of Federal Regulations, Section 1.56;

I further declare that all statements made herein of my own knowledge are true and that all statements made on information and belief are believed to be true, and further that these statements were made with the knowledge that willful false statements and the like so made are punishable by fine or imprisonment, or both, under section 1001 of Title 18 of the United States Code, and that such willful false statements may jeopardize the validity of the application or any patent issuing thereon.

TITLE OF INVENTION:		
System and Methods for Home Network Communications		
POWER OF ATTORNEY: I HEREBY APPOINT PRACTITIONERS AT CUSTOMER NUMBER 23494 TO PROSECUTE THIS APPLICATION AND TRANSACT ALL BUSINESS IN THE PATENT AND TRADEMARK OFFICE CONNECTED THEREWITH		
SEND CORRESPONDENCE TO: J. Dennis Moore Texas Instruments Incorporated P.O. Box 655474, MS 3999 Dallas, TX 75265		DIRECT TELEPHONE CALLS TO: J. Dennis Moore (972) 917-5646
NAME OF INVENTOR: (1) Mati Amit	NAME OF INVENTOR: (2) N/A	NAME OF INVENTOR: (3) N/A
RESIDENCE & POST OFFICE ADDRESS: 23 Nof Harim St. Zur-Yigal, Israel	RESIDENCE & POST OFFICE ADDRESS:	RESIDENCE & POST OFFICE ADDRESS:
COUNTRY OF CITIZENSHIP: Israel	COUNTRY OF CITIZENSHIP:	COUNTRY OF CITIZENSHIP:
SIGNATURE OF INVENTOR: x 	SIGNATURE OF INVENTOR:	SIGNATURE OF INVENTOR:
DATE: x 1 Aug 2000	DATE:	DATE:



UNITED STATES PATENT AND TRADEMARK OFFICE

COMMISSIONER FOR PATENTS
UNITED STATES PATENT AND TRADEMARK OFFICE
WASHINGTON, D.C. 20231
www.uspto.gov



Bib Data Sheet

SERIAL NUMBER 09/548,048	FILING DATE 04/12/2000 RULE -	CLASS 709	GROUP ART UNIT 2756	ATTORNEY DOCKET NO. TI-30882	
APPLICANTS Mati Amit, Zur-Yigal, ISRAEL; ** CONTINUING DATA ***** THIS APPLN CLAIMS BENEFIT OF 60/128,810 04/12/1999 ** FOREIGN APPLICATIONS *****					
IF REQUIRED, FOREIGN FILING LICENSE GRANTED ** 06/19/2000 -					
Foreign Priority claimed ☐ yes ☐ no 35 USC 119 (a-d) conditions ☐ yes ☐ no ☐ Met after met Allowance Verified and Acknowledged <u>Examiner's Signature</u> <u>Initials</u>		STATE OR COUNTRY ISRAEL	SHEETS DRAWING 10	TOTAL CLAIMS 15	INDEPENDENT CLAIMS 1
ADDRESS Texas Instruments Incorporated P O Box 655474 MS 3999 Dallas ,TX 75265					
TITLE System and methods for home network communications					
FILING FEE RECEIVED 820	FEES: Authority has been given in Paper No. _____ to charge/credit DEPOSIT ACCOUNT No. _____ for following:		☐ All Fees ☐ 1.16 Fees (Filing) ☐ 1.17 Fees (Processing Ext. of time) ☐ 1.18 Fees (Issue) ☐ Other _____ ☐ Credit		

PATENT APPLICATION FEE DETERMINATION RECORD
Effective December 29, 1999

Application or Docket Number

09/548048

CLAIMS AS FILED - PART I

(Column 1) (Column 2)

FOR	NUMBER FILED	NUMBER EXTRA
BASIC FEE		
TOTAL CLAIMS	15 minus 20 = *	
INDEPENDENT CLAIMS	1 minus 3 = *	
MULTIPLE DEPENDENT CLAIM PRESENT		

* If the difference in column 1 is less than zero, enter "0" in column 2

CLAIMS AS AMENDED - PART II

(Column 1) (Column 2) (Column 3)

AMENDMENT A	CLAIMS REMAINING AFTER AMENDMENT	HIGHEST NUMBER PREVIOUSLY PAID FOR	PRESENT EXTRA
Total	*	Minus **	=
Independent	*	Minus ***	=
FIRST PRESENTATION OF MULTIPLE DEPENDENT CLAIM			

AMENDMENT B	CLAIMS REMAINING AFTER AMENDMENT	HIGHEST NUMBER PREVIOUSLY PAID FOR	PRESENT EXTRA
Total	* 69	Minus ** 20	= 1
Independent	* 4	Minus *** 3	= 1
FIRST PRESENTATION OF MULTIPLE DEPENDENT CLAIM			

AMENDMENT C	CLAIMS REMAINING AFTER AMENDMENT	HIGHEST NUMBER PREVIOUSLY PAID FOR	PRESENT EXTRA
Total	* 69	Minus ** 69	= 0
Independent	* 37	Minus *** 3	= 4
FIRST PRESENTATION OF MULTIPLE DEPENDENT CLAIM			

* If the entry in column 1 is less than the entry in column 2, write "0" in column 3.

** If the "Highest Number Previously Paid For" IN THIS SPACE is less than 20, enter "20."

*** If the "Highest Number Previously Paid For" IN THIS SPACE is less than 3, enter "3."

The "Highest Number Previously Paid For" (Total or Independent) is the highest number found in the appropriate box in column 1.

SMALL ENTITY TYPE ☐ OR

OTHER THAN SMALL ENTITY

RATE	FEE
	345.00
X\$ 9=	
X39=	
+130=	
TOTAL	

RATE	FEE
	690.00
X\$18=	
X78=	
+260=	
TOTAL	1090

SMALL ENTITY OR

OTHER THAN SMALL ENTITY

RATE	ADDITIONAL FEE
X\$ 9=	
X39=	
+130=	
TOTAL ADDIT. FEE	

RATE	ADDITIONAL FEE
X\$18=	
X78=	
+260=	
TOTAL ADDIT. FEE	

RATE	ADDITIONAL FEE
X\$ 9=	
X39=	
+130=	
TOTAL ADDIT. FEE	

RATE	ADDITIONAL FEE
X\$18=	8820
X78=	86
+260=	
TOTAL ADDIT. FEE	8820

RATE	ADDITIONAL FEE
X\$ 9=	
X39=	
+130=	
TOTAL ADDIT. FEE	

RATE	ADDITIONAL FEE
X\$18=	
X78=	3440
+260=	
TOTAL ADDIT. FEE	3440

PATENT APPLICATION SERIAL NO. _____

U.S. DEPARTMENT OF COMMERCE
PATENT AND TRADEMARK OFFICE
FEE RECORD SHEET

04/24/2000 LIRSHING 00000050 200668 09548048
01 FC:101 690.00 CH

PTO-1556
(5/87)

*U.S. GPO: 1999-459-022/18144