



(12) **United States Patent**
Azancot et al.

(10) **Patent No.:** **US 9,048,696 B2**
(45) **Date of Patent:** ***Jun. 2, 2015**

(54) **TRANSMISSION-GUARD SYSTEM AND METHOD FOR AN INDUCTIVE POWER SUPPLY**

(71) Applicant: **POWERMAT TECHNOLOGIES, LTD.**, Neve Ilan (IL)

(72) Inventors: **Yossi Azancot**, Jerusalem (IL); **Amir Ben-Shalom**, Modiin (IL); **Oola Greenwald**, Mevasseret Zion (IL); **Arik Rofo**, Jerusalem (IL); **Alfred Lei-Bovitz**, Petach Tikva (IL); **Moti Ashery**, Jerusalem (IL)

(73) Assignee: **POWERMAT TECHNOLOGIES, LTD.**, Neve Ilan (IL)

(*) Notice: Subject to any disclaimer, the term of this patent is extended or adjusted under 35 U.S.C. 154(b) by 0 days.

This patent is subject to a terminal disclaimer.

(21) Appl. No.: **14/152,358**

(22) Filed: **Jan. 10, 2014**

(65) **Prior Publication Data**

US 2014/0125146 A1 May 8, 2014

Related U.S. Application Data

(60) Division of application No. 12/883,457, filed on Sep. 16, 2010, which is a continuation of application No. PCT/IL2008/001641, filed on Dec. 18, 2008.

(60) Provisional application No. 61/064,618, filed on Mar.

(Continued)

(51) **Int. Cl.**

H01F 38/14 (2006.01)

H02J 17/00 (2006.01)

(Continued)

(52) **U.S. Cl.**

CPC **H02J 17/00** (2013.01); **H01F 27/266** (2013.01); **H01F 27/365** (2013.01); **H01F 38/14** (2013.01); **H01F 2038/143** (2013.01); **H02J 7/025** (2013.01)

(58) **Field of Classification Search**

CPC **H02J 17/00**
USPC **307/104; 320/108**
See application file for complete search history.

(56) **References Cited**

U.S. PATENT DOCUMENTS

3,414,796 A 12/1968 Henquet
3,771,085 A 11/1973 Hojo et al.

(Continued)

FOREIGN PATENT DOCUMENTS

EP 0160990 A2 11/1985
EP 0160990 B1 1/1991

(Continued)

OTHER PUBLICATIONS

Liu et al. "An Analysis of Double-layer Electromagnetic Shield for a Universal Contactless Battery Charging Platform", IEEE 2005, p. 1767-1772.

(Continued)

Primary Examiner — Fritz M Fleming


(74) *Attorney, Agent, or Firm* — Brooks Kushman P.C.

(57)

ABSTRACT

A transmission-guard is disclosed for preventing an inductive power outlet from transmitting power in the absence of an inductive power receiver. A transmission lock is associated with an inductive power outlet and a transmission key is associated with an inductive power receiver. The transmission lock is configured to prevent a primary inductor from connecting to the power supply unless triggered by a release signal via the transmission key.

17 Claims, 19 Drawing Sheets



Related U.S. Application Data

17, 2008, provisional application No. 61/071,151, filed on Apr. 15, 2008, provisional application No. 61/129,526, filed on Jul. 2, 2008, provisional application No. 61/129,859, filed on Jul. 24, 2008, provisional application No. 61/129,970, filed on Aug. 4, 2008.

(51) Int. Cl.

H02J 7/02 (2006.01)
H01F 27/26 (2006.01)
H01F 27/36 (2006.01)

(56)**References Cited**

U.S. PATENT DOCUMENTS

3,938,018 A	2/1976	Dahl	7,385,357 B2	6/2008	Kuennen et al.
4,160,193 A	7/1979	Richmond	7,392,068 B2	6/2008	Dayan et al.
4,349,814 A	9/1982	Akehurst	7,405,535 B2	7/2008	Frerking et al.
RE31,524 E	2/1984	Hoebel	7,462,951 B1	12/2008	Baarman
4,431,948 A	2/1984	Elder et al.	D586,809 S	2/2009	Jones et al.
4,580,062 A	4/1986	MacLaughlin	7,518,267 B2	4/2009	Baarman
4,754,180 A	6/1988	Kiedrowski	7,522,878 B2	4/2009	Baarman
4,977,515 A	12/1990	Rudden et al.	7,576,514 B2	8/2009	Hui
5,221,877 A	6/1993	Falk	D599,735 S	9/2009	Amidei et al.
5,278,771 A	1/1994	Nyanya	D599,736 S	9/2009	Ferber et al.
5,367,242 A	11/1994	Hulman	D599,737 S	9/2009	Amidei et al.
5,374,930 A *	12/1994	Schuermann 342/42	D599,738 S	9/2009	Amidei et al.
5,455,466 A	10/1995	Parks et al.	D603,603 S	11/2009	Laine et al.
5,455,467 A	10/1995	Young	7,612,528 B2	11/2009	Baarman et al.
5,486,394 A	1/1996	Stough	D607,879 S	1/2010	Ferber et al.
5,528,113 A	6/1996	Boys et al.	D611,407 S	3/2010	Webb
5,550,452 A	8/1996	Shirai et al.	D611,408 S	3/2010	Ferber et al.
5,600,225 A	2/1997	Goto	8,049,370 B2	11/2011	Azancot
5,680,035 A	10/1997	Haim et al.	8,188,619 B2 *	5/2012	Azancot et al. 307/104
5,713,939 A	2/1998	Nedungadi et al.	8,427,012 B2 *	4/2013	Azancot et al. 307/104
5,734,254 A	3/1998	Stephens	2002/0057584 A1	5/2002	Brockmann
5,762,250 A	6/1998	Carlton et al.	2002/0158512 A1	10/2002	Mizutani et al.
5,821,728 A	10/1998	Schwind	2003/0210106 A1	11/2003	Cheng et al.
5,821,731 A	10/1998	Kuki et al.	2004/0023633 A1	2/2004	Gordon
5,838,074 A *	11/1998	Loeffler et al. 340/5.61	2004/0195767 A1	10/2004	Randall
5,907,285 A	5/1999	Toms et al.	2004/0203537 A1	10/2004	Yoshida et al.
5,929,598 A	7/1999	Nakama et al.	2004/0242264 A1	12/2004	Cho
5,949,214 A	9/1999	Broussard et al.	2004/0261802 A1	12/2004	Griffin et al.
6,042,005 A	3/2000	Basile et al.	2005/0007067 A1	1/2005	Baarman et al.
6,127,799 A	10/2000	Krishnan	2005/0083020 A1	4/2005	Baarman
6,211,649 B1	4/2001	Matsuda	2005/0130593 A1	6/2005	Michalak
6,230,029 B1	5/2001	Hahn et al.	2005/0164636 A1	7/2005	Palermo et al.
6,396,935 B1	5/2002	Makkonen	2005/0169506 A1	8/2005	Fenrich et al.
6,436,299 B1	8/2002	Baarman et al.	2005/0189910 A1	9/2005	Hui
6,441,589 B1	8/2002	Frerking et al.	2005/0192062 A1	9/2005	Michkle et al.
6,484,260 B1	11/2002	Scott et al.	2005/0233768 A1	10/2005	Guo et al.
6,532,298 B1	3/2003	Cambier et al.	2006/0028176 A1	2/2006	Tang et al.
6,586,909 B1	7/2003	Trepka	2006/0043927 A1	3/2006	Beart et al.
6,624,616 B1	9/2003	Frerking et al.	2006/0052144 A1	3/2006	Seil et al.
6,644,557 B1	11/2003	Jacobs	2006/0061325 A1	3/2006	Tang et al.
6,673,250 B2	1/2004	Kuennen et al.	2006/0071632 A1	4/2006	Ghabra et al.
6,721,540 B1	4/2004	Hayakawa	2006/0091222 A1	5/2006	Leung et al.
6,731,071 B2	5/2004	Baarman	2006/0093132 A1	5/2006	Desormiere et al.
6,766,040 B1	7/2004	Catalano et al.	2006/0202665 A1	9/2006	Hsu
6,803,744 B1	10/2004	Sabo	2007/0023559 A1	2/2007	Scapillato et al.
6,825,620 B2	11/2004	Kuennen et al.	2007/0057763 A1	3/2007	Blattner et al.
6,888,438 B2	5/2005	Hui et al.	2007/0076459 A1	4/2007	Limpkin
6,894,457 B2	5/2005	Germagian et al.	2007/0103110 A1	5/2007	Sagoo
D519,275 S	4/2006	Shertzer	2007/0136593 A1	6/2007	Plavcan et al.
7,026,789 B2 *	4/2006	Bozzone et al. 320/108	2007/0165371 A1	7/2007	Brandenburg
7,043,060 B2	5/2006	Quintana	2007/0182367 A1	8/2007	Partovi
7,126,450 B2	10/2006	Baarman et al.	2007/0210889 A1	9/2007	Baarman et al.
7,132,918 B2	11/2006	Baarman et al.	2007/0279002 A1	12/2007	Partovi
7,164,255 B2	1/2007	Hui	2007/0296393 A1 *	12/2007	Malpas et al. 323/355
7,180,248 B2	2/2007	Kuennen et al.	2008/0001922 A1	1/2008	Johnson et al.
7,180,265 B2	2/2007	Naskali et al.	2008/0030985 A1	2/2008	Joen et al.
7,224,086 B2	5/2007	Germagian et al.	2008/0049988 A1	2/2008	Basile et al.
7,233,319 B2	6/2007	Johnson et al.	2008/0055047 A1	3/2008	Osada et al.
D553,852 S	10/2007	Brandenburg	2008/0079388 A1	4/2008	Sarnowsky et al.
7,278,310 B1	10/2007	Rice	2008/0132293 A1	6/2008	Gundlach et al.
			2008/0157715 A1	7/2008	Rosenboom et al.
			2008/0223926 A1	9/2008	Miller et al.
			2008/0258680 A1	10/2008	Frerking et al.
			2008/0265835 A1	10/2008	Reed et al.
			2009/0026959 A1	1/2009	Lin et al.
			2009/0040807 A1	2/2009	Doumae et al.
			2009/0047768 A1	2/2009	Jain
			2009/0047769 A1	2/2009	Bhat et al.
			2009/0075704 A1	3/2009	Wang
			2009/0079387 A1	3/2009	Jin et al.
			2009/0084705 A1	4/2009	Justiss
			2009/0097221 A1	4/2009	Sayed et al.
			2009/0102416 A1	4/2009	Burley
			2009/0134972 A1	5/2009	Wu, Jr. et al.
			2009/0146608 A1	6/2009	Lee
			2009/0153098 A1	6/2009	Toya et al.
			2009/0153297 A1	6/2009	Gardner
			2009/0174263 A1	7/2009	Baarman et al.
			2009/0203355 A1	8/2009	Clark

(56)

References Cited**U.S. PATENT DOCUMENTS**

2009/0212639	A1	8/2009	Johnson	
2009/0226050	A1	9/2009	Hughes	
2009/0243791	A1	10/2009	Partin et al.	
2009/0251102	A1	10/2009	Hui	
2009/0273891	A1	11/2009	Peiker	
2009/0278494	A1	11/2009	Randall	
2010/0039066	A1	2/2010	Yuan et al.	
2014/0125146	A1 *	5/2014	Azancot et al.	307/104
2014/0125147	A1 *	5/2014	Azancot et al.	307/104

FOREIGN PATENT DOCUMENTS

EP	0558316	A1	9/1993	
EP	1990734	A1	11/2008	
GB	2399466	A	9/2004	
GB	2399466	B	11/2005	
GB	2429372	A	2/2007	
JP	04-156242		5/1992	
JP	07-039078		2/1995	
JP	07-036556		7/1995	
JP	2001-309579		11/2001	
JP	2001309579		11/2001	
JP	2005-006440		1/2005	
JP	2005-110412		4/2005	
JP	2006-102055		4/2006	
JP	2007-529110		10/2007	
WO	9602879	A1	2/1996	
WO	0201557	A1	1/2002	
WO	0215320	A1	2/2002	
WO	2005041281	A1	5/2005	
WO	2005043775	A1	6/2005	
WO	2006037972	A1	9/2005	
WO	2006015143	A2	2/2006	
WO	WO 2006031133	A1 *	3/2006	
WO	2008030985	A2	3/2008	
WO	2008086080	A2	7/2008	
WO	2008093334	A2	8/2008	
WO	2008114268	A2	9/2008	
WO	2009040807	A2	4/2009	
WO	2009047768	A2	4/2009	
WO	2009047769	A2	4/2009	
WO	2009049657	A1	4/2009	
WO	2009108958	A1	9/2009	
WO	2010025156	A1	3/2010	
WO	2010025157	A1	3/2010	

OTHER PUBLICATIONS

Hui et al. "A New Generation of Universal Contactless Battery Charging Platform for Portable Consumer Electronic Equipment", IEEE Transactions on Power Electronics May 2005, vol. 20, No. 3, p. 620-627.

Liu et al. "Equivalent Circuit Modeling of a Multilayer Planar Winding Array Structure for Use in a Universal Contactless Battery Charging Platform", IEEE Transactions on Power Electronics Jan. 2007, vol. 22, No. 1, p. 21-29.

Tang et al. "Evaluation of the Shielding Effects on Printed-Circuit-Board Transformers Using Ferrite Plates and Copper Sheets", IEEE Transactions on Power Electronics Nov. 2002, vol. 17, No. 6, p. 1080-1088.

Su et al. "Extended Theory on the Inductance Calculation of Planar Spiral Windings Including the Effect of Double-layer Electromagnetic Shield", IEEE 2007, p. 3022-3028.

Liu et al. "Optimal Design of a Hybrid Winding Structure for Planar Contactless Battery Charging Platform", IEEE Transactions on Power Electronics Jan. 2008, vol. 23, No. 1, p. 455-463.

Liu et al. "Simulation Study and Experimental Verification of a Universal Contactless Battery Charging Platform With Localized Charging Features", IEEE Transactions on Power Electronics Nov. 2007, vol. 22, No. 6, p. 2202-2210.

International Search Report for PCT/IL2009/000915 Completed by the European Patent Office on Mar. 15, 2010, 3 Pages.

Search report and Written Opinion for PCT/IL2008/001282, Both completed by the US Patent Office on Feb. 25, 2009, 9 pages all together.

Search Report and Written Opinion for PCT/IL2008/001347, Both completed by the US Patent Office on Feb. 2, 2009, 10 Pages all together.

Search Report and Written Opinion for PCT/IL2008/001348, Both completed by the US Patent Office on Jan. 28, 2009, 9 Pages all together.

International Search Report for PCT/IL2008/01641, Completed by the US Patents and Trademark Office on May 21, 2009, 3 Pages.

Office Action dated Mar. 22, 2013, for Mexican Application MX/A/2011/003088.

Office Action dated Feb. 5, 2013, for Chinese Application 201110068458.7.

Office Action dated May 28, 2013, for Japanese Application 2010-526422.

Office Action dated May 28, 2013, for Japanese Application 2010-528526.

Office Action dated May 21, 2013, for Japanese Application 2011-500345.

* cited by examiner




Fig. 1b




Fig. 1a




Fig. 1c




Fig. 2a




Fig. 2b




Fig. 2c




Fig. 2d




Fig. 2e




Fig. 2f




Fig. 3a

PRIOR ART




Fig. 3b

PRIOR ART




Fig. 4a




Fig. 4b




Fig. 4c




Fig. 4d




Fig. 4e




Fig. 5a






Fig. 5b






Fig. 5e




Fig. 5f




Fig. 6a




Fig. 6b





Fig. 6c

**Fig. 6d**




FIG. 6e





Fig. 7a

**Fig. 7b**





FIG. 7c

**Fig. 7d**

1

TRANSMISSION-GUARD SYSTEM AND METHOD FOR AN INDUCTIVE POWER SUPPLY

CROSS-REFERENCE TO RELATED APPLICATIONS

This application is a division of U.S. application Ser. No. 12/883,457 filed Sep. 16, 2010, which is a continuation of PCT application Serial No. PCT/IL2008/001641 filed Dec. 18, 2008, which claims the benefit of U.S. provisional application Ser. Nos. 61/064,618 filed Mar. 17, 2008; 61/071,151 filed Apr. 15, 2008; 61/129,526 filed Jul. 2, 2008; 61/129,859 filed Jul. 24, 2008; and 61/129,970 filed Aug. 4, 2008, which are hereby incorporated by reference in their entirety.

TECHNICAL FIELD

The present invention is directed to inductive electrical power transfer. More specifically, the present invention relates to providing a transmission guard for preventing an inductive power outlet from transmitting power in the absence of an inductive power receiver.

BACKGROUND

Inductive power coupling, as known in the art, allows energy to be transferred from a power supply to an electric load without connecting wires. A power supply is wired to a primary coil and an oscillating electric potential is applied across the primary coil, thereby inducing an oscillating magnetic field. The oscillating magnetic field may induce an oscillating electrical current in a secondary coil placed close to the primary coil. In this way, electrical energy may be transmitted from the primary coil to the secondary coil by electromagnetic induction without the two coils being conductively connected. When electrical energy is transferred from a primary coil to a secondary coil the coil pair are said to be inductively coupled. An electric load wired in series with such a secondary coil may draw energy from the power source wired to the primary coil when the secondary coil is inductively coupled thereto.

Induction type power outlets may be preferred to the more common conductive power sockets because they provide seamless power transmission and minimize the need for trailing wires.

Low power inductive electrical power transmission systems have been proposed. One such example is described in U.S. Pat. No. 7,164,255 to Hui. In Hui's system a planar inductive battery charging arrangement enables electronic devices to be charged. The system includes a planar charging module having a charging surface on which a device to be charged is placed. Within the charging module, and parallel to the charging surface, at least one, and preferably an array of primary windings are provided. The primary windings inductively couple with secondary windings within the device to be charged.

Such systems provide inductive coupling at relatively low power adequate for charging batteries. It will be appreciated however, that base units such as Hui's charging surface which transmit energy continuously, in a largely uniform manner over an extended area, are not suitable for use with high energy systems, such as those required to power computers, light bulbs, televisions and the like.

Energy losses associated with high power inductive transfer systems are typically larger than those in low power systems such as Hui's charging surface. In addition whereas in

2

low power systems excess heat may be readily dissipated, an uncoupled high power primary coil or its surroundings may become dangerously hot.

Moreover, the oscillating voltage in a high power primary coil produces an oscillating magnetic field. Where a secondary coil is inductively coupled to the primary coil, the resulting flux linkage causes power to be drawn by the secondary coil. Where there is no secondary coil to draw the power, the oscillating magnetic field causes high energy electromagnetic waves to be radiated in all directions which may have undesired side effects, such as erasing data from credit cards and may be harmful to bystanders particularly to those with pace-makers.

U.S. Pat. No. 6,803,744, to Sabo, titled "Alignment independent and self-aligning inductive power transfer system" describes an inductive power transfer device for recharging cordless appliances. Sabo's device includes a plurality of inductors which serve as the primary coil of a transformer. The secondary coil of the transformer is arranged within the appliance. When the appliance is positioned proximate to the power transfer device with the respective coils in alignment, power is inductively transferred from the device to the appliance via the transformer.

The inductors of Sabo's system are arranged in an array and connected to a power supply via switches which are selectively operable to activate the respective inductors. These selectively operable switches are provided to conserve power and to eliminate objectionable electromagnetic fields. '744 thus indicates the problem of electromagnetic leakage as well as the need for each primary coil to be energized from the power supply only when a secondary coil is within effective range. Furthermore the power receiving units described in '744 are bulky and impractical for use with small electrical devices.

The need remains therefore for a practical inductive power transfer system for safely and conveniently delivering power wirelessly from inductive power outlets to inductive power receivers in an energy efficient manner. The present invention addresses this need.

SUMMARY

It is an aim of the invention to provide a transmission system comprising at least one inductive power outlet for transferring power inductively to at least one inductive power receiver, at least one alignment mechanism for aligning the power receiver to the power outlet and at least one signal transfer system for passing control signals from the power receiver to the power outlet. Typically, the inductive power outlet comprises at least one primary inductive coil wired to a power source via a driver, the driver for providing an oscillating voltage across the primary inductive coil at high frequency, and a primary ferromagnetic core. The inductive power receiver comprises at least one secondary inductive coil for coupling with the primary inductive coil, the secondary inductive coil being wired to a power regulator. The signal transfer system comprises a signal emitter associated with the power receiver and a signal detector associated with the power outlet.

Optionally, the alignment mechanism comprises a first element associated with the power outlet and a second magnetic element associated with the power receiver. Typically, the signal emitter comprises an optical emitter and the signal detector comprises an optical detector. Optionally, again, the power regulator comprises a rectifier for converting an AC input from the inductive power outlet into a DC output for powering the electrical device. Another aim of the invention is

3

to present an inductive power receiver for receiving power inductively from an inductive power outlet. Optionally, the system comprises a power converter selected from the group comprising: a transformer, a DC-to-DC converter, an AC-to-DC converter, an AC-to-AC converter, a flyback transformer, a flyback converter, a full-bridge converter, a half-bridge converter and a forward converter.

A further aim of the invention is to present an inductive power transfer system comprising at least one inductive power outlet for transferring power inductively to at least one inductive power receiver, the inductive power outlet comprising at least one primary inductor wired to a power source via a driver, and the inductive power receiver comprising at least one secondary inductor for coupling with the primary inductor, the secondary inductor for providing power to an electric load; the inductive power transfer system comprising a low heat-loss full wave rectifier comprising: a first half-wave rectifier having one anode wired to a first output terminal and one cathode wired to a first input terminal; a second half-wave rectifier having one anode wired to the first output terminal and one cathode wired to a second input terminal; a third half-wave rectifier having one anode wired to the first input terminal and one cathode wired to a second output terminal, and a fourth half-wave rectifier having one anode wired to the second input terminal and one cathode wired to the second output terminal; the full wave rectifier for providing an output of constant polarity from an input of variable polarity, wherein at least one half-wave rectifier comprises an electronic switch configured to be in its ON state when the current flowing through the cathode of the switch exceeds a predetermined threshold.

Optionally, the first half-wave rectifiers comprises a first electronic switch configured to be in its ON setting when the current flowing through its cathode exceeds a first predetermined threshold, and the second half-wave rectifiers comprises a second electronic switch configured to be in its ON setting when the current flowing through its cathode exceeds a second predetermined threshold. Preferably, at least one half-wave rectifier comprises an electronic switch configured to be switched between its ON and OFF states in synchrony with the frequency of the input signal.

Preferably, the first half-wave rectifier comprises a first electronic switch configured to be in its ON state when the current flowing through its cathode exceeds a predetermined threshold; the second half-wave rectifiers comprises a second electronic switch configured to be in its ON state when the current flowing through its cathode exceeds a predetermined threshold; the third half-wave rectifiers comprises a third electronic switch configured to be switched between its ON and OFF states in phase with the voltage signal at the second input terminal, and the fourth half-wave rectifiers comprises a third electronic switch configured to be switched between its ON and OFF states in phase with the voltage signal at the first input terminal.

Typically the electronic switch comprises a transistor, in particular, a MOSFET device. Preferably, the electronic switch comprises: a MOSFET device comprising a source terminal, a drain terminal and a gate terminal; a half-wave rectifier wired to the source terminal and the drain terminal in parallel with the MOSFET device, and a current monitor configured to monitor a drain-current flowing through the drain terminal and to send a gate signal to the gate terminal such that the MOSFET is switched to its ON state when the drain-current exceeds a first threshold current and the MOSFET is switched to its OFF state when the drain-current falls below a second threshold current. Optionally, the current monitor comprises a current transformer.

4

It is another aim of the invention to present an inductive power transfer system comprising at least one inductive power outlet comprising at least one primary inductive coil wired to a power supply via a driver; the primary inductive coil for forming an inductive couple with at least one secondary inductive coil wired to an electric load, the secondary inductive coil associated with an inductive power receiver wherein the driver is configured to provide a driving voltage across the primary inductive coil, the driving voltage oscillating at a transmission frequency significantly different from the resonant frequency of the inductive couple. Optionally, the driver comprises a switching unit for intermittently connecting the primary inductive coil to the power supply.

Preferably, the transmission frequency lies within a range in which induced voltage varies approximately linearly with frequency. Optionally, the driver is configured to adjust the transmission frequency in response to the feedback signals.

Optionally, the inductive power outlet comprising a signal detector adapted to detect a first signal and a second signal, and the driver is configured to: increase the transmission frequency when the first signal is detected by the detector, and decrease the transmission frequency when the second signal is detected by the detector. The feedback signals generally carry data pertaining to the operational parameters of the electric load. Operational parameters are selected from the group comprising: required operating voltage for the electric load; required operating current for the electric load; required operating temperature for the electric load; required operating power for the electric load; measured operating voltage for the electric load; measured operating current for the electric load; measured operating temperature for the electric load; measured operating power for the electric load; power delivered to the primary inductive coil; power received by the secondary inductive coil, and a user identification code. Optionally, the detector is selected from the list comprising optical detectors, radio receivers, audio detectors and voltage peak detectors.

Preferably, the driver further comprises a voltage monitor for monitoring the amplitude of a primary voltage across the primary coil. Optionally, the voltage monitor is configured to detect significant increases in primary voltage.

In preferred embodiments, the driving voltage oscillating at a transmission frequency higher than the resonant frequency of the inductive couple, wherein the primary inductive coil is further wired to a reception circuit comprising a voltage monitor for monitoring the amplitude of a primary voltage across the primary coil, and the secondary inductive coil is further wired to a transmission circuit for connecting at least one electric element to the secondary inductive coil thereby increasing the resonant frequency such that a control signal may be transferred from the transmission circuit to the reception circuit. Optionally, the secondary inductive coil is wired to two inputs of a bridge rectifier and the electric load is wired to two outputs of the bridge rectifier wherein the transmission circuit is wired to one input of the bridge rectifier and one output of the bridge rectifier. Typically, the transmission circuit further comprises a modulator for modulating a bit-rate signal with an input signal to create a modulated signal and a switch for intermittently connecting the electrical element to the secondary inductive coil according to the modulated signal. Optionally, the voltage monitor further comprises a correlator for cross-correlating the amplitude of the primary voltage with the bit-rate signal for producing an output signal.

In certain embodiments, the control signal is for transferring a feedback signal from the secondary inductive coil to the primary inductive coil for regulating power transfer across an

5

inductive power coupling. The driver may be configured to adjust the transmission frequency in response to the feedback signals. Typically, the system is adapted to transfer a first signal and a second signal, and the driver is configured to: increase the transmission frequency when the first signal is received by the receiver, and decrease the transmission frequency when the second signal is received by the receiver.

It is still a further aim of the invention to present an inductive power adaptor comprising: at least one inductive power receiver for receiving power from an inductive power outlet; at least one power connector for conductively connecting the power receiver to at least one electrical device, and a grip for handling the adapter, the grip being thermally isolated from the power receiver such that when the power receiver is in operation a user may handle the adapter without injury. Optionally, the adapter further comprises a printed circuit board.

Typically, the power receiver is for providing power at a rate above 50W. Preferably, the adapter comprises a cooling system for dissipating heat generated therein. Optionally, the cooling system comprises at least one air outlet, situated above the power receiver, and at least one air inlet, situated below the power receiver such that hot air heated by the power receiver flows out of the adapter through the air outlet and cool air from outside is drawn into the adapter through the air inlets.

Preferably, the adapter further comprises at least one heat sink for dissipating heat generated by the power receiver. Optionally, the heat sink is a metallic disk. Typically, the heat sink is smaller than the internal diameter of a casing of the adapter thereby allowing air to circulate between the heat sink and the casing.

It is a further aim of the invention to present a transmission-guard for preventing an inductive power outlet from transmitting power in the absence of an electric load inductively coupled thereto, the inductive power outlet comprising at least one primary coil connectable to a power supply, for inductively coupling with a secondary coil wired to the electric load, the transmission-guard comprising at least one transmission-lock for preventing the primary coil from connecting to the power supply in the absence of a transmission-key.

Optionally, the transmission-lock comprises at least one magnetic switch and the transmission-key comprises at least one magnetic element associated with the secondary coil. Typically, the transmission-lock comprises an array of magnetic switches configured to connect the primary coil to the power supply only when activated by a matching configuration of magnetic elements. Optionally, the magnetic switch comprises a magnetic sensor.

Alternatively, the transmission-guard comprises: at least one emitter for emitting a release-signal, and at least one detector for detecting the release signal; the transmission-key comprises at least one bridge associated with the secondary coil for bridging between the at least one emitter and the at least one detector, such that when the secondary coil is brought into alignment with the primary coil the release signal is guided from the emitter to the detector. Optionally, the release-signal is an optical signal and the bridge comprises at least one optical wave-guide. Alternatively, the release-signal is a magnetic signal and the bridge comprises a magnetic flux guide. In other embodiments the transmission-key comprises a release-signal emitted by an emitter associated with the secondary coil. The release-signal may be an optical signal and the optical signal may be an infra-red pulse received by an optical detector configured to release the transmission-lock.

6

Alternatively the release-signal is a magnetic signal. In some embodiments of the transmission guard the emitter is the secondary coil.

Optionally, the transmission-guard comprises a low-power power pulse transmitted by the primary coil, such that when the secondary coil is aligned to the primary coil the power pulse is transferred to the secondary coil and the transmission-key is triggered by the power pulse. Preferably, a first transmission-lock is released by a first transmission-key indicating the probable presence of a secondary coil and a second transmission-lock is released by a second transmission-key confirming the presence of the secondary coil. The first transmission-lock may initiate a power pulse transmitted from the primary coil, and the second transmission key being triggered by the power pulse being received by the secondary coil. The magnetic element may comprise a ferrite flux guidance core. Various, the release-signal is selected from the group comprising: mechanical signals, audio signals, ultra-sonic signals and microwaves. It is also an aim to present separately: a transmission-key for use in the transmission-guard, a transmission-lock for use in the transmission-guard, and an inductive power outlet protected by the transmission-guard.

It is yet another aim of the invention to present an inductive power transfer system comprising at least one inductive power receiver for receiving power from an inductive power outlet, the inductive power outlet comprising at least one primary inductor wired to a power source via a driver, and the inductive power receiver comprising at least one secondary inductor for coupling with the primary inductor, the secondary inductor for providing power to an electric load; the inductive power transfer system comprising at least one magnetic flux guide for directing magnetic flux from the primary inductor to the secondary inductor wherein the magnetic flux guide comprises an amorphous ferromagnetic material. Optionally, the amorphous ferromagnetic material has a thickness of less than 30 microns. Typically, the amorphous ferromagnetic material is sandwiched between two polymer layers. Preferably, the magnetic flux guide comprises a plurality of layers of amorphous ferromagnetic material separated by electrically insulating material.

In some embodiments, the magnetic flux guide comprises a wafer of the amorphous ferromagnetic material. Preferably, the wafer is at least partially split so as to reduce the buildup of eddy currents. Optionally, the wafer is circular and having a split extending along at least one diameter. In certain embodiments, the wafer is cut from a sheet of the amorphous ferromagnetic material. Alternatively, the magnetic flux guide comprises microwires of the amorphous ferromagnetic material. Optionally, the microwires form a cloth.

It is a particular aim of the invention to present an inductive power transfer system comprising at least one inductive power outlet for transferring power inductively to at least one inductive power receiver, the inductive power outlet comprising at least one primary inductor wired to a power source via a driver, and the inductive power receiver comprising at least one secondary inductor for coupling with the primary inductor, the secondary inductor for providing power to an electric load; the inductive power transfer system comprising at least one of the optimization components selected from the group comprising: a low heat-loss full wave rectifier comprising at least one electronic switch configured to be in its ON state when the current flowing through the cathode of the switch exceeds a predetermined threshold; a driver connected between the power source and the primary inductor, the driver being configured to provide a driving voltage across the primary inductive coil, the driving voltage oscillating at a transmission frequency significantly different from the reso-

7

nant frequency of the inductive couple formed by the primary inductor and the secondary inductor; an inductive power adaptor comprising a grip for handling the power receiver, the grip being thermally isolated from the power receiver such that when the power receiver is in operation a user may handle the adapter without injury; a transmission-guard for preventing the inductive power outlet from transmitting power in the absence of an electric load inductively coupled thereto, the transmission-guard comprising at least one transmission-lock for preventing the primary coil from connecting to the power supply in the absence of a transmission-key, and a magnetic flux guide for directing magnetic flux from the primary inductor to the secondary inductor wherein the magnetic flux guide comprises an amorphous ferromagnetic material.

In further embodiments the inductive power transfer system comprises at least two of the optimization components listed above. Preferably, the inductive power transfer system comprises at least three of the optimization components.

BRIEF DESCRIPTION OF THE DRAWINGS

For a better understanding of the invention and to show how it may be carried into effect, reference will now be made, purely by way of example, to the accompanying drawings.

With specific reference now to the drawings in detail, it is stressed that the particulars shown are by way of example and for purposes of illustrative discussion of the preferred embodiments of the present invention only, and are presented in the cause of providing what is believed to be the most useful and readily understood description of the principles and conceptual aspects of the invention. In this regard, no attempt is made to show structural details of the invention in more detail than is necessary for a fundamental understanding of the invention; the description taken with the drawings making apparent to those skilled in the art how the several forms of the invention may be embodied in practice. In the accompanying drawings:

FIG. 1a is a schematic diagram representing an inductive power transfer system according to an exemplary embodiment of the present invention;

FIG. 1b is a schematic diagram representing an inductive power receiver for use in the inductive power transfer system of FIG. 1a;

FIG. 1c is a block diagram representation of the main components of the inductive power transfer system according to the exemplary embodiment of the present invention;

FIG. 2a is a block diagram representing the main components of a transmission-guard for an inductive power outlet according to another embodiment of the present invention;

FIG. 2b is a schematic representation of an inductive power outlet protected by an exemplary transmission-guard according to a further embodiment of the present invention wherein a transmission-lock is released by a magnetic key;

FIGS. 2c-e are schematic representations of a transmission-guard according to another embodiment of the invention in which a transmission-lock is releasable by a passive optical transmission-key;

FIG. 2f is a schematic representation of a transmission-guard according to a further embodiment of the invention in which a transmission-lock is releasable by an active optical transmission-key;

FIG. 3a is a circuit diagram of a full-wave diode bridge rectifier of the prior art;

FIG. 3b is a diagram of a Power MOSFET of the prior art;

8

FIG. 4a is a block diagram of a first synchronous full-wave rectifier in which two of the diodes of the diode bridge of FIG. 3 have been replaced by electronic switches;

FIG. 4b is a block diagram of a second synchronous full-wave rectifier according to an exemplary embodiment of the invention in which all four diodes of the diode bridge of FIG. 3 have been replaced by electronic switches;

FIG. 4c is a schematic diagram showing a current triggered Power MOSFET which draws a gate signal from the current flowing through its drain terminal;

FIG. 4d is a graphical representation of the variations in drain-current and state of the MOSFET of FIG. 4c, over a single cycle of a sinusoidal input voltage;

FIG. 4e is a circuit diagram representing a synchronous full-wave MOSFET bridge rectifier according to another embodiment of the invention;

FIG. 5a shows schematic diagram of a computer being powered by an inductive power outlet via an inductive power adapter according to a further embodiment of the present invention;

FIG. 5b is an isometric projection of an inductive power adapter according to an exemplary embodiment of the invention;

FIG. 5c is an exploded view showing the internal components of the power receiver of the exemplary embodiment;

FIG. 5d is a side view cross section of the power receiver of the exemplary embodiment;

FIG. 5e is an exploded view of an inductive power receiver having a magnetic flux guide according to another embodiment of the invention;

FIG. 5f is an isometric view of the inductive power receiver of FIG. 5e;

FIG. 6a is a block diagram showing the main elements of an inductive power transfer system with a feedback signal path;

FIG. 6b is a graph showing how the amplitude of operational voltage varies according to frequency;

FIG. 6c is a schematic diagram representing a laptop computer drawing power from an inductive power outlet;

FIG. 6d is a flowchart showing a method for regulating power transfer by varying the power transmission frequency in an inductive power transfer system;

FIG. 6e is a circuit diagram of an inductive power transfer system including a peak detector for detecting large increases in transmission voltage;

FIG. 7a is a block diagram showing the main elements of an inductive power transfer system with an inductive feedback channel according to another embodiment of the present invention;

FIG. 7b is a graph showing how the amplitude of operational voltage of an inductive power transfer system varies according to the voltage transmission frequency and the resonant frequency of the system;

FIG. 7c is a circuit diagram of an inductive power transfer system including an inductive feedback channel for providing coil-to-coil signal transfer concurrently with uninterrupted inductive power transfer between the coils in accordance with another embodiment of the invention, and

FIG. 7d is a flowchart showing a method for transferring a signal from the secondary inductive coil to a primary inductive coil of an inductive power transfer system according to still a further embodiment of the invention.

DETAILED DESCRIPTION

As required, detailed embodiments of the present invention are disclosed herein; however, it is to be understood that the

disclosed embodiments are merely exemplary of the invention that may be embodied in various and alternative forms. The figures are not necessarily to scale; some features may be exaggerated or minimized to show details of particular components. Therefore, specific structural and functional details disclosed herein are not to be interpreted as limiting, but merely as a representative basis for teaching one skilled in the art to variously employ the present invention.

Reference is now made to FIGS. 1a and 1b showing an inductive power outlet 200 and an inductive power receiver 300 for use in an exemplary inductive power transfer system 100 according to an exemplary embodiment of the invention.

The inductive power outlet 200 consists of four primary inductors 220a-d incorporated within a platform 202. The inductive power receiver 300 includes a secondary inductor 320 incorporated within a case 302 for accommodating a mobile telephone 342. When a mobile telephone 342 is placed within the case 302 a power connector 304 electrically connects the secondary inductor 320 with the mobile telephone 342. As shown in FIG. 1a, the inductive power receiver 300 may be placed upon the platform 202 in alignment with one of the primary inductors 220b so that the secondary inductor 320 inductively couples with the primary inductor 220b.

Referring now to FIG. 1c, which shows a block diagram representing the main components of the inductive transfer system 100, various features are included to improve power transfer across the inductive couple.

The inductive power outlet 200 includes a primary inductor 220, wired to a power supply 240 via a driver 230. The driver 230 typically includes electronic components, such as a switching unit for example, for providing an oscillating electrical potential to the primary inductor 220. The oscillating electrical potential across the primary inductor 220 produces an oscillating magnetic field in its vicinity.

The inductive power receiver 300 includes a secondary inductor 320 wired to an electric load 340, typically via a rectifier 330. The secondary inductor 320 is configured such that, when placed in the oscillating magnetic field of an active primary inductor 220, a secondary voltage is induced across the secondary inductor 320. The secondary voltage may be used to power the electric load 340. It is noted that an induced secondary voltage across the secondary inductor 320 produces an alternating current (AC). Where the electric load 340 requires direct current (DC), such as for charging electrochemical cells, the rectifier 330 is provided to convert AC to DC.

In contradistinction to prior art inductive power transfer systems, which have proved impractical or commercially unviable, embodiments of the current invention include further elements for improving the efficiency of power transfer from the inductive power outlet 200 to the inductive power receiver 300. For example, preferred embodiments of the invention include a signal transfer system 400, an alignment mechanism 500 and a magnetic flux guide 600.

The signal transfer system 400 provides a channel for passing signals between the inductive power receiver 300 and the inductive power outlet 200. The signal transfer system 400 includes a signal emitter 420, associated with the inductive power receiver 300 and a signal detector 440, associated with the inductive power outlet 200. Signals may perform a variety of functions such as inter alia, confirming the presence of a power receiver 300, regulating power transfer or for communicating required power transmission parameters. The latter being particularly useful in systems adapted to work at multiple power levels. Various signal transfer systems

may be used such as optical, inductive, ultrasonic signal emitters or the like in combination with appropriate detectors.

The alignment mechanism 500 is provided to facilitate the alignment of the secondary inductor 320 with the primary inductor 220 thereby improving the efficiency of the inductive transfer system 100. Where the user is able to see the primary inductor 220 directly, the secondary inductor 320 may be aligned by direct visual observation. However, where the primary inductor 220 is concealed behind an opaque surface, alternative alignment mechanisms 500 may be necessary. Such alignment mechanisms 500 may include tactile, visual and/or audible indications, for example.

The magnetic flux guide 600 is provided to guide magnetic flux from the primary inductor 220 to the secondary inductor 320 and to prevent flux leakage out of the inductive power transfer system 100, particularly into metallic or other conductive materials in the vicinity.

Prior art inductive power transfer systems have typically been either inefficient or impractical for powering electrical devices wirelessly. As a result, in spite of the long felt need to reduce trailing wires, the use of inductive power transfer has been generally limited to low power applications such as the charging of batteries. In order to be practical, an inductive power transfer system must be efficient, safe and unobtrusive, preferably having small dimensions and being lightweight. As will be described hereinbelow, embodiments of the present invention are directed towards providing an inductive power transfer system which answers these requirements.

Particular aspects of the current invention include: a transmission-guard for preventing the inductive power outlet 200 from transmitting power in the absence of an inductive power receiver 300; an AC-DC rectifier 330 which uses electronic switches for reducing heat loss from diodes; an inductive power receiver 300 having a heat dissipation system such that a user may comfortably and safely handle the inductive power receiver 300; a magnetic flux guide 600 constructed from thin materials and which is adapted to improve flux linkage between the primary inductor 220 and the secondary inductor 320 as well as to prevent flux leakage into the surroundings; a driver 230 configured and operable to generate a driving voltage which oscillates at a transmission frequency which is substantially different from the resonant frequency of the inductive couple.

Any one of the above described aspects by itself represents a significant improvement to the prior art. However, it is particularly noted that for any inductive power transfer system 100 to be practical for powering electrical devices, it needs to incorporate at least two or more of the above described features in combination. More detailed descriptions of embodiments of the invention which incorporate these features are given below.

Transmission-Guard

Reference is now made to FIG. 2a which shows a block diagram representing a transmission-guard 2100 for preventing an inductive power outlet 2200 from transmitting power in the absence of a secondary unit 2300 connected to an electric load 2340, according to another embodiment of the invention.

The inductive power outlet 2200 consists of a primary coil 2220, wired to a power supply 2240, for inductively coupling with a secondary coil 2320 wired to an electric load 2340. The primary coil 2220 is wired to the power supply 2240 via a driver 2230 which provides the electronics necessary to drive the primary coil 2220. Driving electronics may include a switching unit providing a high frequency oscillating voltage supply, for example. Where the power outlet 2200 consists of

11

more than one primary coil **2220**, the driver **2230** may additionally consist of a selector for selecting which primary coil **2220** is to be driven.

It is a particular feature of this embodiment of the invention that a transmission-guard **2100** is provided consisting of a transmission-lock **2120** connected in series between the power supply **2240** and the primary coil **2220**. The transmission-lock **2120** is configured to prevent the primary coil **2220** from connecting to the power supply **2240** unless it is released by a transmission-key **2140**. The transmission-key **2140** is associated with the secondary unit **2300** and serves to indicate that the secondary coil **2320** is aligned to the primary coil **2220**.

With reference to FIG. **2b**, a schematic representation is shown of an inductive power outlet **2200** protected by an exemplary magnetic transmission-guard **2100** according to another embodiment of the present invention. Power may only be provided by the protected power outlet **2200** when an authenticated secondary unit **2300** is aligned thereto.

The protected power outlet **2200** includes a magnetic transmission-lock **2120** consisting of an array of magnetic switches **2122** electrically connected in series between the primary coil **2220** and the driver **2230**. A magnetic transmission-key **2140** consisting of an array of magnetic elements **2142** is provided within the authenticated secondary unit **2300**.

The configuration of magnetic elements **2142** in the transmission-key **2140** is selected to match the configuration of magnetic switches **2122** in the transmission-lock **2120**. The authenticated secondary unit **2300** may be aligned with the protected induction outlet **2200** by aligning both the transmission-key **2140** with the transmission-lock **2120** and the secondary coil **2320** with the primary coil **2220**. Once correctly aligned, all the magnetic switches **2122** in the transmission-lock **2120** are closed and the driver **2230** is thereby connected to the primary coil **2220**.

Various examples of magnetic switches **2122** are known in the art including for example reed switches, Hall-effect sensors or such like. Such magnetic switches **2122** may be sensitive to any magnetic elements **2142** such as either North or South poles of permanent magnets or electromagnetic coils for example. It is further noted that Hall-effect sensors may be configured to sense magnetic fields of predetermined strength.

According to certain embodiments, the magnetic transmission-key **2140** may consist of a permanent magnet and a ferromagnetic element incorporated within the secondary unit **2300**. The characteristics of the magnetic field produced by a transmission-key of this type depend upon the strength and position of the permanent magnetic as well as the dimensions and characteristics of the ferromagnetic element. The magnetic transmission-lock **2120** may consist of an array of magnetic switches, such as unipolar Hall switches for example, which are strategically placed and orientated such that they connect the primary coil **2220** to the driver **2230** only when triggered by a particular combination of a permanent magnet and ferromagnetic element.

It is noted that permanent magnets may commonly be provided to assist with alignment of the secondary coil **2320** to the primary coil **2220**. Ferromagnetic elements may also be commonly included in secondary units **2300** for providing flux guidance from the primary coil **2220** to the secondary coil **2320**. The magnetic transmission-lock **2120** may therefore be made sensitive to these components. Indeed a single magnetic transmission-lock **2120** may be provided which is

12

configured to detect various secondary units and to selectively connect more than one primary coil **2220** depending on the secondary unit detected.

Referring back to FIG. **2a**, according to other embodiments of the transmission-guard **2100**, a power outlet **2200** may be protected by a transmission-lock **2120** which may be released when a release signal S_R is received by a detector **2124**. The release signal S_R may be actively emitted by the transmission-key **2140** or alternatively the transmission-key may passively direct the release signal towards the detector **2124**.

One example of a passive transmission-key **2140** is shown in FIGS. **2c-e** which represents an optical transmission-guard **2100** according to a further embodiment of the invention.

The transmission-guard **2100** consists of an active optical transmission-lock **2120'** incorporated within an inductive power outlet **2200'** and a passive optical transmission-key **2140'** incorporated within the secondary unit **2300**.

With particular reference to FIG. **2c**, the optical transmission-lock **2120'** includes a switch **2122'**, an optical detector **2124'**, such as a photodiode, a phototransistor, a light dependent resistor or the like, and an optical emitter **2126'** such as light emitting diode (LED). The switch **2122'** is normally open but is configured to close when a release signal S_R is received by the optical detector **2124'**, thereby connecting a primary coil **2220** to a driver **2230**. The optical emitter **2126'** is configured to emit the optical release-signal S_R which is not directly detectable by the optical detector **2124'**.

Referring now to FIG. **2d**, the optical transmission-key **2140'** includes a bridging element **2142'** such as an optical wave-guide, optical fiber, reflector or the like. The bridging element **2142'** is configured to direct the optical release-signal S_R from the optical emitter **2124'** towards the optical detector **2126'**, when a secondary coil **2320** is aligned with the primary coil **2220**.

When the secondary unit **2300** is correctly aligned with the inductive power outlet **2200**, as shown in FIG. **2e**, the secondary coil **2320** aligns with the primary coil **2220'** and the passive optical transmission-key **2140'** aligns with the optical transmission-lock **2120'**. The optical release-signal S_R is thus detected by the optical detector **2126'** and the switch **2122'** is closed connecting the primary coil **2220** to the driver **2230**.

It is noted that many materials are partially translucent to infra-red light. It has been found that relatively low intensity infrared signals from LEDs and the like, penetrate several hundred microns of common materials such as plastic, cardboard, Formica or paper sheet, to a sufficient degree that an optical detector **2124'**, such as a photodiode, a phototransistor, a light dependent resistor or the like, behind a sheet of from 0.1 mm to 2 mm of such materials, can receive and process the signal. For example a signal from an Avago HSDL-4420 LED transmitting at 850 nm over 24 degrees, may be detected by an Everlight PD15-22C-TR8 NPN photodiode, from behind a 0.8 mm Formica sheet. For signaling purposes, a high degree of attenuation may be tolerated, and penetration of only a small fraction, say 0.1% of the transmitted signal intensity may be sufficient.

Although an optical transmission-key **2140'** is described above, it will be appreciated that other passive transmission-keys may incorporate bridging elements configured to guide release-signals of other types. For example, a ferromagnetic bridge may be incorporated for transmitting magnetic release-signal from a magnetic element to a magnetic detector such as a Hall-effect sensor or the like. The magnetic emitter in such a case may be the primary coil itself.

Alternatively, audio signals may be guided through dense elements, or low power microwaves along microwave wave guides for example.

13

An example of an active optical transmission-key **2140**" is shown in FIG. 2f representing a transmission-guard **2100**" according to another embodiment of the invention.

The transmission-guard **2100**" of this embodiment includes a transmission-lock **2120**" incorporated within an inductive power outlet **2200** and an active optical transmission-key **2140**" incorporated within secondary unit **2300**.

The active optical transmission-key **2140**" includes an optical emitter **2142**", configured to emit an optical release-signal S_R , and the transmission-lock **2120**" includes a switch **2122**" and an optical detector **2124**". The transmission-lock **2120**" is configured to close the switch **2122**" thereby connecting a primary coil **2220** to a driver **2230** when the optical detector **2124**" receives the release-signal S_R .

When the secondary unit **2300** is aligned with the inductive power outlet **2200**, the transmission-key **2140**" emits an optical release-signal S_R which is received by the optical detector **2124**" of the transmission-lock **2120**" and this closes the switch **2122**". Thus the inductive power outlet **2200**" is enabled to transfer power to the secondary coil **2320**.

It will be appreciated that a release signal S_R may be coded to provide a unique identifier. Coding may be by modulation of frequency, pulse frequency, amplitude or the like. The code may be used, for example, to identify the type or identity of the secondary unit for authentication. Other data may additionally be encoded into the release-signal. This data may include required power transmission parameters, billing information or other information associated with the use of the power outlet.

Although an optical active transmission-key **2140**" is described above, it will be appreciated that other active transmission-keys may emit other types of release-signals. For example, the secondary coil **2320** may be used to transmit a magnetic release-signal to a magnetic detector incorporated in the transmission-lock. This could be a Hall-effect sensor or the like or even the primary coil **2220** itself.

To actively emit a release-signal transmission-keys typically require a power source. In some cases, particularly where the secondary unit is incorporated into a portable electrical device, power may be provided by internal power cells with the secondary unit. Alternatively, power may be drawn from a power pulse transferred from the primary coil to the secondary coil.

In certain embodiments of the invention, the inductive power outlet transfers a periodic low energy power pulse, for example a pulse of a few milliseconds duration may be transmitted by the primary coil at a frequency of 1 hertz or so. When a secondary coil is brought into the vicinity of the primary coil the power may be transferred to the secondary coil and may be used to power an active transmission-key.

In other embodiments of the transmission-guard, a first transmission-lock (preferably a passive transmission-lock) associated with the secondary unit, releases a first transmission-lock thereby indicating the probable presence of a secondary coil. A low energy power pulse is then emitted by the primary coil to power an active second transmission-key which may release a second transmission-lock thereby connecting the primary coil to a driver.

Synchronous Rectifier

Reference is now made to FIG. 3a showing a circuit diagram of a typical full-wave rectifier **3100** of the prior art. The rectifier has two input terminals T_1 and T_2 and two output terminals T_3 and T_4 . When an alternating current source AC_{in} is wired to the two input terminals T_1 and T_2 , a direct current output DC_{out} may be drawn from the two output terminals T_3 and T_4 of the rectifier **3100**.

14

Four diodes D_{1-4} are arranged so that two diodes D_1 and D_2 form a first branch **3110** of a Graetz circuit and the other two diodes D_3 and D_4 form a second branch **3120** of the Graetz circuit. The anodes of two upstream diodes D_1 and D_3 are wired to the first output terminal T_3 and the cathodes of the two downstream diodes D_2 and D_4 are wired to the second output terminal T_4 . The cathode of the first upstream diode D_1 and the anode of first downstream diode D_2 are wired to the first input terminal T_1 and the cathode of the second upstream diode D_3 and the anode of second downstream diode D_4 are wired to the second input terminal T_2 .

When the polarity of the first input terminal T_1 is positive relative to the second input terminal T_2 , current flows through the first downstream diode D_2 and through the second upstream diode D_3 . When the polarity of the first input terminal T_1 is negative relative to the second input terminal T_2 , current flows through the second downstream diode D_4 and through the first upstream diode D_1 .

Diode bridge rectifiers, such as that shown in FIG. 3a, are used to produce an output with a fixed polarity that is independent of the polarity of the input. Such diode bridge rectifiers may be used in AC-to-DC power converters, for example. Optionally, the output is smoothed by a smoothing capacitor C.

It will be appreciated that power is lost from each diode with each reversal of polarity. In high frequency power converters, where the polarity of the input terminals T_1 and T_2 may oscillate at a frequencies of 100 kHz or more, such power losses may result in significant heating of the bridge circuit and its surrounding components, which may result in reduced reliability or failure.

Power loss may be reduced by replacing diodes with electronic switches, such as the Power MOSFETs shown in FIG. 3a, which have much lower associated power loss. FIG. 4a is a block diagram of one such synchronous full-wave rectifier **4200** in which the first downstream diode D_2 and the second downstream diode D_4 of the diode bridge of FIG. 3a have been replaced by two electronic switches M_2 and M_4 .

The electronic switches M_2 and M_4 are controlled by switching signals G_2 and G_4 which switch them between the ON and OFF states. The switching signal G_2 controlling the electronic switch M_2 must be synchronized to switch to the ON state whenever the polarity of the first input terminal T_1 is positive relative to the second input terminal T_2 . The switching signal G_4 controlling the electronic switch M_4 must be synchronized to switch to the ON state whenever polarity of the first input terminal T_1 is negative relative to the second input terminal T_2 .

Typically, this synchronization is achieved by drawing the first switching signal G_2 from the voltage of the second input terminal T_2 and drawing the second switching signal G_4 from the voltage of the first input terminal T_1 .

The above described synchronous full-wave rectifier **4200** in which two diodes are replaced by MOSFETs may reduce power loss from the rectifier by up to 50% as compared with the diode bridge rectifier **4100** of the prior art. Where further reduction in power loss is required it would be desirable to replace the remaining two diodes D_1 and D_3 with electronic switches. However, it is much more difficult to synchronize four electronic switches without inadvertently causing short circuits between either the input or output terminals.

FIG. 4b is a block diagram of a second synchronous full-wave rectifier **4300** in which all four diodes D_{1-4} of the diode bridge of FIG. 3a have been replaced by electronic switches M_{1-4} . In order to provide an output DC_{out} of constant polarity, the switching signals G_{1-4} need to be carefully controlled.

15

When the polarity of the first input terminal T_1 is positive relative to the polarity of the second input T_2 , the first upstream and second downstream electronic switches M_1 and M_4 must be switched to the OFF state and the first downstream and second upstream electronic switches M_2 and M_3 must be switched to the ON state. When the polarity of the first input terminal T_1 is negative relative to the polarity of the second input terminal T_2 , the first upstream and second downstream electronic switches M_1 and M_4 must be switched to the ON state and the electronic switches first downstream and second upstream electronic M_2 and M_3 must be switched to the OFF state.

Synchronization of the switching signals G_{1-4} , is complicated by an additional constraint. In order to prevent shorting across the output terminals, the upstream and downstream electronic switches along a common branch **4310**, **4320** must never be in the ON state at the same time. In practice, when both of the switching signals G_1 and G_2 controlling the two electronic switches M_1 and M_2 along the first branch **4310** are each drawn from one of the input terminals T_1 and T_2 , the two switches M_1 and M_2 are periodically both in their ON states. Because the switches M_1 and M_2 are adjacent along the first branch **4310** of the circuit, a short circuit is formed between the output terminals T_3 and T_4 . Similar shorting may occur along the second branch **4320** when the switching signals G_3 and G_4 which control the other two electronic switches M_3 and M_4 are each drawn from one of the input terminals T_1 and T_2 .

According to preferred embodiments of the invention, only the switching signals G_2 and G_4 for the downstream electronic switches M_2 and M_4 are drawn directly from the voltage at the input terminals T_1 and T_2 whilst the switching signals G_1 and G_3 for the upstream switches M_1 and M_3 are controlled independently. Preferably, the switching signals G_1 and G_3 are responsive to changes in the cathode current of switches M_1 and M_3 respectively.

FIG. **4c** shows an exemplary current-triggered synchro-rectifier **4330**, which may serve as an electronic switch M incorporated into a bridge synchro-rectifier **4300**. The current-triggered synchro-rectifier **4330** includes a Power MOSFET **4130**, such as that shown in FIG. **3b**, and a current monitor **4332**. The current monitor **4332** is wired to the drain terminal **4136** of the Power MOSFET **4130** and is configured to send a current-based gate signal G_i to the gate terminal **4138** of the Power MOSFET when the drain-current I_d exceeds a predetermined threshold I_{th} . Although in the above example the current-triggered synchro-rectifier **4330** includes an n-channel MOSFET **4130**, it will be appreciated that in other embodiments current-triggered synchro-rectifiers may incorporate p-channel MOSFETs.

In order to understand the functioning of the current-triggered synchro-rectifier **4330** consider the case where a sinusoidal alternating voltage is connected across the cathode **4334** and the anode **4336** terminals of the current-triggered synchro-rectifier **4330**. FIG. **4d** shows three graphs showing variations in 1) the voltage drop V_d from the cathode **4334** to the anode **4336**, 2) the drain-current I_d , and 3) the MOSFET state during one voltage cycle.

For the first half of the sinusoidal cycle the voltage drop V_d between the cathode **4334** and the anode **4336** is negative, thus the polarity of the cathode **4334** is negative relative to the anode **4336**. Consequently, no current flows through the drain-terminal **4136** and the MOSFET remains in the OFF state.

At the beginning of the second half of the sinusoidal cycle, the voltage drop V_d between the cathode **4334** and the anode **4336** increases above zero. The polarity of the cathode **4334**

16

becomes positive relative to the anode. **4336** so a small drain-current I_d begins to flow through the diode **4132**. This current is measured by the current monitor **4332**.

During the third quarter of the cycle, the voltage drop V_d between the cathode **4334** and the anode **4336** continues to rise. The current monitor **4332** measures an increasing drain-current I_d .

When the drain-current I_d exceeds the predetermined threshold I_{th} , the current-based gate signal G_i triggers the MOSFET **4130** to switch to the ON state.

As long as the MOSFET **4130** is in the ON state, current flows through the ohmic conductive path of the electronic switch **4131**. Consequently, the drain-current I_d varies in proportion to the voltage drop V_d .

During the last quarter of the cycle, the voltage drop V_d between the cathode **4334** and the anode **4336** decreases. The current monitor **4332** measures a decreasing drain-current I_d .

When the drain-current falls below the predetermined threshold I_{th} , the current-based gate signal G_i triggers the MOSFET **4130** to switch to the OFF state.

FIG. **4e** is a circuit diagram representing a synchronous full-wave bridge rectifier **4400** incorporated within an inductive power receiver according to a further embodiment of the invention. The electronic switches M_{1-4} are all MOSFET transformers having three terminals: a source terminal, a drain terminal and a gate terminal. The upstream MOSFETs M_1 and M_3 are both re-channel MOSFETs and their source terminals are both wired to the first output terminal T_3 of the rectifier. The downstream MOSFETs M_2 and M_4 are both p-channel MOSFETs and their source terminals are both wired to the second output terminal T_4 of the rectifier. The drain terminals of the first upstream MOSFET M_1 and the first downstream MOSFET M_2 are both wired to the first input terminal T_1 of the rectifier and the drain terminals of the second upstream MOSFET M_3 and the second downstream MOSFET M_4 are both wired to the second input terminal T_2 of the rectifier.

The input terminals T_1 and T_2 are wired to a secondary coil L_2 of a power transformer which is inductively coupled to a primary coil (not shown). The secondary coil L_2 provides an alternating current input to the two input terminals T_1 and T_2 .

The gate terminals of the downstream MOSFETs M_2 and M_4 are wired to the input terminals T_2 and T_1 via smoothing circuits **4420**, **4440** respectively. The switching signals G_2 and G_4 , are therefore in out of phase with each other.

The gate terminals of the upstream MOSFETs M_1 and M_3 receive switching signals G_1 and G_3 driven by their own drain-currents I_{d1} and I_{d3} . The drain current I_{d1} of the first upstream MOSFET M_1 is monitored by a first current transformer **4410**, in which a primary current monitor coil CT_{1P} transfers the current signal to a secondary current monitor CT_{2S} the output of which is rectified and relayed to a first input IN_1 of a driver **4450** which amplifies the signal before outputting a signal from a first output OUT_1 . This first output signal from the driver is then fed back to the first upstream MOSFET M_1 such that when the drain current I_{d1} exceeds a threshold value the MOSFET M_1 switches itself to the ON state. This produces a switching signal G_1 at the same frequency as the alternating current input AC_{in} .

Similarly the drain current I_{d3} of the second upstream MOSFET M_3 is monitored by a second current transformer **4430**, in which a primary current monitor coil CT_{2P} transfers the current signal to a secondary current monitor CT_{2S} the output of which is rectified and relayed to a second input IN_2 of the driver **4450** which amplifies the signal before outputting a signal from a second output OUT_2 . The second output signal from the driver is then fed back to the second upstream

17

MOSFET M_3 such that when the drain current I_{d2} exceeds a threshold value the MOSFET M_3 switches itself to the ON state. This produces a switching signal G_3 at the same frequency as the alternating current input AC_{in} .

Although in the example hereabove, current transformers **4410**, **4430** are used to monitor the drain-currents I_{d1} , I_{d2} , in alternative embodiments other current monitors such as ammeters, galvanometers, Hall effect sensors or the like may be preferred.

Heat Dissipation within Inductive Power Receivers

Reference is now made to FIG. **5a** showing a laptop computer **5300** drawing power from an inductive power outlet **5200** via an inductive power adapter **5100**, according to a further embodiment of the present invention. The adaptor is configured such that it can be safely handled by a user while it is operation.

The power adapter **5100** includes an inductive receiver **5120**, housed in a casing **5160** and a power connector **5140** for connecting to an electrical device, such as the computer **5300**. The inductive receiver **5120** includes a secondary inductor **5122** configured to couple with a primary inductor **5220** in the power outlet **5200**. Typically, the primary inductor **5220** is wired to a power source **5240** via a driver **5230**. The driver **5230** provides an oscillating driving voltage to the primary inductive coil **5220**.

Preferably, an alignment mechanism (not shown) is provided for aligning the secondary inductor **5122** to the primary core **5220**. The alignment mechanism may consist of a primary magnetic element in the inductive outlet configured to snag and/or engage a secondary magnetic element in the power adapter **5100**.

It will be appreciated that electrical components of power converters generate heat. There are a number of problems associated with the heat generated in an inductive receiver **5120**, particularly in systems running at high power above say 50W or 100W. Heat produces high temperatures which can reduce overall efficiency and may also reduce the reliability of components. Much design effort is typically required to overcome this problem, and other factors such as the dimensions of the system may be compromised as a result.

In practice, electrical components of the power adapter **5100** are selected which function at high temperatures. However, the maximum temperature of the casing **5160** is further constrained by the requirement that it is to be handled by the user. If the casing **5160** reaches high temperatures, above 50 degrees Celsius or so, a user may find handling the adapter to be unpleasant and may even be at risk of injury. In order to allow a user to comfortably and safely handle the adaptor **5100**, it is a particular feature of the present invention that a heat dissipation system for directing heat away from the hand grip **5162**.

The heat dissipation system may be better understood with reference to FIGS. **5b-d** showing an exemplary inductive power adapter **5100** according to another embodiment of the invention. FIG. **5b** shows an isometric projection, FIG. **5c** shows an exploded view and FIG. **5d** shows a cross-section through the same embodiment of the power adaptor **5100**.

The exemplary power adapter **5100** includes an inductive receiver **5120**, and a heat sink **5130** housed between a lower casing **5160L**, and an upper casing **5160U** and a power connector **5140** which can be wound around a hand grip **5162** for storage.

The inductive power receiver **5120** consists of a secondary inductive coil **5122** a ferromagnetic disk **5124** and a printed circuit board (PCB) **5126**. The heat sink **5130** of the exemplary embodiment consists of a metallic disk sandwiched between the inductive receiver **5120** and the upper casing

18

5160U. The ferromagnetic disk **5124** may serve as a flux guiding core to improve inductive coupling between the secondary inductive coil **5122** and a primary inductive coil **5220** (FIG. **1**) of an inductive power outlet **5200**.

When the power adapter **5100** is in operation, heat is generated by a number of components of the inductive receiver **5120**. An alternating current is induced in the secondary inductive coil **5122** therefore causing the coil wire to heat up. Furthermore hot spots are typically generated around certain electrical components typically provided on the PCB **5126**, such as rectifiers, diodes, MOSFETS, power regulators, LDOs, feedback transmitters or the like.

The heat sink **5130** is typically a thermal conductive material such as aluminum, copper or the like which serves to distribute heat more evenly around the inductive receiver **5120**. Preferably, thermal vias are provided through the PCB **5126** and thermal grease or a similar agent is used to improve thermal contact between the heat sink **5130**, PCB **5126**, ferromagnetic disk **5124** and secondary coil **5122**.

Air outlets **5132** are provided in the top **5161** of the upper casing **5160U** allowing hot air from inside the power adaptor to escape into the atmosphere. Air inlets **5134** are provided in the bottom **5165** and sides **5167** of the lower casing **5160L** and on the sides **5163** of the upper casing **5160U** allowing cool air to enter into the power adaptor from below. It is a particular feature of the exemplary embodiment that the outer diameter d of the heat sink is smaller the inner diameter D of the casing **5160** thus allowing air to circulate around the inductive receiver **5120**. Thus hot air heated by the inductive power receiver **5120** flows out of the adapter **5100** through the outlets **5132** and cool air from outside is drawn into the adapter **5100** through said air inlets **5134**. The hand grip **5162** may be additionally protected from heat by a barrier of thermal insulating material.

It is noted that the air outlets **5132** may allow dust to enter the power adapter **5100**. In some embodiments therefore a dust-guard is provided to prevent dust from entering the outlets **5132**. In the exemplary embodiment, the grip **5162** overhangs the outlets **5132** serving as a dust-guard to prevent dust from entering the adapter **5100** whilst in operation. When not in operation, the power connector **5140** may be wound around the hand grip **5162**, thereby providing further protection against dust.

In certain embodiments, the PCB **5126** includes a light emitting diode (not shown) used as a feedback transmitter for sending signals to an optical detector in the power outlet **5200** (FIG. **5a**). It will be appreciated that in such embodiments, it is necessary that a clear line-of-sight is maintained between the optical emitter and detector. To this end, in preferred embodiments an optical window, transparent to the wavelength of the wavelength of the optical transmission, is provided through the secondary inductive coil **5122**, ferrite disk **5124**, lower casing **5160L** and other layers between the PCB **5126** and the primary coil **5220** (FIG. **5a**).

Magnetic Flux Guidance

Referring now to FIGS. **5e** and **5f**, an inductive power receiver **5200** is shown including a secondary inductor **5220**, a magnetic flux guide **5260** and a PCB **5270**, according to a further embodiment of the invention. The secondary inductor **5220** is configured to receive power inductively from a primary inductor of an inductive power outlet (not shown). The magnetic flux guide **5260** is provided to direct magnetic flux from the primary inductor to the secondary inductor **5220** and to reduce flux leakage to the surroundings. The magnetic flux guide **5260** consists of a ferromagnetic core **5262** and a mag-

netic shield **5264**. The ferromagnetic core **5262** is provided to guide magnetic flux from an active primary inductor to the secondary inductor **5220**.

In preferred embodiments, the ferromagnetic core **5262** is constructed from amorphous ferromagnetic material, typically cut into wafers from a sheet approximately 20 microns thick or so. In one exemplary embodiment, the ferromagnetic core consists of two amorphous ferromagnetic wafers **5262a**, **5262b**. A first wafer **5262a** is adhered to the primary inductor **5220** by a first adhesive insulating layer **5265a**. A second wafer **5262b** is adhered to the first wafer **5262a** by a second adhesive insulating layer **5265b**. The two wafers **5262a**, **5262b** serve as a ferromagnetic core guiding magnetic flux from a primary inductor to the secondary inductor **5220**. It is a particular feature of preferred embodiments that the ferromagnetic wafers **5262a**, **5262b** each have a radial slit **5265a**, **5265b** to prevent the buildup of eddy currents within the wafer due to the oscillating magnetic field produced by the primary inductor. Where the wafer has a circular cross section, the slit may extend inwardly diametrically from the circumference.

The magnetic shield **5264** is provided to prevent flux leakage into the surroundings. Preferably, the magnetic shield **5264** is also fabricated from a sheet of thin amorphous ferromagnetic material and may be adhered to the PCB by a third adhesive insulating layer **5265c**.

It will be appreciated that a magnetic shield is of particular importance when the inductive receiver **5200** is mounted upon a conductive surface or a device containing conductive components. Thus, for example, when such an inductive power receiver **5200** is mounted upon an electrical device, such as a computer, mobile telephone or the like, the magnetic shield **5264** prevents magnetic flux from leaking into the metallic components of the electrical device and causing them to heat up.

Amorphous ferromagnetic sheets may have a thickness of around 20 microns. When laminated by a polymer laminate on both sides the overall thickness of the sheet is around 60 microns. Thus, in contradistinction to other ferrite elements used to guide magnetic flux in inductive systems, amorphous ferromagnetic materials may be used to fabricate an extremely thin magnetic guide **5260**. A thin magnetic guide **5260** in turn allows the inductive power receiver **5200** to be flexible and unobtrusive. It will be appreciated that these considerations are very important in the design and manufacture of device mounted inductive receivers. Various methods of fabricating magnetic guiding elements from amorphous ferromagnetic material include, inter alia: printing, stamping, cutting, amorphous ferromagnetic microwire cloth and the like.

Power Transmission at a Non-resonant Frequency

The strength of an induced voltage in the secondary inductor of an inductive couple varies according to the oscillating frequency of the electrical potential provided to the primary inductor. The induced voltage is strongest when the oscillating frequency equals the resonant frequency of the system. The resonant frequency f_R depends upon the inductance L and the capacitance C of the system according to the equation

$$f_R = \frac{1}{2\pi\sqrt{LC}}.$$

Known inductive power transfer systems typically transmit power at the resonant frequency of the inductive coupling. This can be difficult to maintain as the resonant frequency of

the system may fluctuate during power transmission, for example in response to changing environmental conditions or variations in alignment between primary and secondary coils.

Inductive transfer systems designed to transmit at resonance therefore require tuning mechanisms for maintaining transmission at the resonant frequency of the system. Tuning may be achieved by adjusting the driving frequency to seek resonance. For example, U.S. Pat. No. 6,825,620, titled "Inductively coupled ballast circuit" to Kuennen et al. describes a resonance seeking ballast circuit for inductively providing power to a load. The ballast circuit includes an oscillator, a driver, a switching circuit, a resonant tank circuit and a current sensing circuit. The current sensing circuit provides a current feedback signal to the oscillator that is representative of the current in the resonant tank circuit. The current feedback signal drives the frequency of the ballast circuit causing the ballast circuit to seek resonance. The ballast circuit preferably includes a current limit circuit that is inductively coupled to the resonant tank circuit. The current limit circuit disables the ballast circuit when the current in the ballast circuit exceeds a predetermined threshold or falls outside a predetermined range.

Alternatively, tuning may be achieved by adjusting the characteristics of the inductive system. For example, U.S. Pat. No. 7,212,414, titled "Adaptive inductive power supply" to Baarman describes a contactless power supply which has a dynamically configurable tank circuit powered by an inverter. The contactless power supply is inductively coupled to one or more loads. The inverter is connected to a DC power source. When loads are added or removed from the system, the contactless power supply is capable of modifying the resonant frequency of the tank circuit, the inverter frequency, the inverter duty cycle or the rail voltage of the DC power source.

Tuning mechanisms such as those described above are necessary in order to maintain transmission at resonance because resonant transmission is highly sensitive. At resonance small variations to the system result in large changes to the power transferred. A further problem associated with resonant transmission is the high transmission voltages involved. At high operating voltages, the capacitors and transistors in the circuit need to be relatively large.

Reference is now made to FIG. 6a showing a block diagram of the main elements of an inductive power transfer system **6100** adapted to transmit power at a non-resonant frequency. The inductive power transfer system **6100** consists of an inductive power outlet **6200** configured to provide power to a remote secondary unit **6300** according to another embodiment of the invention. The inductive power outlet **6200** includes a primary inductive coil **6220** wired to a power source **6240** via a driver **6230**. The driver **6230** is configured to provide an oscillating driving voltage to the primary inductive coil **6220**.

The secondary unit **6300** includes a secondary inductive coil **6320**, wired to an electric load **6340**, which is inductively coupled to the primary inductive coil **6220**. The electric load **6340** draws power from the power source **6240**. A communication channel **6120** may be provided between a transmitter **6122** associated with the secondary unit **6300** and a receiver **6124** associated with the inductive power outlet **6200**. The communication channel **6120** may provide feedback signals S and the like to the driver **6230**.

In some embodiments, a voltage peak detector **6140** is provided to detect large increases in the transmission voltage. As will be described below the peak detector **6140** may be used to detect the removal of the secondary unit **6200**, the introduction of power drains, short circuits or the like.

21

FIG. 6b is a graph showing how the amplitude of the operational voltage varies according to the transmission frequency. It is noted that the voltage is at its highest when the transmission frequency is equal to the resonant frequency f_R of the system, this maximum amplitude is known as the resonance peak 2. It is further noted that the slope of the graph is steepest in the regions 4a, 4b to either side of the resonance peak 2. Thus in inductive transfer systems, which operate at or around resonance, a small variation in frequency results in a large change in induced voltage. Similarly, a small change in the resonant frequency of the system results in a large change in the induced voltage. For this reason prior art inductive transfer systems are typically very sensitive to small fluctuations in environmental conditions or variations in alignment between the induction coils.

It is a particular feature of embodiments of the current invention that the driver 6230 (FIG. 6a) is configured and operable to transmit a driving voltage which oscillates at a transmission frequency which is substantially different from the resonant frequency of the inductive couple. Preferably the transmission frequency is selected to lie within one of the near-linear regions 6, 8 where the slope of the frequency-amplitude graph is less steep.

One advantage of this embodiment of the present invention may be demonstrated with reference now to FIG. 6c. A schematic diagram is shown representing a laptop computer 6340 drawing power from an inductive power outlet 6200 via a secondary power receiving unit 6300. The power receiving unit 6300 includes a secondary inductive coil 6320 which is aligned to a primary inductive coil 6220 in the inductive power outlet 6200. Any lateral displacement of the secondary power receiving unit 6300 changes the alignment between the secondary inductive coil 6320 to the primary inductive coil 6220. As a result of the changing alignment, the combined inductance of the coil pair changes which in turn changes the resonant frequency of the system.

If the inductive power outlet 6200 transmits power at the resonant frequency of the system, even a small lateral movement would reduce significantly the amplitude of the induced voltage. In contradistinction, according to embodiments of the present invention, the inductive power outlet 6200 transmits power at a frequency in one of the regions 6, 8 to either side of the resonance peak 2 (FIG. 6b) where the slope of the resonance graph is much shallower. Consequently, the system has a much larger tolerance of variations such as lateral movement.

Another advantage of non-resonant transmission is that the transmission frequency may be used to regulate power transfer. In known inductive power transfer systems, power is typically regulated by altering the duty cycle of the transmission voltage provided by the driver. Thus, it will be appreciated that when the transmission frequency is not equal to the resonance frequency of the system, the driver 6230 may be configured to adjust the transmission frequency in order to regulate the power transfer.

Referring back to FIG. 6b, the frequency of transmission is selected to be in the approximately linear region 8 of the curve between a lower frequency value of f_L , and an upper frequency value of f_U . A transmission frequency f_t , higher than the resonant frequency f_R of the system, produces an induced voltage of V_t . The induced voltage can be increased by reducing the transmission frequency and can be reduced by increasing the transmission frequency. For example, an increase in transmission frequency of δf produces a decrease in induced voltage of δV .

In some embodiments, a communication channel 6120 (FIG. 6a) is provided between the secondary unit 6300 and

22

the inductive power outlet 6200. Such a communication channel 6120, may be used to communicate required operating parameters which, for example, may indicate the transmission frequency required by the electric load 6340 to the driver 6230.

Various transmitters 6122 and receivers 6124 may be used with the communication channel 6120. Where, as is often the case for inductive systems, the primary and secondary coils 6220, 6320 are galvanically isolated for example, optocouplers may have a light emitting diode serving as a transmitter which sends encoded optical signals over short distances to a photo-transistor which serves as a receiver. Optocouplers typically need to be aligned such that there is a line-of-sight between transmitter and receiver. In systems where alignment between the transmitter and receiver may be difficult to achieve, optocoupling may be inappropriate and alternative systems may be preferred such as ultrasonic signals transmitted by piezoelectric elements or radio signals such as Bluetooth, WiFi and the like. Alternatively the primary and secondary coils 6220, 6320 may themselves serve as the transmitter 6122 and receiver 6124.

In certain embodiments, an optical transmitter, such as a light emitting diode (LED) for example, is incorporated within the secondary unit 6300 and is configured and operable to transmit electromagnetic radiation of a type and intensity capable of penetrating the casings of both the secondary unit 6300, and the power outlet 6200. An optical receiver, such as a photodiode, a phototransistor, a light dependent resistors of the like, is incorporated within the power outlet 6200 for receiving the electromagnetic radiation.

The communication channel 6120 may further provide a feedback signal during power transmission. The feedback transmission may communicate required or monitored operating parameters of the electric load 6240 such as: required operating voltage, current, temperature or power for the electric load 6240; the measured voltage, current, temperature or power supplied to the electric load 6240 during operation; the measured voltage, current, temperature or power received by the electric load 6240 during operation and the like.

In some embodiments, a microcontroller in the driver 6230 may use such feedback parameters to calculate the required transmission frequency and to adjust the driver accordingly. Alternatively, simple feedback signals may be provided indicating whether more or less power is required.

One example of a power regulation method using simple feedback signals is shown in the flowchart of FIG. 6d. The method involves the following steps: (a) The driver 6230 provides an oscillating voltage at a transmission frequency f_t , which is higher than the resonant frequency f_R of the system; (b) A secondary voltage is induced in the secondary coil 6320; (c) A power monitor in the secondary unit 6300, monitors the power received by the electric load 6340; (d) If the power received by the electric load 6340 lies within a predetermined range then no action is taken. If the power received by the electric load 6340 is below the predetermined range, then a feedback signal of a first type S_a is sent to the driver. If the power received by the electric load 6340 is above the predetermined range, then a feedback signal of a second type S_b is sent to the driver; (e) A feedback signal is received by the driver 6230; (f) If the received feedback signal is of the first type S_a , then the transmission frequency is increased by an incremental value $+\delta f_1$. If the received feedback signal is of the second type S_b , then the transmission frequency is decreased by an incremental value $-\delta f_2$.

It is noted that by using the power regulation method described above, when the power received by the load is too high, a series of feedback signals of the first type S_a will be

23

transmitted until the power is reduced into the acceptable range. Likewise when the power received by the load is too low, a series of feedback signals of the second type S_b will be transmitted until the power is increased into the acceptable range. It is noted that the positive incremental value δf_1 may be greater than, less than or equal to the negative incremental value δf_2 .

Alternatively, other power regulation methods using frequency adjustment may be used. For example, in alternative embodiments, the operating parameters of the electric load may be monitored and their values may be transmitted to the power outlet via the communications channel **6120**. A processor in the power outlet may then calculate the required transmission frequency directly.

The method described hereabove, refers to a non-resonant transmission frequency lying within the linear region **8** (FIG. **6b**), higher than the resonant peak **2**. It will be appreciated however that in alternative embodiments frequency controlled power regulation may be achieved when the transmission frequency lies in the lower linear region **6** of the resonance curve. Nevertheless, as explained below, for certain embodiments, the selection of transmission frequencies in the higher linear **8** may be preferred.

As described above, the resonant frequency f_R of an inductive couple is given by the formula

$$f_R = \frac{1}{2\pi\sqrt{LC}},$$

where L is the inductance of the system and C is the capacitance of the system. Thus any decrease in either the inductance L or the capacitance C of the system thereby increases its resonant frequency.

In inductive power outlets transmitting at frequencies above the normal resonant frequency of the system, an increase in resonant frequency of the system causes a large increase in the transmission voltage. In preferred embodiments, a peak detector **6140** (FIG. **1**) is provided to monitor the transmission voltage of the power outlet **6200** and is configured to detect large increases in the transmission voltage indicating an increase in resonant frequency. Such increases in transmission voltage may be indicative of power drains, short circuits, removal of the secondary unit or the like.

As an example of the use of a peak detector reference is again made to FIG. **6c**. It will be appreciated that in a desktop environment, conductive bodies such as a paper clip, metal rule, the metal casing a stapler, a hole-punch or any metallic objects may be introduced between the inductive power outlet **6200** and the secondary power receiving unit **6300**. The oscillating magnetic field produced by the primary coil **6220** would then produce eddy currents in the conductive body heating it and thereby draining power from the primary coil **6220**. Such a power drain may be wasteful and/or dangerous.

Power drains such as described above reduce the inductance L of the system. The inductance L may also be reduced by the removal of the secondary coil **6220**, a short circuit or the like. A peak detector **6140**, wired to the inductive power outlet, would detect any of these scenarios as a large increase in transmission voltage. Preferably, the power transfer system may be further configured to shut down, issue a warning or otherwise protect the user and the system in the event that the peak detector **6140** detects such an increase in transmission voltage.

24

FIG. **6e** is a circuit diagram of an inductive power outlet **6200** and a secondary unit **6300**. The secondary unit **6300** comprises a secondary coil **6320** wired to an electric load **6340** via a rectifier **6330**.

The inductive power outlet **6200** comprises a primary coil **6220** driven by a half-bridge converter **6230** connected to a power source **6240**. The half-bridge converter **6230** is configured to drive the primary coil **6220** at a frequency higher than the resonant frequency of the system and a peak detector **6140** is configured to detect increases in the transmission voltage.

Although only a half-bridge converter is represented in FIG. **6e**, it is noted that other possible driving circuits include: a DC-to-DC converter, an AC-to-DC converter, an AC-to-AC converter, a flyback transformer, a full-bridge converter, a flyback converter or a forward converter for example.

Thus, by using a transmission voltage oscillating at a frequency different from the resonant frequency of the system, the inductive transfer system has a higher tolerance to environmental fluctuations and variations in inductive coil alignment than other transfer systems and the frequency may be used to regulate power transfer. Moreover, when the transmission frequency is higher than the resonant frequency of the system, a peak detector may be used to indicate hazards.

Inductive Communication Channel

U.S. Pat. No. 5,455,466 titled, "Inductive coupling system for power and data transfer" to Terry J. Parks and David S. Register describes a system for inductively coupling power and data to a portable electronic device. The portable device, such as a personal digital assistant (PDA), is powered or recharged via an inductive link between the device and a support unit. The same inductive link is also used to transfer data signals between the device and a second electronic device, such as a conventional desktop computer. The support unit includes a primary winding of a transformer, a power amplifier and a modulator. The portable device includes a secondary winding connected in parallel with the input of a rectifier, the output of which is connected to a battery charging circuit, and to a modem, which is further connected to the device microprocessor. Placement of the device on the support unit affects the inductive coupling when the primary and secondary windings are in proximity to one another. Parks' system is thus directed to providing a data channel for synchronizing two data storage devices for example a PDA and a computer.

In Parks' system data transfer from the primary winding to the secondary winding may be provided by modulating the power signal. This requires a separate data signal to be transmitted by the secondary winding which is induced in the primary winding. Power transmission must therefore be interrupted in order to transmit data signals from the secondary winding to the primary winding. As a result, Parks' system does not offer any solution to providing a feedback signal for the regulation of uninterrupted inductive power transfer to an electric load.

Reference is now made to FIG. **7a** showing a block diagram of the main elements of an inductive power transfer system **7100** consisting of an inductive power outlet **7200** configured to provide power to a remote secondary unit **7300**. The inductive power transfer system **7100** includes an inductive communication channel **7120** according to a further embodiment of the present invention. The communication channel **7120** is configured to produce an output signal S_{out} in the power outlet **7200** when an input signal S_{in} is provided by the secondary unit **7300** without interrupting the inductive power transfer from the outlet **7200** to the secondary unit **7300**.

25

The inductive power outlet **7200** includes a primary inductive coil **7220** wired to a power source **7240** via a driver **7230**. The driver **7230** is configured to provide an oscillating driving voltage to the primary inductive coil **7220**, typically at a voltage transmission frequency f_t which is higher than the resonant frequency f_R of the system.

The secondary unit **7300** includes a secondary inductive coil **7320**, wired to an electric load **7340**, which is inductively coupled to the primary inductive coil **7220**. The electric load **7340** draws power from the power source **7240**. Where the electric load **7340** requires a direct current supply, for example a charging device for an electrochemical cell or the like, a rectifier **7330** may be provided to rectify the alternating current signal induced in the secondary coil **7320**.

An inductive communication channel **7120** is provided for transferring signals from the secondary inductive coil **7320** to the primary inductive coil **7220** concurrently with uninterrupted inductive power transfer from the primary inductive coil **7220** to the secondary inductive coil **7320**. The communication channel **7120** may provide feedback signals to the driver **7230**.

The inductive communication channel **7120** includes a transmission circuit **7122** and a receiving circuit **7124**. The transmission circuit **7122** is wired to the secondary coil **7320**, optionally via a rectifier **7330**, and the receiving circuit **7124** is wired to the primary coil **7220**.

The signal transmission circuit **7122** includes at least one electrical element **7126**, selected such that when it is connected to the secondary coil **7320**, the resonant frequency f_R of the system increases. The transmission circuit **7122** is configured to selectively connect the electrical element **7126** to the secondary coil **7320**.

As known, the resonant frequency f_R of an inductive couple is given by the formula

$$f_R = \frac{1}{2\pi\sqrt{LC}},$$

where L is the inductance of the system and C is the capacitance of the system. Thus any decrease in either the inductance L or the capacitance C increases the resonant frequency of the system. The electrical element **7126** may be a low resistance for example, typically the resistance of the electrical element **7126** is under 50 ohms and preferably about 1 ohm.

The signal receiving circuit **7124** may include a voltage peak detector **7128** configured to detect large increases in the transmission voltage. In systems where the voltage transmission frequency f_t is higher than the resonant frequency f_R of the system, such large increases in transmission voltage may be caused by an increase in the resonant frequency f_R thereby indicating that the electrical element **7126** has been connected to the secondary coil **7320**. Thus the transmission circuit **7122** may be used to send a signal pulse to the receiving circuit **7124** and a coded signal may be constructed from such pulses.

According to some embodiments, the transmission circuit **7122** may also include a modulator (not shown) for modulating a bit-rate signal with the input signal S_{in} . The electrical element **7126** may then be connected to the secondary inductive coil **7320** according to the modulated signal. The receiving circuit **7124** may include a demodulator (not shown) for demodulating the modulated signal. For example the voltage peak detector **7128** may be connected to a correlator for

26

cross-correlating the amplitude of the primary voltage with the bit-rate signal thereby producing the output signal S_{out} .

In other embodiments, a plurality of electrical elements **7126** may be provided which may be selectively connected to induce a plurality of voltage peaks of varying sizes in the amplitude of the primary voltage. The size of the voltage peak detected by the peak detector **7128** may be used to transfer multiple signals.

FIG. **7b** is a graph showing how the amplitude of the operational voltage varies according to the transmission frequency. It is noted that the voltage is at its highest when the transmission frequency is equal to the resonant frequency f_R of the system, this maximum amplitude is known as the resonance peak **2**. If the resonant frequency f_R of the system increases, a new resonance peak **2'** is produced.

According to an exemplary embodiment of the invention, an inductive power transfer system **7100** operates at a given transmission frequency f_t which is higher than the resonant frequency f_R of the system. The normal operating voltage V_t is monitored by the voltage peak detector **7128**. When the electric element **7126** is connected to the secondary inductive coil **7320** the resonant frequency of the system increases. Therefore, the operating voltage increases to a higher value V'_t . This increase is detected by the voltage peak detector **7128**.

The present invention allows data signals to be transferred from the secondary coil **7320** to the primary coil **7220** concurrently with inductive transfer of power from the primary coil **7220** to the secondary coil **7320**. Consequently, the signal transfer system may be used to provide feedback signals for real time power regulation. This is in contradistinction to prior art inductive signal transfer systems, such as the system described in U.S. Pat. No. 5,455,466 titled, "Inductive coupling system for power and data transfer" to Terry J. Parks and David S. Register, in which a separate data signal is supplied to the secondary inductive coil such that a voltage is induced in the primary coil.

FIG. **7c** shows an exemplary circuit diagram of an inductive power outlet **7200** and a secondary unit **7300**, according to another embodiment of the invention. An inductive feedback channel **7120** is provided for transferring signals between the coils concurrently with uninterrupted inductive power transfer.

The inductive power outlet **7200** comprises a primary coil **7220** driven by a half-bridge converter **7230** connected to a power source **7240**. The half-bridge converter **7230** is configured to drive the primary coil **7220** at a frequency higher than the resonant frequency of the system. The secondary unit **7300** comprises a secondary coil **7320** wired to the input terminals T_1 , T_2 of a rectifier **7330**, and an electric load **7340** wired to the output terminals T_3 , T_4 of the rectifier **7330**.

Although only a half-bridge converter **7230** is represented in the inductive power outlet **7200** of FIG. **7c**, it is noted that other driving circuits could be used. These include: a DC-to-DC converter, an AC-to-DC converter, an AC-to-AC converter, a flyback transformer, a full-bridge converter, a fly-back converter or a forward converter for example.

The inductive feedback channel **7120** comprises a transmission circuit **7122**, in the secondary unit **7300** and a receiving circuit **7124** in the inductive power outlet **7200**. The transmission circuit **7122** comprises an electrical resistor **7126** connected to the rectifier **7330** via a power MOSFET switch **7125**. A modulator **7123** may provide an input signal S_{in} to the power MOSFET **7125**.

It is noted that in this embodiment the transmission circuit **7122** is wired to one input terminal T_1 and one output terminal T_3 of the rectifier **7330**. This configuration is particularly

27

advantageous as, even when the transmission circuit **7122** is connected, the resistor **7126** only draws power from the system during one half of the AC cycle, thereby significantly reducing power loss.

The receiving circuit **7124** includes a voltage peak detector **7128** that is configured to detect increases in the transmission voltage, and a demodulator **7129** for producing an output signal S_{out} .

With reference now to FIG. **7d**, a flowchart is presented showing the main steps in a method for transferring a signal from the secondary inductive coil to a primary inductive coil of an inductive power transfer system. The method includes the following steps:

Step (a)—connecting the primary inductive coil to a voltage monitor for monitoring the amplitude of a primary voltage across the primary coil;

Step (b)—connecting the secondary inductive coil to a transmission circuit for connecting an electric element to the secondary inductive coil thereby increasing the resonant frequency of the inductive power transfer system;

Step (c)—providing an oscillating voltage to the primary inductive coil at an initial transmission frequency higher than the resonant frequency thereby inducing a voltage in the secondary inductive coil;

Step (d)—using the transmission circuit to modulate a bit-rate signal with the input signal to create a modulated signal and connecting the electrical element to the secondary inductive coil intermittently according to the modulated signal;

Step (e)—using the voltage monitor to cross-correlate the amplitude of the primary voltage with the bit-rate signal for producing an output signal.

The inductive feedback channel **7120** may be used for transferring data, such as data pertaining to any or all of the following: the required operating voltage, current, temperature or power for the electric load **7240**; the measured voltage, current, temperature or power supplied to the electric load **7240** during operation; the measured voltage, current, temperature or power received by the electric load **7240** during operation and the like; identification data for the user, electronic device and such like; a release signal of a transmission-key for releasing a transmission-lock.

Therefore, the inductive communication channel may be used to transfer a feedback signal from the secondary inductive coil to the primary inductive coil for regulating power transfer across an inductive power coupling.

For example the system may be configured to transfer two signals with the driver being configured to decrease the transmission power when a first signal is received, and to increase the transmission power when a second signal is received.

Power may be regulated by altering the duty cycle of the transmission voltage provided by the driver. Furthermore, the driver **7230** may be configured to adjust the transmission frequency in order to regulate the power transfer, as described hereinabove. Accordingly, the driver may be configured to adjust the transmission frequency in response to feedback signals. The transmission frequency may be increased when the first signal is received thereby decreasing the operating voltage, and the transmission frequency may be decreased when the second signal is received, thereby increasing the operating voltage.

Thus a communication channel is provided for regulating power transfer and/or for transmitting data signals from the secondary coil to the primary coil of an inductive couple while power is being transferred.

It will be apparent from the above description that various embodiment of the present invention disclose significant

28

advantages enabling the efficient, safe and unobtrusive inductive transfer of power. It is further noted that, in combination, these advantages allow an inductive power transmission system to become a practical tool suitable for a variety of applications.

The scope of the present invention is defined by the appended claims and includes both combinations and sub combinations of the various features described hereinabove as well as variations and modifications thereof, which would occur to persons skilled in the art upon reading the foregoing description.

In the claims, the word “comprise”, and variations thereof such as “comprises”, “comprising” and the like indicate that the components listed are included, but not generally to the exclusion of other components.

While exemplary embodiments are described above, it is not intended that these embodiments describe all possible forms of the invention. Rather, the words used in the specification are words of description rather than limitation, and it is understood that various changes may be made without departing from the spirit and scope of the invention. Additionally, the features of various implementing embodiments may be combined to form further embodiments of the invention.

What is claimed is:

1. An inductive power outlet operable to transfer power to an inductive power receiver, said inductive power outlet comprising:

a platform for supporting said inductive power receiver; at least one primary inductive coil embedded in said platform;

an alignment mechanism configured to facilitate alignment between said primary inductive outlet and said inductive power receiver such that an inductive couple is formed between said primary inductive coil and a secondary inductive coil of said inductive power receiver, said inductive couple having a characteristic resonant frequency; and

a driving circuit wired to said primary inductive coil, said driving circuit comprising a switching unit configured and operable to provide an oscillating driving voltage across said primary inductive coil such that a secondary voltage is induced in the secondary inductive coil; wherein said driving circuit is configured and operable to produce said oscillating driving voltage at a transmission frequency substantially different from said characteristic resonant frequency of said inductive couple.

2. The inductive power outlet of claim 1 said inductive power outlet comprising a signal detector adapted to detect a first signal and a second signal, and said driver is configured to:

increase said transmission frequency when said first signal is detected by the detector, and decrease said transmission frequency when said second signal is detected by the detector.

3. The inductive power outlet of claim 1 said driver being configured to adjust said transmission frequency in response to feedback signals.

4. The inductive power outlet of claim 3 wherein said feedback signals carry data pertaining to the operational parameters of said electric load.

5. The inductive power outlet of claim 4 wherein said operational parameters are selected from the group consisting of:

required operating voltage for said electric load; required operating current for said electric load; required operating temperature for said electric load; required operating power for said electric load;

29

measured operating voltage for said electric load;
 measured operating current for said electric load;
 measured operating temperature for said electric load;
 measured operating power for said electric load;
 power delivered to said primary inductive coil;
 power received by said secondary inductive coil, and
 a user identification code.

6. The inductive power outlet of claim 2 wherein said detector is selected from the list comprising optical detectors, radio receivers, audio detectors and voltage peak detectors.

7. The inductive power outlet of claim 1 wherein said driver further comprises a voltage monitor for monitoring the amplitude of a primary voltage across said primary coil.

8. The inductive power outlet of claim 7 wherein said voltage monitor is configured to detect significant increases in primary voltage.

9. The inductive power outlet of claim 1 comprising a power converter selected from the group comprising: a transformer, a DC-to-DC converter, an AC-to-DC converter, an AC-to-AC converter, a flyback transformer, a flyback converter, a full-bridge converter, a half-bridge converter and a forward converter.

10. The inductive power outlet of claim 1 incorporated into at least one application selected from a group consisting of: inductive chargers, inductive power adaptors, power tools, kitchen appliances, bathroom appliances, computers, media players, office equipment, implanted devices, pace makers, trackers and RFID tags.

11. The inductive power outlet of claim 1 wherein said alignment mechanism comprises a first magnetic element configured to engage a second magnetic element associated with the power receiver.

30

12. The inductive power outlet of claim 1 wherein said alignment mechanism comprises an audible indication.

13. The inductive power outlet of claim 1 wherein said alignment mechanism comprises a visual indication.

14. The inductive power outlet of claim 1 wherein said alignment mechanism comprises a tactile indication.

15. A method for transferring power from an inductive power outlet to an inductive power receiver, said method comprising:

providing at least one primary inductive coil embedded in a platform;

forming an inductive couple between said primary inductive coil and a secondary inductive coil of said inductive power receiver, said inductive couple having a characteristic resonant frequency; and

providing an oscillating driving voltage across said primary inductive coil such that a secondary voltage is induced in the secondary inductive coil, wherein said oscillating driving voltage has a transmission frequency substantially different from said characteristic resonant frequency of said inductive couple.

16. The method of claim 15 further comprising increasing said transmission frequency by an incremental value when a signal of a first type is detected from said inductive power receiver.

17. The method of claim 15 further comprising decreasing said transmission frequency by an incremental value when a signal of a second type is detected from said inductive power receiver.

* * * * *