



US010142659B2

(12) **United States Patent**
Norkin et al.

(10) **Patent No.:** **US 10,142,659 B2**

(45) **Date of Patent:** ***Nov. 27, 2018**

(54) **DEBLOCKING FILTERING**

(56) **References Cited**

(71) Applicant: **Telefonaktiebolaget L M Ericsson**
(publ), Stockholm (SE)

U.S. PATENT DOCUMENTS

(72) Inventors: **Andrey Norkin**, Solna (SE); **Kenneth Andersson**, Gavle (SE); **Rickard Sjöberg**, Stockholm (SE)

6,167,164 A 12/2000 Lee
2004/0101059 A1 5/2004 Joch et al.
(Continued)

FOREIGN PATENT DOCUMENTS

(73) Assignee: **TELEFONAKTIEBOLAGET LM ERICSSON (PUBL)**, Stockholm (SE)

CN 101951519 A 1/2011
WO 02096117 A1 11/2002
(Continued)

(*) Notice: Subject to any disclaimer, the term of this patent is extended or adjusted under 35 U.S.C. 154(b) by 0 days.

This patent is subject to a terminal disclaimer.

OTHER PUBLICATIONS

Chun-Lung Hsu; Yu-Sheng Huang, "A Fast-Deblocking Boundary-strength Based Architecture Design of Deblocking Filter in H.264/AVC Applications", Journal of Signal Processing Systems ; for Signal, Image, and Video Technology (formerly the Journal of VLSI Signal Processing Systems for Signal, Image, and Video Technology), Nov. 20, 2007, Springer US, Boston, ISSN 1939-8115; whole document.

(Continued)

(21) Appl. No.: **15/639,229**

(22) Filed: **Jun. 30, 2017**

(65) **Prior Publication Data**

US 2017/0302967 A1 Oct. 19, 2017

Related U.S. Application Data

(63) Continuation of application No. 15/008,013, filed on Jan. 27, 2016, now Pat. No. 9,743,115, which is a
(Continued)

(51) **Int. Cl.**
H04N 7/12 (2006.01)
H04N 19/86 (2014.01)
(Continued)

(52) **U.S. Cl.**
CPC **H04N 19/865** (2014.11); **H04N 19/117**
(2014.11); **H04N 19/14** (2014.11);
(Continued)

(58) **Field of Classification Search**
CPC H04N 19/865; H04N 19/176
(Continued)


Primary Examiner — Richard T Torrente

(74) *Attorney, Agent, or Firm* — Rothwell, Figg, Ernst & Manbeck, p.c.

(57) **ABSTRACT**

Blocking artifacts at a block boundary between a block and a neighboring block in a video frame are reduced by calculating an offset based on pixel values of pixels in a line of pixels in the block and based on pixel values of pixels in a corresponding line of pixels in the neighboring block. The offset is added to the pixel value of the pixel closest to the block boundary in the line of pixels and is subtracted from the pixel value of the pixel closest to the block boundary in the corresponding line of pixels. The resulting deblocking filter has good low-pass characteristics and is efficient for reducing blocking artifact.

18 Claims, 7 Drawing Sheets



INTEL-1001
10,142,659

Related U.S. Application Data

continuation of application No. 13/955,448, filed on Jul. 31, 2013, now Pat. No. 9,407,912, which is a continuation of application No. 13/583,437, filed as application No. PCT/SE2011/051199 on Oct. 6, 2011, now Pat. No. 8,526,509.

- (60) Provisional application No. 61/432,751, filed on Jan. 14, 2011.

(51) **Int. Cl.**

H04N 19/176 (2014.01)
H04N 19/61 (2014.01)
H04N 19/117 (2014.01)
H04N 19/14 (2014.01)
H04N 19/82 (2014.01)
H04N 19/80 (2014.01)
H04N 19/182 (2014.01)

(52) **U.S. Cl.**

CPC *H04N 19/176* (2014.11); *H04N 19/182* (2014.11); *H04N 19/61* (2014.11); *H04N 19/80* (2014.11); *H04N 19/82* (2014.11); *H04N 19/86* (2014.11)

(58) **Field of Classification Search**

USPC 375/240.25
 See application file for complete search history.

(56) **References Cited**

U.S. PATENT DOCUMENTS

2005/0147319 A1 7/2005 Deshpande et al.
 2006/0078048 A1 4/2006 Bjontegaard
 2008/0117980 A1 5/2008 Hung et al.
 2008/0123750 A1 5/2008 Bronstein et al.
 2011/0194614 A1 8/2011 Norkin et al.

FOREIGN PATENT DOCUMENTS

WO 2005117447 A2 12/2005
 WO 2010080645 A2 7/2010
 WO 2011080645 A1 7/2011
 WO 2011096869 A1 8/2011

OTHER PUBLICATIONS

Ugur, K et al, "High Performance, Low Complexity Video Coding and the Emerging HEVC Standard", In: IEEE Transactions on Circuits and Systems for Video Technology, vol. 20 Issue:12, On pp. 1688-1697, ISSN: 1051-8215, Digital Object Identifier: 10.1109/TCSVT.2010.2092613, Date of Publication: Nov. 18, 2010; whole document.

Norkin, A., et al., "Development of HEVC deblocking filter", 4th JCT-VC Meeting, 95, MPEG Meeting; Jan. 20-28, 2011; Daegu; (Joint Collaborative Team on Video Coding of ISO/IEC JTC1/SC29/WG11 and ITU-T SG.16); URL:<http://wftp3.itu.int/av-arch/jctvc-site/>, No. JCTVC-D377, Jan. 16, 2011, 4 pages, XP030008416.

Anonymous; "Test Model under Consideration", 2nd JCT-VC Meeting; Jul. 21-28, 2010; Geneva; (Joint Collaborative Team on Video Coding of ISO/IEC JTC1/SC29/WG11 and ITU-T SG. 16); URL:<http://wftp3.itu.int/av-arch/jctvc-site/>, No. JCTVC-B205, Jul. 28, 2010, pp. 1-152, XP030007704.

Supplementary European Search Report dated Nov. 8, 2013, in corresponding European application No. EP 11 85 5586, 10 pages. Office Action issued in corresponding Japanese Application No. JP 2013-549384, dated Dec. 20, 2013, 2 pages.

Office Action (English translation only) dated Jun. 25, 2015 in corresponding Taiwan application No. 101101515, 3 pages.

Office Action (English translation only) dated Aug. 24, 2015 in corresponding Korean Application No. 10-2013-7020997, 6 pages. First Office Action issued in related Chinese Patent Application No. 201180064761.8, dated Feb. 3, 2016, 6 pages.

Office Action (English translation only) dated Jul. 31, 2015 in corresponding Japanese application No. 2014-094843, 2 pages.




Fig. 2A

Fig. 1




Fig. 2B







Fig. 5

Fig. 6






Fig. 14




Fig. 11




Fig. 12




Fig. 13

DEBLOCKING FILTERING

CROSS-REFERENCE TO RELATED APPLICATIONS

This application is a continuation of U.S. application Ser. No. 15/008,013, filed on Jan. 27, 2016 (published as US 20160142739), which is a continuation of U.S. application Ser. No. 13/955,448, filed on Jul. 31, 2013 (now U.S. Pat. No. 9,407,912), which is a continuation of U.S. application Ser. No. 13/583,437, having a § 371 date of Sep. 7, 2012 (now U.S. Pat. No. 8,526,509), which is a 35 U.S.C. § 371 National Phase Entry Application from PCT/SE2011/051199, filed Oct. 6, 2011, which claims the benefit of U.S. Provisional App. No. 61/432,751, filed Jan. 14, 2011. The above identified applications and publications are incorporated by reference herein in their entirety.

TECHNICAL FIELD

The present description relates to deblocking filtering for reducing blocking artifacts at block boundaries.

BACKGROUND

Deblocking filters are used in the video coding standards in order to combat blocking artifacts. The blocking artifacts arise because the original video is split into blocks which are processed relatively independently. The blocking artifacts can, for instance, arise due to different intra predictions of the blocks, quantization effects and motion compensation. Two particular variants of deblocking are described below.

H.264 Deblocking

In state of the art video coding, such as H.264, there is a deblocking filter, also denoted loop filter, after prediction and residual reconstruction, but before storage of the reconstruction for later reference when encoding or decoding the subsequent frames. The deblocking filtering consists of several steps such as filter decisions, filtering operations, a clipping function and changes of pixel values. The decision to filter the border or not is made based on evaluation of several conditions. Filter decisions depend on macroblock (MB) type, motion vector (MV) difference between neighboring blocks, whether neighboring blocks have coded residuals and on the local structure of the current and/or neighboring blocks.

Then the amount of filtering for a pixel depends, among others, on the position of that pixel relative to the block border or boundary and on the quantization parameter (QP) value used for residual coding.

The filter decision is based on comparing three pixel differences with three thresholds. The thresholds are adapted to the quantization parameter (QP). For instance, assume a vertical block boundary of a b c d e f g h where a, b, c and d denote the pixel values of the pixels of a row of pixels in the current block with e, f, g and h denoting the corresponding pixel values of the pixels of a corresponding row of pixels in the neighboring block. If the following conditions are fulfilled the filter decision is positive, e.g. $\text{abs}(d-e) < \text{thr1}$, $\text{abs}(c-d) < \text{thr2}$, and $\text{abs}(e-f) < \text{thr2}$, where thr1 and thr2 are adapted based on QP.

There are two filtering modes in H.264. In the first filtering mode, referred to as normal filtering, filtering can be described with a delta value with which filtering changes the current value with. The filtering for the pixels closest to the block boundary is $d' = d + \text{delta}$ and $e' = e - \text{delta}$, where delta has been clipped off to a threshold $\pm \text{thr3}$ to a value that is

constrained by the QP. More filtering is thereby allowed for high QP than for low QP. Clipping can be described as $\text{delta_clipped} = \max(-\text{thr3}, \min(\text{thr3}, \text{delta}))$, where thr3 is controlling the filter strength. A larger value of thr3 means that the filtering is stronger which means that a stronger low-pass filtering effect will happen.

The filter strength can be increased if any of the following two conditions also holds, e.g. $\text{abs}(b-d) < \text{thr2}$ and $\text{abs}(e-g) < \text{thr2}$. The filter strength is adapted by clipping the delta less, e.g. allow for more variation.

The second filtering mode, referred to as strong filtering, is applied for intra macroblock boundaries only, when the following condition is fulfilled $\text{abs}(d-e) < \text{thr1}/4$.

For more information of deblocking filtering in H.264 reference is made to List et al., Adaptive Deblocking Filter, *IEEE Transactions on Circuits and Systems for Video Technology*, vol. 13, no. 7, July 2003.

Deblocking in HEVC Draft

In the draft HEVC (High Efficiency Video Coding) specification "Test Model under Consideration", ITU-T SG16 WP3 document, JCTVC-B205, Chapter 6.5 In-loop filter process, the deblocking filter works differently from H.264. The filtering is performed if at least one of the blocks on the side of the boundary is intra, or has non-zero coefficients, or the difference between the motion vector components of the blocks is greater or equal to one integer pixel. For example, when filtering the border between the blocks with a vertical block boundary of

$$p_3, p_2, p_1, p_0, q_0, q_1, q_2, q_3,$$

with p_i denoting the pixel value of pixel number/row number i in the current block and q_j denoting the pixel value of pixel number/row number j in the neighboring block, $i=0 \dots 7$, $j=0 \dots 3$, then the following condition should also be satisfied:

$$d = |p_2 - 2 \times p_1 + p_0 + q_2 - 2 \times q_1 + q_0| + |p_2 - 2 \times p_1 + p_0 + q_2 - 2 \times q_1 + q_0| < \beta$$

where β depends on QP. In the above mentioned HEVC specification, there is a table of β , where β increases with QP.

If the conditions are fulfilled and filtering is done between the current block and the neighboring block, one of two types of filtering is performed, referred to as weak and strong filtering, respectively. The choice between the strong and the weak filtering is done separately for each line depending on the following conditions. For each line $i=0 \dots 7$, the strong filtering is performed if all the following conditions are true, otherwise, weak filtering is performed:

$$d < (\beta >> 2)$$

$$(|p_3 - p_0 + q_0 - q_3|) < (\beta >> 3)$$

$$|p_0 - q_0| < ((5 \times t_c + 1) >> 1)$$

where t_c and β depend on QP and $>>$ denotes a right shift operator.

Weak Filtering in HEVC Draft

Weak filtering is performed based on the above conditions. The actual filtering works by computing an offset (Δ), adding it to the original pixel value and clip the sum to a filtered output pixel value in the range of 0-255:

$$\Delta = \text{Clip}(-t_c, t_c, (13 \times (q_0 - p_0) + 4 \times (q_1 - p_1) - 5 \times (q_2 - p_2) + 16) >> 5)$$

$$p_0' = \text{Clip}_{0-255}(p_0 + \Delta)$$

$$q_0' = \text{Clip}_{0-255}(q_0 - \Delta)$$

3

$$p1_i = \text{Clip}_{0-255}(p1_i + \Delta/2)$$

$$q1_i = \text{Clip}_{0-255}(q1_i - \Delta/2)$$

Strong Filtering in HEVC Draft

Strong filtering mode is performed by the following set of operations:

$$p0_i = \text{Clip}_{0-255}((p2_i + 2 \times p1_i + 2 \times p0_i + 2 \times q0_i + q1_i + 4) >> 3)$$

$$q0_i = \text{Clip}_{0-255}((p1_i + 2 \times p0_i + 2 \times q0_i + 2 \times q1_i + q2_i + 4) >> 3)$$

$$p1_i = \text{Clip}_{0-255}((p2_i + p1_i + p0_i + q0_i + 2) >> 2)$$

$$q1_i = \text{Clip}_{0-255}((p0_i + q0_i + q1_i + q2_i + 2) >> 2)$$

$$p2_i = \text{Clip}_{0-255}((2 \times p3_i + 3 \times p2_i + p1_i + p0_i + q0_i + 4) >> 3)$$

$$q2_i = \text{Clip}_{0-255}((p0_i + q0_i + q1_i + 3 \times q2_i + 2 \times q3_i + 4) >> 3)$$

One problem with the deblocking in HEVC is that the weak filter does not have good low-pass characteristics. One can see that the first and the second pixels from the block border are modified by adding or subtracting Δ and $\Delta/2$ respectively. Such a filter cannot remove high frequencies that can appear near the block border and cannot remove ringing. Moreover, the frequency characteristics of the filter in HEVC show slight amplifications of higher frequencies when filtering the second pixel ($p1_i$ and $q1_i$) from the block boundary, which can result in worse rate-distortion (RD) performance of the coder. Moreover, the offset for pixel $p1_i$ is equal in magnitude to the offset of pixel $q1_i$, although the structure of the signal can be different on different sides of the block boundary. Therefore, the HEVC filter does not adapt well to the local structure of the side of the block boundary.

Hence, there is a need for an efficient deblocking filter that can be used to reduce blocking artifacts at block boundaries and that does not have the above mentioned drawbacks.

SUMMARY

It is a general objective to combat blocking artifacts at block boundaries between blocks of pixels in a video frame.

This and other objectives are met by embodiments as disclosed herein.

An aspect of the embodiments defines a method of reducing blocking artifacts at a block boundary between a block of pixels and a neighboring block of pixels in a video frame. The method calculates a first offset to be based on $(9 \times (q0 - p0) - 3 \times (q1 - p1)) / 16$, wherein $p0$ denotes a pixel value of a pixel closest to the block boundary in a line of pixels in the block, $p1$ denotes a pixel value of a pixel next closest to the block boundary in the line of pixels, $q0$ denotes a pixel value of a pixel closest to the block boundary in a corresponding line of pixels in the neighboring block and $q1$ denotes a pixel value of a pixel next closest to the block boundary in the corresponding line of pixels. The line of pixels and the corresponding line of pixels are perpendicular to the block boundary. The pixel value of the pixel closest to the block boundary in the line of pixels is modified by adding the first offset to the pixel value of this pixel to form a modified pixel value. Correspondingly, the pixel value of the pixel closest to the block boundary but in the corresponding line of pixels is modified by subtracting the first offset from the pixel value of this pixel to form a modified pixel value.

In an optional embodiment of this aspect, the first offset is calculated to be equal to $(9 \times (q0 - p0) - 3 \times (q1 - p1) + 8) >> 4$, wherein $>>$ denotes a right shift operation.

4

In an optional embodiment of this aspect, the method further comprises clipping the first offset to be within an interval of $-t_c$ and t_c by setting the first offset to be equal to $-t_c$ if the first offset is smaller than $-t_c$ and by setting the first offset to be equal to t_c if the first offset is larger than t_c , wherein t_c is a threshold value that is dependent on a quantization parameter value assigned to the block.

In an optional embodiment of this aspect, the method further comprises clipping the modified pixel value of the pixel closest to said block boundary in the line of pixels to be within an interval of zero and a defined maximum value and clipping the modified pixel value of the pixel closest to the block boundary in the corresponding line of pixels to be within an interval of zero and the defined maximum value. This optional clipping is achieved by setting the modified pixel value to be equal to zero if the modified pixel value is smaller than zero and by setting the modified pixel value to be equal to the defined maximum value if the modified pixel value is larger than the defined maximum value.

In an optional embodiment of this aspect, the method further comprises calculating a second offset to be based on $(p2 + p0 - 2 \times p1 + 2 \times \Delta) / 4$, wherein $p2$ denotes a pixel value of a pixel second next closest to the block boundary in the line of pixels and Δ denotes the first offset. The method also comprises, in this optional embodiment, calculating a third offset to be based on $(q2 + q0 - 2 \times q1 - 2 \times \Delta) / 4$, wherein $q2$ denotes a pixel value of a pixel second next closest to the block boundary in the corresponding line of pixels. The pixel value of the pixel next closest to the block boundary in the line of pixels is then modified by adding the second offset to the pixel value of the pixel next closest to the block boundary in the line of pixels to form a modified pixel value. Correspondingly, the method also comprises, in this optional embodiment, modifying the pixel value of the pixel next closest to the block boundary in the corresponding line of pixels by adding the third offset to the pixel value of the pixel next closest to the block boundary in the corresponding line of pixels to form a modified pixel value.

In an optional embodiment of this aspect, the second offset is calculated to be equal to $((p2 + p0 + 1) >> 1) - p1 + \Delta >> 1$, wherein $>>$ denotes a right shift operation and the third offset is calculated to be equal to $((q2 + q0 + 1) >> 1) - q1 - \Delta >> 1$.

In an optional embodiment of this aspect, the method further comprises clipping the second offset within an interval of $-t_{c2}$ and t_{c2} and clipping the third offset within an interval of $-t_{c2}$ and t_{c2} , wherein t_{c2} is a threshold value that is dependent on a quantization parameter value assigned to the block. This optional clipping is achieved by setting the second or third offset to be equal to $-t_{c2}$ if the second or third offset is smaller than $-t_{c2}$ and by setting the second or third offset to be equal to t_{c2} if the second or third offset is larger than t_{c2} .

In an optional embodiment of this aspect, the method further comprises clipping the modified pixel value of the pixel next closest to the block boundary in the line of pixels within an interval of zero and a defined maximum value and clipping the modified pixel value of the next pixel closest to the block boundary in the corresponding line of pixels within an interval of zero and the defined maximum value. This optional clipping is achieved by setting the modified pixel value to be equal to zero if the modified pixel value is smaller than zero and by setting the modified pixel value to be equal to the defined maximum value if the modified pixel value is larger than the defined maximum value.

In an optional embodiment of this aspect, the method further comprises calculating a fourth offset to be based on

5

$(p_3+p_1-2\times p_2+2\times \Delta_{p_1})/4$, wherein p_3 denotes a pixel value of a pixel third next closest to the block boundary in the line of pixels and Δ_{p_1} denotes the second offset. The method also comprises, in this optional embodiment, calculating a fifth offset to be based on $(q_3+q_1-2\times q_2+2\times \Delta_{q_1})/4$, wherein q_3 denotes a pixel value of a pixel third closest to the block boundary in the corresponding line of pixels and Δ_{q_1} denotes the third offset. The pixel value of the pixel second next closest to the block boundary in the line of pixels is modified by adding the fourth offset to the pixel value of the pixel second next closest to the block boundary in the line of pixels to form a modified pixel value. The method also comprises, in this optional embodiment, modifying the pixel value of the pixel second next closest to the block boundary in the corresponding line of pixels by adding the fifth offset to the pixel value of the pixel second next closest to the block boundary in the corresponding line of pixels to form a modified pixel value.

In an optional embodiment of this aspect, the fourth offset is calculated to be equal to $((p_3+p_1+1)>>1)-p_2+\Delta_{p_1}>>1$, wherein $>>$ denotes a right shift operation and the fifth offset is calculated to be equal to $((q_3+q_1+1)>>1)-q_2+\Delta_{q_1}>>1$.

In an optional embodiment of this aspect a deblocking filter unit calculates the first offset to be based on $(9\times(q_0-p_0)-3\times(q_1-p_1))/16$. The deblocking filter unit modifies the pixel value of the pixel closest to the block boundary in the line of pixels by adding the first offset to the pixel value of the pixel closest to the block boundary in the line of pixels to form a modified pixel value. The deblocking filter unit also modifies the pixel value of the pixel closest to the block boundary in the corresponding line of pixels by subtracting the first offset from the pixel value of the pixel closest to the block boundary in the corresponding line of pixels to form a modified pixel value.

Another aspect of the embodiments defines a deblocking filter unit for reducing blocking artifacts at a block boundary between a block of pixels and a neighboring block of pixels in a video frame. The deblocking filter unit comprises a first offset calculator configured to calculate a first offset to be based on $(9\times(q_0-p_0)-3\times(q_1-p_1))/16$, wherein p_0 denotes a pixel value of a pixel closest to the block boundary in a line of pixels in the block, p_1 denotes a pixel value of a pixel next closest to the block boundary in the line of pixels, q_0 denotes a pixel value of a pixel closest to the block boundary in a corresponding line of pixels in the neighboring block and q_1 denotes a pixel value of a pixel next closest to the block boundary in the corresponding line of pixels. The line of pixels and the corresponding line of pixels are perpendicular to the block boundary. The deblocking filter unit also comprises a pixel value modifier configured to modify the pixel value of the pixel closest to the block boundary in the line of pixels by adding the first offset to the pixel value of this pixel to form a modified pixel value. The pixel value modifier is also configured to modify the pixel value of the pixel closest to the block boundary but in the corresponding line of pixels by subtracting the first offset from the pixel value of this pixel to form a modified pixel value.

In an optional embodiment of this aspect, the first offset calculator is configured to calculate the first offset to be equal to $(9\times(q_0-p_0)-3\times(q_1-p_1)+8)>>4$, wherein $>>$ denotes a right shift operation.

In an optional embodiment of this aspect, the deblocking filter unit comprises a first clipping unit configured to clip the first offset to be within an interval of $-t_c$ and t_c by setting the first offset to be equal to $-t_c$ if the first offset is smaller than $-t_c$ and by setting the first offset to be equal to t_c if the

6

first offset is larger than t_c , wherein t_c is a threshold value that is dependent on a quantization parameter value assigned to the block.

In an optional embodiment of this aspect, the deblocking filter unit comprises a second clipping unit configured to clip the modified pixel value of the pixel closest to the block boundary in the line of pixels within an interval of zero and a defined maximum value, and clip the modified pixel value of the pixel closest to the block boundary in the corresponding line of pixels within an interval of zero and the defined maximum value. This optional clipping by the optional second clipping unit is achieved by setting the modified pixel value to be equal to zero if the modified pixel value is smaller than zero and by setting the modified pixel value to be equal to the defined maximum value if the modified pixel value is larger than the defined maximum value.

In an optional embodiment of this aspect, the deblocking filter unit comprises a second offset calculator configured to calculate a second offset to be based on $(p_2+p_0-2\times p_1+2\times \Delta)/4$, wherein p_2 denotes a pixel value of a pixel second next closest to the block boundary in the line of pixels and Δ denotes the first offset. The deblocking filter unit also comprises, in this optional embodiment, a third offset calculator configured to calculate a third offset to be based on $(q_2+q_0-2\times q_1-2\times \Delta)/4$, wherein q_2 denotes a pixel value of a pixel second next closest to the block boundary in the corresponding line of pixels. In this optional embodiment the pixel value modifier is configured to modify the pixel value of the pixel next closest to the block boundary in the line of pixels by adding the second offset to the pixel value of the pixel next closest to the block boundary in the line of pixels to form a modified pixel value, and to modify the pixel value of the pixel next closest to the block boundary in the corresponding line of pixels by adding the third offset to the pixel value of the pixel next closest to the block boundary in the corresponding line of pixels to form a modified pixel value.

In an optional embodiment of this aspect, the second offset calculator is configured to calculate the second offset to be equal to $((p_2+p_0+1)>>1)-p_1+\Delta>>1$, wherein $>>$ denotes a right shift operation, and the third offset calculator is configured to calculate the third offset to be equal to $((q_2+q_0+1)>>1)-q_1-\Delta>>1$.

In an optional embodiment of this aspect, the deblocking filter unit comprises a third clipping unit configured to clip the second offset within an interval of $-t_{c2}$ and t_{c2} , and clip the third offset within an interval of $-t_{c2}$ and t_{c2} , wherein t_{c2} is a threshold value that is dependent on a quantization parameter value assigned to the block. This optional clipping by the optional third clipping unit is achieved by setting the second or third offset to be equal to $-t_{c2}$ if the second or third offset is smaller than $-t_{c2}$ and by setting the second or third offset to be equal to t_{c2} if the second or third offset is larger than t_{c2} .

In an optional embodiment of this aspect, the deblocking filter unit comprises a second clipping unit configured to clip the modified pixel value of the pixel next closest to the block boundary in the line of pixels within an interval of zero and a defined maximum value, and clip the modified pixel value of the next pixel closest to the block boundary in the corresponding line of pixels within an interval of zero and the defined maximum value. This optional clipping by the optional second clipping unit is achieved by setting the modified pixel value to be equal to zero if the modified pixel value is smaller than zero and by setting the modified pixel

value to be equal to the defined maximum value if the modified pixel value is larger than the defined maximum value.

In an optional embodiment of this aspect, the deblocking filter unit comprises a fourth offset calculator configured to calculate a fourth offset to be based on $(p_3 + p_1 - 2 \times p_2 + 2 \times \Delta_{p_1})/4$, wherein p_3 denotes a pixel value of a pixel third next closest to the block boundary in the line of pixels and Δ_{p_1} denotes the second offset. The deblocking filter unit also comprises, in this optional embodiment, a fifth offset calculator configured to calculate a fifth offset to be based on $(q_3 + q_1 - 2 \times q_2 + 2 \times \Delta_{q_1})/4$, wherein q_3 denotes a pixel value of a pixel third closest to the block boundary in the corresponding line of pixels and Δ_{q_1} denotes the third offset. In this optional embodiment the pixel value modifier is configured to modify the pixel value of the pixel second next closest to the block boundary in the line of pixels by adding the fourth offset to the pixel value of the pixel second next closest to the block boundary in the line of pixels to form a modified pixel value, and modify the pixel value of the pixel second next closest to the block boundary in the corresponding line of pixels by adding the fifth offset to the pixel value of the pixel second next closest to the block boundary in the corresponding line of pixels to form a modified pixel value.

In an optional embodiment of this aspect, the fourth offset calculator is configured to calculate the fourth offset to be equal to $((p_3 + p_1 + 1) \gg 1) - p_2 + \Delta_{p_1} \gg 1$, wherein $\gg$ denotes a right shift operation, and the fifth offset calculator is configured to calculate the fifth offset to be equal to $((q_3 + q_1 + 1) \gg 1) - q_2 + \Delta_{q_1} \gg 1$.

Further aspects of the embodiments define an encoder and a decoder, respectively, comprising a deblocking filter unit as defined above.

Furthermore, an aspect of the embodiments defines a user equipment comprising a memory configured to store encoded video frames, a decoder as defined above configured to decode the encoded video frames into decoded video frames and a media player configured to render the decoded video frames into video data that is displayable on a display.

Another aspect defines a network device being or belonging to a network node in a communication network between a sending unit and a receiving user equipment. The network device comprises an encoder and/or a decoder as defined above.

A further aspect of the embodiments defines a computer program for reducing blocking artifacts at a block boundary between a block of pixels and a neighboring block of pixels in a video frame. The computer program comprises code means which when run on a computer causes the computer to calculate an offset to be based on $(9 \times (q_0 - p_0) - 3 \times (q_1 - p_1))/16$, wherein p_0 denotes a pixel value of a pixel closest to the block boundary in a line of pixels in the block, p_1 denotes a pixel value of a pixel next closest to the block boundary in the line of pixels, q_0 denotes a pixel value of a pixel closest to the block boundary in a corresponding line of pixels in the neighboring block and q_1 denotes a pixel value of a pixel next closest to the block boundary in the corresponding line of pixels. The line of pixels and the corresponding line of pixels are perpendicular to the block boundary. The computer is also caused to modify the pixel value of the pixel closest to the block boundary in the line of pixels by adding the offset to the pixel value of this pixel. The code means further causes the computer to modify the pixel value of the pixel closest to the block boundary in the corresponding line of pixels by subtracting the offset from the pixel value of this pixel.

Yet another aspect of the embodiments defines a computer program product comprising computer readable code means and a computer program as defined above stored on the computer readable means.

The present embodiments enable efficient reduction in blocking artifacts and also have good low-pass characteristics.

BRIEF DESCRIPTION OF THE DRAWINGS

The invention, together with further objects and advantages thereof, may best be understood by making reference to the following description taken together with the accompanying drawings, in which:

FIG. 1 is a flow diagram illustrating a method of reducing blocking artifacts according to an embodiment;

FIGS. 2A and 2B illustrate two embodiments of neighboring blocks and a block boundary over which de-blocking filtering can be applied;

FIG. 3 is a flow diagram illustrating additional, optional steps of the method in FIG. 1 according to an embodiment;

FIG. 4 is a flow diagram illustrating additional, optional steps of the method in FIGS. 1 and 5 according to an embodiment;

FIG. 5 is a flow diagram illustrating additional, optional steps of the method in FIG. 1 according to another embodiment;

FIG. 6 is a flow diagram illustrating additional, optional steps of the method in FIG. 5 according to an embodiment;

FIG. 7 is a flow diagram illustrating additional, optional steps of the method in FIG. 5 according to another embodiment;

FIG. 8 is a schematic block diagram of a deblocking filter unit according to an embodiment;

FIG. 9 is a schematic block diagram of a deblocking filter unit according to another embodiment;

FIG. 10 is a schematic block diagram of a software implementation of a deblocking filter module in a computer according to an embodiment;

FIG. 11 is a schematic block diagram of an encoder according to an embodiment;

FIG. 12 is a schematic block diagram of a decoder according to an embodiment;

FIG. 13 is a schematic block diagram of a user equipment according to an embodiment; and

FIG. 14 is a schematic overview of a portion of a communication network comprising a network device according to an embodiment.

DETAILED DESCRIPTION

Throughout the drawings, the same reference numbers are used for similar or corresponding elements.

The embodiments generally relate to deblocking filtering to combat blocking artifacts over block boundaries in a video frame. The embodiments use a deblocking filter that has good frequency characteristics. The present deblocking filter is configured not to modify the pixel values over a block boundary if these pixel values form a ramp but smooth the pixel values if they instead are in the form of a step. This implies that the deblocking filter will have good lowpass characteristics and can remove high frequencies that can appear near the block boundary.

FIG. 1 is a flow diagram of a method of reducing blocking artifacts at a block boundary between a block of multiple pixels and a neighboring block of multiple pixels in a video frame according to an embodiment. As is well-known in the

art, a video frame is divided into non-overlapping blocks of pixels that are encoded and decoded according to the various available intra and inter coding modes. Generally, a video frame is divided into non-overlapping macroblocks of 16×16 pixels. Such a macroblock can in turn be divided into smaller blocks of different sizes, such as 4×4 or 8×8 pixels. However, also rectangular blocks could be possible according to the embodiments, such as, 4×8, 8×4, 8×16 or 16×8. The embodiments can be applied to any such block of pixels, including macroblocks or even larger blocks of pixels.

In the emerging High Efficiency Video Coding (HEVC) standard, coding units (CU), prediction units (PU) and transform units (TU) are used. The prediction units are defined inside a coding unit and contain the intra or inter prediction modes. Transform units are defined inside a coding unit and the largest transform size is 32×32 pixels and the smallest size is 4×4 pixels. The CU size is currently varying from 64×64 pixels (largest) to 4×4 pixels (smallest). In this way, the largest CU can be split into smaller CUs with the “level of granularity” depending on the local characteristics of the frame. That means that the largest CU may be split into smaller CUs of different sizes. The embodiments can also be used in connection with such coding units, which are regarded as being encompassed by the expression “block of pixels” as used herein.

Each pixel in the block has a respective pixel value. Video frames generally have color values assigned to the pixels, where the color values are represented in a defined color formats. One of the common color formats uses one luminance component and two chrominance components for each pixel, although other formats exist, such as using red, green and blue components for each pixel.

Traditionally, luminance component filtering and chrominance component filtering are done separately possibly employing different filtering decisions and different deblocking filters. It is, though, possible that the luminance filtering decisions are used in chroma filtering, like in HEVC. The embodiments can be applied to filter the luminance component, filter the chrominance component or filter both the luminance component and the chrominance component. In a particular embodiment, the embodiments are applied to achieve luminance or luma filtering. Filtering decisions, or parts of filtering decisions for one component, such as luma, can be then used when making the filtering decisions for other components, such as chroma.

Deblocking filtering is conducted over a boundary, edge or border between neighboring blocks. As a consequence, such boundaries can be vertical boundaries 1, see FIG. 2A, between two neighboring blocks 10, 20 present side by side in the video frame. Alternatively, the boundaries are horizontal boundaries 1, see FIG. 2B, between two neighboring blocks 10, 20, where one block 10 is positioned above the other block 20 in the video frame. In a particular embodiment, vertical boundaries are filtered first starting from the left-most boundary and proceeding through the boundaries towards the right-hand side in their geometrical order. Then, horizontal boundaries are filtered starting with the boundary on the top and proceeding through the boundaries towards the bottom in their geometrical order. The embodiments are, however, not limited to this particular filtering order and can actually be applied to any predefined filtering order. In a particular embodiment, the boundaries at the edge of the video frame are preferably not filtered and thereby excluded from the deblocking filtering.

The method of this embodiment starts in step S1 where a first offset or delta is calculated for a line 12 of pixels 11, 13, 15, 17 in the block 10. According to the embodiments, this first offset is calculated based on $(9 \times (q_0 - p_0) - 3 \times (q_1 - p_1)) / 16$, wherein p_0 denotes the pixel value of the pixel 11 closest

to the block boundary 1 in the line 12 of pixels 11, 13, 15, 17 in the block 10, p_1 denotes the pixel value of the pixel 13 next closest to the block boundary 1 in the line 12 of pixels 11, 13, 15, 17, q_0 denotes the pixel value of the pixel 21 closest to the block boundary 1 in a corresponding or opposing line 22 of pixels 21, 23, 25, 27 in a neighboring block 20 and q_1 denotes the pixel value of the pixel 23 next closest to the block boundary 1 in the corresponding line 22 of pixels 21, 23, 25, 27.

The line 12 of pixels 11, 13, 15, 17 in the block 10 and the corresponding line 22 of pixels 21, 23, 25, 27 in the neighboring block 20 belong to the same horizontal line of pixels, i.e. row of pixels, extending over a vertical boundary 1, see FIG. 2A, or belong to the same vertical line of pixels, i.e. column of pixels, extending over a horizontal boundary 1, see FIG. 2B. Hence, the line 12 of pixels 11, 13, 15, 17 and the corresponding line 22 of pixels 21, 23, 25, 27 are perpendicular to the block boundary 1 between the block 10 and the neighboring block 20. Furthermore, the line 12 of pixels 11, 13, 15, 17 in the block 10 and the corresponding line 22 of pixels 21, 23, 25, 27 in the neighboring block 20 have the same line number. For instance, if the block 10 and the neighboring block 20 each comprises N, such as eight, rows or columns of pixels, having row or column numbers $i = 0 \dots N-1$ then the line 12 of pixels 11, 13, 15, 17 has line number i in the block 10 and the corresponding line 22 of pixels 21, 23, 25, 27 also has line number i but in the neighboring block 20. Thus, line 12 of pixels 11, 13, 15, 17 in the block and the corresponding line 22 of pixels 21, 23, 25, 27 in the neighboring block 20 are opposing lines with regard to the block boundary 1.

According to the embodiments, “line of pixels” and “corresponding line of pixels” are employed to denote a “row of pixels” and a “corresponding row of pixels” in the case of a vertical block boundary as in FIG. 2A and denote a “column of pixels” and a “corresponding column of pixels” in the case of a horizontal block boundary as in FIG. 2B.

A next step S2 modifies the pixel value of the pixel 11 closest to the block boundary 1 in the line 12 of pixels 11, 13, 15, 17 by adding the first offset calculated in step S1 to the pixel value of this pixel 11 to form a modified pixel value p_0' . Thus, the modified pixel value p_0' for this pixel 11 is $p_0' = p_0 + \Delta$, wherein Δ denotes the first offset from step S1. Correspondingly, the pixel value of the pixel 21 closest to the block boundary 1 but in the corresponding line 22 of pixels 21, 23, 25, 27 in the neighboring block 20 is modified in step S3 by subtracting the first offset from the pixel value of this pixel 21 to form a modified pixel value q_0' . The modified pixel value q_0' is therefore calculated as $q_0' = q_0 - \Delta$.

The modification of the pixel value for the pixel 11 closest to the block boundary 1 in the line 12 of pixels 11, 13, 15, 17 in the block 10 in step S2 and the modification of the pixel value for the pixel 21 closest to the block boundary 1 in the corresponding line 22 of pixels 21, 23, 25, 27 in the neighboring block 20 in step S3 can be performed serially as illustrated in FIG. 1 or serially but in the opposite order, i.e. step S3 prior to step S2. Alternatively, the two steps S2 and S3 can be performed at least partly in parallel.

The method illustrated in FIG. 1 and including steps S1 to S3 reduces blocking artifacts at the block boundary 1 by processing pixels in one line 12 of pixels 11, 13, 15, 17 in the block and also in the corresponding line 22 of pixels 21, 23, 25, 27 in the neighboring block 20. This pixel modification can be performed for one of the (horizontal or vertical) lines 12 in the block 10 or for multiple, i.e. at least two, lines 12 in the block 10, possibly for all (horizontal or vertical) lines 12 in the block 10. This is schematically illustrated by the line L1.

11

Generally, and which was discussed in the foregoing, deblocking filtering involves filter decisions that determine whether a deblocking filter is to be applied over a horizontal or vertical block boundary for a block. If such a decision is positive the deblocking filter is then possibly applied to all columns (vertical lines) or rows (horizontal lines) of the block. Alternatively, further filtering decisions are taken for each column or row to decide whether deblocking filter is to be applied or not and/or what type of deblocking filter to use for that particular column or row. Therefore, the method as illustrated in FIG. 1 could be applied to a column, to a row, to multiple columns, to multiple rows or both for at least one column and at least one row in a block of pixels in the video frame. It is further anticipated that deblocking filtering does not necessarily have to be applied to all blocks in the video frame. In clear contrast, such deblocking filtering is preferably only applied to the blocks and over block boundaries where there are blocking artifacts as determined by one or more filter decisions.

The deblocking filtering will now be further described herein in connection with various implementation embodiments.

Clipping of the first offset can be performed in an embodiment to thereby restrict the value of the first offset to be within an interval of $-t_c$ and t_c . The threshold value t_c is preferably dependent on a quantization parameter (QP) value assigned to the block. In such a case, a table of different threshold values for different QP values could be used. Table 1 listed below is an example of such a table.

TABLE 1

t_c values for different QP values	
QP	
	0 1 2 3 4 5 6 7 8 9 10 11 12 13 14 15 16 17 18
t_c	0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 1
QP	
	19 20 21 22 23 24 25 26 27 28 29 30 31 32 33 34 35 36 37
t_c	1 1 1 1 1 1 1 1 2 2 2 2 3 3 3 4 4 4
QP	
	38 39 40 41 42 43 44 45 46 47 48 49 50 51 52 53 54 55
t_c	5 5 6 6 7 8 9 9 10 10 11 11 12 12 13 13 14 14

The present embodiments are, however, not limited to the particular relationship between t_c and QP as shown in Table 1 but could instead determine the t_c value for the block based on the QP value for the block in some other way.

FIG. 3 illustrates this clipping action. The method then continues from step S1 of FIG. 1. A next step S10 investigates whether the first offset is within the interval $-t_c$ and t_c , i.e. whether $-t_c \leq \Delta \leq t_c$. In such a case, the method continues to step S2 of FIG. 1 and no modification of the first offset is required. However, if the first offset is not within the interval as determined in step S10 the method continues to step S11 where the first offset is clipped to have a value within the interval. Thus, if $\Delta < -t_c$ the first offset is set to have a value of $-t_c$ in step S11. Correspondingly, if $\Delta > t_c$ then the first offset is set to have a value of t_c in step S11. The method then continues to step S2 of FIG. 2.

Correspondingly, the modified pixel values calculated in steps S2 and S3 of FIG. 1 could be clipped to be within an allowed interval. This is schematically illustrated by the flow diagram of FIG. 4. The method then continues from step S2

12

or S3 in FIG. 1 and a next step S20 investigates whether the modified pixel value, i.e. p_0' or q_0' , is within an allowed interval of 0 and M. The parameter M denotes a defined maximum value that the modified pixel values can assume. In a particular embodiment, this maximum value is defined based on the number of bits that are spent on the pixel values. Thus, assume that the pixel values are in the form of a m-bit value, then M is preferably equal to $2^m - 1$. For instance, if each pixel value is a 8-bit value, i.e. $m=8$, then $M=255$. Step S20 therefore investigates whether $0 \leq p_0' \leq M$ or $0 \leq q_0' \leq M$. If the modified pixel value is within the interval [0, M] the method continues to step S3 of FIG. 1 or ends. However, if the modified pixel value is outside of the interval it is clipped in step S21 to have a value inside the interval. In other words, if $p_0' < 0$ or $q_0' < 0$ then the modified pixel value is set in step S21 to be $p_0' = 0$ or $q_0' = 0$. Correspondingly, if $p_0' > M$ or $q_0' > M$ then step S21 sets the modified pixel value to be $p_0' = M$ or $q_0' = M$.

Step S1 of FIG. 1 calculates the first offset to be based on $(9 \times (q_0 - p_0) - 3 \times (q_1 - p_1)) / 16$. In a particular embodiment, the first offset is calculated in step S1 to be equal to $(9 \times (q_0 - p_0) - 3 \times (q_1 - p_1)) / 16$. In an embodiment, the pixel values are therefore updated by the proposed deblocking filter by using the following calculations:

$$\Delta = (9 \times (q_0 - p_0) - 3 \times (q_1 - p_1)) / 16$$

$$p_0' = p_0 + \Delta$$

$$q_0' = q_0 - \Delta$$

Clipping of the first offset and/or the modified pixel values as illustrated in FIGS. 3 and 4 can also be used.

In an alternative embodiment, the offset is calculated as a function of $(9 \times (q_0 - p_0) - 3 \times (q_1 - p_1)) / 16$. Such a function could then be defined so that the calculation of the first offset is efficiently performed in hardware. In such a case, it is generally preferred not to have any divisions and/or define the function so that the first offset will be an integer value. In an embodiment, $(X+8) \gg 4$ is used as an integer-expression of $X/16$, where $\gg$ denotes a right shift operation. Thus, in a particular embodiment step S1 calculates the first offset to be based on and preferably equal to $(9 \times (q_0 - p_0) - 3 \times (q_1 - p_1) + 8) \gg 4$.

In this embodiment, the pixel values are therefore updated by the proposed deblocking filter by using the following calculations:

$$\Delta = (9 \times (q_0 - p_0) - 3 \times (q_1 - p_1) + 8) \gg 4$$

$$p_0' = p_0 + \Delta$$

$$q_0' = q_0 - \Delta$$

13

or if clipping is used:

$$\Delta = \text{Clip3}(-t_C, t_C, (9 \times (q_0 - p_0) - 3 \times (q_1 - p_1) + 8) >> 4)$$

$$p_0' = \text{Clip}(p_0 + \Delta)$$

$$q_0' = \text{Clip}(q_0 - \Delta)$$

wherein $\text{Clip3}(A, B, x)$ is defined as $\text{Clip3}(A, B, x) = A$ if $x < A$, $\text{Clip3}(A, B, x) = B$ if $x > B$ and $\text{Clip3}(A, B, x) = x$ if $A \leq x \leq B$ and $\text{Clip}(x)$ is defined as $\text{Clip}(0, M, x)$.

In alternative embodiments other implementations, such as integer representations of $(9 \times (q_0 - p_0) - 3 \times (q_1 - p_1)) / 16$ and preferably such integer representations that are efficiently implemented in hardware are used.

The above disclosed embodiments define a deblocking filter that generates a first offset for the pixels closest to the block boundary with a formula that produces approximately zero, preferably exactly zero, when applied to a ramp of pixel values and which produces an offset value that smoothes a step in the pixel values when applied to a step of pixel values. For instance, a ramp can be described as linearly increasing or decreasing pixel values, e.g. 10, 20, 30, 40. When calculating the first offset for these pixel values, i.e.

$p_1=10$, $p_0=20$, $q_0=30$, $q_1=40$, the first offset will be zero. Correspondingly, a step can be described as a step increase or decrease in pixel values, e.g. 10, 10, 20, 20. When calculating the first offset for these pixel values, i.e. $p_1=10$, $p_0=10$, $q_0=20$, $q_1=20$, the first offset will be 3.75 if $\Delta = (9 \times (q_0 - p_0) - 3 \times (q_1 - p_1)) / 16$ or 4 if $\Delta = (9 \times (q_0 - p_0) - 3 \times (q_1 - p_1) + 8) >> 4$. The modified pixel values will then be 10, 13.75, 16.25, 30 or 10, 14, 16, 20 and thereby a smoothing of the step is achieved. The first offset is also zero for a flat line, i.e. if the pixel values are equal, $p_0=p_1=q_0=q_1$.

In a particular embodiment, also the pixel values of the pixels next closest to the block boundary can be modified. This is described further herein with reference to FIGS. 2A, 2B and 5. The method then continues from step S3 of FIG. 1 or from step S2 or indeed step S1. A next step S30 calculates a second offset to be based on $(p_2 + p_0 - 2 \times p_1 + 2 \times \Delta) / 4$, wherein p_2 denotes the pixel value of the pixel 15 second next closest to the block boundary 1 in the line 12 of pixels 11, 13, 15, 17 in the block 10. A next step S31 calculates a third offset to be based on $(q_2 + q_0 - 2 \times q_1 - 2 \times \Delta) / 4$, wherein q_2 denotes the pixel value of the pixel 25 second next closest to the block boundary 1 in the corresponding line 22 of pixels 21, 23, 25, 27 in the neighboring block 20. Steps S30 and S31 can be performed sequentially in any order or at least partly in parallel.

The second offset calculated in step S30 is used in step S32 to modify the pixel value of the pixel 13 next closest to the block boundary 1 in the line 12 of pixels 11, 13, 15, 17. In an embodiment, the second offset is added to the pixel value of this pixel 13 to obtain a modified pixel value. Correspondingly, step S33 modifies the pixel value of the pixel 23 next closest to the block boundary 1 in the corresponding line 22 of pixels 21, 23, 25, 27 by adding the third offset to the pixel value of this pixel 23 to form a modified pixel value. Steps S32 and S33 can be performed in any sequential order or at least partly in parallel.

The proposed deblocking filter is, in this embodiment, a low-pass filter on all the filter positions p_0 , p_1 , q_0 , q_1 . When applied to a ramp signal, the deblocking filter will not modify it since Δ , Δ_p , Δ_q will all be equal to zero, wherein Δ_p denotes the second offset and Δ_q denotes the third offset. When applied to a step signal, i.e. a deblocking artifact, the deblocking filter will smooth it, i.e. reduce the blocking

14

artifact. In clear contrast to the current HEVC filter, the proposed deblocking filter will smooth and thereby attenuate small ripples on the sides of the block boundary.

In the above described embodiment, the filters for the coefficients that stand at the second position from the block boundary (p_1 , q_1) are produced by using a combination of the first offset and a symmetrical low-pass filter. An advantage of this embodiment is that the offsets for the pixels second next closest to the block boundary can have different values that allows for a better local adaptation. In similar to the first offset, the second and third offsets can be clipped to be within an interval of $-t_{C2}$ and t_{C2} , where the threshold value t_{C2} is determined based on the QP value assigned to the block. In a particular embodiment the threshold value t_{C2} is determined based on the threshold value t_C used for clipping the first offset in FIG. 3. For instance,

$$t_{C2} = \frac{t_C}{2}$$

or with a hardware adapted implementation $t_{C2} = t_C >> 1$.

FIG. 6 is a flow diagram illustrating such a clipping of the second and the third offsets. The method continues from step S30 or S31 of FIG. 5. A next step S40 investigates whether the second or third offset is within the interval of $-t_{C2}$ and t_{C2} . If this is true the method continues to step S32 or S33 of FIG. 5. However, if the second or third offset is smaller than t_{C2} or larger than t_{C2} the method continues to step S41. This step S41 clips the second or third offset to be $-t_{C2}$ if $\Delta_{p,q} < -t_{C2}$ or sets the second or third offset to t_{C2} if $\Delta_{p,q} > t_{C2}$.

The modified pixel values of the pixels next closest to the block boundary are preferably clipped to be within the interval of 0 and M in similarity to the modified pixel values for the pixels closest to the block boundary. Hence, the method steps of FIG. 4 can be applied also to these pixels to force the pixel values to be within $[0, M]$.

In an embodiment, the modified pixel values of the pixels 13, 23 next closest to the block boundary 1 are calculated as:

$$\Delta_p = (p_2 + p_0 - 2 \times p_1 + 2 \times \Delta) / 4$$

$$p_1' = p_1 + \Delta_p$$

$$\Delta_q = (q_2 + q_0 - 2 \times q_1 - 2 \times \Delta) / 4$$

$$q_1' = q_1 + \Delta_q$$

Optionally clipping of the second and third offsets and/or the modified pixel values as disclosed above are used.

In alternative embodiment, the computations of the offsets could be performed to be independent of each other.

$$\Delta = (9 \times (q_0 - p_0) - 3 \times (q_1 - p_1) + 8) >> 4$$

$$p_0' = p_0 + \Delta$$

$$q_0' = q_0 - \Delta$$

$$\Delta_p = (p_0 + p_2 - 2 \times p_1) / 4$$

$$p_1' = p_1 + \Delta_p + \Delta / 2$$

$$\Delta_q = (q_0 + q_2 - 2 \times q_1) / 4$$

$$q_1' = q_1 + \Delta_q - \Delta / 2$$

Mathematically this is equivalent as the previously disclosed embodiment. Optional clipping can also be performed for this embodiment.

15

In an alternative embodiment, the second and third offsets are calculated based on, such as a function, of $(p2+p0-2 \times p1+2 \times \Delta)/4$ and $(q2+q0-2 \times q1-2 \times \Delta)/4$, respectively. For instance, such function could be adapted for a hardware implementation and/or be an integer representation of $(p2+p0-2 \times p1+2 \times \Delta)/4$ and $(q2+q0-2 \times q1-2 \times \Delta)/4$. A particular example of such a hardware implementation that produces integer values is to calculate the second offset to be based on, preferably equal to, $((p2+p0+1) \gg 1) - p1 + \Delta \gg 1$. Correspondingly, the third offset is preferably calculated to be based on, preferably equal to, $((q2+q0+1) \gg 1) - q1 - \Delta \gg 1$.

In such a case, the modified pixel values are calculated as:

$$\Delta_p = (((p2+p0+1) \gg 1) - p1 + \Delta) \gg 1$$

$$p1' = p1 + \Delta_p$$

$$\Delta_q = (((q2+q0+1) \gg 1) - q1 + \Delta) \gg 1$$

$$q1' = q1 + \Delta_q$$

or if clipping is used:

$$\Delta_p = \text{Clip3}(-t_{C2}, t_{C2}, (((p2+p0+1) \gg 1) - p1 + \Delta) \gg 1)$$

$$p1' = \text{Clip}(p1 + \Delta_p)$$

$$\Delta_q = \text{Clip3}(-t_{C2}, t_{C2}, (((q2+q0+1) \gg 1) - q1 - \Delta) \gg 1)$$

$$q1' = \text{Clip}(q1 + \Delta_q)$$

An alternative embodiment for calculating the second and third offsets, which is adapted for hardware-implementation, is:

$$\Delta_p = \text{Clip3}(-t_{C2}, t_{C2}, ((p2+p0 - ((p1-\Delta) \ll 1) + 2) \gg 2))$$

$$\Delta_q = \text{Clip3}(-t_{C2}, t_{C2}, ((q2+q0 - ((q1+\Delta) \ll 1) + 2) \gg 2))$$

A further alternative embodiment for calculating the second and third offsets, which is adapted for hardware-implementation, is:

$$\Delta_p = \text{Clip3}(-t_{C2}, t_{C2}, (((p2+p0+1) \gg 1) - p1 + \Delta + 1) \gg 1))$$

$$\Delta_q = \text{Clip3}(-t_{C2}, t_{C2}, (((q2+q0+1) \gg 1) - q1 - \Delta + 1) \gg 1))$$

In another embodiment, one can use a stronger low-pass filter in combination with the first offset. In this case the second offset is calculated based on, such as equal to, $(p2+p0-2 \times p1+\Delta)/2$ or, in a hardware-adapted implementation, based on, preferably equal to, $((p2+p0+1+\Delta) \gg 1) - p1$ or alternatively $((q2+p0+\Delta - (p1 \ll 1) + 1) \gg 1)$. The third offset could then be calculated based on, such as equal to, $(q2+q0-2 \times q1-\Delta)/2$ or, in a hardware-adapted implementation, based on, preferably equal to, $((q2+q0+1-\Delta) \gg 1) - q1$ or alternatively $((q2+q0-\Delta - (q1 \ll 1) + 1) \gg 1)$.

A particular embodiment calculates the first, second and third offsets for a line of pixels in the block to thereby modify the pixel values of both the pixels closest to the block boundary and the pixels next closest to the block boundary.

In an alternative embodiment, a decision is first made whether to calculate the second and third offsets and thereby whether to modify the pixel values of the pixels next closest to the block boundary in addition to modifying the pixel values of the pixels closest to the block boundary.

In similarity to the embodiments disclosed in the foregoing calculating second and third offsets in order to modify the pixel values of the pixels next closest to the block boundary, fourth and fifth offsets can be calculated in order to modify the pixel values of the pixels second next closest to the block boundary.

16

FIG. 7 is a flow diagram illustrating such an embodiment. The method continues from step S33 of FIG. 5. A next step S50 calculates a fourth offset based on $(p3+p1-2 \times p2+2 \times \Delta_p)/4$, wherein $p3$ denotes the pixel value of the pixel 17 third next closest to the block boundary 1 in the line 12 of pixels 11, 13, 15, 17 in the block 10 and Δ_p denotes the second offset. Step S51 correspondingly calculates a fifth offset to be based on $(q3+q1-2 \times q2+2 \times \Delta_{q1})/4$, wherein $q3$ denotes the pixel value of the pixel 27 third closest to the block boundary 1 in the corresponding line 22 of pixels 21, 23, 25, 27 in the neighboring block 20 and Δ_{q1} denotes the third offset. Steps S50 and S51 can be performed sequentially in any order or at least partly in parallel.

The fourth and fifth offsets can, in an alternative embodiment, be calculated to be based on $(p3+p1-2 \times p2+\Delta_{p1})/2$ and $(q3+q1-2 \times q2+\Delta_{q1})/2$ respectively, or alternatively $(p3+p1-2 \times p2+2 \times \Delta_{q1})/4$ and $(q3+q1-2 \times q2+2 \times \Delta_{q2})/4$.

The next two steps modify pixel values based on the fourth and fifth offset. Thus, step S52 modifies the pixel value of the pixel 15 second next closest to the block boundary 1 in the line 12 of pixel 11, 13, 15, 17 in the block 10 by adding the fourth offset to the pixel value of this pixel 15 to form a modified pixel value. Step S53 correspondingly modifies the pixel value of the pixel 25 second next closest to the block boundary 1 in the corresponding line 22 of pixels 21, 23, 25, 27 in the neighboring block 20 by adding the fifth offset to the pixel value of this pixel 25 to form a modified pixel value. Steps S52 and S53 can be performed sequentially in any order or at least partly in parallel.

This concept can also be generalized for the filters modifying more than three pixels from the block boundary. For example, the fourth pixel 17, 27 from the block boundary 1 can be obtained using a combination of the offsets for the third pixels 15, 25 (or the offset from the second pixels 13, 23 or the offset from the first pixels 11, 21) and a symmetrical low-pass filter. Even longer filters are also possible.

In similarity to the previous embodiments, the fourth and fifth offsets can also be clipped. In such a case, the same interval as for the second and third offsets or half that interval could be used. In an alternative embodiment, the clipping interval is $-t_{C3}$ to t_{C3} , wherein the threshold value t_{C3} is determined based on the QP value associated with the block. Also the modified pixel values of the pixels second next closest to the block boundary can be clipped to be within the interval of 0 and M as disclosed in FIG. 4.

In a particular embodiment the modification of these pixel values are performed according to below:

$$\Delta_{p2} = (p3+p1-2 \times p2+2 \times \Delta_{p1})/4$$

$$p2' = p2 + \Delta_{p2}$$

$$\Delta_{q2} = (q3+q1-2 \times q2+2 \times \Delta_{q1})/4$$

$$q2' = q2 + \Delta_{q2}$$

wherein Δ_{p2}, Δ_{q2} denote the fourth and fifth offsets, respectively. Optionally clipping can be performed as described in the foregoing.

A representation of $(p3+p1-2 \times p2+2 \times \Delta_{p1})/4$ and $(q3+q1-2 \times q2+2 \times \Delta_{q1})/4$ suitable for hardware implementation can be used in order to get the fourth and fifth offsets as integer values. In a particular embodiment, the fourth offset is calculated to be based on, preferably equal to, $((p3+p1+1) \gg 1) - p2 + \Delta_{p1} \gg 1$. Correspondingly, $((q3+q1+1) \gg 1) - q2 + \Delta_{q1} \gg 1$ is an integer representation for the fifth offset.

The present embodiments are adapted for combating blocking artifacts in connection with coding and decoding of

video frames. The embodiments can therefore be applied to such video coding and decoding standards which divide video frames into blocks of pixels and thereby run a risk of having blocking artifacts over block boundaries. Examples of such standards, to which the present embodiments can be applied, are H.264 and HEVC. In particular HEVC, has the possibility to select between a weak filtering mode and a strong filtering mode. The present embodiments can then advantageously be used in the weak filtering mode in order to calculate offsets that are employed to modify the pixel values in a line of pixels and a corresponding line of pixels over a block boundary. Hence, the decisions whether to perform such deblocking filtering according to the prior art HEVC can advantageously be used for the present embodiments.

A particular aspect relates to a method of reducing blocking artifacts at a block boundary between a block of multiple pixels and a neighboring block of multiple pixels in a video frame. With reference to FIG. 1, the method comprises calculating, in step S1, a first offset based on a pixel value of a pixel closest to the block boundary in a line of pixels in the block, a pixel value of a pixel next closest to the block boundary in the line of pixels, a pixel value of a pixel closest to the block boundary in a corresponding or opposing line of pixels in the neighboring block and a pixel value of a pixel next closest to the block boundary in the corresponding line of pixels. The line of pixels and the neighboring line of pixels are perpendicular to the block boundary. The first offset is calculated based on these pixel values and a formula that produces an offset value that approximates zero, preferably equals zero, when the pixel values are linearly increasing or decreasing or are the same when traveling along the line of pixels and the corresponding line of pixels and produces an offset value that smoothes a step in the pixel values when the pixel values increase or decrease in a step when traveling along the line of pixels and the corresponding line of pixels. The method also comprises modifying, in step S2, the pixel value of the pixel closest to the block boundary in the line of pixels by adding the first offset to the pixel value of the pixel closest to the block boundary in the line of pixels. A next step S3 modifies the pixel value of the pixel closest to the block boundary in the corresponding line of pixels by subtracting the first offset from the pixel value of the pixel closest to the block boundary in the corresponding line of pixels.

This particular aspect can be combined with the embodiments discussed in the foregoing in connection with FIGS. 1-7.

The method of reducing blocking artifacts according to the embodiment disclosed in FIG. 1 is preferably performed by a deblocking filter unit. Hence, such a deblocking filter unit then calculates the first offset in step S1 and modifies the pixel values of the pixels closest to the block boundary in steps S2 and S3. FIG. 8 is a schematic block diagram of an embodiment of such a deblocking filter unit 100.

The deblocking filter unit 100 comprises a first offset calculator 110 configured to calculate a first offset based on $(9 \times (q_0 - p_0) - 3 \times (q_1 - p_1)) / 16$ as previously disclosed herein for a line of pixels in a block of pixels in a video frame. A pixel modifier 120 of the deblocking filter unit 100 is configured to modify the pixel value of a pixel closest to a block boundary in the line of pixels in the block by adding the first offset calculated by the first offset calculator 110 to the pixel value of this pixel to form a modified pixel value. The pixel modifier 120 further modifies the pixel value of a pixel closest to the block boundary but in a corresponding line of pixels in a neighboring block of pixels in the video

frame. This modification by the pixel value modifier 120 is achieved by subtracting the first offset calculated by the first offset calculator 110 from the pixel value of this pixel to form a modified pixel value.

Hence, in a particular embodiment the pixel modifier 120 is configured to add the first offset to the pixel value of the pixel closest to the block boundary in the line of pixels to form a modified pixel value. The pixel modifier 120 is further configured to subtract the first offset from the pixel value of the pixel closest to the block boundary in the corresponding line of pixels to form a modified pixel value.

In a particular embodiment, the first offset calculator 110 is configured to calculate the first offset to be $f((9 \times (q_0 - p_0) - 3 \times (q_1 - p_1)) / 16)$, i.e. a function $f(\cdot)$ or representation of $(9 \times (q_0 - p_0) - 3 \times (q_1 - p_1)) / 16$. This function preferably outputs an integer representation of $(9 \times (q_0 - p_0) - 3 \times (q_1 - p_1)) / 16$ and preferably the function is suitable for hardware implementation. The first offset calculator 110 is configured, in an embodiment, to calculate the first offset to be based on, preferably equal to, $(9 \times (q_0 - p_0) - 3 \times (q_1 - p_1) + 8) \gg 4$.

FIG. 9 is a schematic block diagram of a deblocking filter unit 200 according to another embodiment. The deblocking filter unit 200 comprises the first offset calculator 210 and the pixel value modifier 220. These units 210, 220 operate as discussed in the foregoing in connection with FIG. 8. The deblocking filter unit 200 preferably also comprises a first clipping unit 230. This first clipping unit 230 is configured to clip the first offset to be within an interval of $-t_c$ and t_c . The threshold value t_c is then dependent on a QP value associated with the block and can, for instance, be selected from Table 1 based on the QP value of the block.

An optional second clipping unit 240 is implemented in the deblocking filter unit 200 for clipping the modified pixel values calculated by the pixel value modifier 220. Thus, the second clipping unit 240 limits these modified pixel values to be within an interval of zero and the defined maximum value M.

In a preferred embodiment the deblocking filter unit 200 also comprises a second offset calculator 250 configured to calculate a second offset based on $(p_2 + p_0 - 2 \times p_1 + 2 \times \Delta) / 4$ for the line of pixels in the block.

In a particular embodiment, the second offset calculator 250 is configured to calculate the second offset to be $g((p_2 + p_0 - 2 \times p_1 + 2 \times \Delta) / 4)$, i.e. a function $g(\cdot)$ or representation of $(p_2 + p_0 - 2 \times p_1 + 2 \times \Delta) / 4$. This function preferably outputs an integer representation of $(p_2 + p_0 - 2 \times p_1 + 2 \times \Delta) / 4$ and preferably the function is suitable for hardware implementation. The second offset calculator 250 is configured, in an embodiment, to calculate the second offset to be based on, preferably equal to, $((p_2 + p_0 + 1) \gg 1) - p_1 + \Delta \gg 1$.

The deblocking filter unit 200 preferably comprises a third offset calculator 260 configured to calculate a third offset based on $(q_2 + q_0 - 2 \times q_1 - 2 \times \Delta) / 4$ for the corresponding line of pixels in the neighboring block.

In a particular embodiment, the third offset calculator 260 is configured to calculate the third offset to be $h((q_2 + q_0 - 2 \times q_1 - 2 \times \Delta) / 4)$, i.e. a function $h(\cdot)$ or representation of $(q_2 + q_0 - 2 \times q_1 - 2 \times \Delta) / 4$. This function preferably outputs an integer representation of $(q_2 + q_0 - 2 \times q_1 - 2 \times \Delta) / 4$ and preferably function is suitable for hardware implementation. The third offset calculator 260 is configured, in an embodiment, to calculate the third offset to be based on, preferably equal to, $((q_2 + q_0 + 1) \gg 1) - q_1 - \Delta \gg 1$.

The pixel modifier 220 of the deblocking filter unit 200 is then furthermore configured to modify the pixel value of the pixel next closest to the block boundary in the line of pixels in the block. The pixel modifier 220 adds the second offset

calculated by the second offset calculator **250** to the pixel value of this pixel. The pixel modifier **220** is additionally configured to modify the pixel value of the pixel next closest to the block boundary but in the corresponding line of pixels in the neighboring block. This modification is achieved by adding the third offset calculated by the third offset calculator **260** to the pixel value of this pixel.

An optional third clipping unit **270** of the deblocking filter unit **200** is configured to clip the second offset calculated by the second offset calculator **250** and the third offset calculated by the third offset calculator **260** to be within an interval of t_{c2} and t_{c2} . The threshold value t_{c2} is preferably dependent on the QP value associated with the block and is advantageously calculated based on the threshold value t_c used for clipping the first offset. In an alternative embodiment, the third clipping unit **270** is omitted and any clipping of the second and third offsets is instead performed by the first clipping unit **230**.

The second clipping unit **240** preferably not only clips the modified pixel values of the pixels closest to the block boundary but also the modified pixel values of the pixels next closest to the block boundary and calculated using the second and third offsets, respectively. Thus, also these modified pixel values are preferably restricted to be within the interval of zero to the defined maximum value M.

The second offset calculator **250** and the third offset calculator **260** could be configured to calculate the second and third offsets for each line of pixels and each corresponding line of pixels for which deblocking filtering is to be applied over the block boundary between the block and the neighboring block. In an alternative approach the deblocking filter unit **200** performs a selection whether to only calculate the first offset and thereby only modify the pixel values of the pixels closest to the block boundary or to calculate both the first, second and third offsets and thereby modify the pixel values of the pixels closest to and the pixels next closest to the block boundary.

In an optional embodiment, the deblocking filter unit **200** can comprise a fourth offset calculator **280** configured to calculate a fourth offset to be based on $(p3+p1-2 \times p2+2 \times \Delta_{p1})/4$.

In a particular embodiment, the fourth offset calculator **280** is configured to calculate the fourth offset to be $b((p3+p1-2 \times p2+2 \times \Delta_{p1})/4)$, i.e. a function $b()$ or representation of $(p3+p1-2 \times p2+2 \times \Delta_{p1})/4$. This function preferably outputs an integer representation of $(p3+p1-2 \times p2+2 \times \Delta_{p1})/4$ and preferably the function is suitable for hardware implementation. The fourth offset calculator **280** is configured, in an embodiment, to calculate the fourth offset to be based on, preferably equal to, $((p3+p1+1) \gg 1) - p2 + \Delta_{p1} \gg 1$.

The deblocking filter **200** could also comprise an optional fifth offset calculator **290** configured to calculate a fifth offset to be based on $(q3+q1-2 \times q2+2 \times \Delta_{q1})/4$.

In a particular embodiment, the fifth offset calculator **290** is configured to calculate the fifth offset to be $k((q3+q1-2 \times q2+2 \times \Delta_{q1})/4)$, i.e. a function $k()$ or representation of $(q3+q1-2 \times q2+2 \times \Delta_{q1})/4$. This function preferably outputs an integer representation of $(q3+q1-2 \times q2+2 \times \Delta_{q1})/4$ and preferably the function is suitable for hardware implementation. The fifth offset calculator **290** is configured, in an embodiment, to calculate the fifth offset to be based on, preferably equal to, $((q3+q1+1) \gg 1) - q2 + \Delta_{q1} \gg 1$.

In this embodiment, the pixel value modifier **220** is also configured to modify the pixel value of the pixel second next closest to the block boundary in the line of pixels in the block by adding the fourth offset calculated by the fourth offset calculator **280** to the pixel value of this pixel. The

pixel value modifier **220** additionally modifies, in this embodiment, the pixel value of the pixel second next closest to the block boundary in the corresponding line of pixels in the neighboring block by adding the fifth offset calculated by the fifth offset calculator to the pixel value of this pixel.

The second clipping unit **240** preferably processes the modified pixel values to restrict them within the interval of zero and the predefined maximum value M. The third clipping unit **270** can also be used to clip the fourth and fifth offsets in similarity to the second and third offsets. Alternatively, the deblocking filter unit **200** comprises a fourth clipping unit configured to clip the fourth and fifth offsets to be within an interval having end points that are defined based on the QP value of the block and preferably based on the threshold value t_c .

A particular aspect relates to a deblocking filter unit for reducing blocking artifacts at a block boundary between a block of multiple pixels and a neighboring block of multiple pixels in a video frame. With reference to FIG. 8, the deblocking filter unit **100** comprises a first offset calculator **110** configured to calculate a first offset based on a pixel value of a pixel closest to the block boundary in a line of pixels in the block, a pixel value of a pixel next closest to the block boundary in the line of pixels, a pixel value of a pixel closest to the block boundary in a corresponding or opposing line of pixels in the neighboring block and a pixel value of a pixel next closest to the block boundary in the corresponding line of pixels. The line of pixels and the neighboring line of pixels are perpendicular to the block boundary. The first offset is calculated by the first offset calculator **110** based on these pixel values and a formula that produces an offset value that approximates zero, preferably equals zero, when the pixel values are linearly increasing or decreasing or are the same when traveling along the line of pixels and the corresponding line of pixels and produces an offset value that smoothes a step in the pixel values when the pixel values increase or decrease in a step when traveling along the line of pixels and the corresponding line of pixels. The deblocking filter unit **100** also comprises a pixel value modifier **120** configured to modify the pixel value of the pixel closest to the block boundary in the line of pixels by adding the first offset to the pixel value of the pixel closest to the block boundary in the line of pixels to form a modified pixel value. The pixel value modifier **120** is further configured to modify the pixel value of the pixel closest to the block boundary in the corresponding line of pixels by subtracting the first offset from the pixel value of the pixel closest to the block boundary in the corresponding line of pixels to form a modified pixel value.

Although the respective unit **110**, **120** and **210-290** disclosed in conjunction with FIGS. 8 and 9 have been disclosed as physically separate units **110**, **120** and **210-290** in the device **100**, **200**, and all may be special purpose circuits, such as ASICs (Application Specific Integrated Circuits), alternative embodiments of the device **100**, **200** are possible where some or all of the units **110**, **120** and **210-290** are implemented as computer program modules running on a general purpose processor. Such an embodiment is disclosed in FIG. 10.

FIG. 10 schematically illustrates an embodiment of a computer **70** having a processing unit **72**, such as a DSP (Digital Signal Processor) or CPU (Central Processing Unit). The processing unit **72** can be a single unit or a plurality of units for performing different steps of the method described herein. The computer **70** also comprises an input/output (I/O) unit **71** for receiving recorded or generated video frames or encoded video frames and

21

encoded video frame or decoded video data. The I/O unit **71** has been illustrated as a single unit in FIG. **10** but can likewise be in the form of a separate input unit and a separate output unit.

Furthermore, the computer **70** comprises at least one computer program product **73** in the form of a non-volatile memory, for instance an EEPROM (Electrically Erasable Programmable Read-Only Memory), a flash memory or a disk drive. The computer program product **73** comprises a computer program **74**, which comprises code means which when run on the computer **70**, such as by the processing unit **72**, causes the computer **70** to perform the steps of the method described in the foregoing in connection with FIG. **1**. Hence, in an embodiment the code means in the computer program **74** comprises a first offset calculating module or first offset calculator **310** for calculating the first offset and a pixel value modifying module or a pixel value modifier **320** for modifying pixel values of a deblocking filter module **300** or deblocking filter device. These modules **310**, **320** essentially perform the steps of the flow diagram in FIG. **1** when run on the processing unit **72**. Thus, when the different modules **310**, **320** are run on the processing unit **72** they correspond to the corresponding units **110**, **120** of FIG. **8** and units **210**, **220** of FIG. **9**.

The computer program **74** may additionally comprise a first clipping module, a second clipping module, a second offset calculating module, a third offset calculating module and optionally also a third clipping module, a fourth offset calculating module and a fifth offset calculating module to perform the operation of the corresponding units **230-290** in FIG. **9**.

The computer **70** of FIG. **10** can be a user equipment or be present in a user equipment **80**. In such a case, the user equipment **80** may additionally comprise or be connected to a display **88** to display video data.

The deblocking filter unit **100**, **200** of FIGS. **8** and **9** is preferably used in video coding. It functions and is therefore preferably implemented both in a video encoder and in a video decoder. The video decoder can be implemented preferably in hardware but also in software. The same holds for the video encoder.

FIG. **11** is a schematic block diagram of an encoder **40** for encoding a block of pixels in a video frame of a video sequence according to an embodiment.

A current block of pixels is predicted by performing a motion estimation by a motion estimator **50** from an already provided block of pixels in the same frame or in a previous frame. The result of the motion estimation is a motion or displacement vector associated with the reference block, in the case of inter prediction. The motion vector is utilized by a motion compensator **50** for outputting an inter prediction of the block of pixels.

An intra predictor **49** computes an intra prediction of the current block of pixels. The outputs from the motion estimator/compensator **50** and the intra predictor **49** are input in a selector **51** that either selects intra prediction or inter prediction for the current block of pixels. The output from the selector **51** is input to an error calculator in the form of an adder **41** that also receives the pixel values of the current block of pixels. The adder **41** calculates and outputs a residual error as the difference in pixel values between the block of pixels and its prediction.

The error is transformed in a transformer **42**, such as by a discrete cosine transform, and quantized by a quantizer **43** followed by coding in an encoder **44**, such as by entropy encoder. In inter coding, also the estimated motion vector is

22

brought to the encoder **44** for generating the coded representation of the current block of pixels.

The transformed and quantized residual error for the current block of pixels is also provided to an inverse quantizer **45** and inverse transformer **46** to retrieve the original residual error. This error is added by an adder **47** to the block prediction output from the motion compensator **50** or the intra predictor **49** to create a reference block of pixels that can be used in the prediction and coding of a next block of pixels. This new reference block is first processed by a deblocking filter unit **100** according to the embodiments in order to perform deblocking filtering to combat any blocking artifact. The processed new reference block is then temporarily stored in a frame buffer **48**, where it is available to the intra predictor **49** and the motion estimator/compensator **50**.

FIG. **12** is a corresponding schematic block diagram of a decoder **60** comprising a deblocking filter unit **100** according to the embodiments. The decoder **60** comprises a decoder **61**, such as entropy decoder, for decoding an encoded representation of a block of pixels to get a set of quantized and transformed residual errors. These residual errors are dequantized in an inverse quantizer **62** and inverse transformed by an inverse transformer **63** to get a set of residual errors.

These residual errors are added in an adder **64** to the pixel values of a reference block of pixels. The reference block is determined by a motion estimator/compensator **67** or intra predictor **66**, depending on whether inter or intra prediction is performed. A selector **68** is thereby interconnected to the adder **64** and the motion estimator/compensator **67** and the intra predictor **66**. The resulting decoded block of pixels output from the adder **64** is input to a deblocking filter unit **100** according to the embodiments in order to deblocking filter any blocking artifacts. The filtered block of pixels is output from the decoder **60** and is furthermore preferably temporarily provided to a frame buffer **65** and can be used as a reference block of pixels for a subsequent block of pixels to be decoded. The frame buffer **65** is thereby connected to the motion estimator/compensator **67** to make the stored blocks of pixels available to the motion estimator/compensator **67**.

The output from the adder **64** is preferably also input to the intra predictor **66** to be used as an unfiltered reference block of pixels.

In the embodiments disclosed in FIGS. **11** and **12** the deblocking filter unit **100** performs deblocking filtering as so called in-loop filtering. In an alternative implementation at the decoder **60** the deblocking filter unit **100** is arranged to perform so called post-processing filtering. In such a case, the deblocking filter unit **100** operates on the output frames outside of the loop formed by the adder **64**, the frame buffer **65**, the intra predictor **66**, the motion estimator/compensator **67** and the selector **68**. No deblocking filtering is then typically done at the encoder.

FIG. **13** is a schematic block diagram of a user equipment or media terminal **80** housing a decoder **60** with a deblocking filter unit. The user equipment **80** can be any device having media decoding functions that operates on an encoded video stream of encoded video frames to thereby decode the video frames and make the video data available. Non-limiting examples of such devices include mobile telephones and other portable media players, tablets, desktops, notebooks, personal video recorders, multimedia players, video streaming servers, set-top boxes, TVs, computers, decoders, game consoles, etc. The user equipment **80** comprises a memory **84** configured to store encoded video frames. These encoded video frames can have been gener-

23

ated by the user equipment **80** itself. In such a case, the user equipment **80** preferably comprises a media engine or recorder together with a connected encoder, such as the encoder of FIG. **11**. Alternatively, the encoded video frames are generated by some other device and wirelessly transmitted or transmitted by wire to the user equipment **80**. The user equipment **80** then comprises a transceiver (transmitter and receiver) or input and output port **82** to achieve the data transfer.

The encoded video frames are brought from the memory **84** to a decoder **60**, such as the decoder illustrated in FIG. **12**. The decoder **60** comprises a deblocking filter unit **100** according to embodiments. The decoder **60** then decodes the encoded video frames into decoded video frames. The decoded video frames are provided to a media player **86** that is configured to render the decoded video frames into video data that is displayable on a display or screen **88** or of connected to the user equipment **80**.

In FIG. **13**, the user equipment **80** has been illustrated as comprising both the decoder **60** and the media player **86**, with the decoder **60** implemented as a part of the media player **86**. This should, however, merely be seen as an illustrative but non-limiting example of an implementation embodiment for the user equipment **80**. Also distributed implementations are possible where the decoder **60** and the media player **86** are provided in two physically separated devices are possible and within the scope of user equipment **80** as used herein. The display **88** could also be provided as a separate device connected to the user equipment **80**, where the actual data processing is taking place.

As illustrated in FIG. **14**, the encoder **40** and/or decoder **60**, such as illustrated in FIGS. **11** and **12**, may be implemented in a network device **30** being or belonging to a network node in a communication network **32** between a sending unit **34** and a receiving user equipment **36**. Such a network device **30** may be a device for converting video according to one video coding standard to another video coding standard, for example, if it has been established that the receiving user equipment **36** is only capable of or prefers another video coding standard than the one sent from the sending unit **34**. The network device **30** can be in the form of or comprised in a radio base station, a Node-B or any other network node in a communication network **32**, such as a radio-based network.

The embodiments described above are to be understood as a few illustrative examples of the present invention. It will be understood by those skilled in the art that various modifications, combinations and changes may be made to the embodiments without departing from the scope of the present invention. In particular, different part solutions in the different embodiments can be combined in other configurations, where technically possible. The scope of the present invention is, however, defined by the appended claims.

The invention claimed is:

1. A method of reducing blocking artifacts at a block boundary between a block of multiple pixels and a neighboring block of multiple pixels in a video frame, said method comprises:

calculating a first offset to be equal to $(9 \times (q_0 - p_0) - 3 \times (q_1 - p_1) + 8) \gg 4$, wherein $\gg$ denotes a right shift operation, p_0 denotes a pixel value of a pixel closest to said block boundary in a line of pixels in said block, wherein said line of pixels is perpendicular to said block boundary, p_1 denotes a pixel value of a pixel next closest to said block boundary in said line of pixels, q_0 denotes a pixel value of a pixel closest to said block boundary in a corresponding line of pixels in said

24

neighboring block, wherein said corresponding line of pixels is perpendicular to said block boundary and q_1 denotes a pixel value of a pixel next closest to said block boundary in said corresponding line of pixels;

modifying said pixel value p_0 of said pixel closest to said block boundary in said line of pixels by adding said first offset to said pixel value p_0 of said pixel closest to said block boundary in said line of pixels to form a modified pixel value p_0' of said pixel closest to said block boundary in said line of pixels; and

modifying said pixel value q_0 of said pixel closest to said block boundary in said corresponding line of pixels by subtracting said first offset from said pixel value q_0 of said pixel closest to said block boundary in said corresponding line of pixels to form a modified pixel value q_0' of said pixel closest to said block boundary in said corresponding line of pixels.

2. The method according to claim 1, further comprising clipping said first offset to be within an interval of $-t_c$ and t_c by setting said first offset to be equal to $-t_c$ if said first offset is smaller than $-t_c$ and by setting said first offset to be equal to t_c if said first offset is larger than t_c , wherein t_c is a threshold value that is dependent on a quantization parameter value assigned to said block.

3. The method according to claim 1, further comprising: clipping said modified pixel value p_0' of said pixel closest to said block boundary in said line of pixels to be within an interval of zero and a defined maximum value by setting said modified pixel value p_0' of said pixel closest to said block boundary in said line of pixels to be equal to zero if said modified pixel value p_0' of said pixel closest to said block boundary in said line of pixels is smaller than zero and by setting said modified pixel value p_0' of said pixel closest to said block boundary in said line of pixels to be equal to said defined maximum value if said modified pixel value p_0' of said pixel closest to said block boundary in said line of pixels is larger than said defined maximum value; and

clipping said modified pixel value q_0' of said pixel closest to said block boundary in said corresponding line of pixels to be within an interval of zero and said defined maximum value by setting said modified pixel value q_0' of said pixel closest to said block boundary in said corresponding line of pixels to be equal to zero if said modified pixel value q_0' of said pixel closest to said block boundary in said corresponding line of pixels is smaller than zero and by setting said modified pixel value q_0' of said pixel closest to said block boundary in said corresponding line of pixels to be equal to said defined maximum if said modified pixel value q_0' of said pixel closest to said block boundary in said corresponding line of pixels is larger than said defined maximum value.

4. The method according to claim 1, further comprising: calculating a second offset to be based on $(p_2 + p_0 - 2 \times p_1 + 2 \times \Delta) / 4$, wherein p_2 denotes a pixel value of a pixel second next closest to said block boundary in said line of pixels and Δ denotes said first offset;

calculating a third offset to be based on $(q_2 + q_0 - 2 \times q_1 - 2 \times \Delta) / 4$, wherein q_2 denotes a pixel value of a pixel second next closest to said block boundary in said corresponding line of pixels;

modifying said pixel value p_1 of said pixel next closest to said block boundary in said line of pixels by adding said second offset to said pixel value p_1 of said pixel next closest to said block boundary in said line of pixels

25

to form a modified pixel value p1' of said pixel next closest to said block boundary in said line of pixels; and modifying said pixel value q1 of said pixel next closest to said block boundary in said corresponding line of pixels by adding said third offset to said pixel value q1 of said pixel next closest to said block boundary in said corresponding line of pixels to form a modified pixel value q1' of said pixel next closest to said block boundary in said corresponding line of pixels.

5. The method according to claim 4, wherein calculating said second offset comprises calculating said second offset to be equal to $((p2+p0+1)>>1)-p1+\Delta$, wherein $>>$ denotes a right shift operation; and calculating said third offset comprises calculating said third offset to be equal to $((q2+q0+1)>>1)-q1-\Delta$.

6. The method according to claim 4, further comprising: clipping said second offset to be within an interval of $-t_{c2}$ and t_{c2} by setting said second offset to be equal to $-t_{c2}$ if said second offset is smaller than $-t_{c2}$ and by setting said second offset to be equal to t_{c2} if said second offset is larger than t_{c2} , wherein $-t_{c2}$ is a threshold value that is dependent on a quantization parameter value assigned to said block; and

clipping said third offset within an interval of $-t_{c2}$ and t_{c2} by setting said third offset to be equal to $-t_{c2}$ if said third offset is smaller than $-t_{c2}$ and by setting said third offset to be equal to t_{c2} if said third offset is larger than t_{c2} .

7. The method according to claim 4, further comprising: clipping said modified pixel value p1' of said pixel next closest to said block boundary in said line of pixels to be within an interval of zero and a defined maximum value by setting said modified pixel value p1' of said pixel next closest to said block boundary in said line of pixels to be equal to zero if said modified pixel value p1' of said pixel next closest to said block boundary in said line of pixels is smaller than zero and by setting said modified pixel value p1' of said pixel next closest to said block boundary in said line of pixels to be equal to said defined maximum value if said modified pixel value p1' of said pixel next closest to said block boundary in said line of pixels is larger than said defined maximum value; and

clipping said modified pixel value q1' of said pixel next closest to said block boundary in said corresponding line of pixels to be within an interval of zero and said defined maximum value by setting said modified pixel value q1' of said pixel next closest to said block boundary in said corresponding line of pixels to be equal to zero if said modified pixel value q1' of said pixel next closest to said block boundary in said corresponding line of pixels is smaller than zero and by setting said modified pixel value q1' of said pixel next closest to said block boundary in said corresponding line of pixels to be equal to said defined maximum if said modified pixel value q1' of said pixel next closest to said block boundary in said corresponding line of pixels is larger than said defined maximum value.

8. The method according to claim 4, further comprising: calculating a fourth offset to be based on $(p3+p1-2 \times p2+2 \times \Delta_{p1})/4$, wherein p3 denotes a pixel value of a pixel third next closest to said block boundary in said line of pixels and Δ_{p1} denotes said second offset; and calculating a fifth offset to be based on $(q3+q1-2 \times q2+2 \times \Delta_{q1})/4$, wherein q3 denotes a pixel value of a pixel third closest to said block boundary in said corresponding line of pixels and Δ_{q1} denotes said third offset;

26

modifying said pixel value p2 of said pixel second next closest to said block boundary in said line of pixels by adding said fourth offset to said pixel value p2 of said pixel second next closest to said block boundary in said line of pixels to form a modified pixel value p2' of said pixel second next closest to said block boundary in said line of pixels; and

modifying said pixel value q2 of said pixel second next closest to said block boundary in said corresponding line of pixels by adding said fifth offset to said pixel value q2 of said pixel second next closest to said block boundary in said corresponding line of pixels to form a modified pixel value q2' of said pixel second next closest to said block boundary in said corresponding line of pixels.

9. The method according to claim 8, wherein calculating said fourth offset comprises calculating said fourth offset to be equal to $((p3+p1+1)>>1)-p2+\Delta_{p1}$, wherein $>>$ denotes a right shift operation; and

calculating said fifth offset comprises calculating said fifth offset to be equal to $((q3+q1+1)>>1)-q2+\Delta_{q1}$.

10. A user equipment comprising a deblocking filter unit for reducing blocking artifacts at a block boundary between a block of multiple pixels and a neighboring block of multiple pixels in a video frame, wherein the deblocking filter unit comprises:

a first offset calculator configured to calculate a first offset to be equal to $(9 \times (q0-p0)-3 \times (q1-p1)+8)>>4$, wherein $>>$ denotes a right shift operation, p0 denotes a pixel value of a pixel closest to said block boundary in a line of pixels in said block, wherein said line of pixels is perpendicular to said block boundary, p1 denotes a pixel value of a pixel next closest to said block boundary in said line of pixels, q0 denotes a pixel value of a pixel closest to said block boundary in a corresponding line of pixels in said neighboring block, wherein said corresponding line of pixels is perpendicular to said block boundary, and q1 denotes a pixel value of a pixel next closest to said block boundary in said corresponding line of pixels; and

a pixel value modifier configured to modify said pixel value p0 of said pixel closest to said block boundary in said line of pixels by adding said first offset to said pixel value p0 of said pixel closest to said block boundary in said line of pixels to form a modified pixel value p0' of said pixel closest to said block boundary in said line of pixels and to modify said pixel value q0 of said pixel closest to said block boundary in said corresponding line of pixels by subtracting said first offset from said pixel value q0 of said pixel closest to said block boundary in said corresponding line of pixels to form a modified pixel value q0' of said pixel closest to said block boundary in said corresponding line of pixels.

11. The user equipment according to claim 10, wherein the deblocking filter unit further comprises a first clipping unit configured to clip said first offset within an interval of $-t_c$ and t_c by setting said first offset to be equal to $-t_c$ if said first offset is smaller than $-t_c$ and by setting said first offset to be equal to t_c if said first offset is larger than t_c , wherein t_c is a threshold value that is dependent on a quantization parameter value assigned to said block.

12. The user equipment according to claim 10, wherein the deblocking filter unit further comprises a second clipping unit configured to clip said modified pixel value p0' of said pixel closest to said block boundary in said line of pixels to be within an interval of zero and a defined maximum value

27

by setting said modified pixel value $p0'$ of said pixel closest to said block boundary in said line of pixels to be equal to zero if said modified pixel value $p0'$ of said pixel closest to said block boundary in said line of pixels is smaller than zero and by setting said modified pixel value $p0'$ of said pixel closest to said block boundary in said line of pixels to be equal to said defined maximum value if said modified pixel value $p0'$ of said pixel closest to said block boundary in said line of pixels is larger than said defined maximum value and to clip said modified pixel value $q0'$ of said pixel closest to said block boundary in said corresponding line of pixels to be within an interval of zero and said defined maximum value by setting said modified pixel value $q0'$ of said pixel closest to said block boundary in said corresponding line of pixels to be equal to zero if said modified pixel value $q0'$ of said pixel closest to said block boundary in said corresponding line of pixels is smaller than zero and by setting said modified pixel value $q0'$ of said pixel closest to said block boundary in said corresponding line of pixels to be equal to said defined maximum if said modified pixel value $q0'$ of said pixel closest to said block boundary in said corresponding line of pixels is larger than said defined maximum value.

13. The user equipment according to claim 10, wherein the deblocking filter unit further comprises:

a second offset calculator configured to calculate a second offset to be based on $(p2+p0-2 \times p1+2 \times \Delta)/4$, wherein $p2$ denotes a pixel value of a pixel second next closest to said block boundary in said line of pixels and Δ denotes said first offset; and

a third offset calculator configured to calculate a third offset to be based on $(q2+q0-2 \times q1-2 \times \Delta)/4$, wherein $q2$ denotes a pixel value of a pixel second next closest to said block boundary in said corresponding line of pixels,

wherein said pixel value modifier is configured to modify said pixel value $p2$ of said pixel second next closest to said block boundary in said line of pixels by adding said second offset to said pixel value $p2$ of said pixel second next closest to said block boundary in said line of pixels to form a modified pixel value $p2'$ of said pixel second next closest to said block boundary in said line of pixels and to modify said pixel value $q2$ of said pixel second next closest to said block boundary in said corresponding line of pixels by adding said third offset to said pixel value $q2$ of said pixel second next closest to said block boundary in said corresponding line of pixels to form a modified pixel value $q2'$ of said pixel second next closest to said block boundary in said corresponding line of pixels.

14. The user equipment according to claim 13, wherein said second offset calculator is configured to calculate said second offset to be equal to $((p2+p0+1) \gg 1) - p1 + \Delta \gg 1$, wherein $\gg$ denotes a right shift operation; and said third offset calculator is configured to calculate said third offset to be equal to $((q2+q0+1) \gg 1) - q1 - \Delta \gg 1$.

15. The user equipment according to claim 13, wherein the deblocking filter unit further comprises a third clipping unit configured to clip said second offset to be within an interval of $-t_{c2}$ and t_{c2} by setting said second offset to be equal to $-t_{c2}$ if said second offset is smaller than $-t_{c2}$ and by setting said second offset to be equal to t_{c2} if said second offset is larger than t_{c2} , wherein t_{c2} is a threshold value that is dependent on a quantization parameter value assigned to said block, and to clip said third offset within an interval of $-t_{c2}$ and t_{c2} by setting said third offset to be equal to $-t_{c2}$ if said third offset is smaller than $-t_{c2}$ and by setting said third offset to be equal to t_{c2} if said third offset is larger than t_{c2} .

28

16. The user equipment according to claim 13, wherein the user equipment further comprises a second clipping unit configured to clip said modified pixel value $p1'$ of said pixel next closest to said block boundary in said line of pixels to be within an interval of zero and a defined maximum value by setting said modified pixel value $p1'$ of said pixel next closest to said block boundary in said line of pixels to be equal to zero if said modified pixel value $p1'$ of said pixel next closest to said block boundary in said line of pixels is smaller than zero and by setting said modified pixel value $p1'$ of said pixel next closest to said block boundary in said line of pixels to be equal to said defined maximum value if said modified pixel value $p1'$ of said pixel next closest to said block boundary in said line of pixels is larger than said defined maximum value, and to clip said modified pixel value $q1'$ of said pixel next closest to said block boundary in said corresponding line of pixels to be within an interval of zero and said defined maximum value by setting said modified pixel value $q1'$ of said pixel next closest to said block boundary in said corresponding line of pixels to be equal to zero if said modified pixel value $q1'$ of said pixel next closest to said block boundary in said corresponding line of pixels is smaller than zero and by setting said modified pixel value $q1'$ of said pixel next closest to said block boundary in said corresponding line of pixels to be equal to said defined maximum if said modified pixel value $q1'$ of said pixel next closest to said block boundary in said corresponding line of pixels is larger than said defined maximum value.

17. The user equipment according to claim 13, wherein the deblocking filter unit further comprises:

a fourth offset calculator configured to calculate a fourth offset to be based on $(p3+p1-2 \times p2+2 \times \Delta_{p1})/4$, wherein $p3$ denotes a pixel value of a pixel third next closest to said block boundary in said line of pixels and Δ_{p1} denotes said second offset; and a fifth offset calculator configured to calculate a fifth offset to be based on $(q3+q1-2 \times q2+2 \times \Delta_{q1})/4$, wherein $q3$ denotes a pixel value of a pixel third closest to said block boundary in said corresponding line of pixels and Δ_{q1} denotes said third offset,

wherein said pixel value modifier is configured to modify said pixel value $p2$ of said pixel second next closest to said block boundary in said line of pixels by adding said fourth offset to said pixel value $p2$ of said pixel second next closest to said block boundary in said line of pixels to form a modified pixel value $p2'$ of said pixel second next closest to said block boundary in said line of pixels, and to modify said pixel value $q2$ of said pixel second next closest to said block boundary in said corresponding line of pixels by adding said fifth offset to said pixel value $q2$ of said pixel second next closest to said block boundary in said corresponding line of pixels to form a modified pixel value $q2'$ of said pixel second next closest to said block boundary in said corresponding line of pixels.

18. The user equipment according to claim 17, wherein said fourth offset calculator is configured to calculate said fourth offset to be equal to $((p3+p1+1) \gg 1) - p2 + \Delta_{p1} \gg 1$, wherein $\gg$ denotes a right shift operation; and said fifth offset calculator is configured to calculate said fifth offset to be equal to $((q3+q1+1) \gg 1) - q2 + \Delta_{q1} \gg 1$.

* * * * *