Handbook of Photovoltaic Science and Engineering

Edited by

Antonio Luque
Instituto de Energía Solar, Universidad Politécnica de Madrid, Spain

and

Steven Hegedus
Institute of Energy Conversion, University of Delaware, USA



TK8322
.H36
2003

Copyright © 2003 John Wiley & Sons Ltd, The Atrium, Southern Gate, Chichester,
West Sussex PO19 8SQ, England

Telephone (+44) 1243 779777

Email (for orders and customer service enquiries): cs-books@wiley.co.uk
Visit our Home Page on www.wileyeurope.com or www.wiley.com

All Rights Reserved. No part of this publication may be reproduced, stored in a retrieval system or transmitted in any form or by any means, electronic, mechanical, photocopying, recording, scanning or otherwise, except under the terms of the Copyright, Designs and Patents Act 1988 or under the terms of a licence issued by the Copyright Licensing Agency Ltd, 90 Tottenham Court Road, London W1T 4LP, UK, without the permission in writing of the Publisher. Requests to the Publisher should be addressed to the Permissions Department, John Wiley & Sons Ltd, The Atrium, Southern Gate, Chichester, West Sussex PO19 8SQ, England, or emailed to permreq@wiley.co.uk, or faxed to (+44) 1243 770620.

This publication is designed to provide accurate and authoritative information in regard to the subject matter covered. It is sold on the understanding that the Publisher is not engaged in rendering professional services. If professional advice or other expert assistance is required, the services of a competent professional should be sought.

Other Wiley Editorial Offices

John Wiley & Sons Inc., 111 River Street, Hoboken, NJ 07030, USA

Jossey-Bass, 989 Market Street, San Francisco, CA 94103-1741, USA

Wiley-VCH Verlag GmbH, Boschstr. 12, D-69469 Weinheim, Germany

John Wiley & Sons Australia Ltd, 33 Park Road, Milton, Queensland 4064, Australia

John Wiley & Sons (Asia) Pte Ltd, 2 Clementi Loop #02-01, Jin Xing Distripark, Singapore 129809

John Wiley & Sons Canada Ltd, 22 Worcester Road, Etobicoke, Ontario, Canada M9W 1L1

Wiley also publishes its books in a variety of electronic formats. Some content that appears in print may not be available in electronic books.

Library of Congress Cataloging-in-Publication Data

Handbook of photovoltaic science and engineering / edited by Antonio Luque and Steven Hegedus.
p. cm.
Includes bibliographical references and index.
ISBN 0-471-49196-9 (alk. paper)
1. Photovoltaic cells. 2. Photovoltaic power generation. I. Luque, A. (Antonio) II. Hegedus, Steven.

TK8322 .H33 2003
621.31′244 – dc21

2002191033

British Library Cataloguing in Publication Data

A catalogue record for this book is available from the British Library

ISBN 0-471-49196-9

Typeset in 10/12 Times by Laserwords Private Limited, Chennai, India
Printed and bound in Great Britain by Antony Rowe Ltd, Chippenham, Wiltshire
This book is printed on acid-free paper responsibly manufactured from sustainable forestry in which at least two trees are planted for each one used for paper production.

Contents

List of Contributors xxiii

1 Status, Trends, Challenges and the Bright Future of Solar Electricity from Photovoltaics 1
Steven S. Hegedus and Antonio Luque
1.1 The Big Picture 1
1.2 What Is Photovoltaics? 3
1.3 Six Myths of Photovoltaics 5
1.4 History of Photovoltaics 11
1.5 PV Costs, Markets and Forecasts 15
1.6 What Are the Goals of Today's PV Research and Manufacturing? 19
1.7 Global Trends in Performance and Applications 20
1.8 Crystalline Silicon Progress and Challenges 23
1.9 Thin Film Progress and Challenges 27
1.10 Concentration PV Systems 31
1.11 Balance of Systems 32
1.12 Future of Emerging PV Technologies 37
1.13 Conclusions 39
References 41

2 Motivation for Photovoltaic Application and Development 45
Joachim Luther
2.1 Characteristics of Photovoltaic Energy Conversion 45
2.2 A Long-term Substitute for Today's Conventional Electricity Production – The Ecological Dimension of Photovoltaics 48
2.2.1 In Summary 54
2.3 A Technological Basis for Off-grid Electricity Supply – The Development Dimension of Photovoltaics 54
2.3.1 In Summary 57
2.4 Power Supply for Industrial Systems and Products – The Professional Low Power Dimension 57
2.5 Power for Spacecraft and Satellites – the Extraterrestrial Dimension of Photovoltaics 59
References 60

3 The Physics of the Solar Cell **61**
Jeffery L. Gray
3.1 Introduction 61
3.2 Fundamental Properties of Semiconductors 64
3.2.1 Crystal Structure 64
3.2.2 Energy Band Structure 65
3.2.3 Conduction-band and Valence-band Densities of State 66
3.2.4 Equilibrium Carrier Concentrations 67
3.2.5 Light Absorption 70
3.2.6 Recombination 74
3.2.7 Carrier Transport 78
3.2.8 Semiconductor Equations 81
3.2.9 Minority-carrier Diffusion Equation 82
3.3 *PN*-Junction Diode Electrostatics 83
3.4 Solar Cell Fundamentals 87
3.4.1 Solar Cell Boundary Conditions 87
3.4.2 Generation Rate 89
3.4.3 Solution of the Minority-carrier Diffusion Equation 89
3.4.4 Terminal Characteristics 89
3.4.5 Solar Cell $I-V$ Characteristics 92
3.4.6 Properties of Efficient Solar Cells 95
3.4.7 Lifetime and Surface Recombination Effects 96
3.4.8 An Analogy for Understanding Solar Cell Operation: A Partial Summary 98
3.5 Additional Topics 99
3.5.1 Efficiency and Band gap 99
3.5.2 Spectral Response 100
3.5.3 Parasitic Resistance Effects 102
3.5.4 Temperature Effects 104
3.5.5 Concentrator Solar Cells 106
3.5.6 High-level Injection 107
3.5.7 *p-i-n* Solar Cells 109
3.5.8 Detailed Numerical Modeling 109
3.6 Summary 110
References 111

4 Theoretical Limits of Photovoltaic Conversion **113**
Antonio Luque and Antonio Martí
4.1 Introduction 113
4.2 Thermodynamic Background 114
4.2.1 Basic Relationships 114
4.2.2 The Two Laws of Thermodynamics 116
4.2.3 Local Entropy Production 116
4.2.4 An Integral View 117
4.2.5 Thermodynamic Functions of Radiation 117
4.2.6 Thermodynamic Functions of Electrons 119
4.3 Photovoltaic Converters 120

4.3.1 The Balance Equation of a PV Converter 120
4.3.2 The Monochromatic Cell 124
4.3.3 Thermodynamic Consistence of the Shockley–Queisser Photovoltaic Cell 126
4.3.4 Entropy Production in the Whole Shockley–Queisser Solar Cell 129
4.4 The Technical Efficiency Limit for Solar Converters 131
4.5 Very High Efficiency Concepts 132
4.5.1 Multijunction Solar Cells 132
4.5.2 Thermophotovoltaic Converters 135
4.5.3 Thermophotonic Converters 136
4.5.4 Higher-than-one Quantum Efficiency Solar Cells 140
4.5.5 Hot Electron Solar Cells 141
4.5.6 Intermediate Band Solar Cell 144
4.6 Conclusions 148
References 149

5 Solar Grade Silicon Feedstock 153
Bruno Ceccaroli and Otto Lohne
5.1 Introduction 153
5.2 Silicon 154
5.2.1 Physical Properties of Silicon Relevant to Photovoltaics 154
5.2.2 Chemical Properties Relevant to Photovoltaics 156
5.2.3 Health Factors 156
5.2.4 History and Applications of Silicon 157
5.3 Production of Metallurgical Grade Silicon 161
5.3.1 The Carbothermic Reduction of Silica 161
5.3.2 Refining 163
5.3.3 Casting and Crushing 166
5.3.4 Economics 167
5.4 Production of Semiconductor Grade Silicon (Polysilicon) 167
5.4.1 The Siemens Process 168
5.4.2 The Union Carbide Process 172
5.4.3 The Ethyl Corporation Process 173
5.4.4 Economics and Business 175
5.5 Current Silicon Feedstock to Solar Cells 175
5.6 Requirements of Silicon for Crystalline Solar Cells 179
5.6.1 Solidification 179
5.6.2 Effect of Crystal Imperfections 182
5.6.3 Effect of Various Impurities 186
5.7 Routes to Solar Grade Silicon 193
5.7.1 Crystallisation 193
5.7.2 Upgrading Purity of the Metallurgical Silicon Route 194
5.7.3 Simplification of the Polysilicon Process 198
5.7.4 Other Methods 201
5.8 Conclusions 201
References 202

6 Bulk Crystal Growth and Wafering for PV **205**
W. Koch, A. L. Endrös, D. Franke, C. Häßler, J. P. Kalejs and H. J. Möller
6.1 Introduction 205
6.2 Bulk Monocrystalline Material 206
6.2.1 Cz Growth of Single-crystal Silicon 207
6.2.2 Tri-crystalline Silicon 211
6.3 Bulk Multicrystalline Silicon 214
6.3.1 Ingot Fabrication 214
6.3.2 Doping 216
6.3.3 Crystal Defects 217
6.3.4 Impurities 219
6.4 Wafering 223
6.4.1 Multi-wire Wafering Technique 224
6.4.2 Microscopic Process of Wafering 226
6.4.3 Wafer Quality and Saw Damage 229
6.4.4 Cost and Size Considerations 230
6.5 Silicon Ribbon and Foil Production 230
6.5.1 Process Description 232
6.5.2 Productivity Comparisons 238
6.5.3 Manufacturing Technology 239
6.5.4 Ribbon Material Properties and Solar Cells 240
6.5.5 Ribbon/Foil Technology – Future Directions 243
6.6 Numerical Simulations of Crystal Growth Techniques 244
6.6.1 Simulation Tools 245
6.6.2 Thermal Modelling of Silicon Crystallisation Techniques 245
6.6.3 Simulation of Bulk Silicon Crystallisation 247
6.6.4 Simulation of Silicon Ribbon Growth 249
6.7 Conclusions 251
6.8 Acknowledgement 252
References 252

7 Crystalline Silicon Solar Cells and Modules **255**
Ignacio Tobías, Carlos del Cañizo and Jesús Alonso
7.1 Introduction 255
7.2 Crystalline Silicon as a Photovoltaic Material 257
7.2.1 Bulk Properties 257
7.2.2 Surfaces 257
7.3 Crystalline Silicon Solar Cells 259
7.3.1 Cell Structure 259
7.3.2 Substrate 260
7.3.3 The Front Surface 263
7.3.4 The Back Surface 266
7.3.5 Size Effects 266
7.3.6 Cell Optics 268
7.3.7 Performance Comparison 270

7.4 Manufacturing Process 271
7.4.1 Process Flow 271
7.4.2 Screen-printing Technology 276
7.4.3 Throughput and Yield 279
7.5 Variations to the Basic Process 280
7.5.1 Thin Wafers 280
7.5.2 Back Surface Passivation 281
7.5.3 Improvements to the Front Emitter 281
7.5.4 Rapid Thermal Processes 282
7.6 Multicrystalline Cells 283
7.6.1 Gettering in mc Solar Cells 283
7.6.2 Passivation with Hydrogen 283
7.6.3 Optical Confinement 285
7.7 Other Industrial Approaches 288
7.7.1 Silicon Ribbons 288
7.7.2 Heterojunction with Intrinsic Thin Layer 288
7.7.3 Buried Contact Technology 289
7.8 Crystalline Silicon Photovoltaic Modules 291
7.8.1 Cell Matrix 291
7.8.2 The Layers of the Module 292
7.8.3 Lamination and Curing 293
7.8.4 Postlamination Steps 294
7.8.5 Special Modules 294
7.9 Electrical and Optical Performance of Modules 295
7.9.1 Electrical and Thermal Characteristics 295
7.9.2 Fabrication Spread and Mismatch Losses 297
7.9.3 Local Shading and Hot Spot Formation 297
7.9.4 Optical Properties 300
7.10 Field Performance of Modules 301
7.10.1 Lifetime 301
7.10.2 Qualification 301
7.11 Conclusions 302
References 303

8 Thin-film Silicon Solar Cells 307
Bhushan Sopori
8.1 Introduction 307
8.2 A Review of Current Thin-film Si Cells 310
8.2.1 Single-crystal Films Using Single-crystal Si Substrates 317
8.2.2 Multicrystalline-Si Substrates 320
8.2.3 Non-Si Substrates 321
8.3 Design Concepts of TF-Si Solar Cells 324
8.3.1 Light-trapping in Thin Si Solar Cells 326
8.3.2 Description of PV Optics 327
8.3.3 Electronic Modeling 333
8.3.4 Methods of Making Thin-Si Films for Solar Cells 341

8.3.5 Methods of Grain Enhancement of a-Si/μc-Si Thin Films 343
8.3.6 Processing Considerations for TF-Si Solar Cell Fabrication 350
8.4 Conclusion 353
References 354

9 High-Efficiency III-V Multijunction Solar Cells 359
J. M. Olson, D. J. Friedman and Sarah Kurtz
9.1 Introduction 359
9.2 Applications 363
9.2.1 Space Solar Cells 363
9.2.2 Terrestrial Energy Production 363
9.3 Physics of III-V Multijunction and Single-junction Solar Cells 363
9.3.1 Wavelength Dependence of Photon Conversion Efficiency 363
9.3.2 Theoretical Limits to Multijunction Efficiencies 364
9.3.3 Spectrum Splitting 364
9.4 Cell Configuration 365
9.4.1 Four-terminal 365
9.4.2 Three-terminal Voltage-matched Interconnections 366
9.4.3 Two-terminal Series-connected (Current Matched) 366
9.5 Computation of Series-Connected Device Performance 366
9.5.1 Overview 366
9.5.2 Top and Bottom Subcell QE and J_{SC} 367
9.5.3 Multijunction $J-V$ Curves 368
9.5.4 Efficiency versus Band Gap 370
9.5.5 Top-cell Thinning 372
9.5.6 Current-matching Effect on Fill Factor and V_{OC} 373
9.5.7 Spectral Effects 374
9.5.8 AR Coating Effects 375
9.5.9 Concentration 376
9.5.10 Temperature Dependence 380
9.6 Materials Issues Related to GaInP/GaAs/Ge Solar Cells 382
9.6.1 Overview 382
9.6.2 MOCVD 382
9.6.3 GaInP Solar Cells 383
9.6.4 GaAs Cells 393
9.6.5 Ge Cells 395
9.6.6 Tunnel-junction Interconnects 396
9.6.7 Chemical Etchants 397
9.6.8 Materials Availability 398
9.7 Troubleshooting 398
9.7.1 Characterization of Epilayers 398
9.7.2 Transmission Line Measurements 400
9.7.3 I-V Measurements of Multijunction Cells 400
9.7.4 Evaluation of Morphological Defects 401
9.7.5 Device Diagnosis 401

9.8 Future-generation Solar Cells 403
9.8.1 Refinements to the GaInP/GaAs/Ge Cell 403
9.8.2 Mechanical Stacks 404
9.8.3 Growth on Other Substrates 405
9.8.4 Spectrum Splitting 406
9.9 Implementation into Terrestrial Systems 406
9.9.1 Economic Issues 406
9.9.2 Concentrator Systems 406
9.9.3 Terrestrial Spectrum 407
References 407

10 Space Solar Cells and Arrays 413
Sheila Bailey and Ryne Raffaelle
10.1 The History of Space Solar Cells 413
10.1.1 Vanguard I to Deep Space I 413
10.2 The Challenge for Space Solar Cells 416
10.2.1 The Space Environment 417
10.2.2 Thermal Environment 420
10.2.3 Solar Cell Calibration and Measurement 424
10.3 Silicon Solar Cells 425
10.4 III-V Solar Cells 426
10.4.1 Thin-film Solar Cells 428
10.5 Space Solar Arrays 431
10.5.1 Body-mounted Arrays 432
10.5.2 Rigid Panel Planar Arrays 432
10.5.3 Flexible Fold-out Arrays 433
10.5.4 Thin-film or Flexible Roll-out Arrays 435
10.5.5 Concentrating Arrays 436
10.5.6 High-temperature/Intensity Arrays 438
10.5.7 Electrostatically Clean Arrays 439
10.5.8 Mars Solar Arrays 440
10.5.9 Power Management and Distribution (PMAD) 441
10.6 Future Cell and Array Possibilities 441
10.6.1 Low Intensity Low Temperature (LILT) Cells 441
10.6.2 Quantum Dot Solar Cells 442
10.6.3 Integrated Power Systems 442
10.6.4 High Specific Power Arrays 443
10.6.5 High-radiation Environment Solar Arrays 443
10.7 Power System Figures of Merit 444
References 446

11 Photovoltaic Concentrators 449
Richard M. Swanson
11.1 Introduction 449
11.1.1 The Concentrator Dilemma 450
11.2 Basic Types of Concentrators 452
11.2.1 Types of Optics 452
11.2.2 Concentration Ratio 455

11.2.3 Types of Tracking 456
11.2.4 Static Concentrators 456
11.3 Historical Overview 460
11.3.1 The Sandia National Laboratories Concentrator Program (1976 to 1993) 461
11.3.2 The Martin Marietta Point-focus Fresnel System 462
11.3.3 The Entech Linear-focus Fresnel System 463
11.3.4 Other Sandia Projects 465
11.3.5 The Concentrator Initiative 465
11.3.6 Early Demonstration Projects 466
11.3.7 The EPRI High-concentration Program 467
11.3.8 Other Concentrator Programs 471
11.3.9 History of Performance Improvements 472
11.4 Optics of Concentrators 474
11.4.1 Basics 474
11.4.2 Reflection and Refraction 478
11.4.3 The Parabolic Concentrator 479
11.4.4 The Compound Parabolic Concentrator 482
11.4.5 The V-trough Concentrator 483
11.4.6 Refractive Lenses 485
11.4.7 Secondary Optics 489
11.4.8 Static Concentrators 491
11.4.9 Innovative Concentrators 492
11.4.10 Issues in Concentrator Optics 494
11.5 Current Concentrator Activities 495
11.5.1 Amonix 496
11.5.2 Australian National University 496
11.5.3 BP Solar and the Polytechnical University of Madrid 496
11.5.4 Entech 497
11.5.5 Fraunhofer-Institut fur Solare Energiesysteme 497
11.5.6 Ioffe Physical-Technical Institute 498
11.5.7 National Renewable Energy Laboratory 498
11.5.8 Polytechnical University of Madrid 498
11.5.9 Solar Research Corporation 499
11.5.10 Spectrolab 499
11.5.11 SunPower Corporation 499
11.5.12 University of Reading 500
11.5.13 Tokyo A&T University 500
11.5.14 Zentrum fur Sonnenenergie und Wasserstoff Forschung Baden Wurttenberg (ZSW) 500
References 500

12 Amorphous Silicon–based Solar Cells 505
Xunming Deng and Eric A. Schiff
12.1 Overview 505
12.1.1 Amorphous Silicon: The First Bipolar Amorphous Semiconductor 505

12.1.2 Designs for Amorphous Silicon Solar Cells: A Guided Tour 508
12.1.3 Staebler–Wronski Effect 511
12.1.4 Synopsis of this Chapter 512
12.2 Atomic and Electronic Structure of Hydrogenated Amorphous Silicon 513
12.2.1 Atomic Structure 513
12.2.2 Defects and Metastability 514
12.2.3 Electronic Density-of-states 515
12.2.4 Bandtails, Bandedges, and Band Gaps 516
12.2.5 Defects and Gap States 517
12.2.6 Doping 518
12.2.7 Alloying and Optical Properties 518
12.3 Depositing Amorphous Silicon 520
12.3.1 Survey of Deposition Techniques 520
12.3.2 RF Glow Discharge Deposition 521
12.3.3 Glow Discharge Deposition at Different Frequencies 523
12.3.4 Hot-wire Chemical Vapor Deposition 525
12.3.5 Other Deposition Methods 526
12.3.6 Hydrogen Dilution 526
12.3.7 Alloys and Doping 528
12.4 Understanding a-Si *pin* Cells 528
12.4.1 Electronic Structure of a *pin* Device 528
12.4.2 Photocarrier Drift in Absorber Layers 530
12.4.3 Absorber Layer Design of a *pin* Solar Cell 533
12.4.4 The Open-circuit Voltage 534
12.4.5 Optical Design of a-Si:H Solar Cells 537
12.4.6 Cells under Solar Illumination 540
12.4.7 Light-soaking Effects 541
12.5 Multiple-Junction Solar Cells 542
12.5.1 Advantages of Multiple-junction Solar Cells 542
12.5.2 Using Alloys for Cells with Different Band Gaps 544
12.5.3 a-Si/a-SiGe Tandem and a-Si/a-SiGe/a-SiGe Triple-junction Solar Cells 546
12.5.4 Microcrystalline Silicon Solar Cells 551
12.5.5 Micromorph and Other μc-Si-based Multijunction Cells 552
12.6 Module Manufacturing 553
12.6.1 Continuous Roll-to-roll Manufacturing on Stainless Steel Substrates 553
12.6.2 a-Si Module Production on Glass Superstrate 555
12.6.3 Manufacturing Cost, Safety, and Other Issues 556
12.6.4 Module Performance 557
12.7 Conclusions and Future Projections 558
12.7.1 Status and Competitiveness of a-Si Photovoltaics 558
12.7.2 Critical Issues for Further Enhancement and Future Potential 559
12.8 Acknowledgments 559
References 560

13 Cu(InGa)Se_2 Solar Cells **567**
William N. Shafarman and Lars Stolt
13.1 Introduction 567
13.2 Material Properties 570
13.2.1 Structure and Composition 571
13.2.2 Optical Properties 574
13.2.3 Electrical Properties 574
13.2.4 The Surface and Grain Boundaries 576
13.2.5 Substrate Effects 578
13.3 Deposition Methods 578
13.3.1 Substrates 579
13.3.2 Back Contact 580
13.3.3 Coevaporation of Cu(InGa)Se_2 580
13.3.4 Two-step Processes 583
13.3.5 Other Deposition Approaches 584
13.4 Junction and Device Formation 584
13.4.1 Chemical Bath Deposition 585
13.4.2 Interface Effects 586
13.4.3 Other Deposition Methods 587
13.4.4 Alternative Buffer Layers 588
13.4.5 Transparent Contacts 590
13.4.6 Buffer Layers 591
13.4.7 Device Completion 592
13.5 Device Operation 592
13.5.1 Light-generated Current 593
13.5.2 Recombination 595
13.5.3 The Cu(InGa)Se_2/CdS Interface 599
13.5.4 Wide and Graded Band Gap Devices 600
13.6 Manufacturing Issues 602
13.6.1 Processes and Equipment 602
13.6.2 Module Fabrication 604
13.6.3 Module Performance 604
13.6.4 Production Costs 607
13.6.5 Environmental Concerns 608
13.7 The Cu(InGa)Se_2 Outlook 609
References 611

14 Cadmium Telluride Solar Cells **617**
Brian E. McCandless and James R. Sites
14.1 Introduction 617
14.2 CdTe Properties and Thin-film Fabrication Methods 621
14.2.1 Condensation/Reaction of Cd and Te_2 Vapors on a Surface 628
14.2.2 Galvanic Reduction of Cd and Te Ions at a Surface 629
14.2.3 Precursor Reaction at a Surface 630
14.3 CdTe Thin-Film Solar Cells 631
14.3.1 Window Layers 631
14.3.2 CdTe Absorber Layer and $CdCl_2$ Treatment 633

14.3.3 CdS/CdTe Intermixing 637
14.3.4 Back Contact 642
14.3.5 Solar Cell Characterization 644
14.3.6 Summary of CdTe-cell Status 650
14.4 CdTe Modules 651
14.5 The Future of CdTe-based Solar Cells 653
14.6 Acknowledgments 657
References 657

15 Dye-sensitized Solar Cells 663
Kohjiro Hara and Hironori Arakawa
15.1 Introduction to Dye-Sensitized Solar Cells (DSSC) 663
15.1.1 Background 663
15.1.2 Structure and Materials 664
15.1.3 Mechanism 670
15.1.4 Charge-transfer Kinetics 673
15.1.5 Characteristics 678
15.2 DSSC Fabrication ($\eta = 8\%$) 678
15.2.1 Preparation of TiO_2 Colloid 678
15.2.2 Preparation of the TiO_2 Electrode 679
15.2.3 Dye Fixation onto the TiO_2 Film 680
15.2.4 Redox Electrolyte 681
15.2.5 Counter Electrode 681
15.2.6 Assembling the Cell and Cell Performance 681
15.3 New Developments 682
15.3.1 New Oxide Semiconductor Film Photoelectrodes 683
15.3.2 New Dye Photosensitizers 683
15.3.3 New Electrolytes 688
15.3.4 Quasi-solid-state and Solid-state DSSCs 689
15.4 Approach to Commercialization 691
15.4.1 Stability of the DSSC 691
15.4.2 Module Fabrication and Other Subjects for Commercialization 694
15.5 Summary and Prospects 695
References 696

16 Measurement and Characterization of Solar Cells and Modules 701
Keith Emery
16.1 Introduction 701
16.2 Rating PV Performance 701
16.2.1 Standard Reporting Conditions 702
16.2.2 Alternative Peak Power Ratings 715
16.2.3 Energy-based Performance Rating Methods 716
16.2.4 Translation Equations to Reference Conditions 719
16.3 Current Versus Voltage Measurements 721
16.3.1 Measurement of Irradiance 721
16.3.2 Simulator-based $I-V$ Measurements: Theory 722

16.3.3 Primary Reference Cell Calibration Methods 723
16.3.4 Uncertainty Estimates in Reference Cell Calibration Procedures 726
16.3.5 Intercomparison of Reference Cell Calibration Procedures 727
16.3.6 Multijunction Cell Measurement Procedures 728
16.3.7 Cell and Module $I-V$ Systems 731
16.3.8 Solar Simulators 736
16.4 Spectral Responsivity Measurements 738
16.4.1 Filter-based Systems 739
16.4.2 Grating-based Systems 741
16.4.3 Spectral Responsivity Measurement Uncertainty 742
16.5 Module Qualification and Certification 745
Acknowledgements 746
References 747

17 Photovoltaic Systems **753**
Klaus Preiser
17.1 Introduction to PV Systems and Various Forms of Application 753
17.2 Principles of photovoltaic Power System Configuration and their Application 755
17.2.1 Grid-independent Photovoltaic Systems for Small Devices and Appliances 755
17.2.2 Photovoltaic Systems for Remote Consumers of Medium and Large Size 761
17.2.3 Decentralised Grid-connected Photovoltaic Systems 774
17.2.4 Central Grid-connected Photovoltaic Systems 779
17.2.5 Space Application 780
17.3 Components for PV Systems 784
17.3.1 Battery Storage 784
17.3.2 Charge Controller 787
17.3.3 Inverters 788
17.3.4 Auxiliary Generators 790
17.3.5 System Sizing 791
17.3.6 Energy-saving Domestic Appliances 793
17.4 Future Developments in Photovoltaic System Technology 794
17.4.1 Future Developments in Off-grid Power Supply with Photovoltaics 794
17.4.2 Future Developments in Grid-connected Photovoltaic Systems 796
References 797

18 Electrochemical Storage for Photovoltaics **799**
Dirk Uwe Sauer
18.1 Introduction 799
18.2 General Concept of Electrochemical Batteries 801
18.2.1 Fundamentals of Electrochemical Cells 801

18.2.2 Batteries with Internal and External Storage 807
18.2.3 Commonly Used Technical Terms and Definitions 809
18.2.4 Definitions of Capacity and State of Charge 811
18.3 Typical Operation Conditions of Batteries in PV Applications 812
18.3.1 An Example of an Energy Flow Analysis 812
18.3.2 Classification of Battery-operating Conditions in PV Systems 813
18.4 Secondary Electrochemical Accumulators with Internal Storage 817
18.4.1 Overview 817
18.4.2 NiCd Batteries 818
18.4.3 Nickel-metal Hydride (NiMH) Batteries 821
18.4.4 Rechargeable Alkali Mangan (RAM) Batteries 822
18.4.5 Lithium-ion and Lithium-polymer Batteries 822
18.4.6 Double-layer Capacitors 824
18.4.7 The Lead Acid Battery 826
18.5 Secondary Electrochemical Battery Systems with External Storage 849
18.5.1 Redox-flow Batteries 850
18.5.2 Hydrogen/Oxygen Storage Systems 852
18.6 Investment and Lifetime Cost Considerations 857
18.7 Conclusion 859
References 860

19 Power Conditioning for Photovoltaic Power Systems 863
Jürgen Schmid, Heribert Schmidt
19.1 Charge Controllers and Monitoring Systems for Batteries in PV Power Systems 864
19.1.1 Charge Controllers 864
19.1.2 Charge Equaliser for Long Battery Strings 877
19.2 Inverters 881
19.2.1 General Characteristics of PV Inverters 881
19.2.2 Inverters for Grid-connected Systems 881
19.2.3 Inverters for Stand-alone Operation 883
19.2.4 Inverter Principles 884
19.2.5 Power Quality of Inverters 896
19.2.6 Active Quality Control in the Grid 900
19.2.7 Safety Aspects with Grid-connected Inverters 900
19.3 Acknowledgement 902
References 902

20 Energy Collected and Delivered by PV Modules 905
Eduardo Lorenzo
20.1 Introduction 905
20.2 Movement between Sun and Earth 906
20.3 Solar Radiation Components 912
20.4 Solar Radiation Data and Uncertainty 915
20.4.1 Clearness Index 920
20.5 Radiation on Inclined Surfaces 920

20.5.1 Estimation of the Direct and Diffuse Components of Horizontal Radiation, Given the Global Radiation 920
20.5.2 Estimation of the Hourly Irradiation from the Daily Irradiation 925
20.5.3 Estimation of the Radiation on Surfaces on Arbitrary Orientation, Given the Components Falling on a Horizontal Surface 927
20.6 Diurnal Variations of the Ambient Temperature 933
20.7 Effects of the Angle of Incidence and of the Dirt 934
20.8 Some Calculation Tools 937
20.8.1 Generation of Daily Radiation Sequences 937
20.8.2 The Reference Year 937
20.8.3 Shadows and Trajectory Maps 939
20.9 Irradiation on Most Widely Studied Surfaces 940
20.9.1 Fixed Surfaces 943
20.9.2 Sun-tracking Surfaces 945
20.9.3 Concentrators 946
20.10 PV Generator Behaviour under Real Operation Conditions 947
20.10.1 The Selected Methodology 949
20.10.2 Second-order Effects 953
20.11 Reliability and Sizing of Stand-alone PV Systems 956
20.12 The Case of Solar Home Systems 962
20.13 Energy Yield of Grid-connected PV Systems 964
20.14 Conclusions 966
Acknowledgements 967
References 967

21 Economic Analysis and Environmental Aspects of Photovoltaic Systems 971
Richard A. Whisnant, Stephen A. Johnston and James H. Hutchby
21.1 Background 972
21.2 Economic Analysis 973
21.2.1 Key Concepts 973
21.2.2 General Methodology 980
21.2.3 Case Studies 984
21.3 Energy Payback and Air Pollution Reduction 997
21.4 Prospects for the Future 999
References 1003

22 PV in Architecture 1005
Tjerk H. Reijenga
22.1 Introduction 1005
22.1.1 Photovoltaics (PV) as a Challenge for Architects and Engineers 1005
22.1.2 Definition of Building Integration 1006

22.2 PV in Architecture 1008
22.2.1 Architectural Functions of PV Modules 1008
22.2.2 PV as Part of "Green Design" 1011
22.2.3 PV Integrated as Roofing Louvres, Facades and Shading 1011
22.2.4 Well-integrated Systems 1014
22.2.5 Integration of PV Modules in Architecture 1019
22.2.6 Brundtland Centre, Toftlund (DK) – a Case Study 1022
22.3 BIPV Basics 1026
22.3.1 Categories and Type of Buildings 1026
22.3.2 Cells and Modules 1029
22.4 Steps in the Design Process with PV 1036
22.4.1 Urban Aspects 1036
22.4.2 Practical Rules for Integration 1037
22.4.3 Step-by-step Design 1038
22.4.4 Design Process: Strategic Planning 1039
22.5 Conclusions 1040
References 1041
Further Reading 1042

23 Photovoltaics and Development 1043
Jorge M. Huacuz and Lalith Gunaratne
23.1 Electricity and Development 1043
23.1.1 Energy and the Early Man 1043
23.1.2 Let There be Electricity 1044
23.1.3 One Third of Humanity Still in Darkness 1044
23.1.4 The Centralized Electrical System 1045
23.1.5 Rural Electrification 1045
23.1.6 The Rural Energy Scene 1046
23.2 Breaking the Chains of Underdevelopment 1046
23.2.1 Electricity Applications in the Rural Setting 1046
23.2.2 Basic Sources of Electricity 1047
23.3 The PV Alternative 1048
23.3.1 PV Systems for Rural Applications 1049
23.3.2 Barriers to PV Implementation 1051
23.3.3 Technical Barriers 1052
23.3.4 Nontechnical Issues 1055
23.3.5 Trained Human Resources 1059
23.4 Four Examples of PV Rural Electrification 1061
23.4.1 Argentina 1061
23.4.2 Bolivia 1061
23.4.3 Brazil 1063
23.4.4 Mexico 1064
23.4.5 Sri Lanka 1065
23.4.6 Water Pumping in the Sahel 1067
23.5 Toward a New Paradigm for Rural Electrification 1068
References 1069

24 Financing PV Growth **1073**
Michael T. Eckhart, Jack L. Stone and Keith Rutledge
24.1 Historical Development of PV Financing 1073
24.2 Capital Requirements 1075
24.2.1 Market Drivers 1075
24.2.2 Growth Outlook 1075
24.2.3 Capital Requirements 1076
24.3 Financial Characteristics of PV 1077
24.4 Financing PV for Grid-connected Residences 1079
24.4.1 Impact of Loan Terms on End-user Cost 1079
24.4.2 Types of Residential Financing 1080
24.4.3 Lender's Issues 1081
24.4.4 Borrowers' Experience 1081
24.4.5 Example Calculation 1082
24.4.6 Improving the Financing of Residential PV 1082
24.5 Financing PV in Rural Areas of Developing Countries 1083
24.5.1 Rural Applications 1083
24.5.2 Impact of Financing on Market Demand 1084
24.5.3 Examples of PV Financing in Rural Areas 1085
24.6 Sources of International Financing 1086
24.6.1 International Aid and Donor Funding 1086
24.6.2 United Nations 1087
24.6.3 World Bank Solar Home System Projects 1088
24.6.4 International Finance Corporation (IFC) 1089
24.6.5 Global Environment Facility 1089
24.7 Financing the PV Industry 1091
24.7.1 Financing Working Capital in the Distribution Channels 1092
24.8 Government Incentives and Programs 1092
24.8.1 Potential Impact of Financing as a Government Policy Option 1092
24.8.2 Direct Subsidies ("Buy-downs") 1094
24.8.3 Soft Loans (Interest Subsidies) 1095
24.8.4 Income Tax Deductions and Credits 1096
24.9 Funding Government Research and Development 1096
24.9.1 PV Programs in the United States 1096
24.9.2 PV Programs in Japan 1097
24.9.3 PV Programs in Europe 1097
24.9.4 Future PV R&D Programs 1099
24.9.5 Sources of R&D Funding 1099
Annex 1100
References 1114

Index **1117**

The FF is a function of V_{OC} (equation 3.134), so

$$\eta^{\text{Xsuns}} = \eta^{\text{1sun}} \left(\frac{FF^{\text{Xsuns}}}{FF^{\text{1sun}}} \right) \left(1 + \frac{\dfrac{kT}{q} \ln \text{X}}{V_{\text{OC}}^{\text{1sun}}} \right). \tag{3.165}$$

Both factors multiplying the 1 sun efficiency increase as the illumination concentration increases. Therefore, the efficiency of concentrator cells increases as the illumination concentration increases, as shown in Figure 3.25.

Of course, there are many obstacles to achieving this. Concentrator cells must be cooled, since an increase in operating temperature reduces V_{OC}, and hence the cell efficiency. The FF^{Xsuns} eventually decreases with increasing X and current due to the parasitic series resistance. Concentrator solar cells are discussed in more detail in Chapter 11.

3.5.6 High-level Injection

In high-level injection, the excess carrier concentrations greatly exceed the doping in the base region, so $\Delta p \approx \Delta n \approx n \approx p$ if the carriers are moving generally in the same direction. This occurs with back-contact solar cells, such as the silicon point-contact solar




Figure 3.25 Relative efficiency as a function of illumination concentration




Figure 3.26 Schematic of a back-contact solar cell

cell [22], as illustrated in Figure 3.26. Since both electrical contacts are on the back, there is no grid shadowing. These cells are typically used in concentrator application and high-level injection conditions pervade. Assuming high-level injection, a simple analysis is possible.

Returning to equations (3.76) and (3.77), it can be seen that in high-level injection, the electric field can be eliminated (it is not necessarily zero), resulting in the ambipolar diffusion equation

$$D_a \frac{d^2 p}{dx^2} - \frac{p}{\tau_n + \tau_p} = -G(x), \tag{3.166}$$

where the ambipolar diffusion coefficient is given by

$$D_a = \frac{2D_n D_p}{D_n + D_p}. \tag{3.167}$$

The ambipolar diffusion coefficient is always less than the larger diffusion coefficient and greater than the smaller one.

In silicon, where $D_n/D_p \approx 3$ over a wide range of doping, the ambipolar diffusion coefficient is $D_a \approx 3/2D_p \approx 1/2D_n$ and, if we also assume $\tau_p \approx \tau_n$, the ambipolar diffusion length is

$$L_a \approx \sqrt{3} L_p \approx L_n. \tag{3.168}$$

Thus, the increased high-injection lifetime (see equation 3.40) offsets the reduced ambipolar diffusion coefficient.

It is crucial that the front surface of a back-contacted cell be well passivated, so we will assume that $S_F = 0$. We will further assume that optical generation is uniform throughout the base region. At open circuit, with these assumptions, $d^2p/dx^2 = 0$ and therefore

$$V_{OC} = \frac{2kT}{q} \ln\left[\frac{G(\tau_n + \tau_p)}{n_i}\right]. \tag{3.169}$$

The short-circuit current (with $p \simeq 0$ at the back of the cell) is

$$I_{SC} = qAL_aG \sinh(W_B/L_a) \tag{3.170}$$

which, when $L_a \gg W_B$, becomes

$$I_{SC} = qAW_BG. \tag{3.171}$$

3.5.7 *p-i-n* Solar Cells

The *p-i-n* solar cell takes advantage of the fact that in many semiconductor materials, especially direct band gap semiconductors (i.e. large absorption coefficient), most of the electron–hole pairs are created very near the surface. If an intrinsic (undoped) layer is placed between the (very thin) n and p regions, the depletion region thickness is the most significant fraction of the total solar cell thickness, as illustrated in Figure 3.27. Carrier collection is now aided by the electric field in the depletion region, which helps offset the low lifetimes in some materials, such as amorphous silicon (see Chapter 12). The $I-V$ characteristic of a *p-i-n* solar cell can be described with minor modifications to the previously derived expressions. The most significant modification is to equation (3.129) where the depletion width is now written as

$$W_D = \chi_N + W_I + \chi_P \tag{3.172}$$

where W_I is the thickness of the intrinsic layer. Since χ_N and χ_P are very thin, short-base approximations are in order for equations (3.127) and (3.128). Also, there is no BSF ($S_{BSF} \rightarrow \infty$).

3.5.8 Detailed Numerical Modeling

While analytic solutions such as those discussed thus far in this chapter provide an intuitive understanding of solar cell performance and are therefore very important, they are limited in their accuracy due to the many simplifying assumptions that must be made in order to obtain them. It is rather straightforward to solve the semiconductor equations numerically without the need to make so many simplifications. Several computer codes have been written that solve the semiconductor equations for the explicit purpose of modeling solar cells – PC-1D [23], AMPS [24], ADEPT [25], and its predecessors [16, 26, 27], for example. The basic design of these computer programs is very similar. The semiconductor

7

Crystalline Silicon Solar Cells and Modules

Ignacio Tobías[1], Carlos del Cañizo[1] and Jesús Alonso[2]

[1]*Universidad Politécnica de Madrid, Madrid, Spain,* [2]*Isofotón S.A., Málaga, Spain*

7.1 INTRODUCTION

Crystalline silicon solar cells and modules have dominated photovoltaic (PV) technology from the beginning. They constitute more than 85% of the PV market today, and although their decline in favor of other technologies has been announced a number of times, they presumably will retain their leading role for a time, at least for the next decade.

One of the reasons for crystalline silicon to be dominant in photovoltaics is the fact that microelectronics has developed silicon technology greatly. On the one hand, not only has the PV community benefited from the accumulated knowledge but also silicon feedstock and second-hand equipment have been acquired at reasonable prices. On the other hand, Microelectronics has taken advantage of some innovations and developments proposed in Photovoltaics.

For several decades, the terrestrial PV market has been dominated by *p*-type Czochralski silicon substrates. Continuous improvements in performance, yields and reliability have allowed an important cost reduction and the subsequent expansion of the PV market. Because of the lower cost of mc-Si wafers, multicrystalline (MC) silicon cells emerged in the 1980s as an alternative to single-crystal ones. However, their lower quality precluded the achievement of similar efficiencies to those of Cz, so that the figure of merit \$ W^{-1} has been quite similar for both technologies over a long time (see Table 7.1).

Deeper understanding of the physics and optics of the mc-Si material led to improved device design, which allowed a wider spread of the technology. A combination

Handbook of Photovoltaic Science and Engineering. Edited by A. Luque and S. Hegedus
© 2003 John Wiley & Sons, Ltd ISBN: 0-471-49196-9

Table 7.1 Breakdown of costs of fabrication of single-crystalline (SX) and multicrystalline (MC) solar cells (corresponding to year 1990) [1]

Item	SX	MC
Pure Si	38	38
Ingot formation	115	35
Sawing	77	77
Wafer cost	**230**	**150**
Cell fabrication	80	80
Total components	310	230
Yield	0.95	0.9
Cell cost	**326**	**256**
Module assembling	75	75
Lamination	75	75
Module cost (Euro m^{-2})	**476**	**406**
Efficiency	0.14	0.12
Module cost (Euro Wp^{-1})	**3.40**	**3.38**

Table 7.2 Market share of monocrystalline and multicrystalline solar cells [2]

Year	Cz-Si solar cells		MC-Si solar cells	
	Output [MW]	Market share [%]	Output [MW]	Market share [%]
1996	48.7	55	28.4	32
2000	92.0	32	146.7	51

of improved material quality and material processing has allowed higher efficiencies at a still lower cost, increasing the share of MC in the PV market, well ahead of monocrystalline. Recent evolution of the market can be seen in Table 7.2 [2].

This chapter offers an overview of silicon solar cell and module technology. First, Si properties justifying its use as photovoltaic material are presented. Then, design of Si solar cells is reviewed, highlighting the benefits and limits of different approaches. Manufacturing processes are described, paying special attention to technologies that are currently implemented at the industrial level, mostly based on screen-printing metallization technology. Considerations of ways of improving solar cell technology are also specified. Peculiarities of multicrystalline material are explained in Section 7.6, while other approaches that are already in industrial production are also described briefly. Next, crystalline Si modules are reviewed, pertaining to electrical performance, fabrication sequence and reliability concerns.

7.2 CRYSTALLINE SILICON AS A PHOTOVOLTAIC MATERIAL

7.2.1 Bulk Properties

Crystalline silicon has a fundamental indirect band gap $E_G = 1.17$ eV and a direct gap above 3 eV [3] at ambient temperature. These characteristics determine the variation of optical properties of Si with wavelength, including the low absorption coefficient for carrier generation for near band gap photons [4]. At short ultraviolet (UV) wavelengths in the solar spectrum, the generation of two electron–hole pairs by one photon seems possible, though quantitatively this is a small effect [5]; at the other extreme of the spectrum parasitic free-carrier absorption competes with band-to-band generation [6]. The intrinsic concentration is another important parameter related to the band structure; it links carrier disequilibrium with voltage [7].

At high carrier densities, doping- or excitation-induced, the band structure is altered leading to an increase in the effective intrinsic concentration: this is one of the so-called heavy doping effects that degrade the PV quality of highly doped regions [8].

Recombination in Si is usually dominated by recombination at defects, described with Shockley–Read–Hall (SRH) lifetimes. The associated lifetime τ (which can also be described in terms of diffusion length L) increases for good quality materials. Auger recombination, on the contrary, is a fundamental process that becomes important at high-carrier concentration [9]. The Auger coefficients are reported to be higher at moderate carrier densities due to excitonic effects [10]. Band-to-band direct recombination is also a fundamental process but quantitatively negligible (it is instructive, however, to notice that record-efficiency solar cells have such extraordinarily low SRH recombination levels that they perform as 1%-efficient light-emitting diodes, that is, radiative recombination is significant [11]).

At low and moderate doping, electrons present mobilities about three times higher than holes, both limited by phonon scattering. Impurity scattering dominates for higher doping densities [12, 13]. Carrier–carrier scattering affects transport properties in highly injected material [14].

7.2.2 Surfaces

7.2.2.1 Contacts

Contacts are structures built on a semiconductor surface that allow charge carriers to flow between the semiconductor and the external circuit. In solar cells, contacts are required to extract the photogenerated carriers from the absorbing semiconductor substrate. They should be selective, that is, should allow one type of carrier to flow from Si to metal without energy loss while blocking the transport of carriers of the opposite type.

Direct Si-metal contacts, in general, do not behave this way. As an exception, good hole contacts to highly doped p-Si substrates with aluminum are possible. But the

most used approach is to create heavily doped regions under the metal, p-type for hole extraction and n-type for electron extraction. Majority carriers in this region can flow through the contact with low voltage loss. The transport of minority carriers is described by a surface recombination velocity (SRV), S. Although the SRV is high, limited only by thermal diffusion so that $S \cong 10^6$ cm·s^{-1} [15], the concentration of minority carriers, for a given pn product, is suppressed by the high doping and the flow is reduced.

As will be seen later on, the contact for the minority carriers is usually placed at the front (illuminated) face of the substrate, and the corresponding heavily doped layer is usually called *emitter*. The doped region under the majority carrier contact at the back is called a *Back Surface Field* (BSF).

Recombination at these heavily doped regions is described by the saturation current density J_0 that includes volume and true contact recombination. Their thickness w should be much higher than the minority-carrier diffusion length L so that few excess carriers reach the contact, and the doping level must be very high to decrease contact resistance and the minority-carrier concentration, although heavy doping effects may limit the doping level advisable for such regions. The recombination activity of BSF layers is often described in terms of an effective SRV instead of the saturation current density.

Typical 10^{-13} to 10^{-12} A·cm^{-2} J_0 values are achieved [16, 17]. Diffused phosphorus is used for n-contacts. Aluminum alloying has the advantages over boron for p-contacts that very thick p^+ layers can be formed in a short time at moderate temperatures and that gettering action is achieved [18]. As a shortcoming, the p^+ layer is nonhomogeneous and can even be locally absent; the obtained J_0 is larger than expected for a uniform layer. In comparison to aluminum, boron offers higher doping levels because of a larger solubility [19] and transparency to light so that it can also be used at illuminated surfaces.

Other structures have been tested to obtain selective contacts: metal-insulator-semiconductor (MIS) contacts [20], polysilicon contacts [21] and heterojunction to a-Si or other wide band gap material [22].

7.2.2.2 Noncontacted surfaces

Because of the severe alteration of the bonding of Si atoms, a large number of band gap states exist at a bare Si surface which, acting as SRH recombination centers, make the SRV very large, around 10^5 cm·s^{-1} [23, 24]. In order to reduce surface recombination, two main approaches are followed [25].

In the first one, the density of electron surface states in the gap is decreased. This is accomplished by depositing or growing a layer of an appropriate material that partially restores the bonding environment of surface Si atoms. This material must be an insulator.

Thermal SiO_x is grown in an oxygen-rich atmosphere at the expense of substrate Si atoms at high temperatures around 1000°C. SiN_x is deposited by plasma-enhanced chemical vapor deposition (PECVD) [26] at low temperatures between 300 and 400°C range. The quality of both techniques is very sensitive to subsequent treatments, with hydrogen playing a major role in obtaining low SRV values below 100 cm·s^{-1}.

As a general rule, S increases with the doping of the substrate [23, 24]. It also depends on the injection level and doping type, because the interfaces contain positive

charges that affect the number of carriers at the surface, and because the capture probability for electrons and holes is different [27]. N-type or intrinsic surfaces are usually better than p-type ones. Stability under UV exposure is another fundamental concern.

In the second approach, the excess carrier density at the interface is decreased relative to the bulk. This effect has already been commented upon with respect to contacts and results in a reduced effective SRV at the bulk edge of the corresponding space charge region. It can be produced by charges in the surface layer, by the electrostatics associated to a MOS structure [28] or by doping.

The surface layer can be accumulated or inverted, or, correspondingly, doped with the same or the opposite type of the substrate. Its recombination activity is better described by a constant saturation current density, J_0, whose minimization follows the same rules as mentioned for the contacts if S at the surface is high. On the contrary, if S is low when compared to D/L for minority carriers (with D the diffusion constant and L the diffusion length in the substrate) in the surface layer, it is better for it to be thin or "transparent" to minority-carrier flow ($w < L$). The optimum doping level is a compromise between reduction of the excess carriers, and heavy doping effects and the increase of the SRV with doping. Moderate doping levels are favored in this case. Under passivated surfaces, J_0 values around 10^{-14} A·cm^{-2} are achievable, with phosphorus-doped substrates giving better results than boron-doped ones [16, 17].

In conclusion, recombination at a noncontacted surface can be made much smaller than at a metallized one, and this has a deep influence in the evolution of Si solar cell design.

7.3 CRYSTALLINE SILICON SOLAR CELLS

7.3.1 Cell Structure

Several studies have been carried out to find the limiting efficiency and the optimum structure of a-Si solar cell [29–31]. All avoidable losses are assumed to be suppressed:

1. no reflection losses and maximum absorption as achieved by ideal light-trapping techniques,
2. minimum recombination: SRH and surface recombination are assumed avoidable and only Auger recombination remains,
3. the contacts are ideal: neither shading nor series resistance losses,
4. no transport losses in the substrate: the carrier profiles in the substrate are flat so that recombination is the minimum possible for a given voltage.

The optimum cell should use intrinsic material, to minimize Auger recombination and free-carrier absorption, and should be around 80-μm thick, the result of the trade-off between absorption and recombination. It could attain nearly 29% efficiency at one sun AM1.5 Global, 25°C [30].

This ideal case does not tell us where to put the contacts. To realize Condition 4 mentioned above, the contacts should be located at the illuminated or the front face, closest to photogeneration (Figure 7.1a). Because of metal shading losses this threatens




Figure 7.1 Contacting structures: (a) both contacts at the front; and (b) at the back; (c) both faces contacted; and (d) one carrier extracted at both faces. The structures with interchanged *n*- and *p*-types are also possible

Condition 3 mentioned above. This solution is being considered for concentration [32]. Putting both contacts at the back works the other way round (Figure 7.1b). Back-contacted cells exhibit record efficiencies under concentration and demonstrate very high values near 23% at one sun [33].

In most cells, each contact is placed on a different face, which is technologically simpler (Figure 7.1c). Minority carriers in the substrate are usually collected at the front since their extraction is more problematic because of their low density. The diffusion length describes the maximum distance from where they can be collected. Majority carriers can drift to the back contact with low loss. Several designs extract minority carriers both at the front and at the back (Figure 7.1d) [34], thus increasing the volume of profitable photogeneration.


Bifacial cells are designed to collect light incident at both faces, which allows a boost in output power if there is a significant albedo component. They can be implemented with any structure in Figure 7.1 on the condition that both surfaces allow light through [35].

Both 24.7% record-efficiency laboratory solar cells [36] (Figure 7.2a) and mass-produced industrial devices (Figure 7.2b), typically 15% efficient, display the contacting structure in Figure 7.1(c). They will be described in the paragraphs that follow with the aim of illustrating the amplitude and the reasons for the performance gaps between the ideal and the best Si cell, and between this cell and industrial cells.


7.3.2 Substrate

7.3.2.1 Materials and processing

Highest efficiencies are achieved with monocrystalline float zone (FZ-Si) material, which in addition to extreme crystalline perfection shows the lowest contamination levels of both



(a)



(b)

Figure 7.2 (a) Passivated emitter and rear locally diffused (PERL) cell; and (b) industrial cell with screen-printed contacts. (Not to scale)

metallic and light (O, C, N) impurities. This translates into the longest post-processing SRH lifetimes in the millisecond range, but still shorter than the Auger limit. Magnetic Czochralski (MCz) material contains much less oxygen than conventional Czochralski and also allows very high efficiencies to be obtained [36].

Industrial cells use Czochralski (Cz-Si) wafers because of their availability. Cz wafers are also perfect crystals but they contain a high concentration of oxygen that affects lifetime in several ways [37]. Some commercial devices are made on multicrystalline (mc-Si) substrates grown in blocks or ribbons with procedures specially developed for photovoltaics. In addition to crystal defects, such as grain boundaries and dislocations, the potential content of metallics is higher because of lower segregation to the melt during the faster solidification process. As a result, the lifetime of mc-Si is lower.

But lifetime is important at the end of solar cell fabrication during which it can undergo strong variations. This issue is handled in different ways in a laboratory and a factory environment. In the laboratory, measures are taken to maintain long initial lifetimes by avoiding contamination during high-temperature steps: furnace cleaning, ultra pure chemicals and so on. In a rough, industrial environment and with defect-containing (Cz- and mc-Si) materials, the problem is more complex: in addition to contamination from the surroundings, impurities and defects in the substrate move, interact and transform at high temperature. The solution is to integrate gettering steps [38] in the fabrication flow that reduce the impact of contamination, and to tailor the thermal treatments to the peculiarities of the material. Final substrate lifetimes of industrial cells range from 1 to 10 μs.

Gettering techniques eliminate or reduce contaminant impurities in a wafer, and so neutralize the effect of lifetime reduction. Although gettering processes are not always well understood, it is admitted, in general, that in a gettering process a sink region is formed, which is able to accommodate the lifetime-killing impurities in such a way that they are not harmful to the device being manufactured, or at least they are where they can be easily removed.

In solar cell fabrication, we take advantage of the fact that phosphorus and aluminum diffusions, appropriate candidates for emitter and BSF layers, respectively, produce gettering in certain conditions [39]. Other techniques have been explored [40, 41], but their integration in a solar cell process is not so straightforward.

P gettering effect has been proved for a wide variety of P diffusion techniques (spin-on, $POCl_3$, PH_3 etc), provided diffusion is done in supersaturation conditions (i.e. over its solid solubility in silicon). Unfortunately, this leaves a "dead layer" of electrically inactive phosphorus near the surface, which reduces UV response of the cells in case it is not etched away [42]. Another phenomenon related to this supersaturated P is the injection of silicon self-interstitials to the bulk of the material, which is responsible for an enhancement of the gettering effect [43].

When Al is deposited on Silicon (by different techniques such as sputtering, vacuum evaporation or screen printing) and annealed over the eutectic temperature (577°C), a liquid Al-Si layer is formed, where impurities tend to segregate because of their enhanced solubility [44]. They will remain in this gettering layer while cooling, so that bulk lifetime will improve after the process.

Another approach to improve material quality is "bulk passivation", a treatment with hydrogen, for example, during SiN_x deposition, to which some defected materials respond very well [45].

7.3.2.2 Doping level and type

Both laboratory record-efficiency and industrial cells use boron-doped substrates. Rather than fundamental advantages [46], there are practical (properties of P diffusion, easiness of Al alloying) and historical reasons for this preference [47]. However, the situation may change once the role of boron in the degradation of Cz-Si cells under illumination has been established [48].

The optimum substrate doping depends on the cell structure and dominant recombination mechanism. Though intrinsic substrates present the advantage of highest Auger-limiting lifetimes, higher doping is favored when SRH recombination is present, since recombination is proportional to the excess density that decreases, for a given voltage, as doping increases [29]. This is balanced with a reduction of the lifetime itself.

A high doping also helps in minimizing the series resistance losses associated to the transport of carriers to the back face in thick cells with the majority carrier contact at the back.

Doping levels in the 10^{16} cm^{-3} range are found in the substrate of industrial cells. Very high efficiencies have been obtained with both low (1 Ω·cm for PERL cells) and high substrate resistivities, as in the point-contact cells [33].

7.3.2.3 Thickness

From the point of view of electrical performance, the choice of the optimum substrate thickness also depends on the structure and the quality of the materials and involves several considerations. In cells with diffusion lengths longer than the thickness, the most important issue is surface recombination: if S at the back is higher than D/L for the minority carriers in the substrate (around 250 $cm \cdot s^{-1}$ for the best cells), thinning the cell increases recombination at a given voltage, and vice versa. Thinner cells always absorb less light as well, which is attenuated by light-trapping techniques. Passivated emitter and rear locally diffused (PERL) cells were reported to improve when going from 280- to 400-μm thickness because of a (relatively) high rear surface recombination and nonideal light-trapping [49].

The losses associated with the transport of carriers extracted at the nonilluminated face decrease with thinning: in conventional structure cells; this leads to decreased series resistance. In back-contacted cells, both types of carriers benefit from thinning and the trade-off in absorption leads to lower w values, around 150 to 200 μm.

The diffusion length of industrial cells (around 100 μm) is generally lower than thickness. These cells are rather insensitive to thinning because they collect only the generation near the contact and are not affected by rear surface recombination. The driving criteria are cost and fabricability. A thickness in the 200- to 300-μm range is usually employed but there is a clear trend toward thinner wafers for saving expensive silicon material [47], and advanced wafering techniques and procedures to process very thin, large-area substrates without breaking are being developed: light-trapping and back recombination will become increasingly important.

7.3.3 The Front Surface

7.3.3.1 Metallization techniques

Metal grids are used at the front face to collect the distributedly photogenerated carriers. The compromise between transparency and series resistance requires metallization technologies able to produce very narrow but thick and highly conductive metal lines with

a low contact resistance to Si. Laboratory cells use photolithography and evaporation to form 10- to 15-μm metal fingers. Ti/Pd/Ag structures combine low contact resistance to *n*-Si and high bulk conductivity. These processes are not well suited to mass production that relies on thick-film technologies. Ag pastes are screen printed, resulting in over 100-μm wide lines with higher bulk and contact resistance. Laser-grooved buried-grid (LGBG) industrial cells implement a finer metallization technology [50], which will be presented in Section 7.7.3.

Coarser metallization techniques imply higher shading and resistance losses, and restrict the efficiency enhancement that could be achieved by internal cell design.

7.3.3.2 Homogeneous emitters

Under the metal lines, the substrate must be heavily doped to make the contact selective. Usually the doped region, the emitter, extends all across the front surface, acting as a "transparent electrode" by offering minority carriers in the substrate a low resistance path to the metal lines.

When the exposed surface is not passivated (Figure 7.3a), the emitter should be as thin as possible, because the high SRV makes the light absorbed in this region poorly collected, and also highly doped to decrease recombination. On the other hand, a sufficient low-sheet resistance is to be achieved. The solution is to make very thin and highly doped emitters.

If the surface is passivated (Figure 7.3b), the collection efficiency of the emitter can be raised by lowering the doping level thus avoiding heavy doping and other detrimental




Figure 7.3 Different emitter structures: (a) homogenous emitter without surface passivation; (b) homogenous emitter with surface passivation; (c) selective emitter; and (d) localized emitter

effects. This must be balanced with contact resistance. Etching off of the passivating layer before metallization is usually needed (not in screen-printed cells). To maintain low sheet resistance and diminish recombination at the metallized fraction, the emitter is deep (around 1 μm). Note that the collection of carriers near the surface implies that the emitter is thin in terms of the minority-carrier diffusion length ($w < L$) and so it is very sensitive to surface recombination. Recombination is further reduced, by making the contact window narrower than the finger width, as illustrated in Figure 7.3 [51].

Control of both the surface concentration and the depth of the emitter, is achieved by depositing, in a thermal step, the desired amount of phosphorus or boron (predeposition) and then diffusing it into the substrate (drive-in) during subsequent furnace steps. The MIS solar cell, on the contrary, uses no diffusion for the n region, which is electrostatically induced by charges on top of the surface [20].

The J_0 of the emitter is the average, weighted by the contacted area, of the J_0 of contacted and noncontacted portions.

7.3.3.3 Selective and point emitters

A further improvement involves making separate diffusions for the different regions since the requirements are so different (Figure 7.3c) [52]: a heavily doped and thick region under the contacts, a thin and lowly doped region under the passivating layer. These structures, known as "selective emitters", come at the expense of more complicated processing usually involving photolithographic delineation and alignment of the diffusions (not in LGBG cells to be seen later).

If a very low SRV is possible, it would be best to have no emitter at all since doping always degrades bulk lifetime (Figure 7.3d). Examples are the back point-contact solar cell and the point-emitter design with bifacial contact [53], originally designed for concentration but capable of very high one-sun efficiency as well.

With localized contacts, surface recombination decreases with the penalty of an increase in transport losses in the substrate: deeper gradients for minority carriers, or increased series resistance for majority carriers, because of current crowding near the contacts. The trading is more favorably solved as the contact size shrinks [54]. Light and/or localized diffusions also have the drawback of decreased gettering action.

7.3.3.4 Industrial cells

Screen printing drastically affects the design of the emitter: it must be very highly doped to decrease the high-contact resistance and not very shallow so that it is not perforated during paste firing, which would short-circuit the junction [55]. Besides, the wide metal lines must be placed well apart; and in order to keep shading losses moderate, the emitter lateral conductance must be high, which also advises deep and highly doped regions. These characteristics are good to decrease recombination at the contacts, but are far from optimum at the exposed surface.

Industrial phosphorus emitters, typically, feature surface concentrations over 10^{20} cm^{-3} and 0.4-μm depth, and result in a sheet resistance around 40 Ω. As already

mentioned, the very highly doped region exhibits almost no photovoltaic activity due to the presence of precipitates ("dead layer"). As a result, the collection of short-wavelength light is very poor and the J_0 large, irrespective of a hypothetical surface passivation is therefore not implemented. The advantage is that heavy phosphorus diffusions produce very effective gettering. Some ways of incorporating selective emitters to screen-printed cells are being considered, SiN_x appearing very well suited for surface passivation [55]. This, however, must be accompanied by a decrease in the finger width so that lower sheet resistances are tolerated.

7.3.4 The Back Surface

The majority carrier, back p-contact of industrial solar cells is usually made by printing, and subsequently, firing an aluminum-containing Ag-conducting paste.

The p^+ layer would be useful in decreasing contact recombination, as explained, but this is immaterial to the electrically thick ($w > L$) present industrial cells and it is not optimized for this purpose.

For high-efficiency cells, contact passivation is essential. A BSF is a first step (Figure 7.4a). Localized contacts, as shown in Figure 7.4(b), further reduce recombination. This structure is presented by some of the bifacial cells [56].

If the surface passivation is good, the BSF is restricted to point contacts, some microns in size, as in PERL and similar cells (Figure 7.4c) [57]. The back face of bifacial cells passivated with SiN_x is shown in Figure 7.4(d).

A shallow and light diffusion helps in decreasing surface recombination (Figure 7.4e). The diffusion can be the same type of the substrate, or the opposite one: so-called PERT (Passivated emitter rear totally diffused) [36] and PERF (Passivated emitted rear floating junction) [58] cells demonstrate these concepts. The latter structure benefits from the lower J_0 values of n^+ layers, and it is essential that no electron flow is injected from the n region to the p contact: the junction must be in open-circuit (a "floating" junction). Note that this structure has nothing to do with structures sometimes found at the back of industrial cells (Figure 7.4f) where a coarse metal mesh is fired through the parasitic n^+ layer formed during front diffusion. A mesh is preferred to a continuous layer for mechanical reasons. The junction is shorted and presents to the substrate a high SRV.

7.3.5 Size Effects

Substrate edges are highly recombining surfaces that adversely affect cell performance, especially for small size, large diffusion length devices. For laboratory cells, efficiency is defined on the basis of a design area. The emitter is limited to it by planar masking or mesa etching. The true edge is thus placed far away from the cell limit, and then recombination is reduced. For real applications, on the contrary, only the substrate area counts, and edge optimization is more complex. Advanced passivation schemes such as edge diffusions are being considered [59, 60]. In large industrial cells, this recombination is much less important.




Figure 7.4 Rear contact structures: (a) continuous BSF; (b) bifacial cell; (c) local BSF; (d) local BSF, bifacial cell; (e) selective emitter or floating junction passivation; and (f) shorted junction at the back face of industrial cells

Large cell sizes are preferred by the industry, 10×10 cm^2 or 12.5×12.5 cm^2 being standard. Apart from fabricability concerns, a bigger cell means that more current must be collected at the terminals, making Joule losses grow: the longitudinal resistance of the metal lines increases quadratically with their length. This problem, more severe for coarser metallization techniques, decreases efficiency with increasing size. To alleviate series resistance at the price of increased shading, terminals are soldered to metal bus bars inside the cell's active area, thus decreasing the distance from where current must be collected along the fingers.

7.3.6 Cell Optics

Flat plate solar cells in operation are illuminated from a large portion of the sky, not only because of the isotropic components of radiation, but also because of the sun's apparent motion over the day and the year. So, with regard to angular distribution, these cells must accept light from the whole hemisphere. The spectral distribution also varies with time, weather conditions, and so on. For calibration purposes, a standard spectral distribution AM1.5 Global is adopted as a representative condition, usually specified at 0.1 W·cm^{-2}.

A solar cell should absorb all useful light. For nonencapsulated cells, the first optical loss is the shading by the metal grid at the illuminated face, if any. This loss can amount to more than 10% for industrial cells while for laboratory cells using fine metallization it is much lower. Though several techniques have been proposed to decrease the effective shading, such as shaped fingers, prismatic covers, or cavities [61], their efficacy depends upon the direction of light and so they are not suited to isotropic illumination.

7.3.6.1 Antireflection coatings

Next, loss comes from the reflectance at the Si interface, more than 30% for bare Si in air due to its high refraction index. A layer of nonabsorbing material with a lower refraction index (n_{ARC}) on top of the Si substrate decreases reflectance: this is a step toward the zero-reflection case of a smoothly varying refraction index. If the layer is thick in terms of the coherence length of the illumination, around 1 μm for sunlight, there are no interference effects inside it. The encapsulation (glass plus lamination) belongs to this category.

Antireflection coating (ARC) means an optically thin dielectric layer designed to suppress reflection by interference effects. Reflection is at a minimum when the layer thickness is (an odd multiple of) $n_{ARC}\lambda_0/4$, with λ_0 the free space wavelength, since in this case reflected components interfere destructively. At other wavelengths reflection increases, but is always below the value with no ARC or, at most, equal [62]. The ARC is usually designed to present the minimum at around 600 nm, where the flux of photons is a maximum in the solar spectrum. For reflection to become zero at the minimum, the coating index should be the geometric average of those of air and silicon, that is, 2.4 at 600 nm for nonencapsulated cells.

The industry uses TiO_x deposited by chemical vapor deposition (CVD). PECVD SiN_x is very interesting since it also serves as a passivating layer, as explained earlier.

By using double layer coatings with $\lambda/4$ design, with growing indices from air to silicon, the minimum in reflection is broader in wavelength. Evaporated SZn and MgF_2

are used in laboratory high-efficiency cells. The low index of passivating SiO_x in contact with Si degrades the performance of the ARC. The SiO_x layer is then made as thin as is compatible with efficient passivation [63].

7.3.6.2 Texturing

Alkaline (KOH or NaOH-based) solutions etch anisotropically a-Si crystal exposing {1 1 1} planes on which the etching rate is lowest. On [1 0 0]–oriented wafers, randomly distributed, square-base pyramids are formed, whose size is adjusted to a few microns by controlling etching time and temperature. In a textured face, a ray can be reflected toward a neighboring pyramid (Figure 7.5a) and hence absorption is enhanced. Though calculation of reflection requires ray tracing, a rough estimate of near-normal incidence can be derived, by assuming that each ray strikes twice the Si surface so that reflection is the square of the untextured case.

Texturing is incorporated into both industrial and laboratory Si solar cells, and, in combination with antireflection (AR) coating, reduces reflection losses to a few percent. In the latter case, in order to better control the pyramid geometry and to allow delineation of fine features on the surface, photolithographic techniques are used to define inverted or upright pyramids at the desired positions. It has to be noted that in this case the reflectivity is similar to that of a random texture [64].

Light entering the substrate at a textured surface is tilted with respect to the cell normal. This means that photogeneration takes place closer to the collection junction, which is very beneficial for low-diffusion length cells, by enhancing the collection efficiency of medium- to long wavelengths (Figure 7.5a). The effect is equivalent to an increase of the absorption coefficient. As a drawback, textured surfaces present higher SRVs.

7.3.6.3 Light-trapping

Long-wavelength photons are weakly absorbed in silicon, and, unless internal reflectances are high, they will escape the substrate without contributing to photogeneration. The aim of light-trapping or light confinement techniques is to achieve high internal reflectances.




Figure 7.5 Effects of surface texturing: (a) decreased reflection; and (b) increased photogeneration in the base

Practical back mirrors that are fully compatible with the cell electrical design, can be implemented, such as those schematized in Figure 7.4. A metal can make a good reflector, but Al, especially after heat treatment, gives low reflectance. The Si-oxide-metal structure in Figure 7.4(c) can present a high reflectance by capitalizing on interference effects [65].

At the front, the metal mirror is not applicable because the ray paths must be kept open for the entering light. Still, high front reflectance can be achieved because of total internal reflection [61]. Rays striking the surface at angles larger than the critical air-Si one are totally reflected. Texturing one or both surfaces with macroscopic or microscopic features serves this purpose by tilting the rays. Even in the case of geometric texturing with well-defined surface orientations, after a few internal reflections, the direction of rays inside the wafer is randomly distributed: this is the lambertian case, useful analytic approximation to light-trapping. Bifacial structures in Figure 7.4 can, for the same reason, be very efficient at confining the light [66].

Light-trapping increases the effective thickness of the wafer for absorption. In the geometrical optics regime, it has been shown that for one-side isotropic illumination the maximum enhancement factor (though perhaps not realizable) is 4 $(n_{Si}/n_{air})^2$, that is, each ray traverses 50 times the cell thickness before escaping [67]. The corresponding enhancement in photogeneration will be lower because of the competition of the absorption by free carriers at long wavelength.

Light-trapping is essential for thin cells. Even in the thick PERL design it can suppose around 1 $mA \cdot cm^{-2}$ enhancement in short-circuit current with respect to the case where the internal reflectances were zero.

7.3.7 Performance Comparison

For illustration purposes, Table 7.3 collects relevant parameters of the Auger-limited ideal Si solar cell [30], the best one-sun PERL cell [36] and a typical screen-printed, industrial cell on Cz-Si. The different concepts behind each set of data must be accounted for when comparing the figures. For instance, the ideal cell is assumed as being isotropically illuminated, while measurements are made for near-normal incidence.

Table 7.3 Cell performance (25°C, AM1.5 Global 0.1 $W \cdot cm^{-2}$)

Cell type	Ideal (calculated)	PERL (measured)	Industrial (typical)
Size (cm^2)	–	4	100
Thickness (μm)	80	450	300
Substrate resistivity ($\Omega \cdot cm$)	Intrinsic	0.5	1
Short-circuit current density, J_{SC} ($A \cdot cm^{-2}$)	0.0425	0.0422	0.034
Open-circuit voltage, V_{OC} (V)	0.765	0.702	0.600
Fill factor, FF	0.890	0.828	0.740
Efficiency, η (%)	28.8	24.7	15.0

The most striking difference between the best and the ideal solar cell is the difference in design: thick and low injection *versus* thin and high injection. The PERL cell is surely the best design for the currently achievable levels of surface recombination, which limit open-circuit voltage and shift the optimum thickness to high values. The low resistivity follows then from transport considerations for the chosen structure. The very high fill factor of the ideal cell is characteristic of high injection, Auger-limited operation.

Reduction of surface recombination in the best laboratory cells relies on surface passivation and the restriction of very heavily doped regions to a minimum. In the end, this is possible because of the possibility of defining and aligning very small features on the surfaces.

The very heavily doped emitter, along with lower substrate lifetimes, is responsible for the reduced short-circuit current and open-circuit voltage in the industrial cell. The fill factor is affected by the large device area in conjunction with the limitations of the metallization technique, which further reduces the current because of shading.

Continuous improvement in material quality and cost-driven thinning of the substrates will increase the need for industrial cells to implement surface passivation schemes. This will require the refinement of the metallization technique; another issue is that substrate lifetimes in an industrial environment depend on the gettering action of very heavy diffusions, which are not compatible with optimum surface performance. The PERL approach – high-temperature processes and delineation of fine features – is the most successful path to high efficiency, but it is not the only one that can inspire the forthcoming developments in industrial cells. It is worth noting, in this respect, that heterojunction with intrinsic thin-layer (HIT) solar cells have entered the exclusive club of more than 20% efficiency with a different approach (see Section 7.7.2).

7.4 MANUFACTURING PROCESS

7.4.1 Process Flow

Figure 7.6 shows the main steps of a simple process for solar cell fabrication based on screen printing. With more or less minor modifications, this process is currently used by many manufacturers. The main virtues of this 30-year-old PV technology are easy automation, reliability, good usage of materials and high yield. The drawback, as explained in preceding sections, is the efficiency penalty derived from the coarse and aggressive metallization technique. Some specific treatments worked out for mc-Si will be explained in Section 7.6.

Each step is briefly described in the following text with illustrative purposes: values of temperature, time and so on will only be indicative.

1. *Starting material*: The industry uses so-called solar grade Cz-Si wafers, round in origin but very often trimmed to a pseudo-square shape, or multicrystalline square wafers. Wafer dimensions are between 10- and 15-cm side and between 200- and 350-μm thickness. Doping is *p*-type (boron) to a resistivity of around 1 Ω·cm.
2. *Saw damage removal*: The sawing operation leaves the surfaces of "as cut" wafers with a high degree of damage. This presents two problems: the surface region is of




Figure 7.6 A typical processing sequence with schematic illustrations of the resulting structures

a very bad quality and the defects can lead to wafer fracture during processing [68]. For this reason, about ten microns are etched off from each face in alkaline or acid solutions. The wafers, in Teflon cassettes, are immersed in tanks containing the solution under temperature and composition control. Alkaline etches are preferred to acid solutions due to considerations of waste disposal.