



US 20080217720A1

(19) **United States**

(12) **Patent Application Publication**
Fan et al.

(10) **Pub. No.: US 2008/0217720 A1**

(43) **Pub. Date: Sep. 11, 2008**

(54) **DUAL ISOLATION FOR IMAGE SENSORS**

Publication Classification

(75) Inventors: **Xiaofeng Fan**, Boise, ID (US);
Richard A. Mauritzson, Meridian,
ID (US)

(51) **Int. Cl.**
H01L 31/00 (2006.01)
H01L 21/76 (2006.01)
(52) **U.S. Cl.** **257/446**; 438/425; 257/E21.54;
257/E31.001

Correspondence Address:
TRASK BRITT, P.C./ MICRON TECHNOLOGY
P.O. BOX 2550
SALT LAKE CITY, UT 84110 (US)


(57) **ABSTRACT**

Methods, methods of making, devices, and systems for image sensors that include isolation regions are disclosed. A semiconductor imager includes a pixel array and peripheral circuitry arranged on at least one side of the pixel array. Array devices are formed as part of the pixel array and periphery devices are formed in the periphery. Array isolation regions are disposed around at least a portion of at least some of the array devices and periphery isolation regions are disposed around at least a portion of at least some of the periphery devices. Within the semiconductor imager, the periphery isolation regions are configured differently from the array isolation regions. The semiconductor image sensor may be included in as part of an imaging system that includes a processor.

(73) Assignee: **Micron Technology, Inc.**

(21) Appl. No.: **11/716,342**

(22) Filed: **Mar. 9, 2007**






FIG. 1




FIG. 2




FIG. 3A




FIG. 3B




FIG. 3C




FIG. 4




FIG. 5




FIG. 6A




FIG. 6B




FIG. 6C




FIG. 7A




FIG. 7B




FIG. 7C




FIG. 8A




FIG. 8B




FIG. 8C




FIG. 9A




FIG. 9B





FIG. 9C

**FIG. 10**

DUAL ISOLATION FOR IMAGE SENSORS

FIELD OF THE INVENTION

[0001] Embodiments of the present invention relate to semiconductor devices. More particularly, embodiments of the present invention relate to complementary metal oxide semiconductor (CMOS) image sensors.

BACKGROUND OF THE INVENTION

[0002] Many systems include imaging devices to sense and capture optical images that can be electronically converted to a digital representation of the image. These image sensors include an array of photo-sensitive devices such as photodiodes, photo-transistors, photoconductors, or photogates, fabricated on, for example, a complementary metal oxide semiconductor (CMOS) device. The photo-sensitive devices are arranged as an array of pixel cells in a focal plane. Each photo-sensitive device is sensitive to light in such a way that it can create an electrical charge that is proportional to the intensity of light striking the photo-sensitive device. The overall image captured by an image sensor includes many pixels arranged in an array such that each pixel detects the light intensity at the location of that pixel. A single pixel may include a single photo-sensitive device configured for detecting a broad frequency range, which may be used for gray scale images. In addition, a pixel may be defined as a single photo-sensitive device configured for detecting a specific color (i.e., frequency). Finally, a pixel may be defined as a group of photo-sensitive devices arranged near each other wherein different devices within the group are configured for detecting different colors. Thus, a full color image may be detected with the proper combination of color sensing pixels.

[0003] Many conventional CMOS imagers include isolation regions around devices in the pixel array and isolation regions around devices in a periphery region outside of the pixel array. These isolation regions may assist in preventing leakage current between the various devices. Particularly with imagers, it is important to reduce leakage currents that may adversely affect the charge collected on photodiodes. This leakage current to photodiodes may manifest as dark-current or as a coupling between adjacent pixels.

[0004] Isolation regions may be formed in different ways. For example, shallow trench isolation (STI) regions have been used, doped regions have been used, and a Local Oxidation of Silicon (LOCOS) process has been used. Each of these isolation types may have benefits and disadvantages. For example, a common problem associated with the formation of STI regions is that, when ions are implanted in the substrate close to the bottom and edges or sidewalls of the trench, current leakage can occur at the junction between the active device regions and the trench resulting in "hot pixels," (i.e., pixels that may appear brighter than other pixels). Minimizing hot pixels and dark current in a photodiode is important in CMOS image sensor fabrication. However, isolation between pixels and various devices in the pixel array is also important. As a result, in many cases, isolation regions are a trade off between hot pixel effects and coupling between adjacent devices. Furthermore, a type of isolation that is advantageous for pixel array devices may not be as advantageous for devices in the periphery logic.

[0005] There is a need for image sensors with isolation regions in the pixel array that differ from isolation regions in the periphery around the pixel array.

BRIEF DESCRIPTION OF THE DRAWINGS

[0006] In the drawings, which illustrate embodiments for carrying out the invention:

[0007] FIG. 1 is a simplified block diagram of a CMOS image sensor in accordance with a representative embodiment of the invention;

[0008] FIG. 2 is a top plan view illustrating an example of a possible layout of a sensor array and peripheral circuitry in accordance with an embodiment of the invention;

[0009] FIG. 3A is a top plan view illustrating an example layout of a single pixel sensor in accordance with an embodiment of the invention;

[0010] FIG. 3B is a circuit diagram of the pixel sensor of FIG. 3A;

[0011] FIG. 3C is a cross-sectional view of the pixel sensor of FIG. 3A along section line A-A;

[0012] FIG. 4 is a top plan view illustrating example layouts of transistors in accordance with an embodiment of the invention;

[0013] FIG. 5 is a cross-sectional view of the layout of FIG. 4 along section line B-B;

[0014] FIGS. 6A-6C are cross-sectional views of structures along section lines C-C of FIG. 4 that may be used in accordance with embodiments of the invention;

[0015] FIGS. 7A-7C are cross-sectional views illustrating process stages used in accordance with an embodiment of the invention; and

[0016] FIGS. 8A-8C are cross-sectional views illustrating process stages used in accordance with another embodiment of the invention;

[0017] FIGS. 9A-9C are cross-sectional views illustrating process stages used in accordance with another embodiment of the invention; and

[0018] FIG. 10 is a simplified imaging system block diagram including an image sensor formed according to embodiments of the present invention.

DETAILED DESCRIPTION OF THE INVENTION

[0019] Embodiments of the present invention comprise methods, devices, and systems for image sensors that include isolation regions in the pixel array that differ from isolation regions in the periphery around the pixel array.

[0020] An embodiment of the present invention comprises a semiconductor imager that includes a sensor array and peripheral circuitry arranged on at least one side of the sensor array. The sensor array includes a plurality of pixels arranged in rows and columns and each pixel includes one or more array isolation regions configured to substantially isolate a first array-circuit-element from a second array-circuit-element. The peripheral circuitry includes one or more periphery isolation regions configured to isolate a first peripheral-circuit-element from a second peripheral-circuit-element. Within the semiconductor imager, the periphery isolation regions are configured differently from the array isolation regions.

[0021] Another embodiment of the present invention comprises a method of isolating circuit elements in a semiconductor imager. The method includes isolating array devices that are formed as part of a pixel array and isolating periphery

devices that are formed outside of the pixel array. Isolation of the array devices is performed with array isolation regions disposed around at least a portion of at least some of the array devices. Isolation of the periphery devices is performed with periphery isolation regions disposed around at least a portion of at least some of the periphery devices. In addition, the array isolation regions are formed differently from the periphery isolation regions.

[0022] Another embodiment of the present invention comprises a method of forming a semiconductor imager. The method includes providing a semiconductor substrate. Array devices are formed on the semiconductor substrate in a pixel array region and periphery devices are formed on the semiconductor substrate in at least one periphery region bordering the pixel array region. The method also includes forming array isolation regions in the pixel array region and forming periphery isolation regions in the periphery regions. In addition, the periphery isolation regions differ in configuration from the array isolation regions.

[0023] Yet another embodiment, in accordance with the present invention, comprises an imaging system including a semiconductor imager and a memory operably coupled to the semiconductor imager. The memory is configured for storing a digital representation of an image captured by the semiconductor imager. The semiconductor imager includes a sensor array and peripheral circuitry arranged on at least one side of the sensor array. The sensor array includes a plurality of pixels arranged in rows and columns and each pixel includes one or more array isolation regions configured to substantially isolate a first array-circuit-element from a second array-circuit-element. The peripheral circuitry includes one or more periphery isolation regions configured to isolate a first peripheral-circuit-element from a second peripheral-circuit-element. Within the semiconductor imager, the periphery isolation regions are configured differently from the array isolation regions.

[0024] In the following detailed description, reference is made to the accompanying drawings which form a part hereof, and in which is shown by way of illustration specific embodiments in which the invention may be practiced. These embodiments are described in sufficient detail to enable those skilled in the art to practice the invention, and it is to be understood that other embodiments may be utilized, and that structural, logical and electrical changes may be made without departing from the spirit and scope of the present invention.

[0025] In this description, circuits and functions may be shown in block diagram form in order not to obscure the present invention in unnecessary detail. Conversely, specific circuit implementations shown and described are exemplary only and should not be construed as the only way to implement the present invention unless specified otherwise herein. Additionally, block definitions and partitioning of logic between various blocks is exemplary of a specific implementation. It will be readily apparent to one of ordinary skill in the art that the present invention may be practiced by numerous other partitioning solutions. For the most part, details concerning timing considerations and the like have been omitted where such details are not necessary to obtain a complete understanding of the present invention and are within the abilities of persons of ordinary skill in the relevant art.

[0026] Some drawings may illustrate signals as a single signal for clarity of presentation and description. It will be understood by a person of ordinary skill in the art that the

signal may represent a bus of signals, wherein the bus may have a variety of bit widths and the present invention may be implemented on any number of data signals including a single data signal.

[0027] The terms “wafer” and “substrate” are to be understood as a semiconductor-based material including silicon, silicon-on-insulator (SOI) or silicon-on-sapphire (SOS) technology, doped and undoped semiconductors, epitaxial layers of silicon supported by a base semiconductor foundation, and other semiconductor structures. Furthermore, when reference is made to a “wafer” or “substrate” in the following description, previous process steps may have been utilized to form regions or junctions in or over the base semiconductor structure or foundation. In addition, the semiconductor need not be silicon-based, but may be based on silicon-germanium, silicon-on-insulator, silicon-on-sapphire, germanium, or gallium arsenide, among others.

[0028] The term “pixel” refers to a picture element unit cell containing a photosensor and transistors for converting electromagnetic radiation to an electrical signal. For purposes of illustration, a representative pixel is illustrated in the figures and description herein and, typically, fabrication of all pixels in an imager will proceed simultaneously in a similar fashion.

[0029] FIG. 1 is a simplified block diagram of a semiconductor imager **100** in accordance with an embodiment of the invention. The imager includes a sensor array **200**, a row decoder **110**, a column decoder **120**, and a controller **130**. The sensor array **200** (which may also be referred to as an array of pixels) includes photo-sensitive devices such as photodiodes, photo-transistors, photoconductors, and photogates fabricated on, for example, a complementary metal oxide semiconductor (CMOS) device. Each photo-sensitive device is sensitive to light in such a way that it can create an electrical charge that is proportional to the intensity of light striking the photo-sensitive device. The overall image captured by the sensor array **200** includes many pixels arranged in an array such that each pixel detects the light intensity at the location of that pixel.

[0030] As stated earlier, a single pixel may include a single photo-sensitive device configured for detecting a broad frequency range, which may be used for gray scale images. In addition, a pixel may be defined as a single photo-sensitive device configured for detecting a specific color (i.e., frequency). Finally, a pixel may be a group of photo-sensitive devices arranged near each other wherein different devices within the group are configured for detecting different colors. Thus, a full color image may be detected with an appropriate combination of color sensing pixels. The term pixel as used herein may refer to a single photo-sensitive device for detecting a broad range of frequencies, a single photo-sensitive device for detecting a narrow frequency band, or a combination of photo-sensitive devices configured to capture a color image at the location of the pixel. The pixels of the sensor array **100** are arranged in individually addressable rows and columns such that the row decoder **110** can address each row of the sensor array **200** and the column decoder **120** can address each column of the sensor array **200**. While not illustrated with connections, it will be understood by those of ordinary skill in the art that the controller **130** may control functions of many or all of the other blocks within the image sensor. For example, the controller **130** may control the exposure of the sensor array **200** (i.e., capturing an image) and the

sequencing of the row decoder 110 and column decoder 120 to read out the analog values at each pixel location within the sensor array 200.

[0031] While not limited to a certain sequence, generally, the row decoder 110 selects a specific row and the column decoder 120 then receives every pixel in the selected row in parallel. The column decoder 120 can then sequence through each pixel within the selected row to determine the charge on each pixel.

[0032] As the pixels are each individually addressed, the resulting analog signal from each pixel may be sequentially directed from the column decoder 120 to an analog to digital converter 140. The analog to digital converter 140 converts the analog signal for each pixel to a digital signal representing the intensity of light at that pixel.

[0033] The digital signal for each pixel may be directed through a pixel processor 150. The pixel processor 150 may perform a number of functions on the pixel being processed. By way of example, and not limitation, if a pixel is identified as including an anomaly or defect, the value for the pixel may be replaced with a new value. For example, the value may be replaced by the value of a neighboring pixel or an average value from a number of neighboring pixels. In addition, other signal processing functions, such as, for example, filtering and compression may be performed by the pixel processor 150.

[0034] After processing, the current pixel may be transferred to an input/output (I/O) port 160 for transmission out of the semiconductor imager 100. The I/O port 160 may include storage to save up values from a number of pixels such that pixel values may be transferred out of the semiconductor imager 100 in a parallel or serial fashion.

[0035] FIG. 2 is a top plan view illustrating an example of a possible layout of a semiconductor imager 100 including a sensor array 200 and peripheral circuitry 190 in accordance with an embodiment of the invention. The sensor array 200 includes the area of the semiconductor imager 100 where the pixels are formed and may be referred to herein as a pixel array region 200. Bordering the pixel array region 200 is the periphery region 190. The periphery region 190 may include peripheral circuitry, such as, for example, row decoders, column decoders, analog signal processing circuitry, analog to digital converters, input/output circuitry, and input/output pads. The configuration illustrated in FIG. 2 is simplified and shown as an example layout. Furthermore, while FIG. 2 illustrates periphery regions 190 on all sides of the pixel array region 200, those of ordinary skill in the art will recognize that the periphery regions 190 may be present on one or more sides of the pixel array region 200.

[0036] A brief discussion of a possible pixel configuration is included to give a basic understanding of the types of devices that may be present in the pixel array region 200 and how they may be isolated. FIGS. 3A-3C illustrate various views of an example implementation of a pixel 210 using a photodiode 220 and a 4-transistor control structure for the pixel 210. Those of ordinary skill in the art will recognize that the present invention may be practiced with a wide variety of pixel structures other than the one illustrated in FIGS. 3A-3C and may include devices not shown, such as, for example resistors, capacitors, photoconductors, phototransistors and photogates. FIG. 3A is a top plan view illustrating an example layout of the pixel sensor 210 in accordance with an embodiment of the invention. FIG. 3B is a circuit diagram of the pixel sensor 210 of FIG. 3A. Finally, FIG. 3C is a cross-sectional

view of the pixel sensor 210 of FIG. 3A along section line A-A. The pixel sensor 210 includes a photodiode 220, a transfer transistor 230, a floating diffusion region 240, a reset transistor 250, a source follower transistor 260, and a row select transistor 270.

[0037] In operation, the reset transistor 250 may be enabled to place the floating diffusion region 240 to a known potential, such as substantially near the potential of the V_{aa} voltage source. Either before or after initializing the floating diffusion region 240, the photodiode 220 may be exposed to light to convert photons to electrons in the photodiode region 220. The transfer transistor 230 is enabled to transfer the charge collected by the photodiode 220 onto the floating diffusion region 240. The floating diffusion region 240 is coupled to the gate of the source follower transistor 260 such that the charge on the floating diffusion region 240 is converted to a signal at the drain of the source follower transistor 260, wherein the signal is proportional to the charge on the floating diffusion region 240. The row select transistor 270 may be enabled to allow the signal at the drain of the source follower transistor 260 to be presented on the V_{out} signal.

[0038] The cross-section of FIG. 3C also illustrates isolation regions 310. The isolation region 310 on the right side of FIG. 3C assists in isolating the photodiode region 220 from any other devices in the pixel array. Similarly, the isolation region 310 on the left side of FIG. 3C assists in isolating the floating diffusion node 240 from other devices in the pixel array. Although not illustrated, those of ordinary skill in the art will recognize that the isolation regions may substantially surround the diffusion regions of the photodiode and diffusion regions of other devices in the pixel array.

[0039] FIGS. 4 and 5 illustrate isolation regions substantially surrounding devices, such as, for example, transistors in both the pixel array region 200 and the periphery region 190. For simplicity, most of the figures and discussion presented herein are directed to n-channel transistors on a p-type substrate. However, those of ordinary skill in the art will recognize the embodiments of the present invention may include isolation structures for other devices, such as, for example, p-channel transistors, resistors, capacitors, photoconductors, and photogates. With a p-type substrate, the p-channel devices may be formed in an n-well and the isolation structures discussed herein may be formed within the n-well rather than the p-type substrate. Also, an n-type substrate, with p-wells may be used as is known by those of ordinary skill in the art.

[0040] FIG. 4 is a top plan view illustrating example layouts of transistors in both the periphery region 190 and the pixel array region 200. Although FIGS. 4-9C illustrate only a portion of the substrate with a single device in the periphery region 190 and one or two devices in the pixel array region 200, those of ordinary skill in the art will recognize that these figures and their corresponding descriptions contemplate the substantially simultaneous formation of many devices and isolation structures at various locations in the periphery region 190 and pixel array region 200.

[0041] FIG. 5 is a cross-sectional view of the layout of FIG. 4 along section line B-B. As stated earlier, a type of isolation region that is advantageous for pixel array devices may not be as advantageous for devices in the periphery around the array. When discussing isolation regions 310, the element numbering follows a convention of appending an "A" to indicate that the isolation region 310 is in the array region 200, or a "P" to indicate the isolation region 310 is in the periphery region

190. Furthermore, the element number may include an additional indicator such as “S” to indicate an STI region type of isolation, an “L” to indicate a LOCOS type of isolation, or a “D” to indicate a diffusion type of isolation.

[0042] In FIGS. 4 and 5, a periphery transistor is formed by gate **340P** crossing n-type diffusion regions **350** to form an n-channel transistor. This periphery transistor includes an isolation region **310P** surrounding the diffusion regions **350**. While illustrated as completely surrounding the diffusion regions, embodiments of the present invention may include isolation on only some sides of the transistor. FIGS. 4 and 5 also illustrate a top gate **340A1** crossing n-type diffusion regions **350** to form an n-channel transistor in the pixel array region **200** and a bottom gate **340A** crossing n-type diffusion regions **350** to form another n-channel transistor in the pixel array region **200**. These array transistors include an isolation region **310A** surrounding the diffusion regions **350**. While illustrated as completely surrounding the diffusion regions, embodiments of the present invention may include isolation on only some sides of the transistors in the pixel array region **200**.

[0043] As illustrated in FIG. 5, an insulating layer **330** for example, silicon oxide may be grown or deposited on the substrate **300**. This insulating layer **330** serves as the gate oxide or dielectric layer for the subsequently formed transistors. Next, a layer of conductive material is deposited over the oxide layer **330**. The conductive layer (**340A** and **340P**) serves as the gate electrode for the transistors. The conductive layer may be a layer of doped polysilicon or other suitable material. A second insulating layer (not shown) may be deposited over the polysilicon layer (**340A** and **340P**). The second insulating layer may be formed of, for example, an oxide (SiO_2), a nitride (silicon nitride), an oxynitride (silicon oxynitride), ON (oxide-nitride), NO (nitride-oxide), or ONO (oxide-nitride-oxide).

[0044] FIG. 5 illustrates isolation regions (**310P** and **310A**) formed at certain depths within the substrate **300**. An example of a need for isolation between devices may be illustrated in FIG. 4, by discussing the region between the top gate **340A1** of the top transistor in the pixel array region **200** and the bottom gate **340A2** of the bottom transistor in the pixel array region **200**. Without isolation in this region, the area between these two transistors may behave somewhat like a transistor such that when one or both gates (**340A1** and **340A2**) are asserted and there is a potential voltage bias difference between the diffusion areas **350**, an inversion layer causing a small amount of conduction may occur between the diffusion areas **350** of the top transistor and the bottom transistor. An isolation region between the diffusion areas **350** of these two transistors will help to eliminate the potential inversion layer and minimize this possible conduction or leakage.

[0045] As discussed earlier, different types of isolation may have different advantages and shortcomings. As a result, isolation that is advantageous for devices in the pixel array region **200** may not be as advantageous for devices in the periphery region **190**. For example, a common issue associated with the formation of STI regions is that, when ions are implanted in the substrate close to the bottom and edges or sidewalls of the trench, current leakage can occur at the junction between the active device regions and the trench resulting in “hot pixels,” (i.e., pixels that may appear brighter than other pixels). In addition, the dominant crystallographic planes along the bottom and sidewalls of the trench isolation regions have a higher silicon density than the adjacent silicon sub-

strate and, therefore, create a high density of trap sites along the trench bottom and sidewalls. These trap sites are normally uncharged but may become charged when electrons and holes become trapped in the trap sites. As a result of these trap sites formed along the bottom and sidewalls of the trench isolation regions, current generation near and along the trench bottom and sidewalls may occur. Current generated from trap sites inside or near the photodiode depletion region may cause undesired dark current. Minimizing hot pixels and dark current in a photodiode is important in CMOS image sensor fabrication. However, isolation between pixels and various devices in the pixel array is also important. As a result, embodiments of the present invention may use STI regions of a certain depth in the pixel array region **200** and STI regions of a different depth in the peripheral region **190**.

[0046] As another example, LOCOS isolation or diffusion isolation may provide sufficient isolation between devices in the pixel array region **200**, but may not be deep enough into the substrate to provide sufficient isolation in the periphery region **190** or may not allow small enough isolation regions (e.g., tight geometries) in the periphery region **190**, adversely affecting packing density. Conversely, in some cases it may be more advantageous to include STI isolation in the pixel array region **200** with LOCOS isolation or diffusion isolation in the periphery region **190**.

[0047] Therefore, embodiments of the present invention contemplate all combinations of isolation regions wherein the isolation regions **310P** in the periphery region differ from the isolation regions **310A** in the array region **200**. For example these combinations may include STI regions of a first depth, STI regions of a second depth, LOCOS isolation regions, and diffusion isolation regions.

[0048] FIGS. 6A-6C are cross-sectional views of structures along section lines C-C of FIG. 4 that may be used in accordance with embodiments of the invention. FIG. 6A illustrates a periphery gate **340P** over oxide **330** to form an n-channel region **360** in the periphery region **190**. Bordering the n-channel region **360** are periphery isolation regions **310PS** formed as STI regions of a first depth **D1**. In the array region **200**, array gate **340A** over oxide **330** forms an n-channel region **360**. Bordering the n-channel region **360** are array isolation regions **310AS** formed as STI regions of a second depth **D2**.

[0049] FIG. 6B illustrates a periphery gate **340P** over oxide **350** to form an n-channel region **360** in the periphery region **190**. Bordering the n-channel region **360** are periphery isolation regions **310PS** formed as STI regions. In the array region **200**, array gate **340A** over oxide **350** forms an n-channel region **360**. Bordering the n-channel region **360** are array isolation regions **310AL** formed as LOCOS regions.

[0050] FIG. 6C illustrates a periphery gate **340P** over oxide **330** to form an n-channel region **360** in the periphery region **190**. Bordering the n-channel region **360** are periphery isolation regions **310PS** formed as STI regions. In the array region **200**, array gate **340A** over oxide **330** forms an n-channel region **360**. Bordering the n-channel region **360** are array isolation regions **310AD** formed as diffusion regions of heavily doped p-type material. Of course, if the transistor was formed as a p-channel transistor in an N-well (or N-substrate), the isolation region **310AD** would be formed as a diffusion region of heavily doped n-type material.

[0051] As stated earlier, other combinations of isolation regions may be used. Thus, while FIGS. 6A-6C illustrate only STI regions in the periphery, with different combinations in the array, combination with LOCOS regions or doped regions

in the periphery are contemplated within the scope of the invention. These other combinations may be easily derived from the discussion herein by a person of ordinary skill in the art and need not be described in detail.

[0052] FIGS. 7A-9C are cross-sectional views illustrating process stages used for various embodiments of the invention. For simplicity, only process steps involved in forming the isolation regions are illustrated. Those of ordinary skill in the art will recognize other process steps involved in forming devices on the wafer may occur before, after, or in conjunction with the process steps involved in forming the isolation regions.

[0053] FIGS. 7A-7C are cross-sectional views illustrating process stages used in accordance with an embodiment of the invention that uses STI regions in the periphery region **190** and STI regions of a different depth in the array region **200**. Trench isolation regions may be formed by etching trenches into the substrate **300** to provide a physical barrier between adjacent devices and to isolate devices optically and electrically from one another.

[0054] The example shown in FIGS. 7A-7C illustrate deeper trenches in the periphery region **190** than the trenches in the array region **200**. By way of example, and not limitation, the periphery trenches **315PS** may be about 3000 angstroms deep and the array trenches **315AS** may be about 500-1500 angstroms deep. While not shown, embodiments of the present invention may have the deeper trenches in the array region **200** with shallower trenches in the periphery region **190**.

[0055] FIG. 7A illustrates the process for forming STI trenches in the array region **200**. The substrate **300** is covered with a barrier oxide layer **305** and a patterning layer **360**. Typically, the barrier oxide may be a grown oxide. The patterning layer **360** may be a hard mask material, such as silicon nitride or silicon oxide material formed over the barrier oxide layer **305**. Although, for simplicity, the process is described illustrating the patterning layer **360** formed over the barrier oxide layer **305**, it should be understood that the barrier oxide layer **305** need not be present. The patterning layer **360** and barrier oxide layer **305** are coated with resist, photo-patterned, and etched to expose areas of the substrate where trenches are to be formed. Then, the trenches **315AS** are etched to the second depth D2. The trenches may be etched by employing a dry anisotropic or other etching process. After the array trenches **315AS** are formed, the photoresist **370** is stripped by conventional techniques, such as wet or dry etching.

[0056] FIG. 7B illustrates the process for forming STI trenches in the periphery region **190**. The nitride patterning layer **360'** and barrier oxide layer **305** are again coated with resist, photo-patterned, and etched to expose areas of the substrate where the periphery trenches are to be formed. Then, the trenches **315PS** are etched to the first depth D1. After the periphery trenches **315PS** are formed, photoresist **370** is removed by conventional techniques, such as wet or dry etching. Of course, the order of forming the array trenches **315AS** first and the periphery trenches **315PS** second may be reversed.

[0057] As illustrated in FIG. 7C, with trenches formed in the periphery region **190** and the array region **200**, the trenches may be filled with a dielectric, such as, for example, a silicon oxide such as SiO or SiO₂, a thermally grown oxide, oxynitride, a nitride material such as silicon nitride, silicon carbide, a high temperature polymer, or other suitable dielec-

tric materials and combinations thereof. For example, the trench isolation region may include a thin layer of insulating material formed on the sidewalls and bottom of the trench. The thin insulating layer may be formed of a thermally grown oxide or of silicon nitride or an oxide/nitride combination, for example, to aid in smoothing out the corners in the bottom of the trench and to reduce the amount of stress in the dielectric material used to later fill in the trenches. The remaining trench area may be filled with a silicon oxide or other suitable material with a process such as chemical vapor deposition (CVD). The filled trenches **315AS** and **315PS** are then planarized by an etch-back process, or Chemical-Mechanical Planarization (CMP) process for example, so that the dielectric remains only in the trenches and their top surface remains level with, or slightly above, that of the substrate **300**. After the trenches (**315AS**, **315PS**) are filled, the barrier oxide **305** and patterning nitride layer **360** are removed by conventional techniques, such as wet or dry etching. The result is periphery STI regions **310PS** and array STI regions **310AS**.

[0058] FIGS. 7A-7C illustrate the filing of the array trenches **315AS** and periphery trenches **315PS** at the same time. However, the two different types of trenches may be filled separately. In other words, the periphery trenches **315PS** may be filled after they are patterned and etched and the array trenches **315AS** may be filled after they are patterned and etched.

[0059] FIGS. 8A-8C are cross-sectional views illustrating process stages used in accordance with another embodiment of the invention that uses STI regions in the periphery region **190** and LOCOS regions in the array region **200**.

[0060] FIG. 8A illustrates the process for forming STI trenches in the periphery region **190**. The substrate **300** is covered with a barrier oxide layer **305** and a patterning layer **360**. Typically, the barrier oxide may be a grown oxide. The patterning layer **360** may be a hard mask material, such as silicon nitride or silicon oxide material formed over the barrier oxide layer **305**. Although, for simplicity, the process is described illustrating the patterning layer **360** formed over the barrier oxide layer **305**, it should be understood that the barrier oxide layer **305** need not be present. The patterning layer **360** and barrier oxide layer **305** are coated with resist, photo-patterned, and etched to expose areas of the substrate where trenches are to be formed. Then, the trenches **315PS** are etched. The trenches may be etched by employing a dry anisotropic or other etching process. After the trenches **315PS** are formed, the photoresist **370** is removed by conventional techniques, such as wet or dry etching. With trenches formed in the periphery region **190**, the trenches may be filled with a dielectric and planarized as is explained above. Then, the barrier oxide layer **305** and nitride patterning layer **360** are removed by conventional techniques, such as wet or dry etching.

[0061] FIG. 8B illustrates the formation of LOCOS isolation regions in the array region **200**. The substrate **300** is covered with a barrier oxide layer **305** and a second patterning layer **360''**. Typically, the barrier oxide may be a deposited oxide. The patterning layer **360''** may be a hard mask material, such as silicon nitride or silicon oxide material formed over the barrier oxide layer **305**. The patterning layer **360''** and barrier oxide layer **305** are coated with resist, photo-patterned, and etched to expose areas of the substrate where LOCOS regions are to be formed. With the substrate exposed in selected regions, the photoresist **370** is removed by con-

ventional techniques, and the LOCOS regions **310AL** may be formed of thermally grown oxide in the exposed regions.

[0062] As illustrated in FIG. 8C, after the LOCOS regions **310AL** are formed, the barrier oxide layer **305** and patterning layer **360** are removed by conventional techniques, such as wet or dry etching.

[0063] FIGS. 8A-8C illustrate the formation of the periphery STI structures **310PS** first and the formation of the array LOCOS regions **310AL** second. Of course, these steps may occur in the opposite order.

[0064] FIGS. 9A-9C are cross-sectional views illustrating process stages used in accordance with another embodiment of the invention that uses STI regions in the periphery region **190** and doped regions in the array region **200**.

[0065] FIG. 9A illustrates the process for forming STI trenches in the periphery region **190**. The substrate **300** is covered with a barrier oxide layer **305** and a patterning layer **360**. Typically, the barrier oxide may be a grown oxide. The patterning layer **360** may be a hard mask material, such as silicon nitride or silicon oxide material formed over the barrier oxide layer **305**. Although, for simplicity, the process is described illustrating the patterning layer **360** formed over the barrier oxide layer **305**, it should be understood that the barrier oxide layer **305** need not be present. The patterning layer **360** and barrier oxide layer **305** are coated with resist, photo-patterned, and etched to expose areas of the substrate where trenches are to be formed. Then, the trenches **315PS** are etched. The trenches may be etched by employing a dry anisotropic or other etching process. After the trenches **315PS** are formed, the photoresist **370** is removed by conventional techniques, such as wet or dry etching. With trenches formed in the periphery region **190**, the trenches may be filled with a dielectric and planarized as is explained above. After the trenches **315PS** are filled, the barrier oxide **305** and patterning nitride layer **360** are removed by conventional techniques, such as wet or dry etching.

[0066] FIG. 9B illustrates the formation of doped regions **310AD** in the array region **200**. The substrate **300** is covered with a barrier oxide layer **305** and a patterning layer **370**. Typically, the barrier oxide may be a deposited oxide. The patterning layer **370** may be a photoresist layer formed over the barrier oxide layer **305**. As with the other embodiments, it should be understood that the barrier oxide layer **305** need not be present. The patterning layer **370** is developed and baked to expose areas of the substrate where doped regions are to be formed.

[0067] With the substrate exposed in selected regions, the doped regions **310AD** may be formed by implantation of a p-type dopant through the open regions in the patterning layer **370**. By way of example, and not limitation, the p-type dopant may be boron, beryllium, indium, or magnesium. As stated earlier, isolation regions may be formed around p-channel devices also. For the case of p-channel devices, the doped regions **310AD** may be formed with n-type dopant. By way of example, and not limitation, the n-type dopant may be phosphorus, arsenic, or antimony.

[0068] As illustrated in FIG. 9C, after the doped regions **310AD** are formed, the barrier oxide layer **305** and patterning layer **370** are removed by conventional techniques, such as wet or dry etching.

[0069] FIGS. 9A-9C illustrate the formation of the periphery STI structures **310PS** first and the formation of the doped regions **310AD** second. Of course, these steps may occur in the opposite order. Furthermore, those of ordinary skill in the

art will recognize that the doped isolation regions **310AD** may also be formed after poly gate deposition.

[0070] While only illustrated with one type of isolation in the periphery and another type of isolation in the array, those of ordinary skill in the art will understand that embodiments of the present invention may include more than one type of isolation in the periphery and more than one type of isolation in the array.

[0071] FIG. 10 illustrates an imaging system **400** including a semiconductor imager **100** containing isolation devices according to the present invention. The imaging system **400** includes a processor **430** for receiving and modifying digital representations of images from the semiconductor imager **100**. The imaging system **400** may also include an optical receiver **410** for channeling, focusing, or modifying incident energy **420**, being visible light in one case, to present an optical image to the image sensor. For example, the optical receiver **410** may include a lens **415** for focusing the incident energy **420** onto the semiconductor imager **100**.

[0072] The imaging system **400** may include a communication interface **460** for transmitting and receiving data and control information. Finally, the imaging system **400** may include memory (**440** and **450**) in the form of local storage **440** and removable storage **450**, such as, for example, Flash memory, magnetic recording media and optical recording media.

[0073] Without being limiting, such an imaging system **400** may include systems such as a computer system, camera system, scanner, machine vision, videophone, surveillance system, auto focus system, image stabilization system, and data compression system.

[0074] Although this invention has been described with reference to particular embodiments, the invention is not limited to these described embodiments. Rather, the invention is limited only by the appended claims, which include within their scope all equivalent devices or methods that operate according to the principles of the invention as described.

1. A semiconductor imager, comprising:

a sensor array comprising a plurality of pixels arranged in rows and columns, each pixel of the plurality including at least one array isolation region configured to substantially isolate a first array-circuit-element from a second array-circuit-element; and

peripheral circuitry arranged on at least one side of the sensor array, the peripheral circuitry including at least one periphery isolation region configured to isolate a first peripheral-circuit-element from a second peripheral-circuit-element, wherein the at least one periphery isolation region differs in configuration from the at least one array isolation region.

2. The semiconductor imager of claim 1, wherein each of the first array-circuit-element and the second array-circuit-element are selected from the group consisting of a photodiode, a photoconductor, a photogate, a transistor, and a capacitor.

3. The semiconductor imager of claim 1, wherein the at least one periphery isolation region includes a shallow trench isolation structure.

4. The semiconductor imager of claim 3, wherein at least one additional periphery isolation region includes one or more structures selected from the group consisting of, a p-type doped region, an n-type doped region, and a LOCOS region.

5. The semiconductor imager of claim 3, wherein the at least one array isolation region includes one or more structures selected from the group consisting of a STI region with a depth different from the STI region of the at least one periphery isolation region, a p-type doped region, an n-type doped region, and a LOCOS region.

6. The semiconductor imager of claim 1, wherein the at least one periphery isolation region includes a LOCOS region.

7. The semiconductor imager of claim 6, wherein at least one additional periphery isolation region includes one or more structures selected from the group consisting of a p-type doped region, an n-type doped region, and a STI region.

8. The semiconductor imager of claim 6, wherein the at least one array isolation region includes one or more structures selected from the group consisting of a p-type doped region, an n-type doped region, and a STI region.

9. The semiconductor imager of claim 1, wherein the at least one periphery isolation region includes a doped region.

10. The semiconductor imager of claim 9, wherein at least one additional periphery isolation region includes one or more structures selected from the group consisting of a LOCOS region, and a STI region.

11. The semiconductor imager of claim 9, wherein the at least one array isolation region includes one or more structures selected from the group consisting of a LOCOS region, and a STI region.

12. The semiconductor imager of claim 9, wherein the doped region is selected from the group consisting of a p-type doped region and an n-type doped region.

13. A method of isolating circuit elements in a semiconductor imager, comprising:

isolating array devices formed as part of pixel array with array isolation regions disposed around at least a portion of at least some of the array devices; and

isolating periphery devices formed outside of the pixel array with periphery isolation regions disposed around at least a portion of at least some of the periphery devices;

wherein the array isolation regions are formed differently from the periphery isolation regions.

14. The method of claim 13, wherein:

isolating the array devices is performed using first STI structures disposed around at least a portion of at least some of the array devices; and

isolating the periphery devices is performed using second STI structures disposed around at least a portion of at least some of the periphery devices, wherein the second STI structures have a depth that differs from a depth of the first STI structures.

15. The method of claim 13, wherein:

isolating the array devices is performed using STI structures disposed around at least a portion of at least some of the array devices; and

isolating the periphery devices is performed using LOCOS structures disposed around at least a portion of at least some of the periphery devices.

16. The method of claim 13, wherein:

isolating the array devices is performed using STI structures disposed around at least a portion of at least some of the array devices; and

isolating the periphery devices is performed using doped regions around at least a portion of at least some of the periphery devices.

17. The method of claim 13, wherein:

isolating the array devices is performed using LOCOS structures disposed around at least a portion of at least some of the array devices; and

isolating the periphery devices is performed using STI structures disposed around at least a portion of at least some of the periphery devices.

18. The method of claim 13, wherein:

isolating the array devices is performed using LOCOS structures disposed around at least a portion of at least some of the array devices; and

isolating the periphery devices is performed using doped regions around at least a portion of at least some of the periphery devices.

19. The method of claim 13, wherein:

isolating the array devices is performed using doped regions around at least a portion of at least some of the array devices; and

isolating the periphery devices is performed using STI structures disposed around at least a portion of at least some of the periphery devices.

20. The method of claim 13, wherein:

isolating the array devices is performed using doped regions around at least a portion of at least some of the array devices; and

isolating the periphery devices is performed using LOCOS structures disposed around at least a portion of at least some of the periphery devices.

21. A method of forming a semiconductor imager, comprising:

providing a semiconductor substrate;

forming array devices on the semiconductor substrate in a pixel array region and forming periphery devices on the semiconductor substrate in at least one periphery region bordering the pixel array region;

forming array isolation regions in the pixel array region of the semiconductor substrate; and

forming periphery isolation regions in the at least one periphery region, wherein the periphery isolation regions differ in configuration from the array isolation regions.

22. The method of claim 21, wherein:

forming the periphery isolation regions comprises forming periphery trenches to a first depth and filling the periphery trenches with an oxide material; and

forming the array isolation regions comprises forming array trenches to a second depth and filling the array trenches with the oxide material, wherein the second depth differs from the first depth.

23. The method of claim 22, wherein filling the array trenches and filling the periphery trenches occurs at substantially the same time.

24. The method of claim 21, wherein:

forming the periphery isolation regions comprises forming periphery trenches and filling the periphery trenches with an oxide material; and

forming the array isolation regions comprises forming doped regions.

25. The method of claim 24, wherein forming the doped regions comprises an operation selected from the group consisting of implanting a p-type dopant, implanting an n-type dopant, and combinations thereof.

26. The method of claim 21, wherein:
forming the periphery isolation regions comprises forming periphery trenches and filling the periphery trenches with an oxide material; and
forming the array isolation regions comprises forming LOCOS regions by thermal growth of another oxide material.
27. The method of claim 21, wherein:
forming the periphery isolation regions comprises forming doped regions; and
forming the array isolation regions comprises forming array trenches and filling the array trenches with an oxide material.
28. The method of claim 27, wherein forming the doped regions comprises an operation selected from the group consisting of implanting a p-type dopant, implanting an n-type dopant, and combinations thereof.
29. The method of claim 21, wherein:
forming the periphery isolation regions comprises forming doped regions; and
forming the array isolation regions comprises forming LOCOS regions by thermal growth of an oxide material.
30. The method of claim 29, wherein forming the doped regions comprises an operation selected from the group consisting of implanting a p-type dopant, implanting an n-type dopant, and combinations thereof.
31. The method of claim 21, wherein:
forming the periphery isolation regions comprises forming LOCOS regions by thermal growth of an oxide material; and
forming the array isolation regions comprises forming periphery trenches and filling the periphery trenches with another oxide material.
32. The method of claim 21, wherein:
forming the periphery isolation regions comprises forming LOCOS regions by thermal growth of an oxide material; and

forming the array isolation regions comprises forming doped regions.

33. The method of claim 32, wherein forming the doped regions comprises an operation selected from the group consisting of implanting a p-type dopant, implanting an n-type dopant, and combinations thereof.

34. The method of claim 21, wherein forming the array devices comprises forming devices selected from the group consisting of photodiodes, photoconductors, photogates, transistors, capacitors, and combinations thereof.

35. An imaging system, comprising:

a semiconductor imager, comprising:

a sensor array comprising a plurality of pixels arranged in rows and columns, each pixel of the plurality including at least one array isolation region configured to substantially isolate a first array-circuit-element from a second array-circuit-element; and

peripheral circuitry arranged on at least one side of the sensor array, the peripheral circuitry including at least one periphery isolation region configured to isolate a first peripheral-circuit-element from a second peripheral-circuit-element, wherein the at least one periphery isolation region differs in configuration from the at least one array isolation region; and

a memory operably coupled to the semiconductor imager and configured for storing a digital representation of an image captured by the sensor array.

36. The imaging system of claim 35, further comprising an optical receiver configured to receive and modify incident light and present the modified light to the sensor array.

37. The imaging system of claim 35, further comprising:
a processor operably coupled to the semiconductor imager; and

a communication interface operably coupled to the processor and configured for communicating the digital representation to an external device.

* * * * *