




US 20100232492A1

(19) **United States**(12) **Patent Application Publication****Mezer et al.**(10) **Pub. No.: US 2010/0232492 A1**(43) **Pub. Date: Sep. 16, 2010**(54) **TRANSMITTER CONTROL IN
COMMUNICATION SYSTEMS****Publication Classification**(51) **Int. Cl.**
H04L 27/01 (2006.01)(52) **U.S. Cl.** **375/232**(76) Inventors: **Amir Mezer**, Haifa (IL); **Adee
Ran**, Maayan Baruch (IL)Correspondence Address:
INTEL CORPORATION
c/o CPA Global
P.O. BOX 52050
MINNEAPOLIS, MN 55402 (US)(57) **ABSTRACT**

Techniques are described to adaptively adjust the equalizer settings of each transmitter in a transmitter-receiver pair. The transmitter-receiver pair can be used at least with implementations that comply with 40GBASE-CR4 or 100GBASE-CR10. For implementations that comply with 40GBASE-CR4, equalizer settings of four transmitters may be independently established.

(21) Appl. No.: **12/381,282**(22) Filed: **Mar. 10, 2009**




FIG. 1




FIG. 2
(PRIOR ART)

TRANSMITTER CONTROL IN COMMUNICATION SYSTEMS

RELATED APPLICATIONS

[0001] This application is a continuation-in-part of U.S. patent applications having Ser. Nos. _____, and _____ entitled “Interconnection Techniques” and “Cable Interconnection Techniques,” both filed Mar. 9, 2009, inventors Ganga and Mellitz and incorporates by reference the contents of those applications in their entirety.

FIELD

[0002] The subject matter disclosed herein relates generally to techniques to transmit signals.

RELATED ART

[0003] The Institute of Electrical and Electronics Engineers, Inc. (IEEE) has defined numerous networking standards. For example, 10 GBASE-CX4 defines signal transmission at 10 Gbps using four lanes over copper cabling. Similarly, 10 GBASE-KX4 defines signal transmission at 10 Gbps using four lanes over backplane whereas 10 GBASE-KR defines signal transmission at 10 Gbps over a single lane over backplane.

[0004] The evolving IEEE 802.3ba draft 1.1 (2008) standard defines 40 Gbps operation over copper cable. This evolving standard is also known as 40 GBASE-CR4. Copper coaxial cables are characterized by frequency dependent loss and exhibit loss strongly dependent on channel length. Various vendors have proposed manners to transmit at 40 Gbps over copper cable. For example, one implementation involves use of fixed transmit equalization in compliance with SFP+ as described in IEEE Std. 802.3ae-2002 and IEEE Std. 802.3aq-2006. In this implementation, the transmitter circuit is coupled to a hot pluggable optical cable using a fixed length printed circuit board trace. Fixed transmit equalization involves establishing a desired eye opening at a transmitter side. An eye diagram represents transitions of a signal. The more open an eye diagram, the less likelihood the signal will be misread. However, because copper cable length varies, this scheme leads to varying voltage levels and eye patterns at the receiver. Different eye openings at the receiver can lead to errors in reading received data.

[0005] Another approach to reproducing received signals includes use of an analog filter at the receiver (e.g., a continuous-time linear equalizer (CTLE)). However, this approach provides suboptimal eye opening characteristics at the receiver. Yet another approach involves use of an analog-to-digital converter (A/D) and digital signal processor at the receiver. However, this approach uses high power and is complicated to implement.

[0006] It is desirable to develop techniques to provide acceptable received signal performance over copper cable at speeds over 10 Gbps such as at 40 Gbps.

BRIEF DESCRIPTION OF THE DRAWINGS

[0007] Embodiments of the present invention are illustrated by way of example, and not by way of limitation, in the drawings and in which like reference numerals refer to similar elements.

[0008] FIG. 1 depicts a system, in accordance with an embodiment.

[0009] FIG. 2 depicts an example of a transmitter equalizer defined by FIG. 72-11 of IEEE Std 802.3ap-2007.

DETAILED DESCRIPTION

[0010] Reference throughout this specification to “one embodiment” or “an embodiment” means that a particular feature, structure, or characteristic described in connection with the embodiment is included in at least one embodiment of the present invention. Thus, the appearances of the phrase “in one embodiment” or “an embodiment” in various places throughout this specification are not necessarily all referring to the same embodiment. Furthermore, the particular features, structures, or characteristics may be combined in one or more embodiments.

[0011] Various authors have expressed that use of multiple cables to increase the rate of data transmission may incur cross talk among signals on the cables and lead to unacceptable performance. For example, slide 10 of Cole, “Nx10G Electrical I/O Issues,” IEEE 802.3 Higher Speed Study Group (November 2007) indicates that cross talk from adjacent conductors, traces, and connectors may lead to unacceptable performance. However, embodiments described herein may exhibit acceptable bit error rates when IEEE 802.3ap (2007) is applied across multiple adjacent conductors.

[0012] FIG. 1 depicts a system, in accordance with an embodiment. System 100 includes transmitters 110-A and 110-B and respective complementary receivers 150-A and 150-B. Transmitter 110-A and receiver 150-A are part of the same remote device whereas transmitter 110-B and receiver 150-B are part of the same local device. A receiver may request to adjust equalizer settings of each transmitter from which the receiver receives signals. For example, receiver 150-A may request to adjust equalizer settings of transmitter 110-B. Transmitter 110-A and receiver 150-A operate in a similar manner as that of transmitter 110-B and receiver 150-B.

[0013] For 40 Gbps operation, the transmitter-receiver pairs can be replicated four times for receipt of signals on four lanes. For 100 Gbps operation, the transmitter-receiver pairs can be replicated ten times for receipt of signals on ten lanes. Signals from transmitter-receiver pair channel can be transmitted independently so that each lane operates independently. The number of pairs can be increased to achieve any higher multiple of the basic signaling rate. Also, the basic signaling rate may be higher or lower than that specified by 10 GBASE-KR.

[0014] Electrical transmit and receive specifications of transmitter-receiver pairs may be based on clause 72.7.1 of IEEE 802.3ba draft 1.1 (2008). Combining signals from multiple lanes can be accomplished at a logic level as defined in IEEE 802.3ba draft 1.1 (2008).

[0015] Receiver 150-B includes clock and data recovery logic 152, remote transmit (TX) adaptation engine 154, control channel decoder 156, and transmit control 158. Clock and data recovery logic 152 may recover a clock from a signal received from transmitter 110-A and manipulate the data (e.g., through filtering or adaptive or fixed equalization) to recover the data which was transmitted by transmitter 110-A. Clock and data recovery logic 152 may reproduce a data signal from a signal received from transmitter 110-A and generate an error signal.

[0016] Control channel decoder 156 is a decoder which deciphers the answers (e.g., UPDATED, NOT UPDATED, MIN, OR MAX) received from remote transmitter 110-A

generated in response to requests from transmitter **110-B** to adjust equalizer settings of remote transmitter **110-A**. Table **72-5**, FIG. **72-6**, and clauses 72.6.10.2.4, 72.6.10.2.5, 72.7.1.11 in IEEE Std 802.3ap provide examples of some answers from remote transmitter **110-A**. Control channel decoder **156** transfers the answers to remote TX adaptation engine **154**.

[0017] Control channel decoder **156** may also decipher the requests from a remote device to change the settings of transmitter equalizer **114** of transmitter **110-B** (e.g., increment a tap gain). Control channel decoder **156** may pass the requests to TX control block **158**. TX control block **158** may produce answers to requests from a remote device. TX control block **158** may insert the answers into the control channel for transmission to the remote device by transferring requests to control channel encoder **112**.

[0018] Control channel encoder **112** inserts requests and answers into the control channel, in order to send them to the remote partner. Control channel decoder **156** may try to change the settings of transmit equalizer **114** per requests from a remote device, if possible.

[0019] Transmit equalizer **114** may include a 3-tap transmit FIR driving the analog front-end, as described in 802.3ap (2007). For example, an embodiment of transmit equalizer is depicted in FIG. **2**.

[0020] Some implementations of transmit equalizers may have a bank of N predefined (or arbitrary) transmit equalizers of any form (e.g., Continuous-Time Linear Equalizers (CTLE), finite impulse response filter, and Digital Infinite Impulse Response (IIR) filter), and apply a protocol which scans, while handshaking, between all the equalizer settings, and chooses the best equalizer in the remote transmitter for the receiver.

[0021] Referring again to receiver **150-B**, remote transmit (TX) adaptation engine **154** may determine how to adapt the equalizer of remote transmitter **110-A** based in part on the error signal and the received data from clock and data recovery **152** and an answer from control channel decoder **156**. Remote TX adaptation engine **154** passes the adaptation requirements to control channel encoder **112** of transmitter **110-B**. Control channel encoder **112** inserts these requests into the control channel to send them to receiver **150-A** for transfer to transmitter **110-A**.

[0022] In one embodiment, a receiver **150-A** adjusts the equalization applied by a complementary transmitter **110-A** using a control channel described with regard to the 10 GBASE-KR PMD control function as defined in clause 72.6.10 of IEEE Std 802.3ap-2007. Of note, 10 GBASE-KR is defined in IEEE Std 802.3ap-2007 for backplane but not cable. Establishing equalizer settings may take place after auto-negotiation (described later) successfully completes in order for the receiver to know the number of transmit-receive pairs.

[0023] In some embodiments, twin axial cables can be used as a medium between complementary transmitter and receiver pair. A twin axial cable may include two coaxial cables, with one coaxial cable for transmit direction and another coaxial cable for receive direction. For 40 Gbps signal transmission, eight coaxial cables are used, namely four for the transmit direction and four for the receive direction. However, other types of cable types may be used provided the specifications of clauses 85.10 and 85.11 of IEEE 802.3ba draft 1.1 (2008) are met. Cables with metal conductors other than copper can be used (e.g., any alloy such as but not limited to silver or platinum). Optical single and multimode cables

can be used. Optical cables can be used in active cable assemblies. Active means there are electrical to optical converters in the cable assembly at each end. An equalization setting may be applied for each length of cable between complementary transmitter and receiver pairs.

[0024] Various embodiments of system are capable of transmitting signals at least at 40 Gbps in compliance with 40 GBASE-CR4.

[0025] FIG. **2** depicts an example of a transmitter equalizer defined by FIG. **72-11** of IEEE Std 802.3ap-2007. The feed forward equalizer (FFE) structure is described at clauses 72.7.1.10 and 72.7.1.11 of IEEE Std 802.3ap-2007. In this example, UI represents a clock cycle, $C(1)$ represents a gain applied to a bit two clock cycles ago, $C(0)$ represents a gain of a bit one clock cycle ago, and $C(-1)$ represents a gain of the current bit. An output from the transmitter equalizer is a sum of weighted bits. For example, receiver **150-B** may control the gains $C(-1)$, $C(0)$, and $C(1)$. For example, remote transmit adaptation engine **154** (FIG. **1**) may request to adjust the gains of the transmitter equalizer.

[0026] linear optical modules, standard IEEE 802.3aq (LRM) defines how to perform equalization at receiver to combat inter-symbol interference at receiver. Equalizer settings at linear optical modules of a transmitter may be adjusted to adjust an eye at the receiver side using techniques described herein.

[0027] Adaptive transmit equalization enables enhanced performance compared to fixed equalization. For example, margins for noise (including crosstalk) and jitter may be better for adaptive transmit equalization than those of fixed equalization. Adaptive transmit equalization may permit a broader range of cable lengths and supported tolerances. In addition, adaptive transmit equalization may provide a simplified receiver design as compared to a system with a fixed transmitter equalizer and any form of adaptive receiver equalizer, e.g., equalization in the digital domain after analog to digital conversion, thereby resulting in reduced power consumption. In addition, adaptive transmit equalization may save power in the transmitter by using power back-off, e.g., for short channels. As part of the equalization, the signal power at the receiver is implicitly known and the signal power at the receiver can be used to request the transmitter to reduce its power.

[0028] Embodiments of the present invention may be provided, for example, as a computer program product which may include one or more machine-readable media having stored thereon machine-executable instructions that, when executed by one or more machines such as a computer, network of computers, or other electronic devices, may result in the one or more machines carrying out operations in accordance with embodiments of the present invention. A machine-readable medium may include, but is not limited to, floppy diskettes, optical disks, CD-ROMs (Compact Disc-Read Only Memories), and magneto-optical disks, ROMs (Read Only Memories), RAMs (Random Access Memories), EPROMs (Erasable Programmable Read Only Memories), EEPROMs (Electrically Erasable Programmable Read Only Memories), magnetic or optical cards, flash memory, or other type of media/machine-readable medium suitable for storing machine-executable instructions.

[0029] The drawings and the forgoing description gave examples of the present invention. Although depicted as a number of disparate functional items, those skilled in the art will appreciate that one or more of such elements may well be

combined into single functional elements. Alternatively, certain elements may be split into multiple functional elements. Elements from one embodiment may be added to another embodiment. For example, orders of processes described herein may be changed and are not limited to the manner described herein. Moreover, the actions of any flow diagram need not be implemented in the order shown; nor do all of the acts necessarily need to be performed. Also, those acts that are not dependent on other acts may be performed in parallel with the other acts. The scope of the present invention, however, is by no means limited by these specific examples. Numerous variations, whether explicitly given in the specification or not, such as differences in structure, dimension, and use of material, are possible. The scope of the invention is at least as broad as given by the following claims.

1. A method comprising:
 - receiving a first signal from a first lane;
 - determining first equalizer settings of a first transmitter of the first signal based in part on clock and data recovery of the first signal, wherein the first equalizer used by the first transmitter is in compliance with one or more of clauses 72.7.1.10 and 72.7.1.11 of IEEE Std 802.3ap-2007;
 - requesting adjustment of first equalizer settings using a control channel in compliance with a 10GBASE-KR PMD control function defined in clause 72.6.10 of IEEE Std 802.3ap-2007;
 - receiving a second signal from a second lane;
 - determining second equalizer settings of a second transmitter of the second signal based in part on clock and data recovery of the second signal; and
 - forming a third signal by combining contents of the received first and second signals, wherein
 - an aggregate transmission rate of signals transmitted over the multiple lanes is approximately a number of lanes times a transmission rate specified in 10GBASE-KR of IEEE 802.3ap (2007) and
 - electrical characteristics of the first and second transmitters are in compliance with clause 72.7.1 of IEEE Std 802.3ap-2007.
2. The method of claim 1, wherein the receiving the first and second signals comprise receiving the first and second signals in compliance with electrical characteristics of clause 72.7.1 of IEEE Std 802.3ap-2007.
3. The method of claim 1, wherein the receiving the first and second signals comprise:
 - receiving the first and second signals over a conductive material, wherein the conductive material includes two differential pairs.
4. (canceled)
5. The method of claim 1, further comprising:
 - receiving an indication of whether the first equalizer settings were applied.
6. (canceled)
7. A system comprising:
 - a first transmitter comprising an equalizer, wherein the equalizer is in compliance with one or more of clauses 72.7.1.10 and 72.7.1.11 of IEEE Std 802.3ap-2007;
 - a second transmitter comprising an equalizer, wherein the equalizer is in compliance with one or more of clauses 72.7.1.10 and 72.7.1.11 of IEEE Std 802.3ap-2007, wherein electrical characteristics of the first and second transmitters are in compliance with clause 72.7.1 of IEEE Std 802.3ap-2007;

- a first receiver;
- a second receiver;
- logic to form a third signal by combining content from the first and second signals; and
- at least two sets of differential conductors to communicatively couple the first transmitter to the first receiver and to communicatively couple the second transmitter to the second receiver, wherein each of the at least two sets of conductors are capable of signal transmission in accordance with 10GBASE-KR of IEEE Std 802.3ap-2007, wherein
 - the first receiver comprises:
 - logic to receive a first signal from the first transmitter;
 - logic to determine first equalizer settings of the first transmitter based in part on clock and data recovery of the first signal;
 - logic to request to adjust first equalizer settings of the first transmitter using a control channel in compliance with 10GBASE-KR PMD control function defined in clause 72.6.10 of IEEE Std 802.3ap-2007;
 - the second receiver comprises:
 - logic to receive a second signal from the second transmitter;
 - logic to determine second equalizer settings of the second transmitter based in part on clock and data recovery of the second signal;
 - logic to request to adjust equalizer settings of the second transmitter using a control channel in compliance with 10GBASE-KR PMD control function defined in clause 72.6.10 of IEEE Std 802.3ap-2007; and
 - an aggregate transmission rate of signals transmitted between transmitter-receiver pairs is approximately a number of transmitter-receiver pairs times a transmission rate specified in 10GBASE-KR of IEEE 802.3ap (2007).
- 8. The system of claim 7, wherein the second transmitter further comprises:
 - logic to transmit the first equalizer settings to the second receiver to request to adjust equalizer settings of the first transmitter.
- 9. The system of claim 8, wherein the first receiver comprises:
 - logic to receive an indication of whether the transmitted first equalizer settings were applied by the first transmitter.
- 10. The system of claim 7, wherein the equalizer of the first transmitter comprises a feed forward equalizer and wherein the first transmitter comprises:
 - a control channel encoder to encode control signals for transmission to a the first receiver.
- 11. The system of claim 7, wherein the first receiver comprises:
 - clock and data recovery logic to receive a signal and determine error properties of the first signal,
 - control channel decoder to decode control signals from the first transmitter,
 - remote transmit adaptation engine to determine equalizer settings of the equalizer of the first transmitter based in part on the error properties and the control signals, and

a transmit control logic to request to adjust the settings applied by the equalizer of the first transmitter.

12-15. (canceled)

16. The system of claim 7, wherein the equalizer of the first transmitter comprises a finite impulse response filter.

17. The system of claim 7, wherein the equalizer of the first transmitter comprises a feed forward equalizer.

18. The system of claim 7, wherein the second transmitter includes a Continuous-Time Linear Equalizer (CTLE), finite impulse response filter, and digital infinite impulse response filter, and wherein the first transmitter requests an equalizer used in the second transmitter.

* * * * *