



(51) International Patent Classification:

H04B 10/50 (2013.01) **H04B 10/588** (2013.01)
G02F 1/225 (2006.01)

(21) International Application Number:

PCT/GB2016/051724

(22) International Filing Date:

10 June 2016 (10.06.2016)

(25) Filing Language:

English

(26) Publication Language:

English

(30) Priority Data:

1510449.0 15 June 2015 (15.06.2015) GB

(71) Applicant: **OCLARO TECHNOLOGY LIMITED**
[GB/GB]; Caswell, Towcester Northamptonshire NN12
8EQ (GB).

(72) Inventor: **GRIFFIN, Robert**; 15 Nightingale Drive, Tow-
cester Northamptonshire NN12 6RA (GB).

(74) Agent: **TALBOT-PONSONBY, Daniel**; Marks & Clerk
LLP, Fletcher House (2nd Floor), Heatley Road, The Ox-
ford Science Park, Oxford Oxfordshire OX4 4GE (GB).

(81) Designated States (unless otherwise indicated, for every

kind of national protection available): AE, AG, AL, AM,
AO, AT, AU, AZ, BA, BB, BG, BH, BN, BR, BW, BY,
BZ, CA, CH, CL, CN, CO, CR, CU, CZ, DE, DK, DM,
DO, DZ, EC, EE, EG, ES, FI, GB, GD, GE, GH, GM, GT,
HN, HR, HU, ID, IL, IN, IR, IS, JP, KE, KG, KN, KP, KR,
KZ, LA, LC, LK, LR, LS, LU, LY, MA, MD, ME, MG,
MK, MN, MW, MX, MY, MZ, NA, NG, NI, NO, NZ, OM,
PA, PE, PG, PH, PL, PT, QA, RO, RS, RU, RW, SA, SC,
SD, SE, SG, SK, SL, SM, ST, SV, SY, TH, TJ, TM, TN,
TR, TT, TZ, UA, UG, US, UZ, VC, VN, ZA, ZM, ZW.

(84) Designated States (unless otherwise indicated, for every

kind of regional protection available): ARIPO (BW, GH,
GM, KE, LR, LS, MW, MZ, NA, RW, SD, SL, ST, SZ,
TZ, UG, ZM, ZW), Eurasian (AM, AZ, BY, KG, KZ, RU,
TJ, TM), European (AL, AT, BE, BG, CH, CY, CZ, DE,
DK, EE, ES, FI, FR, GB, GR, HR, HU, IE, IS, IT, LT, LU,
LV, MC, MK, MT, NL, NO, PL, PT, RO, RS, SE, SI, SK,
SM, TR), OAPI (BF, BJ, CF, CG, CI, CM, GA, GN, GQ,
GW, KM, ML, MR, NE, SN, TD, TG).

Published:

— with international search report (Art. 21(3))

(54) Title: CALIBRATION OF PLUGGABLE OPTICAL MODULE




Figure 1

(57) Abstract: An optical communications apparatus comprising a host (100) and an optical module (200) comprising a Mach-Zehnder modulator (202), MZM, wherein the optical module is removably connected to the host via a connection path, the optical communications apparatus comprising: a signal generator (101) at the host, configured to generate a plurality of calibration signals at a plurality of frequencies; a host interface (102) configured to transmit the calibration signals to the optical module via the connection path; a module interface (201) configured to receive the transmitted calibration signals; wherein the MZM is configured to use the calibration signals to modulate a laser light source (206) and biased to a point at which average output power is proportional to the output modulated signal; an optical detector configured to measure an average magnitude of an output of the MZM when each of the calibration signals is used to modulate the laser light source; one of a host calibration unit (103) and a module calibration unit (203), configured to determine a magnitude response of the connection path based on the measured average magnitudes and magnitudes of the respective calibration signals, and further configured to determine a pre-emphasis characteristic based on the magnitude response, the pre-emphasis characteristic for application to signals transmitted by the optical transmitter in use.

Calibration of pluggable optical module

Technical Field

5 The invention relates to a method and apparatus for the calibration of an optical transmitter. The optical transmitter may comprise a pluggable optical module and a host device to which the pluggable module connects and in particular, to a method and apparatus for the automated self-calibration of the module and host.

10 Background

Communications devices are increasingly using pluggable modules that plug into a host via a connector, which may be an optical connector. Some components of the communications device will be on the pluggable module, with the other components
15 being on the host, and communication between the components on the host and the components on the module will take place over the connector. Optics for the system are located on the pluggable module (as well as some electronic control circuitry), and the remainder of the device components (e.g. the electronic signal processing) may be located on the host.

20 Until recently, signalling over the optical connection was digital. However, as bandwidths increase in optical communications, complex modulation formats and Nyquist pulse shaping mean that the data transmitted can be treated as essentially analogue rather than digital. The electronics at the end points (i.e. at the host) are
25 predominantly digital. Therefore, digital-analogue convertors (DACs) are used to translate between the two domains. The DAC is generally located in the host.

The DAC receives a digital electrical input signal and outputs an analogue electrical signal. The output analogue signal is then used as an input to an optical modulator
30 (which has a further optical input for a laser carrier wave), which outputs the modulated optical signal for transmission on an external optical connection. The modulator is generally located in the pluggable module, which may have multiple independent modulators which are used to build up a final signal.

The analogue nature of the signalling can cause problems which are not faced by digital methods at a lower bitrate. Due to the characteristics of the transmission path, there will be differing levels of attenuation for different frequencies of the transmitted signal, i.e. different frequency components of the signal will experience different changes to magnitude and/or phase, which will cause distortion in the overall signal. The relationship between the change in magnitude of a transmitted sine wave and the frequency of the wave is called the magnitude response of the transmission path. The distortion experienced by an arbitrary transmitted signal can be calculated if the magnitude and phase response is known over the frequency range of the signal (e.g. the range of components determined by Fourier analysis). The inverse of this distortion can then be calculated, i.e. the waveform that must be transmitted to ensure that the desired waveform arrives at the receiver. This process is called pre-emphasis, since certain frequency components are emphasised in order to counteract the magnitude response.

There will naturally be some variance between devices, connectors, and the connection quality each time a connector is plugged in, which will cause distortion between the DAC and the modulator in the transmit circuit, and between the demodulator and the digital signal processor in the receiver circuit. This variable signal distortion can be partially compensated for in the receiver circuit following demodulation, provided the signal-to-noise ratio is high enough. However, distortion on the transmit circuit can make the signal much harder to distinguish from the noise introduced on the optical connection, which results in a significant loss of signal quality.

Summary

According to an aspect of the invention, there is provided an optical module for removable connection via a connection path to a host module of an optical telecommunications apparatus, the optical module comprising: a module interface for receiving from the host over the connection path a plurality of calibration signals each at a plurality of frequencies; a Mach-Zehnder modulator, MZM, configured to use the calibration signals to modulate a laser light source and biased to a point at which average output power is proportional to the output modulated signal; an optical detector configured to measure an average magnitude of an output of the MZM when each of the calibration signals is used to modulate the laser light source; a module calibration

unit configured to determine a magnitude response of the connection path based on the measured average magnitudes of the outputs and magnitudes of the respective calibration signals, and further configured to determine a pre-emphasis characteristic based on the magnitude response, the pre-emphasis characteristic for application to
5 signals transmitted by the telecommunications apparatus in use.

Optionally, the magnitudes of the calibration signals are predetermined and stored in a memory of the optical module.

10 Optionally, the interface is further configured to receive data identifying the magnitudes of the calibration signals from the host.

Optionally, the module calibration unit is further configured to estimate a phase response of the connection path based on the determined magnitude response, wherein the pre-emphasis characteristic is further determined based on the phase
15 response.

Optionally, the phase response is estimated as a Hilbert transform of the logarithm of the determined magnitude response.

20 Optionally, the module calibration unit is further configured to apply a bias voltage to the MZM to bias the MZM to the point at which average output power is proportional to the output peak-to-peak modulated signal.

25 Optionally, the biasing voltage biases the MZM at an operating point at a minimum or a maximum of an opto-electric transfer function for the MZM.

Optionally, the optical detector is a slow detector having a response time greater than a period of the plurality of calibration signals.

30 Optionally, the slow detector has a bandwidth in a range from 5 Hz to 100Hz.

Optionally, the optical detector is configured to detect an average optical power output of the MZM.

35

Optionally, the module calibration unit is configured to block an output optical signal of the optical module while modulating the laser light source with the calibration signals.

5 Optionally, the module calibration unit is further configured to apply the pre-emphasis characteristic to signals transmitted from the optical communications apparatus.

Optionally, the optical module comprises a plurality of MZMs, and wherein each MZM is configured to use the calibration signals to modulate a laser light source.

10 According to a further aspect of the invention, there is provided a host for removable connection via a connection path to an optical module of an optical telecommunications apparatus, the host comprising: a signal generator configured to generate a plurality of calibration signals at a plurality of frequencies; a host interface configured to transmit the calibration signals to the optical module over the connection path, and to receive in
15 response, data indicating an average magnitude of an output of a Mach-Zehnder modulator, MZM, when each of the calibration signals is used to modulate a laser light source and when the MZM is biased to a point at which average output power is proportional to the output modulated signal; a host calibration unit configured to determine a magnitude response of the connection path based on the received data
20 indicating the average magnitude and magnitudes of the respective calibration signals, and further configured to determine a pre-emphasis characteristic based on the magnitude response, the pre-emphasis characteristic for application to signals transmitted by the telecommunications apparatus in use.

25 Optionally, the host calibration unit is further configured to estimate a phase response of the connection path based on the determined magnitude response, wherein the pre-emphasis characteristic is further determined based on the phase response.

30 Optionally, the phase response is estimated as a Hilbert transform of the logarithm of the determined magnitude response.

Optionally, the data indicating an average magnitude of an output of the MZM comprises data indicating an average optical power of the output of the MZM.

Optionally, the MZM is biased to an operating point at a minimum or a maximum of an opto-electric transfer function for the modulator.

5 Optionally, the host calibration unit is further configured to apply the pre-emphasis characteristic to signals transmitted from the optical communications apparatus.

10 According to the invention in a further aspect, there is provided an optical communications apparatus comprising a host and an optical module comprising a Mach-Zehnder modulator, MZM, wherein the optical module is removably connected to the host via a connection path, the optical communications apparatus comprising: a signal generator at the host, configured to generate a plurality of calibration signals at a plurality of frequencies; a host interface configured to transmit the calibration signals to the optical module via the connection path; a module interface configured to receive the transmitted calibration signals; wherein the MZM is configured to use the calibration
15 signals to modulate a laser light source and biased to a point at which average output power is proportional to the output modulated signal; an optical detector configured to measure an average magnitude of an output of the MZM when each of the calibration signals is used to modulate the laser light source; one of a host calibration unit and a module calibration unit, configured to determine a magnitude response of the connection path based on the measured average magnitudes and magnitudes of the
20 respective calibration signals, and further configured to determine a pre-emphasis characteristic based on the magnitude response, the pre-emphasis characteristic for application to signals transmitted by the optical transmitter in use.

25 Brief Description of the Drawings

Figure 1 is a schematic diagram showing a host and a pluggable optical module;
Figure 2 is a graph showing measured and derived phase response;
Figure 3 is a schematic diagram of a pluggable optical module comprising multiple
30 modulators; and
Figure 4 is a flowchart showing a method of calibrating an optical module.

Detailed Description

The most accurate approach to determining the pre-emphasis required for an optical transmitter comprising a host and a pluggable module would be to calibrate the system when the module is plugged in to the host. It is desirable that this calibration solution can be performed automatically, and without the need for additional components. A method and apparatus for performing such a calibration is described below.

Figure 1 shows a schematic of a communications apparatus comprising a host board 100 and a pluggable optical module 200. The host board 100 comprises a DAC or other signal generator 101, a host interface 102 communicates with the pluggable optical module 200 over a connector 250, and a host calibration unit 103 which controls a calibration procedure.

The pluggable optical module 200 comprises a module interface 201 which communicates with the host 100 over the connector 250, a modulator 202 which controls the modulation of the output laser signals of the communications apparatus, and a module calibration unit 203 which controls a calibration procedure of the communications apparatus.

The host calibration unit 103 and module calibration unit 203 may be implemented as software running on a processor, as an application specific integrated circuit (ASIC), or by any other suitable means. As an alternative to separate module and host calibration units 103, 203, there may be a single calibration unit in either the optical module 200 or the host 100, with suitable connections provided to allow it to control components in the other part of the system.

In operation, the DAC 101 may produce analogue data signals that are passed to the modulator 202 via the host interface 102, the connector 250 and the module interface 201. The data is used by the modulator 202 to modulate an output of the laser 206 to produce a modulator output.

The modulator 202 may be an electro-optic (EO) modulator, i.e. one which makes use of an electro-optic substance which changes its optical properties in response to applied electric field. In exemplary pluggable optical modules, the modulator is a Mach-Zehnder modulator (MZM). The calibration process is therefore the calibration of

the electro-optic response of the modulator to suit the frequency and/or phase characteristics of the connector 250.

Generally, an exemplary calibration process comprises the following steps:

5

- Generating a number of calibration signals, each at one of a plurality of frequencies, at the host 100 and sending each calibration signal to the pluggable optical module 200 via the connector 250;
- Using each calibration signal to drive the modulator 202;
- 10 • Measuring a magnitude of the modulator output signal when driven by each calibration signal;
- Determining a magnitude response of the connection between the host 100 and the optical module 200 based on the measured modulator output magnitudes and the respective calibration signal magnitudes;
- 15 • Determining a required pre-emphasis from the determined magnitude response.

Going into the method in more detail, the calibration signals are generated by the DAC 101 and sent to the pluggable optical module 200 via the interface 102, connector 250, and interface 201.

20

In exemplary methods and apparatus, a MZM may be biased to a point at which average output power is proportional to the output modulated signal before being driven by the plurality of calibration signals. The MZM may be biased to a point at which average output power is proportional to the peak-to-peak output modulated signal. For example, the MZM may be biased to a minimum power transmission point or a maximum power transmission point. Biasing to a minimum or maximum transmission point may comprise biasing the modulator 202 such that the operating point is at a minimum or maximum (respectively) on the opto-electric transfer function for the modulator. For a MZM, the opto-electric transfer function is typically a raised cosine.

30

Biasing at a minimum or maximum transmission point on the transfer function ensures that the average output optical power is proportional to the output peak-to-peak modulated signal. Using this relationship, a slow photodetector may be used to determine the modulation magnitude of the modulator output for any frequency without

35

additional calibration. The average optical power of the modulator output is mathematically related to (and may be used to determine) the signal driving the modulator 202 after transmission from the DAC 101. This in turn allows the determination of the magnitude of the response of the transmission path from the DAC 101 to the modulator 202.

As used herein, the term “slow” or “low bandwidth” detector encompasses a detector that has a response time greater than a period of a signal to be detected and a bandwidth less than a frequency of the signal to be detected. The response time may be very much greater than the period of the signal to be detected and the detector bandwidth may be very much less than the frequency of the signal to be detected. Exemplary slow or low bandwidth detectors may have a response time greater than a plurality of periods of the signal to be detected and, specific exemplary detectors may have a response time in a range from 1×10^8 periods to 3×10^9 periods of the signal to be detected. That is, the electro-optic bandwidth of the signal to be detected may be in a range from 1×10^8 to 3×10^9 times greater than the bandwidth of the slow detector. Exemplary slow detectors may have a bandwidth of around 10 Hz and may be used to determine an average power of a signal having a bandwidth of around 20 GHz. Slow detectors may be configured to determine an average power of a signal at a frequency one or more orders of magnitude greater than the bandwidth of the detector. The slow detector may be a monitor photo-receiver. The slow detector may produce an output proportional to the time-average of the optical power incident on the detector. Exemplary slow detectors may be photodetectors and this exemplary detector is referred to in the remainder of this document.

The modulator 202 may comprise the detector, although in other arrangements the detector may be separate from the modulator 202 and may even be located off the optical module 200.

Using this relationship, the slow photodetector may be used to determine the average power of the modulator output. The average power of the modulator output is proportional to (and may be used to determine) the signal driving the modulator 202 after transmission from the DAC 101. This in turn allows the determination of the magnitude of the response of the transmission path from the DAC 101 to the modulator 202.

The calibration procedure will result in the modulator 202 generating output which could look similar to actual data if it were transmitted over the external optical connection. In order to ensure that no spurious signals are sent over the external
 5 optical connection, output from the pluggable optical module 200 may be blocked during calibration.

Once the magnitude has been measured at the modulator 202 for each of the frequencies to be tested, the magnitude response is calculated. In one embodiment,
 10 this is performed at the module calibration unit 203, which either obtains the original transmitted magnitudes from the host 100, or retrieves them from a memory (in the case where the magnitudes used are standardised). In an alternative embodiment, calculation of the magnitude response is performed at the host calibration unit 103, and the module calibration unit 203 provides the measured amplitudes at the modulator 202
 15 to the host calibration unit 103. In either case, the transmitted amplitudes from the DAC 101 are compared to the measured amplitudes at the modulator 202 for each of the transmitted frequencies, and this is used to construct a model for the magnitude response.

20 As an additional step, the calibration may involve using the magnitude response to estimate the phase response of the signal path (i.e. how the phase shift of a sine wave signal varies with frequency). The characteristics of the connection 250 may be approximated as a “minimum phase” system, i.e. a system where both the system and its inverse are causal and stable. The phase response may then be calculated by
 25 applying the Hilbert transform to the logarithm of the magnitude response, i.e.:

$$\varphi = kH(\log \mathbf{M})$$

Where φ is the phase response, $\mathbf{M}$ is the magnitude response, k is a constant (which depends on the units used for magnitude and phase) and $H()$ is the Hilbert transform
 30 operator defined as:

$$H\{x(t)\} = \frac{1}{\pi} \int_{-\infty}^{\infty} \frac{x(\tau)}{t - \tau} d\tau$$

As shown in Figure 2, this gives a good estimate of the phase response up to significant frequencies. This function may be calculated by a processor, ASIC or other means which is configured to perform the calculation or calculate a suitable approximation to the function above.

5

Once the magnitude response (and optionally the phase response) has been determined, pre-emphasis characteristics for the host transmitter can be derived from the magnitude response (and phase response, if it was calculated). The pre-emphasis may be substantially the inverse of the determined response. A pre-emphasis filter may be determined. The derivation of the pre-emphasis characteristics and the pre-emphasis filter can occur at either the host calibration unit 103 or the module calibration unit 203. The pre-emphasis filter is provided to the host calibration unit 103, which applies the filter to the DAC 101. The pre-emphasis filter is then applied to outgoing signals from the host 100, in order to correct for the properties of the signal path via the connector 250. The pre-emphasis filter will be a function of the frequency of the outgoing signal, i.e. the amount of pre-emphasis applied will vary depending on the frequency components of the outgoing signal.

The self-calibration procedure disclosed above may be controlled entirely by the host calibration unit 103 and/or module calibration unit 203 with no need for external intervention or input. The host calibration unit 103 and/or module calibration unit 203 may be configured to perform the calibration automatically, e.g. when the optical module 200 is first plugged in to the host 100, periodically, or during periods where no signals are being transmitted over the external optical link.

25

Where the pluggable optical module 200 comprises multiple modulators 202, the calibration may be performed separately for each modulator 202.

Figure 3 shows a quadrature phase shift keying (QPSK) MZM 300 in a single polarisation configuration. The single polarisation QPSK modulator comprises two MZMs 302a, 302b arranged in parallel such that a first modulator 302a is in phase (I) and a second modulator 302b is quadrature phase (Q). A polarisation (P) bias voltage may also be applied at the output of each of the I and Q modulators 302a, 302b. In order to implement the method disclosed above, the output photocurrent may be measured separately for each modulator at photodetectors 304a, 304b, and magnitude

35

response, phase response, and pre-emphasis may be calculated separately for the I modulator 302a and Q modulator 302b.

5 Figure 4 is a flowchart of an exemplary method for calibration of a pluggable optical module 200 and/or host 100.

10 In step S101, the host 100 generates a calibration signal at one of a plurality of frequencies, which is then transmitted S102 to the pluggable optical module 200 over the connection 101, 102, 250, 201 to be calibrated. The pluggable optical module 200 applies S103 the signal as an input to the modulator 202 and measures S104 a corresponding output of the modulator 202. Steps S101 to S104 are repeated for each of the plurality of calibration signals at the plurality of frequencies. In step S105, the magnitude response of the connection is determined based on magnitudes of the measured modulator outputs and magnitudes of the respective calibration signals. In step S106, the phase response of the connection is estimated based on the determined magnitude response. This may be done by taking the Hilbert transform of the logarithm of the magnitude response. Pre-emphasis is then applied to signals transmitted from the host in dependence upon the magnitude and/or phase response of the connection.

20 Returning again to Figure 1, the host 100 comprises a DAC/signal generator 101, an interface 102, and a host calibration unit 103. The signal generator 101 is configured to generate signalling, the interface 102 is configured to communicate with the pluggable optical module 200. The host calibration unit 103 is configured to cause the signal generator 101 to generate calibration signals at each of a plurality of frequencies and to cause the interface to transmit the signals to the optical module 200.

30 The optical module 200 comprises an interface 201, a modulator 202, and a calibration unit 203. The interface 201 is configured to communicate with the host 100. The modulator 202 is configured to modulate an output from a laser 206. The module calibration unit 203 may be configured, upon receipt of each calibration signal at the interface 201, to:

apply the calibration signal as an input to the modulator 202; and
measure an output of the modulator 202.

One of the host calibration unit 103 and the module calibration unit 203 may be further configured to determine magnitude response of the connection based on magnitudes of the measured outputs and magnitudes of the respective signals.

- 5 A computer program may be configured to provide any of the above described methods. The computer program may be provided on a computer readable medium. The computer program may be a computer program product. The product may comprise a non-transitory computer usable storage medium. The computer program product may have computer-readable program code embodied in the medium
- 10 configured to perform the method. The computer program product may be configured to cause at least one processor to perform some or all of the method.

Various methods and apparatus are described herein with reference to block diagrams or flowchart illustrations of computer-implemented methods, apparatus (systems and/or

15 devices) and/or computer program products. It is understood that a block of the block diagrams and/or flowchart illustrations, and combinations of blocks in the block diagrams and/or flowchart illustrations, can be implemented by computer program instructions that are performed by one or more computer circuits. These computer program instructions may be provided to a processor circuit of a general purpose

20 computer circuit, special purpose computer circuit, and/or other programmable data processing circuit to produce a machine, such that the instructions, which execute via the processor of the computer and/or other programmable data processing apparatus, transform and control transistors, values stored in memory locations, and other hardware components within such circuitry to implement the functions/acts specified in

25 the block diagrams and/or flowchart block or blocks, and thereby create means (functionality) and/or structure for implementing the functions/acts specified in the block diagrams and/or flowchart block(s).

Computer program instructions may also be stored in a computer-readable medium

30 that can direct a computer or other programmable data processing apparatus to function in a particular manner, such that the instructions stored in the computer-readable medium produce an article of manufacture including instructions which implement the functions/acts specified in the block diagrams and/or flowchart block or blocks.

A tangible, non-transitory computer-readable medium may include an electronic, magnetic, optical, electromagnetic, or semiconductor data storage system, apparatus, or device. More specific examples of the computer-readable medium would include the following: a portable computer diskette, a random access memory (RAM) circuit, a
5 read-only memory (ROM) circuit, an erasable programmable read-only memory (EPROM or Flash memory) circuit, a portable compact disc read-only memory (CD-ROM), and a portable digital video disc read-only memory (DVD/Blu-ray).

The computer program instructions may also be loaded onto a computer and/or other
10 programmable data processing apparatus to cause a series of operational steps to be performed on the computer and/or other programmable apparatus to produce a computer-implemented process such that the instructions which execute on the computer or other programmable apparatus provide steps for implementing the functions/acts specified in the block diagrams and/or flowchart block or blocks.

15 Accordingly, the invention may be embodied in hardware and/or in software (including firmware, resident software, micro-code, etc.) that runs on a processor, which may collectively be referred to as "circuitry," "a module" or variants thereof.

20 It should also be noted that in some alternate implementations, the functions/acts noted in the blocks may occur out of the order noted in the flowcharts. For example, two blocks shown in succession may in fact be executed substantially concurrently or the blocks may sometimes be executed in the reverse order, depending upon the functionality/acts involved. Moreover, the functionality of a given block of the
25 flowcharts and/or block diagrams may be separated into multiple blocks and/or the functionality of two or more blocks of the flowcharts and/or block diagrams may be at least partially integrated. Finally, other blocks may be added/inserted between the blocks that are illustrated.

30 It will be appreciated by the person of skill in the art that various modifications may be made to the above described embodiment without departing from the scope of the present invention.

CLAIMS:

1. An optical module for removable connection via a connection path to a host module of an optical telecommunications apparatus, the optical module comprising:
 - 5 a module interface for receiving from the host over the connection path a plurality of calibration signals each at a plurality of frequencies;
a Mach-Zehnder modulator, MZM, configured to use the calibration signals to modulate a laser light source and biased to a point at which average output power is proportional to the output modulated signal;
 - 10 an optical detector configured to measure an average magnitude of an output of the MZM when each of the calibration signals is used to modulate the laser light source;
a module calibration unit configured to determine a magnitude response of the connection path based on the measured average magnitudes of the outputs and magnitudes of the respective calibration signals, and further configured to determine a
15 pre-emphasis characteristic based on the magnitude response, the pre-emphasis characteristic for application to signals transmitted by the telecommunications apparatus in use.
- 20 2. An optical module according to claim 1, wherein the magnitudes of the calibration signals are predetermined and stored in a memory of the optical module.
3. An optical module according to claim 1, wherein the interface is further configured to receive data identifying the magnitudes of the calibration signals from the
25 host.
4. An optical module according to any preceding claim, wherein the module calibration unit is further configured to estimate a phase response of the connection path based on the determined magnitude response, wherein the pre-emphasis
30 characteristic is further determined based on the phase response.
5. An optical module according to 4, wherein the phase response is estimated as a Hilbert transform of the logarithm of the determined magnitude response.

6. An optical module according to any preceding claim, wherein the module calibration unit is further configured to apply a bias voltage to the MZM to bias the MZM to the point at which average output power is proportional to the output modulated signal.
- 5
7. An optical module according to claim 6, wherein the biasing voltage biases the MZM at an operating point at a minimum or a maximum of an opto-electric transfer function for the MZM.
- 10
8. An optical module according to any preceding claim, wherein the optical detector is a slow detector having a response time greater than a period of the plurality of calibration signals.
9. An optical module according to claim 8, wherein the slow detector has a bandwidth in a range from 5 Hz to 100Hz.
- 15
10. An optical module according to any preceding claim, wherein the optical detector is configured to detect an average optical power output of the MZM.
- 20
11. An optical module according to any preceding claim, wherein the module calibration unit is configured to block an output optical signal of the optical module while modulating the laser light source with the calibration signals.
- 25
12. An optical module according to any preceding claim, wherein the module calibration unit is further configured to apply the pre-emphasis characteristic to signals transmitted from the optical communications apparatus.
- 30
13. An optical module according to any preceding claim, comprising a plurality of MZMs, and wherein each MZM is configured to use the calibration signals to modulate a laser light source.
14. A host for removable connection via a connection path to an optical module of an optical telecommunications apparatus, the host comprising:
a signal generator configured to generate a plurality of calibration signals at a plurality of frequencies;
- 35

a host interface configured to transmit the calibration signals to the optical module over the connection path, and to receive in response, data indicating an average magnitude of an output of a Mach-Zehnder modulator, MZM, when each of the calibration signals is used to modulate a laser light source and when the MZM is biased to a point at which average output power is proportional to the output modulated signal;

5 a host calibration unit configured to determine a magnitude response of the connection path based on the received data indicating the average magnitude and magnitudes of the respective calibration signals, and further configured to determine a pre-emphasis characteristic based on the magnitude response, the pre-emphasis characteristic for application to signals transmitted by the telecommunications apparatus in use.

15 15. A host according to claim 14, wherein the host calibration unit is further configured to estimate a phase response of the connection path based on the determined magnitude response, wherein the pre-emphasis characteristic is further determined based on the phase response.

20 16. A host according to 15, wherein the phase response is estimated as a Hilbert transform of the logarithm of the determined magnitude response.

17. A host according to claim 14, wherein the data indicating an average magnitude of an output of the MZM comprises data indicating an average optical power of the output of the MZM.

25 18. A host according to claim 17, wherein the MZM is biased to an operating point at a minimum or a maximum of an opto-electric transfer function for the modulator.

30 19. A host according to any of claims 14 to 18, wherein the host calibration unit is further configured to apply the pre-emphasis characteristic to signals transmitted from the optical communications apparatus.

35 20. An optical communications apparatus comprising a host and an optical module comprising a Mach-Zehnder modulator, MZM, wherein the optical module is removably connected to the host via a connection path, the optical communications apparatus comprising:

a signal generator at the host, configured to generate a plurality of calibration signals at a plurality of frequencies;

a host interface configured to transmit the calibration signals to the optical module via the connection path;

5 a module interface configured to receive the transmitted calibration signals;

wherein the MZM is configured to use the calibration signals to modulate a laser light source and biased to a point at which average output power is proportional to the output modulated signal;

10 an optical detector configured to measure an average magnitude of an output of the MZM when each of the calibration signals is used to modulate the laser light source;

one of a host calibration unit and a module calibration unit, configured to determine a magnitude response of the connection path based on the measured average magnitudes and magnitudes of the respective calibration signals, and further
15 configured to determine a pre-emphasis characteristic based on the magnitude response, the pre-emphasis characteristic for application to signals transmitted by the optical transmitter in use.

1/2




Figure 1




Figure 2

2/2




Figure 3

5




Figure 4

INTERNATIONAL SEARCH REPORT

International application No

PCT/GB2016/051724

A. CLASSIFICATION OF SUBJECT MATTER

INV. H04B10/50 G02F1/225 H04B10/588
ADD.

According to International Patent Classification (IPC) or to both national classification and IPC

B. FIELDS SEARCHED

Minimum documentation searched (classification system followed by classification symbols)

H04B G02F

Documentation searched other than minimum documentation to the extent that such documents are included in the fields searched

Electronic data base consulted during the international search (name of data base and, where practicable, search terms used)

EPO-Internal, WPI Data

C. DOCUMENTS CONSIDERED TO BE RELEVANT

Category*	Citation of document, with indication, where appropriate, of the relevant passages	Relevant to claim No.
A	WO 2005/125061 A1 (BAE SYSTEMS PLC [GB]; WOOD JOHN MICHAEL [GB]) 29 December 2005 (2005-12-29) page 1, line 17 - line 21 page 12, line 5 - page 13, line 29; figures 2,3 -----	1-20
A	WO 2012/163419 A1 (ERICSSON TELEFON AB L M [SE]; MAGRI ROBERTO [IT]; DEHO ALBERTO [IT]) 6 December 2012 (2012-12-06) page 7, line 8 - page 9, line 22; figures 1,15 page 10, line 14 - page 11, line 7 -----	1-20
A	US 2011/280582 A1 (PIEHLER DAVID [US]) 17 November 2011 (2011-11-17) page 1, paragraph 6 - paragraph 8 page 8, paragraph 67; figure 7 -----	1-20



Further documents are listed in the continuation of Box C.



See patent family annex.

* Special categories of cited documents :

"A" document defining the general state of the art which is not considered to be of particular relevance

"E" earlier application or patent but published on or after the international filing date

"L" document which may throw doubts on priority claim(s) or which is cited to establish the publication date of another citation or other special reason (as specified)

"O" document referring to an oral disclosure, use, exhibition or other means

"P" document published prior to the international filing date but later than the priority date claimed

"T" later document published after the international filing date or priority date and not in conflict with the application but cited to understand the principle or theory underlying the invention

"X" document of particular relevance; the claimed invention cannot be considered novel or cannot be considered to involve an inventive step when the document is taken alone

"Y" document of particular relevance; the claimed invention cannot be considered to involve an inventive step when the document is combined with one or more other such documents, such combination being obvious to a person skilled in the art

"&" document member of the same patent family

Date of the actual completion of the international search

22 August 2016

Date of mailing of the international search report

21/09/2016

Name and mailing address of the ISA/

European Patent Office, P.B. 5818 Patentlaan 2
NL - 2280 HV Rijswijk
Tel. (+31-70) 340-2040,
Fax: (+31-70) 340-3016

Authorized officer

Koch, Bernhard

INTERNATIONAL SEARCH REPORT

Information on patent family members

International application No

PCT/GB2016/051724

Patent document cited in search report	Publication date	Patent family member(s)	Publication date
WO 2005125061 A1	29-12-2005	AT 388538 T DE 602005005194 T2 EP 1756981 A1 ES 2300021 T3 US 2007241805 A1 WO 2005125061 A1	15-03-2008 12-03-2009 28-02-2007 01-06-2008 18-10-2007 29-12-2005
WO 2012163419 A1	06-12-2012	EP 2715952 A1 US 2014169802 A1 WO 2012163419 A1	09-04-2014 19-06-2014 06-12-2012
US 2011280582 A1	17-11-2011	TW 201203889 A US 2011280582 A1 US 2014376927 A1 WO 2011146363 A2	16-01-2012 17-11-2011 25-12-2014 24-11-2011