



US008432767B2

(12) **United States Patent**
Gillingham et al.

(10) **Patent No.:** **US 8,432,767 B2**
(45) **Date of Patent:** **Apr. 30, 2013**

(54) **CLOCK MODE DETERMINATION IN A MEMORY SYSTEM**

5,557,221 A 9/1996 Taguchi et al.
5,629,897 A 5/1997 Iwamoto et al.
5,666,322 A 9/1997 Conkle

(75) Inventors: **Peter B. Gillingham**, Ottawa (CA);
Graham Allan, Stittsville (CA)

(Continued)

(73) Assignee: **MOSAID Technologies Incorporated**,
Ottawa, Ontario (CA)

EP 0818734 1/1998
JP 06103762 4/1994

FOREIGN PATENT DOCUMENTS

(Continued)

(*) Notice: Subject to any disclaimer, the term of this patent is extended or adjusted under 35 U.S.C. 154(b) by 204 days.

OTHER PUBLICATIONS

(21) Appl. No.: **13/006,005**

Hara, T. et al., "A 146mm² 8Gb NAND Flash Memory with 70nm CMOS Technology", ISSCC Session 2 Non-Volatile Memory 2.1, IEEE International Solid-State Circuits Conference, Feb. 2005, pp. 44, 45 and 584.

(22) Filed: **Jan. 13, 2011**

(Continued)

(65) **Prior Publication Data**

US 2011/0110165 A1 May 12, 2011

Related U.S. Application Data

(62) Division of application No. 12/032,249, filed on Feb. 15, 2008, now Pat. No. 7,885, 140.

(60) Provisional application No. 60/902,003, filed on Feb. 16, 2007.

(51) **Int. Cl.**
G11C 8/00 (2006.01)

(52) **U.S. Cl.**
USPC **365/233.1**; 365/233.11

(58) **Field of Classification Search** 365/233.1, 365/233.11, 233.12, 230.03
See application file for complete search history.

(56) **References Cited**


U.S. PATENT DOCUMENTS

5,093,807 A 3/1992 Hashimoto et al.
5,204,669 A 4/1993 Dorfe et al.
5,243,703 A 9/1993 Farmwald et al.

(57) **ABSTRACT**

A clock mode configuration circuit for a memory device is described. A memory system includes any number of memory devices serially connected to each other, where each memory device receives a clock signal. The clock signal can be provided either in parallel to all the memory devices or serially from memory device to memory device through a common clock input. The clock mode configuration circuit in each memory device is set to a parallel mode for receiving the parallel clock signal, and to a serial mode for receiving a source synchronous clock signal from a prior memory device. Depending on the set operating mode, the data input circuits will be configured for the corresponding data signal format, and the corresponding clock input circuits will be either enabled or disabled. The parallel mode and the serial mode is set by sensing a voltage level of a reference voltage provided to each memory device.

35 Claims, 15 Drawing Sheets



U.S. PATENT DOCUMENTS

5,729,683	A	3/1998	Le et al.	
5,773,968	A	6/1998	Kondo et al.	
5,778,419	A	7/1998	Hanson et al.	
5,802,399	A	9/1998	Yumoto et al.	
5,818,783	A	10/1998	Kim	
5,859,809	A	1/1999	Kim	
5,917,759	A	6/1999	Akashi	
5,949,252	A	9/1999	Taguchi	
5,982,309	A	11/1999	Xi et al.	
6,002,638	A	12/1999	John	
6,026,465	A	2/2000	Mills et al.	
6,088,254	A	7/2000	Kermani	
6,104,225	A	8/2000	Taguchi et al.	
6,111,807	A	8/2000	Ooishi	
6,125,078	A	9/2000	Ooishi et al.	
6,191,987	B1	2/2001	Ogawa	
6,212,591	B1	4/2001	Kaplinsky	
6,236,249	B1	5/2001	Choi et al.	
6,335,901	B1	1/2002	Morita et al.	
6,337,832	B1	1/2002	Ooishi et al.	
6,438,060	B1	8/2002	Li et al.	
6,442,644	B1	8/2002	Gustavson et al.	
6,480,946	B1	11/2002	Tomishima et al.	
6,567,904	B1	5/2003	Khandekar et al.	
6,668,292	B2	12/2003	Meyer et al.	
6,696,862	B2	2/2004	Choi et al.	
6,732,224	B2	5/2004	Hashimoto et al.	
6,795,906	B2	9/2004	Matsuda	
6,937,680	B2	8/2005	Fong et al.	
6,965,964	B2	11/2005	Lee et al.	
7,031,221	B2	4/2006	Mooney et al.	
7,130,958	B2	10/2006	Chou et al.	
7,139,308	B2	11/2006	Doblar et al.	
7,296,173	B2	11/2007	Nambu et al.	
2002/0075989	A1	6/2002	Joo	
2003/0009713	A1	1/2003	Endou	
2003/0147298	A1 *	8/2003	Ooishi et al.	365/233
2004/0148482	A1	7/2004	Grundy et al.	
2004/0186956	A1	9/2004	Perego et al.	
2005/0146980	A1	7/2005	Mooney et al.	
2006/0067123	A1	3/2006	Jigour et al.	
2006/0250883	A1 *	11/2006	Szczypinski	365/233
2006/0268624	A1	11/2006	Jang	
2006/0268642	A1	11/2006	Chen et al.	
2007/0076479	A1	4/2007	Kim et al.	
2007/0076502	A1	4/2007	Pyeon et al.	
2007/0109833	A1	5/2007	Pyeon et al.	
2007/0233903	A1	10/2007	Pyeon	
2007/0233917	A1	10/2007	Pyeon et al.	
2007/0234071	A1	10/2007	Pyeon	
2008/0016269	A1	1/2008	Chow et al.	
2008/0049505	A1	2/2008	Kim et al.	
2008/0140899	A1	6/2008	Oh et al.	
2008/0155179	A1	6/2008	Pyeon et al.	
2008/0181214	A1	7/2008	Pyeon et al.	
2008/0192649	A1	8/2008	Pyeon et al.	

FOREIGN PATENT DOCUMENTS

JP	06104725	4/1994
JP	08147967	6/1996
JP	09007395	1/1997
JP	09063277	3/1997
JP	09091047	4/1997
JP	10020974	1/1998
JP	11007768	1/1999
JP	11066862	3/1999
JP	2000031807	1/2000
JP	2000067577	3/2000
JP	2000090696	3/2000
JP	2000148656	5/2000
JP	2000149554	5/2000
JP	2000163965	6/2000
JP	2000215689	8/2000
JP	2001044825	2/2001
JP	2001067870	3/2001
JP	2002007200	1/2002

JP	2002271189	9/2002
JP	2003036674	2/2003
JP	2003085973	3/2003
JP	2003233998	8/2003
JP	2004287691	10/2004
WO	02099810	12/2002

OTHER PUBLICATIONS

Byeon, D. et al., "An 8Gb Multi-Level NAND Flash Memory with 63nm STI CMOS Process Technology", ISSCC Session 2 Non-Volatile Memory 2.2, IEEE International Solid-State Circuits Conference, Feb. 2005, pp. 46 and 47.

Tanzawa, T. et al., "Circuit Techniques for a 1.8-V-Only NAND Flash Memory", IEEE Journal of Solid-State Circuits, vol. 37, No. 1, Jan. 2002, pp. 84-89.

Imamiya, K. et al., "A 125-mm² 1-Gb NAND Flash Memory with 10-MByte/s Program Speed", IEEE Journal of Solid-State Circuits, vol. 37, No. 11, Nov. 2002, pp. 1493-1501.

Lee, J. et al., "High-Performance 1-Gb NAND Flash Memory with 0.12- μ m Technology", IEEE Journal of Solid-State Circuits, vol. 37, No. 11, Nov. 2002, pp. 1502-1509.

Cho, T. et al., "A Dual-Mode NAND Flash Memory: 1-Gb Multilevel and High-Performance 512-Mb Single-Level Modes", IEEE Journal of Solid-State Circuits, vol. 36, No. 11, Nov. 2001, pp. 1700-1706.

Hara, T. et al., "A 146-mm² 8-Gb Multi-Level NAND Flash Memory With 70-nm CMOS Technology", IEEE Journal of Solid State Circuits, Jan. 2006, vol. 41, No. 1, pp. 161-169.

Lee, S. et al., "A 3.3V 4Gb Four-Level NAND Flash Memory with 90nm CMOS Technology", ISSCC 2004/Session 2Non-Volatile Memory/2.7, IEEE International Solid-State Circuits Conference, Feb. 15-19, 2004, Digest of Technical Papers, vol. 1, XP010722148, ISBN: 0-7803-8267-6.

Takeuchi, K. et al., "A 56nm CMOS 99mm² 8Gb Multi-level NAND Flash Memory with 10MB/s Program Throughput", Solid-State Circuits, 2006 IEEE International Conference Digest of Technical Papers, Session 7, Feb. 6-9, 2006, pp. 507-516, ISBN: 1-4244-0079-1.

Samsung Electronics Co. Ltd., "256Mx8 Bit / 128 Mx16 Bit / 512Mx8 Bit NAND Flash Memory", K9K4G08U1M, May 6, 2005, pp. 1-41.

Samsung Electronics Co. Ltd., "1Gx8 Bit / 2Gx8 Bit NAND Flash Memory", K9F8G08UXM, Mar. 31, 2007, pp. 1-54.

Samsung Electronics Co. Ltd., "512Mx8 Bit / 1Gx8 Bit NAND Flash Memory", K9XXG08UXA, May 7, 2006, pp. 1-43.

Samsung Electronics Co. Ltd., "1Gx8 Bit / 2Gx8 Bit / 4Gx8 Bit NAND Flash Memory", K9XXG08UXA, Jul. 18, 2006, pp. 1-50.

Lee J. et al., "A 90-nm CMOS 1.8-V 2Gb NAND Flash Memory for Mass Storage Applications", IEEE Journal of Solid-State Circuits, vol. 38, No. 11, Nov. 2003, pp. 1934-1942.

Samsung Electronics Co. Ltd., "2Gx8 Bit NAND Flash Memory", K9GAG08U0M, Apr. 12, 2006, pp. 1-48.

Toshiba, "16 GBIT (2Gx8 Bit) CMOS NAND E2PROM (Multi-Level-Cell)", TC58NVG4D1D1TG00, Nov. 9, 2006.

Toshiba, "2GBIT (256Mx8 Bits) CMOS NAND E2PROM", TH58NVG1S3AFT05, May 19, 2003, pp. 1-32.

"IEEE Standard for High-Bandwidth Memory Interface Based on Scalable Coherent Interface (SCI) Signaling Technology (RamLink)", IEEE Std. 1596.4-1996, The Institute of Electrical Electronics Engineers, Inc., pp. i-91, (Mar. 1996).

Diamond, S.L., "Synclink: High: High-speed DRAM for the Future", Micro Standards, IEEE Micro, pp. 74-75, Dec. 1996.

Atmel, "8-megabit 2.5-volt Only or 2.7-volt Only DataFlash[®]", Technical Specification, Atmel, Rev. 2225H-DFLSH, Oct. 2004.

"The I2C-Bus Specification," Version 2.1, Philips Semiconductors, Jan. 2000, 46 pages.

"16 Mbit SPI Serial Flash," Preliminary Specification, Silicon Storage Technology Inc., Apr. 2005, 28 pages.

"HyperTransport TMI/O Link Specification", Revision 3.00a, Document No. HTC20051222-0046-0017, 2001-2006, Hypertransport Technology Consortium, Nov. 22, 2006, pp. 1-443.

Integrated Device Technology, Inc., "2.5V Differential 1:5 Clock Buffer Terabuffer[™]", IDT5T915, Feb. 2003, pp. 1-19.

International Search Report dated Jun. 6, 2008 from International Application PCT/CA2008/000292, p. 2.

U.S. Appl. No. 12/032,249, Notice of Allowance dated Sep. 28, 2010.

* cited by examiner




Fig. 1 (Prior Art)




Fig. 2A




Fig. 2B




Fig. 3A




Fig. 3B




Fig. 3C




Fig. 3D




Fig. 4




Fig. 5




Fig. 6




Fig. 7




Fig. 8A




Fig. 8B




Fig. 9




Fig. 10




Fig. 11

1

CLOCK MODE DETERMINATION IN A MEMORY SYSTEM

CROSS REFERENCE TO RELATED APPLICATIONS

This application is a Divisional application of U.S. patent application Ser. No. 12/032,249 filed on Feb. 15, 2008, which claims the benefit of priority of U.S. Provisional Patent Application Ser. No. 60/902,003 filed on Feb. 16, 2007, the contents of which are incorporated herein by reference in their entirety.

BACKGROUND

Flash memory is a commonly used type of non-volatile memory in widespread use as mass storage for consumer electronics, such as digital cameras and portable digital music players for example. The density of a presently available Flash memory component, consisting of 2 stacked dies, can be up to 32 Gbits (4 GB), which is suitable for use in popular USB Flash drives, since the size of one Flash component is small.

The advent of 8 mega pixel digital cameras and portable digital entertainment devices with music and video capabilities has spurred demand for ultra-high capacities to store the large amounts of data, which cannot be met by the single Flash memory device. Therefore, multiple Flash memory devices are combined together into a memory system to effectively increase the available storage capacity. For example, Flash storage densities of 20 GB may be required for such applications.

FIG. 1 is a block diagram of a prior art flash memory system 10 integrated with a host system 12. Flash memory system 10 includes a memory controller 14 in communication with host system 12, and multiple non-volatile memory devices 16. The host system 12 includes a processing device such as a microcontroller, microprocessor, or a computer system. The Flash memory system 10 of FIG. 1 is configured to include one channel 18, where memory devices 16 are connected in parallel to channel 18. Those skilled in the art will understand that the memory system 10 can have more or less than four memory devices connected to it.

Channel 18 includes a set of common buses, which include data and control lines that are connected to all its corresponding memory devices. Each memory device is enabled/disabled with respective chip select signals CE#1, CE#2, CE#3 and CE#4, provided by memory controller 14. The “#” indicates that the signal is an active low logic level signal. The memory controller 14 is responsible for issuing commands and data, via the channel 18, to a selected memory device based on the operation of the host system 12. Data read from the memory devices is transferred via the channel 18 back to the memory controller 14 and host system 12. Operation of flash memory system 10 can be asynchronous or synchronous. FIG. 1 illustrates an example of a synchronous system that uses a clock CLK, which is provided in parallel to each memory device 16. Flash memory system 10 is generally referred to as a multi-drop configuration, in which the memory devices 16 are connected in parallel with respect to channel 18.

In Flash memory system 10, non-volatile memory devices 16 may be (but not necessarily) substantially identical to each other, and are typically implemented as NAND flash memory devices. Those skilled in the art will understand that flash memory is organized into banks, and each bank is organized

2

into blocks to facilitate block erasure. Most commercially available NAND flash memory devices are configured to have two banks of memory.

There are specific issues that will adversely impact performance of the system. The configuration of Flash memory system 10 imposes physical performance limitations. With the large number of parallel signals extending across the system, the signal integrity of the signals they carry will be degraded by crosstalk, signal skew, and simultaneous switching noise (SSN). Power consumption in such a configuration becomes an issue as each signal track between the flash controller and flash memory devices is frequently charged and discharged for signaling. With increasing system clock frequencies, the power consumption will increase.

There is also a practical limit to the number of memory devices which can be connected in parallel to the channel since the drive capability of a single memory device is small relative to the loading of the long signal tracks. Furthermore, as the number of memory devices increase, more chip enable signals (CE#) are required, and the clock signal CLK will need to be routed to the additional memory devices. Clock performance issues due to extensive clock distribution are well known in the art, which would need to be addressed. Therefore, in order to accommodate a memory system having a large number of memory devices, either a controller having more channels must be used, or and/or the system will need to be clocked at a lower frequency. A controller configured to have multiple channels and additional chip enable signals increases the cost of the memory system. Otherwise, the memory system is limited to a small number of memory devices.

Therefore, it is desirable to provide a memory system device architecture capable of high speed operation while overcoming issues associated with the prior art memory system having memory devices connected in parallel to each other.

BRIEF DESCRIPTION OF THE DRAWINGS

Embodiments of the clock mode circuits will now be described, by way of example only, with reference to the attached Figures, wherein:

FIG. 1 is a block diagram of a prior art Flash memory system;

FIG. 2A is a general block diagram of a serial memory system receiving a clock signal in parallel;

FIG. 2B is a general block diagram of a serial memory system receiving a clock signal serially;

FIG. 3A is a block diagram of a serial memory system receiving clock signals serially, according to one embodiment;

FIG. 3B is a timing diagram showing the operation of the memory system of FIG. 3A;

FIG. 3C is a block diagram of a serial memory system receiving clock signals in parallel, according to another embodiment;

FIG. 3D is a timing diagram showing the operation of the memory system of FIG. 3C;

FIG. 4 is a block diagram of a memory device having a native core and a serial input/output interface suitable for use in the serial memory systems of FIGS. 3A and B;

FIG. 5 is a block diagram illustrating a configurable input circuit embodiment usable in the serial memory systems of FIGS. 3A and 3C;

FIG. 6 is a circuit schematic embodiment of the mode setter of FIG. 5;

3

FIG. 7 is a sequence diagram illustrating the operation of the mode setter of FIG. 6;

FIG. 8A is a schematic embodiment of the configurable input circuit shown in FIG. 5;

FIG. 8B is a timing diagram showing the operation of the circuits of FIG. 8A;

FIG. 9 is a block diagram of an embodiment of a dynamically configurable serial memory system;

FIG. 10 is a schematic embodiment of an alternate clock switch circuit embodiment used in the memory devices shown in FIG. 9; and,

FIG. 11 is a flow chart of a method for configuring an clock operating mode of a memory device.

DETAILED DESCRIPTION

In a first aspect, there is provided a semiconductor device for receiving a clock and input data. The semiconductor device includes a configurable input circuit operable in a first mode for receiving coincident edges of the clock and the input data, and for providing shifted clock edges positioned within a data valid window for sampling the input data. The configurable input circuit is operable in a second mode for receiving non-coincident edges of the clock and the input data for sampling the input data. In an embodiment of the present aspect, the semiconductor device further includes an input pin for providing a voltage to the configurable input circuit for setting the first mode and the second mode. The input pin includes a reference voltage pin set to one of low and high power supply levels for setting the second mode, and a reference voltage level for setting the first mode. The reference voltage level can be between the low and high power supply levels, and is used by the configurable input circuit to sense logic levels of the input data.

In further embodiments of the present aspect, the configurable input circuit includes a single ended input buffer and a differential input buffer. The single ended input buffer is coupled to a data input pin for receiving the input data, and is enabled in the second mode and disabled in the first mode. The differential input buffer is coupled to the data input pin for receiving the input data, and is enabled in the first mode for sensing logic levels of the input data relative to the voltage. Alternately, the configurable input circuit includes a clock synthesizer for providing the shifted clock edges in response to the clock. The clock synthesizer includes one of a delay locked loop and a phase locked loop, or the clock synthesizer can be disabled in the second mode.

In a second aspect, the present invention provides a configurable memory device. The configurable memory device includes a mode setter, a clock switch, and a configurable data input/output buffer. The mode setter senses a voltage level of a reference voltage input port and provides a mode selection signal corresponding to the sensed voltage level. The clock switch is coupled to a clock input port for receiving at least one of parallel complementary clock signals and serial complementary clock signals. The clock switch generates complementary internal clock signals corresponding to the parallel complementary clock signals in response to a first logic state of the mode selection signal, or the serial complementary clock signals in response to a second logic state of the mode selection signal. The configurable data input/output buffer is coupled to a data input port and the reference voltage input port for sensing data received on the data input port relative to the voltage level in response to the second logic state of the mode selection signal. In an embodiment of the present aspect, the mode setter includes a sense circuit and a latch. The sense circuit compares the voltage level to a preset

4

reference voltage, and provides a sense output corresponding to the voltage level relative to the preset reference voltage. The latch latches the sense output and provides the mode selection signal having one of the first logic state and the second logic state.

In the current embodiment, the sense circuit includes a reference voltage circuit and a comparator. The reference voltage circuit provides the preset reference voltage and the comparator provides the sense output in response to the voltage level and the preset reference voltage. The reference voltage circuit includes a voltage divider coupled between VDD and VSS, and a power shut-off device for cutting off current through the voltage divider after a predetermined period of time. The mode setter includes a delay circuit for turning off the power shut-off device after the predetermined period of time when a reset signal is driven to an inactive logic state. The delay circuit includes an n-bit counter enabled when the reset signal is at the inactive logic state for driving a most significant bit to an active logic state. The most significant bit is driven to the active logic state when 2^n active edges of a clock signal are counted, where n is an integer value greater than 1, such that the delay circuit generates a disable signal corresponding to the most significant bit being at the active logic state for turning off the power shut-off device.

In yet another embodiment of the present aspect, the clock switch includes a clock input buffer, a clock generator and a clock output buffer. The clock input buffer provides the buffered parallel complementary clock signals in response to the first logic state of the mode selection signal, and provides a sensed clock signal corresponding to the serial complementary clock signals in response to the second logic state of the mode selection signal. The clock generator generates the complementary internal clock signals in response to either the buffered parallel complementary clock signals when the mode selection signal is at the first logic state, or the sensed clock signal when the mode selection signal is at the second logic state. The clock output buffer drives the complementary internal clock signals through clock output ports when the mode selection signal is at the second logic state. The clock input buffer includes a comparator and a pair of buffers. The comparator is enabled in response to the mode selection signal at the second logic state for providing the sensed clock signal in response to the serial complementary clock signals. The pair of buffers are enabled in response to the mode selection signal at the second logic state for providing the buffered parallel complementary clock signals in response to the parallel complementary clock signals. The clock output buffer includes a pair of drivers enabled in response to the mode selection signal at the second logic state for driving the complementary internal clock signals through the clock output ports.

In a further embodiment, the clock generator includes a clock synthesizer and a switch circuit. The clock synthesizer provides a first clock signal and a second clock signal shifted 180 degrees relative to the first clock signal, in response to the sensed clock signal. The switch circuit passes the first clock signal and the second clock signal as the complementary internal clock signals when the mode selection circuit is at the second logic state. The switch circuit passes the buffered parallel complementary clock signals as the complementary internal clock signals when the mode selection circuit is at the second logic state. The clock synthesizer can be one of a phase locked loop and a delay locked loop. The clock synthesizer provides a third clock signal and a fourth clock signal, where the third clock signal is shifted 90 degrees relative to the first clock signal and the fourth clock signal is shifted 180 degrees relative to the third clock signal. The clock generator

5

further includes a phase selector circuit for selectively passing either the complementary internal clock signals or the third and fourth clock signals to the clock output buffer.

According to another embodiment, the configurable data input/output buffer includes a data input buffer for selectively providing input data corresponding to either sensed data resulting from a comparison between the data and the voltage level, or buffered data corresponding to the data, in response to the mode selection signal. The data input buffer includes a comparator and a buffer. The comparator is enabled when the mode selection signal is at the second logic state for providing the input data in response to the voltage level and a voltage of the data. The buffer is enabled when the mode selection signal is at the first logic state for providing the buffered data. The configurable data input/output buffer can further include a data switch for selectively passing one of the input data and local read data to a data output buffer.

In a third aspect, the present invention provides a method for configuring a clock operating mode of a memory device that receives a reference voltage for sensing input data. The method includes setting the reference voltage level; comparing the reference voltage to a preset reference voltage for generating a mode selection signal corresponding to the reference voltage relative to the preset reference voltage; and configuring a clock input buffer to receive either parallel complementary clock signals or serial complementary clock signals in response to the mode selection signal. In embodiments of the present aspect, the step of comparing includes latching the mode selection signal, and the step of comparing includes disabling a sense circuit used for comparing the reference voltage to the preset reference voltage after a predetermined delay. The predetermined delay is determined by counting 2^n clock edges after deasserting a reset signal, and the preset reference voltage floats to a voltage supply while the reset signal is asserted.

In yet another embodiment of the present aspect, the step of configuring includes enabling a comparator receiving serial complementary clock signals and disabling buffers receiving parallel complementary clock signals in response to a first logic state of the mode selection signal. The step of enabling includes enabling a clock synthesizer for generating a first clock signal and a second clock signal shifted 180 degrees relative to the first clock signal, in response to a sensed clock signal from the comparator. The step of enabling a clock synthesizer includes providing as internal clock signals one of the first clock signal and the second clock signal and buffered parallel complementary clock signals corresponding to the parallel complementary clock signals, in response to the mode selection signal. The clock synthesizer generates a third clock signal and a fourth clock signal, where the third clock signal is shifted 90 degrees relative to the first clock signal and the fourth clock signal is shifted 180 degrees relative to the third clock signal. The step of configuring includes selectively passing one of the internal clock signals and the third and fourth clock signals in response to a phase selection signal.

In a fourth aspect, the present invention provides a memory system configurable to operate with one of parallel clock signals and serial clock signals. The memory system includes a memory controller and at least one serially connected memory device. The at least one memory device has clock input ports, a reference voltage input port, a mode setter, and a clock switch circuit. The clock input ports receive one of the parallel clock signals and the serial clock signals. The reference voltage input port receives a reference voltage set to one of a predetermined voltage level and a voltage supply level. The mode setter compares the reference voltage to the pre-

6

terminated voltage level, and generates a mode selection signal corresponding to a result of the comparison. The clock switch circuit is coupled to the clock input ports for generating complementary internal clock signals corresponding to one of the parallel clock signals and the serial complementary clock signals, in response to the mode selection signal.

A memory system that resolves many performance issues of the Flash memory system **10** of FIG. **1** is a serially connected memory system in which the memory devices are serially connected with each other and the memory controller in a ring topology configuration. FIGS. **2A** and **2B** are block diagrams illustrating the conceptual nature of a serial memory system. FIG. **2A** is a block diagram of a serial memory system receiving a parallel clock signal while FIG. **2B** is a block diagram of the same serial memory system of FIG. **2A** receiving a source synchronous clock signal.

In FIG. **2A**, the serial memory system **20** includes a memory controller **22** having at least one serial channel output port Sout and a serial channel input port Sin, and memory devices **24**, **26**, **28** and **30** that are connected in series. Input and output ports correspond to physical pins or connections interfacing the memory device to the system it is integrated with. In one embodiment, the memory devices can be flash memory devices. Alternately, the memory devices can be DRAM, SRAM or any other type of memory device provided it has a serial input/output interface compatible with a specific command structure, for executing commands or for passing through commands and data to the next memory device. The current example of FIG. **2A** includes four memory devices, but alternate embodiments can include a single memory device, or any number of memory devices. Accordingly, if memory device **24** is the first device of serial memory system **100** as it is connected to Sout, then memory device **30** is the Nth or last device as it is connected to Sin, where N is an integer number greater than zero. Memory devices **26** to **28** are then intervening serially connected memory devices between the first and last memory devices. Each memory device can assume a distinct identification (ID) number, or device address (DA) upon power up initialization of the system, so that they are individually addressable. Commonly owned U.S. patent application Ser. No. 11/622,828 titled "APPARATUS AND METHOD FOR PRODUCING IDS FOR INTERCONNECTED DEVICES OF MIXED TYPE", U.S. patent application Ser. No. 11/750,649 titled "APPARATUS AND METHOD FOR ESTABLISHING DEVICE IDENTIFIERS FOR SERIALY INTERCONNECTED DEVICES", U.S. patent application Ser. No. 11/692,452 titled "APPARATUS AND METHOD FOR PRODUCING DEVICE IDENTIFIERS FOR SERIALY INTERCONNECTED DEVICES OF MIXED TYPE", U.S. patent application Ser. No. 11/692,446 titled "APPARATUS AND METHOD FOR PRODUCING IDENTIFIERS REGARDLESS OF MIXED DEVICE TYPE IN A SERIAL INTERCONNECTION", U.S. patent application Ser. No. 11/692,326 titled "APPARATUS AND METHOD FOR IDENTIFYING DEVICE TYPE OF SERIALY INTERCONNECTED DEVICES" and U.S. patent application Ser. No. 11/771,023 titled "ADDRESS ASSIGNMENT AND TYPE RECOGNITION OF SERIALY INTERCONNECTED MEMORY DEVICES OF MIXED TYPE" describe methods for generating device addresses for serially connected memory devices of a memory system, the contents of which are incorporated by reference in its entirety.

Memory devices **24** to **30** are considered serially connected because the data input of one memory device is connected to the data output of a previous memory device, thereby forming a series-connection configuration, with the exception of the

first and last memory devices in the chain. The channel of memory controller **22** includes data, address, command, and control information provided by separate pins or the same pins. For example, a data channel of any suitable data width will carry command, data and address information, while a control channel will carry control signal data. The embodiment of FIG. **2A** includes one channel, where the one channel includes Sout and corresponding Sin ports. However, memory controller **22** can include any number of channels for accommodating separate memory device chains. In the example of FIG. **2A**, the memory controller **22** provides a clock signal CLK, which is connected in parallel to all the memory devices.

In general operation, the memory controller **22** issues a command through its Sout port, which includes an operational code (op code), a device address, address information for reading or programming, and data for programming. The command is issued as a serial bitstream packet, where the packet can be logically subdivided into predetermined size segments, such as a byte for example. A bitstream is a sequence or series of bits provided over time. The command is received by the first memory device **24**, which compares the device address to its assigned address. If the addresses match, then memory device **24** executes the command. Otherwise, the command is passed through its own output port to the next memory device **26**, where the same procedure is repeated. Eventually, the memory device having the matching device address, referred to as a selected memory device, will execute the operation dictated by the command. If the command is to read data, the selected memory device will output the read data through its output port, which is serially passed through intervening memory devices until it reaches the Sin port of the memory controller **22**. Since the commands and data are provided in a serial bitstream, the clock is used by each memory device for clocking in/out the serial bits and for synchronizing internal memory device operations. This clock is used by all the memory devices in the serial memory system **20**.

The performance of serial memory system **20** is superior to that of the parallel memory system **10** shown in FIG. **10**. The parallel distributed clock lines can provide a relatively relaxed clock frequency, thereby allowing memory system **20** to use low voltage CMOS unterminated full swing signaling to provide robust data communication. This is also referred to as LVTTTL signaling. For example, assuming a 66 MHz clock is used and the serial memory system **20** includes four memory devices, the data rate per pin of one of the serially connected memory devices employing double data rate (DDR) signaling will be about 133 Mbps.

Serial memory system **40** of FIG. **2B** is similar to serial memory system **20** of FIG. **2A**, except that the clock signal CLK is provided serially to each memory device from an alternate memory controller **42** configured for providing the source synchronous clock signal CLK. Each memory device **44**, **46**, **48** and **50** will be configured to receive and pass the source synchronous clock CLK. In a practical implementation of serial memory system **40**, the clock signal CLK is passed from one memory device to another via short signal lines. Therefore none of the clock performance issues related to the parallel clock distribution scheme are present, and CLK can operate at high frequencies. Accordingly, the serial memory system **40** can operate with greater speed than serial memory system **20** of FIG. **2A**. For example, high speed transceiver logic (HSTL) signaling can be used to provide high performance data communication. In the HSTL signaling format, each memory device will receive a reference voltage that is used for determining a logic state of the incom-

ing data signals. Another similar signaling format is the SSTL signaling format. Accordingly, the data and clock input circuits in the memory devices of serial memory systems **20** and **40** will be configured differently from each other.

While high speed serial memory systems are suitable for newer computing devices, there may be existing computing systems that do not require high speed operation, but can still benefit from the high memory capacity of a serial memory system. For example, the serial memory system can be modular, as disclosed in commonly owned U.S. patent application Ser. No. 11/843,440, where additional memory devices can be added to the memory system in order to expand the total memory capacity. On the other hand, it may not be cost effective to replace existing slower speed serial memory systems with the high speed memory systems. Therefore, both types of memory devices would have to be available for upgrading or assembling of both types of serial memory systems. However, persons skilled in the art will understand that it is not cost effective to manufacture two different types of memory devices, where one type is configured for interfacing with memory controller **22** while another type is configured for interfacing with memory controller **42**.

Therefore, a clock mode configuration circuit for a configurable memory device is provided for allowing the configurable memory device to be used in both a parallel clocked memory system and a serially clocked memory system. Such a memory system includes any number of configurable memory devices serially connected to each other, where each configurable memory device receives a clock signal. The clock signal can be provided either in parallel to all the configurable memory devices or serially from one memory device to another through the same clock input. The clock mode configuration circuit in each configurable memory device is set to a parallel mode for receiving the parallel clock signal, and to a serial mode for receiving a source synchronous clock signal from a prior memory device or memory controller. Depending on the set operating mode, the data input circuits will be configured for a corresponding data signal format, and the corresponding clock input circuits will be either enabled or disabled. The parallel mode and the serial mode is set by sensing a reference voltage level provided to each memory device.

FIGS. **3A** and **3C** are block diagrams of serial memory systems using the same type of memory device that includes embodiments of the clock mode configuration circuit, the details of which will be described later. The memory devices of the serial memory system of FIG. **3A** receive the clock serially while the memory devices of the serial memory system of FIG. **3C** receive the clock in parallel. In the memory system embodiments of FIGS. **3A** and **3C**, four memory devices are shown connected in series in a ring topology configuration with the memory controller, however any number of memory devices can be included in either serial memory system. The serial memory systems of FIGS. **3A** and **3C** illustrate that the same type of memory device can be used for both a parallel clocked system and a serially source synchronous clocked system, provided the memory devices have the clock mode configuration circuit.

In FIG. **3A**, serial memory system **100** includes a memory controller **102** and four memory devices **104**, **106**, **108** and **110**. The memory controller **102** provides control signals in parallel to the memory devices. These include the chip enable signal CE# and the reset signal RST#. In one example use of CE#, the device is enabled when CE# is at the low logic level. Once the memory device starts a program or erase operation, CE# can be de-asserted, or driven to a high logic level. In one example use of RST#, the memory device is set to a reset

mode when RST# is at the low logic level. In the reset mode, the power is allowed to stabilize and the device prepares itself for operation by initializing all finite state machines and resetting any configuration and status registers to their default states. The memory controller **102** includes clock output ports CKO# and CKO for providing complementary clock signals CK and CK#, and clock input ports CKI# and CKI for receiving the complementary clock signals from the last memory device of the system. Each memory device will include a clock synthesizer, such as a DLL or a PLL for generating phases of the received clocks. Certain phases will be used to center the clock edges within the input data valid window internally to ensure reliable operation. Each memory device has clock output ports CKO# and CKO for passing the complementary clock signals to the clock input ports of the next memory device, and clock input ports CKI and CKI# for receiving the complementary clock signals from either the memory controller **102** or a previous memory device. The last memory device **110** provides the clock signals back to the memory controller **102**.

The channel of memory controller **102** includes a data channel consisting of data output port Qn and data input port Dn, and a control channel consisting of a command strobe input CSI, a command strobe output CSO (echo of CSI), data strobe input DSI, and a data strobe output DSO (echo of DSI). Output port Qn and input port Dn can be one bit in width, or n bits in width where n is a non-zero integer, depending on the desired configuration. For example, if n is 1 then one byte of data is received after eight data latching edges of the clock. A data latching clock edge can be a rising clock edge for example in single data rate (SDR) operation, or both rising and falling edges of the clock for example in double data rate (DDR) operation. If n is 2 then one byte of data is received after four latching edges of the clock. If n is 4 then one byte of data is received after two latching edges of the clock. The memory device can be statically configured or dynamically configured for any width of Qn and Dn. Hence, in a configuration where n is greater than 1, the memory controller provides data in parallel bitstreams. CSI is used for latching command and write data appearing on the input port Dn, and has a pulse duration corresponding to the length of the command data received. More specifically, the command and write data will have a duration measured by a number of clock cycles, and the pulse duration of the CSI signal will have a corresponding duration. DSI is used for enabling the output port Qn buffer to output read data, and has a pulse duration corresponding to the length of the read data being requested.

Since the present embodiment of FIG. 3A is intended for high speed operation, a high speed signaling format, such as the HSTL signaling format by example, will be used. Accordingly, a reference voltage VREF is provided to each memory device which is used by each memory device to determine the logic level of the signals received at the Dn, CSI and DSI input ports. The reference voltage VREF may be generated by another circuit on the printed circuit board, for example, and is set to a predetermined voltage level based on the voltage swing of the HSTL signal. By example, VREF can be set to a mid-point voltage of the maximum voltage level of the HSTL signal. According to the present embodiment, setting VREF to the aforementioned predetermined voltage level will set the clock mode configuration circuit in a first operating mode in which the input circuits are set to receive HSTL input signals and the appropriate internal clock circuits will be generated. The first operating mode can be referred to as a high speed operating mode.

In a practical implementation of the embodiment of FIG. 3A, each memory device is positioned on a printed circuit

board such that the distance and signal track between input and output ports is minimized. Alternately, the four memory devices can be implemented in a system in package module (SIP) which further minimizes signal track lengths. The memory devices can also be implemented as multiple SIP modules. Memory controller **102** and memory devices **104** to **110** are serially connected to form a ring topology, meaning that the last memory device **110** provides its outputs back to the memory controller **102**. As such, those skilled in the art will understand that the distance between memory device **110** and memory controller **102** is easily minimized.

FIG. 3B is a timing diagram showing the general timing relationship between the input signals and output signals for each memory device in serial memory system **100** with some internal signals shown as well. In this diagram internal gate delays are assumed to be minimal, although in an actual system significant delays can be accommodated and will not affect functionality. Signal traces for received input clocks CKI and CKI#, input data Dn, output clocks CKO and CKO#, and output data Qn are shown in FIG. 3B, as are internally generated 90, 180, 270 and 360 degree phases of the received input clocks. Since each memory device operates at the double data rate, received data is buffered into an internal single data rate even data stream D_E and an internal single data rate odd data stream D_O. In the example of FIG. 3B, data "A", "B", "C", "D" and "E" are provided serially on the Dn input of the memory device, where each has a data input valid window corresponding to a rising and falling edge of CKI or CKI#. In other words, the input data and the clock edges are coincident with each other. Data "A", "C" and "E" are latched on each rising edge of the internal 90 degree clock and provided on the D_E data stream. Data "B" and "D" are latched on each rising edge of the internal 270 degree clock and provided on the D_O data stream. Assuming that the received input data on Dn is simply passed through to its Qn output, the double data rate output data Qn is generated from the even D_E data latched on each rising edge of the 270 degree clock output and the odd D_O data latched on each rising edge of the 90 degree clock output. As shown in FIG. 3B, CKO corresponds to the 270 degree clock output while CKO# corresponds to the 90 degree clock output.

In the presently shown embodiment of FIG. 3C, each memory device has the same serial input/output interface, which includes RST#, CE#, CKI# and CKI input ports for receiving the corresponding signals from the memory controller **202**. The serial input/output interface further includes a data input port Dn, a data output port Qn, CSI, DSI, CSO and DSO ports. As shown in FIG. 3C, the Dn, CSI and DSI input ports for each memory device are connected to the Qn, CSO and DSO output ports respectively, of a previous memory device. Accordingly, the memory devices are considered serially connected to each other as each can pass command and read data to the next memory device in the chain.

In FIG. 3C, serial memory system **200** includes a memory controller **202** and the same memory devices **104**, **106**, **108** and **110** of FIG. 3A. The memory controller **202** will be configured to provide the same functionality as memory controller **102** of FIG. 3A except that the clock signals are provided in parallel, therefore the clock output ports CKO# and CKO of each memory device are unconnected. Furthermore, the signaling format for the data and the strobe signals will be different, such as the full swing un-terminated LVTTTL signaling format by example. At lower clock frequencies, the LVTTTL signaling format does not require the use of reference voltage VREF, thus VREF can be set to a voltage level other than the predetermined level used in the embodiment of FIG. 3A. For example, VREF can be set to either VDD or VSS.

11

According to the present embodiment, setting VREF to VSS or some voltage other than the aforementioned predetermined voltage level will set the clock mode configuration circuit in a second operating mode in which the input circuits are set to receive LVTTTL input signals and the appropriate internal clock circuits will be generated. The second operating mode can be referred to as a low speed operating mode. Accordingly, an advantage of using the existing VREF input of the memory devices to set the operating mode of the clock mode configuration circuit is that no additional pin and corresponding logic in the memory controllers is required for configuring the memory devices. Each memory device self-configures based on the voltage level of VREF, thereby reducing any design overhead in the memory controller. Furthermore, the same clock input ports CKI and CKI# can receive either the parallel clock signals or the serial clock signals, which minimizes the pin count of the memory device.

FIG. 3D is a timing diagram showing the general timing relationship between the input signals and output signals for each memory device in serial memory system 200 with some internal signals shown as well. In this diagram internal gate delays are assumed to be minimal, although in an actual system significant delays can be accommodated and will not affect functionality. Signal traces for received input clocks CKI and CKI#, input data Dn and output data Qn are shown in FIG. 3B. The memory devices do not have an internal clock synthesizer, and no output clocks CKO and CKO# are provided. Each memory device operates at the double data rate, hence received data is buffered into a single data rate even data stream D_E and a single data rate odd data stream D_O. In the example of FIG. 3D, data "A", "B", "C", "D" and "E" are provided serially on the Dn input of the memory device, and the rising and falling edges of CKI and CKI# are centered within each data input valid window. In the present example, internal read data "Ci" and "Di" will be provided to the output circuits of the memory device via RD_E and RD_O, in response to a read command received by the memory device. Accordingly, there is an even output data stream Q_E and an odd output data stream Q_O that will provide either the internal read data from RD_E and RD_O or external data from the D_E and D_O on the Qn output. More specifically, data from RD_E and RD_O will be provided on Q_E and Q_O in response to enable signals EN_E and EN_O at the high logic level.

Data "A", "C" and "E" are latched on each rising edge of CKI and provided on the D_E data stream. Data "B" and "D" are latched on each rising edge of CKI# and provided on the D_O data stream. While EN_E and EN_O are at the inactive low logic level, data "A" and "B" will be latched on the rising edges of CKI and CKI# and provided on D_E and D_O respectively. On the rising edge of CKI#, data "A" on D_E is latched and provided on Q_E, while data "B" on D_O is latched on the rising edge of CK and provided on Q_O. Data "A" and "B" are then provided on the Qn output on the rising edges of CKI# and CKI respectively. When EN_E is high, data "Ci" on RD_E is latched and provided on Q_E on the rising edge of CKI#. Subsequently, while EN_O is high, data "Di" on RD_O is latched and provided on Q_O on the rising edge of CKI. Data "Ci" and "Di" are then provided on the Qn output on the rising edges of CKI# and CKI respectively. When EN_E and EN_O fall to the low logic level, external data "E" will be latched onto Q_E and passed onto Qn. Delay through the output path of the device, the interconnection to the following device, and the input path of the following device will shift the Qn data stream so that the rising edge of CKI in the following device falls within the received Dn data stream bits A, Ci, and E, and the rising edge of CKI# in the

12

following device falls within the received Dn data stream bits B and Di. Persons skilled in the art will ensure that the delay path from serial output Qn to serial input Dn is less than half a clock period.

According to an example embodiment, memory devices 104, 106, 108 and 110 can be any type of memory device having a serial input/output interface designed for serial interconnection with other memory devices. While memory devices 104, 106, 108 and 110 can be implemented as Flash memory devices, they can also be implemented as DRAM, SRAM or any other suitable type of volatile or non-volatile memory device. More specifically, other memory types can be adapted to operate with the serial input/output interface and configured to receive LVTTTL input signals or HSTL input signals.

FIG. 4 is a block diagram illustrating the conceptual organization of a generic memory device having a native core and a serial input/output interface suitable for use in the serial memory systems of FIGS. 3A and 3C. Memory device 300 includes a native memory core, which includes memory array banks 302 and 304, and native control and I/O circuits 306 for accessing the memory array banks 302 and 304. Those skilled in the art will understand that the memory array can be organized as a single memory bank or more than two memory banks. The native memory core can be DRAM, SRAM, NAND flash, or NOR flash memory based for example. Of course, any suitable emerging memory and its corresponding control circuits can be used. Accordingly, depending on the type of native memory core, circuit block 306 can include error correction logic, high voltage generators, refresh logic and any other circuit blocks that are required for executing the operations native to the memory type.

Typically, memory devices use command decoders for initializing the relevant circuits in response to a received command by asserting internal control signals. They will also include well known I/O circuitry for receiving and latching data, commands and addresses. According to the present embodiment, the existing I/O circuits are replaced with the serial interface and control logic block 308. In the present example, the serial interface and control logic block 308 receives RST#, CE#, CK#, CK, CSI, DSI and Dn inputs, and provides Qn, CSO, DSO, CKO and CKO# outputs.

The serial interface and control logic block 308 is responsible for various functions, as discussed in U.S. patent application Ser. No. 11/324,023. Example functions of serial interface and control logic block 308 include setting a device identifier number, passing data through to the next serially connected memory device, and decoding a received command for executing native operations. This circuit will be configured to receive commands serially, and will be configured to include additional commands specific to serial operation of the memory device, in addition to existing native commands specific for controlling core circuits. The command set can be expanded to execute features usable by the memory controller when the memory devices are serially connected. For example, status register information can be requested to assess the status of the memory device.

Therefore, the serial memory systems of FIGS. 3A and 3C can include a mix of memory device types, each providing different advantages for the greater system. Such a configuration having memory devices of mixed types is disclosed in U.S. Provisional Patent Application No. 60/868,773 filed Dec. 6, 2006, the disclosure of which is incorporated herein by reference in its entirety. Further details are such configurations are disclosed in U.S. patent application Ser. No. 11/771,023 titled "ADDRESS ASSIGNMENT AND TYPE RECOGNITION OF SERIALY INTERCONNECTED

13

MEMORY DEVICES OF MIXED TYPE”, and in U.S. patent application Ser. No. 11/771,241 titled “SYSTEM AND METHOD OF OPERATING MEMORY DEVICES OF MIXED TYPE”. For example, the high speed of DRAM memory can be used for caching operations while the non-volatility of flash memory can be used for low power mass data storage. Regardless of the type of memory device being used, each memory device is individually addressable to act upon a command because the serial interface and control logic block **306** is configured to receive commands according to a predetermined protocol. According to one embodiment, the previously discussed clock mode configuration circuit is implemented in the serial interface and control logic block **308**.

FIG. **5** is a block diagram illustrating a clock mode configuration circuit according to one embodiment, which generates signals to be used by an embodiment of a configurable input/output buffer. Both the clock mode configuration circuit and the configurable input buffer can be used in the previously described serial interface and control logic block **308**. The clock mode configuration circuit includes a mode setter **400** and a clock switch circuit **402**. The mode setter **400** generates a mode signal **MODE** having either a high logic level or a low logic level in response to a voltage level of a reference voltage **VREF**. As previously noted by example, **VREF** is used by the memory device to determine the logic level of high speed input signals, such as those using the HSTL signaling format. In the present embodiment, **VREF** will be set to some predetermined voltage level between the high and low voltage supply levels, such as $VDD/2$ for HSTL signaling for example. If lower speed input signals are to be used, such as those using the LVTTL signaling format, then the **VREF** voltage is not required, and the **VREF** pin can be connected to either supply voltage level (**VDD** or **VSS**). From this point on, the HSTL and LVTTL signaling formats will be used to describe the operation of the embodiments, and **VREF** will be set to **VSS** when the memory device is to receive LVTTL signals. The clock switch circuit **402** is responsible for enabling generation of internal clock signals based on one of a parallel clock signal or a source synchronous serial clock signal, in response to the mode signal **MODE** provided by the mode setter **400**. A further discussion of the components of the clock switch circuit **402** will follow later.

The configurable input/output buffer of FIG. **5** is implemented as a configurable data input/output buffer **404** that will sense HSTL or LVTTL input signals and pass either the received input signals or internal data from the memory device, to the output port **Qn**. The configurable data input/output buffer **404** will use the internally generated clock signals provided by clock switch circuit **402** in order to maintain synchronous operation in accordance with the selected input signaling format. While only one configurable input/output buffer is shown in FIG. **5**, persons of skill in the art will understand that there is one configurable input/output buffer for input signals **DSI** and **CSI** as well.

In the present example embodiments, **VREF** at the predetermined voltage level, typically $VDD/2$, will correspond to a serial clock mode of operation, while **VREF** at the **VSS** voltage level will correspond to a parallel clock mode of operation. This means that during assembly of the memory system, if each memory device receives the clock signal in series as in FIG. **3A**, then **VREF** will be set to the predetermined voltage level. Accordingly, the HSTL signaling format will be used. On the other hand, if each memory device receives the clock signal in parallel as in FIG. **3C**, then **VREF** will be set to **VSS**. Then the LVTTL signaling format will be used instead. Therefore, **VREF** is sensed by mode setter **400** to set signal

14

MODE to a first logic state corresponding to a serial clock mode of operation or to a second logic state corresponding to a parallel clock mode of operation.

Returning to the clock switch circuit **402** with this understanding of the **MODE** signal, clock switch circuit **402** includes a clock input buffer **406**, a clock generator **408**, and a clock output buffer **410**. The clock input buffer **406** is connected to the clock input ports **CK** and **CK#**, and generates either a single ended clock signal based on two differential clock inputs **CK** and **CK#**, or separate buffered versions of **CK** and **CK#** in response to the logic state of the mode signal **MODE**. For example, the single ended clock signal is generated when **MODE** is at the first logic state. The clock generator **408** receives either the single ended clock signal or the buffered versions of **CK** and **CK#** to provide two internal clock phases used for internal operation and generating the proper output timing. The internal clock signals **CKI** and **CKI#** are distributed to the internal circuits of the memory device, and to the configurable input/output buffers. The clock output buffer **410** receives the internal clock signals **CKI** and **CKI#**, and drives them through the **CKO** and **CKO#** output port when **MODE** is at the first logic state. When **MODE** is at the second logic state corresponding to a parallel mode of operation, the clock output buffer **410** is disabled since there is no need to provide the serial clock to the next memory device.

The configurable data input/output buffer **404** includes a data input buffer **412**, a data switch **414**, and a data output buffer **416**. The data input buffer **412** receives input data **Dn** and the reference voltage **VREF**, which is used when **MODE** is at the first logic level. A buffered input signal **Din** is then provided to the data switch **414**, which passes either **Din** or native data from the memory device, to the data output buffer **416**. The native data in the present example includes even data **RD_e** and odd data **RD_o**, because data is provided on both the rising and falling edge of the clock signal. Signals **EN_o** and **EN_e** are used to select **Din** or both **RD_e** and **RD_o** to pass to the data output buffer **416**. Furthermore, it is noted that the serial data of **Dn** is provided on both the rising and falling edge of the clock signal. The selection of which data to pass will depend on the command received by the memory device. In either case, the data is synchronized to the internal clock signals **CKI** and **CKI#** and passed to the data output buffer as even and odd data **Dout_e** and **Dout_o** respectively. The data output buffer **416** will then interleave the **Dout_e** and **Dout_o** bits of data in response to the clock and drive it through the **Qn** data output port.

An advantage provided by the clock mode configuration circuit of FIG. **5** is that no additional package pin is required because **VREF** is now used for two different purposes. If each memory device is individually packaged, then the package size is thereby minimized by reducing the number of pins that are required. Those skilled in the art will understand that smaller package sizes minimize required printed circuit board area upon which the memory system is integrated upon. Alternately, the memory devices of the serial memory systems shown in FIGS. **3A** and **3C** can be packaged together as a system in package (**SIP**). Once again, a reduced pin count will minimize the package size. The mode setter **400** being connected to the **VREF** input port provides this advantage. A further advantage is that a single memory component can operate correctly in high performance source synchronous clocking configurations, and in lower performance parallel clocking configurations with reduced power consumption, as will be further explained as follows.

FIG. **6** is a circuit schematic of the mode setter **400**, according to one embodiment. Mode setter **400** will sense the volt-

15

age level of VREF and drive signal MODE to either a first logic level or a second logic level. In this particular example, the first and second logic levels can correspond to VDD and VSS respectively. Mode setter 400 includes a sense circuit 500, a latch 502, and a digital delay circuit 504. The sense circuit 500 includes resistor elements 506, 508, a power shut-off device 510 connected in series between VDD and VSS, and a comparator 512. In the present embodiment, power shut-off device 510 is implemented as an n-channel transistor having a gate terminal receiving an enable signal EN. The shared terminal of resistor elements 506 and 508 is connected to one input of comparator 512, while a second input of comparator 512 receives the reference voltage VREF. Resistor elements 506 and 508 form a reference voltage circuit. The ratio of resistor elements 506 and 508 can be set depending on the value of VREF to be detected. For example, if the stable voltage level of VREF is to be VDD/2, then resistor element 506 can be set to 3R while resistor element 508 can be set to R. Accordingly, the shared terminal "x" will be at approximately VDD/4. The comparator 512 can be implemented with any known circuit, and in the present example, includes an optional enable input for receiving the enable signal EN.

The latch 502 can be implemented with any known circuit, and in the present example optionally receives enable signal EN. When the latch enable input is high the signal appearing on the D input is provided at the Q output. When the latch enable input transitions from high to low, the state of the D input is latched and provided to the output Q. The digital delay circuit 504 includes a counter 514, a NOR logic gate 516, and an inverter 518. The counter 514 is an n-bit counter, where n can be any integer number greater than 1, having only its most significant bit output (MSB) connected to the input of inverter 518. The counter is reset such that all bits, including the MSB output, are set to 0 (VSS) when RST# is at the low logic level. MSB is also connected to one input of NOR logic gate 516, while its other input receives clock signal CK. Therefore, when reset, MSB is at VSS in the present example. When RST# is released by setting it to the high logic level, the counter is permitted to increment the count with each rising or falling edge of the clock CK. When the MSB is toggled to 1 (VDD), then power shut-off device 510 is turned off via inverter 518, the comparator 512 is turned off to save power, the MODE output is latched, and the clock input of the counter 514 is disabled via the NOR gate to freeze the counter 514. After the delay provided by the counter, MODE will be stably set to either VDD or VSS.

The operation of mode setter 400 is now described with reference to the sequence diagram of FIG. 7. At time t1, RST# is at VDD, which results in counter 514 driving MSB to VDD. EN is then driven to VSS by inverter 518, which turns off power shut-off device 510 to allow node "x" to float to VDD. The advantage of having node "x" float to VDD while the circuit is disabled is that regardless of the value of VREF, MODE will immediately default to VSS when comparator 512 and latch 502 are enabled, because node "x" will always be greater than VREF. This immediately sets the memory device to the parallel clock mode of operation so that normal memory operations can begin without delay. At time t2, RST# is pulsed to VSS to reset MSB to VSS. RST# returning high releases counter 514 to count a predetermined number of edges of clock signal CK to allow the analog portions of the circuit sufficient time to settle and properly determine the level on the VREF pin, even if the RST# low level pulse is short. When MSB drops to VSS, EN is driven to VDD by inverter 518 to enable the resistor divider, comparator 512, and latch 502 to evaluate the level on the VREF pin and determine the MODE of operation. Because node "x" is cur-

16

rently floating at VDD, the enabled comparator 512 will drive a low logic output which is then passed through latch 502 for setting MODE to the low logic level.

In the present example, it is assumed that VREF is configured to be approximately VDD/2, and the ratio of resistor elements 506/508 is 3R/R. While the circuit is enabled, the voltage at node "x" will therefore settle to a level of approximately VDD/4. Eventually, the voltage on node "x" will be established at a steady VDD/4 level as shown in FIG. 7 at time t3. If VREF is set to VSS, then no change will occur in comparator 512 to keep MODE at VSS. On the other hand, if VREF is set to VDD/2, comparator 512 will then drive its output to VDD which causes latch 502 to drive MODE to VDD around time t3. Eventually, counter 514 will set MSB to VDD at time t4 to drive EN to VSS. MSB at VDD will cause NOR logic gate 516 to output a low logic level signal to effectively terminate counting by counter 514, thereby "freezing" the counter 514. Once EN drops to VSS, power shut-off device 510 is turned off and node "x" will eventually float to VDD. However, EN at VSS will now disable comparator 512, and latch 502 is prevented from latching any changing output signal on its D input. Therefore, power is saved by turning off sense circuit 500. In the source synchronous mode of operation, normal memory operations can begin only after PLL or DLL synchronization. This time is not wasted since the voltage at node "x" will settle to the correct value during this synchronization period.

Therefore, the time delay corresponding to the time for counter 514 to toggle MSB to VDD will be sufficiently long to ensure that node "x" and VREF have stabilized for sensing by comparator 512. By example only, a 1 ms time delay may be a sufficient time delay provided by digital delay circuit 504. Hence by turning off power shut-off device 510 after MSB is toggled to VDD, the current path from VDD through the resistor elements 506 and 508 to VSS is cut off, thereby conserving power during operation of the memory device. This time delay can be selected based on the clock frequency being applied and the number of bits in the counter 514.

FIG. 8A is a schematic embodiment of the clock switch circuit 402 and the configurable data input/output buffer 404 of FIG. 5. Both circuits can be referred to as a configurable input circuit, since one receives an input clock and the other receives input data from at least one input data port. The clock switch circuit 402 is configurable to operate in the parallel or serial clock modes in response to a logic state of the mode signal MODE, while the configurable data input/output buffer 404 is configurable to receive input data in either the HSTL or LVTTTL signaling format in response to the logic state of MODE. It is noted that this Dn input can receive both write data and commands from a memory controller. In order to simplify the circuit schematic of FIG. 8A, the command data path and the input write data path are not shown. The same numbered reference numbers appearing in FIG. 8A have been generally described in FIG. 5.

The details of the clock switch circuit 402 now follows. The clock input buffer 406 includes a comparator 700 for receiving complementary clock signals from clock input ports CK1 and CK1#, a first buffer circuit 702 receiving a clock signal from clock input port CK1 and a second buffer circuit 704 receiving a complementary clock signal from clock input port CK1#. Comparator 700 is enabled by one state of MODE while the first and second buffers 702 and 704 are both enabled by an opposite state of MODE. Thus, only one of the comparator 700 and the buffers 702 and 704 will be active for any single logic state of MODE. However, the outputs of comparator 700 and buffers 702 and 704 are coupled to clock generator 408 in parallel. For the presently

17

described example where mode setter **400** sets MODE to the first logic state corresponding to the serial clock mode of operation and to a second logic state corresponding to the parallel clock mode of operation, MODE at the first logic state will enable comparator **700**. Accordingly, MODE at the second logic state will enable first and second buffers **702** and **704**.

Clock generator **408** includes a phase locked loop (PLL) circuit **706** that is enabled when MODE is at the first logic state. When enabled, PLL circuit **706** will generate clock outputs shifted by 90, 180, 270 and 360 degrees relative to the clock signal received at its REF input, which is connected to the output of comparator **700**. These shifted clock outputs are provided from the terminals labeled 90, 180, 270 and 360. In the serial clock mode of operation, received input clock transitions and received input data transitions are coincident. The PLL circuit **706** is used to place the edges of the internal clock signals within the input data valid window, for reliable data capture. A feedback input FB receives the 360 degree shifted clock output to facilitate locking of the clock signals. Those skilled in the art should be familiar with PLL circuit operation, and that the clock will be locked after several clock cycles to ensure stable operation. Instead of a PLL, a delayed lock loop (DLL) circuit can be used in place of the PLL circuit **706**. A PLL and a DLL are both examples of clock synthesizers which can be used in the disclosed embodiments. The 90 and 270 degree clock outputs are provided to first inputs of 2-1 multiplexors **708** and **710**, both being controlled by MODE. The second inputs of multiplexors **708** and **710** receive the outputs of buffers **702** and **704** respectively. In the parallel clock mode of operation, the received input clock transitions will be within the input data valid window so that no phase shifted clocks are required. Therefore, multiplexors **708** and **710** collectively form a switch circuit for selectively passing one of the 90 and 270 degree clock outputs from PLL circuit **706** and the buffered clock signals from buffers **702** and **704** in response to MODE. In the present example when MODE is at the first logic level, PLL circuit **706** is enabled and multiplexors **708** and **710** will be controlled to pass the 90 and 270 degree clock outputs as internal clock signals CK and CK#. On the other hand, when MODE is at the second logic level, PLL circuit **706** is disabled and multiplexors **708** and **710** will be controlled to pass the clock signals from buffers **702** and **704** as the internal clock signals CK and CK#. Accordingly, turning off the PLL that is not being used will reduce power consumption.

While not explicitly shown in FIG. 8A, complementary internal clock signals CK and CK# are distributed to other circuits within the memory device. An optional feature of clock generator **408** is the phase selector circuit that includes multiplexors **712** and **714**. First inputs of multiplexors **712** and **714** receives the internal clock signals CK# and CK respectively, while second inputs receive the 360 and 180 degree clock outputs from PLL circuit **706**. Both multiplexors **712** and **714** are controlled by signal PHASE, which is provided by the command decoder of the memory device. The purpose of the phase selector circuit is to centre the output clock signals provided on output ports CKO and CKO# with the output data provided on the output port Qn. In a serially connected memory system, this feature is enabled in the last memory device of the system. The advantage is that the memory controller design can be simplified as it will not require a PLL or DLL to reliably receive the data from the last memory device in the ring. Further details of the application of this feature in a memory system will be described later. The clock output buffer **410** includes a pair of drivers **716** and **718** for driving the clock signals provided by multiplexors **712**

18

and **714** onto output ports CKO and CKO#. Both drivers **716** and **718** are enabled by MODE, when it is at the first logic level representing the serial clock mode for example.

Therefore, in response to MODE, clock switch circuit **402** is configured to generate internal clock signals corresponding to a serially provided source synchronous clock signal or to a parallel clock signal. Because the memory devices will operate at high speeds in response to a high speed source synchronous clock signal, this mode can be referred to as a high speed mode of operation. On the other hand, because the parallel clock signals will be at a lower frequency than the source synchronous clock, the other mode can be referred to as a low power mode of operation since circuits such as the comparator **700**, PLL **706**, and drivers **716** and **718** will be turned off, and the lower frequency operation reduces overall power consumption relative to when the memory device operates at high frequencies. In either mode of operation, the internal clock signals CK and CK# will be generated for use by other circuits of the memory device, such as the configurable data input/output buffer consisting of data input buffer **412**, data switch **414** and data output buffer **416**.

The data input buffer **412** includes a comparator **720**, a buffer circuit **722** and a data input selector **724**, where the data input selector **724** is implemented as a 2-1 multiplexor. Comparator **720** has one input connected to input port Dn, and a second input connected to the reference voltage input port VREF. The buffer circuit **722** is also connected to input port Dn. Comparator **720** generates a logic output corresponding to the voltage level of Dn relative to VREF, while buffer circuit **722** drives a logic level corresponding to what it receives. All three circuits are controlled by MODE, and in the presently described example where MODE being at the first logic level corresponds to a high speed mode of operation, comparator **720** is enabled, buffer **722** is disabled, and data input selector **724** is controlled to pass the output of comparator **720**. The output of data input selector **724** is referred to as Din.

Since the memory devices of the present embodiments are to be serially connected to each other, external data arriving at the Dn input port can be selectively passed through a memory device to the designated, or addressed, memory device. However, each memory device can also provide local read data that is to be passed on to the memory controller through any intervening memory devices. The purpose of data switch **414** is to selectively pass either external Dn data or local read data to the output port Qn. The data switch **414** includes external data input latches **726** and **728**, data output selectors **730** and **732**, and output latches **734** and **736**. In the present embodiment, data is latched on both edges of the internal clock CK. Therefore, latches **726** and **728** receive CK and CK# respectively. Data output selector **730** passes one of latched external data from data input latch **726** or local even read data RD_e in response to select signal EN_e. Similarly, data output selector **732** passes one of latched external data from data input latch **728** or local odd read data RD_o in response to select signal EN_o. Select signals EN_e and EN_o are provided by the command decoder of the memory device.

The data output latches **734** and **736** latch the outputs of output selectors **730** and **732** in response to active edges of the internal clock signals CK# and CK respectively. The operation of the data switch **414** is well understood by those of skill in the art familiar with double data rate operation. The data output buffer **416** includes a data output selector **738** implemented as a 2-1 multiplexor, and a driver **740**. Data output selector **738** alternately passes the outputs of data output latches **734** and **736** in response to CK, which is then provided onto output port Qn by driver **740**. In summary, when MODE

19

is set, the data input buffer **412** is automatically configured to receive a corresponding data signal format, and the appropriate internal clock signals are automatically generated by clock switch circuit **402** for use by data switch **414** and data output buffer **416**.

Therefore, the same memory devices connected in series in a ring topology with a memory controller can be configured to receive either a parallel clock or a source synchronous clock in series in response to a reference voltage that is used for sensing data signal voltage levels, as shown in FIGS. **3A** and **3C**. Furthermore, data input circuits are automatically configured to receive data signals having a signaling format that corresponds with the parallel clock and the source synchronous clock. Although not shown, the output buffer drive strength can also be configured based on the MODE setting, to optimize performance and power in the multi-drop bus and point-to-point ring topologies.

As previously discussed, each memory device can include the optional phase selector circuit that includes multiplexors **712** and **714** shown in FIG. **8A**. In use with the memory system of FIG. **3A** for example, only the last memory device **110** will have PHASE set to a logic level for passing the 180 and 360 degree clock outputs from PLL **706**. For example, all memory devices except the last memory device in the ring will output the 90 and 270 degree clocks, which are the same clocks used to generate output data transitions. Therefore, output clock edges and output data edges are co-incident and fully compatible with the input sampling stages of the next memory device. If the controller does not have a PLL or DLL to shift the input clock edges to the middle of the input data valid window, the PHASE bit can be set to provide output clock transitions already positioned in the middle of the data valid window, so that the controller can sample received data directly with the received clock signal. In the present examples, these would be the 180 and 360 degree degree clock outputs. Signal PHASE can be set by loading a single bit register from a command received by the memory device. This would be set during a power up sequence of the memory system, which would start with the memory controller **202** executing an algorithm for assigning addresses to each memory device. Such algorithms can include the ones disclosed in the previously mentioned commonly owned U.S. patent applications which are directed to generating ID numbers for memory devices in the memory system.

During ID number assignment, all memory devices will have the PHASE bit set to output co-incident clock and data edges. In the present embodiments for example, this can correspond to a default state of PHASE in which the 90 and 180 degree clocks are output. If the memory controller does not have a PLL or DLL, then it will not be able to properly receive data until PHASE of the last memory device has been properly programmed. However, since devices will not output any data transitions at all until their device addresses have been assigned, the memory controller will recognize transitions on its data input as an indication that the last memory device has been programmed with a device address. Once the last memory device in the system is known by the memory controller, a command is issued to set the aforementioned single bit register that changes the default state of PHASE to one for passing the 180 and 360 degree clock outputs. After this setting has taken effect full communication around the ring can occur.

FIG. **8B** is a timing diagram showing the operation of the circuits of FIG. **8A**. In particular, the timing diagram of FIG. **8B** shows the internally generated clock signals in response to different settings of MODE and PHASE during a continuous sequence of CKI and CKI# clock transitions. At the same

20

time, hypothetical data on the Qn output port is shown to contrast timing differences relative to the output data valid windows in response to different logic levels of MODE and PHASE. This timing diagram is merely illustrative of the behaviour of the circuits of FIG. **8A**. Those skilled in the art will understand that data would not be provided proximate to transitions of MODE and PHASE during actual use. Dynamic transitions of MODE and PHASE would be done during an initialization or reset period of the memory system. FIG. **8B** includes signal traces for MODE, PHASE, CKI and CKI#, the internally generated 90, 180, 270 and 360 degree clock signals from the clock synthesizer, CK and CK# and CKO and CKO#.

In the time period between time **t1** and **t2**, the circuit is operating in the parallel clock mode when MODE is at a low logic level. Because MODE is at the low logic level, PLL circuit **706** is turned off resulting in its 90, 180, 270 and 360 clock outputs being set to the low logic level. The internal clocks CK and CK# are therefore buffered versions of CKI and CKI# respectively. Using the circuits shown in FIG. **8A**, the data transfer operation between the input Dn (not shown) and Qn will follow the same sequence as shown in FIG. **3D**, except that the latching operations are now responsive to CK and CK# instead of directly to CKI and CKI#. With MODE at the low logic level, the clock output buffer **410** is disabled to keep CKO and CKO# at the low logic level.

In the time period between time **t2** and **t4**, the circuit is operating in the serial clock mode when MODE is at a high logic level. Because MODE is at the high logic level, PLL circuit **706** is turned on to generate the 90, 180, 270 and 360 clock outputs. The current timing diagram assumes that mode reset and PLL locking is immediate. With MODE at the high logic level, internal clocks CK and CK# will correspond to the 90 and 270 degree clock outputs, and the clock output buffer **410** is enabled to drive CKO and CKO# with the CK and CK# clocks. Using the circuits shown in FIG. **8A**, the data transfer operation between the input Dn (not shown) and Qn will follow the same sequence as shown in FIG. **3B**, except that the latching operations are now responsive to CK and CK# instead of directly to the 90 and 270 degree clock outputs.

At time **t3** PHASE is at the high logic level, but in actual use PHASE is set to either the high or low logic level before normal operations of the memory device. The transition shown in FIG. **8B** merely contrasts the relationship between rising and falling edges of CKO and CKO# relative to the output data of Qn between different logic levels of PHASE. With PHASE set to the high logic level, multiplexors **712** and **714** will pass the 180 and 360 degree clock outputs to the clock output buffer **410**. Accordingly, CKO and CKO# will correspond to the 180 and 360 degree clock outputs, thereby centering the clock edges within the data valid windows.

The system embodiments of FIGS. **3A** and **3C** are static, meaning that once manufactured or assembled for use, they cannot be changed. According to another embodiment, the memory system can be dynamically changed such that the memory devices receive either a parallel clock or a source synchronous clock in series. FIG. **9** is an embodiment of a dynamically configurable serial memory system where the memory controller provides both parallel and source synchronous clocks, and data signals in signaling formats corresponding to the type of clocks. The memory devices will include the same circuits shown in FIG. **8A**, with a minor modification to receive both parallel and source synchronous clock signals.

In FIG. **9**, configurable serial memory system **800** includes a memory controller **802**, and four dynamically clock configurable memory devices **804**, **806**, **808** and **810**. Memory

21

controller **802** provides the same control and data signals as memory controller **102** or **202**, but now provides parallel complementary clocks through clock output ports CK1 and CK1#, and complementary source synchronous clocks through clock output ports CK2 and CK2#. Memory controller **802** is further configured to dynamically provide data and the strobe signals through its Qn, CSO and DSO output ports in one signaling format corresponding to the parallel clock, and another signaling format corresponding to the source synchronous clock. For example, LVTTTL signaling can be used with the parallel clock while HSTL signaling can be used with the source synchronous clock. Memory controller **802** further includes serial clock input ports CKI and CKI# for receiving the source synchronous clocks from the last memory device. Each memory device is similarly configured to the memory devices shown in FIGS. 3A and 3C, except that each now includes a parallel input clock ports CK1 and CK1# and serial input clock ports CKI and CKI#. Depending on the level of VREF, each memory device will selectively use either the parallel clocks or the source synchronous clocks.

FIG. 10 is a schematic showing details of a clock switch circuit **402** according to an alternate embodiment. This clock switch circuit shows a modification to the clock switch circuit shown in FIG. 8A, where elements that are the same share the same reference numerals. The only difference over the embodiment of FIG. 8A is that clock input buffer **406** now includes comparator **900**, first buffer circuit **902** and second buffer circuit **904** that replace comparator **700**, first buffer circuit **702** and second buffer circuit **704** of FIG. 8A. Comparator **900** has its inputs connected to clock input ports CKI and CKI# that are dedicated to receiving complementary source synchronous clock signals. The first buffer circuit **902** and second buffer circuit **904** are connected to clock input ports CK1# and CK1 that are dedicated to receiving complementary parallel clock signals. Now each memory device can be physically connected to both parallel and source synchronous clocks at the same time. The voltage level of VREF will then determine which of the clock inputs are to be used. In the memory system embodiment of FIGS. 9 and 10, VREF can now be controlled by the memory controller, or alternatively by some suitable circuit separate from the memory controller that is controllable to drive VREF to the predetermined voltage level, or to either supply voltage. Therefore, the memory system illustrated in FIGS. 9 and 10 can be dynamically switched to operate with the source synchronous clocks for high speed operation, or with the parallel clocks if low power consumption operation is desired.

FIG. 11 is a flow chart summarizing the general algorithm executed by both the memory controller and the memory devices of the memory systems shown in FIGS. 3A, 3C and 9 for setting an operating mode. The method begins at step **1000** where the memory system is powered up, or reset by asserting the reset signal RST#. At step **1002** the memory controller will execute start-up algorithms, such as an algorithm to assign device ID numbers to each memory device in the memory system. At power up or reset, VREF will be set to a power supply voltage or to a predetermined voltage level. It should be understood to those skilled in the art that other start-up algorithms can be executed by the memory controller and the memory devices themselves. Each memory device will then sense the level of VREF at step **1004**, via their respective clock input buffers, such as the clock input buffer **406** shown in FIG. 8A. The level of VREF is then determined at step **1006**, and if it is not a reference voltage, then it should be either the VDD or VSS voltage supply, and MODE is set to a first logic level at step **1008**. Otherwise, VREF is the pre-

22

determined reference voltage level and MODE is set to a second logic level at step **1010**.

Once MODE has been set, then all the memory devices will automatically configure their clock switch circuits and configurable data input/output buffers, such as clock switch circuit **402** and configurable data input/output buffer **404**, in the manner previously described at step **1012**. Once the memory devices have been configured to receive clock and data signals corresponding to MODE, then as an optional step, the memory controller can issue a command to switch PHASE of the last memory device from a default value to an active level. With reference to FIG. 8A, the default value of PHASE at start-up or reset of the memory device can be a low logic level to pass CKI and CKI#, while an active value can be VDD for passing the 180 and 360 degree clock outputs of PLL **706**.

While the previously described embodiments are directed to serial memory devices, they can be applied to any semiconductor device that operates with a clock provided in parallel or in series.

In the preceding description, for purposes of explanation, numerous details are set forth in order to provide a thorough understanding of the embodiments of the invention. However, it will be apparent to one skilled in the art that for any particular embodiment of the invention, not all described details are required in order to practice that embodiment of the invention. In some instances, well-known electrical structures and circuits are shown in block diagram form in order not to obscure the invention. For example, specific details are not provided as to whether the embodiments of the invention described herein are implemented as a software routine, hardware circuit, firmware, or a combination thereof.

Certain adaptations and modifications of the described embodiments can be made. Therefore, the above discussed embodiments are considered to be illustrative and not restrictive.

What is claimed is:

1. A method for configuring a clock operating mode of a memory device that receives a reference voltage for sensing input data, comprising:

- a) setting the reference voltage level;
- b) comparing the reference voltage to a preset reference voltage for generating a mode selection signal corresponding to the reference voltage relative to the preset reference voltage; and
- c) configuring a clock input buffer to receive one of parallel complementary clock signals and serial complementary clock signals in response to the mode selection signal.

2. A semiconductor device for receiving a clock and input data comprising:

- a) a configurable input circuit operable in a first mode for receiving coincident edges of the clock and the input data, and for providing shifted clock edges positioned within a data valid window for sampling the input data, the configurable input circuit being operable in a second mode for receiving non-coincident edges of the clock and the input data for sampling the input data.

3. A memory device comprising:

- a) a mode selection circuit for providing a mode selection signal, the memory device being configured for high speed operation as determined by the mode selection signal being at a first logic level, and the memory device being further configured for low speed operation as determined by the mode selection signal being at a second logic level;
- b) a reference voltage input terminal for receiving an input reference voltage level;

23

- c) a data input terminal for receiving a write data input signal; and
- d) a data input buffer including a comparator circuit coupled to the data input terminal and the reference voltage input terminal, and
 - i) when the mode selection signal is at the first logic level, the data input buffer is configured to compare the write data input signal to the input reference voltage level in providing a buffered data input signal; and
 - ii) when the mode selection signal is at the second logic level, the data input buffer is configured to provide the buffered data input signal independent of the input reference voltage level.

4. The memory device as claimed in claim 3 wherein the data input buffer further includes a buffer circuit having a single input coupled to the data input terminal.

5. The memory device as claimed in claim 4 wherein the comparator circuit is disabled when the mode selection signal is at the second logic level, and the buffer circuit is disabled when the mode selection signal is at the first logic level.

6. The memory device as claimed in claim 4 wherein the data input buffer further comprises a multiplexer circuit coupled to the output of the comparator circuit and the output of the buffer circuit, the multiplexer circuit being configured to provide a signal from the comparator circuit as the buffered data input signal when the mode selection signal is at the first logic level, and the multiplexer circuit being further configured to provide a signal from the buffer circuit as the buffered data input signal when the mode selection signal is at the second logic level.

7. The memory device as claimed in claim 3 wherein the mode selection circuit is configured to determine a state of the mode selection signal based on the voltage level received on a mode selection input terminal, and the mode selection input terminal is the reference voltage input terminal.

8. The memory device as claimed in claim 7 wherein the mode selection signal is at the second logic level when the input reference level is Vss.

9. The memory device as claimed in claim 3 wherein the data input terminal is configured to receive command signals.

10. The memory device as claimed in claim 3 wherein the write data input signal is a double data rate signal.

11. The memory device as claimed in claim 3 wherein the write data input signal is an SSTL signal in a high speed mode of operation.

12. The memory device as claimed in claim 3 wherein the write data input signal is an HSTL signal in a high speed mode of operation.

13. The memory device as claimed in claim 3 wherein the write data input signal is an LVTTTL signal or an un-terminated low voltage CMOS signal in a low speed mode of operation.

14. The memory device as claimed in claim 3 wherein the mode selection circuit is configured to determine a state of the mode selection signal based on the voltage level received on a mode selection input terminal.

15. A memory device comprising:

- a. a mode selection circuit for providing a mode selection signal, the memory device being configured for high speed operation as determined by the mode selection signal being at a first logic level, and the memory device being further configured for low speed operation as determined by the mode selection signal being at a second logic level;
- b. a positive clock input terminal for receiving a positive clock input signal;

24

- c. a negative clock input terminal for receiving a negative clock input signal; and
- d. circuitry including a comparator circuit coupled to the positive clock input terminal and the negative clock input terminal, and
 - i) when the mode selection signal is at the first logic level, the comparator circuit is configured to compare the positive clock input signal to the negative clock input signal in providing a buffered clock input signal; and
 - ii) when the mode selection signal is at a second logic level, the circuitry is configured to provide the buffered clock input signal based on either the positive clock input signal or the negative clock input signal.

16. The memory device as claimed in claim 15 wherein the circuitry further includes a first buffer circuit having a single input coupled to either the positive clock input terminal or the negative clock input terminal.

17. The memory device as claimed in claim 16 wherein the comparator circuit is disabled when the mode selection signal is at the second logic level and the first buffer circuit is disabled when the mode selection signal is at the first logic level.

18. The memory device as claimed in claim 16 wherein the circuitry further comprises a multiplexer circuit in communication with the output of the comparator circuit and coupled to the output of the first buffer circuit, and the multiplexer circuit being configured to provide a signal from the comparator circuit as the buffered clock input signal when the mode selection signal is at the first logic level, and the multiplexer circuit being further configured to provide a signal from the first buffer circuit as the buffered clock input signal when the mode selection signal is at the second logic level.

19. The memory device as claimed in claim 16 wherein the circuitry includes a second buffer circuit having a single input coupled to the one of the positive clock input terminal and the negative clock input terminal that is not coupled to the first buffer circuit, the second buffer circuit for providing an inverted buffered clock input signal when the mode selection signal is at a second logic level.

20. The memory device as claimed in claim 15 wherein the circuitry includes a delay locked loop coupled to the comparator to provide a phase shifted buffered clock input signal in connection with the high speed operation.

21. The memory device as claimed in claim 15 wherein the positive clock input signal and the negative clock input signal are SSTL signals in a high speed mode of operation.

22. The memory device as claimed in claim 15 wherein the positive clock input signal and the negative clock input signal are HSTL signals in a high speed mode of operation.

23. The memory device as claimed in claim 15 wherein at least one of the positive clock input signal and the negative clock input signal is an LVTTTL signal in a low speed mode of operation.

24. The memory device as claimed in claim 15 wherein at least one of the positive clock input signal and the negative clock input signal is an un-terminated low voltage CMOS signal in a low speed mode of operation.

25. A memory device comprising:

- a. a mode selection circuit for providing a mode selection signal;
- b. a clock input terminal for receiving a clock input signal;
- c. a clock output terminal for providing a clock output signal;
- d. a data output terminal for providing a read data output signal;

25

- e. circuitry including an input buffer coupled to the clock input terminal for providing a buffered clock input signal;
 - f. an output latch for latching internal read data on edges of the buffered clock input signal;
 - g. a data output buffer circuit coupled to the data output terminal, the data output buffer circuit also coupled to the output latch in order to enable the data output terminal to provide the read data output signal; and
 - h. a clock output buffer circuit operatively coupled to the buffered clock input signal and enabled by the mode select signal in a high speed mode of operation to provide a source synchronous clock output signal while read data is provided on the data output terminal and disabled by the mode select signal in a low speed mode of operation.
- 26.** The memory device as claimed in claim **25** wherein the data output buffer circuit has configurable drive strength.
- 27.** The memory device as claimed in claim **25** wherein the data output buffer circuit has a drive strength configurable by the mode selection signal.
- 28.** The memory device as claimed in claim **25** further comprising a data input terminal for receiving command and

26

address information, the data output buffer circuit capable of providing the command and address information on the data output terminal.

29. The memory device as claimed in claim **25** wherein the circuitry includes a delay locked loop coupled to the input buffer to provide a phase shifted buffered clock input signal.

30. The memory device as claimed in claim **25** wherein the read data output signal is a double data rate signal.

31. The memory device as claimed in claim **25** wherein the read data output signal and the clock output signal are SSTL signals in the high speed mode of operation.

32. The memory device as claimed in claim **25** wherein the read data output signal and the clock output signal are HSTL signals in the high speed mode of operation.

33. The memory device as claimed in claim **25** wherein the read data output signal is an LVTTL signal in the low speed mode of operation.

34. The memory device as claimed in claim **25** wherein the read data output signal is an un-terminated low voltage CMOS signal in the low speed mode of operation.

35. The memory device as claimed in claim **25** wherein the clock output buffer circuit provides the buffered clock input signal on the clock output terminal while in the high speed mode of operation.

* * * * *