


(19) **United States**(12) **Patent Application Publication**
Rofougaran et al.(10) **Pub. No.: US 2007/0127590 A1**(43) **Pub. Date: Jun. 7, 2007**(54) **SYSTEM AND METHOD PROVIDING
SIGNAL COMBINING TO SUPPORT
MULTIMODE COMMUNICATION****Publication Classification**(51) **Int. Cl.**
H04B 15/00 (2006.01)(52) **U.S. Cl.** **375/285**(76) Inventors: **Ahmadreza Rofougaran**, Newport
Coast, CA (US); **Arya Behzad**, Poway,
CA (US)Correspondence Address:
MCANDREWS HELD & MALLOY, LTD
500 WEST MADISON STREET
SUITE 3400
CHICAGO, IL 60661(21) Appl. No.: **11/376,643**(22) Filed: **Mar. 15, 2006****Related U.S. Application Data**(60) Provisional application No. 60/741,572, filed on Dec.
1, 2005.(57) **ABSTRACT**

A system and method providing signal combining to support multimode communication. Various aspects of the present invention may provide a first input adapted to receive a first baseband signal corresponding to a first communication protocol. A second input may be provided, which is adapted to receive a second baseband signal corresponding to a second communication protocol. A spectral placement module may, for example, be adapted to spectrally shift the first baseband signal. For example, the spectral placement module may be adapted to spectrally shift the first baseband signal to one or more frequency bands substantially distinct from one or more frequency bands associated with the second baseband signal. The spectrally shifted first baseband signal and the second baseband signal, which may also be spectrally shifted, may then be combined to form a composite signal.






Figure 1




Figure 2




Figure 3




Figure 4




Figure 5




Figure 6




Figure 7




Figure 8

SYSTEM AND METHOD PROVIDING SIGNAL COMBINING TO SUPPORT MULTIMODE COMMUNICATION

CROSS-REFERENCE TO RELATED APPLICATIONS/INCORPORATION BY REFERENCE

[0001] This patent application is related to and claims priority from provisional patent application Ser. No. 60/741,522, filed Dec. 1, 2005, entitled "SYSTEM AND METHOD PROVIDING SIGNAL COMBINING TO SUPPORT MULTIMODE COMMUNICATION," the contents of which are hereby incorporated herein by reference in their entirety.

FEDERALLY SPONSORED RESEARCH OR DEVELOPMENT

[0002] [Not Applicable]

SEQUENCE LISTING

[0003] [Not Applicable]

MICROFICHE/COPYRIGHT REFERENCE

[0004] [Not Applicable]

BACKGROUND OF THE INVENTION

[0005] Communication devices (e.g., mobile communication devices) are continually increasing in popularity. Such communication devices include, for example and without limitation, cellular phones, paging devices, portable email devices, and personal digital assistants. Mobile communication devices, for example, provide the user with the capability to conduct communications while moving through a variety of environments.

[0006] Communication devices may operate in accordance with multiple communication modes. For example a mobile communication device may be adapted to operate in a cellular communication mode and a wireless computer network communication mode. Such multimode communication devices may utilize respective radio configurations for each communication mode. For example, various communication modes may correspond to different respective radios and/or different communication protocols.

[0007] Various communication modes may potentially operate in common frequency bands. Thus, the potential exists for transmissions (e.g., simultaneous transmissions) in various communication modes to interfere with each other. Further limitations and disadvantages of conventional and traditional approaches will become apparent to one of skill in the art, through comparison of such systems with the present invention as set forth in the remainder of the present application with reference to the drawings.

BRIEF SUMMARY OF THE INVENTION

[0008] Various aspects of the present invention provide a system and method providing signal combining to support multimode communication, substantially as shown in and/or described in connection with at least one of the figures, as set forth more completely in the claims. These and other advantages, aspects and novel features of the present invention, as

well as details of illustrative aspects thereof, will be more fully understood from the following description and drawings.

BRIEF DESCRIPTION OF SEVERAL VIEWS OF THE DRAWINGS

[0009] FIG. 1 is a diagram showing a portion of a first non-limiting exemplary communication system, in accordance with various aspects of the present invention.

[0010] FIG. 2 is a diagram showing a portion of a second non-limiting exemplary communication system, in accordance with various aspects of the present invention.

[0011] FIG. 3 is a diagram showing a portion of a third non-limiting exemplary communication system, in accordance with various aspects of the present invention.

[0012] FIG. 4 is a diagram showing a portion of a fourth non-limiting exemplary communication system, in accordance with various aspects of the present invention.

[0013] FIG. 5 is a diagram showing a portion of a fifth non-limiting exemplary communication system, in accordance with various aspects of the present invention.

[0014] FIG. 6 is a diagram showing a portion of a sixth non-limiting exemplary communication system, in accordance with various aspects of the present invention.

[0015] FIG. 7 is a diagram showing a portion of a seventh non-limiting exemplary communication system, in accordance with various aspects of the present invention.

[0016] FIG. 8 is a diagram illustrating a first non-limiting exemplary method for combining signals in support of multimode communications, in accordance with various aspects of the present invention.

DETAILED DESCRIPTION OF THE INVENTION

[0017] FIG. 1 is a diagram showing a portion of a first non-limiting exemplary communication system 100, in accordance with various aspects of the present invention. The communication system (or device) may comprise characteristics of any of a variety of communication systems/devices (e.g., multimode wireless communication devices). For example and without limitation, the communication system may comprise characteristics of any of a variety of mobile wireless communication devices (e.g., cellular phones, paging devices, portable email devices, etc.). Also for example, the communication system may comprise characteristics of fixed communication systems or devices (e.g., network access points, base stations, satellites, wireless routers, set top boxes, etc.). Further for example, the communication system may comprise characteristics of a variety of electronic devices with wireless communication capability (e.g., televisions, music players, cameras, remote controls, personal digital assistants, handheld computers, gaming devices, etc.). Accordingly, the scope of various aspects of the present invention should not be limited by characteristics of particular communication systems or devices.

[0018] The following discussion will, at times, refer to various communication modes. A multimode communication device may, for example, be adapted to communicate in

a plurality of such communication modes. For the following discussion, a communication mode may generally be considered to coincide with communication utilizing a particular communication protocol or standard. A non-limiting list of exemplary communication protocols includes various cellular communication protocols (e.g., GSM, GPRS, EDGE, CDMA, WCDMA, TDMA, PDC, etc.), various wireless networking protocols or standards, including WLAN, WMAN, WPAN and WWAN (e.g., IEEE 802.11, Bluetooth, IEEE 802.15, UWB, IEEE 802.16, IEEE 802.20, Zigbee, any WiFi protocol, etc.), various television communication standards, etc. The scope of various aspects of the present invention should not be limited by characteristics of particular communication modes or protocols, whether standard or proprietary.

[0019] The exemplary communication system 100 may comprise at least a first input 101 adapted to receive a first baseband signal. The first baseband signal may, for example, correspond to a first communication protocol (e.g., any of a variety of wireless communication protocols and/or standards). For example and without limitation, the first baseband signal may correspond to any of the previously mentioned communication protocols.

[0020] The exemplary communication system 100 may also comprise at least a second input 102 adapted to receive a second baseband signal. The second baseband signal may, for example, correspond to a second communication protocol (e.g., a second communication protocol different from the first communication protocol discussed above). For example and without limitation, the second baseband signal may correspond to any of the previously mentioned communication protocols.

[0021] The first baseband signal and the second baseband signal may, for example, be generated by one or more modules (i.e., hardware and/or software modules) of the communication system 100. For example, such modules may generate the first and second baseband signals independently (e.g., corresponding to independent respective communications). Alternatively, for example, such modules may generate the first and second baseband signals in a dependent manner (e.g., coordinating independent respective communications or utilizing both the first and second baseband signals for a single communication).

[0022] The exemplary communication system 100 may additionally comprise a spectral placement module 110 that is adapted to spectrally shift the first baseband signal (i.e., shift the frequency spectrum of the first baseband signal). In a non-limiting exemplary scenario, the spectral placement module 110 may be adapted to spectrally shift the first baseband signal by, at least in part, spectrally shifting the first baseband signal to one or more frequency bands that are substantially distinct from one or more frequency bands associated with the second baseband signal. Occupying such substantially distinct frequency bands, the spectrally shifted first baseband signal may, for example, be combined with the second baseband signal for simultaneous transmission with no interference, relatively little interference, or an acceptable level of interference.

[0023] In a non-limiting exemplary scenario, the spectral placement module 110 may be adapted to implement a frequency-hopping scheme with the first baseband signal. For example, in a scenario, where there are one or more

frequency bands (e.g., a second frequency space) associated with the second baseband signal, the spectral placement module 110 may be adapted to shift the first baseband signal to numerous consecutive frequency spaces (or bands) that are substantially distinct from the second frequency space.

[0024] In another non-limiting exemplary scenario, spectrally shifting the first baseband signal may result in the production of a spectral image (e.g., frequency content mirrored about a mixing frequency utilized to spectrally shift the first baseband signal). In such a scenario, the image may be accepted or rejected. A non-limiting example of such an image is illustrated in FIG. 2 and will be discussed later.

[0025] In a scenario where an image is produced, the spectral placement module 110 may be adapted to reject such an image (e.g., reject an upper or lower image). The spectral placement module 110 may be adapted to reject such an image in any of a variety of manners. For example and without limitation, the spectral placement module 110 may comprise an image reject mixer utilized to spectrally shift the first baseband signal. Such an image reject mixer generally spectrally shifts a signal and rejects an image associated with the spectrally shifted signal. An exemplary image reject mixer is illustrated in FIG. 3 and will be discussed later. Also for example, the spectral placement module 110 may utilize an image reject filter to remove an unwanted image. The scope of various aspects of the present invention should not be limited by the utilization of image rejection or by any particular manner of performing such image rejection.

[0026] The exemplary communication system 100 may also comprise a second spectral placement module 120. Such a second spectral placement module 120 may, for example, share any or all characteristics with the spectral placement module 110 discussed previously. The incorporation of such a second spectral placement module 120 may, for example, provide spectral shifting flexibility. For example, in such an exemplary configuration, either or both of the first and second baseband signals may be spectrally shifted to substantially distinct frequency spaces. Also for example, in such an exemplary configuration, either or both of the first and second baseband signals may be frequency hopped. Note that though the second spectral placement module 120 is illustrated separate from the first spectral placement module 110, the second spectral placement module 120 may share any or all hardware and/or software components with the spectral placement module 110.

[0027] The exemplary communication system 100 may further comprise a signal combiner 130 that is adapted to generate a composite signal comprising various input signals to the signal combiner 130. For example, the composite signal may simultaneously (i.e., at an instant in time) comprise components associated with various input signals. Note that such simultaneity need not always be present. For example, at a first instant in time, the signal output from the signal combiner 130 might comprise a plurality of components associated with a plurality of respective input signals, at a second instant in time, the signal output from the signal combiner 130 might comprise a single component associated with a single respective input signal, and at a third instant in time, the signal output from the signal combiner 130 might comprise no components.

[0028] In a first non-limiting exemplary scenario, the signal combiner 130 may receive a first signal that is based

on the first baseband signal (e.g., associated with a first communication protocol). Also, the signal combiner **130** may receive a second signal that is based on the second baseband signal (e.g., associated with a second communication protocol). In such a scenario, the signal combiner **130** may combine the first and second signals to generate a composite signal, where the composite signal simultaneously comprises a first signal component based on the first baseband signal and a second signal component based on the second baseband signal. In such a scenario, for example where the frequency spectra of the first and second baseband signals do not overlap, the first and second baseband signals might not be spectrally shifted prior to combining by the signal combiner **130**. In such a scenario, the spectral placement module **110** (and optionally, the second spectral placement module **120**) may receive a control signal indicating whether or not to perform spectral shifting and/or to what degree spectral shifting should be implemented.

[0029] In a second non-limiting exemplary scenario, the signal combiner **130** may receive a first signal from the spectral placement module **110** that is based on the spectrally shifted first baseband signal. Also, the signal combiner **130** may receive a second signal that is based on the second baseband signal. In such a scenario, the signal combiner **130** may combine the first and second signals to generate a composite signal, where the composite signal simultaneously comprises a first signal component based on the spectrally shifted first baseband signal and a second signal component based on the second baseband signal (e.g., not spectrally shifted).

[0030] In a third non-limiting exemplary scenario, the signal combiner **130** may receive a first signal from the spectral placement module **110** that is based on the spectrally shifted first baseband signal. Also, the signal combiner **130** may receive a second signal from the second spectral placement module **120** that is based on the spectrally shifted second baseband signal. In such a scenario, the signal combiner **130** may combine the first and second signals to generate a composite signal, where the composite signal simultaneously comprises a first signal component based on the spectrally shifted first baseband signal and a second signal component based on the spectrally shifted second baseband signal.

[0031] The exemplary communication system **100** may also comprise an upconverter **140** adapted to upconvert a signal (e.g., the composite signal from the signal combiner **130**) for transmission. As a non-limiting example, the upconverter **140** may receive a composite signal from the signal combiner **130**, where the composite signal comprises at least one component of a baseband signal. In such an example, the upconverter **140** may comprise upconverting (e.g., mixing) hardware adapted to convert the received composite signal to RF frequencies for subsequent transmission. Such conversion may, for example, comprise performing direct conversion or multi-stage conversion. The upconverter **140** may, for example, comprise various mixing, frequency generating and filtering components utilized for upconverting a communication signal to an RF frequency.

[0032] The exemplary communication system **100** may further comprise a RF transmission stage **150** adapted to transmit an RF signal. Such an RF signal may, for example,

be associated with the composite signal output from the signal combiner **130** and upconverted by the upconverter **140**. The RF transmission stage **150** may, for example and without limitation, comprise various power amplifier, filtering and antenna components utilized for transmission of an RF signal.

[0033] The exemplary communication system **100** (and most other communication systems illustrated and discussed herein) is shown with two input signals for the sake of illustrative clarity and not limitation. For example, various aspects of the present invention readily extend to three or more input signals (e.g., three or more baseband signals).

[0034] The exemplary communication system **100** (and most other communication systems illustrated and discussed herein) generally illustrate spectrally shifting one or more baseband signals and combining baseband signals into a composite signal for subsequent transmission. Note that various aspects of the present invention are readily extensible to spectrally shifting IF and/or RF signals, which are then combined into a composite signal for upconverting/transmission or for transmission. Accordingly, the scope of various aspects of the present invention should not be limited by characteristics of baseband signals or the processing thereof.

[0035] Various components of the exemplary communication system **100** (and other communication systems illustrated and discussed herein) may be implemented in analog and/or digital circuitry. To illustrate this, the exemplary communication system **100** is not shown with analog-to-digital converters (ADCs) or digital-to-analog converters (DACs). FIGS. 4-6, to be discussed later, show various non-limiting exemplary configurations including such converters.

[0036] FIG. 2 is a diagram showing a portion of a second non-limiting exemplary communication system **200**, in accordance with various aspects of the present invention. The communication system **200** may, for example and without limitation, share any or all characteristics with the communication system **100** illustrated in FIG. 1 and discussed previously.

[0037] The exemplary communication system **200** may comprise at least a first input **201** adapted to receive a first baseband signal. The first baseband signal may, for example, correspond to a first communication protocol (e.g., any of a variety of wireless communication protocols and/or standards). For example and without limitation, the first baseband signal may correspond to the Bluetooth communication protocol. FIG. 2 shows an exemplary frequency spectrum **203** associated with the first baseband signal.

[0038] The exemplary communication system **200** may also comprise at least a second input **202** adapted to receive a second baseband signal. The second baseband signal may, for example, correspond to a second communication protocol (e.g., a second communication protocol different from the first communication protocol discussed above). For example and without limitation, the first baseband signal may correspond to an IEEE 802.11 communication protocol (e.g., IEEE 802.11(b) or IEEE 802.11(g)). FIG. 2 shows an exemplary frequency spectrum **204** associated with the second baseband signal.

[0039] As with the exemplary communication system **100** discussed previously, the first baseband signal and the sec-

ond baseband signal may, for example, be generated by one or more modules (i.e., hardware and/or software modules) of the communication system 200. For example, such modules may generate the first and second baseband signals independently or in a dependent manner.

[0040] The exemplary communication system 200 may additionally comprise a spectral placement module 210 that is adapted to spectrally shift the first baseband signal (i.e., shift the frequency spectrum of the first baseband signal). For example and without limitation, the spectral placement module 210 may share any or all characteristics with the spectral placement module 110 discussed previously.

[0041] In a non-limiting exemplary scenario, the spectral placement module 210 may be adapted to spectrally shift the first baseband signal by a frequency f_s . FIG. 2 shows an exemplary frequency spectrum 211 associated with the spectrally shifted first baseband signal. The exemplary frequency spectrum 211 shows a lower spectral image 213 and an upper spectral image 212 associated with shifting the spectrum of the first baseband signal. As discussed previously with regard to FIG. 1, one of the images may be cancelled (e.g., by an image reject mixer or filter). In this particular example, the spectral placement module 210 may comprise an image reject mixer that rejects the lower spectral image 213.

[0042] The exemplary communication system 200 may further comprise a signal combiner 230 that is adapted to generate a composite signal comprising various input signals to the signal combiner 230. The signal combiner 230 may, for example and without limitation, share any or all characteristics with the signal combiner 130 discussed previously. For example, the composite signal may simultaneously comprise components associated with various input signals.

[0043] In a non-limiting exemplary configuration illustrated in FIG. 2, the signal combiner 230 receives a first signal from the spectral placement module 210 that is based on the spectrally shifted first baseband signal. Also, the signal combiner 230 receives a second signal that is based on the second baseband signal. In such a configuration, the signal combiner 230 combines the first and second signals to generate a composite signal, where the composite signal simultaneously comprises a first signal component based on the spectrally shifted first baseband signal and a second signal component based on the second baseband signal (e.g., not spectrally shifted).

[0044] FIG. 2 shows an exemplary frequency spectrum 231 associated with the composite signal formed by the signal combiner 230. The spectrum 231 comprises a first portion 233 corresponding to the first signal component, and a second portion 232 corresponding to the second signal component. Note that the first portion 233 occupies a frequency space (e.g., one or more frequency bands) that is distinct from the frequency space occupied by the second portion 232.

[0045] The exemplary communication system 200 may also comprise an upconverter 240 adapted to upconvert a signal (e.g., the composite signal from the signal combiner 230) for transmission. The upconverter 240 may, for example and without limitation, share any or all characteristics with the upconverter 140 discussed previously.

[0046] The upconverter 240 may, for example, comprise a mixer 247, a local oscillator 246 and one or more filters 248. The mixer 247 may, for example, receive the composite signal from the signal combiner 230 and an RF mixing signal at frequency f_{RF} from a local oscillator 246. The upconverter 240 may, for example, filter the upconverted signal from the mixer 247 with one or more filters 248. The output of the upconverter 240 may, for example, comprise a signal indicative of the composite signal spectrally shifted to an RF frequency.

[0047] FIG. 2 shows an exemplary frequency spectrum 241 associated with the RF signal formed by the upconverter 240. The frequency spectrum 241 comprises a first portion 243 corresponding to the first signal component and a second portion 242 corresponding to the second signal component. Note that the first portion 243 occupies a frequency space (e.g., one or more frequency bands) that is distinct from the frequency space occupied by the second portion 242. Also note that the first portion 243 and second portion 242 might be formed with a first mirror portion 244 and second mirror portion 245, respectively. Note that a mirror portion may either be removed or may be kept for later processing.

[0048] The exemplary communication system 200 may further comprise a RF transmission stage 250 adapted to transmit an RF signal. The RF transmission stage 250 may, for example and without limitation, share any or all characteristics with the RF transmission stage 150 discussed previously.

[0049] Such an RF signal may, for example, be associated with the composite signal output from the signal combiner 230 and upconverted by the upconverter 240. The RF transmission stage 250 may, for example and without limitation, comprise a power amplifier 252, antenna 254 and other components generally associated with RF signal transmission.

[0050] FIG. 3 is a diagram showing a portion of a third non-limiting exemplary communication system 300, in accordance with various aspects of the present invention. The exemplary communication system 300 may, for example and without limitation, share any or all characteristics with the exemplary communication systems 100, 200 discussed previously.

[0051] The exemplary communication system 300 may comprise a spectral placement module 310. The spectral placement module 310 may, for example and without limitation, share any or all characteristics with the exemplary spectral placement modules 110, 210 discussed previously.

[0052] The spectral placement module 310 comprises an image reject mixer. The spectral placement module 310 comprises a first mixer 311 that receives the “I” component of the first baseband signal (BB) and the “I” component of a mixing signal (IF). The output of the first mixer 311 may, for example, comprise a signal that is a function of $\cos(\omega_{BB}) \cdot \cos(\omega_{IF})$. The spectral placement module 310 may also comprise a second mixer 312 that receives the “Q” component of the first baseband signal (BB) and the “Q” component of the mixing signal (IF). The output of the second mixer 312 may, for example, comprise a signal that is a function of $\sin(\omega_{BB}) \cdot \sin(\omega_{IF})$. The outputs of the first mixer 311 and the second mixer 312 may then be combined with a first summer 313.

[0053] The spectral placement module 310 may also comprise a third mixer 315 that receives the “Q” component of the first baseband signal (BB) and the “I” component of the mixing signal (IF). The output of the third mixer 315 may, for example, comprise a signal that is a function of $\sin(\omega_{BB}) \cdot \cos(\omega_{IF})$. The spectral placement module 310 may also comprise a fourth mixer 316 that receives the “I” component of the first baseband signal (BB) and the “Q” component of the mixing signal (IF). The output of the fourth mixer 316 may, for example, comprise a signal that is a function of $\cos(\omega_{BB}) \cdot \sin(\omega_{IF})$. The outputs of the third mixer 315 and the fourth mixer 316 may then be combined with a second summer 317.

[0054] Note that operation of the image reject mixer may be adjusted to reject any image (e.g., an upper or lower image). For example, signs of the first and/or second adders 313, 317 or of other components or signals may be modified to reject the desired image.

[0055] The exemplary communication system 300 may comprise a signal combiner 330. The signal combiner 330 may, for example and without limitation, share any or all characteristics with the exemplary signal combiners 130, 230 discussed previously.

[0056] The signal combiner 330 may, for example, comprise a third summer 332, which sums the output signal from the first summer 313 and the “I” component of the second baseband signal. The signal combiner 330 may also, for example, comprise a fourth summer 334, which sums the output signal from the second summer 317 and the “Q” component of the second baseband signal.

[0057] As illustrated in FIG. 3, the first baseband signal and the second baseband signal may be separated into I and Q components. This principal also applies to all systems and methods discussed herein. For example, though the exemplary communication systems 100, 200 discussed previously each show one respective line for each of the first and second baseband signals and subsequent signals derived therefrom, such signals may readily be separated into I and Q components and processed individually.

[0058] As discussed briefly above, various portions of the exemplary communication systems and/or methods discussed herein may be implemented in the analog and/or digital domains. FIGS. 4-6, to be discussed next, present non-limiting examples of a variety of potential configurations.

[0059] FIG. 4 is a diagram showing a portion of a fourth non-limiting exemplary communication system 400, in accordance with various aspects of the present invention. The exemplary communication system 400 may, for example and without limitation, share any or all characteristics with the exemplary communication systems 100-300 illustrated in FIGS. 1-3 and discussed previously.

[0060] The exemplary communication system 400 may, for example, comprise a spectral placement module 410, an optional second spectral placement module 420, a signal combiner 430, an upconverter 440 and a RF transmission stage 450 similar in various respects to like-named components of exemplary systems 100-300 discussed previously. The exemplary communication system 400 may also comprise a digital-to-analog converter 480.

[0061] For example, the spectral placement module 410, optional second spectral placement module 420 and signal combiner 430 may operate in the digital domain. The digital-to-analog converter 480 may then convert the digital composite signal output from the signal combiner 430 to the analog domain. The upconverter 440 and RF transmission stage 450 may then perform their respective operations in the analog domain.

[0062] FIG. 5 is a diagram showing a portion of a fifth non-limiting exemplary communication system 500, in accordance with various aspects of the present invention. The exemplary communication system 500 may, for example and without limitation, share any or all characteristics with the exemplary communication systems 100-300 illustrated in FIGS. 1-3 and discussed previously.

[0063] The exemplary communication system 500 may, for example, comprise a spectral placement module 510, an optional second spectral placement module 520, a signal combiner 530, an upconverter 540 and a RF transmission stage 550 similar in various respects to like-named components of exemplary systems 100-400 discussed previously. The exemplary communication system 500 may also comprise a first digital-to-analog converter 592 and a second digital-to-analog converter 594.

[0064] For example, the spectral placement module 510, optional second spectral placement module 520 and signal combiner 530 may operate in the analog domain. The first digital-to-analog converter 592 may convert the first baseband signal to the analog domain for processing by the spectral placement module 510. The second digital-to-analog converter 594 may convert the second baseband signal to the analog domain for processing by the second spectral placement module 520 or signal combiner 530. The signal combiner 530 then combines signals in the analog domain to generate an analog composite signal, which is then upconverted and transmitted by the upconverter 540 and RF transmission stage 550, respectively.

[0065] As mentioned previously, various signals may, in various respective exemplary configurations, be characterized by baseband, IF and/or RF frequencies. FIG. 6 shows a non-limiting exemplary configuration where signals are converted to RF frequencies prior to the creation of the composite signal.

[0066] FIG. 6 is a diagram showing a portion of a sixth non-limiting exemplary communication system 600, in accordance with various aspects of the present invention. The exemplary communication system 600 may, for example and without limitation, share any or all characteristics with the exemplary communication systems 100-300 illustrated in FIGS. 1-3 and discussed previously.

[0067] The exemplary communication system 600 may, for example, comprise a spectral placement module 610, an optional second spectral placement module 620, a signal combiner 630, an upconverter 640 and a RF transmission stage 650 similar in various respects to like-named components of exemplary systems 100-500 discussed previously. The exemplary communication system 600 may also comprise a first digital-to-analog converter 692 and second digital-to-analog converter 694.

[0068] For example, the spectral placement module 610 and optional second spectral placement module 620 may

operate in the analog domain. The first digital-to-analog converter **692** may convert the first spectrally shifted baseband signal output from the spectral placement module **610** to the analog domain for processing by the combining module **630**. The second digital-to-analog converter **694** may convert the second baseband signal (or spectrally shifted second baseband signal) to the analog domain for processing by the signal combiner **630**. The signal combiner **630** then combines signals in the analog domain to generate an analog composite signal, which is then upconverted and transmitted by the upconverter **640** and RF transmission stage **650**, respectively.

[0069] As mentioned previously, various signals may, in various respective exemplary configurations, be characterized by baseband, IF and/or RF frequencies. FIG. 7 shows a non-limiting exemplary configuration where signals are converted to RF frequencies prior to the creation of the composite signal.

[0070] FIG. 7 is a diagram showing a portion of a seventh non-limiting exemplary communication system **700**, in accordance with various aspects of the present invention. The exemplary communication system **700** may, for example and without limitation, share any or all characteristics with the exemplary systems **100-600** illustrated in FIGS. 1-6 and discussed previously.

[0071] The exemplary communication system **700** may comprise a first mixer **744** that receives a spectrally shifted first baseband signal from the spectral placement module **710** and a first RF mixing signal (e.g., a 2.446 GHz signal generally associated with the Bluetooth communication protocol) from a first local oscillator **742**. The exemplary communication system **700** may also comprise a second mixer **748** that receives a second baseband signal (or a spectrally shifted second baseband signal) and a second RF mixing signal (e.g., a 2.486 GHz signal generally associated with the IEEE 802.11(g) communication protocol) from a second local oscillator **746**.

[0072] The exemplary communication system **700** may comprise an RF signal combiner **730** that is adapted to combine input RF signals. The RF signal combiner **730** may, for example, receive and combine the output signals from the first mixer **744** and second mixer **748** to generate an RF composite signal. The exemplary communication system **700** may also comprise a RF transmission stage **750** that receives the RF composite signal from the RF signal combiner **730** and transmit the signal.

[0073] The exemplary communication systems **100-700** illustrated in FIGS. 1-7 and discussed previously provided non-limiting exemplary illustrations of various aspects of the present invention. Accordingly, the scope of various aspects of the present invention should not be limited by particular characteristics of the exemplary communication systems **100-700**.

[0074] For illustrative clarity, the exemplary systems **100-700** illustrated in FIGS. 1-7 were presented in terms of various functional modules. Various modules may, for example, be implemented in hardware, software or a combination thereof. Various modules may, for example, be implemented in a single integrated circuit or a combination of integrated circuits. Also, various modules may share various sub-modules and/or subcomponents. For example

and without limitation, various hardware modules may share various electrical components, and various software modules may share various software subroutines. Accordingly, the scope of various aspects of the present invention should not be limited by characteristics of any particular hardware and/or software implementation or by any arbitrary boundaries between various functional modules.

[0075] Also for illustrative clarity, various signals (or associated pathways) were represented in the exemplary systems **100-700** utilizing single lines and were generally referred to as "signals." It should be noted that such signals may be complex or real, depending on the particular implementation. For example and without limitation, with reference to FIG. 2, the input signal to the upconverter **240** may be complex, the local oscillator **246** may output a complex signal, and the signal output from the upconverter **240** to the RF transmission stage **250** may be real. Also for example, the respective input signals to the upconverters illustrated in FIGS. 2-7 may be complex, and the respective signals output from such upconverters may be real. Further for example, referring to FIG. 7, the input signals to the first mixer **744** and second mixer **748** (including the signals from the first local oscillator **742** and second local oscillator **746**) may be complex. Still further for example, the output signals from the exemplary spectral placement modules of FIGS. 1-7 may be complex. Accordingly, the scope of various aspects of the present invention should not be limited by real or complex characteristics of one or more particular signals.

[0076] FIG. 8 is a diagram illustrating a first non-limiting exemplary method **800** for combining signals in support of multimode communications, in accordance with various aspects of the present invention. The exemplary method **800** may share any or all functional characteristics with the exemplary systems **100-700** illustrated in FIGS. 1-7 and discussed previously.

[0077] The exemplary method **800** may begin executing at step **805**. The exemplary method **800** (and all methods discussed herein) may begin executing for any of a variety of reasons. For example and without limitation, the exemplary method **800** may begin executing in response to a user input, a power-up condition or a reset condition. Also for example, the exemplary method **800** may begin executing in response to a detected event (e.g., a timer expiration, detected signal, detected network access point, system command, etc.). Further for example, the exemplary method **800** may begin executing in response to a determination to communicate in a plurality of communication modes simultaneously. Still further for example, the exemplary method **800** may begin executing in response to a determination to utilize bandwidth in a plurality of communication systems for a single communication or multiple communications. Accordingly, the scope of various aspects of the present invention should not be limited by characteristics of any particular initiating cause or condition.

[0078] The exemplary method **800** may, at step **810**, comprise generating and/or receiving a first baseband signal corresponding to a first communication protocol. Step **810** may, for example and without limitation, share any or all functional characteristics with the first input **101** of the exemplary system **100** illustrated in FIG. 1 and discussed previously.

[0079] The first baseband signal may, for example, correspond to a first communication protocol (e.g., any of a

variety of wireless communication protocols and/or standards). In an exemplary scenario where step **810** comprises receiving the first baseband signal, step **810** may comprise receiving the first baseband signal in any manner generally associated with receiving a baseband signal.

[**0080**] The first baseband signal may, for example, be generated by one or more modules (i.e., hardware and/or software modules) of a communication system implementing the exemplary method **800**. Step **810** may, for example, comprise generating the first baseband signal independently (e.g., corresponding to an independent communication). Step **810** may alternatively, for example, comprise generating the first baseband signal in a dependent manner (e.g., coordinating independent respective communications or utilizing both the first baseband signal and other baseband signals for a single communication).

[**0081**] The exemplary method **800** may, at step **820**, comprise spectrally placing (or shifting) the first baseband signal (e.g., received at step **810**). Step **820** may, for example and without limitation, share any or all functional characteristics with the spectral placement modules **110-710** of the exemplary systems **100-700** illustrated in FIGS. **1-7** and discussed previously.

[**0082**] Step **820** may, for example, comprise spectrally shifting the first baseband signal by, at least in part, spectrally shifting the first baseband signal to one or more frequency bands that are substantially distinct from one or more frequency bands associated with a second baseband signal. Occupying such substantially distinct frequency bands, the spectrally shifted first baseband signal may, for example, be combined with the second baseband signal for simultaneous transmission with no interference, relatively little interference, or an acceptable level of interference.

[**0083**] In a non-limiting exemplary scenario, step **820** may comprise implementing a frequency-hopping scheme with the first baseband signal. For example, in a scenario where there are one or more frequency bands (e.g., a second frequency space) associated with a second baseband signal, step **820** may comprise spectrally shifting the first baseband signal to numerous consecutive frequency spaces (or bands) that are substantially distinct from the second frequency space.

[**0084**] In another non-limiting exemplary scenario, spectrally shifting the first baseband signal may result in the production of a spectral image (e.g., frequency content mirrored about a mixing frequency utilized to spectrally shift the first baseband signal). In such a scenario, step **820** may comprise accepting or rejecting the image.

[**0085**] In a scenario where an image is rejected, step **820** may comprise rejecting the image in any of a variety of manners. For example and without limitation, step **820** may comprise performing image reject mixing to spectrally shift the first baseband signal. Such image reject mixing generally comprises spectrally shifting a signal and rejecting an image associated with the spectrally shifted signal. Also for example, step **820** may comprise filtering out an unwanted image. The scope of various aspects of the present invention should not be limited by the utilization of image rejection or by any particular manner of performing such image rejection.

[**0086**] The exemplary method **800** may, at step **830**, comprise generating and/or receiving a second baseband

signal corresponding to a second communication protocol (e.g., different from the first communication protocol). Step **830** may, for example and without limitation, share any or all functional characteristics with the second input **102** of the exemplary system **100** illustrated in FIG. **1** and discussed previously.

[**0087**] The second baseband signal may, for example, correspond to a second communication protocol (e.g., any of a variety of wireless communication protocols and/or standards). In an exemplary scenario where step **830** comprises receiving the second baseband signal, step **830** may comprise receiving the second baseband signal in any manner generally associated with receiving a baseband signal.

[**0088**] The second baseband signal may, for example, be generated by one or more modules (i.e., hardware and/or software modules) of a communication system implementing the exemplary method **800**. Step **830** may, for example, comprise generating the second baseband signal independently (e.g., corresponding to a communication independent of a communication associated with the first baseband signal). Step **830** may alternatively, for example, comprise generating the second baseband signal in a dependent manner (e.g., coordinating independent respective communications or utilizing both the second baseband signal and the first baseband signal for a single communication).

[**0089**] The exemplary method **800** may, at step **840**, in various optional exemplary scenarios, comprise spectrally shifting the second baseband signal (e.g., at received at step **830**). Step **840** may, for example and without limitation, share any or all functional characteristics with step **820** and/or the second spectral placement modules **120-720** of the exemplary systems **100-700** illustrated in FIGS. **1-7** and discussed previously.

[**0090**] Performing step **840** may, for example, provide spectral shifting flexibility. For example, by performing step **840**, or providing the option to perform step **840**, either or both of the first and second baseband signals may be spectrally shifted to substantially distinct frequency spaces. Also for example, in such an exemplary scenario, either or both of the first and second baseband signals may be frequency hopped.

[**0091**] The exemplary method **800** may, at step **850**, comprise generating a composite signal comprising a first simultaneous component based on the first baseband signal and a second simultaneous component based on the second baseband signal. Step **850** may, for example and without limitation, share any or all characteristics with the exemplary signal combiners **130-730** of the exemplary systems **100-700** illustrated in FIGS. **1-7** and discussed previously.

[**0092**] In a first non-limiting exemplary scenario, steps **820** and **840** do not spectrally shift the first and second baseband signals. In such an exemplary scenario, step **850** may comprise combining the first baseband signal received or generated at step **810** with the second baseband signal received or generated at step **830**. Step **850** may thus comprise generating a composite signal that simultaneously comprises a first signal component based on the first baseband signal and a second signal component based on the second baseband signal. In such an exemplary scenario, for example where the frequency spectra of the first and second baseband signals do not overlap, the first and second baseband signals might not be spectrally shifted prior to combining at step **850**.

[0093] In a second non-limiting exemplary scenario, step 840 might not be performed. In such an exemplary scenario, step 850 may comprise combining the first baseband signal received or generated at step 810 and spectrally shifted at step 820 with the second baseband signal received or generated at step 830. Step 850 may thus comprise generating a composite signal that simultaneously comprises a first signal component based on the spectrally shifted first baseband signal and a second signal component based on the second baseband signal (e.g., not spectrally shifted).

[0094] In a third non-limiting exemplary scenario, both spectrum-shifting steps 820 and 840 might be performed. In such an exemplary scenario, step 850 may comprise combining the first baseband signal received or generated at step 810 and spectrally shifted at step 820 with the second baseband signal received or generated at step 830 and spectrally shifted at step 840. Step 850 may thus comprise generating a composite signal that simultaneously comprises a first signal component based on the spectrally shifted first baseband signal and a second signal component based on the spectrally shifted second baseband signal.

[0095] The exemplary method 800 may, at step 895, comprise performing any of a large variety of continued processing. For example and without limitation, step 895 may comprise performing various operations associated with communicating the composite signal formed at step 850. Such operations may, for example, comprise upconverting and transmitting the composite signal. Step 895 may, for example, share various functional characteristics with the upconverters 140-740 and RF transmission stages 150-750 discussed previously.

[0096] Also for example, step 895 may comprise directing execution flow of the exemplary method 800 back up to previously discussed steps (e.g., for generating/receiving additional signals or for performing additional spectral placement operations). The scope of various aspects of the present invention should not be limited by characteristics of any particular continued processing.

[0097] The exemplary method 800 was presented with two baseband signals for the sake of illustrative clarity and not limitation. For example, various aspects of the present invention readily extend to three or more input signals. Additionally, as discussed previously with regard to the exemplary communication systems 100-700, various aspects of the exemplary method 800 may be implemented in the analog and/or digital domains.

[0098] The exemplary method 800 also generally comprises spectrally shifting one or more baseband signals and combining baseband signals into a composite signal for subsequent transmission. Note that various aspects of the present invention are readily extensible to spectrally shifting IF and/or RF signals, which are then combined into a composite signal for upconverting/transmission or for transmission. Accordingly, the scope of various aspects of the present invention should not be limited by characteristics of baseband signals or the processing thereof.

[0099] The exemplary method 800 was presented to provide non-limiting examples of various aspects of the present invention. Accordingly, the scope of various aspects of the present invention should not be limited by specific characteristics of the exemplary method 800.

[0100] In summary, various aspects of the present invention provide a system and method providing signal combining to support multimode communication. While the invention has been described with reference to certain aspects and embodiments, it will be understood by those skilled in the art that various changes may be made and equivalents may be substituted without departing from the scope of the invention. In addition, many modifications may be made to adapt a particular situation or material to the teachings of the invention without departing from its scope. Therefore, it is intended that the invention not be limited to the particular embodiment disclosed, but that the invention will include all embodiments falling within the scope of the appended claims.

What is claimed is:

1. A multimode communication system comprising:

at least a first module adapted to:

generate a first baseband signal corresponding to a first communication protocol; and

generate a second baseband signal corresponding to a second communication protocol different from the first communication protocol; and

at least a second module adapted to:

receive the first baseband signal;

receive the second baseband signal; and

generate a composite signal comprising, at an instant in time, a first component based on the first baseband signal, and a second component based on the second baseband signal.

2. The multimode communication system of claim 1, wherein the at least a second module is further adapted to spectrally shift the first baseband signal, and wherein the first component is based on the spectrally-shifted first baseband signal.

3. The multimode communication system of claim 2, wherein the at least a second module is further adapted to spectrally shift the second baseband signal, and wherein the second component is based on the spectrally-shifted second baseband signal.

4. The multimode communication system of claim 2, wherein the at least a second module is adapted to spectrally shift the first baseband signal by, at least in part, spectrally shifting the first baseband signal to one or more frequency bands substantially distinct from one or more frequency bands associated with the second baseband signal.

5. The multimode communication system of claim 4, wherein the at least a second module is further adapted to spectrally shift the first baseband signal by, at least in part, frequency hopping the first baseband signal to one or more frequency bands substantially distinct from one or more frequency bands associated with the second baseband signal.

6. The multimode communication system of claim 2, wherein the at least a second module is adapted to spectrally shift the first baseband signal by, at least in part, rejecting an image associated with spectrally shifting the first baseband signal.

7. The multimode communication system of claim 6, wherein the at least a second module comprises an image-reject mixer that is adapted to spectrally shift the first baseband signal.

8. The multimode communication system of claim 6, wherein the at least a second module comprises an image-reject filter that is adapted to remove the image associated with spectrally shifting the first baseband signal.

9. The multimode communication system of claim 2, wherein the first baseband signal, second baseband signal and composite signal are digital signals.

10. The multimode communication system of claim 2, wherein the first baseband signal, second baseband signal and composite signal are analog signals.

11. The multimode communication system of claim 2, wherein the first communication protocol is based on Bluetooth, and the second communication protocol is based on an IEEE 802.11 standard.

12. The multimode communication system of claim 2, wherein the composite signal comprises a baseband signal.

13. The multimode communication system of claim 2, wherein the composite signal comprises an IF signal.

14. The multimode communication system of claim 2, wherein the composite signal comprises an RF signal.

15. The multimode communication system of claim 14, wherein the at least a second module is adapted to generate the composite signal by, at least in part, upconverting to RF a single signal comprising components associated with the first component and the second component.

16. The multimode communication system of claim 14, wherein the at least a second module is adapted to generate the composite signal by, at least in part:

upconverting to RF a first signal associated with the first component;

upconverting to RF a second signal associated with the second component; and

combining the upconverted first and second signals.

17. In a multimode communication system, a method for communicating in multiple communication modes simultaneously, the method comprising:

generating a first baseband signal corresponding to a first communication protocol;

generating a second baseband signal corresponding to a second communication protocol that is different from the first communication protocol; and

generating a composite signal comprising, at an instant in time, a first component based on the first baseband signal and a second component based on the second baseband signal.

18. The method of claim 17, wherein generating a composite signal comprises generating the first component by, at least in part, spectrally shifting the first baseband signal.

19. The method of claim 18, wherein generating a composite signal further comprises generating the second component by, at least in part, spectrally shifting the second baseband signal.

20. The method of claim 18, wherein spectrally shifting the first baseband signal comprises spectrally shifting the first baseband signal to one or more frequency bands substantially distinct from one or more frequency bands associated with the second baseband signal.

21. The method of claim 20, wherein spectrally shifting the first baseband signal comprises frequency hopping the first baseband signal to one or more frequency bands substantially distinct from one or more frequency bands associated with the second baseband signal.

22. The method of claim 18, wherein spectrally shifting the first baseband signal comprises rejecting an image associated with spectrally shifting the first baseband signal.

23. The method of claim 22, wherein rejecting an image associated with spectrally shifting the first baseband signal comprises utilizing an image reject mixer to spectrally shift the first baseband signal.

24. The method of claim 22, wherein rejecting an image associated with spectrally shifting the first baseband signal comprises utilizing an image reject filter to remove the image.

25. The method of claim 18, wherein the first baseband signal, second baseband signal and composite signal are digital signals.

26. The method of claim 18, wherein the first baseband signal, second baseband signal and composite signal are analog signals.

27. The method of claim 18, wherein the first communication protocol is based on Bluetooth, and the second communication protocol is based on an IEEE 802.11 standard.

28. The method of claim 18, wherein the composite signal comprises a baseband signal.

29. The method of claim 18, wherein the composite signal comprises an IF signal.

30. The method of claim 18, wherein the composite signal comprises an RF signal.

31. The method of claim 30, wherein generating a composite signal comprises upconverting to RF a single signal comprising components associated with the first component and the second component.

32. The method of claim 30, wherein generating a composite signal comprises:

upconverting to RF a first signal associated with the first component;

upconverting to RF a second signal associated with the second component; and

combining the upconverted first and second signals.

33. A module for utilization in a multimode communication system, wherein the module is at least adapted to:

receive a first signal associated with a first communication protocol;

receive a second signal associated with a second communication protocol different from the first communication protocol; and

generate a composite signal comprising, at an instant in time, a first component based on the first signal, and a second component based on the second signal.

34. The module of claim 33, wherein the module is further adapted to spectrally shift the first signal, and wherein the first component is based on the spectrally shifted first signal.

* * * * *