


Silicon Processing

for the VLSI Era

Volume 4 - Deep-Submicron Process Technology



S. Wolf

**SILICON PROCESSING
FOR
THE VLSI ERA**

**VOLUME 4:
DEEP-SUBMICRON PROCESS TECHNOLOGY**

**SILICON PROCESSING
FOR
THE VLSI ERA**

**VOLUME 4:
DEEP-SUBMICRON
PROCESS TECHNOLOGY**

STANLEY WOLF Ph.D.

LATTICE PRESS

Sunset Beach, California

DISCLAIMER

This publication is based on sources and information believed to be reliable, but the authors and Lattice Press disclaim any warranty or liability based on or relating to the contents of this publication.

Published by:

LATTICE PRESS

Post Office Box 340

Sunset Beach, California 90742, U.S.A.

Cover design by: S. C. Ross Wolf.

Copyright © 2002 by Lattice Press.

All rights reserved. No part of this book may be reproduced or transmitted in any form or by any means, electronic or mechanical, including photocopying, recording or by any information storage and retrieval system without written permission from the publisher, except for the inclusion of brief quotations in a review.

Library of Congress Cataloging in Publication Data

Wolf, Stanley

Silicon Processing for the VLSI Era

Volume 4: Deep-Submicron Process Technology

Includes Index

1. Integrated circuits-Very large scale integration. 2. Silicon. I. Title

ISBN 0-9616721-7-X

9 8 7 6 5 4 3 2 1

PRINTED IN THE UNITED STATES OF AMERICA

MASTER TABLE OF CONTENTS

PREFACE

Chap. 1 - THE EVOLUTION OF THE STRUCTURE OF MOSFETS	1
Chap. 2 - 300-MM SILICON WAFERS	17
Chap. 3 - GATE DIELECTRICS: THIN GATE OXIDES	75
Chap. 4 - HIGH-<i>k</i> DIELECTRICS	145
Chap. 5 - THE STRUCTURE OF DEEP-SUBMICRON MOSFETS: Retrograde-Wells; Super-Steep Retrograde Channel Doping; Drain Engineering; Punchthrough-Control Implants	181
Chap. 6 - DEEP-SUBMICRON LITHOGRAPHY I: PHOTORESISTS	227
Chap. 7 - DEEP-SUBMICRON LITHOGRAPHY II: OPTICS AND HARDWARE	259
Chap. 8 - CHEMICAL MECHANICAL POLISHING (CMP)	313
Chap. 9 - SHALLOW TRENCH ISOLATION (STI)	433
Chap. 10 - SILICON-GERMANIUM (Si-Ge) TECHNOLOGY FOR HIGH-PERFORMANCE TELECOMMUNICATIONS ICs	475
Chap. 11 - SILICON-ON-INSULATOR (SOI) TECHNOLOGY	501
Chap. 12 - MULTILEVEL INTERCONNECTS FOR ULSI	573
Chap. 13 - POLYCIDES AND SALICIDES OF TiSi_2, CoSi_2 AND NiSi	603
Chap. 14 - LOW-<i>k</i> DIELECTRICS	639
Chap. 15 - DUAL-DAMASCENE INTERCONNECTS	671
Chap. 16 - COPPER INTERCONNECT PROCESS TECHNOLOGY	711
INDEX	795

DETAILED TABLE OF CONTENTS

PREFACE

Chap. 1 - THE EVOLUTION OF THE STRUCTURE OF MOSFETS **1**

1.1 THE STRUCTURE OF DEEP-SUBMICRON MOSFETS: (0.25- μm to 0.13- μm) - COMPARED TO THE STRUCTURE OF "CONVENTIONAL" MOSFETS (2.0- μm to 0.5- μm)	2
1.1.1 Evolution of the MOSFET Gate Stack and Contact Structure	
1.1.2 Gate Dielectric Materials in Deep-Submicron MOSFETs	
1.1.3 Doping-Concentration Profiles of the MOSFET Channel	
1.1.4 Evolution of the Drain Structure of MOSFETs	
1.2 DEEP-SUBMICRON CMOS STRUCTURES	10
1.2.1 Substrate Issues for Deep-Submicron CMOS	
1.2.2 Well Formation in Deep-Submicron CMOS	
1.2.3 Dual-Doped Poly in Deep-Submicron CMOS	
1.2.4 Shallow Trench Isolation for Deep-Submicron CMOS	
1.2.5 Silicon-On-Insulator (SOI) Technology	
1.3 LIMITS TO CONVENTIONAL MOSFET SCALING	15
REFERENCES	16

Chap. 2 - 300-MM SILICON WAFERS **17**

2.1 300-mm SILICON CRYSTAL GROWTH	17
2.2 GROWN-IN SILICON DEFECTS:	21
CRYSTAL-ORIGINATED-PARTICLES (COPS) & DISLOCATION LOOPS	
2.3 DETAILS OF THE FORMATION OF CRYSTAL-ORIGINATED-PARTICLES (COPS)	23
2.3.1 The Radial Distribution of Grown-In Defects on the Wafer Surface	
2.4 THE OXYGEN-STACKING-FAULT RING (OSF-RING)	26
2.5 MITIGATING EFFECTS OF COPS BY USE OF POST-CRYSTAL-GROWTH ANNEALING	27
2.6 ELIMINATION OF COPS WITH "PERFECT-SILICON"	29

2.7 MINIMIZING PERFORMANCE-DEGRADATION CAUSED BY COPS THROUGH THE USE OF HIGH-PULL-SPEED SILICON	30
2.8 GETTERING FOR ULSI PROCESSES	32
2.8.1 Basic Gettering Principles	
2.8.2 Extrinsic Gettering	
2.8.3 Intrinsic Gettering	
2.8.4 Gettering with Oxygen Precipitates	
2.8.5 Summary of Gettering	
2.9 STATUS OF SILICON WAFER TECHNOLOGY & FUTURE TRENDS	45
2.9.1 Epitaxy-Optimized Substrate (EOS) Wafers	
2.9.2 Comparing the Grown-In Defect Characteristics of the "New" Wafers	
2.9.3 Gettering Methods & Denuded Zone Formation Techniques Used with the "New" Wafers	
2.9.3.1 "Magic DeNuded Zone"	
2.10 FROM INGOT TO FINISHED WAFER: SLICING, ETCHING, AND POLISHING	52
2.10.1 Ingot Evaluation	
2.10.2 Ingot Surface Grinding	
2.10.3 Grinding Flats or Notches on the Ingot for Orientation Purposes	
2.10.4 Sawing the Ingot into Slices (Wafers)	
2.10.5 Laser Marking the Wafers	
2.10.6 Lapping and Grinding the Wafers	
2.10.7 Removal of Surface Mechanical Damage by Chemical Etching	
2.10.8 Rounding the Wafer Edge (and Notch)	
2.10.9 Edge Polishing of the Wafers	
2.10.10 Chemical-Mechanical Polishing of the Wafers	
2.10.11 Cleaning the Wafers	
2.10.12 Depositing Epitaxial Silicon Layers on the Wafers	
2.10.13 Shipping 300-mm Wafers: Its Impact on the Evolution of Wafer Shipping Boxes	
2.11 SPECIFICATIONS OF SILICON WAFERS FOR VLSI	63
2.12 THE ECONOMICS OF SILICON WAFERS	66
REFERENCES	69
Chap. 3 - GATE DIELECTRICS: THIN GATE OXIDES	75
3.1 REQUIRED CHARACTERISTICS OF GATE DIELECTRICS FOR DEEP-SUBMICRON MOSFETS	76
3.2 THE STRUCTURE OF THERMALLY GROWN SiO ₂ AND THE PROPERTIES OF THE Si/SiO ₂ INTERFACE	80

3.2.1 The Microscopic Structure of Thermally Grown SiO ₂	
3.2.2 The Si/SiO ₂ Interface	
3.2.2.1 Interface Trap Charge	
3.2.2.2 Effect of Interface Traps on IC Characteristics	
3.2.2.3 Oxide Trapped Charge	
3.2.2.3 Effect of Oxide Trapped Charge on Device Characteristics	
3.3 DIELECTRIC BREAKDOWN IN SILICON DIOXIDE FILMS	90
3.3.1 Electron Trapping in Silicon Dioxide;	
3.3.2 The Electric-Field Driven Model of Oxide Degradation (<i>E</i> Model)	
3.3.3 The Current-Driven Model of Oxide Degradation (1/ <i>E</i> Model)	
3.3.4 The Hole-Trapping Model that Describes How Holes are Injected & Trapped in SiO ₂	
3.3.5 Comparing the Electric-Field Driven and Current Driven Oxide Breakdown Models	
3.3.6 Time to Breakdown (T _{BD}) and Charge to Breakdown (Q _{BD})	
3.4 LEAKAGE CURRENTS IN SiO ₂ FILMS (TUNNELING PHENOMENA)	99
3.4.1 Fowler-Nordheim (FN) Tunneling (Tunneling Into Silicon Dioxide)	
3.4.2 Direct Tunneling (Tunneling Through Silicon Dioxide)	
3.5 MODELS OF THIN OXIDE GROWTH	104
3.6 SINGLE-WAFER TECHNOLOGY OF THIN OXIDE GROWTH	109
3.6.1 Rapid Thermal Oxidation Tools	
3.6.2 Wet RTO Processes	
3.7 NITRIDED & FLUORINATED OXIDES AS GATE DIELECTRICS	112
3.7.1 Oxynitridation of Silicon in N ₂ O	
3.7.2 Oxynitridation of Oxides in N ₂ O or NO	
3.7.3 Fluorinated Gate Oxides	
3.8 PROJECTIONS OF THICKNESS LIMITS OF GATE OXIDES	121
3.8.1 Minimum Oxide Thickness Due to Defects and Tunneling	
3.8.2 Minimum Oxide Thickness: Stress Induced Leakage Current (SILC)	
3.8.3 Soft-Breakdown of Oxide Films	
3.8.4 Impact of Polysilicon Depletion	
3.8.5 Impact of Process Induced Damage	
3.8.6 Summary of Oxide Thickness Projections	
3.9 MEASURING THIN GATE OXIDES	135
3.10 MANUFACTURING THIN GATE OXIDES	137
3.10.1 Process Control Issues of Growing Ultra-Thin Gate Oxides	
3.10.2 Thin Gate Dielectric Stacks Based on Silicon Dioxide	
REFERENCES	139

Chap. 4 - HIGH-<i>k</i> DIELECTRICS	145
4.1 HIGH- <i>k</i> DIELECTRICS AS THE GATE DIELECTRIC IN MOSFETS	145
4.1.1 Integrating High- <i>k</i> Dielectrics into MOSFET Structures:	
4.2 HIGH- <i>k</i> DIELECTRICS AS THE CAPACITOR DIELECTRIC IN DRAMS	150
4.3 HIGH- <i>k</i> DIELECTRICS FOR FeRAM APPLICATIONS	154
4.4 TANTALUM PENTOXIDE (Ta_2O_5)	154
4.4.1 Tantalum Pentoxide as a DRAM Capacitor Dielectric	
4.4.2 Tantalum Pentoxide as a MOSFET Gate Dielectric	
4.5 BARIUM STRONTIUM TITANATE (BST)	162
AS A DRAM CAPACITOR DIELECTRIC	
4.5.1 Deposition of BST Films by CVD	
4.5.2 Microstructure Effects on the Electrical Properties of BST	
4.5.3 BST Integration Issues	
4.6 USE OF OTHER HIGH- <i>k</i> MATERIALS AS GATE DIELECTRICS	169
4.6.1 Atomic Layer Deposition for Depositing Thin High- <i>k</i> Dielectric Films	
4.6.2 Aluminum Oxide (Al_2O_3) as a Gate Dielectric	
4.6.3 Zirconium Oxide (ZrO_2) as a Gate Dielectric	
4.6.4 Hafnium Oxide (HfO_2) as a Gate Dielectric	
4.6.5 Praseodymium Oxide (Pr_2O_3) as a High- <i>k</i> Gate Dielectric	
REFERENCES	177
Chap. 5 - THE STRUCTURE OF DEEP-SUBMICRON MOSFETS: Retrograde-Wells; Super-Steep Retrograde Channel Doping; Drain Engineering; Punchthrough-Control Implants	181
5.1 WELL-FORMATION IN DEEP-SUBMICRON CMOS	181
5.1.1 Retrograde-Wells for Deep Submicron CMOS	
5.1.2 Process Integration Issues Involving the Use of Retrograde-Wells	
5.2 SUPERSTEEP RETROGRADE CHANNEL (SSR) PROFILES	191
5.2.1 Fabricating SSR Profiles for Sub-0.1 μm MOSFETs	
5.3 SOURCE/DRAIN ENGINEERING IN DEEP-SUBMICRON CMOS	195
5.3.1 Parasitic Resistance of Deep-Submicron Source/Drains	
5.3.1.1 Physical Meaning of R_{ac} , R_{sp} , and R_{SDE}	
5.3.1.2 Comparing the Resistance of the SDE Region ($R_{sp} + R_{SDE}$) to R_{sat}	
5.3.1.3 Parasitic Resistance of the Deep Contact Region of the Drain R_{co}	
5.3.2 MOSFETs with Elevated Source/Drains	

5.3.2 MOSFETs with Elevated Source/Drains	
5.3.3 Shallow-Junction Formation for Deep-Submicron Source/Drains	
5.3.3.1 Ultra-Low-Energy Implants	
5.3.3.2 Transient-Enhanced Diffusion	
5.3.3.3 Rapid Thermal Annealing of Shallow Junctions	
5.3.3.4 Dopant Loss for Sub-keV Implants from Self-Sputtering, Out Diffusion, and Surface Oxide	
5.3.4 Effect of the Overlap of the SDE Region and Gate Edge on MOSFET Performance	
5.3.5 SDE Junction Lateral Abruptness	
5.4 ANTI-PUNCHTHROUGH STRUCTURES IN DEEP-SUBMICRON CMOS	219
REFERENCES	223

Chap. 6 - ADVANCED LITHOGRAPHY I: DEEP-SUBMICRON RESISTS 227

6.1 CHEMICALLY-AMPLIFIED DEEP-UV RESISTS FOR OPTICAL LITHOGRAPHY	227
6.1.1 248-nm Photoresists	
6.1.1.1 Amine-Contamination of DUV CA Resists	
6.1.1.2 Current State of 248-nm Resist Technology	
6.1.2 193-nm DUV Photoresists	
6.1.2.1 Problems of 193-nm Resists	
6.1.3 157-nm DUV Photoresists	
6.2 ANTI-REFLECTIVE COATING (ARCs)	244
6.2.1 Organic BARCs	
6.2.2 Inorganic Dielectric BARCs	
6.2.3 PVD-Deposited BARCs	
6.2.4 BARCs for Dual-Damascene Applications	
6.3 PHOTORESIST PROCESSING SYSTEMS	251
REFERENCES	257

Chap. 7 - ADVANCED LITHOGRAPHY II: OPTICS AND HARDWARE 259

7.1 EXCIMER LASER DEEP-UV LIGHT SOURCES	259
7.1.1 KrF Excimer Lasers	
7.1.2 ArF Excimer Lasers	
7.1.3 F ₂ Excimer Lasers	
7.2 EXPOSURE TOOLS For DUV LITHOGRAPHY	265
7.2.1 Exposure Tools for 248-nm Lithography	

7.2.2 Exposure Tools for 193-nm Lithography	
7.2.3 Exposure Tools for 157-nm Lithography	
7.2.4 Calcium Fluoride Optical Elements for DUV Lithography	
7.2.5 300-mm Lithography Tools	
7.2.6 Mix-an-Match Lithography	
7.3 RESOLUTION ENHANCEMENT TECHNOLOGIES (RETs)	274
7.3.1 Off-Axis Illumination	
7.3.2 Optical Proximity Correction (OPC)	
7.3.3 Phase Shift Masks (PSM)	
7.4 MASK ERROR FACTOR (MEF, or MEEF)	292
7.5 EXTENDING THE LIMITS OF OPTICAL LITHOGRAPHY	296
7.6 NON-OPTICAL (or NEXT GENERATION)	
LITHOGRAPHIC TECHNOLOGIES (NGL)	301
7.6.1 Extreme Ultra-Violet Reflective Projection Lithography (EUV)	
7.6.2 Electron Beam Projection Lithography (SCALPEL and PREVAIL)	
REFERENCES	309
Chap. 8 - CHEMICAL MECHANICAL POLISHING (CMP)	313
8.1 TERMINOLOGY AND EVOLUTION OF PLANARIZATION PROCESSES FOR ICS	313
8.1.1 Defining the Degree of Planarization	
8.1.2 The Need for Dielectric Planarization:	
8.1.3 Design Rules Related to Intermetal Dielectric-Formation and Planarization Processes	
8.1.4 Step-Height Reduction of Underlying Topography as a Technique to Alleviate the Need for Planarization	
8.1.5 Planarization through Sacrificial-Layer Etchback	
8.1.5.1 Sacrificial-Etchback Process Problems	
8.2 INTRODUCTION TO CHEMICAL MECHANICAL POLISHING (CMP)	322
8.3 THE TERMINOLOGY USED TO CHARACTERIZE CMP PROCESSES	325
8.3.1 CMP Removal Rate (RR)	
8.3.2 The Degree of Planarization (DOP)	
8.3.3 Within-Die Non-Uniformity (WIDNU)	
8.3.4 Within-Wafer Non-Uniformity (WIWNU)	
8.3.5 Wafer-to-Wafer Non-Uniformity (WTWNU)	
8.3.6 Efficiency of Planarization (EOP)	

8.5.1 The Mechanical Aspects of Silicon Dioxide Removal by CMP: (Preston's Law)	
8.5.1.1 Model of WIWNU Effects in Rotary CMP Tools Based on Preston's Law	
8.5.2 Models Which Describe Factors that Impact Oxide RR in CMP Through the Preston Constant	
8.5.2.1 Impact on the Oxide RR from the Electrochemical Interactions Between the Slurry Particles and the Oxide Surface	
8.5.2.2 Dependence of Oxide RR in CMP on Dielectric Hardness	
8.5.3 Models Which Describe Chemical-Mechanical Phenomena that Give Rise to Planarization Phenomena Associated with CMP of Oxides	
8.5.3.1 Model of the Mechanism That Produces Planarization of Steps in Oxide CMP	
8.5.3.2 Pattern Dependence of the Planarization Rate in CMP Processes	
8.5.4 Metal-CMP Mechanisms	
8.6 CMP EQUIPMENT	352
8.6.1 CMP Polishing Tools:	
8.6.1.1 CMP Polishing Tool Configurations	
8.6.1.2 Rotary CMP Tools:	
8.6.1.3 Orbital CMP Tools	
8.6.1.4 Linear CMP Tools	
8.6.1.5 Fixed Table CMP Tools	
8.6.1.6 300-mm CMP Tools	
8.6.2 Wafer-Carriers in CMP Polishing Tools (and the CMP Edge Effect)	
8.6.2.1 CMP Edge-Effect	
8.6.3 CMP Consumables (Slurries):	
8.6.3.1 Slurries for Oxide-CMP	
8.6.3.2 Slurries for Metal-CMP	
8.6.3.3 Multi-Step Slurries	
8.6.4 Slurry-Distribution Systems	
8.6.5 Environmental, Safety, and Handling Issues of CMP Slurries	
8.6.6 CMP Consumables (Polishing-Pads)	
8.6.7 Pad-Conditioners	
8.6.8 Slurry-Free Pads	
8.6.9 Endpoint-Detection in CMP	
8.7 CLEANING ISSUES IN CMP	392
8.7.1 Mechanisms of Particle Adhesion and Removal from Surfaces	
8.7.1.1 Electrical Repulsion of the Particle and the Wafer Surface	
8.7.1.2 Chemically Assisted Particle Removal	
8.7.1.3 Mechanically Assisted Particle Removal	
8.7.1.4 Steric Stabilization for Suspending Particles in a Solution	

8.7.2 Practical Particle Removal Processes: Brush Scrubbing	
8.7.2.1 Brush Scrubbing to Remove Particles in Post-Oxide-CMP Processes	
8.7.2.2 Brush Scrubbing to Remove Particles in Post Metal-CMP Processes	
8.7.3 Vibrational Scrubbing to Remove Particles (Megasonic)	
8.7.4 Secondary (or Buff) Polish Procedure as a CMP Cleaning Step	
8.7.5 Post-CMP Cleaning of Metallic Contaminants	
8.7.6 CMP Cleaning Equipment	
8.8 CMP METROLOGY	407
8.8.1 Detection of Defects Associated with the CMP Process	
8.9 CMP POLISHER TOOL RELIABILITY	411
8.10 CMP SYSTEMS AND PROCESS INTEGRATION	412
8.11 CMP OF VARIOUS MATERIALS	413
8.11.1 CMP of Oxide Interlevel & Intermetal Dielectrics (ILDs & IMDs)	
8.11.2 CMP of Tungsten	
8.11.3 CMP of Copper	
8.11.4 CMP of Aluminum	
8.11.5 CMP of Polysilicon	
8.11.6 CMP of Photoresist	
8.11.7 CMP of Low- <i>k</i> Dielectrics	
8.12 MISCELLANEOUS ISSUES CMP	421
8.12.1 Dishing and Erosion	
8.12.2 Thickness Non-Uniformity Within a Wafer After CMP	
REFERENCES	428
Chap. 9 - SHALLOW TRENCH ISOLATION (STI)	433
9.1 EARLY SHALLOW TRENCH ISOLATION STRUCTURES	435
9.2 STI-ENABLING PROCESSES	438
9.3 SHALLOW TRENCH ISOLATION FOR CMOS	439
9.4 DETAILS OF THE PROCESS FLOW TO FORM A BASELINE SHALLOW-TRENCH-ISOLATION (STI) STRUCTURE	446
9.5 ISSUES INVOLVED WITH STI PROCESS INTEGRATION	455
9.5.1 Issues Involved With Etching Trenches for STI	
9.5.2 Corner-Rounding Techniques in STI Structures	
9.5.3 Trench-Fill Dielectrics for STI	
9.5.4 Dishing Problem Associated with the CMP of STI Trench Dielectrics.	
9.5.5 Corner Engineering and Its Effects on MOSFET TURN-OFF Characteristics of MOSFETs Fabricated with STI	
REFERENCES	472

Chap. 10 - SILICON-GERMANIUM (Si-Ge) TECHNOLOGY FOR HIGH-PERFORMANCE TELECOMMUNICATIONS ICs **475**

10.1 INTRODUCTION TO HETEROJUNCTION BIPOLAR TRANSISTORS	475
10.2 HETEROJUNCTION BIPOLAR TRANSISTORS WITH LARGE-BANDGAP EMITTERS	480
10.3 HETEROJUNCTION BIPOLAR TRANSISTORS WITH SMALLER BANDGAP BASE REGIONS (Si-Ge BASE)	482
10.4 PROCESS TECHNOLOGY FOR FABRICATING SI-GE HBTS	484
10.5 PROCESS INTEGRATION ISSUES FOR BiCMOS TECHNOLOGY WITH Si-Ge HBT	486
10.6 HIGH-QUALITY SI-GE EPITAXIAL FILM GROWTH ON PATTERNED WAFERS	491
10.7 THERMAL STABILITY PROCESS INTEGRATION ISSUES	492
10.8 COMPATIBILITY WITH ION IMPLANTATION PROCESSES	492
10.9 COMPATIBILITY WITH THERMAL OXIDATION PROCESSES	493
10.10 VERTICAL SCALING OF Si:Ge HBTS	493
10.11 BASE-DURING-GATE AND BASE-AFTER-GATE BiCMOS PROCESS FLOWS	495
10.12 EXAMPLES OF THE MODULAR INTEGRATION OF Si-Ge HBTS INTO A BiCMOS PROCESS FLOW	497
REFERENCES	499

Chap. 11 - SILICON-ON-INSULATOR (SOI) TECHNOLOGY **501**

11.1 WHAT IS SILICON-ON-INSULATOR (SOI)?	501
11.1.1 Isolation Issues in CMOS in Bulk Silicon	
11.1.2 Isolation in SOI CMOS	
11.2 THE "END OF THE ROAD FOR BULK CMOS" SCENARIO PREDICTED BY THE 1999 INTERNATIONAL TECHNOLOGY ROADMAP FOR SEMICONDUCTORS	505
11.2.1 Source/Drain Junction Scaling	
11.2.2 Dopant Activation in Shallow Source/Drain Junctions	
11.2.3 Doping Profile Abruptness in Shallow Source/Drain Junctions	
11.3 WHY SOI?	510
11.3.1 The Path of Using SOI May Allow Extension of the ITRS Roadmap	
11.4 HISTORY OF SILICON-ON-INSULATOR (SOI) TECHNOLOGY	516
11.5 SILICON-ON-INSULATOR DEVICES	518
11.5.1 Partially-Depleted Thin SOI MOSFETs (PD-SOIs)	

11.5.2 Fully-Depleted Thin SOI MOSFETs (FD-SOIs)	
11.5.3 Process Technologies Used to Fabricate Fully-Depleted SOI Devices	
11.5.3.1 FD-SOI: Thinning Si-SOI Surface Layer by Thermal Oxidation	
11.5.3.2 FD-SOI Fabrication by LOCOS Recess of the MOSFET Channel Region	
11.6 FABRICATION TECHNOLOGIES USED TO PRODUCE SOI-STARTING-WAFERS	527
11.6.1 Silicon-on-Sapphire (SOS)	
11.6.2 SOI by Separation by Implanted Oxygen (SIMOX)	
11.6.2.1 High-Dose SIMOX	
11.6.2.2 Low-Dose SIMOX	
11.6.3 Wafer Bonding	
11.6.3.1 Bond and Etch-back SOI (BESOI)	
11.6.3.2 Hydrogen-Implantation-Induced Layer Splitting to Create SOI Substrates (SMART-CUT [®])	
11.6.3.3 NANOCLEAVE [®] Wafer Bonding SOI	
11.6.3.4 ELTRAN [®] Wafer Bonded SOI	
11.7 LATERAL ISOLATION IN SOI	550
11.8 SOI PRODUCT EVOLUTION	556
11.9 PROBLEMS ASSOCIATED WITH SOI	559
11.9.1 Floating Body Effects in Partially-Depleted SOI MOSFETs	
11.9.1.1 Kink Effect in Partially Depleted SOI NMOSFETs	
11.9.1.2 Transient I_D Effects	
11.9.1.3 Effect of Building Partially Depleted SOI MOSFETs Without Body Contacts	
11.9.2 Short-Channel Effects in SOI MOSFETs	
11.9.3 Self-Heating Effects in SOI MOSFETs	
11.9.4 Reliability Issues of SOI	
REFERENCES	568

Chap. 12 - MULTILEVEL INTERCONNECTS FOR ULSI

573

12.1 EVOLUTION OF THE STRUCTURE AND MATERIALS USED IN IC INTERCONNECTS	575
12.1.1 Single-Level Metal Interconnects in Early ICs	
12.1.2 Double-Level Metal Interconnects in Early Bipolar ICs	
12.1.3 Double-Level Metal Interconnects in CMOS ICs (Partial Planarization of the ILD)	
12.1.4 Three-Level Metal Interconnects in CMOS ICs (CMP of the ILD & W-Plugs)	
12.1.4.1 Problems of W-plug/Al-line Interconnect Structures	
12.1.5 Dual Damascene Cu/Low- k Interconnects	

12.1.6 Other Geometrical Aspects of Multilevel ULSI Interconnects	
12.2 PERFORMANCE REQUIREMENTS OF ULSI INTERCONNECT SYSTEMS	586
12.2.1 Propagation Delays in ULSI Multilevel Interconnects	
12.2.1.1 Case When the k -Value of the ILD is Constant Throughout the Interconnect System	
12.2.1.2 Case When the k -Values of the Interlevel and Intralevel ILD are Different	
12.2.1.3 Minimizing the RC Delay in the Local Interconnect Region	
12.2.1.4 Minimizing the RC Delay in the Global Interconnect Regions	
12.2.2 Power Dissipation Issues in ULSI Interconnects	
12.2.3 Crosstalk in ULSI Interconnects	
12.2.4 Contact Resistance in ULSI Interconnects	
12.2.5 Electrostatic Discharge Protection Issues of Interconnects	
12.3 SUMMARY OF USLI INTERCONNECT ISSUES AND FUTURE TRENDS	599
REFERENCES	601
Chap. 13 - POLYCIDES AND SALICIDES OF $TiSi_2$, $CoSi_2$ AND $NiSi$	603
13.1 POLYCIDES AND SALICIDES	603
13.2 POLYCIDES FABRICATED BY CVD OF TUNGSTEN SILICIDE (WSi_x)	605
13.3 SALICIDE (SELF-ALIGNED SILICIDE) STRUCTURES	608
13.4 THE EFFECTS OF SALICIDES ON MOSFET PERFORMANCE	612
13.5 SALICIDES FORMED WITH TITANIUM SILICIDE ($TiSi_2$)	614
13.5.1 Reaction Kinetics of $TiSi_2$ Formation (and the Problem of <i>Bridging</i>)	
13.5.2 The $TiSi_2$ Narrow-Line Effect	
13.5.3 Proposed Process Modifications to Mitigate the $TiSi_2$ Narrow-Line Effect	
13.5.4 Junction Dopant Redistribution and Silicon Consumption During $TiSi_2$ Formation	
13.6 SALICIDES FORMED WITH COBALT SILICIDE ($CoSi_2$)	624
13.6.1 Advantages and Drawbacks of Cobalt Salicides	
13.6.2 Details of the Cobalt Salicide Fabrication Process	
13.6.3 Diode Leakage Issues Involving Cobalt Salicides	
13.6.4 Sensitivity of Cobalt Salicide Films to Degradation by Oxygen Ambients: TiN Capping of Cobalt Salicide Films	
13.7 EPITAXIAL $CoSi_2$	630
13.8 $CoSi_2$ AS A SOURCE/DRAIN DIFFUSION SOURCE	631
13.9 NICKEL SILICIDE FILMS FOR SALICIDE APPLICATIONS	634
REFERENCES	635

Chap. 14 - LOW-*k* DIELECTRICS**639**

14.1 INTRODUCTION TO LOW- <i>k</i> DIELECTRICS	635
14.1.1 Spin-On versus CVD Methods for Forming Low- <i>k</i> Dielectrics	
14.1.2 Silicon-Based versus Carbon-Based Low- <i>k</i> Dielectrics	
14.1.3 Status of Low- <i>k</i> Dielectrics in 2000	
14.2 DESIRED CHARACTERISTICS OF LOW- <i>k</i> DIELECTRIC FILMS	646
14.3 GENERAL PROCESS INTEGRATION ISSUES INVOLVING LOW- <i>k</i> FILMS	648
14.4 FIRST GENERATION LOW- <i>k</i> DIELECTRICS ($2.8 < k < 3.5$)	650
14.4.1 Hydrogen Silsesquioxanes (HSQ)	
14.4.2 Spin-On Methyl Silsesquioxanes (MSQ)	
14.4.3 Fluorinated Silicate Glass (FSG) Films	
14.5 SECOND-GENERATION LOW- <i>k</i> DIELECTRICS ($2.5 < k < 2.8$)	655
14.5.1 2 nd -Generation Spin-On-Dielectrics: ($2.5 < k < 2.8$)	
14.5.2 2 nd -Generation CVD-Dielectrics: ($2.5 < k < 2.8$)	
14.5.2.1 2 nd Generation Low- <i>k</i> CVD-Films: Organo-Silicate Glasses	
14.5.2.2 2 nd Generation Low- <i>k</i> CVD-Films: <i>FlowFill</i> CVD Films	
14.5.2.3 2 nd Generation Low- <i>k</i> CVD-Films: Black Diamond & Coral CVD Films	
14.5.2.4 2 nd Generation Low- <i>k</i> CVD-Films: Parylene CVD Films	
14.6 ULTRA-LOW- <i>k</i> DIELECTRICS: ($k < 2.3$)	663
REFERENCES	669

Chap. 15 - DUAL-DAMASCENE INTERCONNECTS**671**

15.1 DAMASCENE VERSUS SUBTRACTIVE INTERCONNECT STRUCTURES	671
15.2 DAMASCENE INTERCONNECTS AS ALTERNATIVE DEEP-SUBMICRON INTERCONNECTS	672
15.3 SINGLE-DAMASCENE INTERCONNECT STRUCTURES	
15.4 INTRODUCTION TO DUAL-DAMASCENE INTERCONNECT PROCESSES	674
15.5 THE THREE DUAL-DAMASCENE PROCESS SEQUENCES	676
15.6 THE EVOLUTION OF DUAL-DAMASCENE FROM SiO ₂ TO LOW- <i>k</i> DIELECTRIC STACKS	679
15.7 TRENCH-FIRST DUAL-DAMASCENE PROCESS FLOW	683
15.8 VIA-FIRST DUAL-DAMASCENE PROCESS FLOW WITH AN SiO ₂ DIELECTRIC STACK	685

15.9 PROCESS INTEGRATION ISSUES OF THE VIA-FIRST DUAL-DAMASCENE PROCESS FLOW WITH A LOW- <i>k</i> -DIELECTRIC STACK	687
15.9.1 Via-First-Damascene Integration Issues: Lithography	
15.9.1.1 Via-Patterning Lithography Issues	
15.9.1.2 Trench-Patterning Lithography Issues – DUV Resist Poisoning	
15.9.1.3 Trench-Patterning Lithography Issues – Trench CD Control Issues	
15.9.1.4 Trench-Patterning Lithography Issues – BARC Veils	
15.9.1.5 Bi-Layer Resist Process	
15.9.2 Via-First-Damascene Integration Issues: Dielectric Etching	
15.9.2.1 Via-Etching for Low- <i>k</i> Processes	
15.9.2.1 Trench-Etching	
15.9.2.1 Etching the SiN Barrier at the Bottom of Vias	
15.9.3 Via-First-Damascene Integration Issues: Resist Stripping	
15.9.4 Via-First-Damascene Integration Issues: Cleaning	
15.9.4.1 Post-Dielectric-Etch-and-Strip Residue-Removal	
15.9.4.2 Pre-Metal-Deposition Clean	
15.9.4.3 Post-CMP Clean	
15.9.4.4 Clean of Top-Surface of Cu Prior to Diffusion-Barrier-SiN-Deposition Process	
15.9.4.5 Supercritical Fluids as Wafer Cleaners	
15.10 VIA-FIRST DUAL-DAMASCENE DIELECTRIC STACK WITH NO EMBEDDED ETCH-STOP LAYER	708
15.11 PROCESS INTEGRATION ISSUES OF DUAL-DAMASCENE DIELECTRIC STACK WITH ULTRALOW- <i>k</i> DIELECTRICS	708
REFERENCES	709
Chap. 16 – COPPER INTERCONNECT PROCESS TECHNOLOGY	711
16.1 WHY COPPER FOR DEEP-SUBMICRON IC INTERCONNECTS?	712
16.1.1 The Advantages of Copper Interconnects	
16.1.2 Technological Challenges of Using Copper Interconnects	
16.2 OVERVIEW OF COPPER PROCESS TECHNOLOGY	723
16.2.1 The Transition from Aluminum to Copper Interconnects	
16.2.2 The Key Goal of Depositing Copper into Damascene Recesses	
16.3 BARRIER LAYERS FOR COPPER INTERCONNECTS	728
16.3.1 The Impact of the Barrier-Layer Deposition Process on the Filling of Damascene Recesses with Copper	
16.3.2 Introduction to the Technology of Depositing Barrier-Layers for Cu Interconnects	

16.3.3 Ionized Magnetron Sputter Deposition	
16.3.4 Hollow-Cathode Magnetron Sputtering Source	
16.3.5 Self-Ionized-Plasma Sputtering Source	
16.3.6 Material Properties of Tantalum and Refining Tantalum Metal For Semiconductor Applications	
16.3.6.1 Material Properties of Tantalum	
16.3.6.2 Refining and Forming Tantalum Metal For Sputtering Targets	
16.3.6.3 The Properties of Tantalum (and TaN & TaSiN) as Cu-Barrier Layers	
16.3.7 Other Candidate Materials for Cu-Barrier Layers	
16.4 SEED-LAYER TECHNOLOGY FOR COPPER INTERCONNECTS	740
16.5 COPPER INTERCONNECT FILM DEPOSITION	747
16.5.1 Electrolytic-Plating of Copper	
16.5.2 Filling High-Aspect-Ratio Recesses Without Voids Using a Cu Electrolytic Electroplating Process	
16.5.2.1 The Electroplating Process Sequence	
16.5.2.2 Additives in Plating Baths for Damascene Cu Interconnects	
16.5.2.3 Models of How Additives in Plating Baths Impact “Bottom-Up” Filling	
16.5.2.4 Electroplating Bath Control	
16.5.2.5 Pulsed Plating	
16.5.2.6 Copper Thickness Variation Within a Wafer After Electroplating	
16.5.3 Post-Electroplating Cu Annealing and Recrystallization	
16.5.4 Electrochemical Mechanical Deposition (ECMD™)	
16.5.5 Electroless-Plating of Copper	
16.5.6 CVD of Copper	
16.6 WET-CHEMICAL ETCHING AND ELECTROPOLISHING COPPER	775
16.7 CONTAMINATION CONTROL IN COPPER TECHNOLOGY	778
16.7.1 Sources of Copper Cross-Contamination in a Wafer Fab	
16.7.2 Effects of Copper-Cross Contamination at the Back-End-of-Line (BEOL)	
16.7.3 Cu Removal from the Wafer Bevel/Edge and Backside	
16.8 RELIABILITY OF COPPER INTERCONNECTS	784
16.8.1 Reliability of Copper Interconnects: “Missing-Metal” Defects	
16.8.2 Reliability of Copper Interconnects: Plated vs. CVD Cu Films	
16.9 ENVIRONMENTAL, HEALTH, & SAFETY ISSUES OF CU TECHNOLOGY	787
16.9.1 Copper Waste Handling	
16.9.1.1 Handling Concentrated Waste from Plating and Wafer Reclaim	
16.9.1.2 Handling Copper CMP Effluents	
REFERENCES	789

INDEX**795**

PREFACE

With the dawn of the new millennium, IC technology-nodes have evolved beyond 0.18-micron. New processes also had to be developed to meet the needs of this *Deep-Submicron Era*, including: copper/low-*k* dual-damascene interconnects; high-*k* MOSFET-gate and DRAM dielectrics; 300-mm wafers; chemical-mechanical polishing (CMP); excimer-laser-based DUV-lithography; chemically-amplified (CA) resists; silicon:germanium (Si:Ge); and silicon-on-insulator (SOI).

The semiconductor industry, however, also experienced an economic decline of unprecedented severity at the start of the 2000 decade. It seems clear that to fuel the recovery, chip manufacturers will have to exploit the above innovations. Such processes are a path to achieving the performance goals of future IC technology-nodes that will be needed for manufacturing new and profitable electronic products.

This is the *first available book dedicated exclusively to describing such deep-submicron process technologies* (including those listed above). It is intended to provide semiconductor engineers and researchers with a comprehensive, state-of-the-art reference about these emerging and leading-edge processes. While many other books have been written about the “traditional” IC fabrication processes, none offer what this volume contains. It’s sole focus is those techniques needed to *manufacture chips for 0.18- μ m (and smaller) generations*. Thus, it belongs on the shelf of every microelectronic professional whose livelihood depends on having a thorough grasp of the latest advances in IC fabrication techniques. There is no faster way to gain this information. As with our other volumes, owners will find themselves referring to this text again and again!

Readers can still consult Vol.1, 2nd Edition for background material on basic IC fabrication modules, as this book (Vol. 4) does not repeat that information. Instead, it presents over 800 pages of new content about the process technologies of the 2000’s. It also has over 900 references (with 200 of these being published since 2000), and more than 500 illustrations. It is written in the same lucid, user-friendly style that has been widely praised in the other volumes of *Silicon Processing for the VLSI Era*.

As with the previous volumes, this text was produced using an accelerated book-production schedule. By employing revolutionary publishing techniques made available in the 1990’s, Lattice Press can turn a finished manuscript into a published text in less than 3 months (a task that takes most publishers of technical books 15-18 months). This allows our books to be released faster, and to contain the most-up-to-date information at the time of publication.

SILICON PROCESSING FOR THE VLSI ERA is a multi-volume treatise designed to provide a comprehensive and up-to-date treatment of this important and rapidly changing field. The volume in hand is the fourth in the series. Volume 1 (*Process Technology*, 2nd Edition) was published in 2000 and deals with individual processes employed in the fabrication of silicon ULSI circuits (such as silicon wafering, thermal oxidation of silicon, CVD and PVD of amorphous and polycrystalline films, diffusion and ion implantation of dopants in silicon, microlithography, and patterning technology). Volume 2 (*Process Integration*) was released in 1990, and describes how the individual processes of Volume 1 are combined in various ways to produce MOS and bipolar VLSI and ULSI circuits. The task of integrating these various fabrication processes together is referred to as *process integration*. In Volume 3 (*The Submicron MOSFET*, published in 1995) the topics of submicron MOSFET device physics and the relationship between such device physics and submicron MOSFET fabrication are addressed.

A book of this length and diversity would not have been possible without the indirect and direct assistance of many others. From an indirect perspective, virtually all of the information presented here is based on the research efforts of countless numbers of scientists and engineers. Their contributions are recognized to a small degree in citations of their articles given in the references at the end of each chapter. The direct help was also provided by many people, and the resulting text is thus significantly better. The author expresses heartfelt thanks to those who gave their time, energy, and intellect.

Important direct help came from members of my immediate family. My wife, Carol, read the manuscript for grammatical and stylistic correctness. My son, Ross, designed the cover and improved many of the graphics. My daughter, Jennifer, helped in marketing the book. Thus, it truly represents a family enterprise.

Stanley Wolf

For additional copies of the books contact:

LATTICE PRESS

Post Office Box 340

Sunset Beach, CA 90742 USA

www.latticepress.com

For your convenience an order form is provided on the final leaf of the book.

It can also be ordered from the **LATTICE PRESS** website.

Chapter 1

THE EVOLUTION OF THE STRUCTURE OF MOSFETS

The silicon MOSFET is the most important active-device in ULSI integrated circuits. Over the past 30 years, MOSFET dimensions have been decreasing at a dramatic rate - from gate lengths of 10- μm in the early 1970s to less than 0.13- μm today. This gate-length scaling is expected to continue, and may reach 0.05- μm (50-nm) at the end of the projected shrink path in 2012. Table 1-1 shows the predicted scaling of MOSFETs according to the 2001 IRTS Roadmap.¹

MOSFETs are the dominant devices in Si ICs largely because they can be scaled to increasingly small dimensions, and this scaling results in higher performance. However, the structure of the MOSFET has undergone many changes besides the scaling of feature sizes down to the deep-sub-micron regime of today.

Figure 1-1 shows a SEM of a MOSFET with a gate length of 2- μm (Fig. 1-1a, circa 1985), and also of a MOSFET with a gate length of 0.2- μm (Fig. 1-1b). With the exception of being scaled, the basic structure of the MOSFET does not appear to be fundamentally changed. However, several aspects of the MOSFET device structure have been modified. (This can be better illustrated in schematic drawings that depict MOSFET cross-sections with a 1.5- μm gate length and a 0.18- μm gate length, see Fig. 1-2.) In this chapter the structure of deep-sub-micron MOSFETs is compared to those of technology generations in which the gate length exceeded 1.0- μm . In this discussion the term *deep-submicron MOSFET* refers to MOSFETs with a *gate length of 0.25- μm or smaller*. How the structure of CMOS devices must be reconfigured when building ICs using devices whose minimum sizes are in the deep-submicron regime is also covered.*

* By 2001, several novel MOSFET structures were being studied as alternatives for the “conventional” MOSFET when its scaling limits are reached. Such new structures include the *vertical*-, the *replacement-gate*-, and *double-gate-MOSFETs*. However, by 2002 these structures (and others) were still in their infancy. It is not likely that they will be put into production for many years. The focus of this text, however, is on process technology that is in (or about to be put into) mainstream IC manufacturing lines in the 2001-3 timeframe. Thus, these novel structures will not be described here further. However, readers interested in more data on such futuristic MOSFETs should see such recent reviews as Ref. 8, and the *Technical Digests* of the *IEEE International Electron Devices Meetings (IEDM)*, and *Digests of Technical Papers* of the *Symposium VLSI Technology*.

Table 1-1 PRINTED GATE LENGTHS OF MOSFETS ITRS2001¹

	2001	2002	2003	2004	2005	2006	2007
PRINTED GATE LENGTH (nm)	90	75	65	53	45	40	35

The purpose of this chapter is to show how the MOSFET structure has had to be changed when deep-submicron integrated circuits were fabricated. The device physics details that underlie the need for building such deep-submicron MOSFET structures are not presented here. While some of such information is found in later chapters, a more in-depth discussion of this topic is left to other texts (such as Vol. 3 of this series,² and elsewhere.³)

1.1 THE STRUCTURE OF DEEP-SUBMICRON MOSFETS: (0.25 μm to 0.13 μm) COMPARED TO EARLIER-GENERATION MOSFETS: (2.0 μm to 0.5 μm)

In this section the structures of deep-submicron MOSFETs of the 2001-2002 timeframe (i.e., with gate lengths from 0.25 μm down to about 0.13 μm) are compared to those fabricated in the late 1980s and early 1990s (i.e., with gate lengths that ranged from 2.0 μm down to about 0.5 μm).

The following parts of the MOSFET will be examined, to see how the device structure had to be modified in order to allow high-performance deep-submicron MOSFETs to be implemented:

1. MOSFET gate-stack and contact structure;
2. Gate dielectric materials for the MOSFET;
3. Doping-concentration profiles of the MOSFET channel;
4. Drain structure of the MOSFET.




Fig. 1-1 SEMs of MOSFET cross-sections with different gate lengths: a) 2.0 μm ; b) 0.2 μm .




Fig. 1-2 Schematics of MOSFET cross-sections with different gate lengths: a) $1.5\ \mu\text{m}$; b) $0.2\ \mu\text{m}$.

Note that in CMOS ICs there are some additional structural aspects of the integrated circuit that must be considered besides those pertaining to the active device (MOSFET) structure. That is, the characteristics of the following two CMOS elements must also be addressed: 1) the on-chip interconnect system; and 2) the substrate and isolation structures. The issues relating to the substrate and the isolation structures will be considered in the following section of this chapter, while general issues related to the interconnect system are covered in Chap. 12.

1.1.1 Evolution of the MOSFET Gate Stack and Contact Structure

MOSFETs have used polysilicon as the gate material since the mid-1970s (i.e., when the polysilicon-gate structure replaced metal [Al] gates). The gate material in earlier MOSFETs for both NMOS and CMOS technologies down to about

0.35- μm was n^+ -doped poly (usually heavily doped with phosphorus - see also the following section on CMOS technology for more information on poly doping). However, as the MOSFET gate lengths were scaled below about 1.25- μm , the resistance of the polysilicon lines became too large for them to be effective in their secondary role as a local interconnect (even when they were doped as heavily as possible). At that point it became necessary to clad the top surface of the poly film with a metal silicide layer (most commonly WSi_x). This multi-layer gate *stack* was called a *polycide structure* (see Chap. 13 for more details on WSi_x polycides). Use of the polycide gate stack structure allowed the resistance of lines implemented with heavily-doped poly to be reduced by about a factor of four. Implementing WSi_x polycides thus permitted the use of single-level-metal interconnects in MOS-based ICs to be extended for one or two more technology nodes. (Note that the polycide structure is not shown in Fig. 1-2a, but is shown in Fig. 13-1.)

In deep-submicron CMOS, the silicide atop the poly layer is no longer WSi_x . Instead it is replaced with TiSi_2 or CoSi_2 . These two silicides have lower resistivities than WSi_x . In addition, TiSi_2 or CoSi_2 can be simultaneously formed on the source and drain contact-regions at the same time they are formed on the poly lines. MOSFETs with a silicide on both the poly and the source/drain contact regions are said to contain a *self-aligned silicide* (or *salicide*) structure (as shown in Fig. 1-2b). The salicide structure provides two main benefits to the MOSFET: 1) the poly lines have a lower resistivity due to the presence of the silicide; and 2) the contact region exhibits a smaller contact resistance and sheet resistivity as compared to a contact region that does not have such a silicide. The details of the salicide formation processes, and the comparison of titanium silicides and cobalt silicides for this role are described in Chap. 13.

1.1.2 Gate Dielectric Materials in Deep-Submicron MOSFETs

Thermally grown SiO_2 has been used as the gate dielectric material for over 30 years (ever since MOSFETs ICs were first introduced). The thickness of this oxide has been continuously scaled to improve the MOSFET drain current and to control short-channel effects. The gate-oxide thickness has been approximately linearly scaled with channel length, with the ratio of gate length L_E to oxide thickness t_{ox} being maintained at approximately 45 (i.e., $L_E/t_{\text{ox}} \sim 45$).⁴ For example, a 200-Å gate-oxide thickness was used in MOSFETs with a gate length of 1.0- μm , and a 40-Å gate-oxide thickness was used for 0.18- μm MOSFETs.

It is predicted that SiO_2 will continue to be used as the gate dielectric in MOSFETs until about 2004-2005. At that point (for MOSFETs with a gate




Fig. 1-3 a) Doping profile in a conventional diffused CMOS well; b) Doping profile in the CMOS well with a threshold-adjust implant; c) Doping profile in a CMOS well with a threshold-adjust implant *and* an anti-punchthrough implant.

length of $0.1\ \mu\text{m}$), the required oxide thickness will be less than $20\text{-}\text{\AA}$ (assuming the same ratio L_E/t_{ox} is maintained). However, when the oxide reaches a thickness of less than $20\text{\AA}$, the gate-to-channel tunneling leakage-current will become approximately as great as the off-state source-to-drain leakage-current of the MOSFET ($\sim 10\text{-nA}/\mu\text{m}$). As a result, it may not be feasible to build logic MOSFETs (i.e., not even high-performance-logic MOSFETs) with SiO_2 gate dielectric layers thinner than about $20\text{-}\text{\AA}$. Other devices (e.g., DRAM capacitors, or oxides used in non-volatile memory structures) will face even more stringent oxide thickness limitations. Such limits to gate oxide thickness are considered in more detail in Chap. 3.

To allow the gate lengths of MOSFETs to continue to be scaled below $0.1\ \mu\text{m}$, it seems it will be necessary to use alternative high- k -dielectric materials instead of SiO_2 . With these materials, thicker dielectric layers can be used, and yet the same inversion layer characteristics can be maintained. These thicker layers result in less carrier tunneling, and thus they permit further scaling. The use

of high- k dielectrics as alternative gate-dielectric materials is discussed in Chapter. 4.

1.1.3 Doping-Concentration Profiles of the MOSFET Channel

In earlier MOSFETs the channel region had a doping concentration profile (prior to the V_T -adjust implant) that is initially relatively flat with respect to depth below the silicon/oxide interface. In NMOS technology, this flat profile exists because the starting-substrate Si-wafers in which the NMOSFETs are fabricated are uniformly doped. In CMOS technology, the initial flat doping profiles are created from the processes used to create “conventional” CMOS well regions. That is, in such processes the well dopant is introduced into the silicon wafer near its surface using a shallow implant step. Then a long, high-temperature drive-in process diffuses these dopants away from the silicon surface, resulting in a doping profile that is relatively constant with depth near the silicon surface (see Fig. 1-3a). A V_T -adjust implant (using boron for both NMOS and PMOS) is then carried out to provide a doping profile as shown in Fig. 1-3b. As the NMOSFET approached $1\text{-}\mu\text{m}$ in gate length, a blanket anti-punchthrough boron implant was also carried out (typically following the V_T -adjust implant step). This caused a doping profile to exist in the channel as shown in Fig. 1-3c (and the MOSFET structure as in Fig. 1-2a).

In deep-submicron MOSFETs, the doping profile in both the vertical direction (i.e., in depth from the silicon surface) and in the lateral directions (i.e., along the channel) is changed from that which existed in earlier MOSFETs. Consider the profiles in the vertical and lateral directions separately.

In the *vertical direction*, the doping profile in the channel of deep-submicron MOSFETs has a so-called *super-steep retrograde* (SSR) shape (see Fig. 1-4). Such an SSR channel doping is needed to allow the correct value of the threshold voltage of the MOSFET to be achieved, while avoiding a degradation in the mobility of the carriers in the channel (due to excessively high dopant concentrations near the silicon/oxide interface - where the inversion layer exists). That is, it is desired to keep the doping density at the silicon surface to $<5 \times 10^{17}/\text{cm}^3$. Such an SSR doping profile can be obtained by implanting a heavier dopant species than B for n -channel devices (typically In is used to replace B), and a heavier dopant species than P for p -channel devices (either As or Sb can be used). These species have a smaller diffusivity than either B or P, respectively, and thus the impurity profile does not get spread out during the




Fig. 1-4 As-implanted doping concentration profiles of threshold-adjust-implants with B and In as the implant species. The In implant produces a super-steep retrograde (SSR) profile.

subsequent heat cycles used to activate the implanted dopants. By choosing the correct implant energy and annealing cycles after implant, an appropriate SSR channel doping profile can be created. Chapter 5 covers this topic in more detail.

In the *lateral direction* (i.e., in the direction along the channel from the source to the drain), there is now also a non-uniform doping profile. That is, in the advanced “conventional” MOSFETs, a blanket implant for improving the punchthrough (PT) performance of the MOSFET is employed. Since this implant is a blanket process, the impurities that it introduces are in uniform concentration in the lateral direction of the channel (as shown in Fig. 1-2a). However, for deep-submicron MOSFETs, such blanket PT implants cause performance degradation.

To avoid these problems (and yet maintain the benefits provided by the blanket anti-punchthrough implant), the same dopant species is introduced in another fashion. As shown in Fig. 1-2b, the dopant is introduced only in selected, local regions; namely at the edge of the drain-extension region. This leaves much of the channel length with a lighter doping that is needed for a low V_T .

As the schematic drawing of Fig. 1-2b depicts, this extra dopant region surrounds the edge of the drain extension much like a halo surrounds the head of an angel in medieval paintings. Hence, this localized anti-punchthrough region has been termed a *halo anti-punchthrough structure*. Such a halo structure was originally produced (ca. 1985) by performing a second implant after the implant that created the lightly doped drain region (LDD - see Sect. 1.4.1). The halo implant is again self-aligned to the gate (and with the beam direction normal to the wafer surface). The same implant species as that already present in the well is introduced by the halo implant, and it uses an energy that is somewhat higher than that used for the LDD implant. Thus, the range and lateral straggle of this




Fig. 1-5 Doping concentration contours resulting from a LATIPS implant.⁷

second implant will be greater than that of the first, resulting in the formation of a halo region as shown in Fig. 1-2b.

In more-advanced-technology generations, this second implant step is carried out with the ion beam directed at a high angle to the wafer surface. This allows the peak concentration of the implanted impurities to be located at a precise depth and lateral distance from the edge of the gate. Such an implant process has been named *large angle tilted implanted punchthrough structure (LATIPS)*, or alternatively a *pocket implant*. Such lateral tailoring of the channel doping profile provides some additional design space to control V_T and punchthrough. Figure 1-5 shows the doping concentration contours resulting from such a LATIPS process, and more details on LATIPS are given in Chap. 5. These LATIPS (or pocket) implants, however, may be difficult to control at small dimensions.

1.1.4 Evolution of the Drain Structure of MOSFETs

When MOSFETs were first implemented in ICs, gate lengths were on the order of 10- μm . For MOSFETs with such long channel lengths, the drain-side of the pn junction at the drain end of the channel consisted of a simple single-region drain structure (Fig. 1-6a). As the gate lengths grew smaller than about 2.0- μm , the electric field in the depletion region of this drain pn -junction grew so large that it started to produce severe hot-carrier injection effects (HCI). These HCI effects caused long-term reliability-degradation in MOSFETs, and they had to be curtailed. The technique used to suppress HCI effects was to replace the single-region drain structure with a two-region drain structure (Fig. 1-6b). The two-region drain structure consisted of a region that was in contact with the MOSFET

channel (and extended under the edge of the gate) and a second region that was further from the channel (but was connected to the first region). To reduce the electric field near the drain, the first region was more lightly doped ($\sim 10^{17}/\text{cm}^3$) compared to the second region ($\sim 10^{20}/\text{cm}^3$). The name given to this two-region drain structure is the *lightly doped drain* (or *LDD*).

The process sequence for forming this structure is as follows: 1) After patterning the gate stack, the lightly doped drain region is formed with an ion implantation step using a medium-current implanter. The gate is used to align the drain dopant with that of the gate edge, forming the LDD region; 2) A spacer is formed (by CVD of a dielectric film, followed by an anisotropic-etch step that leaves a spacer structure along the sidewalls of the gate); 3) A high-current implanter is next used to introduce the dopants for the second heavily-doped drain-contact-region (with the spacer preventing these species from being implanted into the LDD region); and 4) An anneal step activates the dopants and drives the edge of the lightly doped region the proper distance beneath the edge of the gate.

In deep-submicron MOSFETs, the drain structure has been modified from the 2-region LDD-drain described above. The reason for this change is that the power-supply voltage has been reduced as MOSFET dimensions were scaled (primarily because gate oxide thicknesses have become thinner, and such thin oxides cannot withstand the oxide electric fields that exist at the higher supply voltage values – see Chap. 3). For MOSFETs at $0.18\text{-}\mu\text{m}$, the power-supply




Fig. 1-6 a) Single-region drain in a MOSFET; b) Lightly-doped-drain in a MOSFET; c) Source/drain-extension and contact-drain-regions used in deep-submicron MOSFETs.

voltage has been reduced to about 2.0 V (down from the 5.0 V power supply value that was retained until devices got to the 0.8- μm generation). In any case, for such small drain-voltage values, the electric field near the drain is already reduced to a degree where few carriers can now gain sufficient energy to create interface states or shallow oxide traps. Hence, in deep-submicron MOSFETs HCI-effects no longer need to be controlled by the use of an LDD structure. However, the parasitic resistance contribution to the overall MOSFET ON-resistance due to the LDD region is increased to an unacceptably large degree.

To overcome the above problem, the two-region drain structure is retained. However, the region closest to the channel is no longer an LDD region. Instead, the first region is now termed the *source/drain-extension-region* (SDE) because the peak doping is no longer lighter than in the contact region. The increase in peak doping is achieved by raising the implant dose into the SDE region (from $1\text{-}5 \times 10^{13}/\text{cm}^2$ to $5\text{-}10 \times 10^{14}/\text{cm}^2$), which produces an extension region of the drain having lower resistivity. The peak doping concentration in the SDE is as high as in the second (contact) region, but its junction depth is shallower. This second drain region is called the *contact region* (Fig. 1-6c). It should also be noted that the penetration of the junction due to the SDE under the gate edge must be more carefully controlled as the gate length gets shorter.

The main challenge is to continue to make the SDE more shallow (to control short-channel effects), while retaining a sufficiently low resistance. Shallow n^+/p S/D junctions can be formed easily by arsenic (As) implantation, because its high mass produces smaller R_p , and the high As dose in the SDE region amorphizes the silicon, suppressing channeling effects. On the other hand, it is more difficult to make shallow p^+/n S/D junctions due to the low mass and susceptibility to TED of boron (the only p -type dopant with solid solubility suitable for this application). This has driven boron implant energies to the ultra-low (0.5-1.0 keV) range, and has forced the development of specialized ion implanters to do these implants economically. These and other issues involved with the formation of the SDE and the contact region are described in detail in Chap. 5.

1.2 DEEP-SUBMICRON CMOS STRUCTURES

Other structures besides just MOSFETs have to be formed when fabricating monolithic ICs. That is, isolation structures and interconnects are also needed.




Fig. 1-7 Perspective schematic view of a twin-well CMOS structure.

Furthermore, the IC technology can be MOSFET-based (e.g., NMOS or CMOS), bipolar-junction-transistor (BJT) based (e.g., emitter-coupled-logic – ECL), or one that contains both BJTs and MOSFETs (e.g., BiCMOS). Since CMOS is the dominant silicon IC technology at the start of the 21st century, the focus will be on the CMOS structures within the silicon substrate that must be created when manufacturing deep-submicron CMOS ICs (Fig. 1-7).

1.2.1 Substrate Issues for Deep-Submicron CMOS

Czochralski-grown single-crystal silicon is the starting material on which silicon ICs are fabricated. Such single-crystal silicon is formed into *wafers*. There are two common doping-concentration configurations that ULSI wafers contain: **1)** the wafers are uniformly doped with a relatively light doping concentration of either *p*- or *n*-type dopant (and such wafers are referred to as *bulk* or, *polished wafers*); and **2)** the wafers are heavily *p*-doped during the crystal growing process, and then a lightly *p*-doped epitaxial Si layer is grown on the polished top surface of the wafer (and these wafers are referred to as *epitaxial*, *epi*, or *p-epi-on-p⁺ wafers*).

Bulk wafers were used for NMOS technologies and some CMOS technologies (especially in chips that have lower selling prices, since the cost of bulk-Si wafers is about one-half that of epi wafers). The epi wafers were used for controlling latchup in CMOS logic circuits that needed high functional density but had a higher average selling price (ASP) than the chips that use bulk-Si wafers.

In deep-submicron CMOS technologies, the *epi wafers* are used for other roles besides just controlling latchup. The use of an epi layer on a heavily *p*-doped Si wafer improves the gate-oxide-integrity (GOI – an important factor that determines the overall yield of the chips), and also the intrinsic-gettering capability of the wafer. That is, some impurities in the Si wafers (e.g., iron) are gettered by the formation of metal-atom-B pairs (Fe-B) in the heavily-B-doped bulk region of the wafer. Chapter 2 discusses both the GOI issue and this gettering capability in detail. It also reviews the new, alternative substrates that are beginning to replace the conventional epi-wafers described above (e.g., such new wafer types as *epi optimized substrates*).

1.2.2 Well Formation in Deep-Submicron CMOS

As described in Sect. 1.1.3, “conventional” wells in CMOS are formed by introducing the well dopants with a shallow implant process, and then diffusing them deeply into the silicon with a long, high-temperature drive-in step. This creates a well doping-concentration profile that has the highest doping concentration at the silicon/oxide interface, and decreases monotonically with distance into the depth of the silicon. Unfortunately, such a well-doping-profile forces tradeoffs to be made among various MOSFET device-performance characteristics, especially when fabricating deep-submicron MOSFETs.

To avoid this problem, and to enable independent optimization of key MOSFET performance characteristics, a different well-doping-profile must be produced. That is, by creating so-called *retrograde-wells* (instead of “conventional” wells), carrier mobility, S/D capacitance, inter-device leakage currents, V_T -control, punchthrough suppression, parasitic transistor effects, and latchup can be optimized almost independently. Retrograde wells are discussed in Ch. 5.

1.2.3 Dual-Doped Poly in Deep-Submicron CMOS

Conventional CMOS structures (down to about $0.35\text{-}\mu\text{m}$) used n^+ -poly for both NMOS and PMOS devices. Surface-channel MOSFETs are produced when n^+ -poly is used as the gate material for NMOS transistors. However, the consequence of using n^+ -poly as the gate material for PMOS transistors is that such PMOSFETs are buried-channel MOSFETs (see Vol. 3 for a complete discussion on surface-channel vs. buried channel MOSFETs, and why the use of n^+ -poly makes buried-channel PMOSFETs inevitable). However, buried-channel PMOSFETs exhibit OFF-state leakage currents that are unacceptably large once MOSFETs are scaled to $0.25\text{-}\mu\text{m}$ (and smaller) gate lengths.

To overcome this problem, it is necessary to build surface-channel PMOSFETs (as well as surface-channel NMOSFETs) in CMOS technologies at 0.25- μm and smaller. This requires the use of p^+ -poly as the poly gate material on the PMOSFETs (Fig. 1-8), and n^+ -poly for NMOSFETs (in other words, the poly in the 0.25- μm [and smaller] CMOS circuits must be *dual doped*). Such a change has several implications. First, additional complexity is introduced into the CMOS process flow (e.g., selective dual doping of the poly layer must be carried out instead of single doping, requiring additional masking layers to permit such selective doping). Second, the p -dopant introduced (boron, B), can penetrate the gate oxide into the silicon substrate unless a sufficiently low thermal budget is used after this poly doping step (or unless the gate oxide is somehow made more resistant to B penetration). Such B penetration would cause unacceptable variations in the threshold voltage of the PMOSFETs. Third, B diffusion along the poly lines can counterdope the poly in other parts of the IC. Some of the issues involved with the use of dual-doped poly in deep-submicron ICs are discussed further in Chap. 3, as well as in Vol. 3, Chap. 5 of this series.

1.2.4 Shallow Trench Isolation for Deep-Submicron CMOS

LOCOS isolation was developed in the early 1970s, and it remained the workhorse isolation structure for NMOS and CMOS ICs until these technologies reached the 0.35- μm generation (Fig. 1-9a). However, for IC generations beyond




Fig. 1-8 Schematic cross-section of a CMOS structure with STI and dual-doped poly.




Fig. 1-9 a) Semirecessed LOCOS isolation structure; b) Shallow trench isolation structure.

0.35 μm , shallow-trench isolation (STI) replaced LOCOS. The drawbacks that LOCOS could not overcome were the field oxide bird's beak (that encroaches into the active areas of the chip) and the non-planar topography that results from thermally growing the semi-recessed field oxide.

Both of these problems are avoided by the use of STI (Fig. 1-8 and 1-9b). That is, in STI, trenches are etched and filled with oxide deposited by CVD to form the thick isolation oxide region. This method of forming the isolation oxide does not produce a bird's beak. In addition, by using CMP to planarize the surface in the course of forming this isolation oxide-structure, the wafer surface is flat at the conclusion of the STI-formation sequence. This eliminates the topography that exists at the conclusion of the LOCOS formation process. Chapter 9 covers the details of STI and CMP is discussed in Chap. 8.

1.2.5 Silicon-On-Insulator (SOI) Technology

CMOS technology has largely been built on so-called bulk-Si wafers. In such wafers the devices are isolated from one another by a combination of isolation structures at the silicon surface, and *pn* junctions in the bulk of the Si. However, latent current paths among devices may still be activated in the bulk regions by such phenomena as latchup or transient radiation events. Furthermore, parasitic circuit elements associated with the CMOS structure (such as source-to-substrate and drain-to-substrate capacitances) can become too large in CMOS structures built on bulk-Si wafers. As a result, the use of *silicon-on-insulator wafers* (SOI)

instead of bulk-Si wafers for some CMOS applications is being pursued. Device isolation and latchup control are simplified for SOI with fewer processing steps required. SOI technology is described in Chap. 11

1.3 LIMITS TO CONVENTIONAL MOSFET SCALING

Conventional scaling of MOSFETs, with some modifications to the device structures (as described in the previous sections) has allowed MOSFETs with gate dimensions to be reduced from 10- μm in the 1970s down to 0.1- μm . (Figure 1-10 shows a SEM micrograph of 0.18- μm MOSFET transistors in typical logic structures.) Certain MOSFET structures were essentially just scaled (without undergoing any fundamental structural changes) as the minimum device dimension was reduced to about 0.1- μm . These include: the gate-oxide thickness; the source/drain junction depth; and the gate length.

However, below 0.1- μm , MOSFET devices built according to the structure described in this chapter (and depicted in Fig. 1-2), appear to run into some fundamental limits. These limits would prevent further size reductions if we were restricted to using only such traditional scaling approaches. Table 1-2 (as postulated by Thompson *et al.*), catalogs these limits.⁴ Consequently, to enable MOSFETs to be scaled even further, new solutions will need to be developed, such as the use of high- k materials for gate dielectrics (see Chap. 4), and novel shallow, ultra-low-resistivity junctions (see Chap. 5). Other issues related to these limits also arise, and will be considered in the chapters of this book. For example, advanced lithography challenges will be covered in Chaps. 6 and 7, and




Fig. 1-10 A SEM micrograph of 0.18- μm MOSFET transistors in logic structures.

Table 1-2 SCALING LIMITS OF CONVENTIONAL MOS DEVICES⁴

FEATURE	LIMIT	REASON
Oxide Thickness	2.0 nm	Leakage (I_{gate})
Junction Depth	30 nm	Resistance (R_{SDE})
Channel Doping	$V_T = 0.25 \text{ V}$	Leakage (I_{off})
SDE Under-Diffusion	15 nm	Resistance (R_{inv})
Channel Length	0.06 μm	Leakage (I_{off})
Gate Length	0.10 μm	Leakage (I_{off})

alternative device architectures, such as Si:Ge technology and SOI CMOS will be discussed in Chaps. 10 and 11, respectively. Issues concerning ULSI interconnect issues are explored in Chaps. 12 to 16. A recent review by Hutchby *et al.*, discusses the novel structures being considered to replace conventional MOSFETs that are still being used in ICs at the start of the decade of 2000.⁸ It describes how such nanoelectronic structures for memory, logic, and information processing architectures could possibly extend the time frame of the ITRS beyond CMOS.

REFERENCES

1. Overall Roadmap Technology Characteristics Chapter. The International Roadmap for Semiconductors, Semiconductor Industry Association, 2001 Edition.
2. S. Wolf, *Silicon Processing for the VLSI Era: Vol. 3 – The Submicron MOSFET*, Lattice Press, Sunset Beach CA, 1995.
3. Y. Taur and T.K. Ning, *Fundamentals of Modern VLSI Devices*, John Wiley & Sons, New York, 1997.
4. S. Thompson *et al.*, "MOS Scaling: Transistor Challenges for the 21st Century," *Intel Technology Journal*, 3rd Quarter 1998.
5. S. Parihar *et al.*, "A High Density 0.10 μm CMOS Technology Using Low- k Dielectric and Copper Interconnect," *Tech. Dig. IEDM*, 2001, p. 249.
6. S. Thompson *et al.*, "An Enhanced 130-nm Generation Logic Technology Featuring 60-nm Transistors Optimized for High-Performance and Low-Power at 0.7 and 1.4 V," *Tech. Dig. IEDM*, 2001, p. 257.
7. T. Hori, "A 0.1 μm CMOS Technology with Tilt-Implanted Punchthrough Stopper (TIPS)," *Tech. Dig. IEDM* 1994, p. 75.
8. J.A. Hutchby *et al.*, "Extending the Road Beyond CMOS," *IEEE Circuits & Devices Magazine*, March 2002, p. 28.

Chapter 2

300-mm SILICON WAFERS

This chapter deals with 300-mm wafer technology, including the growth of 300-mm Si crystals, 300-mm wafer specifications, and the economics of the 300-mm wafer industry. Readers wishing background information on material properties of silicon, general information on Si crystal growth and wafering can consult *Silicon Processing for the VLSI Era - Vol. 1: Process Technology, 2nd Edition*.

2.1 300-mm SILICON WAFER GROWTH

The fabrication of VLSI and ULSI takes place on Si substrates possessing very high crystalline perfection. The critical importance of utilizing single-crystal material for the transistor regions of microelectronic circuits was first recognized by Teal in 1949.¹ He reasoned that polycrystalline material would exhibit inadequately short minority-carrier-lifetimes, due to the defects at the grain boundaries of the polycrystalline grains. Teal also pointed out the need to define the degree of chemical purity and crystal perfection, the uniformity of structure, and the chemical composition of the single-crystals when specifying starting material on which to fabricate semiconductor products. The method of obtaining such single-crystal Si for IC fabrication, involves several steps (Fig. 2-1):




Fig. 2-1 Process sequence: From starting material to polished wafer.




Fig. 2-2 The increase with time of CZ silicon crystal diameter and the percentage increase in wafer area with increase in wafer diameter.

1. Raw material (e.g., quartzite, a type of sand), is refined by a complex, multi-stage process that produces *electronic grade polysilicon*, EGS (Fig. 2-1).
2. This electronic grade polysilicon is used to grow single-crystal silicon by *Czochralski (CZ)* crystal growth or *float-zone (FZ)* crystal growth.

In CZ growth, single-crystal ingots are pulled from molten silicon contained in a crucible. Czochralski silicon is preferred for ULSI applications since it can withstand thermal stresses better than FZ material,² and it is able to offer an internal gettering mechanism (not available with FZ crystals) that can remove unwanted impurities from the device structures on wafer surfaces.

The simplicity of the CZ process and the relatively high-degree of crystal purity helped establish it as the dominant silicon-crystal-growing technology in the early years of the semiconductor industry. The development of dislocation-free ingot growth and automatic diameter control in the late 1960s lead to a rapid growth in the sizes of ingot diameters and crystal melts. Further increases in charge size and diameters were driven by the economic advantages of even larger ingots. As shown in Fig. 2-2, by 1998 300-mm diameter crystals had become available, grown with 150-kg charges. Typical commercial ingots are grown 0.5–2.5-m in length, and a 100-kg charge can grow an ingot roughly 1-m long




Fig. 2-3 a) 300-mm Si crystal after it has been removed from a 300-mm CZ puller; b) 300-mm ingot cooling on a materials-handling device.

with a diameter of 200-mm. The driving function for going to larger wafer diameters is the increase in Si area available per wafer. Figure 2-2 also shows that the area of a 300-mm wafer is 2.25 times the area of a 200-mm wafer. Figure 2-3b shows a 300-mm Si ingot mounted in a materials handling device. We will only concern ourselves in this section with the issues involving the growth of 300-mm Si-crystals.

The wafer manufacturing process for 300-mm wafers is not a straightforward extension or scale-up of 200-mm processes. Most tools needed to produce 200-mm wafers, including crystal pullers, grinders, polishers, cleaners, and inspection stations are not capable of being cost-effectively utilized for 300-mm wafer production. In addition, the cost of growing 300-mm silicon crystals is the principle challenge facing technologists striving to match the 200-mm unit-area cost performance. That is, to be able to achieve the same yield of 300-mm wafers as is possible with 200-mm wafers, the size of the charges will have to be increased from the 150-kg charge being used in 1998 for 200-mm wafers to 300-400 kg for 300-mm wafers. The equipment used to pull crystals from such charges will also have to be able to rotate and lift the crystal while stirring and positioning the




Fig. 2-4 a) Modern computer controlled CZ pullers. Larger silicon wafer sizes and the required manufacturing efficiency have driven crystal puller size. b) Schematic drawing of CZ puller.

melt, doing this all the while without vibration, in a high-vacuum atmosphere, and at temperatures that exceed 1400°C . Figure 2-4 shows how the size of the crystal puller has to be increased with respect to the size of a 200-mm puller to make it possible to handle such larger charges.

The charge must be held in a single-use, high-purity quartz crucible more than 30 inches in diameter. Demands on the crucible increase significantly for a 300-mm process, as the growth cycle time stretches to over 100 hours (~ 4 days). Any flaw that develops in the crucible during that multi-day crystal-growth time can cause a loss in atomic alignment of the crystal, making it unusable.

Another important factor that impacts the cost of producing the wafer is the crystal pull speed (i.e., the longer it takes to pull the crystal, the higher the cost of producing the wafer). However, in growth chambers of identical design, this speed v_{pullrate} is inversely proportional to the crystal diameter D_{crystal} or, $v_{\text{pullrate}} \sim (1/D_{\text{crystal}})$. The reason that the pull speed must be decreased as the diameter increases is that the crystal mass increases as the square of the ingot radius, while the surface area of the ingot (which radiates away the heat of fusion), is proportional to the diameter. Thus, a path toward reducing the cost of manufacturing larger diameter wafers is to develop new and innovative puller

designs that allow the heat to be removed more quickly than in a conventional puller (a project apparently being pursued by most wafer suppliers).

Increasing the pull speed, however, is only one relatively small aspect of decreasing the cost of manufacturing large diameter wafers because there are many steps that comprise the entire growth cycle. (As shown in Fig. 2-5, by tripling the pull speed from 0.5 mm/min to 1.5 mm/min, the wafer production cost is reduced by only about 5%.) Two other significant factors that increase the cost of producing 300-mm wafers above the cost of producing 200-mm wafers are: 1) a 300-mm wafer is 50- μm (or 7%) thicker than a 200-mm wafer; and 2) the back surface of a 300-mm wafer is polished, whereas the back surface of a 200-mm wafer is not. The back-surface polishing process removes an additional 10-20- μm of silicon stock. In total, a 300-mm wafer therefore consumes about 9% more Si-crystal per unit area than a 200-mm wafer, resulting in fewer wafers per unit-length of ingot.

2.2 GROWN-IN CRYSTAL DEFECTS: CRYSTAL-ORIGINATED PARTICLES (COPs) and DISLOCATION LOOPS

As the silicon crystal is being grown in the CZ growth process, several phenomena occur that produce defects in the as-grown crystal. Since these defects arise from the various aspects of the CZ crystal growth sequence (namely, solidification from the melt and cool-down to room temperature), they are termed *grown-in defects*. As the minimum device dimensions in ICs are scaled below 0.25- μm , grown-in defects have been identified as a potential factor that reduces the performance characteristics and decreases the yields of CMOS ICs. The most significant of these grown-in defects are the so-called *crystal-originated defects* (COPs). The COP defects have the form of voids in the Si lattice, and these voids are caused by agglomeration of supersaturated vacancies




Fig. 2-5 300-mm crystal-growth-cycle-time components.

that are introduced into the crystal as the liquid-phase-silicon solidifies. COPs cause two major problems when such voids intersect the wafer surface: **1)** they degrade the integrity of thin gate-oxide films (GOI); and **2)** they create leakage paths in the isolation structures of DRAMs.³ In this section we describe the mechanisms that give rise to these COPs and provide details about the problems they cause in the devices fabricated on wafers containing such defects. Finally, we discuss measures that have been employed to mitigate their effects.

Note that another form of defect is also prevalent in CZ Si wafers, namely oxygen precipitates. These defects, however, form during IC processing (instead of during the crystal growth process itself), and thus oxygen precipitates are not considered to be grown-in defects. However, their density in the wafer (number/cm³) and their size also strongly correlate with prior crystal growth conditions and subsequent heat treatments.

It is believed that the grown-in defects described above (i.e., COPs - as well as their complementary counterparts, dislocation loops) arise from an agglomeration of intrinsic point-defects (namely, vacancies to form COPs and self-interstitials to form dislocation loops), during the cooling of the silicon ingots following the crystallization from the liquid phase. The formation of voids from the homogeneous nucleation (agglomeration) of supersaturated vacancies in silicon was first suggested by Voronkov in 1982.⁴

Intrinsic point defects are incorporated into the silicon when it crystallizes. Estimates from computer simulation indicate that their thermodynamic equilibrium concentrations at the melting point of silicon (1412°C) are $\sim 1 \times 10^{15}$ cm⁻³ for vacancies, and about 20% less for self-interstitials.^{5,6} As the crystal cools continually during CZ growth, the solubility of these intrinsic point-defects decreases, resulting in a condition of supersaturation. Intense recombination of the vacancies and interstitials occurs when the solidified crystal is cooling through the high-temperature range (i.e., from 1412°C to $\sim 1200^\circ\text{C}$). At the same time, some net out-diffusion of self-interstitials occurs from regions near the surface (outer circumference) of the Si ingot. That is, more self-interstitials out-diffuse from the ingot surface than do vacancies because the self-interstitials diffuse 10 times faster than vacancies near the silicon melting-point temperature.

Computer simulations further indicate that $\sim 10\%$ of the original point-defects in both the vacancy- and interstitial-rich regions survive after the intense recombination events which occurred during the cooling through the high-temperature range, but that these surviving point-defects still remain in supersaturation when the temperature of the ingot drops below $\sim 1200^\circ\text{C}$. Since the point-defects continue to diffuse rather rapidly at temperatures above

~1150°C, they can come out of solution either by further recombination events, or by agglomerating into clusters of vacancies or self-interstitials. The vacancies have been found to agglomerate into octohedral voids at about 1150-1180°C. As noted earlier, these voids formed by vacancy-agglomeration are called crystal-originated particles (COPs).^{7,8} Supersaturated self-interstitials, on the other hand, can form large dislocation loops. CZ-silicon-crystals, however, are pulled under conditions where vacancies are the prevailing type of intrinsic point-defect, and as a result, self-interstitial-agglomerated dislocation loops do not occur in significant numbers in 200-mm Si wafers used in IC production. Thus, our discussion of grown-in defects is primarily focused on COPs.

2.3 DETAILS OF THE FORMATION OF CRYSTAL ORIGINATED PARTICLES (COPS)

In this section we provide additional information about the formation of COPs and the effects they have on IC devices. We begin with a more detailed discussion of how COPs are formed during the cooling of the Si ingot.

The formation of COPs was studied by employing crystal-growth-halting-and-quenching techniques. That is, during CZ-growth the crystal ingot pull-rate was abruptly halted, and the ingot temperature was quickly lowered (quenched) to some specific value. By doing this with a number of ingots and quenching to different temperatures, the defects formed during the cooling of the ingot from solidification to that temperature could be examined. Such studies indicated that the formation of COPs consists of two stages. In the first, voids are rapidly formed as the ingot cools through the narrow temperature range of 1150-1180°C. In the second, an oxide is formed on the inner surface of the voids during the cooling-down process following void formation (down to about 900°C). The resultant voids formed within the bulk have been identified by TEM studies as having a tetrahedral shape, and with sizes between 0.1- and 0.3- μm (100-300-nm). Furthermore, their inner surfaces are covered with a thin oxide layer approximately ~5-nm thick (Figs. 2-6 and 2-7).⁹ Such COPs are formed with densities between 10^5 to 10^7 cm^{-3} .¹⁰

It should be noted that before the nature of grown-in defects was well understood, COPs were identified in the literature under different names, depending on the technique that was used to delineate and detect them. These terms included: *COPs*, *laser-scattering tomography defects* (LSTDs), *flow-pattern defects* (FPDs), and *Secco etch-pit defects* (SEPDs). However, by comparative observation, it was confirmed that they were in fact the same type of defect (namely COPs), that just appear under different guises (depending on the technique used to detect them).




Fig. 2-6 SEM of COPs as they appear on the surface of a Si wafer. Oxide layer at the void:crystal-interface is visible.

In fact, the most common method used to make COPs visible with optical instruments when they intersect a wafer surface is to immerse bare silicon wafers in hot RCA-Clean SC-1 solutions (e.g., 4 h @ 85°C). The SC-1 solution etches Si slowly and isotropically, and this enlarges the lateral and vertical dimensions of any COPs that intersect the surface. They appear with the shapes shown in Figs. 2-6 and 2-7.¹¹ This shape enlargement also makes it possible for laser-based defect-detecting tools (which do not have as high a resolution capability as do TEMs - which can be used to image COPs directly), to detect the presence of any COPs as *localized light scatterers* (LLDs). By using this delineation technique, the entire wafer surface can be quickly mapped for the presence of COPs with




Fig. 2-7 Schematic representation of the octahedral structure of a COP defect.

an automated scanning surface inspection system (such as the KLA-Tencor Surfscan).

2.3.1 The Radial Distribution of Grown-In Defects on the Wafer Surface

As described previously, typical 200-mm wafers being used for ULSI today have a central vacancy-rich region surrounded by a self-interstitial-rich edge. These regions are separated by the vacancy/self-interstitial (V/I) boundary that occurs at a critical value of a parameter, ζ_c , defined as:

$$v/G(r) = \zeta_c = 0.138 \text{ mm}^2/\text{min-K} \quad (2.1)$$

where v is crystal pull rate (in mm/min), $G(r)$ is the axial temperature gradient {i.e., $G(r) = dT(r)/dr$ [in K/mm]} at the crystal/melt interface at a radial position (r) from the center of the ingot, and T is the absolute temperature (in kelvins).¹²

The axial temperature gradient, $G(r)$, at the center of the crystal ingot is usually lower than at the ingot surface. In addition, v is the same across the crystal growth interface at a given pull rate. Thus, in conventional CZ crystal growth, the value of $v/G(r)$ is highest at the radial center of the ingot and decreases continually toward the crystal-ingot edge. The wafer central-region inside the V/I boundary is thus vacancy-rich, characterized by $v/G(r) > \zeta_c$, while the edge-region outside the V/I boundary is self-interstitial-rich, with $v/G(r) < \zeta_c$.

The concentration of the vacancies (C_V) and the self-interstitials (C_I) at a given radial position, r , relative to those of the equilibrium levels of (C_V^{eq}) and (C_I^{eq}) at about 1200°C, after passing the intense recombination and out-diffusion regime between the melting-point and ~1200°C, are apparently exponentially proportional to the difference between $v/G(r)$ and ζ_c , or:

$$(C_V/C_V^{eq})_r = \exp \{ \alpha [v/G(r) - \zeta_c] \} \quad (2.2)$$

$$(C_I/C_I^{eq})_r = \exp \{ \beta [\zeta_c - v/G(r)] \} \quad (2.3)$$

where α and β are not known at this time. The supersaturation of vacancies is highest at the radial center, and decreases radially from this value. Thus, more voids are formed at the central-region of the wafer. On the other hand, high supersaturation of self-interstitials is present at the crystal peripheral (edge) region. But, because of out-diffusion of the self-interstitials to the crystal surface (a result of the fact that self-interstitials diffuse 10 times as fast as vacancies near the melting point of Si), high-supersaturation of self-interstitials occurs at some distance from the edge.

In the $v/G(r)$ ratio, the thermal gradient ($G[r]$) is controlled by the thermal environment in the hot-zone of the crystal puller, and by melt convection. With

an appropriately designed crystal-puller, the value of $G(r)$ can thus, in theory, also be controlled. The pull rate v is much more easily controllable. Computer simulations of both the melt convection and the thermal distributions within the puller hot-zone have been extensively employed to modify the design of the crystal puller so that an optimum $v/G(r)$ value can be obtained. The recent rapid progress in the field of simulating crystal-growth processes permit the bulk properties and process stability of the growth processes to be predicted with remarkable accuracy. This should help reduce R&D costs, a requisite for allowing wafer manufacturers to profitably develop the new generations of wafers being called for by the industry.¹³

2.4 THE OXYGEN-STACKING-FAULT RING (OSF-RING)

It is observed that when a typical, polished 200-mm CZ-grown wafer (as described above) is oxidized and then etched in HF and SC-1 to delineate the defects present at the wafer surface, it manifests a multi-ring defect structure. The central region of the wafer contains COPs. The COP-filled region is surrounded by a ring of *oxidation-induced stacking faults*, OSFs (i.e., which emerge after the wafer is subjected to a thermal oxidation step). This feature is also termed an *OSF-ring* (Fig. 2-8). The region of the wafer outside of the OSF-ring is an essentially defect-free region that contains a very low density of dislocation loops. This region extends to the edge of the wafer (Fig. 2-9).¹⁴ The origin of the COPs in the central region has already been described. Here we explain what is believed to be the cause of the OSF-ring.

In the OSF-ring, the delineated defects are oxidation-induced stacking faults (OSFs). These stacking faults, however, arise from the presence of oxygen precipitates.¹⁵ The oxygen precipitates are the actual defects that exist in the as-grown state of the ingot. But since these precipitates act as heterogeneous nucleation sites for the OSFs, the OSFs become the defects that are delineated by the SC-1 etch. Hence, this region is called the OSF-ring. An important aspect of the OSF-ring is that the ring-radius decreases with decreasing pull rate, until at a critical pull-rate-value (that depends on thermal conditions), it disappears into the center of the crystal. The presence and radial location of an OSF-ring in CZ-silicon corresponds qualitatively to the neutral (or boundary) region that separates the vacancy-rich- and self-interstitial-rich-regions of the ingot.¹⁶ (Sometimes anomalous oxygen precipitation is observed between the OSF-ring and the defect-free outer-region, as shown in Fig. 2-9, but we shall not consider this anomalous phenomenon here).

The OSF-ring is thought to be a region in which vacancies are only in slight




Fig. 2-8 Schematic drawing of the ring regions. An OSF-region after oxidation separates the A-defect-rich region (dislocation loops) from the D-defect-rich region (COPs) .

excess over self-interstitials, so recombination proceeds over a longer period of time, since neither species is strongly dominant. This competition results in a lower vacancy supersaturation and a delay in the onset of nucleation. Smaller voids are formed and the final vacancy concentration in the region of the OSF-ring is actually higher than inside the ring. These vacancies may provide the needed free volume for formation of the oxide precipitates that are observed at the center of the stacking faults in the OSF-ring region.¹⁷

2.5 MITIGATING THE EFFECTS OF COPs WITH THE USE OF POST-CRYSTAL-GROWTH ANNEALING

As we noted previously, for ULSI circuits it is important that the wafer be free of grown-in defects and oxide precipitates in the surface and sub-surface device regions of the wafer. Typically, a high-temperature annealing step is performed on the wafers to out-diffuse the oxygen near the surface, so that the concentration of oxygen there drops below the solubility limit. Thus, oxygen precipitation can no longer occur in this region, and no oxide precipitates are formed. High-temperature annealing processes have also been investigated as a method of annihilating the COPs near the wafer surface. That is, annealing at high temperatures (typically $\geq 1200^{\circ}\text{C}$) in an inert ambient (most commonly hydrogen, but also in argon) has been used to reduce the COP density near the wafer surface. Such hydrogen-annealed CZ-polished-wafers were introduced by




Fig. 2-9 a) Plane x-ray topograph of Cu-decorated CZ-Si wafer; b) Plane x-ray topograph of oxygen-precipitated CZ-Si wafer. The D-region, OSF ring, and defect-free regions are observed. c) Details of the defects delineated in each region.

Toshiba Ceramics in 1986, and they have been commercially available under the name of Hi-WAFER.^{TM,18} Other silicon wafer vendors have also offered annealed CZ-polished-wafers (annealed in other gases). It should be noted that it has been reported that the annealing must be carried out in an oxygen-free ambient, otherwise the annealing procedures do not produce optimal benefits.¹⁹

The mechanism thought to be responsible for reducing the COP density in hydrogen-annealed wafers is as follows: The inner surface of the COP void is covered with a thin oxide. Under high-temperature annealing in a hydrogen ambient, the hydrogen species diffuse into the Si. The oxide on the COP surfaces (in regions near the wafer surface) is decomposed by the reduction effect of hydrogen and oxygen. Eventually the COP surface becomes bare-Si and the surface atoms within the COP-void are mobile enough to reconstruct this surface and cause the void to shrink (by vacancy-diffusion into the Si bulk). As the process of void dissolution proceeds, the void is first transformed into a spherical structure from a regularly octahedron (because this decreases the surface free-energy of the void during annealing).²⁰ It has also been proposed that a heavily-doped buried layer (created by high-energy implantation of a heavy boron dose) be incorporated into Hi-WAFERs. In that way, the benefits of a heavily-doped boron region in the substrate (as is available with p/p^+ epitaxial wafers) can also be obtained with a Hi-WAFER, at a lower cost than that of such epi wafers.²¹

Hydrogen annealing at 1150°C for several hours to reduce COP levels extends the usefulness of 200-mm polished wafers. However, it adds 15-20% to the wafer

cost, and according to some opinions, it will not be a feasible technique for 300-mm wafers.²²

In another report, wafers were annealed at 1300°C in an inert ambient for one hour. No observable COPs existed (i.e., at the wafer surface) after this annealing.²³ It was reported in another study that very-good GOI was obtained using such wafers. However, these wafers also showed a very high concentration of oxide precipitates after the thermal processes used during the IC fabrication were carried out. The presence of these precipitates may give rise to excess leakage values in such products as high-density DRAMs. As a result, this report concluded that the high-temperature-annealing process needs further optimization.²⁴

2.6 ELIMINATION OF COPS WITH "PERFECT SILICON"

A special CZ-silicon-growth technique has been developed that eliminates COPs from silicon wafers by preventing their formation during the ingot growth process. Wafers obtained from ingots grown according to this technique are referred to as "*perfect*" silicon wafers, or "*pure*" silicon wafers.²⁵ The idea behind this approach is to create growth conditions such that the concentrations of intrinsic point defects remain close to their quasi-equilibrium values all along the radius of the crystal-melt interface. In that way, the silicon is not supersaturated with either vacancies or self-interstitials. Under these circumstances, regions will still exist that are either vacancy-rich, or self-interstitial-rich. But neither COPs nor dislocation loops can form (because even in those regions there is no supersaturation of the point-defect species which dominates in that region). The goal of the "perfect" silicon-growth-process is to establish the conditions quantified by the following set of conditions:

$$v/G(r) - \zeta_c \approx 0, \quad C_V \approx C_V^{eq}, \quad \text{and} \quad C_I \approx C_I^{eq} \quad (2.4)$$

The name "perfect silicon" was given to such point-defect-equilibrated silicon crystals because wafers from such crystals after immersion in a defect-delineation etch exhibit neither a boundary between vacancy-rich/self-interstitial-rich regions nor an OSF-ring. Instead, the wafer appears "perfect" or "pure." Specifically, a "perfect" silicon wafer will show negligible COP densities, so yield and performance of ULSI devices on such wafers will be enhanced to the levels exhibited by devices fabricated on epitaxial wafers. Growth processes and crystal pullers that can produce "perfect" silicon were being developed in 2000 to be able to produce 200-mm "perfect" silicon wafers in production quantities, and subsequently this effort is expected to be carried out for 300-mm wafers. However, there are some difficulties associated with this approach. The first is

that the hot-zone in the crystal puller must be optimized so that it becomes possible to maintain the condition of $v/G(r) = \zeta_c$ along the whole length of the crystal. The second is that a relatively slow pull-speed is needed to maintain the $v/G(r) = \zeta_c$ condition. The latter requirement is not favorable in terms of the crystal yield.

The ingot yield from a crystal puller is reduced by this method for two reasons. First, the slower pull-speed reduces the throughput of the puller. Second, because the ingot growth cycle becomes much longer, more time is allowed for a disruptive event to occur during the crystal growth time (which would render the ingot useless). Nevertheless, since the cost to produce “perfect” silicon wafers seems to be less than the cost of producing epitaxial wafers, there is still an incentive to pursue the development of “perfect” silicon growth processes.

A report comparing the behavior of MOS-capacitor structures and *pn*-junction diodes fabricated on conventional polished CZ wafers, “perfect-silicon” CZ wafers, and *p/p*⁺-epitaxial wafers was published by Niwa.²⁶ Junction leakage currents were smaller on the “perfect-silicon” and *p/p*⁺-epitaxial wafers than on the conventional CZ wafers. GOI characteristics were also superior on the “perfect-silicon” and *p/p*⁺-epitaxial wafers, and the “perfect-silicon” GOI results matched those obtained with the epitaxial wafers.

2.7 MINIMIZING COPS PERFORMANCE DEGRADATION WITH HIGH-PULL-SPEED SILICON

Another approach that is being pursued to achieve wafer quality similar to “perfect-silicon” is to use a crystal pull-rate that is much faster than that used to pull a “perfect-silicon” ingot (three or four times as fast). With this faster pull-rate, $G(r)$ is increased to some extent as a result of the higher pull-rate. However, since v is much larger than in the “perfect-silicon” case, the overall $v/G(r)$ value becomes substantially larger than the critical value $\zeta_c = 0.138 \text{ mm}^2/\text{min-K}$. Thus, the crystal becomes completely vacancy-rich and the vacancy concentration at temperatures below 1200°C becomes much larger than the quasi-equilibrium value (i.e., the crystal becomes supersaturated with vacancies), or:

$$v/G(r) \gg \zeta_c, \text{ and } C_V \gg C_V^{\text{eq}} \quad (2.5)$$

Nevertheless, due to the high pull rate, the crystal passes quickly through the 1150-1180°C COP-forming temperature-range, so only COPs of smaller sizes and at a high density can be formed. Such small-sized voids near the wafer surface can be annihilated by post-growth wafer-annealing. Doping the ingot with nitrogen during crystal growth is another factor that contributes to the mini-




Fig. 2-10 Size of COPs in a silicon wafer as a function of pulling conditions.²⁸

mization of void formation.²⁷ Figure 2-10 shows how the size of COPs is decreased by combining fast-pull and nitrogen-doping of CZ-ingots.²⁸ The fast-pull-approach offers potential advantages of high throughput and yield, and lower cost.

The process of performing the CZ-ingot-growth process at a high pull-speed and simultaneously doping the ingot with nitrogen (to get small COPs) has been combined with hydrogen annealing of wafers obtained from such ingots. By using infra-red topography, the concentration of COPs near and at the wafer surface (i.e., a technique that can detect the presence of COPs within 20- μm of the surface),²⁹ it was observed that the concentration of COPs decreases dramatically to depth of over 10- μm when such wafers are annealed in hydrogen at 1200°C.³⁰ The GOI of these wafers annealed in hydrogen was also significantly improved (Fig. 2-11).

Some concerns exist about the fast-pull CZ-Si growth processes. First, the relatively high vacancy concentrations remain in the wafer (which could cause




Fig. 2-11 Gate oxide integrity is best on wafers with small COP size ("C" breakdown mode indicates breakdown field of the gate oxide is > 10 MV/cm).³⁰

anomalous oxygen precipitation that degrades DRAM refresh time). Second, the formation of proper denuded zones during the high-temperature annealing steps is a question. For applications that require wafers without COPs that intersect the wafer surface, but which cannot afford to use “conventional” epitaxial wafers, a fast-pulled wafer with a thin epitaxial layer on it may be a possibility. Such wafers are termed *epitaxy-optimized substrates* (EOS), and they are described in Sect. 2.9.1.

2.8 GETTERING FOR ULSI PROCESSES

Unwanted crystalline defects and impurities can be introduced during silicon crystal growth or subsequent wafer fabrication processes. The presence of crystalline defects and impurities is undesirable because both can degrade device characteristics and overall yield. A detailed discussion of the degradation of VLSI device properties by *extended crystalline defects* (dislocations, stacking faults, and precipitates) can be found in *Silicon Processing for the VLSI Era* Vol.1, 2nd Ed. Chap. 2. The damaging effects by *impurities* are discussed here.

The impurities that create problems are grouped into two categories: **1)** impurities that participate in the process of nucleating extended crystalline defects (e.g., oxygen and carbon); and **2)** other impurities that decorate pre-existing extended crystalline defects (the latter being primarily metals, and include such elements as Cu, Ni, Au, and Fe). Such metallic impurities are highly mobile and diffuse long distances in the crystal at moderate process temperatures. Thus, there is a high probability they will migrate near extended defect sites, and be captured by them. Extended defects in device regions of the wafer which capture metal impurities give rise to larger leakage currents and lower breakdown voltages.

Efforts undertaken to eliminate the effects of impurities and defects have involved four approaches:³¹ **1)** suppression of extended defect nucleation; **2)** annihilation of existing extended defects in the device regions; **3)** preventing device degrading impurities from being introduced into the wafer; and **4)** preventing any remaining metallic impurities from being captured in the device regions. Technique **4)** is referred to as *gettering*, which is a term originally used to describe the process in which an appropriate material (such as cesium), was used to getter (remove) the last traces of gas in vacuum tubes, so that the required high vacuums within the glass tubes could be achieved.

By combining these four approaches, the product yield of ICs can be enhanced. That is, proper application of the first two approaches minimizes the number of extended defects that exist in the active regions, and the third reduces

the concentrations of the impurities introduced into the silicon. Gettering is then used to remove any of those impurities that still manage to be incorporated during crystal growth or processing. Thus, gettering reduces the probability of decorating any extended defects formed in the device regions with metallic impurities.

Methods used to suppress extended defect nucleation include: **a)** control of the thermal process conditions during wafer fabrication that lead to excess thermal-stress and resultant dislocations; and **b)** creation of oxygen denuded zones at the wafer surface regions in which active devices are fabricated. The latter procedure eliminates oxygen precipitates in these device regions. *Annihilation of pre-existing or process-induced extended defects* such as stacking faults, is achieved by using various techniques, including elevated temperatures ($>1200^{\circ}\text{C}$)³² and the addition of HCl to the growth ambient³³ during the growth of SiO_2 .

The use of technique **3)**, namely *the control of unwanted impurities* (especially metals), involves identification and removal of the sources of contamination. Such approaches entail the thorough characterization of the material and processing equipment used to fabricate devices. Some examples of the contaminant sources that have been identified include: **a)** stainless steel fixtures in ion-implant machines that ended up being sputtered during the ion-implant process;³⁴ **b)** impurities originating from the sputtering of chamber walls and fixtures of reactive ion etching systems;³⁵ **c)** the diffusion of heavy metals from the heater coils through the fused silica walls of diffusion furnaces; and **d)** the release of transition metals (e.g., Fe and Ti) by the SiC-coated susceptors of (batch) epitaxial reactors.

A variety of procedures have been implemented to reduce the level of metal contamination arising from these sources. Stainless steel parts (which may release metal atoms as a result of sputtering in ion implanters and reactive-ion etchers) have been replaced with parts made from materials which produce less degradation if they are incorporated into Si than do Fe or Cr. Such materials include aluminum, silicon, and carbon. Suggested procedures to decrease contamination by sources of heavy metals have included the following: **1)** reducing process temperatures (since quartz tubes become increasingly permeable to the metal atoms of the furnace heating coils as the temperature increases); **2)** subjecting the furnace tubes to periodic high-temperature HCl cleaning; and **3)** use of double-wall furnace tubes (with HCl or inert gas flowing in the space between the inner and outer tubes). Contamination from epitaxial susceptors can be reduced by performing the epitaxy process at lower temperatures and reduced pressures, and by *in situ* cleaning of the wafers prior to




Fig. 2-12 Four stages of impurity gettering in silicon.

initiating epitaxial growth. The use of cassette-to-cassette operations in transporting of wafers has reduced the possibility of contamination due to manual handling. Use of vacuum wands is now mandated if automatic wafer handling fails or is not yet fully implemented.

2.8.1 Basic Gettering Principles

The mechanism of gettering removes transition metal impurities from device regions by four steps (Fig. 2-12):

1. The metal impurities to be gettering are released into solid solution from any stable-precipitate-form they have assumed;
2. They then diffuse through the silicon lattice;
3. They are "captured" at a position away from the device regions by either: **a)** the formation of chemical pairs (e.g., Fe-B pairs) with other impurities (e.g., boron) present in the crystal; or **b)** by deliberately created extended defects (dislocations or precipitates);

4. The metal impurities are prevented from being re-released into the wafer during subsequent heat treatments.

In general, the transition-metal impurities are initially considered to rapidly disperse themselves uniformly throughout the wafer. This assumption is based on their high diffusivity and long diffusion lengths at typical processing temperatures (see Vol. 1, 2nd Ed., Chap. 2).

Gettering processes are divided into two categories: extrinsic and intrinsic. *Extrinsic gettering* involves the use of external means to create damage or stress on the surface of the silicon wafer that leads to the creation of the extended defects or chemically reactive sites at which the mobile impurities are captured. Normally such capturing sites are generated on the backside of the wafer, although front-side extrinsic gettering has also been explored. Extrinsic gettering can be performed prior to the first oxidation step (*pre-oxidation gettering*), or concurrently with the remainder of the fabrication steps (*gettering during* [or *subsequent to*] *junction formation*). *Intrinsic gettering* involves the localization of impurities at extended defects or regions of high concentration of electrical impurities (such as boron) which exist within the bulk material of the silicon wafer, and whose origin is due to an "intrinsic" property of the starting wafer, such as its oxygen or boron content acquired during CZ crystal growth.

The gettering of gold atoms in silicon by phosphorus diffusion is described, as this process serves to illustrate the basic mechanism of (extrinsic) gettering. A known concentration of gold atoms (e.g., $1 \times 10^{14}/\text{cm}^3$) is first diffused uniformly throughout a group of silicon wafers. Phosphorus diffusions at 900°C are then carried out in an attempt to getter the gold. These diffusions produce surface regions having high concentrations of P (1×10^{19} – $1 \times 10^{21}/\text{cm}^3$). After the P diffusions are completed, the gettering efficiency of the procedure is measured. It is observed that with increasing surface concentration of P, a strongly decreasing concentration of gold in the silicon bulk occurs. At P concentrations of 10^{21} atoms/ cm^3 , the gold concentration is decreased below the detection limit. Further investigations show that the gold has diffused into the phosphorus-containing layers in the silicon.

A model offered by some investigators describes the kinetics of this gettering process according to the following steps:³⁶ **a)** P diffusion is accompanied by the generation of phosphorus-vacancy complexes and/or misfit dislocations which become possible capture sites (sinks) for the gold atoms; **b)** during the P-diffusion step the highly mobile gold atoms also diffuse long distances in the wafer; **c)** the gold is captured at the phosphorus-vacancy or dislocation sites, and is thus removed from solution (this maintains a favorable

concentration gradient of gold in solution toward the phosphorus-rich zones); and d) once a gold atom is captured, the electrostatic interaction energy with the capture site is so high that subsequent heat treatment does not release it back into the wafer. Sufficient phosphorus must be deposited to create enough capture sites to getter the gold present in the wafer.

Diffused phosphorus layers (and other backside gettering methods) are also effective in shrinking OISFs. Oxidation-induced stacking-faults are regions of excess point defects (i.e., Si self-interstitials). Diffused P-layers shrink them for reasons still being argued (i.e., either vacancies are injected, which shrinks the OISFs, or the supersaturated P-concentration causes precipitation to begin and the resulting dislocation loops form sites to soak up the interstitials).

2.8.2 Extrinsic Gettering

Historically, gettering of mobile metallic impurities has been accomplished by *extrinsic gettering*, in which the wafer backside is subjected to a process that creates damage or stress, and subsequently traps mobile impurities. A number of wafer backside treatments have been developed for this purpose. Mechanical damage and polysilicon deposition are the two used most widely.

Mechanical damage by abrasion, grooving, or sandblasting have all been used to create stress fields at the backside of wafers. During subsequent annealing steps, dislocations which relieve these stresses are generated. The dislocations then serve as gettering sites.

A layer of polysilicon deposited on the wafer backside (1.2–1.5- μm thick) is another extrinsic gettering technique that has been developed (Fig. 2-13).³⁷ Start-




Fig. 2-13 Cross-sectional TEM micrographs of: a) as-deposited poly-Si, then wet oxidized at 1150°C for; b) 100 min; c) 765 min, and; d) 1300 min.³⁸

ing wafers up to 200-mm in diameter can be purchased with such a layer already deposited. (However, as we will see, such backside deposition is not compatible with 300-mm wafers.) The grain boundaries, and high degree of lattice disorder in polysilicon act as sinks for mobile impurities.

Unfortunately, extrinsic gettering techniques suffer from a variety of limitations. The primary general limitation of extrinsic gettering procedures is their inherent lack of stability, especially at high temperatures up to 1250°C for bipolar structures. Such instability manifests itself as the dissolution of gettered metal back into the wafer, and the annealing out of dislocations as the wafer undergoes a number of high-temperature steps. Upon being annealed out, dislocations can no longer trap newly introduced impurities, nor recapture the impurities released back into the wafer from getter sites. This limitation is one reason why extensive investigation of intrinsic gettering as a complementary gettering procedure has been undertaken, and why it is being increasingly implemented into ULSI fabrication sequences.

For 300-mm wafers, a *double-sided-polishing (DSP)* standard has been adopted. By polishing the wafer backside of the wafer (as well as the frontside), inspection of the entire wafer surface for the presence of particles can be achieved (i.e., small particles cannot be detected on the rough back-surface of a wafer). However, since the backside layer treatments of a wafer for the purposes of external gettering would have to be carried out after the DSP steps, it will no longer be possible to use them for 300-mm wafers. Hence, 300-mm wafers will have to rely on internal gettering processes.

2.8.3 Intrinsic Gettering

Intrinsic gettering is based on the principle that under proper conditions, fast-diffusing impurities are captured at sites existing within the interior of silicon wafer, away from the device regions near the surface. Two mechanisms are employed to implement internal gettering:

Gettering at Oxygen Precipitates: Supersaturated oxygen in silicon wafers will precipitate out of solution and form clusters within the wafer during thermal processing. The stresses that result as these clusters grow into larger precipitates can be relieved by punching out dislocation loops (or by emitting Si-self interstitials that agglomerate to form stacking faults and dislocation loops). These dislocations become sites at which unwanted impurities can be trapped and localized.³⁶ In an effectively designed intrinsic gettering process, these precipitates are only allowed to form in the bulk regions of the wafer. They are prevented from forming in the active




Fig. 2-14 SEM micrograph of a *pn* junction created by a 450°C anneal for 70 hr in denuded-zoned-Si with SiO_x precipitates formed by thermal treatment.⁴⁰

device regions by reducing the oxygen concentrations to levels below the threshold required for precipitation (denuded zone formation). In this way, unwanted impurities are localized (gettered) only in regions not containing active devices (Fig. 2-14).

Gettering by Formation of Impurity Pairs: In this technique some types of metallic impurities are immobilized by chemically pairing them with other impurities deliberately introduced into the Si for this purpose. For example, Fe appears to form immobile Fe–B pairs. Thus, if regions of high B concentration are present in the interior of a wafer, migrating Fe atoms pair with a B atom and become immobilized at that location. Silicon wafers with a high bulk-concentration of B, topped with a lightly doped (e.g., $1 \times 10^{16} \text{ cm}^{-3}$) thin epitaxial layer of Si (e.g., 3- μm -thick) can be used for this purpose. In fact, such silicon wafers have been historically used to control latchup in CMOS. Only recently has it been discovered that they are also very effective at gettering Fe through Fe–B pair formation, as described above. Recent reports indicate that a heavily doped region of B, created by a high-energy ion-implant process may be as effective in gettering Fe in wafers without an epi layer. If this claim is borne out, it may provide a less

expensive way of obtaining the benefits of gettering and latchup protection offered by the heavily doped boron region in the Si with an epi layer.

The advantages of intrinsic gettering over extrinsic gettering include the following: **a)** the technique may be employed without any external treatment of the wafer other than heating; **b)** the volume of the wafer provides a sink during intrinsic gettering that is roughly two orders of magnitude larger than the volume of the gettering region on the wafer backside; and **c)** the gettering region in the bulk is much closer to the device regions than the backside of the wafer.³⁹ The distance required for impurities to diffuse from the circuit regions to the sinks is therefore 25–50 times shorter. Thus, intrinsic gettering allows diffusion cycles which are significantly shorter than those required for extrinsic gettering to remove the same contamination.

2.8.4 Gettering with Oxygen Precipitates

The first requirement for successfully implementing oxygen precipitate gettering techniques is to have appropriate oxygen concentration levels in the starting Si (i.e., 15–19 ppma). The lower limit of this range is somewhat above the threshold concentration of oxygen required for precipitation ($\sim 6 \times 10^{17}$ atoms/cm³ = 12 ppma). Precipitation does not occur at a measurable rate for concentrations below the 12 ppma level.⁴⁰ Wafers from CZ-grown ingots, however, normally exceed this lower limit, with the oxygen being incorporated during crystal growth by erosion of the SiO₂ crucible. On the other hand, if oxygen concentrations exceed 19 ppma, too high a density of precipitates is formed. This may contribute to both wafer warpage and dislocation generation in the vicinity of the active devices (Fig. 2-15).^{41,42}

Assume that the wafers contain appropriate concentrations of oxygen, and that the oxygen is uniformly distributed across the wafer diameter. The wafers can then be subjected to a series of temperature cycles to achieve intrinsic gettering (Fig. 2-16). A *high-low-high* sequence of such steps is then:

Step 1. *Denuded Zone Formation* - a *high-temperature* step produces a region of reduced oxygen concentration near the wafer surface;

Step 2. *Nucleation of SiO_x Clusters* - a *lower-temperature* step causes homogeneously nucleation of SiO_x precipitation sites;

Step 3. *Precipitate Growth and Gettering* - a *high-temperature* step grows the SiO_x nuclei formed in Step 2 into larger oxide precipitates. The result of their growth is the formation of dislocation loops, which function as the desired gettering sites.




Fig. 2-15 a) Dependence of wafer warpage on bulk microdefect size; b) Wafer warpage as a function of bulk-microdefect-density.⁴² c) Effect of Initial Oxygen content of the wafer on warpage.

In *Step 1*, a region near the surface containing less oxygen than is required to form precipitates (*denuded zone*) is created. Thus, such precipitates or their punched out dislocation loops (which could intersect active device junctions or become decorated with impurities near device surfaces), are prevented from forming. Denuded zones are established by subjecting wafers to a high temperature step.^{44,45,46} The oxygen near the top and bottom wafer surfaces thus diffuses out, reducing its concentration near the surface to about the solubility level




Fig. 2-16 Example of a thermal cycle to form the denuded zone.⁴⁸




Fig. 2-17 Effect of initial oxygen concentration on the denuded zone depth.⁴³

at that temperature. Denuded zones needed for a ULSI process must have a depth exceeding the deepest junction plus its surrounding space-charge region. Since the depletion region thickness depends on the wafer resistivity and the maximum operating voltage of the device, different devices made on the same substrate resistivity may need different denuded zone depths. Therefore, an important question that must be answered is: What is the shallowest denuded zone depth that the design and process can tolerate? There is no real shortcut to determining this information. Functional circuits must be fabricated on wafers containing a variety of initial oxygen levels. These circuits must be tested, and then cleaved and etched to determine the denuded zone depth and precipitate densities. Temperature cycles of 1100–1200°C for 30–240 min reportedly create denuded zones 10–40-μm deep. Figure 2-17 shows the outdiffusion depth for various temperatures and initial oxygen concentrations. Nitrogen and argon are typically suggested as appropriate ambient gases. However, it has been recommended that to avoid pitting, a thin oxide layer be grown before subjecting wafers to the high denuding temperature cycle ($\geq 1200^\circ\text{C}$) in these inert gases.⁴⁷

In *Step 2*, a lower temperature cycle (600–800°C) is next used to cause interstitial oxygen in the wafer bulk to form the nuclei required for the subsequent precipitation and gettering events of *Step 3*. The supersaturated (interstitial) oxygen can diffuse and homogeneously nucleate into small clusters if wafers are subjected to temperatures between 650–800°C for prolonged

periods (e.g., 4–64 hrs). Note that above 950°C, homogeneous nucleation appears to be negligible. Thus, the first temperature step on starting wafers (the denuding step) should be carried out at temperatures greater than 950°C, to prevent formation of clusters near wafer surfaces during this initial heat treatment.

A large number of relatively small oxygen clusters are formed by this step. This number, for a fixed temperature and time, depends on the oxygen content and increases with initial oxygen concentration. Since the oxygen content of the starting wafers is one important parameter that determines the density of oxygen clusters, it is crucial that this concentration be controlled in CZ silicon. Figure 2-18 shows the nucleation rate and final radius of the clusters that are created at 800°C for an initial oxygen content of 15 ppma.⁴⁷ If nucleation cycles are carried out at the lower end of the temperature range (~650°C), significantly longer annealing times are required to achieve a sufficient concentration of adequately sized clusters (16–64 hr). To enable an initial 650°C temperature to be used for this step, and yet allow a reduction in the overall nucleation cycle time, a *ramping up* of the temperature during *Step 2* has been suggested.^{42,49}

The rate of cluster formation can be enhanced by this procedure if the rate of change of the critical size, r_0 , with temperature, is smaller than the rate of growth of the clusters during annealing. That is, by the time a growing cluster reaches a higher temperature, it will have grown fast enough that its size exceeds the required r_0 at that temperature.




Fig. 2-18 Nucleation rate for oxygen precipitates. The curve is the expected rate of precipitate formation at 880°C.⁴⁷

The time to grow the clusters into precipitates that would be large enough to form the desired dislocations in the bulk is prohibitively long over the range of temperatures of *Step 2*. Thus, once the clusters have grown to a size where they exceed the r_0 of a higher temperature step, a third thermal cycle at that temperature can be used to grow the clusters into larger precipitates in a shorter time. If a temperature-ramping technique during the nucleation cycle is used, the final temperature can be that called for by *Step 3*.

In *Step 3*, wafers are heated to high temperatures (900–1250°C) for extended periods (4–16 hrs). At these temperatures, oxygen clusters of a sufficient size (i.e., $> r_0$) which were formed during *Step 2*, will grow (e.g., from 3–5-nm to ~50–100-nm in radius). Such growth is caused by diffusion of interstitial oxygen in the bulk to the SiO_x clusters, and reaction with silicon on the precipitate surface. For each SiO_2 molecule thus formed, a Si-self-interstitial is produced to accommodate the volume expansion. The large volume-change associated with the precipitation is not completely relieved by the emission of self-interstitials, and the precipitate builds up a strain field that can punch out prismatic dislocation loops (Fig. 2-19).⁵⁰

The self-interstitials emitted by the precipitate can also form dislocation loops as discussed in the section on *Bulk Defects* in Vol.1, Ch. 2. The dislocation loops contain an extrinsic stacking fault that grows by absorbing the self-interstitials emitted by the growing precipitate. The dislocations formed from both mechanisms act as the gettering sites which can trap fast diffusing impurities.

The ultimate size of the precipitates apparently also plays a role in the warpage resistance of the wafers. Kishino⁴² shows that wafer warpage increases




Fig. 2-19 a) Image of the core of a dislocation in Si obtained by high resolution TEM depicts an extra plane of atoms that terminates at the core of the dislocation. A precipitate is at the core.²⁴ (©1985 IEEE); b) Dislocation loops generated in Si due to prismatic punching by SiO_2 particles.²⁵




Fig. 2-20 Yield strength of Si showing the influence of oxygen precipitates.⁴²

with increasing precipitate size (Fig. 2-20). These data, and that of others,^{51,52} suggests that *Step 3* heat cycles that lead to precipitates larger than 200-nm in size can negatively impact production yield. Several reports have, in fact, indicated that the best wafers are those in which the precipitation occurs slowly and uniformly throughout the wafer (especially with good radial uniformity), and which results in small precipitates with attached precipitation defect complexes.^{53,54} The concern for wafer strength has lead most users of internal gettering away from materials with high oxygen levels (e.g., > 19 ppma), to material containing medium levels of oxygen (e.g., 15–19 ppma).

2.8.5 Summary of Gettering

Effective gettering is required to produce high-yielding ULSI. We have described a variety of gettering techniques, both extrinsic and intrinsic. In practice, more than one gettering mechanism has been simultaneously exploited in a wafer during fabrication. That is, the approach to gettering has been to deliberately implement more than one technique. An extrinsic, backside technique and an intrinsic gettering process were employed concurrently. Since typical CZ wafers contain oxygen in the appropriate range of 15–19 ppma, it is likely that many early IC processes had inadvertently benefited from intrinsic gettering. However, as low-temperature processes, and/or RTP, become more extensively utilized, and especially when 300-mm wafers are used, the use of intrinsic gettering can no longer be left to chance. The reduced thermal cycles in some cases, and the inability to use extrinsic gettering with 300-mm wafers will demand use of a

gettering technique which allows the placement of gettering sinks in the wafer bulk (and closer to the device regions). The intrinsic gettering method, however, does require the strict control of a number of oxygen-related processes, and this can be a complex task.

2.9 STATUS OF SILICON WAFER TECHNOLOGY IN 2000 AND FUTURE TRENDS

By the year 2000, most 200-mm wafers being used for ULSI IC fabrication were either: **1)** conventional lightly-doped polished CZ wafers (i.e., which exhibit a grown-in defect distribution characterized by central vacancy-rich region surrounded with an OSF-ring); or **2)** conventional heavily p -doped CZ-silicon-substrate-wafers covered with a lightly- p -doped epitaxial layer. Some of the polished wafers are subjected to a post-growth high-temperature annealing step in hydrogen or argon to decrease the density of COPs at the wafer surface (see Sect. 2.5). The polished-CZ-wafers rely on both external gettering methods (e.g., backside polysilicon) and internal gettering methods which require the presence of oxide precipitates to establish gettering sites in the bulk of the wafer. The p -epitaxial/ p^+ -wafers also employ these two gettering techniques, but are able to rely on the gettering capability of the heavily doped p^+ substrate as an additional gettering mechanism (especially for such impurities as Fe and Cu). The polished-CZ-wafers usually use a deliberate process step (or steps), to create a zone near the surface denuded of oxygen (i.e., a denuded zone), to prevent oxide precipitates from forming in the device regions. Epitaxial wafers do not need to establish a separate denuded zone, as oxygen is not incorporated into the epitaxial layer during the epi deposition step (and thus such wafers automatically have a denuded device region).

As devices are being scaled below $0.18\text{-}\mu\text{m}$ and the wafer sizes are increasing to 300-mm in size, a new set of wafers types with respect to: **1)** the grown-in defect characteristics they exhibit; **2)** the gettering methods they employ; and **3)** the denuded zones they possess, will be used. Let us examine each of these characteristics.

There appear to be four types of wafers that will be offered for processes below $0.18\text{-}\mu\text{m}$ and 300-mm wafers; **1)** “perfect-silicon” wafers; **2)** fast-pulled wafers; **3)** *epitaxy-optimized substrate* wafers (EOS); and **4)** “conventional” epitaxial wafers. The “perfect-silicon” wafers are described in Sect. 2.5. The fast-pulled wafers are described in Sect. 2.7. The EOS wafers are described in Sect. 2.9.1. We compare the advantages and disadvantages of these four types of “new” wafers in Sect. 2.9.2.

2.9.1 Epitaxy-Optimized-Substrate (EOS) Wafers

Epitaxy-optimized-substrate (EOS) wafers typically use a fast-pulled, lightly-*p*-doped wafer as the substrate, and cover it with a medium-*p*-doped, epitaxial layer that is thinner than those used in conventional epitaxial wafers. The epitaxial layer in EOS wafers is not deposited thick enough so that it contains the entire device region. Its role instead, is merely to cover the COPs so that they do not degrade the isolation leakage behavior of DRAMs (and also not degrade the GOI of thin gate oxides). As noted, the COPs created in the fast-pulled substrate (i.e., a silicon crystal which may also be doped with nitrogen) are small and are formed with high density.

A thin ($\sim 0.5\ \mu\text{m}$ thick), medium-*p*-doped epitaxial Si layer is thus deposited on a lightly-doped substrate. COPs are not formed in epitaxial layers because the epitaxial deposition temperature is much lower than the temperature encountered by the solidifying Si crystal in CZ growth. Thus, the vacancies created during the epitaxial process are in much lower concentrations (too low, in fact, to allow them to aggregate and form COP voids). In addition, it has also been demonstrated that the small COPs that are formed in the fast-pulled silicon which are covered with such a $0.5\text{-}\mu\text{m}$ -thick epitaxial layer are no longer detected with a surface scanning inspection system after an SC-1 delineation etch.^{55,56} In fact, more thorough experimental data indicates that substrate COPs are still present after epitaxial deposition, but their morphology is radically changed. Their dimensions significantly decrease after being covered by a thin epitaxial layer (their thickness is around 2-nm, compared to 13-nm before the epi deposition), with no dependence on epi thickness detected for epi layers from 0.5 to $3.0\text{-}\mu\text{m}$ thick. Data also show a 100% GOI yield for epi layers only $0.5\text{-}\mu\text{m}$ thick. Thus, on such EOS wafers, the effects of COPs is dramatically reduced with the use of a fast-pull crystal growth process and the deposition of a very thin epitaxial layer.

Note that since these EOS wafers start with a lightly *p*-doped Si substrate, for some applications a heavily doped *p*-type buried layer (formed with high-energy ion implantation) may also be implemented. This type of buried layer would allow the latchup and gettering benefits of the heavily doped p^+ -substrate (present in “conventional” epitaxial wafers) to be obtained on EOS wafers as well. EOS-type wafers are being offered commercially under such names as: fFLASH[®] (Wacker Siltronic AG), and Epi-II[®] (MEMC).

2.9.2 Comparison of Grown-In-Defect Characteristics of the “New” Wafers

The four “new” types of wafers for near-future generations of ULSI circuits and 300-mm can now be compared, especially with respect to the tradeoffs among

them involving low-grown-in defect densities, reliability of devices fabricated on each type, and cost:

1. "Perfect-silicon" wafers are beginning to be offered for mainstream production applications. However, the production of "perfect-silicon" wafers in large quantities presents some serious problems for the wafer manufacturers with respect to developing a cost-effective manufacturing process. That is, the pull-rate required to ensure "perfect-silicon" is slow, and this negatively impacts the throughput of the ingots that can be produced by an (expensive) crystal puller. Furthermore, the ingots must remain within the hot-zone of the puller for much longer periods of time, which increase the likelihood that a growth-disturbing event will occur during the growth cycle. This will further reduce the yield of acceptable ingots produced by a puller. Finally, a "perfect-silicon" growth-process must be developed for 300-mm wafers, which itself is a costly undertaking. In summary, the overall cost of "perfect-silicon" wafers for 300-mm wafer sizes may turn out to exceed the cost of even EOS wafers.

2. The fast-pulled (and perhaps also nitrogen-doped) wafers possess small-sized COPs, present in high densities. However, it has been demonstrated that the presence of COPs no longer degrades the GOI of oxides when the oxide thickness is smaller than 6.5-nm. As an example, it was reported that for MOSFETs fabricated with gate-oxides of 5-nm thickness, almost no COP failures were detected, independent of the size and density of the COPs in different crystals.⁵⁷ As a result, the use of fast-pulled wafers may be acceptable for many logic ICs, despite presence of the COPs (provided such circuit applications do not require the extremely low isolation leakage levels required by other products, such as DRAMs). Thus, such wafers might find use for a wide variety of CMOS IC circuit applications that use gate-oxide thicknesses of less than 6.5-nm-thick, built on 300-mm wafers. Of course, for some applications (such as 256-MB [and larger] DRAMS), the presence of a high-density of COPs might be the potential cause of such high leakage currents that this type of wafer would not be a suitable choice for them.

3. As described above, the EOS wafers use a lightly doped, fast-pulled substrate. Manufacturing such substrates can be achieved with higher throughput, and with a much-less-intensive process-development-effort than will be required for developing a "perfect-silicon" process for 300-mm wafers. In addition, the throughput and yield for such wafers will be

significantly greater than for "perfect-silicon" wafers. Finally, the cost of producing such thin epitaxial layers is significantly lower than that to produce the thicker epitaxial layers used in "conventional" epitaxial-Si-wafers (up to 15- μm thick). That is, the production cost of depositing the epitaxial layer on "conventional" epitaxial wafer is a significant part of the overall wafer cost. It is possible that when all of the factors that go into the cost of producing 300-mm "perfect-silicon" wafers are compared to those that go into the cost of producing EOS wafers, that the EOS production costs will be lower.

4. "Conventional" epitaxial wafers will also probably continue to be used in 300-mm wafers, for a number of reasons. First, the p^+ -substrate used in such wafers may provide latchup and gettering advantages for some circuit that may not be possible to achieve with either "perfect-silicon" or EOS wafers. The highly doped boron substrate enhances the formation of oxide precipitates as well as providing additional solubility gettering for impurity contamination. Second, a significant reduction in the epitaxial-to-polished wafer price-ratio is expected for 300-mm wafers, compared to that which existed for smaller diameter wafers. Finally, it has been observed that the COP density in highly- p -doped wafers ($2 \times 10^{19} \text{ cm}^{-3}$) is very low,⁵⁸ and that this contributes to the excellent GOI of gate oxides fabricated on p/p^+ epitaxial wafers. Thus, despite the fact that such "conventional" epitaxial wafers will likely cost more than the other wafer types, they may still be chosen for some circuits built on 300-mm wafers.

2.9.3 Gettering Methods and Denuded Zone Formation Techniques Employed with the "New" Wafers

As noted in Sect. 2.8.3, external gettering processes based on backside wafer treatments are not compatible with the double-sided-polishing standard adopted for 300-mm wafers. Consequently, 300-mm wafers will have to rely on internal gettering processes. However, gettering sinks are even more critical today, when device fabrication increasingly uses copper interconnects (which could potentially introduce a very fast diffusing impurity in both the device region of the IC and into the IC manufacturing process lines). Let us therefore now discuss the forms of intrinsic gettering that will be available with the "new" wafers described earlier.

In the "new" wafers in which the substrate background doping is low, the intrinsic gettering capability will have to rely on gettering produced with the

assistance of oxide precipitates in the bulk. In the “conventional” epitaxial wafers, the substrate is heavily-*p*-doped with boron. The formation of oxide precipitates is significantly enhanced by the heavy boron doping (allowing a sufficient number of oxide precipitates to be formed, even if the oxygen content in the silicon is low),^{59,60} and some additional solubility gettering will occur due to the heavily-doped substrate that does not occur in the wafers with lightly-doped substrates. Hence, gettering will, in general, be more effective in wafers that have the more heavily-doped substrates (and in particular for gettering Fe). Nevertheless, in one report, it was indicated that equally effective gettering can be obtained in both the lightly-doped and heavily-doped substrates, provided that the oxygen concentration in the lightly doped substrates exceeds $7 \times 10^{17} \text{ cm}^{-3}$.⁶¹ By co-doping the Si with nitrogen during crystal growth, the oxide precipitate densities can, however, be significantly increased. Such nitrogen doping also acts to reduce COP sizes, as noted earlier.

Thus, to enable the use of such lower-cost “new” wafers which have a lightly-doped substrate, adequate gettering capability must be exhibited with such a substrate. To ensure that sufficient gettering capability is available, either one of two approaches is being followed: 1) the wafers are being doped with nitrogen to enhance the number of oxygen precipitate nucleation sites; or 2) an RTP process that manipulates the excess-vacancy-profile throughout the wafer is employed, as this allows the density of oxygen precipitate nucleation sites to be controlled.

As described in Sect. 2.8.4, part of the gettering process involves forming a denuded zone that extends from the wafer surface to a depth that exceeds the region in which device structures are formed. That is, the denuded zone is a region that is devoid of oxygen precipitates. In the “new” wafers, such denuded zones must also exist. In the case of “conventional” epitaxial wafers, the epitaxial layer is a denuded zone because there is no oxygen incorporated into the epitaxial layer as it is deposited. Hence, no oxygen precipitation will occur within the “thick” epitaxial layer of “conventional” epitaxial wafers. For the other three “new” wafer types, the denuded zone is typically formed as in conventional polished wafers with high-temperature annealing steps ($>1000^\circ\text{C}$) to out-diffuse oxygen from the wafer near the surface (including the EOS wafers, in which the epitaxial layer is so thin that it does not extend deep enough to encompass the entire device region). It has been postulated that due to radical reductions in the total thermal budgets, the “conventional” methods of forming adequate denuded zones may no longer be cost effective.

2.9.3.1 Magic DeNuded Zones™: A novel way of producing the denuded zone has recently been introduced by MEMC called the *Magic Denuded Zone* (MDZ).^{TM,62,63} In this method the denuded zone (and the oxide precipitates within the bulk region of the wafer) are formed with the assistance of vacancy-concentration profiles that are introduced into the wafer with a Rapid Thermal Process (RTP) *prior* to the development of the oxygen precipitates in subsequent heat treatments. (Oxygen diffusion rates are much slower than vacancy diffusion rates in silicon.) The patented MDZ process creates a vacancy-concentration depth-profile that effectively pre-programs the oxide-precipitate-density in the bulk of the wafer, as well as the depth of the oxide-precipitate-free-zone to ideal targets. In late-2000 MEMC licensed this technology to Wacker Siltronic AG, another vendor of Si wafers, in a cross-licensing agreement involving a number of patents.

The physics of the Magic Denuded Zone concept is as follows: An otherwise perfect silicon crystal at any temperature above 0 K (e.g., room temperature) nevertheless contains an equilibrium-concentration of point defects, namely *vacancies* and *interstitials*. (For more details see Vol.1, Chap. 2, 2nd Ed.) The higher the equilibrium temperature, the higher are these concentrations. Consider a region in a bulk-silicon-crystal (i.e., far from any surface). If the crystal is heated above room temperature, thermal generation will create equal numbers of *additional* (or *excess*) vacancies and interstitials (vacancy-interstitial pairs). As long as the silicon is kept at an elevated temperature, such higher equilibrium-concentrations of point-defects will be sustained. However, if the silicon is returned to room temperature, the excess vacancies and interstitials will annihilate each other by a reverse process, i.e., recombination. Such recombination of excess point-defects will continue until the room-temperature equilibrium concentrations are restored.

The events that take place when a Si-crystal *wafer* is heated differ dramatically from when a region deep within the *bulk* of a Si-crystal is heated, due to the presence of *surfaces relatively close to any point within the silicon wafer*. The proximity to such surfaces radically alters the relative concentration of vacancies and interstitials in the heated wafer. This alteration in the relative concentrations of the two point defect types occurs for two reasons: 1) interstitials are about 10 times as mobile as vacancies; and 2) when either an interstitial or vacancy arrives at the surface, it is quickly annihilated. That is, when an interstitial arrives at a surface, it will quickly occupy one of the plentiful (vacant) surface lattice sites. Likewise, a vacancy moving onto a lattice site is really just a silicon atom moving from one filled site to an adjacent empty one. Since interstitials can move

more quickly to any nearby surfaces, most vacancies trail behind. (Note that since thermal generation of interstitial-vacancy pairs is a continuous process, some vacancies are always able to recombine with interstitials. But, since the new interstitials also migrate more rapidly to the surfaces, there are always fewer interstitials within the bulk of a wafer than vacancies.) In other words, because of the inequality in point-defect mobility, and the presence of nearby surfaces, a net steady-state excess-vacancy-concentration will exist within a heated silicon wafer. The length of time from when a silicon wafer is heated to when the concentration values of interstitials and vacancies reaches their new, steady-state values is very fast – on the order of a few seconds.

If the wafer temperature is reduced to a value below its initial heated temperature (but to a value still higher than room temperature), the concentration of excess vacancies in the silicon will also eventually decrease to a new, lower, steady-state value. However, the process by which this reduction takes place in a wafer is a combination of: 1) recombination; and 2) the diffusion of vacancies to the surfaces from locations of higher concentration deep within the wafer.

The diffusion of vacancies is also dependent on temperature. At temperatures in the vicinity of 1000°C the vacancies can diffuse rapidly to the surfaces of the wafer (but of course, more slowly than the interstitials), but at room temperature the vacancy diffusion is so slow that the vacancies can be considered essentially immobile. Thus, if a heated wafer is rapidly cooled to room temperature, the concentration profile of excess vacancies within the wafer is “quenched in.” In addition, by controlling the intermediate wafer temperature (and the time during which the wafer is kept at that intermediate temperature), the concentration of vacancies that will be “quenched in” at the surface can also be controlled.

MEMC has invented the MDZ process that uses RTP to produce vacancy-concentration-profiles within a wafer that are well-suited for internal gettering techniques. That is, it is known that the rate and oxygen concentration dependence of oxygen clustering can be substantially modified and controlled by the concentration of vacancies present (as was learned from studies of the oxide precipitate formation in the OSF-ring region of the wafer as was described in Sect. 2.3.2). MEMC determined that in regions of the silicon containing high concentrations of “quenched in” vacancies, the rate of formation of oxide nuclei is dramatically increased, whereas in regions where the concentrations are lower, the oxide nuclei formation rate is much slower. Thus, by creating a profile in which vacancies deep in the wafer bulk are high in concentration, the number of oxide precipitates that form there will also be high. Near the surface (and to the desired depth), the vacancy concentration is tailored to be much lower. Thus, in

such near-surface regions oxide precipitate formation essentially does not occur, even in the presence of relatively high concentrations of oxygen. Thus, a “true denuded zone” near the silicon surface can be produced with a short RTP process after the wafers are formed - instead of with a long, high-temperature process for out-diffusing the oxygen (and which MEMC argues is not a “true denuded zone” because some oxygen nuclei may still remain from the time the oxygen concentration was high enough to have allowed them to form). On the other hand, in Si wafer regions below the denuded zone at the surface, a high number of oxygen precipitates forms, permitting an effective internal gettering scheme to be implemented. No special processing of the silicon during ingot growth (such as nitrogen doping during ingot growth) is necessary with this method.

By using the MDZ process, the density of oxide-precipitates and their depth distribution are completely decoupled from the oxygen and crystal growth influences and details of the IC thermal processes. The precipitation performance is completely controlled by the engineered vacancy-concentration-profile. In addition, the denuded-zone-depth and bulk-oxygen-precipitate-density may be engineered independently *of one another* by this technique. The denuded zone is also formed without the requirement of oxygen out-diffusion. The entire MDZ process is accomplished in less than one minute, and is therefore much faster if compared to the average oxygen diffusion process (that takes several hours).

MDZ provides internal gettering that is nearly independent of initial oxygen concentration, wafer position along the ingot, and thermal history effects. Since the MDZ process is also independent of the crystal growth-process, accurate MDZ performance may be achieved on any type of wafer. This means that the oxygen precipitation process is effectively decoupled from the crystal-growth-related intrinsic-point-defect issues.

2.10 FROM INGOT TO FINISHED WAFER: SLICING, ETCHING, and POLISHING

After a single crystal ingot has been grown, a complex sequence of shaping and polishing steps are performed to produce starting material suitable for fabricating semiconductor devices (*wafers*).^{65,74} The wafering process for 300-mm wafers has been modified to some degree compared to ones used for previous wafer generations. We will emphasize those differences in this section. Figure 2-21 shows a flow chart depicting a generic 300-mm wafer shaping process. Figure 2-22 also illustrates this *wafering* procedure, which includes the steps covered next.

2.10.1 Ingot Evaluation

The grown single crystal ingot undergoes routine evaluation of resistivity, impurity content, crystal perfection, size, and weight. Sections of the ingot that

are crystallographically defective, irregularly shaped, or undersized, are cut off and discarded (as are the seed and butt [or *tang*] ends). Loss of the ingot material may approach 50% at this point.

2.10.2 Ingot Surface Grinding

Since ingots do not grow perfectly round, nor with sufficiently uniform diameters, they must be shaped to the desired form and dimension. Thus, ingots are deliberately grown larger than the final desired wafer diameter and a grinding operation removes the excess material to reduce as-grown crystals to a cylindrical shape of precise diameter. (Exact diameter dimensions are required to make wafers compatible with automated handling procedures.) Since silicon is a hard, brittle material (registering 72.6 on the Rockwell "A" hardness scale), grinding machines with diamond wheels are used to perform this cylindrical shaping process. The grinding step is followed by an etch step that removes the grinding work-damage. The ingot diameter is reduced 0.25-1.0-cm by the grinding and etch steps.

2.10.3 Grinding Flats or Notches on the Ingot for Orientation Purposes

For wafers up to 150 mm, *flats* are used for aligning and crystal orientation. For larger wafers ≥ 200 mm, *notches* are predominantly used (see Fig. 2-23). For 300-mm wafers, notches are used exclusively. These features are next ground along the length of the ingot. The largest flat, called the *primary flat*, is usually positioned relative to a specific crystal direction. (The primary flat orientation is found by using X-rays to produce a Laue photograph.) The primary flat is used for several purposes. Automated wafer handling equipment utilizes the primary flat to obtain correct alignment, and in addition, devices on the wafer can be oriented to specific crystal directions with this flat as a reference. Smaller flats are called *secondary flats*, and they are utilized to identify the orientation and conductivity type of the wafer. Since automated equipment relies on the flats for correct operation, the flat dimensions must be precisely machined. For example, the flat or notch is placed perpendicular to a $\langle 110 \rangle$ direction on a (100) wafer.

2.10.4 Sawing the Ingot into Slices (Wafers)

The sawing operation^{66,74} that produces silicon slices from the shaped ingot also defines the surface orientation, thickness, taper, and warp of the slice. The ingot is rigidly mounted to maintain exact crystallographic orientation during the sawing process. Wafers of $\langle 100 \rangle$ orientation are normally cut "on orientation" (e.g., within $\pm 0.5^\circ$).




Fig. 2-21 Flow chart depicting the steps involved in wafer preparation starting with a whole Si ingot.

Wafer thickness is primarily set by the sawing operation, although some material is also removed by subsequent operations (e.g., for a 200-mm wafer of final 725- μm thickness, a total of ~ 1250 μm of ingot silicon is needed: 725- μm final wafer thickness; 400- μm for kerf loss during sawing; 50- μm lapping loss; 50- μm etching loss; 25- μm polishing loss. Thus, about 8, 200-mm wafers per linear cm of ingot can be produced. As wafers get larger they must be thicker (Table 2-1) to allow them to withstand thermal processes (e.g., epitaxy and

oxidation) and handling during fabrication. Thus, fewer wafers per unit length of ingot are possible than for smaller wafers.

The most common mode of slicing has been *inner diameter (ID) slicing* (Fig. 2-24) using stainless steel blades with diamond particles bonded to their edges.⁷⁴ Continuous monitoring with blade-deflection sensors is required to assure that slices are sawn adequately free of bow, taper, work damage, and saw marks. Cutting speeds are in the neighborhood of 0.05 cm/sec. Since one slice is cut at a time by the saw, this is a relatively slow process.

Wafers with 300-mm diameters are sawn with slurry-coated wires instead of inner-diameter saws. More slices per inch of ingot are possible due to smaller kerf loss (kerf loss is reduced by approximately 30% compared to the ID saw).⁶⁷ In addition, wire sawing enables the silicon slicing to be carried out at higher throughput and superior mechanical properties, such as reduced bow and warp. Figure 2-25 shows a schematic of multiple-wire saw. In this arrangement, parallel, equally spaced and properly tensioned stainless steel wires spun across two pulleys are part of single stainless-steel wire winding through a complex set of pulleys. Cutting of multiple slices results when the ingot is pressed against the traveling wires under injection of slurry. Although the cutting rate is much slower than the ID saw (the ordinary ID saw has a 80-100 times higher sawing




Fig. 2-22 Graphical depiction of the steps in the wafering process.




Fig. 2-23 a) Identifying flats on a silicon wafer; b) Notched wafers.

rate), as many as 300 slices can be produced simultaneously. Since slicing by the multi-wire saw is actually the result of low speed grinding action by the slurry, improved bow, warp, TTV, and taper are much more easily obtained than with the ID saw.

2.10.5 Laser Marking the Wafers

A technique using a *laser* to create an alphanumeric (or bar code) identification mark on the front of the wafer near the primary flat or notch (Fig. 2-26) is then employed. *Laser marking* according to SEMI⁶⁸ Std. M 1.8, specifies an 18 character field to identify the wafer manufacturer, conductivity type, resistivity, flatness, wafer number, and device type. This allows each wafer to be identified. Wafer traceability, correlation of device characteristics produced on a wafer with the wafer properties, and the ability to prevent in-process rejected wafers from being re-inserted into the fab line are all benefits of utilizing wafer marking.




Fig. 2-24 ID saw geometry.⁶⁶

Automatic code readers at various stages of processing can also track wafers and provide data on wafer movement in the fab.^{69,70}

2.10.6 Lapping and Grinding the Wafers

The thickness of the as-sawn slices is sufficiently variable that a *lapping* and *grinding* step is next employed to bring all slices to within the specified thickness.




Fig. 2-25 Wire sawing an ingot to produce wafers.




Fig. 2-26 a) SEM of letter "A" marked on wafer after it appears as marked on lapped wafer (left), after wafer has been etched (center), and after polishing. Courtesy of Wacker Siltronic; b) SEMI specification for marking vendor codes on wafers. Dimensions are specified along flat on wafer; c) SEMI specifications for 18-character vendor code. SEMI standard, used with permission.

tolerance. The lapping takes place between two counter-rotating cast-iron plates in the presence of an abrasive slurry, usually a mixture of micron-sized alumina or silicon carbide particles suspended in a solution. This step also serves to reduce bow and warp, and to increase slice flatness. Both sides of the slice are lapped using a mixture of Al_2O_3 and glycerine, and a succession of increasingly finer polishing grits is used in multiple lapping steps. This process can achieve flatness uniformities of $2\text{-}\mu\text{m}$.

2.10.7 Removal of Surface Mechanical Damage by Chemical Etching

The work damage and contamination caused by the previous mechanical grinding, sawing, and lapping steps must be removed. This is done by chemically etching away the resultant damaged and contaminated layer.⁷¹ The wet etch procedure for this step typically utilizes an etchant solution of hydrofluoric (HF) and nitric (HNO_3) acid (with modifiers such as acetic acid) to attack the silicon. The surface material removal is the result of two-step reactions. The Si surface is first oxidized by the nitric acid to form silicon oxide, and this oxide removed by the HF. A relatively non-porous and clean wafer backside is also produced by this step. Note that etching of the wafer may be repeated after the subsequent operation of edge rounding.

2.10.8 Rounding the Wafer Edge (and Notch)

The edges of the silicon slices are then shaped (rounded) as shown in Fig. 2-27. Edge rounding substantially reduces the incidence of chipping during normal wafer handling, and helps minimize film buildup on the edge of the wafer during photoresist and epitaxial processes. (Edge-chip defect sites are known to nucleate plastic deformation [or *slip*] during subsequent thermal processing steps).⁷² The shape of the rounded edge profile usually follows an industry standard (i.e., SEMI standard) in which the edge profile fits within the boundary of a standard template.

2.10.9 Edge Polishing of the Wafers

Particle contamination reduces yield. In advanced, submicron IC processing some of the major sources of particles are the process equipment and the wafer itself. Defects found on the wafers during the device fabrication sequence are often caused by tiny chips of silicon from the wafer, or by particles removed from the process equipment. This abrasive effect is caused by the contact of the silicon wafer with the process equipment, and can be influenced by the smoothness of the contact area, primarily the wafers edge.

Wafer edges of as-sawn wafers are sharp and prone to chipping (Fig 2-27a). As a result, after sawing, wafers are generally subjected to a grinding process that rounds the wafer edge (with much of the edge-grinding damage being later removed during the wafer-surface etching process). This results in a wafer edge that is rounded, but is not perfectly smooth, as shown in Fig. 2-27b.⁶⁴ Such relatively rough edges still produce enough particles to reduce the yield of ICs, when compared to the yields obtained when these edges are polished after the edge has been etched to remove the grinding damage. That is, after edge-polishing the wafer edge is perfectly smooth, as shown in Fig. 2-27c, and indications are that the defect density on wafers is reduced if their edges are so polished. For the future generations of ICs that will produced on 300-mm wafers, the benefit of edge-polishing should be even more pronounced. That is, the wafer-edge area increases with increasing wafer radius and thickness. In addition, it appears that other particle sources on the wafer topography (such as the notch and deep laser scribe marks), must also be polished (or in some other way smoothed) to further reduce defect density.

2.10.10 Chemical-Mechanical Polishing of the Wafers

A chemical-mechanical polishing⁷¹ step is used to produce the highly reflective, scratch- and damage-free surface on one or both sides of the wafer. This is




Fig. 2-27 a) Wafer edge-rounding process; b) Edge-rounded wafer; c) Non-edge rounded wafer; d) Mechanical strength of edge-rounded vs. non-edge-rounded wafers; e) Edge-rounded, but non-polished wafer; f) Edge-rounded, polished wafer.

accomplished by mounting unpolished slices onto a carrier, and then putting them on a polishing machine. There, a powered platen drives an appropriate polishing pad material across the wafer surface. A colloidal silica slurry of sodium hydroxide and fine (~ 10 -nm) SiO_2 particles is dripped onto the table. The frictional heat of the sliding mounted wafers causes the sodium hydroxide to oxidize the Si (i.e., the chemical part of the process). The oxide is then abraded away by the silica particles (i.e., the mechanical part). Figure 2-28 shows the

wafer thickness and surface roughness changes as it undergoes the various grinding, lapping and polishing processes.

For 300-mm wafers, double-sided-polishing will be standard (instead of the single-sided-polishing used up to the 200-mm wafer sizes). Double-sided polishing (CMP on both the front and back surfaces simultaneously) has been found to result in superior flatness than single-sided polishing.

The wafer preparation via mechanical methods (i.e., grinding, CMP, etc.) has its limits in the degree of flatness that can be obtained. To supplement and fine tune the local lithography for further improvement in local flatness, tools that can carry out such processes as *plasma-assisted chemical etching* (PACE) have been developed.⁷³ Such a tool employs a spatially confined plasma with a scanning mechanism to allow material removal to be controlled as desired over the wafer surface. The PACE utilizes low-energy ions (i.e., $\ll 1$ eV), instead of the energetic ions that are employed in reactive-ion-etching. Therefore, PACE produces minimum or no subsurface damage.

2.10.11 Cleaning the Wafers

Following the polishing cycle (in which a layer of silicon about 25- μm -thick is removed) the wafers are subjected to series of chemical dips and rinses to remove the polish slurry. A cleaning process concludes this step. This is a very important




Fig. 2-28 Wafer thickness and surface roughness changes during grinding and polishing.

step as the silicon wafer must be free of contamination before it is shipped to the device fabrication facility. Chemical cleaning is effective in removing contaminants from the wafer surface. The “RCA Clean” (see Vol. 1, Chap. 5) is widely used to clean the wafer before shipping.

2.10.12 Depositing Epitaxial Silicon Layers on the Wafers

Epitaxial layers are required for some ULSI process technologies. Wafer manufacturers are now supplying silicon wafers with a variety of epitaxial layers for CMOS ULSI technologies. Another option being offered is a layer of polysilicon or mechanical damage on the backside of the wafers for extrinsic gettering purposes.

2.10.13 Shipping 300-mm Wafers: Its Impact on the Evolution of Wafer Shipping Boxes

An inspection, followed by packing in a particle-free package finishes the wafering sequence. The box used to ship 300-mm wafers is called a *front-opening shipping box* (FOSB, pronounced *fos-bee*). FOSBs cost approximately 10 times as much as the boxes that are used to ship 200-mm wafers. The main reason for this cost discrepancy is that the 300-mm wafer is more susceptible to breakage because it is *proportionately* thinner than previous diameters. Consequently, the shipping package must provide more protection. In addition, the FOSB must be more rigid in order to interface with automated load ports.

Since the cost is so high, it must be possible to re-use the FOSB. In fact, as shown in Fig. 2-29, if the FOSB is used only once, the cost per wafer to use it is ~\$15, whereas if it is reused 10 times, the cost per wafer drops to ~\$7. Neverthe-




Fig. 2-29 The cost/reuse of a FOSB levels off at \$7/wafer.

less, the overall cost of the box to ship the wafer is at least 55% higher for 300-mm wafers than for 200-mm wafers.

One topic being discussed concerns the issue of FOSB ownership. One proposal before the SEMI 300-mm Wafer Shipping Box Taskforce is that manufacturers become owners of the FOSB. That is, since device manufacturers want a guarantee of wafer cleanliness, the best way to supply this is to maintain completely control the FOSB history. Ownership of the FOSB makes this possible. The protocol for using the FOSB is to remove the wafers upon receiving them from the wafer supplier, to then seal the FOSB in a polypropylene bag and ship it back to the wafer producer. The FOSB is like a wafer. Once it gets contaminated, it becomes hard, or impossible to clean.

2.11 SPECIFICATIONS OF SILICON WAFERS FOR VLSI

There are many properties that a wafer must exhibit (Table 2-2) in order to be an appropriate starting substrate for the fabrication of VLSI and ULSI. Table 2-3 provides some typical specification ranges for 125-, 150-, and 200-mm diameter CZ wafers. Figure 2-30 graphically summarizes the qualitative characteristics desired in 200-mm device quality Si wafers for ULSI circuits.⁷⁵ The semiconductor industry has seen quality improvements in Si crystals grown by the CZ technique continually over the years. In today's emerging sub-0.13- μm IC manu-

Table 2-2. COMPARISON OF MATERIAL PROPERTIES AND REQUIREMENTS FOR VLSI AND ULSI

Property	Czochralski	Float Zone	Requirements for ULSI
Resistivity (phosphorus) <i>n</i> -type (ohm-cm)	1–50	1–300 and up	5–50 and up
Resistivity (antimony) <i>n</i> -type (ohm-cm)	0.005–10	–	0.001–0.02
Resistivity (boron) <i>p</i> -type (ohm-cm)	0.005–50	1–300	5–50 and up
Resistivity gradient (four point probe) (%)	5–10	20	< 1
Minority carrier lifetime (μs)	30–300	50–500	300–1000
Oxygen (ppma)	5–25	Not detected	Uniform and controlled
Carbon (ppma)	1–5	0.1–1	< 0.1
Dislocation (before processing) (per cm^2)	≤ 500	≤ 500	≤ 1
Diameter (mm)	up to 300	up to 100	up to 300
Wafer bow (μm)	≤ 25	≤ 25	< 5
Wafer taper (μm)	≤ 15	≤ 15	< 5
Surface flatness (μm)	≤ 5	≤ 5	< 1
Heavy-metal impurities (ppba)	≤ 1	≤ 0.01	< 0.001

TABLE 2-3 SPECIFICATIONS FOR SINGLE-CRYSTAL SILICON WAFERS

Parameter	150 mm	200 mm	300 mm
Diameter (mm)	150 ± 0.2	200 ± 0.2	300 ± 0.1
Thickness (μm)	675 ± 25	725 ± 20	775 ± 25
Primary flat length (mm)	55–60	notch	notch
Oxygen content (ASTM '79) (ppma)		$\geq 23 \pm 2$	$\geq 22 \pm 1.5$
Flatness (μm) (GTIR)	1.5	1.5	1.5
Site Flatness (μm) (SFQD)		± 0.17 (1998)	± 0.12 (2001)
Surface orientation	(100)	(100)	(100)

facturing, 200-mm and 300-mm wafers must meet ever tightening wafer quality requirements in terms of the crystalline defects, heavy-metal impurities, oxygen level, oxygen radial uniformity, minority-carrier lifetimes, particles, and flatness.

Note that these specifications have also become tighter with increasing wafer size due to automatic wafer handling and photolithographic requirements. ADE Corporation is the major supplier of tools used to measure many of these specifications. While 300-mm wafers are just being introduced into full-scale IC production, the required quality as updated in the 1999 *Technology Roadmap for Semiconductors* (Table 2-4, p. 69) will be met by further developing and refining crystal growth technology being applied and developed for 200-mm wafers, particularly as it is applied to point-defect and secondary-defect control, and the control of oxygen.

Some questions have arisen, however, about whether some aspects of wafer “goodness” may be specified too tightly, especially with respect to contaminant levels in the silicon. That is, it may be necessary to balance “best wafer possible” against the cost of ownership opportunity of not driving silicon requirements to the detection limit, but to some less stringent value consistent with achieving high yield. This issue is important, as the cost of a 300-mm wafer is projected to account for as much as 30% of the total IC wafer processing cost.⁷⁶

There has been a variety of data in the literature to support such a view.⁷⁷ One example, described earlier, is that the specification on the limits of COPS and metals may be relaxed for device technologies in which thinner gate dielectrics are employed. For example, at gate-oxide thicknesses of 5-nm or less, the influence of COPS on gate-oxide-integrity (GOI) has been found to become negligible for CZ polished wafers.⁷⁸ (On the other hand, at the 0.1- μm node, the device features will approach the size of the void diameters, and this might cause




Fig. 2-30 Silicon wafer structure required for ULSI.⁶⁵

shorts, e.g., between adjacent trench capacitors in a DRAM.) Furthermore, gate oxidation is generally performed after a number of prior thermal processes which typically annihilate near-surface COPs, thereby reducing whatever residual influence these defects may have on the GOI. In addition, in epitaxial material, the COPs are covered up to a depth beyond $\sim 100\text{ nm}$, essentially negating their influence. Accordingly, the necessity of using “perfect-silicon” (while being a remarkable scientific achievement, see Sect. 2.6), apparently needs to be reassessed for future generations of ICs from a cost-of-ownership perspective.

The implications of thin-gate-oxides for the specification of the metal levels in the Si wafer are based on the paradoxical fact that the integrity of thinner gate oxides may be less compromised by metals than is the integrity of thicker oxides.⁷⁹ A second reason that the maximum allowed levels of metal in the silicon may be allowed to be increased is that cleaning technologies have been improving, allowing the incoming critical metal level specifications to be somewhat higher than those now in use. This is because the improved cleaning processes drive the initial levels of metal down to an operational level that is an order of magnitude smaller than the initial level.

The utilization of multiple-well structures fabricated by ion-implantation in effect decouples the MOSFETs from the original silicon material characteristics. This reduces the sensitivity of these devices to the initial resistivity- and uniformity-tolerance of both CZ polished and epitaxial wafers. Whereas the nominal substrate doping for epitaxial wafers is typically in the range of $\sim 5\text{-}10\text{ m}\Omega\text{-cm}$ (to ensure latch-up control), shallow-trench-isolation (STI) is rendering

classical concerns for latch-up, such as n^+p^+ spacing moot. Accordingly, resistivity ranges $\geq 20\%$ may be acceptable, also favorably impacting CoO.

Internal gettering (IG) in CZ-polished-Si wafers will still be required to remove deleterious metallic contaminants inadvertently introduced during IC processing. A ± 2 ppma variation in bulk oxygen concentration in the range ~ 18 -31 ppma (old ASTM standard) may be sufficient to ensure stringent bulk defect control with an acceptable homogeneous IG capability. Adequate wafer strength and resistance to warpage, along with denuded-zone width control, is also required. The utilization of heavily-boron-doped substrates for epitaxial wafers also offers an effective IG capability, especially for gettering Fe.

In summary, it appears that calling for further reduction of various contaminants and defects in Si wafers (and the continued drive to reduce certain other wafer specifications) may not necessarily be required to ensure continued improvements in IC performance.

2.12 THE ECONOMICS OF SILICON WAFERS

As discussed earlier, the size of silicon wafers has been continuously increasing. The motivation for using larger wafers is economic, and here we discuss this issue. The economic benefits of larger wafers are gained from the additional silicon area they provide (Fig. 2-31). If the manufacturing cost per wafer remains constant (or if its percentage increase is smaller than the percentage increase in silicon area) a reduction in the manufacturing cost per chip may be possible.

Let us address the issue of the silicon wafer costs. We see from Fig. 2-32 that the cost per square inch of silicon on a given wafer size is highest when the new wafer size is first introduced, but then drops with time.⁸⁰ For 125-mm prime

Diameter Increase	Percentage Area Increase
2" $\rightarrow$ 3"	125%
3" $\rightarrow$ 100 mm	78%
100 mm $\rightarrow$ 125 mm	56%
125 mm $\rightarrow$ 150 mm	44%
150 mm $\rightarrow$ 200 mm	78%
200 mm $\rightarrow$ 300 mm	125%

Diameter	Area (Sq. Inches)
2 Inch	3.1
3 Inch	7.1
100mm	12.6
125mm	19.6
150mm	28.3
200mm	50.2
300mm	109.5

Fig. 2-31 The increase in silicon wafer area with increasing wafer diameter.

device wafers the minimum silicon cost reached $\sim \$1/\text{in}^2$. For each succeeding wafer size the minimum cost/ in^2 is expected to be 1.4x the cost of the previous generation. Thus, for 200-mm wafers the silicon cost is $\$2/\text{in}^2$, resulting in the minimum cost of prime bulk CZ wafers of this size being $\$80\text{--}\100 . The cost of 300-mm wafers is expected to eventually decline to somewhere above $\$3/\text{in}^2$, with a single bulk-CZ wafer thus eventually costing $\$350\text{--}\400 . In 1998, the cost of prime 300-mm wafers was $\sim \$1000$. Note that adding an epitaxial layer to the wafer approximately doubles the wafer cost, and the cost of 200-mm epi wafers in 1998 was $\$150\text{--}\180 .

The cost/ in^2 increases with wafer size for a number reasons. First, larger wafers are thicker, meaning fewer wafers per cm of ingot length are produced. Second, a smaller percentage of the electronic-grade polysilicon (EGS) ends up in prime wafers. (For 150-mm wafers this percentage was 30%, for 200-mm wafers it dropped to 17%, and for 300 mm wafers it is expected to be only $\sim 10\%$.⁸¹) Third, wafer specs are tighter for each generation, reducing the "sweet spot" in the middle of the ingot that yields prime wafers. Finally, epi may be required for DRAM production on 300-mm wafers, which will create a steep rise in average price of prime wafers.

Note that the consumption of wafers of a given size also varies with time (see Fig. 2-33), and each new wafer size remains in production for about 24 years.⁸² For example, production of 150-mm wafers began in the late 1970s, and their consumption rate peaked in 1997. Their use in production is expected to be phased out by about 2010. Next, 200-mm wafers were first introduced in 1988, and they are expected to reach their peak consumption rate sometime between 2005 and 2010 (depending on the rate of ramp up of the new 300-mm wafer generation).⁷² By 1998, however, full-scale-production IC factories using 300-mm wafers were not yet running. As a result, well-designed 200-mm equipment is predicted to have a long working life before it is made obsolete by future wafer-fabs running larger wafer sizes.

The worldwide consumption of single-crystal silicon has been growing at 15–20% per year. In 1992, about 1.9 billion in^2 of silicon were sold. By 1994 this number was 2.7 billion in^2 , and by 1999 it had increased to ~ 4.5 billion in^2 . In 1994 this translated to a total production of about 100 million wafers. These sales generated an income of $\$5.9$ billion US in 1999.^{83,84} There are a relatively large number of silicon wafer suppliers. In the late 1990's the largest were Shin-Etsu Handotai (SEH: Japanese), MEMC (German); Wacker-Siltronic (German); Sumitomo-Sitix (Japanese); Mitsubishi Materials Silicon (Japanese); and Komatsu (Japanese).





Fig. 2-32 a) Actual wafer pricing cycle by wafer diameter. Reprinted with permission of Semiconductor International.⁷⁰ b) Photograph of a 300-mm wafer. Courtesy of MEMC.

The silicon wafer industry historically funded its R&D and capacity expansion for the next generation, large-diameter wafer through the profits and cash flow from the previous-generation wafers. However, in the 2000-year timeframe the industry was being asked to fund the 200-mm and the 300-mm generation at the same time. According to the Rose Associates this is unprecedented, especially in an industry that lost nearly \$1 billion in 1998 on sales.⁸⁵ These losses resulted from the semiconductor industry downturn, the Asian financial crisis, and excess silicon wafer capacity that combined to cause the average selling price of silicon wafers to fall by 36% over the three year period ending in mid-1999. This caused the industry to focus on cost reduction for survival. While losses in 1999 narrowed, and profitability returned in 2000, the profit outlook was still uncertain. Unless the profitability continues to improve, the funding for 300-mm development will compete with the economics of 200-mm growth and capability requirements.

One possible scenario will be that there will be a shortage of wafers in the 2000 timeframe, especially 300-mm wafers. One vehicle for alleviating this shortage is to use reclaimed wafers, especially for the role of test wafers used in process development applications. That is, during the development and marathon testing of wafer-manufacturing tools, reclaim wafers provide an excellent opportunity to re-use materials. While the maturation of 200-mm processes has greatly reduced the need for test wafers, their use will increase as the 300-mm processes enter the mainstream manufacturing arena. The price of 300-mm




Fig. 2-33 The 24-year single-diameter cycle of silicon wafers.⁸²

Selected near-term general characteristics and polished wafer requirements for silicon*							
TABLE 2-4							
□ = Solutions exist = Solutions being pursued ■ = No known solutions							
Year	1999	2000	2001	2002	2003	2004	2005
Technology node (nm)	180			130			100
Wafer diameter (mm)*	200	300**	300	300	300	300	300
Defined limit values							
Edge exclusion (mm)	2	1	1	1	1	1	1
Front surface particle and COP size (nm)	≥90	≥82.5	75	65	60	55	50
Particles and COPs (cm ⁻²)***	≤0.13	≤0.12	0.12	0.14	0.13	0.12	0.10
Particles and COPs (#/wt) ***	≤38	≤84	80	95	89	84	72
Critical surface metals (aU/cm ²)	≤1.8x10 ¹⁰	≤1.4x10 ¹⁰	≤1.2x10 ¹⁰	≤8.8x10 ⁹	≤6.8x10 ⁹	≤5.8x10 ⁹	≤4.9x10 ⁹
Site flatness (mm)	≤180	≤165	≤150	≤130	≤120	110	100
Oxygen (center point value ±2.0 ppm)	19-31	18-31	18-31	18-31	18-31	18-31	18-31
Total bulk Fe (aU/cm ³)	≤1x10 ¹⁰	<1x10 ¹⁰	<1x10 ¹⁰	<1x10 ¹⁰	<1x10 ¹⁰	<1x10 ¹⁰	<1x10 ¹⁰
OSFs DRAM (cm ⁻²)	≤4.4	≤3.9	≤3.4	≤2.8	≤2.5	≤2.2	≤1.9
OSFs MPU (cm ⁻²)	≤3.1	≤2.5	≤1.9	≤1.5	≤1.4	≤1.1	≤1.0
Recombination lifetime (μm)	≤305	≤350	≤350	≤350	≤350	≤350	≤350

* Significant gaps in metrology and wafer manufacturing equipment need to be closed on 200mm, especially for the 180nm and 130nm nodes

** Values are for 300mm, although 200mm will be the dominant wafer diameter

*** The total allowable, front-surface, light-scattering defect density is the sum of crystal originated pits (COPs) and particles

* The complete Table 34A in the 1999 *International Technology Roadmap for Semiconductors* includes other parameters and requirements for epitaxial and SOI wafers

reclaim wafers is about 60% of the price of virgin wafers. Reclaim wafers in 2000 represented about 10% of the 300-mm market.⁸⁶

REFERENCES

1. G.K. Teal, *IEEE Trans. Electron Dev.*, **ED-23**, 621 (1976).
2. R.N. Thomas *et al.*, "Melt Growth in Large Diameter Wafers: Part II," *Solid State Technology*, April 1990, p. 163.
3. J.G. Park, *et al.*, "Effect of Defects such as COPs, Large Dislocations and OSF-Ring on Device Integrity Degradation. *Mtg. Abs. Electrochem. Soc.*, Spring 1999, Abs. 343.
4. V.V. Voronkov, *J. Crystal Growth*, **59** (1982) p. 625.
5. T. Sinno *et al.*, "Point Defect Dynamics and Oxidation-Induced Stacking Fault Ring in CZ Silicon Crystal," *J. Electrochem. Soc.*, **145**, p. 302 (1998).
6. T. Sinno, R.A. Brown, "Modeling Microdefect Formation in CZ Silicon," *J. Electrochem. Soc.*, **146**, p. 2300 (1999).
7. M. Itsumi *et al.*, *Jpn. J. Appl. Phys.*, **35**, 812 (1996).
8. M. Itsumi *et al.*, *J. Appl Phys*, **78**, 5984 (1996).
9. K.-M. Kim, "Silicon-Pulling Technology for 2000+," *Solid State Technology*, January 2000, p. 72.
10. E. Dornberger *et al.*, "Simulation of Non-Uniform Grown-In Defect Distribution in Czochralski Silicon Crystals," *Mtg. Abs. Electrochem. Soc.*, Spring 1998, Abs. 312.
11. F. Ishikawa *et al.*, "The Formation Mechanism of Coupled Voids in Czochralski Silicon Crystals," *Mtg. Abs. Electrochem. Soc.*, Fall 2000, Abs. 678.
12. W. von Ammon, *et al.*, "The Dependence of Bulk Defects on the Temperature Gradient of Silicon Crystals During CZ Growth" *J. Crystal Growth*, Vol. 151, p. 273, 1995.
13. W. von Ammon, "Silicon Crystal Growth at the Beginning of the 21st Century," *Mtg. Abs. Electrochem. Soc.*, Spring 2000, Abs. 406.
14. K-M. Bae *et al.*, "A Vacancy/Oxygen Based Model Describing Radial Distribution of Voids, OSF-Ring and AOP in Ring Structure of CZ Silicon Crystals," *Mtg. Abs. Electrochem. Soc.*, Fall 1998, p. 644.
15. M. Hasebe, *et al.*, *Defects Control in Semiconductors*, K. Sumino ed., North Holland, New York, p. 157 (1990).
16. T. Sinno *et al.*, "Point Defect Dynamics and Oxidation-Induced Stacking-Fault Ring in CZ-Grown Silicon Crystals," *J. Electrochem. Soc.*, January 1998, p. 302.

17. T. Sinno and R.A. Brown, "Modeling Microvoid Formation in Czochralski Silicon," *Mtg. Abs. Electrochem. Soc.*, Spring 1998, p. 315.
18. Y. Matsushita et al., *Ext. Abs. 18th Intl. Conf Solid State Dev. and Materials*, (Jpn. Soc. Appl. Phys., Tokyo 1986) p. 529S.
19. N. Yamada and H. Yamada-Kaneta, "Comparison of Gate Oxide Reliability Between Ar-Annealed Wafers and H₂-Annealed Wafers," *Mtg. Abs. Electrochem. Soc.*, Spring 1998, Abs. 490.
20. T. Minami et al., "Influence of Void Size on the Formation of Defect-Free Regions in Hydrogen Annealed CZ Silicon Wafers," *Mtg. Abs. Electrochem. Soc.*, Spring 2000, Abs. 514.
21. Y. Matsushita et al., "Hydrogen Anneal of Silicon Wafer Formation of High Quality Device Active Layer," *Mtg. Abs. Electrochem. Soc.*, Spring 1998, Abs. 326.
22. L. Peters, "Striking a Compromise Between Good and Perfect Silicon," *Semiconductor International*, October 1999, p. 19.
23. N. Adachi et al., "Reduction of Grown-in Defects by High Temperature Annealing," *Abs. Mtg. Electrochem. Soc.*, Spring 1998, Abs. 327.
24. R. Winkler et al., "The Gate Oxide Quality of Annealed CZ silicon Wafers and Its Influence on 4-Mb DRAM Device Yield and Reliability," *Mtg. Abs. Electrochem. Soc.*, Fall 2000, Abs. 710.
25. M. Hourai et al., "Nature and Generation of Grown-in Defects in Czochralski Silicon Crystals," *Mtg. Electrochem. Soc.*, Spring 1998, Abs. 310.
26. H. Niwa, "Reduction of Junction Leakage and Improvement of GOI Using advanced CZ wafers," *Mtg. Abs. Electrochem. Soc.*, Spring 1999, Abs. 478.
27. H. Nishikawa, et al., "Formation of Grown-In Defects During CZ Silicon Crystal Growth," *Jpn. J. Appl. Phys.*, Vol. 36, p. 6595, 1997.
28. R. Schmolke et al., "Advanced Silicon Wafers for 0.18 μ m Design Rule and Beyond: Epi and fLASH," *Mtg. Abs. Electrochem. Soc.*, Fall 2000, Abs. 671.
29. K. Moriya et al., *Jpn. J. Appl. Phys.*, 34, 2965 (1995).
30. R. Takeda et al., "Influence of LSTD Size on the Formation of Denuded Zone in Hydrogen Annealed CZ Wafers," *Abs. Mtg. Electrochem. Soc.*, Fall 2000, Abs. 700.
31. G.A. Rozgonyi, "Trends in Defect and Impurity Control for Fine Line VLSI Processing," *Defects in Silicon*, 1983, Electrochem. Soc., Pennington, N.J., 1983, p. 29.
32. S.M. Hu, "Anomalous Temperature Effect of Oxidation Stacking Faults in Silicon," *Appl Phys. Lett.*, 17, 165 (1975).
33. H. Shiraki, "Stacking Fault Generation Suppression and Grown-In Defect Elimination in Dislocation-Free Silicon Wafers by HCl Oxidation," *Jpn. J. Appl. Phys.*, 15, 1 (1976).

34. E.W. Haas *et al.*, *J. of Elec. Matls*, **7**, 525 (1978).
35. L.M. Ephrath and R.S. Bennett, *Extended Abstracts, Electrochem. Soc. Fall Meeting*, Abs. 302, Vol. 80-2, Hollywood, FL., 1980.
36. W. Zuhlechner and D. Huber, "Czochralski Growth Silicon," in *Crystals 8 (Silicon Chemical Etching)*, Springer-Verlag, Berlin (1982).
37. M.C. Chen and V.J. Silvestri, *J. Electrochem. Soc.*, **129**, 1294 (1982).
38. W.T. Stacy *et al*, *Defects in Silicon, Proc. Electrochem. Soc.* 85-9, p. 423, 1983.
39. C.W. Pearce, L.E. Katz, and T.E. Seidel, "Considerations Regarding Gettering in Integrated Circuits," *Semiconductor Silicon 1981*, Electrochem. Soc., Pennington, N.J., 1981, p. 705.
40. D.C. Gupta, R.B. Swaroop, *Solid State Technology*, August 1984, p. 113.
41. J.E. Lawrence and H.R. Huff, "Si Material Properties for VLSI Circuitry," in *VLSI Electronics, Microstructure Science*, Vol. 5 (N.G. Einspruch, Ed.), Academic Press, Orlando FL (1982), p. 51.
42. S. Kishino, "Material Characterization for VLSI Applications," *VLSI Science & Technology*, 1985, Electrochem. Soc., Pennington, N.J., 1985, p. 399.
43. R.B. Swaroop, "Advances in Silicon Technology for the Semiconductor Industry," *Solid State Technology*, July 1983, p. 97.
44. C.W. Pearce and V.C. Kannan, "Saucer Pits in Si," in *Defects in Silicon*, 1983, Electrochemical Soc., Pennington, N.J. (1983), p. 396.
45. *ibid*, Ref. 43.
46. D. Huber, J. Reffle, "Precipitation Process Design for Denuded Zone Formation in CZ Silicon Wafers," *Solid State Technology*, August 1983, p. 137.
47. *ibid*. Ref. 44.
48. M.B. Shabani *et al.*, "Competitive Gettering of Fe, Ni, and Cu in Si Wafers by Poly Backside Gettering and Internal Gettering," *Ext. Abs. Joint Intl. Mtg. Electrochem. Soc.*, Abs. No. 1959, Fall 1997, p. 2270.
49. R.F. Pinizzotto, *et. al*, "Temperature Ramping for Nucleation of Oxygen Precipitates in Si," *Materials Research Soc. Symp. Proc.* Vol. 36, Materials Res. Soc., 1985, p. 275.
50. T. Ono *et al.*, "Oxide Precipitate-Induced Dislocation Generation in Heavily Boron-Doped Czochralski Silicon," *J. Electrochem. Soc.* September 1999, p. 3461.
51. R.K. Watts, *Point Defects in Crystals*, Wiley and Sons, New York, 1977.
52. *ibid*. Ref. 45.
53. D. Huber, J. Reffle, "Precipitation Process Design for Denuded Zone Formation in CZ Silicon Wafers," *Solid State Technology*, August 1983, p. 137.
54. R. Craven "Internal Gettering in CZ Si," *Matls. Res. Soc. Symp. Proc.* Vol. 36 MRS 1985 p. 159.

55. R. Schmolke *et al.*, "Defect Depth Profile in Si (100) p/p^+ Epitaxial Wafers," *Abs. Mtg. Electrochem. Soc.*, Spring 1998, Abs. 339.
56. K. Schmolke *et al.*, "Advanced Silicon Wafers for 0.18 μ m Design Rule and Beyond: Epi and fLASH!," *Mtg Abstracts Electrochem. Soc.*, Fall 2000, Abs. 671.
57. A. Huber *et al.*, "Reliability of Gate Oxides on Silicon Substrates with 5 – 10 nm Oxide Thickness," *Abstracts Mtg. Electrochem. Soc.*, Spring 2000, Abs. 478.
58. M. Suhren *et al.*, "Crystal Defects in Highly Boron Doped Silicon," *Mtg. Abs. Electrochem. Soc.*, Fall 1996, p. 453, Abs. 358.
59. H. Takeno *et al.*, "Influence of Heavy Boron Doping on Oxygen Precipitation of Czochralski silicon Crystals and Its Computer Simulation," *Abstracts Mtg. Electrochem. Soc.*, Spring 1998, Abs. 351.
60. G. Kissinger *et al.*, "Influence of Boron Doping on Oxide Precipitate Nucleation and Gettering of Iron Impurities in Low Thermal Budget Processing of Czochralski Silicon," *Abstracts Mtg. Electrochem. Soc.* Spring 1999, Abs. 338.
61. D. Graf *et al.*, "300-mm Epi p/p^- Wafer: Is There Sufficient Gettering?" *Mtg. Abs. Electrochem. Soc.*, Fall 2000, Abs. 699.
62. R. Falster *et al.*, "The Engineering of Silicon Wafer Material Properties Through Vacancy Concentration Profile Control and the Achievement of Ideal Oxygen Precipitation Behavior," *Mtg. Abs. Electrochem. Soc.*, Fall 1998, Abs. 643.
63. R. Falster *et al.*, *MRS* 510, p. 27 1998.
64. K. Winkler and W. Hanke, "On the Effect of Edge Polishing on the Yield of 4 Mbit DRAMs," *Mtg. Abs. Electrochem. Soc.*, Spring 1998, Abs. 374.
65. W. Helgeland, *et al.*, "CZ Crystal Growth into the 90's," *Microelectronic Mfg. & Test.*, May 1986. p.1.
66. N. Jackson, "Materials and Technology of Wafering," *Solid State Technology*, July 1985, p. 107.
67. G.R. Fisher, "Challenges for 300-mm Polished Wafer Manufacturers," *Semiconductor International*, September 1998, p. 97.
68. Semiconductor Equipment and Materials Institute (SEMI), Mountain View, California.
69. I.A. Morris, "Wafer Identification Increases Yields," *Micro. Manuf. and Test*, Sept. 1985, p. 50.
70. J. Scaroni, "A Close Look at Laser Marking of Silicon Wafers," *Solid State Technology*, July '97 p. 245.
71. D. Biddle, "Characterizing Semiconductor Wafer Topography," *Microelectronics Manuf. and Testing*, March 1985, p. 15.
72. S. Takasu, "Silicon Wafers for VLSI Technology," *VLSI Technology 1983*, Electrochem. Soc., Pennington, N.J. (1983), p. 490.

74 SILICON PROCESSING FOR THE VLSI ERA – VOLUME IV

- 74. A. Bonora, "Flex-Mount Polishing of Si Wafers," *Solid State Technology*, **20**, 55 (1977).
- 75. Y. Matsushita *et al.*, "Hydrogen Anneal of Silicon Wafer Formation of High Quality Device Active Layer," *Mtg. Abs. Electrochem. Soc.*, Spring 1998, p. 326.
- 76. F. Robertson and A. Allan, *Future Fab*, 1, No. 3, p. 27, 1997.
- 77. H.R. Huff, *Silicon Wafers for the Mesoscopic Era*, "Abs. Mtg. Electrochem. Soc.", Spring 2000, Abs. 405.
- 78. *ibid.* Ref. 13.
- 79. K.V. Ravi, *Solid-State Phenomena*, 89-70, p. 103 (1999).
- 80. W.H. Reed, "Large Diameter Wafer Update," *Semiconductor International*, November 1994, p. 140.
- 81. D. Rose, "Wafer Makers Challenged by Many Aspects of 300 mm," *Solid State Technology*, February 1996, p. 79.
- 82. D. Anderson, "Stoking the Productivity Engine with New Materials and Larger Wafers," *Solid State Technology*, March 1997, p. 57.
- 83. Rose's Annual Forecast for Fab Materials, *Semiconductor International*, April 1995, p. 17.
- 84. Rose's Annual Forecast for Fab Materials, 1999.
- 85. J. Highfill *et al.*, "The Cost-Effective Challenges of 300-mm Silicon Wafers," *Solid State Technology*, October 2000, p. S-8.
- 86. C. Thomson and H. Mynster, "300-mm Wafers: Reclaimers Role and Challenges," *Solid State Technology*, August 1999, p. 40.

Chapter 3

GATE DIELECTRICS: THIN SILICON DIOXIDE FILMS

Thermally grown films of silicon dioxide (SiO_2) play many key roles in the operation and fabrication of silicon integrated circuits. However, the most critical application of such films in deep-submicron CMOS USLI circuits is serving as the MOSFET gate dielectric material. Although the many other roles of SiO_2 are also important (including diffusion masking, surface passivation, and functioning as a field oxide, interlevel dielectric, screen oxide, pad oxide, trench liner in STI, tunneling oxide in non-volatile memory devices, and sidewall spacer), the discussion here will focus on its role as the *gate dielectric of MOSFETs*.

It is commonly believed that crystalline-silicon is the main material responsible for the growth and success of the semiconductor industry. But others maintain that the real magic in silicon technology lies with silicon dioxide and its amazing ability to satisfy the myriad demands placed upon it as the gate dielectric of the MOSFET.

In this chapter we will explore the role of thin gate oxide films in deep-submicron MOSFETs, and address the following issues that relate to this subject:

1. The structure and role of silicon dioxide (and the Si/SiO_2 interface) as the gate dielectric of the MOSFET.
2. Dielectric breakdown and defects in SiO_2 ;
3. Leakage currents in silicon dioxide films;
4. Models and processes of the growth of ultra-thin oxide films;
5. Strengthening silicon dioxide films through the addition of nitrogen (oxynitrides), and the related problem boron penetration through gate oxides;
6. Technology of growing ultra-thin oxides on large diameter wafers (200-mm and 300-mm);
7. Limits of silicon dioxide as a gate dielectric material.

Despite the fact that we will restrict our discussion to SiO_2 -films as gate dielectrics, it is informative to list the other IC applications in which oxide films are employed, and the oxide thickness used in such roles (see Table 3-1).

Table 3-1 RANGES OF THERMAL OXIDE THICKNESS USED IN ULSI PROCESSING

Application	SiO ₂ Thickness (nm)
Gate oxide insulators for MOS devices	1.5–10.0
Tunnel oxides in EEPROMs and flash memories	6.0–10.0
Screen oxides for ion implantation	10.0–20.0
Side-wall liners for shallow trench isolation (STI)	15.0–40.0
Field oxide for LOCOS isolation	200–400
Re-oxidation of the etched gate stack side-wall damage	5.0–7.5
Inter-polysilicon dielectric	4.0–20.0
Masking film against ion implantation and diffusion	100–200
Sacrificial oxides for gate applications	6.0–15.0
Capacitor dielectric in DRAM circuits	5.0–10.0

3.1 REQUIRED CHARACTERISTICS OF GATE DIELECTRICS FOR DEEP-SUBMICRON MOSFETS

A dielectric material must satisfy a large number of important demands in order to successfully function as the gate dielectric of a MOSFET. Silicon dioxide has been used as the gate dielectric material in silicon-based MOS ICs ever since they were first introduced in the early 1970's. It continues to serve in this role, even as MOSFETs have been scaled down to the deep-submicron regime. We list the requirements of dielectric material for this application here, and provide more details about them in later sections of the chapter.

1. The most important requirement that the gate dielectric of a deep-submicron MOSFET must meet is the following: *It must be possible to continue to decrease the thickness of the oxide to the degree specified in accordance with the scaling of the gate length L_E of a MOSFET.* We should elaborate upon why being able to scale the gate oxide thickness is so fundamentally important for deep-submicron MOSFETs. Figure 3-1 shows that the ratio of the gate length to the oxide thickness (L_E/t_{ox}) has indeed remained constant at about a value of 45 for process technology at Intel for over 25 years.¹ The gate-oxide requirements for technology nodes for 0.18- μm and beyond (according to the ITRS Roadmap) are given in Table 3-2. At some point, *if SiO₂ cannot be scaled further to meet future demands, another material with higher reliability will be needed.*

As CMOS IC technology advances, the central focus of scaling the MOSFET device structure involves scaling the gate length L_E . That is, gate lengths of MOSFETs are scaled to obtain the significant benefits offered by such scaling. These benefits include: i) an increase in the drain current of the MOSFET I_D (which usually provides an improvement in the circuit

Table 3-2 Gate Oxide Equivalent Thickness for Deep-Submicron CMOS

	1999 (180 nm)	2001 (150 nm)	2003 (130 nm)	2006 (100 nm)	2009 (70 nm)	2012 (50 nm)
Equivalent Oxide thickness (nm)	3–4	2–3	2–3	1.5–2	<1.5	<1.0

speed); ii) a decrease in the gate area of the minimum-size MOSFET (which results in a reduction of the input capacitance that must be charged when logic levels are switched - and thus also improves the circuit speed); and iii) an increase in the density of devices that can be fabricated on a chip. (See Vol. 3 for more details on these issues.)

In deep-submicron MOSFETs, however, such reduction of the gate length increases the subthreshold drain current I_{Dst} of a MOSFET (which is one component of the total off-state leakage current of CMOS ICs). That is, in deep-submicron MOSFETs the short-channel effect known as *drain-induced barrier lowering* (DIBL) causes the subthreshold (off-state) drain current to rise significantly as the gate length is reduced (see Vol. 3 for more details). Two measures must be employed to prevent (or at least mitigate) this rise in the subthreshold leakage current as the gate length is




Fig. 3-1 Channel-length divided by gate-oxide thickness (L_E/t_{ox}) versus channel-length L_E for Intel's process technologies for the past 20 years.¹

reduced. First, the junction depth X_j of the source/drain-extension-regions must be made shallower. Second, the depth of the MOSFET channel-depletion-region must also be made shallower. Both measures serve to keep the electric field of the drain from penetrating along the channel toward the source (which would worsen the DIBL effect).

The second measure (making the channel-depletion-region shallower as the gate length is shortened) is achieved by increasing the doping concentration in the channel (typically with a heavier-dose threshold-adjust-implant). While it is relatively easy to implement such an increase in the channel doping, doing so causes another undesirable effect. That is, if the gate-oxide-thickness of the MOSFET remains unchanged, the threshold-voltage V_T is increased as the doping concentration near the surface of the channel (boron) is increased (e.g., for an NMOSFET with a p -doped channel region). Since the threshold voltage is generally kept unchanged (or it may even be slightly *decreased*) as the CMOS technology is scaled, the increase in V_T due to the increased channel doping must be counteracted. This can only be done by reducing the gate-oxide-thickness (see Fig. 3-2). For example, as shown in Fig. 3-2, if the doping concentration of an NMOSFET with a 250-Å gate-oxide is increased from $6 \times 10^{16}/\text{cm}^3$ to $1 \times 10^{17}/\text{cm}^3$, V_T will increase from 0.6-V to about 1.4-V – which is far higher than the required V_T value of ~ 0.6 V.

In summary, this shows that in order to continue to scale the gate-length of MOSFETs, it will be necessary to decrease the oxide thickness by about the same scaling factor applied to the gate-length! However, such scaling of the oxide thickness brings with it both benefits and problems. One additional benefit is that the on-state drain current is further increased as the oxide thickness is scaled down (see Vol. 3). However, several other negative factors also ensue: the thinner oxide films cannot tolerate the increased gate electric fields, and this forces smaller power-supply voltages to be used (and such smaller supply voltages reduce the MOSFET on-state drain current); the tunneling leakage-current (gate current) through the oxide increases; the oxide is more prone to penetration by poly dopant (especially boron); and defects and oxide-layer thickness non-uniformities become bigger problems when thinner oxides must be manufactured. Figure 3-3 depicts these concerns for ultrathin gate oxides.

2. It must be possible to form the oxide layer with a thickness that closely matches the design specification of the MOSFET. This oxide thickness




Fig. 3-2 Calculated threshold voltages of n -channel (V_{Tn}) and p -channel (V_{Tp}) transistors as a function of their substrate's doping, assuming n^+ polysilicon gate (left scale) and p^+ polysilicon gate (right scale). Curves for gate oxide thicknesses d of $150\text{\AA}$, $250\text{\AA}$, and $650\text{\AA}$ are shown. From S.M. Sze Ed. *VLSI Technology*, 2nd Ed., Chap. 11, "VLSI Process Integration." Copyright, 1988 Bell Telephone Labs. Reprinted with permission.

must also be sufficiently uniform across the entire wafer, and from wafer-to-wafer, and from run-to-run.

3. The oxide film and the Si/SiO₂ interface must maintain stable electrical characteristics. This includes exhibiting adequately small values of charge in the oxide and at the Si-SiO₂ interface (i.e., low Q_f , D_{it} , Q_{ot} and Q_m values).




Fig. 3-3 Concerns in ultra-thin gate oxides.

4. The dielectric breakdown strength of the oxide must be sufficiently high (e.g., $> 8\text{-MV/cm}$), implying that the film is pinhole free and contains a negligible number of defects that would lead to oxide breakdown at lower electric fields.
5. The oxide film must exhibit sufficiently long lifetime under normal operating conditions (i.e., t_{BD} is adequate). This characteristic is related to 4.
6. The dielectric material (oxide) must be compatible with the other materials of the MOSFET structure, and be thermally, electrically, and chemically stable under the processes used to fabricate the ICs.
7. The leakage-current through the gate-oxide must be sufficiently small to meet the off-current leakage requirement of the IC in which it is used.
8. The oxide should exhibit high resistance to hot-carrier damage (i.e., device degradation should be low in the face of hot-carrier stressing).
9. If the oxide is to be used in a symmetric CMOS technology (i.e., in which both p^+ and n^+ poly are used), the oxide film needs to be resistant to the penetration of boron at the process temperatures used after gate doping.
10. The oxide must passivate the silicon surface.

3.2 THE STRUCTURE OF THERMALLY GROWN SiO_2 AND THE PROPERTIES OF THE Si/SiO_2 INTERFACE

3.2.1 The Microscopic Structure of Thermally Grown SiO_2

SiO_2 (silica) can be found in crystalline or amorphous (vitreous) forms. When the atomic structure of silica exhibits long-range order it is in *crystalline* form. Many varieties of crystalline-silica exist, including quartz, cristobalite, coesite, etc. However, the type of silica encountered in silicon ICs (i.e., silicon-dioxide films thermally grown under normal conditions) is not crystalline. Instead, it is silica in its *vitreous* (or *glassy*) form. Vitreous solids do not exhibit long-range order. Instead, their structure is ordered only over short ranges. This glassy state of SiO_2 is also often referred to as *fused-silica*. Since we are interested in thermally grown SiO_2 , our discussion will focus on the glassy state of SiO_2 (fused-silica).

The basic structural unit of silica is centered around the *structural formula* (SiO_4). The spatial arrangement of Si and O atoms is due to their respective valence (+4 and -2), their relative sizes, and their electrostatic interactions. These factors give rise to elementary SiO_2 cells of tetrahedric configurations. That is, a silicon atom (with a valence of +4) is located at the center of the tetrahedron, with oxygen atoms (O^{2-}) at each of the corners (Fig. 3-4a).³ In crystalline- SiO_2 (quartz), each oxygen atom belongs to two tetrahedra and is thus bonded to 2

silicon atoms. Such oxygen atoms are then known as *bridging oxygen atoms*. (Fig. 3-4b).³ In vitreous- or amorphous- SiO_2 some of the vertices of the tetrahedra have *nonbridging oxygen atoms*, meaning they are not shared between two tetrahedra (Fig. 3-4d). The greater the ratio of bridging-to-non-bridging oxygens, the greater the cohesiveness of the SiO_2 structure.

The interatomic distances (from the center of one atom to the center of its nearest neighbor) have been measured and found to have the following mean values: 1.62-Å for the Si-O bond; 2.27-Å for the O-O distance; and 3.12-Å for the Si-Si distance. Note this implies that a 2.0-nm gate oxide is only 10-12 atomic layers thick!

The structure of fused-silica is a continuous random network of tetrahedra, where the Si-O-Si bond angle varies from 110° to 180° , with the most probable value being 144° . A two-dimensional representation of the vitreous- SiO_2 lattice is shown in Fig. 3-4c.⁴




Fig. 3-4 (a) The basic structure of SiO_2 .² (b) Three-dimensional representation of two neighboring SiO_4 cells, bridged by an oxygen atom. (c) Two-dimensional lattice representing vitreous- SiO_2 .² (d) The structure of thermally grown SiO_2 showing bridging and non-bridging oxygen atoms and dopant (i.e., network modifier) atoms.³ (© IEEE 1965)

The density of thermal-SiO₂ (fused-silica) is 2.20-g/cm³ which is smaller than that of quartz (2.65-g/cm³). In fused silica only 43% of the lattice space is occupied, making its structure much more open than that of quartz. Consequently, a large variety of impurity atoms can easily enter this oxide network and diffuse through it. Since it is difficult to directly assess the density of thin films, the refractive index of SiO₂ is usually measured instead, and the density is then inferred from it. A refractive index of 1.460 corresponds to a density of 2.20-g/cm³. Generally, CVD oxides exhibit smaller densities than thermally grown SiO₂, and worse electrical and material properties correspond to less dense films. Hence, measurements of the index of refraction also provide a method for rapidly comparing the characteristics of deposited oxides.

3.2.2 The Si/SiO₂ Interface

In addition to the characteristics of the SiO₂ bulk structure, the characteristics of the Si/SiO₂ interface also play a critical role when SiO₂ functions as the dielectric layer of a MOSFET. Hence, a discussion of these characteristics (and the structure) of the SiO₂ interface is also relevant. First, it is useful to define the types of charges that exist in the oxide and at the Si/SiO₂ interface. (It should be noted that such charges are not expected to exist in an “ideal” oxide or at an “ideal” interface.) Four different types of charges are associated with the bulk oxide and “real” Si/SiO₂ interfaces, as shown schematically in Fig. 3-5. The *effective net* (i.e., *total*) *charge-per-unit-area* due to such charges at the Si/SiO₂ interface and within the oxide bulk (in C/cm²) is denoted by the symbol Q_{tot} , whereas the *net* (*total*) *number of charges* per unit area (Q_{tot}/q) is given by N_{tot} . The standardized terminology and symbols used to differentiate these various individual charge types are as follows:

1. Mobile ionic charge per unit area Q_m (C/cm²), and N_m (no. of mobile charges/cm²);
2. Fixed oxide charge per unit area Q_f (C/cm²), and N_f (no. of fixed oxide charges/cm²);
3. Interface trapped charge per unit area Q_{it} (C/cm²), and N_{it} (no. of interface trapped charges/cm²); D_{it} - number of interface trapped charges per unit area *and* energy (no. of interface trapped charges/cm²-eV);
4. Oxide trapped charge Q_{ot} (C/cm²), and N_{ot} (no. of oxide trapped charges/cm²).

The issues relating to the reliability of deep-submicron MOSFETs primarily involve Q_{it} and Q_{ot} . That is, the problems caused by Q_m and Q_f are not only well

controlled, but their impact does not get any more severe as oxides are scaled. On the other hand, those associated with Q_{it} and Q_{ot} are ongoing, scaling-dependent problems that must be addressed as MOSFETs are pushed further into the deep-submicron regime. Hence, the review provided here will examine only these two categories of interface/oxide bulk charges. This will include the origin of the charges and their effect on device behavior. A more detailed description of the characteristics of Q_m and Q_f can be found in Vols. 1 and 3, and in Refs. 1 and 7.

3.2.2.1 Interface Trapped Charge: The *interface-trapped charges* refer to charges which are localized at sites at the surface of the silicon (i.e., at the Si/SiO₂ interface). Such sites are believed to arise from energy states that exist in the forbidden gap of the silicon, and are referred to as *interface states*. Such surface states are extra allowed energy states (i.e., that electrons can occupy) present at the semi-conductor surface, but not within the bulk.

The term *surface state* was coined by Tamm in 1932.⁵ Using quantum mechanical calculations, he showed that new electronic energy states arise in a crystal if the lattice is terminated at a surface. Such new states are confined to the region very close to the surface. He also calculated that these states will arise at interfaces (such as the Si/SiO₂ interface), as well as at free surfaces. Each of the states is associated with a single atom at the surface. Hence, an electron occupying one of these states is localized (i.e., it is forced to remain in a restricted region of space centered on that atom). Since such states thus effectively *trap* free carriers at the surface, they are also referred to as *interface traps*. The charge-per-unit-area stored in these traps is symbolized by Q_{it} .




Fig. 3-5 Charges associated with the Si/SiO₂ system.




Fig. 3-6 Physical model for the interfacial traps. "Dangling bonds" which occur when the Si lattice is abruptly terminated along a given plane to form a surface. (b) Post-oxidation perfect (ideal) interface. (c & d) Post-oxidation dangling bonds that become interfacial traps.⁷ Reprinted with permission of the publisher, the Electrochemical Society.

Although the theoretical basis of interface traps is well accepted and models exist that accurately detail the electrical behavior of the traps, the *physical origin* of these surface states has not been totally determined. The weight of experimental evidence supports the view that surface-states arise primarily from unsatisfied, or *dangling* bonds at the silicon surface (see Fig. 3-6). Note that a Si atom at a surface with a dangling bond can also be viewed as a *trivalent Si atom*.

From a qualitative perspective, the dangling bond model can be visualized with the aid of Fig. 3-6a. Here it is seen that if a Si lattice is abruptly terminated along a given plane to form a surface, one of the four bonds of each Si atom at the surface is left dangling. There will thus be extra states on this surface because the energy field of the crystal is one-sided (i.e., the electrons in the surface region are bonded only from the side directed toward the bulk). It is plausible that thermal formation of SiO₂ can tie up these surface Si bonds, and that along a perfect Si/SiO₂ interface all such bonds could be tied up (Fig. 3-6b). In this case,

surface-states at the interface would be suppressed.⁶ However, it is more plausible that such oxidation will not tie up *all* the bonds (Fig. 3-6c). If even a very small fraction of the number of dangling bonds is left unsatisfied, a significant number of surface-states could exist. For example, on a (100)-Si-surface there are 6.8×10^{14} Si atoms per cm^2 . If oxidation left 1/1000 of these bonds dangling, and each of them gave rise to a surface-state, the density of interface trapped charges would be $6.8 \times 10^{11}/\text{cm}^2$ (assuming one electronic charge is associated with each energy state). If a gate-oxide-thickness of 20-nm was being used, this would cause a threshold-voltage-shift of 0.63-V. This indicates that if the dangling-bond model correctly describes the origin of interface states, then only a relatively small number of residual-dangling-bonds can significantly perturb MOSFET device characteristics. Crystal-defects near the surface or foreign atoms bonded at the surface are other interface perturbations that have been identified as possible sources of surface-states.

Figure 3-7 represents the bond-stretching and broken-bond model of the Si/SiO₂ bulk of Verwey² and of the Si/SiO₂ interface of Sakurai and Sugano.⁶ That is, Fig. 3-7a depicts the stretched and broken Si-O bonds in the bulk, and Figs. 3-7b-e at the interface. Figures 3-7f-h illustrate the possible defects in the oxide bulk. In Fig. 3-7b, the dangling-Si-bond at the surface is depicted as an *interfacial-trivalent-Si-atom*, while in Fig. 3-7f, a dangling-Si-bond in the bulk is portrayed as a *trivalent-Si-atom*.

Trivalent-Si-atoms introduce a deep trap-level near the Si midgap when located at the interface, and a deep trap-level in the SiO₂ bandgap when located in the oxide bulk. The weak Si-Si* and Si-O stretched bonds (Figs. 3-7c and 3-7d) at the interface introduce a continuum of deep trap levels, or if such stretched bonds exist in the bulk of the oxide (Fig. 3-7g), they produce shallow trap levels. If a dangling-Si-bond is tied up with an impurity (most commonly H or OH), this is thought to produce an electron-trap, while the oxygen vacancy (or weak Si-Si stretched bond) is considered to be the precursor of a hole-trap.

An anneal in a hydrogen ambient (100% H₂ or 4%-H₂ in N₂ [forming gas]) at approximately 450°C is normally the final step prior to assembly and packaging of an IC. This step is thought to allow hydrogen to penetrate the gate-oxide and then tie up the remaining dangling bonds at the Si/SiO₂ interface not tied up by thermal oxidation (as suggested in Fig. 3-8). However, the Si-H or Si-OH bond can be easily broken by injected hot-electrons, giving rise to interface traps. Thus, hydrogen introduced in the post-metal anneal or other process steps (i.e., during the steam reflow of an interlevel BPSG layer, or during the deposition of silicon nitride), can increase hot-electron degradation in a MOSFET.




Fig. 3-7 (a) Strained and broken bonds: (a1) Normal Si-O bonds; (a2) Strained bond in vitreous silica; (a3) Broken bond represented with a trapped electron; (a4) Broken bond represented with a trapped hole. Possible interface defects (b-e): (b) Si dangling bonds. (c) Si-Si stretched bond (or oxygen vacancy). (d) Si-O stretched bond. (e) Impurity at interface. Possible oxide bulk defects (f-h): (f) Si dangling bond; (g) Si-Si stretched bond (or oxygen vacancy). (h) impurity in SiO₂.⁶ (© IEEE 1988)

Consequently, it has been suggested that the ideal gate dielectric and all subsequent dielectric layers should contain as little hydrogen as possible to make them hot-electron resistant.

3.2.2.2 Effect of Interface Traps on IC Characteristics: The presence of interface traps has four major effects on the characteristics of ICs. First, the charge that is present in the interface traps interacts with the charge in the silicon near the surface and thus changes the silicon charge distribution and the surface potential. Second, interface traps act as generation-recombination centers, giving rise to leakage currents, as described below. Third, since the density of interface trap




Fig. 3-8 How hydrogen can passivate the dangling bonds at the silicon surface shown in Fig. 3-7c and reduce the interface trap density.

charge changes with the surface potential, it gives rise to an additional capacitance component in parallel with the silicon gate capacitance. Fourth, an increase in interface-state-density has been correlated to weakening of the oxide, which appears to be a prelude to the second-stage breakdown event in gate oxides.

The issue concerning the *effect on the surface-potential of charge being trapped at the interface* is considered first. That is, such charge trapped at the interface has the same effect on the surface-potential as placing a sheet of charge Q_{ox} at the oxide-silicon interface. Such a sheet of charge will impact the threshold voltage, causing it to shift by an amount given by $\Delta V_T = -Q_{ox}/C_{ox}$. To keep this threshold voltage shift as small as possible, the value of Q_{ox} should also be kept as small as possible. The last paragraph of this section explains the measures taken to achieve this goal.

A secondary effect of interface-trap-charge on the surface-potential was introduced earlier. That is, injection of hot electrons into the gate-oxide is thought to produce interface traps (by breaking the bond between a silicon-surface atom and a hydrogen atom, which leaves a dangling bond on the Si atom). Since this process produces additional dangling bonds (and thus interface traps) as time goes by - and since these interface traps can trap electrons - this phenomenon will also cause the value of Q_{ox} to increase with time. In turn, this will cause the value of V_T to change with time. If V_T increases as result of the

buildup of Q_{ox} , the drain current of the MOSFET will decrease. If such drain current degradation becomes too severe the device will eventually fail to operate properly. Thus, measures to avoid hot-carrier-injection have been employed in MOSFETs as their gate lengths approached $1.0\text{-}\mu\text{m}$ and smaller.

The second effect of interface states involves the fact that they can serve as generation-recombination centers. Since they are present at the silicon surface, they will exist in the depletion regions of pn junctions that intersect the surface of the silicon. There are many such junctions at the Si/SiO_2 interface in every device, and therefore in every IC.

Before the invention of integrated circuits, only discrete diodes, bipolar transistors, and field-effect transistors (FETs) could be fabricated. In the early 1950s, these discrete devices exhibited relatively high reverse-bias junction-leakage and low breakdown-voltage (caused by the large density of interface traps at the surface of single-crystal silicon).

In 1958, a group of workers at Bell Telephone Laboratories, led by Atalla, found that when a thin layer of SiO_2 was grown on the surface of silicon where a pn -junction intercepts the surface, the leakage current of the junction was reduced by a factor from 10 to 100. It was later understood that the oxide reduces the number (or stabilizes many) of the interface traps. Not only did such oxide-passivation of the silicon surfaces allow diodes and transistors to be fabricated with significantly improved device characteristics, but the leakage path along the surface of the silicon was also effectively shut off. Thus, one of the fundamental isolation capabilities needed for planar devices and integrated circuits had also been developed. In his report on the evolution of the MOS transistor, C.T. Sah remarks that the successful effort by the Bell Labs group to stabilize Si surfaces was the most important technological advance in microelectronics during the 1950s, and that it blazed the trail that led to the development of the silicon integrated circuit.⁸

The third effect of interface traps involves the interface-trap capacitance. As noted earlier, the *interface-trap capacitance* C_{it} is in parallel with the gate capacitance. However, only those interface traps that can be filled and emptied at a rate faster than the capacitance measurement signal can contribute to C_{it} . Traps too slow to follow the capacitance-measurement signal will not contribute to C_{it} . Therefore, the observed C_{it} is not only a function of the interface-trap density but also depends on the MOS-capacitor gate voltage (which controls the surface potential and hence the probability of occupancy of the traps) and the frequency at which the capacitance measurement is made.

All of these observations point to the conclusion that for a MOSFET to have

predictable and reproducible capacitance characteristics, it is important to employ fabrication processes that minimize trap density. Using (100)-oriented silicon wafers, and a post-metallization hydrogen-annealing step (at temperatures around 400°C) at the end of the fabrication process, are the main techniques for keeping the interface-trap-density at a minimum.

It has been observed that the passage of tunneling current through a thin oxide also introduces interface traps at the Si/SiO₂ interface. Furthermore, while breakdown may not occur until about 10 C/cm² of charge has passed through the oxide, interface traps are detectable even after 0.001 C/cm² of charge passage. Thus, measuring interface traps has been proposed as a more sensitive means of quantitatively measuring oxide damage (due to Fowler-Nordheim stressing of oxides) prior to breakdown.

3.2.2.3 Oxide Trapped Charge: The oxide trapped charge Q_{ot} is due to holes or electrons trapped in the *bulk* of the oxide, and hence can be positive or negative. They become trapped at *trap centers* that are microscopic defects in the oxide structure *in the bulk of the oxide layer*. Such defects may be caused by ionizing radiation, hot-carrier injection, or high currents through the oxide (e.g., due to Fowler-Nordheim tunneling), or other reactions which either bend or break Si-O bonds in the oxide. Figures 3-7f-h show possible defects in the SiO₂ bulk that may give rise to such traps. For example, a trivalent Si atom in the SiO₂ will introduce a deep trap level in the SiO₂ bandgap ($\text{Si}\equiv\text{O}_3$), and stretched Si-O or Si-Si bonds [in the latter, a missing bridging-oxygen atom leads to a defect ($\text{O}_3\equiv\text{Si}\cdots\text{Si}\equiv\text{O}_3$)]. Figure 3-9 shows schematics illustrating the potential wells of electron traps in silicon dioxide. While, as-grown SiO₂ films contain few such microscopic oxide defects, electron and hole traps can be easily introduced by bombardment with high-energy photons or particles.⁹ (The exception to this




Fig. 3-9 Schematics illustrating the potential wells of electron traps in silicon dioxide: a) Coulomb-attractive trap; b) neutral trap; and c) Coulomb-repulsive trap.

statement is that as-grown wet oxides tend to contain some oxide traps because they also contain OH^- and H_2O species. The density of oxide traps in wet oxides can be significantly reduced with an appropriate post-oxidation-anneal.)

Q_{ot} can be annealed out by low-temperature treatments (above 550°C) although some neutral traps may remain. Therefore, oxide trapped charge was been considered relatively less important than the other oxide charges in just-completed MOSFETs. In early generations of MOSFET ICs, exposure of the devices to ionizing radiation encountered in space flights was the main concern involving Q_{ot} . However, in deep-submicron CMOS ICs, the problems involving Q_{ot} are becoming serious for several reasons. First, processing techniques such as ion implantation, sputter deposition, and plasma etching are potential sources for creating charged and neutral traps in the gate dielectric (all of which may not be completely annealed out at the end of the fabrication process). This may result in long-term reliability problems, especially if hot carriers are injected in these oxides and get trapped. Another reliability concern involves gate-oxide degradation due to high electric-fields in the oxide (and subsequent Fowler-Nordheim tunneling currents in the oxide). This has become more of a concern as oxide thickness has been scaled down.

3.2.2.4 Effect of Oxide Trapped Charge on Device Characteristics: The major effect of oxide trapped charge on MOSFETs is that they are a manifestation of the damage done to the gate oxide during device fabrication or by electrical stressing (either by the application of a high electric-field across the oxide, or by the injection of carriers into or through the oxide). We will discuss this issue in more detail in Sect. 3.3.

3.3 DIELECTRIC BREAKDOWN IN SILICON DIOXIDE FILMS

Dielectric breakdown of the gate-oxide layer is one of the major reliability issues that affects MOSFETs. We provide a review of this phenomenon here, and recommend that interested readers consult Vol. 3, Chap. 7 for more background information on the various breakdown measurements, statistical models, and burn-in tests used to screen out parts with weak oxides. However, significant new information that has been published since 1995 (when Vol. 3 was released) and this new information will be focus of the discussion here.

Figure 3-10 shows the time dependence of the gate current through an oxide under a large and constant voltage stress applied across the oxide layer. One can see that there is a gradual decrease in the current with time until the oxide suffers *dielectric breakdown* (Fig. 3-10). At that point the current rises rapidly (*catastrophic breakdown*).¹⁰ After such breakdown, the oxide is irreparably damaged,




Fig. 3-10 Constant-voltage stress measurements of a 20-nm-thick oxide film. The sharp increase in current near the end of the trace indicates that irreversible breakdown has occurred. and can no longer function as the dielectric layer in the MOSFET. Since such breakdown occurs after the oxide is subjected to a voltage stress for some extended period of time, this phenomenon is also referred to as *time-dependent dielectric breakdown* (TDDB). Anomalous “soft breakdown” of oxides also occurs for films < 5.0-nm thick, and this will be discussed in Sect. 3.8.

A different metric of the quality of oxide films is expressed in terms of the electric field at which dielectric breakdown occurs. To measure this value, a voltage (that increases linearly with time) is applied between the gate and substrate of a MOS-C test structure until the oxide breaks down. The “best” (apparently defect-free) oxides break down at fields greater than about 10 MV/cm, and failures at such field strengths are referred to as “intrinsic breakdown.” Less-than-perfect-oxides (i.e., those that contain some form of defect) may fail at lower voltages (i.e., between 4-6-MV/cm).

In any case, dielectric breakdown in ICs must be avoided. Extensive work has demonstrated that 20-year oxide-lifetimes can be achieved if the oxide field remains below about 8-MV/cm.¹¹ Thus, for devices used in CMOS logic and memory chips, the maximum electric field during normal device operation is typically restricted to the 5 MV/cm range, and this limit on the electric field is projected to remain at about this value for each technology generation. That is, the 5-MV/cm value is expected to give an acceptable safety margin for 20-30-year oxide-lifetimes. Chips are also normally subjected to burn-in tests to screen out those chips that contain oxides that would fail under the normal operating conditions during their time of service.




Fig. 3-11 a) Localized poly filament shorting the gate and substrate after gate oxide breakdown; b) A SEM photograph of two breakdown spots. The polysilicon electrode has melted away over $20 \mu\text{m}^2$. The polysilicon is spread over a large area in the form of dust and little globules. The size of a dash is $1\text{-}\mu\text{m}$. From D.R. Wolters and J.F. Verwey, "Breakdown and Wear-Out Phenomena in SiO_2 Films," Chap. 6, p. 329, in *Instabilities in Silicon Devices*, G.M. Barbottin and A. Vapaille Eds., © 1986 Elsevier Science.

Because dielectric breakdown is such a critical reliability issue in CMOS ICs, breakdown of thin oxide films has been (and still is) a subject of intense research. The physical mechanisms involved in the dielectric breakdown process are quite complex. We will discuss some of the latest proposed models to shed light on this phenomenon.

In general, the catastrophic breakdown of a dielectric is believed to be a two-stage process. First, the dielectric is slowly degraded over time (perhaps years) due to being subjected to high-electric fields or due to the passing of current through the oxide. This degradation takes the form of creating defects in the oxide (e.g., electron/hole traps and/or bond-breakage). These defects form a localized conductive path through the oxide during this time. The second stage is the very short runaway breakdown process itself (it may occur in microseconds). During the runaway breakdown phase the oxide is shorted (due to severe joule-heating that causes a conductive filament to form in the dielectric) and a very large current flows between the gate and substrate in the MOS device (Fig. 3-11).

There are numerous forms of damage to the oxide that are postulated to occur during the oxide degradation process, including lattice damage, trap creation by electrons, and trap creation by holes. The two physical mechanisms that are blamed for producing these types of damage are: 1) externally applied electric

fields; and 2) current that passes through the oxide. Thus, there are two classes of models that have been developed to predict TDDB: 1) models that assume the oxide degradation is electric-field-driven (the so-called *E-models*); and 2) models that assume the oxide degradation is current-driven (the so-called $[1/E]$ -models). Here we briefly describe both models. Also note that although the physical basis for oxide degradation is still under debate, definitions and practices have been developed to describe and test the integrity of the oxide.

3.3.1 Electron Trapping in Silicon Dioxide: (and why the Current in the Oxide Decreases with Time During Constant-Voltage Stressing)

As described in Sect. 3.2.2.3, silicon-dioxide layers contain electron and hole traps (either as a result of residual damage inflicted during device processing, or caused by the electric fields applied across the oxide - or gate current that flows - during normal device operation). If these sites trap carriers which are transported in the oxide conduction-band (electrons), they can give rise to oxide-trap charge Q_{ot} . Electrons can enter the conduction band of the oxide in several ways, including: 1) ionizing radiation can generate electron-hole pairs within the oxide itself; 2) electrons can enter from the silicon substrate or the gate polysilicon either through tunneling or through hot-electron injection. Some of these electrons may get trapped at oxide trap sites. These trapped electrons will then cause the electric field in the oxide to be modified in the following manner: The field near cathode (i.e., the electrode that acts as an electron source) is decreased, while the electric field near the anode (the electrode that acts as the electron sink) is increased (as depicted in Fig. 3-12). A decrease in the field near the cathode causes Fowler-Nordheim current in the oxide to decrease. Since the gate current is due primarily to Fowler-Nordheim tunneling, this explains why the gate current declines with time under a constant-voltage stress (as shown in Fig 3-10).

3.3.2 The Electric-Field-Driven Model of Oxide Degradation

In the electric-field -driven models of oxide degradation (*E-models*), the cause of low-field ($< 10\text{-MV/cm}$) TDDB is postulated to be field-enhanced thermal bond breakage. That is, at a given temperature, chemical bonds in the SiO_2 structure can be broken by thermal vibrations. Such bond breakage produces local defects that weaken the oxide, and when the concentration of such defects reaches a critical value, breakdown can occur. An externally applied electric field serves to reduce the activation energy required for such thermal-bond breakage, and therefore increases the degradation-reaction rate for failure exponentially. The *time-to-breakdown* t_{BD} which is the inverse of degradation rate, decreases exponentially




Fig. 3-12 Schematic illustrating the trapping of tunneling electrons. As electrons are trapped, the oxide field near the cathode (electron source) is decreased, while the oxide field near the anode (electron sink) is increased.

with field according to:

$$t_{BD} = A_0 \exp(-\gamma E_{ox}) \exp(Q/k_B T) \quad (3.1)$$

where γ is the field acceleration-parameter, E_{ox} is the electric field in the oxide (usually expressed in MV/cm), and Q is the enthalpy of activation for bond breaking in the absence of an external electric field. Generally, for oxide thicknesses greater than 90-Å, $\gamma \sim 2.5\text{-}3.5\text{-cm/MV}$.

3.3.3 The Current-Driven Model of Oxide Degradation (1/E Model)

In the so-called 1/E model for TDDDB, degradation is postulated to be due to current flow through the dielectric caused by Fowler-Nordheim conduction. Electrons, which are F-N injected from the cathode, may cause damage to the dielectric due to impact ionization as the electrons are accelerated through the oxide. Also, when these accelerated electrons reach the anode, hot holes may be produced (see Sect. 3.3.4 below) which can tunnel back into the dielectric causing damage. Since both the electrons from the cathode and the hot holes from the anode are the result of F-N conduction, the time-to-failure is expected to show an exponential dependence on the reciprocal of the electric field, 1/E:

$$t_{BD} = \tau_0(T) \exp[G(T)/E_{ox}] \quad (3.2)$$

where $\tau_o(T)$ is a temperature dependent pre-factor, G is the $1/E$ -model field acceleration-factor, and k_B is Boltzmann's constant.

The temperature dependence of G has been expressed as a $1/T$ power series expansion, given by:¹²

$$G = G_o [1 + (\gamma/k_B)\{(1/T) - (1/300K)\}] \quad (3.3)$$

where:

$$\gamma = (k_B/G_o) [dG/d(1/T)]_{300K} \quad (3.4)$$

and where the derivative is evaluated at 300K. At room temperature, $G_o \sim 350$ -MV/cm and $\gamma \sim 0.017$ -eV.

$\tau_o(T)$ is also usually represented as a $1/T$ expansion:

$$\tau_o(T) = \tau_o \exp[(-E_a/k_B)\{(1/T) - (1/300K)\}] \quad (3.5)$$

where $\tau_o \sim 1 \times 10^{-11}$ sec, and $E_a \sim 0.3$ -eV.

3.3.4 The Hole-Trapping Model that Describes How Holes are Injected and Trapped in SiO₂

The transport of holes through the oxide has been shown to precede breakdown, indicating that holes cause damage to the oxide (namely by creating traps in the bulk oxide).¹³ A model (the *anode-hole injection model* [AHI model]) has been published that seeks to explain how such holes are generated and injected into the oxide during high electrical field stress.¹⁴ The mechanisms that occur are depicted in Fig. 3-13.

When an electric field is applied across an oxide layer using an MOS-C structure, the energy-band diagram of this situation is depicted in Fig. 3-13. If an electron tunnels from the cathode into the conduction band of an oxide layer (by F-N tunneling), it can then gain kinetic energy from the electric field applied across the oxide, and get accelerated toward the anode. When the electron arrives at the anode it has a large amount of kinetic energy (E_{gain} in Fig. 3-13). Some fraction of such electrons that arrive at the anode are able to transfer this energy to an electron deep within the valence band of the anode silicon near the oxide-anode interface. This valence band electron is excited to the bottom edge of the silicon conduction band in the anode. The excitation event also produces a hole deep within the valence band, and this "hot" hole can tunnel into the valence band of the oxide (again by F-N tunneling, as depicted in Fig. 3-13). These holes can be trapped in the oxide and also create the damage described earlier. This damage accumulates with time, degrading the oxide.³⁵

In addition, the trapped holes in the oxide layer cause an increase in the oxide field near the cathode, and a decrease in the field near the anode (Fig. 3-14). A small increase in the oxide field near the cathode can cause a large increase in the




Fig. 3-13 Energy-band diagram of the anode-hole injection (AHI) model, illustrating the generation of an electron-hole pair by a tunneling electron. The hole thus generated can then be injected (by tunneling in this model), into the oxide layer.

tunneling current. Thus, hole trapping in the oxide near the cathode provides positive feedback to the electron tunneling process. It should be pointed out that the increase in tunneling current due to hole trapping is usually not readily observable, except near breakdown, because it is masked by the decrease in tunneling current due to electron trapping.

It should be noted that recent work has called some conclusions of this model into question. That is, until recently it was generally accepted that the substrate current originates from the anode-hole-injection (AHI) mechanism, which was schematically depicted in Fig. 3-13. Part of the holes created by the phenomena postulated by this model tunnel into the oxide, and the oxide degradation is related to the hole fluence (which is found to be constant at breakdown, independent of the stress current or stress voltage). However, the explanation of the substrate current by anode-hole-injection has never been completely verified, and other mechanisms such as minority-carrier generation due to F-N-induced photons have been suggested to be a cause as well. Two recent reports claim that the F-N-induced photons in the gate are the dominant source of the substrate hole




Fig. 3-14 Schematic showing the trapping of holes in the oxide layer. The trapped holes enhance the electric field near the cathode, and decrease the electric field near the anode.

current, and thus the generally accepted explanation of oxide degradation based on anode-hole-injection may have to be revised.^{31,32}

3.3.5 Comparing the Electric-Field-Driven and the Current-Driven Oxide Breakdown Models

There has been a great deal of disagreement as to which is the dominant degradation mechanism for low-field TDDB in thin oxide films; i.e., is it field-induced or current-induced? The $(1/E)$ -model fits the TDDB data very well at high fields (in which high F-N-currents exist), but falls short at lower fields (< 10 -MV/cm). In fact, there have been several low-field/long-term TDDB studies carried out, with each showing that TDDB data were described much better by the E -model.^{15,16,34} The good fit of the physics-based E -model to low-field/long-term TDDB data suggests strongly that it is field (not current), which is the dominant degradation mechanism at low fields because the F-N current is simply so vanishingly small at these lower fields. However, for very-thin oxides (< 40 -Å) the direct tunneling-current is very high, which could mean that in these oxides the dominant degradation mechanism may again be current-driven.

3.3.6 Time-to-Breakdown (t_{BD}) and Charge-to-Breakdown (Q_{BD})

The breakdown characteristics of an oxide film are described in terms of the *time-to-breakdown* (as was discussed earlier) and in terms of its *charge-to-breakdown* Q_{BD} (which measures the *integrated* total tunneling current [i.e., total charge] just before breakdown). Recent publications have tended to use the value of Q_{BD} . It appears that it is simpler to develop models relating to the other physical processes, such as hole current, trapping, trap generation, and interface-state generation, than it is to develop models relating time-to-breakdown to these processes. Thus, Q_{BD} needs to be discussed further.

As mentioned above, evidence indicates that tunneling-electron-current can lead to hole-injection into the oxide. Thus, Q_{BD} is the sum of the charges passing through the oxide due to electrons and holes. If a MOS-C structure is used to measure Q_{BD} , then due to the two-terminal nature of the MOS-C, only the total charge can be measured. However, if an NMOSFET is used to measure Q_{BD} , then both the total charge and the hole-charge component can be determined. For the case of an NMOSFET, the bias configuration for such measurements is shown in Fig. 3-15. Integration of the gate current gives the total charge, while integration of the substrate current gives the charge due to the holes. For a given oxide film, Q_{BD} is often plotted as a function of oxide voltage. Figure 3-16 is such a plot for oxide thickness in the 2.5-10-nm range.¹⁵ It shows that for a given oxide thickness, Q_{BD} decreases with increasing oxide voltage.




Fig. 3-15 Schematic depicting the bias configuration of an *n*-channel MOSFET for measuring the charge-to-breakdown Q_{BD} and its hole-charge component.




Fig. 3-16 Typical plot of charge to breakdown versus oxide voltage for several oxide thickness values.

3.4 LEAKAGE CURRENTS IN SiO_2 FILMS (TUNNELING PHENOMENA)

When considering the ideal MOS capacitor structure, it is assumed that no current flows through the oxide. However, in real MOS capacitors, a current from the gate to the substrate through the oxide can flow (termed *gate current*, I_g). Although the carriers that constitute such current can enter the conduction band (electrons) and valence band (holes) of silicon dioxide by hot-carrier injection, here we only discuss the other way that they can enter, namely by tunneling. This is because few carriers in deep-submicron MOSFETs enter the oxide as a result of hot-carrier injection during normal device operating conditions; hence they do not play a major role in the observed gate current.




Fig. 3-17 Energy-band diagram of an *n*-type polysilicon-gate MOS structure at flat band.

The phenomenon of carrier injection into the oxide by tunneling is due to the quantum-mechanical nature of the electron. In the classical sense, the oxide represents an impenetrable barrier to injection of electrons into the conduction-band of the silicon if they possess kinetic energies smaller than the interface energy barrier for the electrons ($E_{ox} = 3.1\text{-eV}$). In Fig. 3-17, the energy-band diagram of a MOS capacitor with silicon dioxide as the insulator and heavily n -doped-polysilicon as the gate is shown when biased at the flat-band condition. When a large positive voltage is applied to the gate electrode, electrons in the strongly inverted Si substrate surface can tunnel into or through the oxide layer, and give rise to gate current. (Similarly, if a large negative voltage is applied to the gate electrode, electrons from the n^+ -polysilicon can tunnel into or through the oxide-layer and again give rise to gate-current.) Such tunneling occurs because the wave nature of an electron (or hole) allows a finite probability of crossing the barrier, even if the electron does not possess sufficient kinetic energy. This probability increases with larger gate electric fields and/or thinner barriers. Electrons injected by tunneling are generally considered to be in equilibrium with the lattice, and are thus characterized as "cold" (i.e., not "hot").

3.4.1 Fowler-Nordheim (F-N) Tunneling (Tunneling *Into* Silicon Dioxide)

The first type of tunneling is called *Fowler-Nordheim tunneling*. Here electrons are injected by tunneling into the conduction band of the oxide through the triangular energy barrier. Once injected into the oxide conduction-band, electrons are accelerated by the oxide field toward the anode (gate), causing a gate current. Figure 3-18a sketches the energy band diagram for this case assuming a positive bias is applied to the gate.

To determine the probability of an electron exhibiting F-N tunneling through a barrier, Schroedinger's equation is solved for a triangular barrier. The WKB approximation (discussed in most quantum mechanical textbooks) is invoked, and the following expression for the tunneling current-density expression is derived:

$$J = A_F E_{ox}^2 \exp (-B/E_{ox}) \quad (3.6)$$

where $A_F = 1.25 \times 10^{-6} \text{ A/V}^2$, $B \sim 240\text{-MV/cm}$, J is the current-density in A/cm^2 , and E_{ox} is the oxide field in V/cm .¹⁷ According to this equation, the oxide current is exponentially dependent on the electric field and experimental studies have found that the equation accurately describes the oxide current. This can be seen in Fig. 3-20, which shows the measured gate current and the gate current calculated using Eq. 3-6 in oxides 6-nm- and 8.3-nm-thick. The tunneling probability rapidly rises as E_{ox} increases because the tunneling distance (i.e., the




Fig. 3-18 Energy-band diagram for the phenomenon of Fowler-Nordheim tunneling in the MOSFET gate oxide. Also shown are some possible interface-trap assisted leakage paths, with trap levels indicated by short, solid bars.

distance from the Si-surface through the triangular barrier to the oxide conduction-band) becomes smaller as E_{ox} increases.*

It should also be noted that it may be possible for electrons to be “hot” but still not possess sufficient energy to surmount the barrier. In this case, carrier injection may occur by allowing these hot-carriers to tunnel through a smaller triangular-barrier distance. Thus, a synergistic combination of processes which individually would not have caused injection may yet enable carriers to be injected. This effect was modeled by Ning and Yu.¹⁸

At an oxide electric-field of 8-MV/cm, the measured Fowler-Nordheim tunneling-current-density is about 5×10^{-7} A/cm². Thus, for normal device operation, Fowler-Nordheim tunneling does not produce enough gate-current leakage to be significant. Hence, Fowler-Nordheim tunneling does not represent an issue when gate-oxides get thinner as the gate length of MOSFETs are scaled, even to deep-submicron gate-lengths.

3.4.2 Direct Tunneling (Tunneling Through Silicon Dioxide)

If the oxide is very thin (say 4-nm or less), electrons from the inverted silicon

* Because the distance of tunneling between Si surface and the oxide conduction band decreases with increasing electric field.

surface can tunnel *directly* through the forbidden-energy-gap of the oxide layer instead of tunneling into the conduction-band of the SiO_2 layer. In direct-tunneling, electrons tunnel through a trapezoid-shaped barrier as shown in Fig. 3-19. (Because of the differences in the height of barriers for electrons and holes, and because holes have a much lower tunneling-probability in oxide than do electrons, the tunneling limit will be reached earlier for NMOS than PMOS.)

The theory of direct-tunneling is even more complex than that of Fowler-Nordheim-tunneling, and there is no theoretical simple dependence of the tunneling-current-density on voltage or electric field. (While an expression for the tunneling probability can be derived, no analytical expression is available for direct tunneling (as exists for the case of F-N tunneling). Instead, direct-tunneling-current must be calculated from numerical analysis, and the results of such calculations are plotted in Fig. 3-20.¹⁹⁾ Nevertheless, experimental data indicates that tunneling current exhibits a weaker dependence on oxide fields than is shown by the equation that governs Fowler-Nordheim tunneling (Eq. 3-6). This means that direct-tunneling dominates in thin oxides at low voltages.

For oxide thicknesses smaller than 3-nm, the direct tunneling-current becomes very large. Figure 3-21 is a plot of the measured and simulated thin-oxide tunneling-current versus voltage in polysilicon gate MOSFETs. For the gate-voltage range shown in Fig. 3-21, the current is primarily a direct-tunneling current.²⁰ This tunneling represents a limit on the oxide thickness that can be used. This limit will be reached approximately when the gate-to-channel tunneling-current becomes equal to the off-state source-to-drain subthreshold




Fig. 3-19 Energy-band diagram for the phenomenon of direct tunneling through the gate oxide for thin oxides. Also shown are both unassisted-tunneling and some possible interface-trap-assisted leakage paths, with trap levels indicated by short, solid bars.




Fig. 3-20 Theoretical (and experimental) tunneling I-V curves of Al-gate *n*-channel MOS structures under negative gate-bias, illustrating the I-V characteristics of Fowler-Nordheim tunneling in 6-nm- and 8.3-nm-thick oxides and the calculated direct tunneling-currents in 3.9-nm- and 3.4-nm-thick oxides.¹⁹ (© IEEE 1983)

leakage current (e.g., $I_{\text{off}}/W = 10 \text{ nA}/\mu\text{m}$). That is, a MOSFET with a $1\text{-}\mu\text{m}$ gate length and width, would have a channel area of $1\text{-}\mu\text{m}^2$. Thus, to keep its value equal to the subthreshold source-to-drain leakage current, the tunneling leakage current density should not exceed $10^{-8} \text{ A}/\mu\text{m}^2$ (which is equal to $1 \text{ A}/\text{cm}^2$).

From Fig. 3-21, the minimum oxide thickness that could be used to achieve a gate current density of $10^{-8} \text{ A}/\mu\text{m}^2$ is 1.4-nm .* Since this is the thickness of the oxide needed for the 70-nm generation (according to the L_E/t_{OX} guideline given at the beginning of Sect. 3.1 of this chapter), it appears that alternative gate-dielectric materials with reduced gate-leakage will be required for 50-nm MOSFETs and beyond. (Another, more detailed analysis of the leakage-currents in CMOS technology in the 100-nm regime arrives at the same oxide-thickness limit due to tunneling-leakage as the one given above [i.e., 1.4-nm].³⁰) This topic is considered in Chap. 4. It should also be noted that logic circuits can usually withstand higher leakage currents than can DRAMs. Therefore, the gate oxide

* Note that the data shown in Fig. 3-21 are the results of work by researchers at Agere Systems.²⁰ They used an *in-situ* cleaning of the silicon surface (with HF gas, followed by ultra-violet [UV] cleaning) before the rapid-thermal-oxidation. The ultra-thin oxides they grew using this cleaning sequence resulted in oxides with very-low gate leakage currents (Fig. 3-21). Ultra-thin oxides grown by wet rapid-thermal-oxidation (RTO) processes have also reportedly shown smaller gate leakage currents (see Sect. 3.6.2).




Fig. 3-21 Negative gate-current-density as a function of negative gate-voltage for oxide thicknesses from 1.1-nm to 3.1-nm, showing gate tunneling-leakage-current-densities.²⁰

limit for DRAMs is expected to be larger (about 3-nm will be the minimum oxide thickness for DRAMs).

3.5 MODELS OF THIN-OXIDE GROWTH

The Deal-Grove model described in Vol. 1 for the growth of SiO_2 provides excellent agreement with experimental observations for thick oxides.²¹ That is, the rate-constants derived in the Deal-Grove model allow the thickness of oxide films $>350\text{-}\text{\AA}$ to be well predicted as a function of temperature, furnace-ambient, silicon-doping-concentration, and silicon-crystal-orientation. However, the model does not give a detailed understanding of the mechanisms that produce these dependencies, nor is it valid when the oxide is thinner than $200\text{-}\text{\AA}$. Specifically, the experimental measurements of oxide-growth-rates in dry- O_2 are not accurately predicted by the Grove-Deal for oxides less than about $200\text{-}\text{\AA}$ (20-nm). This is the so-called *anomalous regime* of the Deal-Grove model. This is particularly troublesome because gate-oxide-thicknesses of $\leq 100\text{-}\text{\AA}$ are used for sub-micron MOSFETs. Figure 3-22 depicts a computer simulation of the formation of the first few layers of oxide being grown on a silicon surface.²²

Several physical mechanisms have been proposed as models for the enhanced oxidation that is observed when oxides thinner than $200\text{-}\text{\AA}$ are grown in dry- O_2 , including:²³




Fig. 3-22 Si(100)/SiO₂ interface structures after oxidation of a) 2nd b) 4th c) 6th d) 8th layer.²²

1. Models based on space-charge effects where the oxidation-enhancement in the thin regime is due to field-assisted oxidant-diffusion (arising from O₂⁻ coupled diffusion with holes).
2. Models based on the existence of structural defects in the oxide, such as micropores or channels (~10-Å in diameter). These would allow the oxygen molecules to diffuse more rapidly when the oxide is thin.
3. Models based on parallel O₂ and O reactions at the Si/SiO₂ interface.
4. Models which postulate that a blocking layer exists near the Si/SiO₂ interface which forms as the oxide grows and slows down the rate for thicker layers.
5. A model by Massoud *et al.*, based on the presence of a thin surface layer in the silicon where additional reaction sites are available. The concentration of these sites decays exponentially with a characteristic decay length L_2 in Eq. 3-9.²³

Despite the large number of models proposed to explain oxide growth in this very-thin regime, none has yet been shown to be clearly correct, and thus none have been convincingly accepted as more valid than the others. We are therefore left with several empirical models that yield reasonable agreement with measured values of oxide thickness in the thin regime, but with no completely satisfactory

physical explanation. Additional work in the future may help clarify some of these issues.

One *empirical* model for thin oxide growth was proposed by Reisman and Nicollian in 1987.⁵⁹ By analyzing a vast amount of data, they derived an empirical model that calculates the oxide thickness versus time using a general power law of the form:

$$t_{\text{ox}} = a (t_g + \tau)^b \quad (3.7)$$

where a and b are constants, and t_g is the growth time measured in a given experiment, and τ is the time to grow an oxide of thickness t_{ox} already present on the surface. Their model could fit all published dry- O_2 data. In fitting this equation to experimental data, they extracted b values between 0.25 and 1.0, depending on temperature and oxidant-partial-pressure. This equation has two fitting parameters (a and b), just as the Deal-Grove model has two (A and B/A). However, there are significant differences between the models. First, the Reisman-Nicollian model is claimed to be able to fit data down to oxide thicknesses of essentially zero thickness. There is no anomalous regime, as exists with the Deal-Grove model. Second, each model has its own physical basis for the oxide growth process. The Deal-Grove model is based on the idea of oxidant-diffusion and an interface-reaction - with each process dominating the growth under different conditions. Reisman suggests that the interface-reaction actually controls the oxidation process at all times, and that the volume expansion necessary at that interface to accommodate the growing oxide was provided by viscous-flow (relaxation) of the oxide layer. The time-dependent viscous-flow of the oxide in the Reisman model, is used to explain the extracted pressure- and temperature-dependence of the parameters in that model (a and b). A third model by Han and Helms (which we will not consider in detail here), has also been proposed to predict oxide growth. We will, however, compare the results of the Reisman and the Han and Helms model to the Grove-Deal model in upcoming paragraphs.

A comparison between the Reisman-Nicollian model of oxide thickness and the Deal-Grove model is shown in Fig. 3-23. Data from Deal and Grove at 700°C are plotted on linear scales and Eq. 3-7 is plotted with measured values of a and b . Shown for comparison is Eq. 3-7 with the appropriate constants obtained by a fractional weighted least squares fit to the data.²⁴ Kouvatsos extracted the a and b parameters of Eq. 3-7 at 950°C and 1100°C for oxide growth in O_2 diluted in He, and found very good fit to the Reisman-Nicollian power-law model.²⁵

Figures 3-24 and 3-25 again compare the predictions of the Reisman and the Han and Helms models with those of the Deal-Grove model. The model para-




Fig. 3-23 Fits to oxide thickness versus oxidation time using the Deal-Grove model and the Reisman-Nicollian power-law model expression.²⁴

meters for these plots for the Deal-Grove model are the standard A and B/A values for 1 atmosphere. For the Reisman model at 800°C , $a = 0.302 \text{ nm}$, $b = 0.704$, and $\tau = 13.1 \text{ min}$. At 1000°C $a = 3.02 \text{ nm}$, $b = 0.701$, and $\tau = 1.26 \text{ min}$. At 800°C (Fig. 3-24), the differences in these models for very-thin oxides is clear.

The Reisman (and the Han and Helms) model agree fairly well with each other and are a good match to experimental data in the thin regime. The Deal-Grove model does not do a good job for thin oxides, either with τ set at 8 hours




Fig. 3-24 Comparison of three oxidation models for 1 atmos, dry- O_2 oxidation at 800°C .

(the value Deal and Grove extracted in their original work), or with $\tau = 0$ (which predicts even thinner oxide than do the Reisman or Han/Helms models). At 1000°C (Fig. 3-25), the differences in the models in the thin regime are less apparent since much thicker oxides grow at the higher temperature on the same time scale. For the particular parameters chosen for this plot, the Reisman-Nicollian model diverges from the predictions for thicker oxides.

Despite the fact that the Deal-Grove model in its original form does a poor job at predicting oxide growth in dry-O₂ in the thin-oxide regime, their model can be “fixed” to do a much better job. Such a “fix” was developed by Massoud *et al.*, who demonstrated that a much better fit can be accomplished than with the Deal-Grove model alone (by adding an additional term that decays exponentially with thickness to the oxidation rate.). The expression for the oxide growth-rate in the classical Deal-Grove model dt_{ox}/dt (see Vol. 1, Chap. 7) given by:

$$(dt_{ox}/dt) = B/(2t_{ox} + A) \quad (3.8)$$

then becomes

$$(dt_{ox}/dt) = \{B/(2t_{ox} + A)\} + C \exp(-t_{ox}/L_2) \quad (3.9)$$

where

$$C = C^0 \exp(-E_A/k_B T) \quad (3.10)$$

where $C^0 \sim 3.6 \times 10^8$ - $\mu\text{m/hr}$, $E_A \sim 2.35$ -eV, and L_2 is the characteristic decay length described in paragraph 5 above. For dry-oxidation of lightly doped substrates in




Fig. 3-25 Comparison of three oxidation models for 1 atmosphere, dry-O₂ oxidation at 1000°C. The dashed lines are the Deal-Grove model.

the 800-1000°C range, L_2 was found to be ≈ 7 -nm, independent of surface orientation [i.e., the above numbers apply to either (100)- or (111)-oriented silicon substrates]. Heavy doping was found to only slightly affect the oxidation-rate-enhancement in the thin regime. Equation 3-9 has been inserted into SUPREM III and SUPREM IV as the model for thin-oxide growth in dry-oxygen. With Massoud's addition to the Deal-Grove model, its predictions match the data well over the whole thickness range. Note that it was decided to implement the Massoud model (but not the Reisman model) in SUPREM III and IV. This is because many other oxidation-effects have also been tied to the basic Deal-Grove model, and these effects are also modeled in SUPREM III and IV.

While the debate continues about the physical mechanisms responsible for thin oxide kinetics, the problem has taken on a new importance. This is because deep-submicron MOSFET gate-oxides are routinely grown with thicknesses in the anomalous regime. This is an example of an industrial application outpacing basic scientific understanding. From the industrial view, it is more important to be able to grow thin oxide layers reproducibly and uniformly (and with good electrical properties), than it is to understand the governing physical principles.

3.6 SINGLE-WAFER TECHNOLOGY OF THIN OXIDE GROWTH

Thin oxides can be grown using a batch process or a single-wafer process. Batch processes currently use vertical furnaces (200-mm wafers), and such tools are discussed in more detail in Vol. 1, 2nd Ed. With the advent of 300-mm wafer processing and the need to grow uniformly-thick 20-nm oxides across such 300-mm wafers, the single-wafer process may begin to make inroads against batch-oxide-growth processes. Here we will limit the discussion to such single-wafer oxide processes, which are also based on rapid-thermal-oxidation (RTO) methods. Note that single-wafer RTP processes are also described in Vol. 1, 2nd Edition, Chap. 7, and a more comprehensive review of RTP systems and processes is given in Ref. 26. However, in both of these references, the focus is more on the general aspects of RTP systems. Here our focus is on the details of rapid-thermal-oxidation (RTO) tools and processes. Wet-RTO processes are also examined, a topic not covered in Vol. 1, 2nd Ed.

3.6.1 Rapid Thermal Oxidation Tools

Conventional furnace-based oxidation has been the workhorse of the industry, but it encounters some problems when gate oxides thinner than 2.0-nm must be grown, including: 1) furnace oxidation is difficult to scale below 2.0-nm thickness; and 2) the lower temperatures used during such ultra-thin oxide growth processes degrade the oxide quality.

RTO is able to offer better quality ultra-thin oxides when compared to those grown in furnaces for two reasons: 1) RTO grows the oxides at higher temperatures; and 2) RTO is more conducive to cluster tooling. RTO can grow thin oxides at high temperatures because the oxidation time is kept down to just a few seconds (whereas the minimum oxidation time in a batch furnace is at least a few minutes).

There are several advantages to growing oxides at higher temperatures. First, oxides exhibit smaller gate-leakage-currents as their growth temperature increases (up to a maximum of 1050°C, beyond which leakage-currents increase).²⁷ Second, they show higher resistance to boron penetration. In one study, 2-nm-thick oxides grown in a furnace at 800°C were compared to RTP-grown oxides at 1000°C. The results indicated that boron penetration was suppressed better by the RTP-grown oxides.²⁸ The third advantage is that MOSFETs built with the RTP-grown oxides had higher effective carrier mobilities (for both electrons and holes) as the temperature of the oxide growth process was increased from 800°C to 1000°C.²⁹ This was attributed to the smoother Si/SiO₂ interface that results from growing the oxides at higher temperatures.

Cluster tools can potentially produce better-quality oxides because they allow process sequences to be carried out in an integrated fashion. For example, in oxide growth processes, a cleaning procedure is done prior to the growth step. If this can be done *in situ*, the quality of the oxides can be improved. Clustering is easily achievable with single-wafer RTP systems, but is impractical with batch furnace tools. By integrating RTO chambers with other processing modules it may be possible to extend the use of oxides to additional technology generations.

As noted above, with the introduction of single-wafer RTO-systems, it becomes possible to carry out *in situ* surface preparation, wafer rotation, ambient control, and process integration. Because such systems can grow oxides at such rapid rates (i.e., more than 1000-Å/min), it also makes RTO capable of competing economically with vertical hot-wall furnaces.

Figure 3-26 is a cross-sectional view of an RTO reaction-chamber depicting the necessary components of a lamp-heated RTO-system. In this reactor, the wafer is inserted into the reaction chamber by a robot wafer handler onto a rotating SiC support ring. The wafer is rapidly heated at rates of 50-100°C to the process temperature (800-1050°C). Process gases are introduced at reduced pressure in an axial flow pattern where they react to form water vapor, hydroxyl ions, oxygen ions, and other species (depending on the H₂:O₂-ratio and whether N₂, NH₃, HCl, or other reactant gases are introduced). At the conclusion of the oxidation and annealing steps, the wafer is cooled rapidly to a temperature where




Fig. 3-26 Cross-section of an Applied Materials ISSG RTO reactor.

it can safely be removed by the wafer handler from the reaction chamber to an additional cool-down chamber that can be used to enhance system throughput. Cool-down can be enhanced further by providing a wafer backside cooling gas, such as helium or hydrogen.

3.6.2 Wet RTO Processes

As will be discussed in Sect. 3.8, traditional dry oxides are expected to be limited to minimum thicknesses somewhere between 1.6-nm³⁶ and 2.5-nm.³⁷ Various techniques are being explored to reduce this thickness limit. One of these methods employs wet-RTO. A technique pioneered by Applied Materials called *in-situ steam generation (ISSG)* has reportedly allowed oxides in the 2.0-nm thickness range to be formed with improved reliability compared to dry oxides of the same thickness.³⁸ ISSG-oxidation is a low-pressure process (typically below 20 torr, for safety reasons) performed in a cold-wall RTP reactor.

Unlike hot-wall furnaces that employ a pyrogenic torch for growing wet oxides, no hot quartz is used to generate the steam ambient (eliminating the problem of quartz devitrification). Instead, in ISSG-oxidation, H₂O, OH and atomic oxygen are generated directly in the reaction chamber without pre-combustion. The hot wafer acts as an ignition switch, causing reactions among electronic-grade H₂ and O₂ gases (that are pre-mixed in a plenum before being injected into the RTP chamber). This configuration reduces risk of metal contamination, since no metal catalyst is used in the in-situ steam generation method.

The oxidation-rate rapidly *increases* as the pressure is decreased below 20 torr (unlike in conventional oxidation processes where oxidation-rates decrease with decreasing pressure). The growth-rate at 10-torr is nearly twice that of atmospheric dry-rapid-thermal-oxidation. Modeling studies indicate that the oxidation-rate exhibits a strong correlation to the atomic-oxygen-concentration

and not to any other atomic or molecular species. The oxidation-rate is also strongly temperature-dependent compared with wet-atmospheric-oxidation.

Oxides grown with the ISSG process show good characteristics. Within-wafer uniformity and wafer-to-wafer repeatability are well below 1% (1σ), both for thin ($< 40\text{-}\text{\AA}$) and thick ($> 100\text{-}\text{\AA}$) oxide-films. The faster growth-rates improve productivity while offering a thermal-budget reduction. The wide range of temperatures and hydrogen concentrations allow controlled oxidation for any thickness of oxide. The ISSG-oxides also demonstrate better reliability than comparable furnace-oxides, or those created by dry-RTO. Several independent measurements of charge-to-breakdown of 30-50- $\text{\AA}$ wet-RTP oxides show a threefold (or more) improvement over furnace-grown-oxides. The wet-RTO-oxides also exhibit about an order-of-magnitude less gate-leakage-current than dry-RTO oxides, which are comparable to furnace-grown-oxides (Fig. 3-27).⁷⁶

3.7 NITRIDED AND FLUORINATED OXIDES AS MOSFET GATE DIELECTRICS

One modification to the basic SiO_2 material that has recently been intensely examined is the addition of nitrogen to the oxide. That is, oxynitrides have been studied as replacements for silicon dioxide as the gate dielectric of MOSFETs for thicknesses below 4.0 nm. The advantages of oxynitrides over silicon dioxide for this application are the following: **1)** they exhibit improved boron penetration resistance; **2)** they have better breakdown characteristics; **3)** they show greater immunity to hot-carrier-injection effects; and **4)** MOSFETs made with such layers exhibit improved high-field channel-electron-mobility. Improved performance of nitrided silicon-dioxide gate-dielectrics has been associated with the accumulation of a small amount of N at the Si/SiO_2 interface. Interfacial N-accumulation is thought to reduce interfacial defects by relieving strained Si-O bonds and “dangling” bonds. An interfacial peak-concentration of about 1-2 atom % is typically associated with higher breakdown electric fields and lower fixed-oxide charge densities. But, a higher N-concentration (> 5 atom %) is needed to effectively suppress boron penetration through the dielectric layer.




Fig. 3-27 Gate leakage current comparing dry-RTO to 2% & 5% ISSG RTO for 30 $\text{\AA}$ oxides.⁷⁶

Nitridation of oxides is considered to be a variation of silicon oxidation, and such films are formed mainly through the nitridation of silicon oxide or the oxidation of silicon in a nitrogen containing ambient such as NH_3 , N_2O , NO (or mixtures of O_2 and NO). Such films have been formed in high-temperature furnace processing or rapid-thermal-processing tools. Fluorine can also be incorporated into gate oxides as a method for improving its dielectric characteristics. This subject is also discussed in a following section.

3.7.1 Oxynitridation of Silicon in N_2O

Early oxynitride films were formed by nitriding a thermally grown oxide film by exposing it to an NH_3 ambient at high temperatures, and then re-oxidizing the nitrided oxide to reduce the amount of hydrogen that remains in the film after NH_3 nitridation. Such oxynitrides were thus called *reoxidized nitrided oxide* (ROXNOX) films.

Although ROXNOX films exhibit better hot-carrier resistance than do pure oxides, some practical issues make them troublesome to manufacture. First, the ROXNOX formation sequence is complex and difficult to optimize, especially for CMOS applications. For example, the combination of nitridation and reoxidation steps used in the ROXNOX process may leave excess hydrogen in the film. In that case, the density of electron traps will be higher than in a pure oxide film. Since electron trapping is the dominant degradation mechanism in PMOS devices, PMOSFETs with such films will exhibit worse hot-carrier degradation.³⁹ On the other hand, if the reoxidation step is excessive, the film can lose its strength against interface-state generation by hot-carriers. Thus, NMOSFETs containing such films would be prone to more hot-carrier degradation. The gate dielectric layer might also grow too thick. Another drawback is that the best NH_3 -nitrided films always exhibit higher densities of positive fixed charge (Q_f) than do the best SiO_2 films. The fixed charge arises as a result of the nitridation process. Finally, the ROXNOX process generally involves multiple high-temperature steps, which are undesirable for ULSI CMOS applications. As a result, ultra-thin oxynitrides are not formed in production by using NH_3 as the nitrogen source.*

A solution to some of the problems of NH_3 -nitrided films is to avoid the incorporation of hydrogen in the film in the first place. One way to accomplish this is to replace NH_3 with N_2O as the nitriding ambient. Such N_2O -based techniques have indeed proved to be more fruitful because of the hydrogen-free nature of the processing.

* Interested readers can find more details on ROXNOX films in Vol. 3.




Fig. 3-28 SIMS depth profiles of N and H in three kinds of oxide films: (a) pure SiO₂ (#1); (b) NH₃-nitrided SiO₂ (#2); and (c) N₂O-nitrided SiO₂ (#3).

This approach was first used to grow a gate dielectric by directly reacting N₂O at the silicon surface in an RTP system.^{40,41,42,43} Since there is no hydrogen in N₂O, this process results in films with significantly less incorporated hydrogen than NH₃-nitride films. Figure 3-28 shows SIMS profiles of dielectric films prepared by: (a) thermally oxidizing silicon; (b) nitriding an oxide film in NH₃; and (c) growing a film on silicon by RTP in an N₂O ambient.⁴¹ It can be seen that the hydrogen concentration in the N₂O film is significantly smaller than in the NH₃ film. It is also evident that the nitrogen concentration in the N₂O film is highest at the Si-SiO₂ interface. Early studies of such films concluded that they are self-limiting in thickness, as is shown in Fig. 3-29a.^{40,44} The build up of the nitrogen concentration was thought to block the oxidation reaction that occurs simultaneously at the interface. Later work showed that the thickness was not self-limiting (see Fig. 3-29b),^{45,46} and that the thickness in fact, increases approximately as (time)^{1/2}. This seems to indicate that the growth is instead limited by the diffusion of N₂O through the oxide bulk (rather than through the nitrogen-rich layer).⁴⁷ The discrepancy in the apparent growth mechanisms may have been explained by Okada, who observed significant retardation of the growth only at relatively high (~0.9 at%) interfacial nitrogen concentrations, which is higher than observed in some N₂O furnace processes.⁵⁹ However, the interfacial reactions may still dominate growth rates for short times and thin oxides.

Nevertheless, the nitrogen profile in the N₂O film is similar to that in the ROXNOX film, yet this is achieved with only a one-step process (i.e., no




Fig. 3-29 (a) N₂O oxynitride thickness versus oxidation time using RTP for various process temperatures. Ramp-up rate was 200°C/sec. Oxide thickness was measured at a fixed refractive index (1.46)⁴⁰ (© IEEE 1990); (b) N₂O oxynitride thickness versus time in a furnace-anneal process. (© Electrochemical Society 1993)⁴⁵

reoxidation is necessary). The peak nitrogen concentration (at the Si/SiO₂ interface) is ~0.5%, which is less than that found (2-10 atom%) in SiO₂ furnace-nitrided in NH₃ under atmospheric pressure. Furthermore, residual hydrogen incorporation into the film is no longer a concern. This is evidenced by the low electron trapping density exhibited by such films. NMOSFETs fabricated with such films also exhibited less tendency toward hot-carrier degradation than those made with control oxides (i.e., they showed smaller values of ΔD_{it}), and were also less susceptible to the creation of electron traps throughout the oxide under hot-carrier stressing.⁴⁸

However, several limitations were still observed in these N₂O-grown oxynitrides. First, larger initial values of D_{it} were observed than in pure oxide films (Fig. 3-30), even though the rate of their generation under hot-carrier stressing was much smaller (see also Fig. 3-30).⁴⁸ Second, the initial Q_f values were also somewhat higher. Third, the slow growth-rate of such films make them only practical for ULSI applications which use dielectric films thinner than 100 Å (see Fig. 3-29). Fourth, the maximum mobility of electrons in MOSFETs made with such films is ~5% less than in MOSFETs with oxide gate dielectrics (but the mobility is actually higher at large lateral electric fields - see Fig. 3-31).⁴⁹ The most severe limitation, however, is that such RTP N₂O-grown films exhibit

unacceptably large nonuniformities in composition and thickness across a wafer.⁵⁰ Such non-uniformities would limit the use of such films in ULSI MOS devices. Temperature nonuniformities in the RTP chamber, gas depletion, and heat-transfer effects were some of the phenomena suspected of leading to these nonuniformities.

Nevertheless, it was found that growth of such N_2O dielectrics in a furnace (rather than by RTP) resulted in films with thickness uniformities comparable to those of pure oxide films, and with adequate compositional uniformity as well.^{51,52} The process described in these reports was a 950°C furnace step in N_2O , which grew 60-Å-thick dielectric films having a nitrogen concentration at the Si/SiO₂ interface of ~3%. Hot-carrier degradation of PMOSFETs with such films was excellent since electron-trap-densities in these films was also low.

3.7.2 Oxynitridation of Oxides in N_2O or NO

Another method used to form thin oxynitride layer involves a two-step operation. Oxides are first grown in O_2 , and are then subjected to an oxynitridation step in N_2O or NO. When N_2O is used as a post-oxidation-annealing ambient, a wide range of final oxide thicknesses is achievable with much smaller thermal budgets. Processes using this two-step N_2O sequence have been described using an atmospheric-pressure-furnace,^{46,53,54,55} a low-pressure-furnace,⁵⁶ and RTP conditions.⁵⁷ Figure 3-32 shows an example of such a two-step process performed in a conventional furnace at atmospheric pressure.⁵⁴




Fig. 3-30 Changes in the interface trap densities of MOS capacitors with: a) pure SiO_2 ; and b) SiO_xN_y by Fowler-Nordheim electron injection. Electrons were injected from the gate electrodes into the oxide films at a current density of $\sim 10 \text{ mA}/\text{cm}^2$.⁴² (© IEEE 1991)




Fig. 3-31 Effective electron mobility versus effective normal field of NMOSFETs with a 65-Å-thick gate dielectric. The mobility values were calculated using the linear region I_D versus V_{GS} curves ($V_{DS} = 100$ mV), with a Z/L ratio of $75\text{-}\mu\text{m}/60\text{-}\mu\text{m}$. The maximum effective mobility of the oxynitride is 5% lower than that of the control oxide. However, the high-field mobility of the oxynitride shows a 10% improvement.⁴⁹ (© IEEE 1991)

Typically, the oxide is grown in dry- O_2 in a furnace at 850-900°C. The N_2O step is usually carried out at 800-850°C for 5-40 minutes. In the process described in Ref. 55, 50-Å SiO_2 films are grown in dry- O_2 at 850°C for 30 minutes. During the second step in N_2O at 950°C, an additional 35-Å of oxide is grown to form films with a final thickness of 85-Å.

PMOSFETs made by oxynitridation of SiO_2 in N_2O also exhibit enhanced




Fig. 3-32 Two-step oxidation & N_2O nitridation process in a conventional furnace.⁵⁴ (© IEEE 1993)

hot-carrier immunity compared to devices made with pure oxide. This is thought to be due to the fact that electron trapping is suppressed in devices with such N_2O dielectrics.⁵⁸ Consequently, it has been suggested that the optimum N_2O oxynitride process is oxidation in O_2 followed by nitridation in N_2O , rather than oxidation in N_2O alone.

In the low-pressure approach⁵⁶ it was reported that a minimum pressure of between 1 and 50 torr of N_2O was needed before a measurable amount of nitrogen was incorporated into the oxide. However, at low pressures of N_2O (i.e., just beyond the minimum needed for the onset of nitrogen incorporation), the concentration of nitrogen at the interface could be well controlled, but at the same time, minimal additional oxide was grown during the oxynitridation step. Thus, tight control of the final film thickness could be maintained.

As noted in a previous paragraph, the oxide film continues to grow during the second (i.e., N_2O) step. However, if re-oxidation of N_2O oxides is carried out after they are formed, unusual behavior occurs. That is, new SiO_2 grows at the Si/SiO_2 interface, and the existing N-rich layer remains intact and is displaced away from the interface by growth of the new oxide (see Fig. 3-33).⁵⁹

Using N_2O as the nitrogen source during the second step of this procedure was found to have some disadvantages. The concentration of N-incorporation may be




Fig. 3-33 SIMS profile of the oxynitride film grown from 100% N_2O at 1100°C before reoxidation, and after 85 min reoxidation.⁵⁹ By permission of the Electrochemical Society.

too low for some applications, especially suppression of boron penetration, unless a much higher thermal budget is permitted.

More recently oxynitrides formed with the two-step process using NO as the nitrogen source have been reported. Generally, the results for NO oxynitrides overcame the problems of using N_2O as the nitrogen source, in that they offer a lower thermal budget process for incorporating higher concentrations of N, as well as better thickness control for scaled dielectrics.^{60,61} It is thought that nitrogen incorporation in the N_2O process is driven by NO species, which is a product of N_2O molecule dissociation. The N_2O molecule likely dissociates into NO (4.7%), N_2 (64.3%), and O_2 (31%), according to calculations by Tobin *et al.*⁶² Such by-products act in competition. That is, while the NO incorporates nitrogen, O_2 continues the oxidation by reacting with the silicon substrate, and N_2 reduces the partial-pressure of the nitridation species (which increases the thermal budget). The parallel oxidation explains the observed increase of oxide thickness during annealing in N_2O . The high temperature needed for N_2O dissociation ($> 850^\circ\text{C}$) mandates the high thermal budget needed to get acceptable results. Good quality gate-dielectric-films have reportedly been produced with RTP processes using NO + O_2 mixtures.

The percent nitrogen incorporation also depends on the relative amount of NO in the gas mixture. Figure 3-34 shows the dependence of N incorporation on NO concentration for both direct (1-step), and 2-step oxynitride growth carried out in a NO + O_2 mixtures using RTP processes. This indicates that NO can produce




Fig. 3-34 Dependence of nitrogen incorporation in oxide on NO concentration in NO + O_2 mixtures.

oxynitride films with a wide range of incorporated N, allowing the films to be tailored for specific applications.

In another reported process, 4.0-nm-thick oxynitrides were formed in a two-step furnace operation. First, 4.0 nm oxides were grown in O_2 at 800°C with a 6% HCl, and a post-oxidation anneal in N_2 . The second step involved annealing this oxide in a diluted NO ambient at 800°C for 45 min.⁶⁰ Finally, a process that uses a mixture of N_2O and NO in the reaction chamber has been described. The postulated advantage of this method is that the vertical positions of the nitrogen concentration peaks within the oxynitride layer can be adjusted by changing the $N_2O + NO$ mixture.⁶⁴

We should also mention that adding nitrogen to gate oxides has also been reported by several other novel techniques, including implantation of nitrogen through the polysilicon gate and drive-in annealing,⁶⁴ reoxidation of films formed by growing the oxynitride in N_2O or NO,⁶⁵ and nitridation of the Si surface by using a nitrogen remote plasma.^{66,67,68}

3.7.3 Fluorinated Gate Oxides

The presence of fluorine in the gate oxide has also been reported to increase the hot-electron resistance of devices fabricated with such oxides.^{69,70} Such fluorine may inadvertently be introduced from a BF_2^+ source/drain implant, or from an LPCVD-W or LPCVD WSi_x process. (In the W-CVD and WSi_x -CVD processes fluorine is produced during the reaction of WF_6 and SiH_4 .⁷¹) Other reports confirm that deliberate incorporation of fluorine into the gate oxide (from implanting fluorine into a polysilicon film, and then diffusing it into the gate oxide) produces a more hot-electron resistant interface.^{72,73} The increased hot-carrier-resistance of the F-containing-oxides is thought to be due to fluorine atoms which form Si-F bonds. These are stronger than Si-H bonds. The presence of the fluorine implies that some of the Si-H bonds at the Si/SiO₂ interface are replaced by Si-F bonds, thus yielding an interface that has better hot-carrier-resistance.

Unfortunately, while the above benefits make fluorinated oxides attractive for NMOSFETs, the presence of fluorine in the gate oxide may increase the penetration of boron (from p^+ -poly gates) through the gate oxides, and this represents a potential problem for deep-submicron PMOSFETs. That is, BF_2^+ is used when the shallow source/drain-extension-region is formed, and this implant enters the poly gate. Thus, the F from this implant will diffuse through the poly and into the gate oxide during the implant activation steps. However, a recent study indicated that if the fluorine dose implanted into the poly is restricted to a medium dose ($1 \times 10^{14}/cm^2$), no noticeable enhanced boron penetration effect is

observed. In addition, the charge-to-breakdown (Q_{BD}) characteristics of the PMOSFET capacitors fabricated with 4-nm-thick oxides are also significantly improved.⁷⁴

Recently, a new form of “anomalous” leakage was discovered in oxides used in Flash-memory devices. Such leakage occurs at temperatures below 150°C, and thus cannot be screened by a traditional 250°C high-temperature retention bake. However, by incorporating a high concentration of fluorine in the tunnel oxide (introduced in a WSi_2 capped-control-gate process), a much higher resistance to this anomalous leakage is obtained.⁷⁵

3.7.4 “Dual-Gate-Oxide-Thickness” Structures

An increasing number of mixed-signal and system-on-a-chip applications require dual on-chip power-supply-voltages. The higher-voltage may be used for the analog and input/output (I/O) circuitry, and the lower-voltage for the core digital-logic-devices. However, a serious reliability problem would be created if the same thin oxide needed for the high-performance logic MOSFETs was used in the devices subjected to the higher voltage (i.e., the analog and I/O circuitry MOSFETs). That is, the analog and I/O devices require thicker gate oxides than the core logic devices. (The thicker oxide also makes the I/O devices more robust against transient, off-chip electrostatic-discharge-events.) Consequently, it must be possible to fabricate gate oxides with different thicknesses on such ICs.

Early “dual-gate-oxide-thickness” processes had two oxidation steps, with a masked etch-step in between to remove the first oxide from regions intended to have thinner oxide. Newer processes use a different, simpler approach. That is, it has been discovered that the rate of thermal-oxidation on silicon is reduced by nitrogen implants.⁸⁸ Hence, nitrogen implantation into the silicon substrate prior to the oxidation process can be used to facilitate the implementation of such “dual-gate-oxide” ICs. Namely, selective implantation of nitrogen will cause oxides grown on such areas to be thinner than those simultaneously grown on non-implanted areas (Fig. 3-35a). Typical implant conditions for the nitrogen implant are energies of 10-30 keV, at doses of $2 \times 10^{14}/\text{cm}^2$ - $1 \times 10^{15}/\text{cm}^2$. Figure 3-35b shows how the oxide thickness from an 800°C, dry- O_2 oxidation is reduced with increasing nitrogen dose.⁸⁹ It is suggested that nitrogen suppresses oxidation by forming Si-N bonds at the interface of the growing oxide, thereby constraining further growth.

3.8 PROJECTIONS OF THICKNESS LIMITS OF GATE OXIDES

In the late 1970's it was projected that the scaling limit of MOSFETs would be 0.5- μm . In the mid-1980's, this limit was reduced to 0.25- μm . In 2001, there




Fig. 3-35 a) Schematic of the process flow for sub-3-nm gate oxide formation on N_2 -implanted substrates. b) Oxide thicknesses obtained in dry- O_2 at $800^\circ C$ for various nitrogen implant doses (energy = 25 keV) and oxidation times.⁸⁹ (© IEEE 1997)

does not seem to be any device physics barrier for scaling at least to $0.05\text{-}\mu m$ (50-nm). The factor that kept the predicted limit on MOSFET gate lengths in previous decades higher than it is today was the uncertainty in the minimum thickness of the gate-oxide-layer that could be successfully implemented in MOSFETs as they were scaled. Thus, the question of the minimum-oxide-thickness that can be implemented in MOSFETs remains an important one. Here we address the predictions of the minimum-oxide-thickness as viewed in 2001.

There are a number of factors that play a role in the minimum-oxide-thickness that can be used, including: oxide-reliability, tunneling-leakage-current, stress-induced leakage-currents (SILC), polysilicon-depletion, process-induced oxide-damage, and hot-carrier-induced damage. The type of application in which the oxide is to be used also plays a role. That is, different minimum-oxide-thickness limits exist for logic devices, DRAMs, and nonvolatile memory devices. We will discuss each of these topics here, with the exception of hot-carrier-induced damage. The latter phenomenon is not treated because hot-carrier-reliability is expected to greatly improve as the gate voltage is decreased below 3-V (since at such low voltages, few carriers can gain sufficient energy to create interface-traps or shallow oxide-traps). This is one of the positive aspects of scaling devices below $0.25\text{-}\mu m$.

3.8.1 Minimum-Oxide-Thickness Due to Defects and Tunneling

The first two (and probably the most important) phenomena that impact the minimum-oxide-thickness that will be usable in full-scale IC production are: 1) defect densities in the thin-oxide films and; 2) the direct-tunneling-current through these films. We discuss these two effects together here because approximately the same minimum-oxide-thickness limit is set by either of them.

In 1996, Hu predicted what the minimum-oxide-thicknesses would be in production ICs, depending on the power-supply voltage.¹¹ He based these values on the following assumptions: First, the oxides will be used in ICs designed to operate for at least 10 years. Second, the time-to-breakdown (t_{BD}) that oxides of various thicknesses will exhibit can be extrapolated to the 10-year limit by using the anode-hole-injection (AHI) model discussed in Sect. 3.3.4. Figure 3-36 shows a plot of such t_{BD} data for oxides of various thicknesses and intrinsic failure behavior (i.e., the oxides depicted in this plot are assumed to be defect-free, and thus fail according to intrinsic-breakdown failure mechanisms). For such defect-free oxide films, the following thicknesses could be expected to exhibit a 10-year time-to-breakdown behavior for respective power supply voltages: a) 80-Å for 5.5 V (5 V power supply + 10%); b) 45-Å for 3.6 v (3.3 V + 10%); c) 33-Å (3.3-nm) for 2.75 V (2.5 V + 10%).

To allow for defects in the oxide that would weaken them (i.e., the B-mode defects, which locally thin, but do not create catastrophic pinholes in the oxide), Hu suggested that a safety margin be employed. That is, he used a 30% increase




Fig. 3-36 Oxide lifetime as described the anode-hole-injection model.¹¹




Fig. 3-37 The largest allowable supply (gate) voltage, V_{max} , as a function of oxide thickness, consistent with a failure rate of 100-ppm for a total gate area of 10 cm^2 on a chip operating at room temperature for 10 years. Solid and dotted curves correspond to t_{ox} measured by CV-extrapolation or quantum mechanical methods, respectively. The heavy dashed line is the SIA Roadmap (1997 version) for t_{ox} and V_{DD} , corresponding to the indicated year of first manufacture and technology generation.³⁷

in the oxide thickness to allow for such defects. Thus, the minimum oxide thicknesses that he predicted that could be used in production were: a) $110 \text{ \AA}$ for 5 V; b) $65 \text{ \AA}$ for 3.3 V; and c) $45 \text{ \AA}$ for 2.5 V.

Since that time, however, MOSFET scaling has been projected to even smaller gate lengths, mandating the use of even thinner gate-oxides (and smaller power-supply voltages). That is, projections for MOSFETs scaled to 50-nm (and using oxides below 2.0-nm) have been subsequently published. In 1998, Stathis and Di Maria of IBM published a study in which they projected the minimum oxide thickness that could be used in production was 2.6-nm for a 1.0-V power supply in order to meet the 10-year operating lifetime.³⁷ This was based on the conclusion that intrinsic oxide-degradation and breakdown would become the most significant reliability concerns, and therefore the dominant limiting factors that would set the allowable oxide thickness. Figure 3-37 shows the graph reported in that study, indicating that at 1.0 V, the minimum oxide thickness to meet a 10-year lifetime would be about 2.6-nm. This plot also implies that a 2.2-nm-thick gate oxide would no longer meet the ITRS Roadmap requirements.

In 1999, however, another study by Weir *et al.*, of Bell Labs (Lucent Technologies) indicated that if the oxide uniformity could be significantly im-




Fig. 3-38 TDDDB data for 2.0-nm thick oxides at 125°C from MOS-capacitor data.⁷⁹

proved, the reliability projections of an oxide at a given thickness can also be increased. That implies that thinner oxide films than were projected by Stathis and Di Maria may be possible. In fact, Weir showed that oxides with a thickness of 1.6-nm could meet the 10-year operating lifetime goal with a power-supply of 1.2 V - if they were produced with a process that allowed the film-thickness-uniformity to be increased.

In 1999, a 100-nm CMOS-technology that uses an oxide with a thickness of 2.0-nm and a power-supply voltage of 1.5 V was reported by Intel.⁷⁹ Figure 3-38 indicates that this oxide is able to meet the 10-year operating lifetime. In 2000, another report by the same group indicated it could fabricate 130-nm CMOS ICs with a gate oxide that was 1.5-nm-thick and with a 1.3-V power supply. These recent results appear to exceed the predictions of the minimum gate oxide thicknesses made just 2 years ago. At this point (circa 2002), the limit of oxide scaling does not yet seem to have reached.

The tunneling gate-leakage-current is another factor that has been predicted to put a limit on the minimum-oxide-thickness that can be used. In Sect. 3.4.2 we mentioned that at oxide thicknesses below 1.4-nm, the tunneling-leakage-current would become excessive.* This about the same thickness of oxide that has been reported to be used in the most advanced CMOS processes by 2000. Thus, both gate oxide reliability and excessive gating tunneling currents both limit the gate

* At some point this leakage will grow to be too large. That is, for SiO₂ at a gate-bias of ~1 V, the leakage-current changes from 1x10⁻¹² A/cm² at 35-Å, to 1x10 A/cm² at ~15-Å (see also Fig. 3-21). This represents a change of *twelve orders of magnitude* in leakage-current for an oxide-thickness-change of little more than a factor of 2!

oxide thickness at about the same value. (Although, it has been reported that even high levels of tunneling current do not seem to affect device reliability.⁸⁷⁾

3.8.2 Minimum-Oxide-Thickness Due to Stress-Induced Leakage-Current (SILC)

When thin oxides are exposed to high electric-field-stress (and consequently Fowler-Nordheim gate current), it causes them to subsequently exhibit low-field leakage. This effect, termed *stress-induced leakage current* (SILC), was first reported in 1987 (Fig. 3-39).⁸⁰ Apparently, such high-field stress generates neutral oxide-traps that facilitate electron tunneling. In addition, SILC is a transient phenomenon in thicker oxides, but is a continuous current in thinner oxides.^{81,82} That is, in thicker oxides the SILC is observed to decay as traps are filled without significant tunneling out of traps. In thinner oxides, a steady-state current flows when there is an equilibrium between trap-filling and -emptying processes.⁸³

The SILC is a particular problem for non-volatile memory devices because such oxide leakage reduces data retentivity. As shown in Fig. 3-40, it also tends to increase under the high-field program/erase cycles that the tunnel-oxides of such devices experience. The leakage makes nonvolatile-memory tunneling-oxide scaling much below 8-nm difficult (and perhaps impossible), unless the 10-year retention requirement is relaxed.

3.8.3 Soft-Breakdown in Thin Gate Oxides

In Sect. 3.3 we described how oxide films undergo sudden, catastrophic breakdown in which the I-V characteristic becomes essentially ohmic after being




Fig. 3-39 Stress-induced (gate) leakage current (SILC) in 50Å gate oxides.⁸⁰




Fig. 3-40 Stress-induced leakage current is a transient current in thicker oxides but is a continuous current in thinner oxides, preventing nonvolatile memory scaling.⁸¹

subjected to sufficient electrical stress. However, for oxide films thinner than 5.0-nm, the breakdown mechanism may be fundamentally different. That is, another “anomalous” breakdown mode, termed *soft breakdown* or *quasi-breakdown*, occurs. Soft breakdown is detected by a much smaller change of voltage or current during stress, and a post-breakdown I-V characteristic that is given by a power law. In fact, while hard breakdown dominates for thicker oxides, it is often not observed in thin gate oxides. Instead, thin oxides appear to undergo soft breakdown. Also, soft breakdown is exhibited when oxides are stressed using lower and more realistic voltages or current densities. Soft breakdown becomes “softer” and even less abrupt as the stress and oxide thickness is decreased.⁹⁰

Figure 3-41a shows how the gate current in MOSFETs with thin (2.5-nm) oxides changes with time during voltage stressing ($V_G = 4.1\text{V}$ and $T = 140^\circ\text{C}$). Two breakdown regimes are observed: 1) soft breakdown - where the current rises suddenly to an intermediate level of $\sim 10^{-4}\text{A}$ in some devices, and 2) hard breakdown - where the current rises suddenly to about 10^{-2}A . The I-V curves of a pre-breakdown oxide (before), and a post-breakdown oxide (after) are shown in Fig. 3-41b. In fact, when the thin oxide is first stressed with excess voltage, it undergoes SILC. However, further stress beyond a critical oxide-field-value causes the SILC to transition to soft breakdown. That is, soft breakdown is observed to be triggered once the oxide electric-field exceeds 10.7-11.0-MV/cm.⁹¹

After the oxide has undergone soft breakdown, the gate voltage becomes noisy (Fig. 3-42), but the threshold voltage V_T and transconductance g_m do not change significantly (as observed in MOSFETs with an oxide thickness of 2.5-nm). While MOSFETs with thicker oxides (5.5-nm-thick) undergo hard breakdown, their V_T and g_m also undergo little change. However, the current through the gate becomes so large that the transistor characteristics are distorted (making the MOSFETs that undergo hard breakdown unusable). Nevertheless, the only measurable effect on MOSFETs after soft breakdown is an increase in noise level in the gate voltage signal. While such noise fluctuations can couple into the drain current, for many applications this effect will not prevent MOSFETs from functioning properly. This suggests the possibility of a low-voltage technology which does not have gate-oxide breakdown as a failure mode.⁹⁰

A later report, however, indicated that the soft breakdown mode in MOSFETs with channel lengths smaller than 1.0- μm is not observed. That is, such small MOSFETs undergo hard-breakdown and immediate device failure.⁹² Thus, being able to operate deep-submicron MOSFETs in a mode in which gate oxides do not undergo hard breakdown is not a likely scenario. This same study also demonstrated that hard- and soft-breakdown events are triggered by the same type of defect paths. The impact of soft breakdown on the reliability of ICs fabricated with deep-submicron MOSFETs is still being actively examined.

3.8.4 Impact of Polysilicon Depletion

Polysilicon depletion becomes a significant effect in MOSFETs when gate




Fig. 3-41 a) Observed soft and hard breakdown in stress current curves vs. time for $t_{\text{ox}} = 2.5\text{-nm}$ with $V_G = 4.1\text{ V}$ at 140°C .⁹³ b) Oxide I-V characteristics before and after soft-breakdown.⁹⁴ (Pre-breakdown – solid line; Post-soft (short-dash); Post-hard (long-dash)).




Fig. 3-42 Gate voltage measured during sequential -10 mA/cm^2 constant-current stresses of a 2.0-nm gate oxide. Soft breakdown occurs after about 360 seconds. Spikes are visible in the pre-breakdown trace because the stress was removed periodically.⁹⁰

lengths are scaled below $0.25\text{-}\mu\text{m}$. However, while the effect is widely discussed as being a problem, its physical basis on a fundamental level has not been carefully addressed in most texts. Thus, it is useful to explain the origin of this effect before describing its ramifications on the characteristics of deep-submicron MOSFETs.

While the polysilicon-depletion-effect has recently become a topic of attention in the technical literature, in truth it is an effect that *always* exists when a MOS-C (or MOSFET) is biased into depletion or inversion. Although the polysilicon-depletion-effect always occurs under such biasing conditions, it can be ignored by treating the polysilicon gate layer as being an ideal, equipotential region. In fact, this idealized perspective is *merely an approximation, that can only be invoked as long as doing so has insignificant effects on the device behavior*. Once the effect becomes significant, this idealization must be removed. (Note that most book authors are probably oblivious to the fact that this approximation is even invoked, as the correct energy-band diagram is only mentioned in one or two of the dozens of device physics texts that purport to treat MOSFETs.)

Let us consider an MOS-C which has an n^+ -doped polysilicon gate and a p -doped silicon substrate. When a positive bias is applied between the gate and substrate, this causes depletion or depletion/inversion in the silicon substrate (depending on the bias voltage), and the charges induced in the silicon substrate by this biasing are *negative*. In any case, an equivalent *positive* charge must exist




Fig. 3-43 a) Energy-band diagram of an NMOS-C biased to inversion which ignores the depletion-region formed in the polysilicon gate; b) Energy-band diagram of an NMOS-C biased to inversion showing the polysilicon depletion-region that actually always forms.

on the gate (polysilicon electrode). Donor ions in the n^+ -doped poly constitute this positive charge (i.e., some of the mobile, negatively charged electrons leave the poly gate when a positive bias is applied to it). In other words, the biasing causes a *depletion region* of some finite thickness to be formed in the poly gate (at the poly/oxide interface). This depletion region in the poly is the basis of the *polysilicon-depletion-effect (PDE)*. While most energy-band diagrams depict the situation of a MOS-C under depletion (or inversion) as in Fig. 3-43a, this is not strictly correct. That is, this diagram ignores the polysilicon depletion-region. The more correct energy-band-diagram is shown in Fig. 3-43b. Here, the presence of the poly depletion-region is indicated by band-bending (which implies the presence of an electric field) in the poly gate near the oxide.

The existence of an electric field means that a voltage-drop exists across the polysilicon depletion-region (which represents some fraction of the applied gate voltage). This means that the remaining voltage (i.e., the sum of the voltage across the gate oxide and the silicon substrate) is smaller than if no voltage was dropped across the poly depletion-region. The reduced remaining voltage will induce a smaller inversion-layer charge-density than if there was no voltage dropped across the polysilicon depletion-layer. (The effect is the same as if the gate oxide thickness was increased; i.e., PDE increases the “equivalent oxide thickness” $t_{ox_{eq}}$ – see Chap. 4, Sect 4.1). The decreased inversion-layer charge-density results in a degradation of the drain-current I_D of the MOSFET.




Fig. 3-44 a) Equivalent-circuit diagram of the polysilicon depletion-capacitance in series with the gate-oxide-capacitance. b) Low-frequency C-V curves of p -type MOS capacitor with an n^+ -polysilicon gate doped at several different concentrations.⁹⁶

The polysilicon-depletion-effect (PDE) becomes more significant as device scaling continues because the oxide capacitance increases as the oxide is made thinner, but the capacitance due to the polysilicon-depletion-layer remains constant (assuming there is no increase in the poly doping). At some point (i.e., at about when the gate-oxide thickness is scaled below 10.0-nm and the gate voltages are 2.5-V [or lower]), the depletion effect starts to adversely impact the device performance of MOSFETs made with polysilicon gates to a significant degree. We will now explain quantitatively why this is so.

The depletion-capacitance due to the PD-region is in series with the gate-oxide-capacitance (and the silicon-substrate depletion-region-capacitance, as well). An equivalent circuit diagram of the poly-depletion-capacitance in series with the gate-oxide-capacitance is shown in Fig. 3-44a.* The total capacitance of two capacitors in series is given by:

$$1/C_{\text{tot}} = (1/C_1) + (1/C_2) \quad (3.11)$$

Thus, the smaller capacitor largely determines the total capacitance value. For the

* Note that although no capacitor electrodes physically exist at the poly/SiO₂ interface, such “virtual” electrodes are shown in Fig. 3-44a. This is nevertheless a valid equivalent-circuit representation because the two “virtual” electrodes each have the same amount of charge (although of opposite polarity). Thus, the effect of one cancels that of the other.




Fig. 3-45 a) Theoretical plot of C_{inv}/C_{ox} as a function of carrier concentration at the polysilicon/oxide interface for different gate oxide thickness.¹⁰¹ b) Theoretical C-V curves for a thin gate oxide (1-nm-thick) including quantum mechanical effects and polysilicon depletion.⁹⁶

case of the polysilicon-depletion-capacitance and the gate-oxide-capacitance, the gate-oxide-capacitance is much smaller than the polysilicon-depletion-capacitance until the oxide thickness gets below about 10.0-nm. For such thin oxides (assuming the poly layers doping remains constant), the oxide-capacitance starts to get large enough that the poly-depletion-capacitance can begin impacting the total capacitance. This is also shown in Fig. 3-44b in which the low-frequency C-V curves are shown for an MOS capacitor (with a 7-nm gate oxide, a p -substrate, and an n^+ -poly gate with several doping concentrations).⁸⁶ It can be seen that the total capacitance at inversion (C_{inv}) does not return to the full oxide capacitance (i.e., the total capacitance in inversion is reduced by the PDE). The degree of reduction in C_{inv} depends on the poly doping concentration (Fig. 3-45a). This is because the higher the doping concentration, the narrower is the PD region, and thus the smaller is effect of PD. For the 7-nm gate-oxide thickness used in Fig. 3-44b, the poly-depletion effect becomes negligible only when the poly doping reaches about $1 \times 10^{20}/\text{cm}^3$ ($C_{inv} \sim 0.98C_{ox}$, see Fig. 3.45a).

As the oxide thickness gets smaller, the problem gets worse.⁹⁵ Figure 3-45b depicts computer simulated C-V curves for an MOS-C with a 1-nm-thick oxide, and an n^+ -poly on a p -type substrate having a doping density of $4 \times 10^{18}/\text{cm}^3$ (to allow for a V_T of several tenths of a volt). Curve a) is the C-V curve for an ideal (infinite conductivity) gate material, ignoring quantum effects. Curve b) is for a metal gate but including quantum effects. Curves c) and d) are for n^+ -poly gates

doped to $2 \times 10^{20}/\text{cm}^3$ and $1 \times 10^{20}/\text{cm}^3$, respectively, and including quantum effects. Curves c) and d) illustrate the effects of finite polysilicon doping.⁹⁶

The above discussions indicate that if the polysilicon doping density could be increased without limit, the polysilicon depletion effect could be minimized. However, it appears that it will be very difficult to get electrically active doping densities above $10^{20}/\text{cm}^3$ for *n*-type polysilicon and above the mid- to upper- $10^{19}/\text{cm}^3$ for *p*-type polysilicon. This will result in reductions in drive-current capability that might not be acceptable.

To summarize, the impact of polysilicon-depletion on the minimum-oxide-thickness is the following: As the oxide is made thinner, the capacitance of the MOS gate structure is more impacted by the polysilicon-depletion-layer capacitance (assuming the doping in the poly remains constant). The effect is to reduce the total MOS-gate-capacitance to a lower value than if there was no poly depletion-layer-capacitance. For the same gate voltage, the potential at the Si surface is thus reduced, which in turn decreases the inversion-layer charge-density. Thus, the drain current actually decreases as the oxide is made thinner, causing the speed of the circuits made with such MOSFETs to decrease. Figure 3-46 shows how the propagation-delay in a ring oscillator increases with decreasing oxide thickness due to this effect.⁸⁴ This implies that it may not be appropriate to use the thinnest oxide thickness that is allowed by the 5-MV/cm breakdown limit.




Fig. 3-46 At low V_{DD} (e.g., 2 V) and $0.2\text{-}\mu\text{m}$, due to the polysilicon-depletion-effect, optimum speed may require a thicker t_{ox} than that allowed by the 5-MV/cm limit.⁸⁴

3.8.5 Impact of Process Induced Damage

In 1996, Hu suggested that process -induced damage would have less impact on gate-oxide-reliability as oxides less than 10-nm in thickness were used.⁷⁸ That is, oxides that were 6.4-nm-thick showed an order of magnitude smaller interface-trap-density than did oxides that were 11.6-nm-thick (Fig. 3-47). A model that sought to explain this effect treats plasma charging-current as a constant-current-source, rather than a fixed voltage-source. Thus, for the same plasma process conditions, the same amount of current will pass through oxides as they are scaled below 10-nm, regardless of their thickness. In addition, the thinner oxide (e.g., 6.4-nm) is more tolerant of the same current stress than the thicker oxide (11.6-nm-thick). This data led Hu to conclude that plasma-process damage would not become a more serious issue with oxide scaling below 5-nm.

However, more recent information was not as optimistic. In 2000, at the 5th International Symposium on Plasma Process-Induced Damage, P.W. Mason of Lucent Technologies reported that plasma damage did, in fact, increase as the gate oxide thickness was decreased from 11.5-nm to 5.5-nm. The main damage source was the rf-backsputter via-clean process used to prepare vias for metal deposition. The plasma damage was found to correlate with long-term oxide reliability degradation, although not with short-term reliability problems. Another report from K.P. Cheung of Lucent at the same conference indicated that currently available measurement techniques cannot determine whether or not a low-level of plasma-induced damage is occurring.

The fact that plasma-induced damage in gate oxides may still remain a relia-




Fig. 3-47 Plasma-process-antenna-effect actually causes less damage to 6.4-nm oxides than to 11.6-nm oxides.¹¹

bility problem, has led work to continue on ways to limit such damage. In July 2000 it was reported that using 3.0-nm-thick oxides nitrided in N_2O produced CMOS transistors which showed significantly improved resistance to charging damage, especially for PMOS devices.⁸⁵

3.9 MEASURING ULTRA-THIN GATE OXIDES

Ultra-thin oxide films can be measured in a number of ways, as described in detail in Ref. 98. Two of the more common methods are *ellipsometry* and *high-resolution transmission electron microscopy* (HRTEM). Ellipsometry is a powerful and accurate optical method. The technique uses plane-polarized monochromatic light to illuminate the oxidized silicon surface at an angle. (The name *ellipsometer* comes from the use of elliptically polarized light to measure film properties.) An elliptically polarized laser beam is directed at the Si surface at an angle, and is then reflected from both the silicon substrate and oxide surface (Fig. 3-48). The technique makes use of the change of state of polarization when light is reflected from a surface. If the index of refraction (n_i) and the extinction coefficient (κ) of the substrate are known, and if the film is non-absorptive at the wavelength being used (so it's $\kappa = 0$), the state of polarization of the reflected beam then depends only on the thickness of the transparent film (and n_i).

The reflected beam passes through an analyzer drum and onto a detector. The analyzer drum is rotated to produce a minimum value in the light intensity reaching the photodetector. By reading the polarizer and analyzer settings, the




Fig. 3-48 Schematic of an ellipsometer.




Fig. 3-49 HRTEM of 2.4 nm-thick oxide.⁹⁰ (© 1997 IEEE)

film thickness and index of refraction can be determined. The direct outputs of an ellipsometric measurement are the angles ϕ and ψ , which are related to the refractive index of the silicon substrate, the refractive index of the silicon oxide, and the thickness of the film.

If a single reflectance angle is used, multiple film thicknesses can produce a null, and the user must thus start with some idea of the expected film thickness to select the correct value. However, if multiple angles are used, an unambiguous single thickness value can be obtained. In any case, ellipsometry can be used to measure oxide thicknesses down the very thin regime ($< 50\text{-}\text{\AA}$). However, inaccuracies in this regime may be present. Therefore, more complicated methods, such as multiple-wavelength ellipsometry or multiple-angle ellipsometry may be used to improve the accuracy of these measurements.⁹⁷ One recently described technique for measuring ultra-thin oxides involves a modification to conventional ellipsometry. In this method, an oxide *under* a polysilicon gate film is measured with a multiple-wavelength, multiple-angle, laser ellipsometer (the Rudolph Technologies S200-*ultra*® model). This allows the thickness of oxides fabricated *in-situ* in the single-wafer cluster tools described in Sect. 3.8.6, to be determined.⁹⁹

Thin-oxide film-thickness can also be measured from micrographs obtained by HRTEM (Fig. 3-49). Preparing a sample for HRTEM requires the tedious tasks of slicing the wafer, mounting the slice in epoxy, and mechanically polishing and ion milling it to the proper thickness. However, unlike other techniques, no physical values such as index-of-refraction or dielectric constant are needed.

As gate-oxides scale to the ultra-thin regime, issues associated with measuring these films becomes increasingly critical. A transition region is thought to exist between the crystalline-silicon and bulk-silicon-dioxide that extends from

several angstroms up to about 10-Å from the silicon. For ultra-thin oxide films this could constitute 20-50% of the film. The structural differences in the transition region can change the properties of the film, including its refractive index, static dielectric constant, band gap, and effective mass. These property changes can effect many measurement techniques used to determine the oxide thickness. Thus, it is necessary to examine the extent to which this interlayer must be included in optical models to obtain the required measurement precision for ultra-thin oxide films. Surface roughness will also play a role since many of the measurements assume an atomically smooth transition between silicon and silicon dioxide. Leakage and tunnel currents through the oxide will also affect many metrology aspects, including capacitance and conductance measurements.

The presence of contamination on the surface of the dielectrics to be measured is another complicating factor. Such airborne contaminants can form an ad-layer on the surface (see Sect. 3.10.1). Under these circumstances, the ellipsometric response will include the effect of the ad-layer. To eliminate these effects, it is necessary to develop a reproducible and easily implemented cleaning procedure. The analysis of ultra-thin stacked dielectrics consisting of individual layers of oxide and nitride may also be made more complex by parameter correlation effects.

3.10 MANUFACTURING ULTRA-THIN GATE OXIDES IN EARLY-2001

3.10.1 Process Control Issues of Growing Ultra-Thin Gate Oxides

In the 2001 timeframe, gate oxides were still largely being grown with batch processes that employ vertical furnaces. Details of such batch oxide-growth processes (and the tools used to carry them out) are found in Vol.1, 2nd Ed., Chap. 7. It has been demonstrated that these types of processes can grow oxide films as thin as 2.5-nm, and with a uniformity of ± 0.5 -Å across a 200-mm wafer.¹⁰⁰

However, when oxide thicknesses have to be made even thinner (≤ 2.0 -nm), it becomes very difficult to maintain this kind of control using such conventional processing methods (i.e., in which the gate oxide is grown in an oxidation furnace and the polysilicon gate electrode is subsequently deposited in a separate processing tool). In the time between gate-oxide-formation and polysilicon-deposition, the gate oxide is exposed to the fab environment, allowing adsorption of *molecular airborne contamination* (MACs – see also Chap. 6).¹⁰² Such MACs have been shown to have a negative effect on gate-oxide integrity, and they are also known to cause the measured thickness of the gate oxide to increase over time. In traditional batch processing, wafers may be stored for hours (or even days) after the gate oxide is grown, before the poly gate electrode is deposited.

Newer production methods thus form both the gate oxide and the polysilicon in the single vacuum environment of a cluster tool (with separate process chambers linked by an isolated vacuum robot that transfers wafers between chambers). This not only speeds the formation of the gate stack but also does not MACs the opportunity to become incorporated MACs between the two layers.⁹⁹

3.10.2 Extending the Use of Ultra-Thin Silicon Dioxide Layers as Gate Dielectrics: Stacked Oxide Films Which Incorporate Nitrogen

As argued earlier, growing gate dielectrics with a thickness of < 2.0 -nm in a manufacturing environment may not be possible, due to several limits: reliability; tunneling leakage-current; and boron penetration. However, work has continued to try and extend the use of oxides into this thickness regime. The main thrust in the 2001 timeframe for doing this involves the formation a dielectric *stack*, still mainly based on SiO_2 . However, nitrogen is incorporated into the oxide such that it is present in several places: **1)** in a very-thin layer near the Si/SiO_2 interface at a concentration of < 1 atom%; and **2)** in another very thin layer at the poly/SiO_2 interface, at a percentage of greater than 5 atom% (or, more commonly, in the form of a very thin SiON layer on top of the SiO_2 layer). To make such a gate-dielectric stack-structure effective, it is critical to be able to control the amount, position, and concentration-profile of the nitrogen throughout the stack.

Excess nitrogen in the bulk of the film may harm the oxide properties, and thus it is desirable that little (or none) exists in the bulk of the oxide. However, nitrogen at a concentration of $< 1\%$ close to the Si/SiO_2 interface has been found to be useful in strengthening the bottom Si/SiO_2 interface against hot-carrier degradation and interface-state generation, without degrading the electrical properties of the stack. On the other hand, a nitrogen concentration of at least 5 atom% is needed at the top oxide/poly interface to prevent boron penetration into the oxide bulk during subsequent high-temperature processing steps. Such boron penetration into the oxide (i.e., from the p^+ -doped poly of deep-submicron PMOSFETs) has two detrimental effects: **1)** If not prevented from doing so, the boron can enter the Si substrate, causing unacceptable shifts in the V_T of the PMOSFETs; and **2)** If the boron does enter the oxide, but is prevented from entering the silicon substrate, it will nevertheless pile up in the oxide. Such boron-pileup in the oxide has been shown to degrade the oxide reliability, likely by causing defects that weaken the oxide structure.

Thermal oxidation with O_2 , N_2O , and NO (as described in Sects. 3.7.1 and 3.7.2) can tailor the nitrogen profile such that reasonable control of the nitrogen density and profile at the Si/SiO_2 interface and within the bulk oxide can be

maintained. However, it may not be possible to form a layer with enough nitrogen at the oxide/poly interface to prevent B penetration (i.e., > 5 atom% is needed) using thermal techniques in oxide films ≤ 2.0 -nm thick. Instead, a low-temperature plasma-technique (e.g., using a remote nitrogen plasma) can be used to form a very-thin nitride film on the top oxide surface (actually a heavily-nitrided oxide-film is formed with this method).¹⁰³ Such thin SiON-layers may be enough not only to reduce or eliminate boron penetration, but also to increase the stacks permittivity. The result is that by adding an oxynitride film to the stack may cause an increase in its effective thickness of approximately 30%. This, in theory, may also make it possible to reduce the gate leakage-current. The nitride film formed by such a remote plasma nitridation process has also recently been shown to improve the reliability of the dielectric stack.¹⁰⁴ These improvements reportedly arise from reduced leakage and higher voltage acceleration factor.

3.10.3 Use of Ultra-Thin Oxide Layers Under High- k Gate-Dielectric Films

Even when it comes time to use high- k dielectrics in MOSFETs, an ultra-thin silicon oxide layer may still need to be formed on the silicon surface under the high- k dielectric film (to produce a reliable interface between the high- k material and silicon substrate). Such an SiO₂ layer would preserve the interface state characteristics and channel mobility. However, since the interfacial layer contributes to the equivalent oxide thickness, the oxide thickness will still have to be minimized without compromising reliable interface properties. Thus, it seems that processing ultra-thin SiO₂ films may remain a part of silicon IC fabrication for yet a long time!

REFERENCES

1. S. Thompson *et al.*, "MOS Scaling: Transistor Challenges for the 21st Century," *Intel Technology Journal*, 3rd Quarter 1998.
2. D. Wolters and J.F. Verwey, "Breakdown and Wearout Phenomena in SiO₂ Films," Chap. 6, in *Instabilities in Silicon Devices - Vol. 1*, Ch. 1 Eds. G. Barbottin and A. Vapaille, (Elsevier) North-Holland, Amsterdam, 1986.
3. A.G. Revesz, "The Defect Structure of Grown Silicon Dioxide Films," *IEEE Trans. Electron Dev.*, **ED-12**, p. 97 (1965).
4. S. Rigo, "Silica Films on Silicon," in *Instabilities in Silicon Devices - Vol. 1*, Ch. 1 Eds. G. Barbottin and A. Vapaille, (Elsevier) North-Holland, Amsterdam, 1986.
5. I.E. Tamm, *Phys. Z. Sowjetunion* **1**, p. 733 (1932).
6. P. Roblin, *et al.*, "Simulation of Hot-Electron Trapping and Aging in n MOSFETs," *IEEE Trans. Electron Dev.*, **ED-35**, December 1988, p. 2229.
7. B.E. Deal, *J. Electrochemical Society*, **121**: 198C (June 1974).

8. C. T. Sah, "The Evolution of the MOS Transistor," *Proceedings of the IEEE*, October 1988, p. 1280.
9. J.C. Burgoin, "Radiation-Induced Defects in Si/SiO₂ Structure," Ch. 17, *Instabilities in Silicon Devices*, Vol. 2, Ed. Barbottin, North Holland, 1989.
10. E. Harari, "Dielectric Breakdown in Electrically Stressed Thin Films of SiO₂," *J. Appl. Physics*, Vol. 49, No. 4, p. 2478, 1978.
11. C. Hu, "Gate Oxide Scaling Limits & Projections," *Tech. Dig. IEDM* 1996, p. 319
12. R. Moazzami, *et al.*, "Temperature Acceleration of Time-Dependent Dielectric Breakdown," *IEEE Trans. Electron Dev.*, **ED-36**, p. 761, 1989.
13. I.C. Chen *et al.*, "The Effect of Channel Hot-Carrier Stressing on Gate Oxide Reliability of N-MOSFETs," *IEEE Trans. Electron Dev.*, **ED-35**, p. 2253, 1988.
14. K.F. Schuegraf and C. Hu, "Hole Injection SiO₂ Breakdown Model for Very Low Voltage Lifetime Extrapolation," *IEEE Trans. Electron Dev.*, **ED-41**, May 1994, p. 761.
15. J. Suehle and P. Chaparal, "Low Electric Field Breakdown of Thin SiO₂ Films Under Static and Dynamic Stress," *IEEE Trans. Electron Dev.*, 1997, p. 801.
16. J. McPherson and H. Mogul, "Underlying Physics of the Thermochemical E-Model in Describing Low-Field Time-Dependent Dielectric Breakdown in SiO₂ Thin Films," *J. Appl. Phys.* **84**, p. 1513, 1998.
17. Y. Nissan-Cohen, *et al.*, "Measurements of Fowler-Nordheim Tunneling Currents in MOS Structures under Charge Trapping Conditions," *Solid-State Electronics*, **28** (7) p. 717, (1985).
18. T.H. Ning and H.N. Yu, "Optimally Induced Injection of Hot Electrons into SiO₂," *J. Appl. Phys.*, vol. 45, p. 5373, (1974).
19. C. Chang *et al.*, "Carrier Tunneling Related Phenomena in Thin Oxide MOSFETs," *Tech. Dig. IEDM*, 1983, p. 194.
20. T. Sorch *et al.*, "Ultra-Thin, 1.0-3.0 nm Gate Oxides for High Performance Sub-100 nm Technology," *Dig. Tech. Papers IEEE Symp. VLSI Tech.* 1998, p. 222.
21. B.E. Deal and A.S. Grove, "General Relationship for the Thermal Oxidation of Silicon," *J. of Appl. Phys.* **36**, p. 3770, 1965.
22. T. Watanabe and I. Ohdoman, "Large-Scale Modeling of SiO₂/Si(001) Interface Structures by Using a Novel Inter-Atomic Interaction Model," *Abs. Mtg. Electrochem. Soc.*, Spring 2000, Abs. 473.
23. H.Z. Massoud, *et al.*, "Thermal Oxidation of Silicon in Dry Oxygen: Growth-Rate Enhancement in the Thin Regime I Experimental Results, II Physical Mechanisms," *J. Electrochem. Soc.*, **132**, 1985, p. 2685 and 2693.
24. A. Reisman *et al.*, "The Modeling of Silicon Oxidation from 1x10⁻⁵ to 20 Atmospheres," *J. Electron. Mat.* **16**, p. 45, (1987).
25. D.N. Kouvatso and M.K. Hatalis, "Thin Silicon Dioxide Films Grown at Very Low Oxygen Partial Pressure in Oxygen Diluted by Helium," *Abs. Mtg. Electrochem. Soc.*, Fall 1992, p. 399.

26. P.J. Timans *et al* "Rapid Thermal Processing," in *Handbook of Semiconductor Manufacturing Technology*, Y. Nishi and R. Doering, Eds., Chap. 9, pp. 201-86, Marcel Dekker, New York, 2000.
27. G. Eftekhari, *J. Electrochem. Soc.*, **140**(3), p. 787 (1993).
28. M.L. Green *et al.*, *Proc. 6th Intl. Conf. on Advanced Processing of Semiconductors, RTP*, 1998, p. 72.
29. A. Joshi and D.L. Kwong, *IEEE Electron Dev. Letts.*, **12**(1), p. 28 (1991).
30. W. Kirklen Henson *et al.*, "Analysis of Leakage Currents and Impact on Off-State Power Consumption for CMOS Technology in the 100-nm Regime," *IEEE Trans. Electron Dev*, **47**, July 2000, p. 1393.
31. M. Rasras *et al.*, "Photo-Carrier Generation as the Origin of F-N-Induced Substrate hole Current in Thin Oxides," *Tech. Dig. IEDM*, 1999, p. 465.
32. P. Palestri *et al.*, "Impact Ionization and Photon Emission in MOS Capacitors and FETs," *Tech. Dig. IEDM*, 2000, p. 97.
33. C. Lam *et al.*, "Anomalous Low Temperature Charge Leakage Mechanism in ULSI Flash Memories," *Tech. Dig. IEDM*, 2000, p. 335.
34. J. McPherson *et al.*, "Comparison of E and 1/E TDDB Models for SiO₂ Under Long-Term/Low-Field Test Conditions," *Tech. Dig. IEDM*, 1998, p. 171.
35. J.D. Bude *et al.*, "Explanation of Stress-Induced Damage in Thin Oxides," *Tech. Dig. IEDM*, 1998, p. 179.
36. B.E. Weir, "Gate Oxides in 50 nm Devices: Thickness Uniformity Improves Projected Reliability," *Tech. Dig. IEDM* 1998, p. 167.
37. J. H. Stathis and D.J. Maria, "Reliability Projection for Ultra-Thin Oxides at Low-Voltage," *Tech. Dig. IEDM* 1998, p. 167.
38. S. Kuppurao *et al.*, "In Situ Steam Generation: A New Rapid Thermal Oxidation Technique," *Solid State Technology*, July 2000, p. 233.
39. B. Doyle and A. Philipossian, "p-Channel Hot-Carrier Optimization of RNO Gate Dielectrics Through the Reoxidation Step," *IEEE Electron Dev. Letts.*, **EDL-14**, April 1993 p. 161.
40. H. Hwang *et al.*, "Electrical and Reliability Characteristics of Ultrathin Oxynitride Gate Dielectric Prepared by Rapid Thermal Processing in N₂O," *Tech. Dig. IEDM*, 1990, p. 421.
41. A. Uchiyama *et al.*, "High Performance Dual-gate Sub-Half-Micron CMOSFETs with 6 nm-thick Nitrided SiO₂ Films in an N₂O Ambient," *Tech. Dig. IEDM*, 1990, p. 425.
42. H. Fukuda, T. Arakawa, and S. Ohno, "Highly reliable thin Nitrided SiO₂ films formed by rapid thermal processing in an N₂O Ambient," *Jap. Jnl. of Appl. Phys.*, **vol. 29**, p. 2333, 1990.
43. *bid.* Ref. 40.
44. Z. Liu *et al.*, "The Effects of Furnace Annealing on MOSFETs," *Tech. Dig. IEDM*, 1992, p. 625.

45. S.C. Sun, T.S. Chen, and H.Y. Chang, "Thermal Oxidation of Silicon in Pure N_2O ," *Ext. Abs. Mtg. Electrochem. Soc.*, Spring 1993, Abs. #749, p. 1080.
46. N.S. Saks *et al.*, "Characteristics of Oxynitrides Grown in N_2O ," *Ext. Abs. Mtg. Electrochem. Soc.*, Spring 1994, Abs. #162, p. 251.
47. Y. Okada *et al.*, "Evaluation of Interfacial Nitrogen Concentration of RTP Oxynitrides by Reoxidation," *J. Electrochem. Soc.*, **140**, p. L87, June 1993.
48. H. Fukuda *et al.*, "Novel N_2O - Oxynitridation Technology for Forming Highly Reliable EEPROM Tunnel Oxide Films," *IEEE Electron Dev. Letts.*, **EDL-12** (1991) p. 587.
49. H. Hwang *et al.*, "Improved Reliability Characteristics of Submicrometer MOSFETs with Oxynitride Gate Dielectric Prepared by Rapid Thermal Oxidation," *IEEE Electron Device Letters*, **EDL-12** (1991), p. 495.
50. T.Y. Chu *et al.*, "Thickness and Compositional Nonuniformities of Ultrathin Oxides Grown by Rapid Thermal Oxidation of Silicon in N_2O ," *J. Electrochemical Soc.*, **138**, June 1991, p. 113.
51. W. Ting *et al.*, "MOS Characteristics of Ultrathin SiO_2 Prepared by Oxidizing Si in N_2O ," *IEEE Electron Device Letters*, **EDL-12** (1991), p. 416.
52. G.Q. Lo *et al.*, "Improved Performance and Reliability of MOSFETs with Ultrathin Gate Oxides Prepared by Conventional Furnace Oxidation of Si in Pure N_2O Ambient," *Symp. VLSI Tech.* p. 43, 1991.
53. J. Ahn, W. Ting and D.-K. Kwong, "Furnace Nitridation of Thermal SiO_2 in Pure N_2O Ambient for ULSI," *IEEE Electron Dev. Letts.*, **EDL-13**, 1992, p. 117.
54. H.G. Pomp *et al.*, "Lightly N_2O nitrided dielectrics grown in a conventional furnace for E^2 PROM and $0.25\ \mu m$ CMOS," *Tech. Dig. IEDM*, 1993, p. 463.
55. G.Q. Lo, J. Ahn, and D.L. Kwong, "Improved Hot-Carrier Immunity in CMOS Analog Device with N_2O -Nitrided Gate Oxides," *IEEE Trans. Electron Dev.*, **EDL-13**, September 1992, p. 457.
56. M.S. Soo *et al.*, "Very Light Nitridation of Thin Gate Oxide in Low Pressure N_2O Ambients," *Ext. Abs. Mtg. Electrochem. Soc.*, Spring 1994, Abs. #168, p. 262.
57. Y. Okada *et al.*, "The Performance and Reliability of 0.4 Micron MOSFETs with Gate Oxynitrides Grown by Rapid Thermal Processing Using Mixtures of N_2O and O_2 ," *IEEE Trans. Electron Dev.*, **ED-41**, p. 191, February 1994.
58. G.Q. Lo *et al.*, "*p*-Channel MOSFETs With Ultrathin N_2O Gate Oxides," *IEEE Electron Device Letters*, **EDL-13** (1992), p. 111.
59. Y. Okada *et al.*, "Evaluation of Interfacial Nitrogen Concentration of RTP Oxynitrides by Reoxidation," *J. Electrochem. Soc.*, **140**, June 1993, p. L87.
60. R.I. Hegde *et al.*, "Surface and Interface Roughness of Ultrathin Nitric Oxide Oxynitride Gate Dielectric," *J. Electrochem. Soc.*, January 1998, p. L13.
61. C. Gerardi *et al.*, "Nitridation of Thin Gate or Tunnel Oxides by Nitric Acid," *J. Electrochem. Soc.*, August 1999, p. 3958.
62. P. Tobin *et al.*, *J. Appl Phys.*, **75**, 1811 (1994).

63. S. Haddad and M.S. Liang, "Improvement of Thin GOI Using Through-Silicon-Gate Ion Implantation," *IEEE Electron Dev. Letts.*, **EDL-8**, p. 58, 1987.
64. G.D. Leonarduzzi and D.-L. Kwong, "Improving Performance with Oxynitride Gate Dielectrics," *Semiconductor International*, July 1998, p. 225.
65. R.I. Hegde *et al.*, *J. Electrochem. Soc.*, **144**, 1081 (1997).
66. S.V. Hattangady *et al.*, *Tech. Dig. IEDM* 1996, p. 495.
67. D. Kapila *et al.*, "Modeling and optimization of Oxynitride Gate Dielectric Formation by Remote Plasma Nitridation of Silicon Dioxide," *J. Electrochem. Soc.*, **146**, 1111 (1999).
68. P.E. Nicollian *et al.*, "Extending the Reliability Scaling Limit of SiO₂ through Plasma Nitridation," *Tech. Dig. IEDM*, 2000, p. 545.
69. E. F. Da Silva, *Tech. Dig. IEDM*, 1987, p. 848.
70. P. Wright *et al.*, "Hot-Electron Immunity of SiO₂ Dielectrics with Fluorine Incorporation," *IEEE Electron Device Letters*, **EDL-10**, August 1989, p. 347.
71. V. Jain, *et al.*, "Improved Sub-micron CMOS Device Performance in CVD Tungsten Silicide," *1991 Symp. VLSI Tech.*, p. 91.
72. Y. Nishioka *et al.*, "Hot-Electron Hardened Si-Gate MOSFET Utilizing F Implantation," *IEEE Electron Device Letters*, **EDL-10**, April 1989, p. 141.
73. N. Kasai, P. Wright, and K.C. Saraswat, "Hot-Carrier Degradation Characteristics for Fluorine Incorporated NMOSFETs," *IEEE Trans. Electron Dev.*, **ED-37**, June 1990 p. 1426.
74. C.-C. Chen *et al.*, "Improved Ultrathin Gate Oxide Integrity in p⁺-Polysilicon-Gate p-Channel MOS with Medium-Dose Fluorine Implantation," *Electrochem. & Solid-State Letts.*, **3**(6), June 2000, p. 290.
75. C. Lam *et al.*, "Anomalous Low Temperature Charge Leakage Mechanism in ULSI Flash Memories," *Tech. Dig. IEDM*, 2000, p. 335
76. K.G. Reid *et al.*, "Dilute Steam Rapid Thermal Oxidation for 30Å Gate Oxides," *Ext. Abs. Mtg. Electrochem. Soc.*, Spring 1999, Abs. #489, Seattle WA.
77. S.C. Everist, "Characterization of Oxynitride Dielectric Films Grown in Nitric Oxide:Oxygen Mixtures by Rapid Thermal Oxinitridation," *Abs. Mtg. Electrochem. Soc.*, Spring 200, Abs. #455, Toronto, Canada.
78. C. Hu, "Gate Oxide Scaling Limits & Projection," *Tech. Dig. IEDM* 1996 p. 319.
79. T. Ghani *et al.*, "100-nm Gate Length High Performance/Low-Power CMOS Transistor Structure," *Tech. Dig. IEDM* 1999, p. 415.
80. T.N. Nguyen, *Internat. Reliability Physics Symp.* 1987, p. 66.
81. M. Moazzami *et al.*, *IEEE Trans. Electron Dev.* p. 1643, 1990.
82. H. Massoud *et al.*, *5th Intl. Conf. Adv. Thermal Process of Semiconductors*, p. 3.
83. M. Moazzami *et al.*, "Stress-Induced Current in Thin Silicon Dioxide Films," *Tech. Dig. IEDM*, 1992, p. 139.
84. C. Chen, *et al.*, *IEEE Electron Dev. Lett.*, p. 202, 1996.
85. C.- C. Chen *et al.*, *IEEE Trans. Electron Dev.*, July 2000, p. 1355.

86. R. Rios and N.D. Arora, "Determination of Ultra-Thin Gate Oxide Thickness for CMOS Structures Using Quantum Effects," *Tech. Dig. IEDM* 1994, p. 613.
87. Caillet *et al.*, *Dig. Tech. Ppers, Symp. VLSI Technology*, 1999, p. 89-90.
88. H.R. Soleimani *et al.*, "Formation of Ultrathin Nitrided SiO₂ Oxides by Direct Nitrogen Implantation into Silicon," *J. Electrochem. Soc.* **142**, p. L132, 1995.
89. C.T. Liu *et al.*, "Light Nitrogen Implant for Preparing Thin-Gate Oxides," *IEEE Electron Device Letters*, **18**, March 1997, p. 105.
90. B.E. Weir *et al.*, "Ultra-Thin Gate Dielectrics: They Breakdown, But Do They Fail?" *Tech. Dig. IEDM* 1997, p. 73.
91. W. Mizubayashi *et al.*, "Soft Breakdown Mechanism in Ultrathin Gate Oxides," *Abs. Mtg. Electrochem. Soc.* Spring 2000, Abs. 481.
92. J. Sune *et al.*, "Understanding Soft and Hard Breakdown Statistics, Prevalence Ratios, and Energy Dissipation During Breakdown Runaway," *Tech. Dig. IEDM* 2001, p. 117.
93. E. Wu *et al.*, "Structural Dependence of Dielectric Breakdown in Ultra-Thin Gate Oxides and Its Relationship to Soft Breakdown Modes and Device Failure," *Tech. Dig. IEDM* 1998, p. 187.
94. M.A. Alam *et al.*, "A Study of Soft and Hard Breakdown Part I (p. 232), and Part II (p. 239)," *IEEE Trans. Electron Dev.* February 2002.
95. C.-H. Choi *et al.*, "Gate Length dependent Polysilicon Depletion Effects," *IEEE Electron Device Letts.*, **23**, April 2002, p. 224.
96. W.C. Holton *et al.*, "Overview of Semiconductor Devices," Ch. 1 in *Handbook of Semiconductor Manufacturing Technology*, Y. Nishi and R. Doering, Eds., Marcel Dekker, New York, 2000, p. 1.
97. H.G. Tomkins, *Spectroscopic Ellipsometry and Reflectometry: A User's Guide*, John Wiley & Sons Inc., New York, 1999.
98. C. Hayzelden, "Gate Dielectric Metrology," Chap. 2, pp. 17-47 in *Handbook of Silicon Semiconductor Metrology*, Ed. A. Diebold, Marcel Dekker, 2001.
99. D. Leet *et al.*, "Process Metrology for Ultrathin Gate Dielectrics," *Semiconductor International*, August 2001, p. 79.
100. D.A. Buchanan, "Scaling the Gate dielectric: Materials, Integration, and Reliability," *IBM J. Res. & Dev.*, Vol. **43**, No. **3**, July 21, 1999, p. 265.
101. C.Y. Wong *et al.*, "Doping of n^+ and p^+ Polysilicon in a Dual-Gate CMOS Process," *Tech. Dig. IEDM* 1988, p. 238.
102. M.M. Heyns *et al.*, "Cost-Effective Cleaning and High-Quality Thin Gate Oxides," *IBM J. Res. & Dev.*, Vol. **43**, No. **3**, July 21, 1999, p. 293.
103. Y. Wu *et al.*, "Performance & Reliability of PMOSFETs with Stacked Gate Dielectrics with Nitrided Si/SiO₂ Interfaces Prepared by Remote PECVD," *IEEE Trans. Electron Dev.* July 2000, p. 1361.
104. P.E. Nicollian *et al.*, "Extending the Reliability Scaling Limit of SiO₂ Through Plasma Nitridation," *Tech. Dig. IEDM* 2000, p. 545.

Chapter 4

HIGH- k DIELECTRICS

For IC applications, high- k dielectrics are defined as those with a dielectric constant greater than that of silicon nitride (i.e., $k > 7$). High- k dielectric materials are being investigated for use in three main IC applications: 1) as a gate dielectric material to replace SiO_2 in advanced MOSFET structures; 2) as a dielectric material in the capacitor structures of dynamic RAMS (DRAMs); and 3) as a dielectric in the capacitor structure of non-volatile ferroelectric random access memories (FeRAMs). In this chapter we will primarily focus on the first two of these applications. That is, since FeRAMs are not yet a mainstream IC product, we will only give a brief description of high- k FeRAM structures.

There are currently a variety of materials with dielectric constants greater than that of SiO_2 being studied as such high- k replacement dielectrics. These include: silicon nitride (Si_3N_4); aluminum oxide (Al_2O_3), tantalum pentoxide (Ta_2O_5); zirconium oxide (ZrO_2); hafnium oxide (HfO_2), barium strontium titanate (BST), and lead-lanthanum-zirconium-titanate (PLZT - PbLaTiO_3). Table 4-1 lists the dielectric constant and bandgap of these materials.

4.1 HIGH- k DIELECTRICS AS THE GATE DIELECTRIC IN MOSFETS

Let us begin by describing the need for high- k dielectrics in the first of the above three applications, namely, as a gate dielectric in advanced MOSFET structures. Metal-oxide-semiconductor field-effect transistors (MOSFETs) have been continually scaled since they were first introduced in the early 1960s. The gate dielectric employed in all of these scaled generations has been silicon dioxide (SiO_2). As each generation was scaled, this gate oxide also had to be made progressively thinner. For the most advanced CMOS technologies being fabricated in 2001 (0.13- μm), the gate oxides had thicknesses of $\sim 3.0\text{-nm}$. According to the *International Technology Roadmap for Semiconductors - 1999* (ITRS-99),¹ when MOSFET devices used in CMOS are scaled to gate lengths below 0.1- μm (100-nm), they will require gate-oxide-equivalent thicknesses, $t_{\text{oxeq}} < 1.5\text{ nm}$. However, because direct tunneling increases exponentially with decreasing thickness, it may not be feasible to use SiO_2 films with thicknesses

TABLE 4-1 IMPORTANT HIGH-*k* DIELECTRIC MATERIALS

	<u>Dielectric Constant</u>	<u>Bandgap (eV)</u>	<u>Crystal Structure</u>
PbLa ZrTiO ₃	1000		
BaSrTiO ₃	300		
Ta ₂ O ₅	26	4.5	Orthorhombic
ZrO ₂	25	7.8	Monoclinic
HfO ₂	24	5.7	Monoclinic
Al ₂ O ₃	9	8.7	Amorphous
Si ₃ N ₄	7	5.1	Amorphous
SiO ₂ (Reference)	3.9	8.9	Amorphous

smaller than 1.5 nm. Thus, it appears that SiO₂ may become unsuitable as the gate insulator in sub-100-nm MOSFETs if future device scaling requirements are to be met. Of course, process engineers will do everything possible to keep using SiO₂ for this role. This is because SiO₂ is compatible with silicon (and polysilicon) and is well behaved and well understood. Furthermore, it has also been used as the gate dielectric since the inception of MOSFET technology some 40 years ago. Finally, it has been widely predicted that the substitution of high-*k* dielectrics for SiO₂ as a gate dielectric will be markedly difficult due to intrinsic chemical bonding effects and difficult process integration challenges.² *Some have predicted that the greatest challenge to the continued scaling of the MOS transistor may be the replacement of SiO₂ with a high-*k* dielectric!*

In any case, when (and if) SiO₂ is replaced, the replacement material will have to be thicker than oxide to reduce the direct-tunneling current and yet maintain the same MOSFET drive-current capability. This can be achieved by using an insulator that has a higher dielectric constant ($\epsilon_{\text{high-}k}$) than does oxide ($\epsilon_{\text{ox}} = 3.9$). That is, it must be possible to achieve the same equivalent thickness as required for SiO₂, where the oxide equivalent thickness t_{oxeq} , is given by:

$$t_{\text{oxeq}} = t_{\text{high-}k} (\epsilon_{\text{ox}} / \epsilon_{\text{high-}k}) = t_{\text{high-}k} (3.9 / \epsilon_{\text{high-}k}) \quad (4.1)$$

For example, a high-*k* gate insulator with a thickness $t_{\text{high-}k} = 10\text{-nm}$ and a dielectric constant ($\epsilon_{\text{high-}k}$) of 20, will behave in the same way in a MOSFET as an SiO₂ layer with a thickness of ~2.0 nm (see also Fig. 4-1).

Of course, an interfacial layer of SiO₂ (or some other lower-*k* material) will limit the highest possible gate stack capacitance or, equivalently, the lowest achievable t_{oxeq} value. That is, when a gate-dielectric structure consists of a

stack of several dielectric materials, the layer with the lowest-*k* value dominates the overall capacitance and also sets a limit on the minimum achievable t_{oxeq} value.

The capacitance of two dielectrics in series is given by:

$$1/C_{\text{tot}} = (1/C_1) + (1/C_2) \quad (4.2)$$

For example, a dielectric stack structure with an SiO_2 bottom layer and a top layer having a higher-*k* value, will thus have a t_{oxeq} that is calculated from:

$$t_{\text{oxeq}} = t_{\text{SiO}_2} + t_{\text{high-}k} (\epsilon_{\text{ox}}/\epsilon_{\text{high-}k}) \quad (4.3)$$

Since the minimum achievable t_{oxeq} value will never be less than that of the lower-*k* layer, a bilayer approach necessarily compromises the performance of the high-*k* dielectric film.

4.1.1 Integrating High-*k* Dielectrics into MOSFET Structures

The use of high-*k* dielectrics as the gate dielectric in submicron MOSFET structures also improves other device characteristics. First, as a MOSFET is scaled below about 0.3 microns, the threshold voltage V_T begins to decrease as the gate length is decreased (for a constant channel doping value and gate dielectric thickness). This is seen in Fig. 4-2a, where the effect of channel length reduction on the threshold voltage value is plotted for deep-submicron MOSFETs (i.e., gate lengths smaller than 1.0- μm) fabricated with gate dielectric films of




Fig. 4-1 As shown in this hypothetical transistor gate stack, a high-*k* material can be physically thicker yet provide an oxide-equivalent thickness that is electrically thinner ($t_{\text{oxeq}} = 10 \text{ \AA}$ for both) than would be possible using oxynitride dielectrics.




Fig. 4-2 a) The effect of channel-length-reduction on the threshold voltage V_T for deep-submicron MOSFETs fabricated with SiO_2 and Ta_2O_5 as the gate dielectric. The use of Ta_2O_5 reduces the V_T degradation with channel length scaling.³ b) The effect of channel length reduction on the subthreshold swing S_t for deep submicron MOSFETs fabricated with SiO_2 and Ta_2O_5 as the gate dielectric. The use of Ta_2O_5 allows an improved S_t value with channel length scaling.³

SiO_2 and Ta_2O_5 . This data shows that for a specific gate length (e.g., 0.1- μm), the change in V_T from that of a long channel MOSFET (e.g., with a length $> 0.5 \mu\text{m}$, in this example) is greater for MOSFETs built with a gate oxide than with a Ta_2O_5 gate dielectric.

The second improvement in device performance observed when a high- k gate dielectric is used involves the subthreshold-swing of a MOSFET, S_t . This is a measure of how effectively a MOSFET is turned off as the gate voltage is decreased below V_T (see Vol. 3 for more information on S_t). As shown in Fig. 4-2b, a value of 80 mV/decade can still be obtained for MOSFETs built with a high- k gate dielectric (e.g., Ta_2O_5). Note that S_t values smaller than 100 mV/decade are considered very good, and the smaller the S_t value the better. It has been shown that for a dielectric thickness of 5-nm, the optimum dielectric constant is 25, which corresponds to the k -value of Ta_2O_5 .³ For MOSFETs, there is a specific dielectric constant for a given dielectric thickness for which the circuit performance is optimum.

One of the drawbacks of using high- k dielectrics is that if they are deposited directly on Si they tend to have a high-level of interface states, D_{it} . The interface-state-density can be reduced by growing a thin layer of oxide (1-2 atomic layers) on the silicon to passivate the surface. We will describe this issue and other




Fig. 4-3 The current-voltage (I_D - V_{DS}) characteristics of a 0.9 μm NMOSFET using Si₃N₄ and SiO₂ as the gate dielectrics.⁴

processing challenges related to the deposition and etching of various high-*k* films with respect to their suitability as alternatives to SiO₂ as a gate dielectric.

Note that initial results of using an alternative dielectric instead of SiO₂ in MOSFETs has produced some promising results, although none are clearly yet ready for full-scale IC production. Several examples of MOSFETs fabricated with alternative gate dielectrics have been reported. Figure 4-3 compares the current-voltage (I_D - V_{DS}) characteristics of a 0.9- μm NMOSFET using a 20-nm-thick Si₃N₄ gate dielectric to one using a 20-nm-thick SiO₂ gate dielectric. The device structure using the RTCVD-Si₃N₄ gate dielectric exhibits greater drain current.⁴ A second MOSFET used a thermal-CVD process to deposit a Ta₂O₅ gate dielectric. The current-voltage characteristics of 150-nm MOS transistors using such a 4.0 nm-thick Ta₂O₅ film showed an improved drain current value compared to those fabricated with a gate oxide.⁵ A third MOSFET used a Ta₂O₅/SiO₂ gate dielectric with a 2.8-nm equivalent-oxide thickness.⁶ A fourth MOSFET used a gate dielectric stack consisting of SiON/Ta₂O₅/TiN.⁷

According to some researchers,⁵⁴ the ideal gate dielectric stack may end up having an interface consisting of a few atomic layers of Si-O (and possibly N), containing a pseudo-binary oxide. This oxide layer could preserve the critical high-quality characteristics of the SiO₂ interface while providing a higher-*k* value. Then a different, higher-*k* material could be used on top of this interfacial layer.

4.2 HIGH- k DIELECTRICS AS THE CAPACITOR DIELECTRIC IN DRAMS

A DRAM capacitor is a stack of materials consisting of a dielectric sandwiched between two electrodes. Since the invention of the DRAM nearly 30 years ago, either SiO_2 with a dielectric constant (k) of 4, or SiN with $k = 7$, or a combination of these materials has been used as the capacitor dielectric. Polysilicon is used as both the bottom and top electrode. Structures containing these materials are therefore called *silicon-insulator-silicon capacitors* (SIS).

As progress is made to put more memory bits on a chip, the surface area of silicon available for each individual memory cell in a DRAM shrinks rapidly (Fig. 4-4). At the same time operating voltages have been falling from 5V a few years ago, to below 3V today (and probably to about a volt in a few years). However, the charge-storage-capacity for each cell remains at about 30 fF/cell (corresponding to about $1\text{--}2 \times 10^6$ electrons/cell). There are three reasons that the amount of stored charge per cell has not been decreased. First, this charge-storage-capacity is needed to prevent the occurrence of soft errors. Soft errors are caused by alpha particles emitted from naturally occurring trace radioactive impurities in packaging materials or from cosmic rays. Such energetic particles generate minority carriers in the silicon, whose charge can alter memory states. By maintaining the capacitance-per-cell at about 30 fF/cell, the soft-error-rate (SER) can be kept acceptably low. Second, as DRAMs have evolved, the detection capability of the DRAM sense amplifiers has remained about the same. Thus, each cell still needs to have about the same charge-storage-capacity to enable the state of the cell to be read. Third, the data-retention time has remained constant, again requiring about the same charge-storage-capacity per cell.




Fig. 4-4 Capacitor area and the required capacitance density as a function of DRAM bit density.²⁷ (© IEEE)

Until recently, three approaches have been used to maintain this constant value of charge storage per cell. The first involves the use of three-dimensional structures to increase the cell surface area (such as trench capacitors and stacked capacitors). The second involves using ever-thinner layers of dielectric in the capacitor. The latter approach entails increasing the surface area of the capacitor by about a factor of 2x by roughening the surface of the polysilicon bottom electrode. This is achieved by growing the bottom-electrode polysilicon with larger grains, and the resulting films are called *hemispherical silicon grain* (HSG) or *rough-surface polysilicon* (RSP).

However, as the silicon area per cell has continued to decrease, the three-dimensional structures can no longer be scaled further to increase surface area. Thus, in the face of shrinking capacitor area and reduced capacitor voltage, even thinner layers of SiO₂ (or multilayers of *oxide/nitride/oxide* - ONO) have been implemented. Nevertheless, in ONO dielectrics, the minimum thickness is about 50-Å (5-nm). In thinner films, tunneling currents produce excessive leakage. However, the combination of such ONO films, together with HSG is currently used in 0.18-μm and 0.15-μm DRAM production.

But, as memory chips surpass about 256 MB this approach will no longer be adequate because unacceptably high values of leakage current occur. Furthermore, the storage capacitors suffer premature catastrophic breakdown, even with reduced operating voltages. Thus, by examining the capacitor equation, the only remaining option for increasing the capacitance per unit area is to incorporate a dielectric with a higher *k*-value. This enables use of a capacitor dielectric with a large enough thickness that low leakage and high operating reliability to be maintained - while still providing sufficient charge storage with a continuously shrinking plate area and storage voltage. By using such high-*k* dielectrics, the DRAM cell structures could also be significantly simplified.

When the list of high-*k* dielectric candidates for DRAM capacitors is examined one notes that Al₂O₃ (with a *k*-value of 9), does not provide a sufficient increase in *k* to maintain the required charge storage/cell. However, Ta₂O₅, with a *k*-value of 25 can meet the requirement for the next generation or two of DRAMs. The IC industry has had some experience with Ta₂O₅, and it can be deposited in a variety of ways, including CVD, metal-organic CVD, sputtering, and anodization. However, Ta₂O₅ does not provide a sufficiently large improvement in charge storage for the memory generations above 4 Gb that are expected to begin production within the next few years (~2006). The long-term solution appears to lie in the various ferroelectric or near-ferroelectric dielectric materials, such as the various combinations of barium and strontium

with titanate (e.g., barium/strontium-titanate - BST), lead/zirconium-titanate (PZT), and other perovskite metal oxides. These types of materials exhibit k -values from a few hundred to several thousand, enabling them, in principle, to provide sufficient capacitance for DRAMs into the foreseeable future. Such ultra-high- k materials can be deposited using almost any method by which a thin film can be formed (and they come in a wide variety of compositions and morphologies). The dielectric constants tend to be a strong function the specific elemental ratios and crystal structures which, in turn, are a function of the deposition method. The selection of a particular dielectric material and the design of the DRAM cell depend on a number of complex factors, including the process simplification leading to cost reduction.

There are, however, several challenging process integration issues involving the use of high- k materials in DRAM capacitor structures. First, note that in DRAM capacitors the bottom capacitor electrode is the *storage node* and the top capacitor electrode is termed the *plate electrode* (Fig. 4-5). Doped-polysilicon has traditionally been the material used to form the bottom electrode of the DRAM capacitor, and either polysilicon or metal has been used to form the plate electrode. (As noted earlier, if polysilicon is used for both electrodes, the capacitor is called a *silicon-insulator-silicon* capacitor [SIS]. If the top electrode is made of metal, the structure is called a *metal-insulator-silicon* capacitor [MIS].) In any case, polysilicon has been used to form at least one of the capacitor electrodes. However, polysilicon has the problem that it tends to form a




Fig. 4-5 The evolution of the capacitor-electrode structure in stacked-capacitor DRAMs.

silicon oxide layer at the polysilicon/high-*k* interface, either as a native oxide, or during the processing steps used to form or anneal the high-*k* dielectric layer (or even during the subsequent chemical-vapor-deposition of interlevel dielectric layers). These interfacial SiO₂ layers cause an increase in the SiO₂-equivalent thickness of the overall capacitor dielectric layer (which, in turn, reduces the cell capacitance). As a result, a number of other bottom-electrode materials are being considered for the manufacture of cell capacitors, including aluminum (Al), iridium (Ir), platinum (Pt), ruthenium (Ru), tantalum nitride (Ta₂N₃), titanium nitride (TiN) and tungsten (W). Note that if *both* the bottom and top electrodes of the DRAM capacitor are made of metal, the structure is called a *metal-insulator-metal capacitor* (MIM). Table 4-2 shows the requirements of DRAM capacitors as the DRAM size increases above 1Gb/chip.

The Platinum Group Metals (PGM) - Pt, Ir, and Ru - have been actively studied due to their low resistivity, chemical corrosion resistance, thermal stability, and diffusion barrier properties. Each, however, has unique problems with respect to serving as an electrode. For example, Pt has adhesion and etch residue problems, while Ru forms RuO₄ as a toxic by-product of the etch process (and Ru is also susceptible to pinholes and notching because of its ease of oxidation). We discuss these issues in more detail in later sections. Note that PVD and CVD are the most common deposition methods for these materials. Each has its advantages and disadvantages. CVD is capable of much better conformality at lower processing temperatures. However, obtaining high-purity precursors of the PGMs is a rather difficult process. PGM deposition by CVD also presents a significant challenge in the development of volatile precursors.

Cost is another significant factor. For example, to sputter deposit a 50-nm (500-Å) film of Pt onto a 200-mm wafer with a 40% deposition efficiency, the cost is roughly \$1000 per wafer. At 20,000 wafer-starts per month, this cost is

TABLE 4-2 DRAM Stack Capacitor Films Technology Requirements

<u>Year</u>	<u>1999</u>	<u>2002</u>	<u>2005</u>	<u>2008</u>	<u>2011</u>	<u>2014</u>
Technology Node	180 nm	130 nm	100 nm	70 nm	50 nm	35 nm
DRAM Capacity	1 Gb	4 Gb	8 Gb	24 Gb	64 Gb	192 Gb
Capacitor Structure	Cylinder	Pedestal	Pedestal	Pedestal	Pedestal	Pedestal
	MIM	MIM	MIM	MIM	MIM	MIM
Capacitor Dielectric Material	Ta ₂ O ₅	Ta ₂ O ₅	BST	Epi-BST	???	???
Capacitor Dielectric Constant	22	50	250	700	1500	1500

is significant. In CVD, only 20% of the precursor is deposited in the chamber, and roughly 80% of the precursor is exhausted as waste. After subsequent processing, on the order of only 1% of the original material remains on the finished wafer. The remaining deposited-99% is removed by plasma etch or chamber cleaning. For expensive metals, this remaining 99% must be reclaimed.⁸ One report describes an MOCVD deposition process for Pt films.⁹

4.3 HIGH- k DIELECTRICS FOR FeRAM APPLICATIONS

The use of high- k dielectric materials in non-volatile memory FeRAMs is an emerging area. Ferroelectric dielectrics such as *lead zirconium titanate* (PZT - whose k value is 1000-1500), or *strontium bismuth titanate* (SBT), have a perovskite structure and are unique in that this crystal structure retains its “memory” without power. That is, since ferroelectric polarization retention is nearly perpetual, refresh is not needed. The capacitor structure in FeRAMs controls read/write speeds, data-storage lifetime, device layout, and packing density. Figure 4-6 shows a cross-section of an FeRAM cell and an example of a process flow used to incorporate such a cell into a conventional IC structure.²⁵ The early FeRAM device (manufactured by Ramtron Corp.) is being used in game cartridges, where memory is maintained without the use of a battery. The challenges of implementing ferroelectric dielectrics in FeRAMs are similar to those encountered in integrating high- k dielectrics into DRAMs. These include: controlling the interfacial reactions between the dielectric and electrode materials; maintaining thermal stability of the electrodes of the capacitor; and developing plasma-etching processes that provide critical dimensions of the devices. A review of the current status of FeRAMs has recently been published.²⁵

4.4 TANTALUM PENTOXIDE (Ta_2O_5)

Tantalum pentoxide, Ta_2O_5 , has a k -value of 25 and the IC industry has been developing techniques for forming thin films of this material since the early 1980s. It can be deposited in various ways including: 1) LPCVD; 2) metalorganic CVD; 3) sputtering of Ta films followed by oxidation; and 4) anodic oxidation of deposited Ta films. For use as a high- k dielectric layer in DRAMs, the most common deposition method of Ta_2O_5 films is LPCVD. Vendors that supply CVD tools to deposit Ta_2O_5 include Lam Research and Applied Materials.

4.4.1 Tantalum Pentoxide as a DRAM Capacitor Dielectric

We will discuss the use of Ta_2O_5 as a DRAM capacitor dielectric first because it




Fig. 4-6 a) The cross-section of a ferroelectric RAM cell (FRAM); and b) A typical FRAM process flow.²⁵

is more likely to be implemented in this role than as a gate dielectric in MOSFETs. However, we will also discuss the application of Ta_2O_5 as a gate dielectric in the next section. The integration of Ta_2O_5 as a DRAM-capacitor-dielectric has been pursued because its k -value of 25 is high enough to result in adequately high charge-storage values per cell for DRAMs after the 256-Mb generation (i.e., perhaps for the 1-Gb and 4-Gb DRAM generations). In addition, Ta_2O_5 capacitors can simply replace ONO -based capacitors without major process integration problems. (The other change in the DRAM capacitor structure that accompanies the shift to a Ta_2O_5 dielectric is the replacement of the top plate polysilicon electrode with TiN – forming a $\text{TiN}/\text{Ta}_2\text{O}_5/\text{polysilicon}$ structure [which is an MIS capacitor]). Here we describe the various processing issues associated with implementing Ta_2O_5 as a DRAM capacitor dielectric material. While Ta_2O_5 films exhibit many outstanding characteristics, their biggest drawback for DRAM applications is their relatively high leakage-current densities.

As noted above, the most common technique for forming Ta_2O_5 films for DRAM dielectrics is LPCVD.¹⁰ Such films provide good step coverage. The film is formed by the oxygen-assisted thermal decomposition of an organometallic precursor in the presence of oxygen, typically tantalum ethylate (i.e., $\text{Ta}[\text{OC}_2\text{H}_5]_5 + \text{O}_2$), or tantalum tetraethoxy dimethylaminoethoxide (i.e., $\text{Ta}[\text{OC}_2\text{H}_5]_4[\text{OCH}_2\text{CH}_2\text{N}(\text{CH}_3)_2]$ TATDMAE and O_2) at 450°C , and at a

pressure of 1-4 torr. Tantalum ethylate is also referred to as tantalum ethoxide – or TAETO. TAETO was the first precursor used for CVD of Ta_2O_5 and has become the standard one. Typically, a 10-nm-thick Ta_2O_5 layer is deposited, whose SiO_2 -equivalent thickness (t_{oxeq}) is 2.5-nm.

Note that both of these precursors are liquid at room temperature, and so must first be vaporized at 170°C before being flowed into the CVD chamber with Ar as the carrier gas. In addition, the freezing point of TAETO is 18°C and that of TATDMAE is 9°C . Thus, it is a challenge to deliver a fully vaporized precursor to the heated wafer surface without any condensation or decomposition anywhere in the liquid delivery system. To circumvent this problem, TAETO is typically mixed with ethanol. TAETO with 2.5% ethanol has a freezing point of $<10^\circ\text{C}$ and thus does not require a heated ampule or heated liquid lines.

The deposition rate of TAETO in the $450\text{--}485^\circ\text{C}$ range is reaction-rate limited and is thus sensitive to temperature. (The activation energy of the deposition process is 1.3 eV, which implies that the deposition rate doubles every 25°C in this region.) Above 485°C the process transitions into a mass-flow limited regime. Since excellent step coverage and film conformality are needed in DRAM capacitors, the deposition process must be carried out in the reaction-rate limited regime. Figure 4-7 is a SEM showing that excellent step coverage and conformality is achieved in such high-aspect-ratio structures as found in DRAM devices. The smaller SEMs in this figure show the film details at the top and bottom of the opening.

Since these films are deposited on the doped-polysilicon bottom electrode of the DRAM capacitor, it is undesirable to have an interfacial oxide form on the polysilicon either as a native oxide or during thermal process steps that are performed after the Ta_2O_5 layer has been deposited. (As noted earlier, such an interfacial oxide layer would cause the effective thickness of the capacitor dielectric layer to increase.) To eliminate the possibility of such an oxide layer from existing on the poly, a rapid-thermal nitridation (RTN) step is thus carried out on the polysilicon prior to depositing the Ta_2O_5 film (e.g., at 900°C for 60 sec in NH_3). This RTN step both nitrates any native oxide layer already existing on the poly, and the nitride layer that is thus formed acts as a diffusion barrier to oxygen, preventing any new oxide from forming on the poly during later processes.

The as-deposited Ta_2O_5 films, however, exhibit poor leakage characteristics. It is believed that this occurs because the as-deposited LPCVD- Ta_2O_5 films are oxygen deficient and amorphous. Thus, such Ta_2O_5 layers are densified using an anneal in O_2 to improve their leakage characteristics. Annealing in oxygen is




Fig. 4-8 An oxide grows on Ta_2O_5 during post-deposition O_2 annealing. This graph depicts the dependence of t_{oxeq} of Ta_2O_5 on the annealing temperature in a dry- O_2 atmosphere.¹¹

thought to balance the stoichiometry of the films by filling vacancies in the undensified film, thus causing the leakage current to decrease.

The conventional oxygen-annealing method is performed in a furnace at 500°C in the presence of UV-generated O_3 .²⁷ However, more recent methods use a rapid-thermal-process in oxygen (RTO). The RTO process minimizes the impact on the thermal budget and reduces the time during which oxygen can react with the substrate beneath the electrode. The oxygenation process in one approach is carried out at 600°C in an oxygen plasma and the temperature is then ramped quickly above 700°C to achieve crystallization of the Ta_2O_5 film.²⁶ The maximum temperature of the RTO step must still be kept below 800°C because the interfacial oxide under the Ta_2O_5 will grow too thick at higher temperatures (Fig. 4-8)¹¹ - making the SiO_2 -equivalent thickness of the Ta_2O_5 film too great. (That is, at higher temperatures than 800°C , Si can diffuse through the SiN barrier on the polysilicon surface and react with the Ta_2O_5 to form SiO_2 .) Up to a six-order-of-magnitude improvement in leakage current has been reported at 1V using such an RTO-annealing procedure.²⁶

The densification step also crystallizes the amorphous as-deposited film, and this is also thought to reduce the leakage current through the Ta_2O_5 layers. Finally, since the precursor $\text{Ta}[\text{OC}_2\text{H}_5]_5$ is an organometallic material, the as-deposited Ta_2O_5 layer is not carbon-free. The densification step desorbs some of the hydrocarbon and water molecules, which also shrinks the film thickness. The decrease in film thickness also decreases the t_{oxeq} of the film.

Another issue involves keeping the top polysilicon electrode from forming a silicide with the Ta_2O_5 layer. This can be prevented by inserting a barrier layer between the Ta_2O_5 layer and the poly. Materials such as TiN and WN have reportedly be employed for this purpose. Another way around this problem is to use a plate electrode material other than polysilicon. For example, as mentioned earlier TiN (deposited by PVD), is typically used as a top (or plate) electrode material with Ta_2O_5 .

In addition, even the nitride layer formed on the bottom polysilicon electrode will degrade the overall capacitance to some degree, reducing the benefit of using a high- k dielectric. As a result, an alternative material for the bottom electrode has also been studied. In one report, TiN was used for the bottom electrode, and Pt for the top electrode.¹² In another report, reactively sputter-deposited RuO_2 was used for the bottom electrode. (RuO_2 is a conductive oxide with a conductivity of $35 \mu\Omega\text{-cm}$. Since it is already an oxide, it will not form a dielectric oxide layer at the $\text{RuO}_2/\text{Ta}_2\text{O}_5$ interface during post- Ta_2O_5 thermal processes.) In one other publication, a $\text{Ru}/\text{Ta}_2\text{O}_5/\text{Ru}$ capacitor structure was described. The Ru electrodes were deposited by sputtering. In this report, the Ta_2O_5 film after annealing was found to have a k -value of 65. It was speculated that the Ta_2O_5 layer crystallized on the Ru material during the annealing step in such a way that its k -value was significantly increased compared to layers used with other electrode materials. Significantly lower leakage-currents through the Ta_2O_5 layers were also observed after annealing them in forming-gas at 400°C .¹³




Fig. 4-9 Annealing temperature dependence of leakage current density for 2.5 nm Ta_2O_5 capacitors. A rapid thermal oxidation (RTO) is performed after Ta_2O_5 film deposition.¹⁹

Subsequent high-temperature process steps, however, cause the leakage currents through the Ta₂O₅ layers to significantly increase (see Fig. 4-9).¹⁴ In this figure, it is observed that if the Ta₂O₅ layers are subjected to furnace-annealing temperatures of 800°C for 1 hour (or more), the leakage current rises precipitously. Two such high temperature steps that are commonly used in post-Ta₂O₅ layer deposition are those used to reflow the BPSG ILD layer, and to activate the dopants after the source-drain implant step. In one paper, this leakage current was reduced by using a novel low-thermal-budget process that exposed the Ta₂O₅ layers to temperatures no higher than 500°C after the Ta₂O₅ layers are deposited. That is, instead of using a conventional BPSG film, the interlevel dielectric layer (ILD) was formed as follows: An SOG film was first spun on, and this was followed by the deposition of an SiO₂ capping-layer using a low-temperature-CVD process. The source/drain regions were formed with an optimized implant step that employed only a 500°C activation anneal.¹⁴ The application of a Ta₂O₅ layer to a DRAM capacitor formed with rugged polysilicon as the bottom electrode and TiN as the top electrode was described in Ref. 15.

Since leakage through the Ta₂O₅ layers is one of the biggest issues with such films for DRAM applications, work has been done to try and solve this problem. One factor that seems to influence leakage is the surface roughness of the underlying electrode.¹⁶

Another technique for depositing Ta₂O₅ layers is by *metalorganic solution deposition* (MOSD). This also allows the Ta₂O₅ layer to be doped with Al (a factor that improves some of the Ta₂O₅ layer dielectric properties). For example, thin films with 0.9Ta₂O₅-0.1Al₂O₃ composition exhibited an increased *k* value of 42 and a lower leakage-current density (6×10^{-8} A/cm² up to an applied electric field of 1 MeV/cm).¹⁷

Etching of Ta₂O₅ layers can be carried out in variety of fluorocarbon gases (e.g., C₂F₆, CH₄, CF₃Cl, CHF₃, and CCl₃F₂),¹⁸ as well as in discharges of Cl₂, SF₆, N₂, or CH₄/H₂. Selectivities of > 6 for Si over Ta₂O₅ were obtained for SF₆/O₂ discharges.¹⁹

In summary, Ta₂O₅ seems to be the DRAM capacitor dielectric material that will replace ONO. Combined with such polysilicon-electrode techniques as hemispherical-grain poly (HSG), Ta₂O₅ capacitors will be suitable for DRAMs up the 1-Gb and 4-Gb generations (0.15-μm node). The minimum thickness of Ta₂O₅ is estimated to be about an equivalent oxide thickness of 1.5 nm. This implies that even by using HSG and the minimum possible Ta₂O₅ thickness, the limits of Ta₂O₅ technology may be reached at the 1-Gb integration level.

However, for the $0.13\text{ }\mu\text{m}$ technology node it may be possible that Ta_2O_5 will be used with a MIS capacitor structure (i.e., $\text{RuO}_2/\text{Ta}_2\text{O}_5/\text{poly}$). At the $0.1\text{ }\mu\text{m}$ node it may be necessary to use metal-insulator-metal (MIM) structure (i.e., $\text{RuO}_2/\text{Ta}_2\text{O}_5/\text{RuO}_2$). At the $0.05\text{ }\mu\text{m}$ node (50 nm) it is likely that the insulator in an MIM structure will be BST.

4.4.2 Tantalum Pentoxide as a MOSFET Gate Dielectric

Tantalum pentoxide has also been considered as an alternative gate-dielectric material to SiO_2 for MOSFETs with gate lengths of less than $0.1\text{-}\mu\text{m}$. Since oxide films for such devices would have to be thinner than 1.5-nm , excessive leakage-current through the oxide film would make such MOSFETs impractical for use in most circuit applications. Due to the fact that direct-tunneling leakage currents decrease exponentially with the thickness increase of the dielectric layer, a dielectric with a higher k -value could provide the same electrical behavior as SiO_2 but it could be used with a larger thickness. For the case of Ta_2O_5 , which has a k -value of 25, a Ta_2O_5 layer would have a thickness $25/4.0$ times larger than that of an equivalent SiO_2 film. Many of the process integration issues of incorporating into a MOS structure were discussed in the previous section. Here, we describe the challenges specific to using Ta_2O_5 as a gate-dielectric layer.

The first problem that must be addressed involves the fact that when Ta_2O_5 is deposited directly on silicon (or when it is subsequently annealed in oxygen), SiO_2 grows under the Ta_2O_5 . As much as 2-nm of oxide can grow, thereby increasing t_{oxeq} (see Eq. 4-3). This was demonstrated in a report in which Ta_2O_5 was deposited directly on Si and NMOSFET transistors were subsequently fabricated.²⁰ An interfacial SiO_2 layer was found to be under the Ta_2O_5 at the conclusion of all processing. A way to prevent uncontrollable growth of such an oxide during subsequent thermal processing steps is to form an interfacial layer between the Ta_2O_5 and the Si substrate. In the first report of fabricating MOSFETs with a Ta_2O_5 gate dielectric, a 2-nm -thick oxide layer was in fact deliberately grown on the Si before the Ta_2O_5 was deposited. This layer was then annealed in N_2 at 800°C for 30 min (nitriding the oxide). A diffusion-barrier is thus created which prevents oxygen from reaching the underlying Si substrate and growing additional oxide. A TiN gate electrode was employed instead of poly (Fig. 4-10). The leakage current was reported to be equivalent to that of a MOSFET with an SiO_2 gate dielectric of identical thickness.²¹

In a second report describing MOSFETs Ta_2O_5 with a gate dielectric layer, the gate dielectric consisted of a stack (i.e., 1.5-nm $\text{SiO}_2/3.0\text{-}7.5\text{-nm}$ $\text{Ta}_2\text{O}_5/0.5\text{-}1.5\text{-nm}$ SiO_2). This dielectric stack was electrically equivalent to $20\text{-}35\text{-nm}$

SiO₂.^{22,31} A later report described the use of RTP to grow an interfacial layer on the Si substrate with NO at 800°C for 20 sec - which when combined with a CVD Ta₂O₅ layer - produced a gate dielectric with a $t_{oxeq} = 2.3$ -nm thick. The main benefit of using this approach was that the leakage current through the dielectric film was 1000x smaller than when an oxide was used as the interfacial layer.²³ A similar process flow reported use of a RTN step (nitridation of the silicon substrate surface by RTP in an NH₃ ambient at 800°C for 30 sec), to form an interfacial layer on the poly before depositing the Ta₂O₅ film.²⁴

Related to the oxide growth under the Ta₂O₅ is the issue of unacceptably large values of interface traps when using a dielectric other than SiO₂ is in contact with Si. In the Kizilyalli study above, a Ta₂O₅ gate-dielectric-stack (with SiO₂ in contact with both the underlying Si and the overlying poly gate) exhibited interface trap densities comparable to those in MOSFETs fabricated with SiO₂. Charge trapping (a major problem of layered dielectrics) was reportedly not an issue.

A final limitation of using Ta₂O₅ as a gate dielectric is that a barrier over the Ta₂O₅ is needed to prevent silicide from forming due to a chemical reaction of the Ta₂O₅ and the polysilicon gate during subsequent thermal processes. This barrier must be conductive, and TiN, WN, or PGMs used in DRAM top electrodes can be used. However, the difficulty with using such a metallic gate barrier is that the threshold voltage of MOSFETs is increased by about 0.6V. Obviously, this high threshold voltage value is not compatible with low-voltage, low-power technologies. Hence, proper threshold voltage adjustment with counterdoping in the active areas must be employed. However, this produces buried-channel MOSFETs, which degrades their short-channel behavior.




Fig. 4-10 Process flow, cross section, and I-V characteristics of an NMOSFET fabricated with a with a Ta₂O₅/SiO₂ gate dielectric. A TiN gate electrode was also employed.²¹

4.5 BARIUM STRONTIUM TITANATE (BST) FILMS FOR DRAM CAPACITOR DIELECTRICS

Barium:strontium-titanate (BST) is the candidate material of most promise for use as a capacitor dielectric in future generations of high-density DRAMs. BST films are polycrystalline films, with the crystalline grains having a perovskite oxide structure. The chemical formula of BST is $(\text{Ba}_x\text{Sr}_{1-x})\text{TiO}_3$. Common compositions for DRAM use are $0.5 < x < 0.7$. BST films are the leading candidates for advanced DRAM capacitor dielectrics because of their high dielectric constant ($k = 88\text{--}90$ in the film thickness range used in DRAM capacitors), and because the value of k in BST films exhibits a relatively small frequency dependence. That is, the permittivity of perovskite oxide films tends to decrease at high frequencies. For BST films deposited by MOCVD k decreases by $< 2\%$ from 100 Hz to 10 MHz and by $< 7\%$ from 200 MHz to 2GHz.³⁰ This is sufficient to meet the requirements of future DRAM generations. Its large dielectric constant (like those of many other perovskites) is the result of the strong ionic polarization in the material.

Many believe that dielectric films with such high- k values will be needed for DRAM capacitors following the 130-nm generation. For example, the required capacitance density in a DRAM technology with a minimum feature size of $0.15\text{-}\mu\text{m}$ with a DRAM capacitor having a stack structure of $0.3\text{-}\mu\text{m}$ in height (i.e., a 2:1 aspect ratio) and a rectangular area of $0.15\text{-}\mu\text{m}$ by $0.45\text{-}\mu\text{m}$ is $\sim 80\text{ fF}/\mu\text{m}^2$. Figure 4-11 shows a schematic representation of a simple stack-capacitor DRAM cell incorporating a high- k dielectric in the stack capacitor. The high- k dielectric




Fig. 4-11 A schematic representation of a simple stack capacitor DRAM cell incorporating a high- k dielectric layer.⁴⁷ Courtesy of Semiconductor International.

material (e.g., BST) covers the top and sides of the patterned bottom electrode. The top electrode forms the common plate electrode, and the word lines and bit lines are located below the capacitor. The structural simplicity in the capacitor of this cell is apparent. In addition, the vertical height of the bottom electrode can be reduced to provide improved control over the critical dimension by reducing depth-of-focus issues.

Note that perovskite materials exhibit *ferroelectric behavior* when held below their Curie point, and *paraelectric behavior* when above that temperature.²⁸ In conventional DRAMs, the perovskite materials used as the capacitor dielectric are chosen so that they exhibit paraelectric behavior. On the other hand, perovskites that exhibit ferroelectric behavior are used as the dielectrics of FeRAM capacitor structures. BST is a perovskite that has a Curie point that varies linearly with composition, with a value of about 1207°C when $x = 1$, and about -2207°C when $x = 0$.²⁹ The strontium is added to reduce the Curie point below room temperature, which ensures paraelectric operation. The dielectric constant also depends on the film composition, and barium/strontium composition is an important parameter in the use of BST in memory capacitors.

To obtain the high-*k* values necessary for high-density DRAMs, the films must be free of impurities, have correct stoichiometry, and be crystalline.

4.5.1 Deposition of BST Films by CVD

The deposition of BST films can be carried out by a number of methods, including PVD by rf sputtering, thermal MOCVD, sol-gel, and pulsed laser ablation. However, BST film deposition is most commonly done with MOCVD. One reason for this is that rf sputtering requires an appropriately designed composite target. Since sputtering rates for the different elements vary, the useful lifetime of a single sputtering target is too short. BST films deposited by sputtering and sol-gel methods also have a conformality which is typically smaller than 60%, while the conformality of BST films deposited by thermal MOCVD processes can exceed 80%. Because of the high conformality which can be realized, the MOCVD method is likely to be used to deposit the high-dielectric layers for DRAM capacitors. Consequently, we will restrict our discussion of deposition of BST films to the MOCVD processes.

Most precursors of BST are solids at room temperature and are dissolved in an organic solvent for delivery as a liquid to a vaporizer. The liquid is flash-vaporized (to minimize the time precursors spend at elevated temperatures, which minimizes precursor decomposition), and is then transported in a gaseous state to the CVD chamber. This liquid delivery method enables the use of solid

precursors. However, it chemically complicates the deposition process by introducing a solvent. Most of the published work on CVD BST uses precursors that are adducts of barium and strontium β -diketones along with organometallic titanium compounds, primarily: $\text{Ba}(\text{THD})_2$ -tetraglyme, $\text{Ba}(\text{THD})_2$ -PMDTA, $\text{Sr}(\text{THD})_2$ -tetraglyme, $\text{Sr}(\text{THD})_2$ -PMDTA, and $(\text{THD})_2\text{Ti}(\text{i-Pr-O})_2$. (Note that: THD = 2,2,6,6-tetramethylheptane-dionate, and (i-Pr-O) = isopropoxide). These diketones and organometallic-Ti compounds are usually dissolved in butyl acetate. BST films of good quality have been produced using this precursor scheme at deposition temperatures around 550°C. However, at these temperatures, conformality of the deposited films is typically poor and may not be acceptable for three-dimensional capacitor fabrication. A different set of precursors has therefore been developed, which appear promising for BST film growth at lower temperatures. In this precursor scheme, non-adducted versions of the same barium and strontium β -diketones: $(\text{Ba}\{\text{THD}\}_2)_4$ and $(\text{Sr}\{\text{THD}\}_2)_4$, along with $(\text{THD})_2\text{Ti}(\text{i-Pr-O})_2$, are dissolved in tetrahydrofuran (THF). Reports in the literature state that BST films with capacitance densities (planar capacitors) of over 100 fF/ μm^2 and leakage currents in the 10^{-8} A/cm² range can be grown at wafer temperatures of 480°C using these precursors. Other work has demonstrated conformality of 100% at 480°C using non-adducted precursors.

The low-temperature CVD processes for depositing BST films give better conformality than do the higher temperature deposition processes. This is due to the fact that different mechanisms are limiting the deposition process. An Arrhenius plot of the deposition rate of BST growth is shown in Fig. 4-12. It can




Fig. 4-12 Arrhenius plot showing two regimes of rate-limiting mechanisms for CVD BST deposition using non-adducted precursors. Courtesy of Marcel Dekker Publishing.

be seen that two distinct regimes are apparent with a crossover at $\sim 480^{\circ}\text{C}$. In the higher temperature regime (where the deposition rate is approximately constant with increasing temperature), film growth is rate-limited by mass transport from the vapor phase to the film surface. In the lower temperature regime, film growth is limited by the chemical reaction rate on the surface. Films grown at the higher temperatures exhibit poor conformality because the precursor material reacts immediately upon arriving at the surface and does not have time to diffuse into narrow patterned features before being incorporated into the growing BST film. In the surface-reaction-limited regime, the precursor molecules can diffuse a long way on the wafer surface (i.e., into the narrow patterned regions) before reacting and being incorporated into the growing film.

In BST deposition, a tradeoff occurs between needing a high enough deposition temperature to ensure good crystallinity of the perovskite phase, and needing a low enough temperature to achieve adequate conformality. The adducted precursors form highly crystalline perovskites at high temperatures, but such films deposited at low temperatures are mostly amorphous (i.e., they do not exhibit the perovskite crystalline structure). On the other hand, non-adducted precursors can produce perovskite BST films in the low-temperature regime. The low-temperature deposition is also favored when Ru bottom electrodes are used (see Sect. 4.5.3), to prevent the Ru surfaces from being oxidized during the BST deposition in an O_2 atmosphere.

Note, however, that since the BST films are deposited by CVD at low temperatures ($400\text{-}500^{\circ}\text{C}$) to meet the stringent step-coverage requirements, these films must be subsequently annealed to achieve the desired capacitance and leakage-current behavior. Annealing is usually done after the top electrode has been deposited. Such a post-top-electrode deposition anneal is especially beneficial if the top electrode is deposited using a technique that bombards the BST surface with energetic species (such as PVD). That is, the anneal then serves the additional purpose of healing the damage done to the BST film by the PVD process that deposits the top electrode. Reported annealing parameters vary widely. Temperatures between $\sim 500^{\circ}\text{C}$ and 700°C have been used, and both oxidizing (N_2O , O_2) and inert (N_2) ambients have been observed to improve the BST electrical properties. Typically, films grown at higher temperatures (550°C) using the adducted precursors require lower annealing temperatures – around 550°C in oxygen is commonly used. Low-temperature depositions require higher annealing temperatures, closer to 700°C .

The main benefit of the annealing processes is a reduction in the leakage characteristics of BST capacitors. Before annealing, films are leaky (Fig. 4-13),




Fig. 4-13 Leakage curves from unannealed and 550°C oxygen-annealed BST films deposited at 600°C. Labels on the leakage curves give the corresponding capacitance densities of the films.

although the capacitance is quite high. After annealing leakage improves to an acceptable level and capacitance increases by roughly 25%, although the improvement is not as dramatic as that seen in the leakage-current properties.

4.5.2 Microstructure Effects on the Electrical Properties of BST Films

A key factor that impacts the electrical properties of BST films is the amount of titanium in the film. Titanium content is referred to as a percentage of all cations in the film, i.e., $\text{Ti}\% = \{[\text{Ti}]/([\text{Ba}] + [\text{Sr}] + [\text{Ti}])\} \times 100\%$. The best properties (e.g., highest capacitance-density) are found when there is a slight excess of titanium, ~51% (compared to the stoichiometric perovskite composition of 50%). Above this amount, the dielectric constant decreases. The sensitivity of the value of k to the titanium content is quite high (e.g., the dielectric constant drops by ~40% when the titanium concentration increases from 51% to 53%). Hence, it is critical that the amount of titanium incorporated during deposition be tightly controlled. A low-temperature, the non-adducted precursor process has been shown to provide such control of incorporated titanium content.

Another important parameter that impacts the BST electrical properties is the surface roughness. Increased surface roughness correlates with lower dielectric constants and higher leakage currents. Roughness is often observed as a hazy film. That is, films that are rough appear hazy to the naked eye under bright light. Roughness can be caused by depositing the film on a rough underlayer, as well as film growth occurring in an island mode. Roughness resulting from film growth

mode is very sensitive to deposition process parameters, and such parameters must be optimized to find a haze-free process window. Typically less haze is observed at higher deposition temperatures, above 600°C.

4.5.3 BST Integration Issues

Integrating BST into a DRAM process poses many difficult challenges. First, BST is incompatible with the materials that have been used for electrodes up to this point, namely: polysilicon, TiN, and aluminum. This is because BST films contain significant amounts of oxygen and also require high-temperature post-deposition annealing in oxygen ambients. Thus, aluminum films cannot be used as the bottom electrode of a BST DRAM capacitor because they cannot tolerate the high-temperatures used to anneal BST films after deposition ($> 500^{\circ}\text{C}$). Likewise, polysilicon will oxidize either by reaction with the oxygen that can bleed out from the BST film or with the oxygen present in the annealing ambients. Finally, TiN is no longer stable against oxidizing species at temperatures above 500°C. Hence, alternative electrode materials must be employed.

The most suitable electrode materials are based on the metals found near the middle of the periodic table - such as platinum (Pt), ruthenium (Ru), and iridium (Ir). Oxides of these metals are also conductive, making them candidates for inclusion in the electrode stack. As we will discuss in more detail, one of the major problems of using these materials is the problem of electrode patterning, as these materials produce minimal volatile species during dry etching of the noble metal electrodes (with Ru and RuO_2 being the exceptions).

Platinum is the most commonly used electrode for BST in R&D work, as it is non-reactive with BST, and the growth characteristics of BST films on Pt films are good. However, using platinum is also difficult. Since it is a chemically-inert noble metal, it is difficult to dry-etch. But, it does form silicides, and hence it must be deposited on a diffusion barrier to prevent Si-Pt reactions with the Si wafer. (An example of such a film is stacked layer of Ti/TiN, which is deposited on the silicon substrate. Then the Pt film is deposited on the Ti/TiN film.) Since Pt has poor adhesion to most surfaces, the barrier layer must also serve as a “glue layer.” This entire multi-layer bottom electrode structure must then be oxidation resistant and thermally stable enough to withstand the high-temperature, oxidizing environments employed in the processes used to deposit and anneal BST films. Finally, platinum can catalyze reduction in the BST during a forming-gas anneal (instead of protecting the BST against such reduction). Thus, Pt is not a good candidate for the top electrode.

Other electrode materials can also be used, especially for the top electrode. These include ruthenium metal (Ru), ruthenium oxide (RuO_2), iridium oxide (IrO_2), or conducting perovskite oxides such as SrRuO_3 or $(\text{La,Sr})\text{CoO}_3$. Ruthenium and RuO_2 are relatively easy to etch, although one of the products of the etching process, RuO_4 , has a melting point of 25.4°C , and is both a flammable and highly toxic gas. Figure 4-14 shows the process flow for the fabrication of Ru/BST/Ru capacitors. However, none of these materials is standard in semiconductor processing, and hence all will require significant process-development for incorporation in DRAMs.

Dry-etching of metal oxides, perovskites (including BST), and refractory metals will also provide some serious challenges because they do not have volatile by-products. The etching mechanism for these materials must therefore be more physical, like ion milling. Ion milling has been used for patterning these kinds of materials, but the small feature sizes hinder this technique. Dual-frequency plasma etching is also being examined as a way to etch materials such as platinum, metal oxides, and perovskites. The energy of the ions striking the wafer is controlled to maximize the physical effect while taking advantage of whatever chemistry effect there is. Work has also been carried out on developing high-temperature etch processes for such materials (i.e., $> 350^\circ\text{C}$), as a way to improve the etch-profile and etch-rate of such materials. Masking for the etch process is another challenge. The material to be etched must be physically attacked, while the materials that are used for the mask are etched more easily.

The exceptions, as noted earlier, are Ru and RuO_2 , both of which can be patterned by dry-etching (in O_2/Cl_2 plasmas) to give totally anisotropic profiles through chemical reactions which produce RuO_4 in oxygen-containing plasmas. Thus, the profile and feature size of the storage electrodes can be precisely controlled by short gas-residence-time techniques to suppress the deposition of reaction products from the plasma onto the sidewalls. This will permit a 3-D stacked capacitor structure with vertically sided Ru bottom electrodes and BST dielectrics to be used down to 4-16-Gbit DRAMs.

It should also be noted that a diffusion barrier under the bottom electrode is also needed to keep the electrodes from reacting with the polysilicon plug during BST deposition and post-deposition annealing (see Fig. 4-14). Several kinds of materials have been investigated for this role, including: TiN, TiAlN, and TiSiN.

The introduction of high-dielectric materials for DRAM fabrication will also require additional tooling, including:

1. A sputtering system for electrode deposition;




Fig. 4-14 Process flow for the fabrication of Ru/BST/Ru capacitors.⁴⁸ (© 2000 IEEE).

2. An MOCVD reactor for the deposition of the high-*k* dielectric layer, and;
3. A reactive-ion-etch system to pattern the electrode.

Numerous companies manufacture sputtering systems capable of depositing the electrode materials. Applied Materials and Novellus have developed MOCVD reactors capable of depositing BST on 200-mm wafers. Tegal Corp. and Lam Research (along with other suppliers of etch equipment) have demonstrated etch processes for Pt electrodes.

4.6 USE OF OTHER HIGH-*k* MATERIALS AS GATE DIELECTRICS

An extensive worldwide research effort is being undertaken to develop alternative high-*k* dielectrics for MOSFETs to replace silicon dioxide. By the end of 2000 workers in the field were not optimistic that despite intensive efforts to find a high-*k* material that works well, such a material would readily be available for IC manufacturing applications. Their view is that it is going to take at least five years (i.e., until 2006) before a suitable high-*k* material can be introduced into manufacturing. A review of research on the use of binary metal oxides and silicates up to 2000 was published by Wilk *et al.*⁵⁰ and by Gusev *et al.*⁵¹ Here we describe some of the candidates for that application, as of 2001.

4.6.1 Atomic Layer Deposition for Depositing Thin High-*k* Dielectric Films

Before describing the individual high-*k* materials that are candidates for gate dielectrics in MOSFETs, it is useful to discuss a new deposition technique that may be employed for forming such thin dielectric layers. That is, a promising method for depositing very-thin films has been developed for a variety of applications, including gate dielectrics, DRAM capacitor dielectrics, and diffusion barriers. This technique is called *atomic layer deposition (ALD)*, or *atomic layer chemical vapor deposition (ALCVD)*. This technique was pioneered by Tuomo Suntola who invented *atomic layer epitaxy (ALE)* in 1980. The appeal of ALE was that it could deposit very-thin layers of material (<10 nm-thick) with tight composition control. However, at that time the thinnest layers in IC devices were about 100-nm thick, and so ALE was not immediately seen as a technique for the semiconductor market. (It was initially developed for depositing ZnS films for electroluminescent devices.)

In the ensuing 20 years, however, things have changed. Aggressive scaling of critical feature sizes led to lateral dimensions approaching 100-nm, and the thinnest layers approached atomic dimensions. For example, in the gate-dielectric layer, only about 1-nm, or about 4 atomic layers in silicon-oxide equivalents are needed. Clearly, the aggressive scaling has now made applications of the Suntola invention appropriate for integrated circuits. The ALE technique has therefore been modified and commercialized as the ALD technique. The ALD process appears to have several advantages over traditional CVD: it can be carried out at lower temperatures (typically < 400°C); it uses a wider range of precursors; it produces very-thin films; and it inherently obtains 100% step coverage and excellent conformality even over the most challenging topography, and with lower impurity levels.

However, deposition rates are limited by the ALD mechanism. By definition, the thickness of each cycle cannot exceed a few angstroms as determined by the lattice constant of the materials. ALD is therefore targeted at very-thin films having the highest quality demands. The thickness of these films can be controlled simply by counting the cycles. The composition can also be modified and controlled at the atomic level, thus providing an opportunity to create new dielectrics that cannot be easily obtained by other means. Further scaling of critical IC feature sizes will inevitably lead to more applications into the realm of ALD. We will show how ALD can be used to deposit various films in the upcoming sections.

Several equipment vendors have introduced ALD tools. The first is ASM International (Bilthoven, Netherlands) which, through its acquisition of Microchemistry Ltd. (Finland) now has several systems capable of ALD for semiconductor and flat-panel display applications. (Note that Atomic Layer CVD and ALCVD are trademarks of ASM International). Genus (Sunnyvale, CA) also announced a new ALD capability on its Lynx2 platform. Other equipment suppliers are also apparently developing tools with ALD capability. The nature of the ALD process is such that it can be done in a simplified reactor, where gas flow and temperature uniformity will be relatively unimportant. Instead, the hardware design will focus on preventing deposition on the reactor interior and the wafer backside. Development efforts will be focused on creating ALD tools with high throughput, long mean times between cleans, and low defect density. Reliable and precise control of reactants, quick removal of extra reactants and reaction by-products, and short cycle-time will also be critical to the success of this emerging technology.

ALD works quite differently from conventional CVD techniques. Instead of mixing two or more reactant gases inside the deposition chamber - where they either react in the gas phase and fall on the wafer surface, or they react on the wafer surface - in ALD one reactant gas is introduced at a time. Through a process called "chemisorption," a monolayer of the first gas is adsorbed on the wafer surface. That is, individual precursors are pulsed onto the wafer surface in a sequential manner, without mixing in the gas phase. Each individual precursor reacts with the surface to form an atomic layer in such a way that only one layer can form at a time. This is because the surface reaction occurs such that the reaction is complete, and permits no more than one layer at a time to be deposited, no matter how many molecules are applied to the surface in an overdosing mode. Films are built up by introducing short bursts of gases in cycles.

As an example, ALD can be used to deposit a thin silicon-oxide layer by using silane and oxygen. At room temperature, silane gas is introduced into a chamber containing the wafer. Silane molecules will be adsorbed onto the wafer surface until a monolayer of silane molecules exists over the entire exposed surface of the wafer. Thereafter, no more molecules will be adsorbed by the wafer surface. If the temperature is kept low enough, a stable chemisorbed monolayer will form over the exposed wafer surface. Then, the excess silane gas is pumped from the chamber, and it is replaced with oxygen or water vapor. These molecules react with the silane to form an oxide, and the reaction is completed when one monolayer of oxide has been formed. Then, the excess oxygen is removed, and a

second burst of silane gas is fed into the chamber to form the next monolayer of silane, and so on. This discussion demonstrates that ALD is a technique best suited for depositing binary materials such as SiO_2 and metal oxides (e.g., Ta_2O_5 , Al_2O_3 , ZrO_2 , HfO_2 , etc).

By quickly switching the gases on and off (in less than 1 sec), it is possible to obtain reasonable growth rates, up to 200-Å/min. For those films that are deposited in the thickness range of 10-50-Å (or less), such growth rates should produce acceptable throughputs. In addition, since it is only necessary to saturate the wafer with the precursor, the chamber does not have to be designed for uniform reactant coverage. This allows the chamber to be kept very small (e.g., only 4 mm high), which in turn, allows as many as 4 cycles per second to be run. The claim made earlier that ALD deposition temperatures are generally low can now be understood in light of the fact that this process depends on chemisorption.

4.6.2 Aluminum Oxide (Al_2O_3) as a Gate Dielectric

Aluminum forms a stable oxide (aluminum oxide, Al_2O_3), and it is one of the materials that is being studied as a high- k gate dielectric. The k -value of Al_2O_3 is about 9, which is about three times as large as that of SiO_2 . The effective k -value of the dielectric layer which employs Al_2O_3 is, in fact, even somewhat smaller (i.e., it is ~5.5-6.0). This reduction in the effective k -value occurs because a thin interfacial SiO_2 layer inevitably forms between the Al_2O_3 layer and the silicon substrate during Al_2O_3 deposition. This extra, unwanted, interfacial layer reduces the effective k -value, and increases the equivalent oxide thickness (EOT) of the Al_2O_3 layer. (But this interfacial layer also plays a beneficial role in reducing the interface state density leakage current.) Thus, while Al_2O_3 promises to provide a dielectric layer that has an improved k -value, this improvement may only be adequate for a single technology node.

Aluminum oxide is attractive as a gate dielectric for future MOSFETs not only because it has a higher k -value than SiO_2 , but because it also exhibits excellent thermal stability when it is in contact with silicon, and because it has a wide energy gap (~8.3 eV). Furthermore, it is compatible with polysilicon without requiring any barrier materials.

Recent work has described the fabrication of CMOS devices with an Al_2O_3 gate dielectric.^{37,38} The Al_2O_3 layer is deposited by atomic layer deposition (ALD - as described in Sect. 4.6.1), using trimethyl-aluminum (TMA) and ozone as the precursors, at 450°C. (Figure 4-15 shows how an ALD process can be used to deposit an Al_2O_3 layer using the above precursors.) Polycrystalline silicon is then deposited and patterned, junction implants are performed, and a rapid ther-

GROWTH Al_2O_3 FILM FROM $\text{Al}(\text{CH}_3)_3$ AND H_2O




Fig. 4-15 Atomic layer CVD works by introducing one reactant gas at a time. The first gas is “chemisorbed” onto the wafer surface. Excess gas is then purged and the second gas (in this case, water vapor) is introduced. This gas reacts with the chemisorbed layer, creating a monolayer of deposited film. Courtesy of Semiconductor International.

mal anneal at $T = 1000^\circ\text{C}$ is performed. The leakage current density exhibited by MOS capacitors with an Al_2O_3 layer is 2-3 orders of magnitude lower than that observed in MOS capacitor built with an SiO_2 layer with the same EOT.

One major drawback of MOSFETs built with an Al_2O_3 dielectric layer is that the carrier mobility is smaller than in MOSFETs built with SiO_2 dielectric layers, probably due to electron trapping by the Al_2O_3 material. By the end of 2000, the reason why such electron trapping occurs in Al_2O_3 layers (and other high-*k* dielectric materials) is still unknown.

4.6.3 Zirconium Oxide (ZrO_2) as a Gate Dielectric

Zirconium oxide (ZrO_2) is considered to be one of the most promising high-*k* dielectric candidates to replace the SiO_2 gate dielectric. ZrO_2 has a dielectric constant of ~20-25 and is thermodynamically stable in contact with silicon.⁴⁴ In addition, ZrO_2 has a band gap of ~5.1 eV and a lattice mismatch with silicon of only 2.1%. It has been shown that reactively sputtered ZrO_2 (i.e., a Zr sputter target is used in an Ar + O_2 ambient) has a low equivalent-oxide-thickness

(EOT), low leakage, and good reliability characteristics.^{40,41} (Another way that ZrO_2 can be formed with a PVD process is by oxidizing a sputtered Zr film in an RTP process.⁴⁵) ZrO_2 films can also be etched in HF solutions. It has also been reported that doping the ZrO_2 films with Al produces amorphous films with better uniformity, but with a slightly lower dielectric constant. This doping can be achieved in a PVD deposition process by co-sputtering with an Al target.⁴¹

ZrO_2 films can also be deposited using an atomic layer deposition process (ALD).^{42,43} The ALD process has the inherent advantage of conformality over PVD deposition processes. Such an ALD process for ZrO_2 is illustrated in Fig. 4-16. Generally, ALD requires that the metal compound precursor and nonmetal compound precursor (ZrCl_4 and H_2O , respectively, for the case of ZrO_2) are introduced alternately instead of simultaneously as in a standard CVD process (see Sect. 4.6.1). This results in the layer-by-layer growth that creates the characteristics of ALD films, making them appropriate for several applications. In the case of Zr-based dielectrics, the material may consist of zirconium, aluminum, and oxygen.

In any case the ZrO_2 films are amorphous, and a very thin interfacial silicate layer (9-Å thick) exists at the silicon/ ZrO_2 interface. Post-deposition annealing in oxygen or inert gases (at 400-500°C) is found to be necessary to reduce the leakage current of deposited films. After high-temperature annealing, this layer grows and converts to a more stoichiometric SiO_2 layer. Significant SiO_2 growth is observed at the ZrO_2/Si interface annealed at 400-600°C even under low partial pressures of oxygen. Reaction with the Si substrate and the polysilicon gate also occurs at higher temperature ($\leq 1000^\circ\text{C}$) processing steps.

Films of zirconium silicate doped with aluminum (Zr-Al-Si-O) have also been studied as candidate high- k gate materials.⁴² It was noted that doping ZrO_2 films with Al improves the resultant ZrO_2 dielectric layer. That is, the undoped ZrO_2 films have high diffusivity of oxygen, and so oxygen can diffuse through the ZrO_2 during the post-deposition anneal and react with the underlying Si to form an SiO_2 interfacial layer. The addition of Al reduces the rate of oxygen diffusion through the ZrO_2 film. Another report described the use of yttria-stabilized ZrO_2 (YSZ) films as a high-dielectric constant layer in MOSFETs. The advantage of the YSZ film is that it can be epitaxially grown on a silicon substrate by pulsed laser ablation without the formation of an interfacial silicon oxide layer.⁴⁶

At the end of 2001, Intel announced that a new transistor structure that included a ZrO_2 gate dielectric layer, deposited by ALD. They stated that this new MOSFET structure would be used for devices built by Intel from 2005 and beyond.⁵⁵




Fig. 4-16 Atomic layer CVD growth mechanism of the high-*k* dielectric ZrO_2 from ZrCl_4 and H_2O . Courtesy of ASM International.

4.6.4 Hafnium Oxide (HfO_2) as a Gate Dielectric

Hafnium oxide (HfO_2) has been investigated as a high-*k* dielectric for MOSFET devices. Early reports described fabrication of MOSFETs with n^+ polysilicon gates,³² and more recent ones have discussed the characteristics of MOSFETs with p^+ polysilicon gates as well.³³ Hafnium oxide exhibits excellent materials properties for these applications, namely: a high dielectric constant ($k = 24 - 40$); good thermal stability when in contact with silicon; and an energy gap of 5.65 eV. (Hf forms the most stable oxide with the highest heat of formation [$\Delta H_f = 271$ Kcal/mol] among the elements in the IVA group of the periodic table [Ti, Zr, Hf].) In addition, HfO_2 is very resistive to impurity diffusion and intermixing at the silicon/dielectric interface because of its high density (9.68 g/cm^3).³⁹

The HfO_2 films described in the reports were deposited either by PVD (reactive sputtering),^{32,33} or by *in situ* RTCVD.³⁴ MOS capacitors were fabricated with an equivalent oxide thickness (EOT) of 12-Å (and a physical thickness of 38-Å) by optimizing the polysilicon deposition process and the subsequent annealing steps that would be used to activate the MOSFET source/drain implants. That is, no interfacial layer was found to be formed between the HfO_2 and the polysilicon gates if the polysilicon deposition temperature was kept below 600°C , and the RTA anneals were carried out at 1000°C . However, the same report indicated that an unwanted interfacial SiO_2 layer IL does form between the HfO_2 and the silicon substrate during the HfO_2 deposition (Fig. 4-17). In addition, some crystallization of the HfO_2 is observed to occur during the RTA anneal steps. A more recent study claims that HfO_2




Fig. 4-17 HR-TEM showing HfO_2 ($\sim 38\text{\AA}$) and IL ($\sim 6\text{\AA}$): (a) after PDA, and (b) and (c) RTA 900°C and 1000°C for 1 min, respectively.³³ (© 2000 IEEE).

exhibits more thermal stability than does ZrO_2 .⁵¹ Two other papers published at the same time also states that better MOSFETs were fabricated with HfO_2 than with ZrO_2 as the gate dielectric.^{52,53}

The leakage current characteristics of such MOS capacitors was about four orders of magnitude smaller than a MOS capacitor fabricated with SiO_2 having the same $12\text{-\AA}$ EOT (as a result of the HfO_2 layer having a physical thickness more than double that of the SiO_2 layer). However, like other high- k dielectrics, the HfO_2 films also tend to trap electrons and thus degrade carrier mobility in the MOSFET channel. In another report, scalability of the EOT of the HfO_2 layer to less than $10\text{-\AA}$ was demonstrated by using a TaN gate electrode to replace the polysilicon gate electrode.³⁵ That is, the polysilicon-depletion effect is avoided if a TaN gate electrode is used instead of polysilicon, and therefore an EOT as small as $8\text{-\AA}$ can be obtained.

A recent study was published on the use of HfSiON as a high- k gate dielectric. This is an amorphous material and exhibits smaller leakage currents than does silicon dioxide at equivalent oxide thicknesses. HfSiON films scaled below $13\text{-\AA}$ showed good reliability performance.

4.6.5 Praseodymium Oxide (Pr_2O_3) as a High- k Gate Dielectric

Another exotic material that has been studied as a high- k gate dielectric is *praseodymium oxide* (Pr_2O_3).³⁶ The key advantage that is exhibited by MOS capacitors made with Pr_2O_3 layers is that they exhibit ultra-low leakage current densities. That is, leakage currents of 5 nA/cm^2 at 1V have been demonstrated for Pr_2O_3 layers with EOT of $14\text{-\AA}$. This is four orders of magnitude lower than the best reported results for other high- k materials. Such Pr_2O_3 films also exhibit an effective dielectric constant of 31. In addition, no significant hysteresis is

observed in the C-V measurements, provided the material is furnace annealed only briefly at 600°C. These layers can also survive an RTA anneal of up to 1000°C for up to 15 seconds with no degradation in electrical properties.

The Pr₂O₃ layers are polycrystalline. Ordinarily, the dielectric layers of MOS capacitors have an amorphous structure, and if the structure begins to become polycrystalline, the films become leaky. High-temperature post-deposition anneals tend to crystallize the dielectric films, and this can cause an increase in the leakage currents through other dielectric layers. Apparently this is not the case with Pr₂O₃. It should be noted, however, that although it is possible to deposit polysilicon films on these layers, the poly/Pr₂O₃ interface is rough. (In this work, instead of using polysilicon as the top electrode, a top electrode to the Pr₂O₃ was formed by evaporating gold onto the Pr₂O₃ through a shadow mask.)

The Pr₂O₃ layers in this study were deposited by molecular beam epitaxy (MBE) at temperatures between 625 and 725°C at a growth rate of 0.1-Å/sec. They were then subsequently furnace-annealed at 600°C for 5 minutes in dry nitrogen. A 1000°C/15 sec RTA anneal in N₂ was shown to cause no structural change in the films, and no change in their electrical properties.

REFERENCES

1. *International Technology Roadmap for Semiconductors*, 1999 Edition, Semiconductor Industry Association, San Jose, CA.
2. G. Lucovsky, "Integration of Alternative High-*k* Gate Dielectric Aggressively-Scaled CMOS Si Devices: Chemical Bonding Constraints at Si-Dielectric Interfaces," *Mtg. Abs. Electrochem. Soc.*, Spring 1999, Abs. 495.
3. H. Shimada and T. Ohmi, "Current Drive Enhancement by Using High-Permittivity Gate Insulator in SOI MOSFETs and Its Limitation," *IEEE Trans. Electron Dev.*, **43**, p. 431 (1996).
4. S.C. Song *et al.*, "Ultra-Thin (<2 nm) CVD Si₃N₄-Gate Dielectric for Deep-Sub-Micron CMOS Devices," *Tech. Dig. IEDM*, 1998, p. 373.
5. T. Devoivre *et al.*, *Proc. 1998 IEEE/SEMI Advanced Semiconductor Manufacturing Conference*, p. 434 (1998).
6. Y. Momiyama *et al.*, "Ultra-Thin Ta₂O₅/SiO₂ Gate Insulator with TiN Gate Technology for 0.1 μm MOSFETs," *Digest of Symp. VLSI Technology*, p. 135, 1997.
7. D. Park *et al.*, "SiON/Ta₂O₅/TiN Gate-Stack Transistor with 1.8-nm-Equivalent SiO₂ Thickness," *Tech. Dig. IEDM*, 1998 p. 381.

8. C. Hoover, "Metal Electrode Challenges with the Emergence of High Permittivity Dielectric Materials," *Mtg. Abs. Electrochem. Soc.*, Spring 2000, Abs. 251.
9. C.V. Srividya *et al.*, "MOCVD Processing of Pt Films for High-*k* Bottom-Electrode Applications," *Mtg. Abs. Electrochem. Soc.*, Spring 2000, Abs. 253.
10. S. Kamiyama *et al.*, "Highly Reliable 2.5-nm Ta₂O₅ Capacitor Process Technology for 256 MBit DRAMs," *Tech. Dig. IEDM*, 1991, p. 827.
11. K.S. Tang *et al.*, "Trends in DRAM Dielectrics," *IEEE Circuits and Devices Mag.*, May 1997, p. 29.
12. M.G.-L. Tai *et al.*, "Thermal stability of Ta₂O₅ Films in Capacitor Systems Using a TiN Metal Electrode," *Mtg. Abs. Electrochem. Soc.*, Spring 2000, Abs. 254.
13. J.-W. Kim *et al.*, "Development of Ru/Ta₂O₅/Ru Capacitor Technology for Giga-Scale DRAMs," *Tech. Dig. IEDM*, 1999, p. 793.
14. Y. Takaishi *et al.*, "Low-Temperature Integrated Process Below 500°C for Thin Ta₂O₅ Capacitor for Giga-Bit DRAMs," *Tech. Dig. IEDM*, 1994, p. 839.
15. I. Asano *et al.*, "1.5-nm-Equivalent-Thickness Ta₂O₅ High-*k* Dielectric with Rugged Si Suited for Mass Production of High Density DRAMs," *Tech. Dig. IEDM*, 1998, p. 755.
16. Y.S. Kim *et al.*, "The Influence of Surface Roughness on the Electric Conduction Process in Amorphous Ta₂O₅ Thin Films," *J. Electrochem. Soc.*, September 1999, p. 3398.
17. P.C. Joshi and M.W. Cole, "Enhanced Electrical Properties of Al-Doped Ta₂O₅ Thin Films for Microelectronic Applications," *Mtg. Abs. Electrochem. Soc.*, Fall 2000, Abs. 812.
18. Y. Kuo, "Reactive Ion Etching of Sputter Deposited Tantalum Oxide and Its Etch Selectivity to Tantalum," *J. Electrochem. Soc.*, February 1992, p. 579.
19. K.-P. Lee *et al.*, "Inductively Coupled Plasma Etching of Ta₂O₅," *J. Electrochem. Soc.*, October 1999, p. 3794.
20. G. Bersuker *et al.*, "Experimental Observation of Ta₂O₅ Gate Dielectric Transistors," *Mtg. Abs. Electrochem. Soc.*, Spring 2000, Abs. 243.
21. Y. Momiyama *et al.*, "Ultra-Thin Ta₂O₅/SiO₂ Gate Insulator with TiN Gate Technology for 0.1 μm MOSFETs," *Dig. Symp. VLSI Tech.*, 1997, p. 135.
22. I.C. Kizilyalli *et al.*, "Stacked Gate Dielectrics with Ta₂O₅ for Future CMOS Technologies," *Dig. Symp. VLSI Tech.*, 1998, p. 216.
23. H.F. Luan *et al.*, "Ultra-Thin High-Quality Gate Ta₂O₅ Dielectric Prepared by *In-Situ* Rapid Thermal Processing," *Tech. Dig. IEDM*, 1998, p. 609.
24. *ibid.*, Ref. 7.
25. G.F. Derbenwick and A.F. Isaacson, "Ferroelectric Memory: On the Verge of Breakthrough," *IEEE Circuits & Device Magazine*, January 2001, p. 20.

26. V. Sivaramakrishnan *et al.*, "High-*k* Dielectrics for Advanced DRAM Applications," *Semiconductor Fabtech*, 12th edition, 2000, p. 217.
27. K.W. Kwon *et al.*, "Ta₂O₅ Capacitors for 1 Gbit DRAM and Beyond," *Tech. Dig. IEDM*, 1994, p. 835.
28. C. Kittel, *Introduction to Solid State Physics, Sixth Edition*, John Wiley & Sons, New York, 1986.
29. F. Jona and G. Shirane, *Ferroelectric Crystals*, Dover Publications, 1993 and references cited therein.
30. R.B. Laibowitz *et al.*, *American Physical Soc. Meeting*, Abs. R28.05 (1996).
31. I.C. Kizilyalli, R.C. Huang, and P.K. Roy, "MOS Transistors with Stacked SiO₂-Ta₂O₅-SiO₂ Gate Dielectrics for Giga-Scale Integration of CMOS Technologies," *IEEE Electron Device Letts.*, November 1998, p. 423.
32. L. Kang *et al.*, "Single-Layer Thin HfO₂ Gate Dielectric with *n*⁺ Polysilicon Gate," *Dig. Symp. VLSI Tech.*, 2000, p. 44.
33. L. Kang *et al.*, "MOSFET Devices with Polysilicon on Single-Layer HfO₂ High-*k* Dielectrics," *Tech. Dig. IEDM*, 2000, p. 35.
34. S.J. Lee *et al.*, "High Quality Ultra Thin CVD HfO₂ Gate Stack with Poly-Si Gate Electrode," *Tech. Dig. IEDM*, 2000, p. 31.
35. B.H. Lee *et al.*, "Characteristics of TaN Gate MOSFET with Ultrathin HfO₂ (8-12Å)," *Tech. Dig. IEDM*, 2000, p. 39.
36. H.J. Osten *et al.*, "High-*k* Dielectrics with Ultra-Low Leakage Current Based on Praseodymium Oxide," *Tech. Dig. IEDM*, 2000, p. 653.
37. D.A. Buchanan *et al.*, "80 nm Poly-silicon Gated *n*-FETs with Ultra-Thin Al₂O₃ Gate Dielectric for ULSI Applications," *Tech. Dig. IEDM*, 2000, p. 223.
38. J.H. Lee *et al.*, "Effect of Polysilicon Gate on Flatband Voltage Shift & Mobility Degradation for ALD- Al₂O₃ Gate Dielectric," *Tech. Dig. IEDM*, 2000, p. 645.
39. B.H. Lee *et al.*, "Ultrathin Hafnium Oxide with Low Leakage & Excellent Reliability for Alternative Gate Dielectric Application," *Tech. Dig. IEDM*, 1999, p. 133.
40. W.-J. Qi *et al.*, "MOSCAP and MOSFET Characteristics Using ZrO₂ Gate Dielectric Deposited Directly on Si," *Tech. Dig. IEDM* 1999, p. 145.
41. Y. Ma *et al.*, "Zirconium Oxide Based Gate Dielectrics with Equivalent Oxide Thickness of Less Than 1.0 nm and Performance of Submicron MOSFETs using a Nitride Gate Replacement Process," *Tech. Dig. IEDM* 1999, p. 149.
42. L. Manchanda *et al.*, "Si-Doped Aluminates for High Temperature Metal-Gate CMOS: Zr-Al-Si-O, A Novel Gate Dielectric for Low Power Applications," *Tech. Dig. IEDM*, 2000, p. 23.
43. C.H. Lee *et al.*, "MOS Characteristics of Ultra Thin Rapid Thermal CVD ZrO₂ and Zr Silicate Gate Dielectrics," *Tech. Dig. IEDM*, 2000, p. 27.
44. K.J. Hubbard and D.G. Schlom, *J. Mater. Res.* 2757 (1996).

45. R. Nieh *et al.*, "Processing Effects and Electrical Evaluation of ZrO_2 Formed by RTP Oxidation of Zr," *Mtg. Abs. Electrochem. Soc.*, Spring 2000, Abs. 247.
46. B. Dance, "Alternative Gate Dielectric Material Shows Promise," *Semiconductor International*, May 2001, p. 58.
47. D. Kotecki, "High- k Dielectric Materials for DRAM Capacitors," *Semiconductor International* November 1996, p. 109.
48. K. On *et al.*, "(Ba,Sr) TiO_3 Capacitor Technology for Gbit-Scale DRAMs," *Tech. Dig. IEDM* 2000, p. 803.
49. A. Shanware *et al.*, "Reliability Evaluation of HfSiON Gate Dielectric Film with 12.8Å SiO_2 Equivalent Thickness," *Tech. Dig. IEDM* 2001, p. 137.
50. G.D. Wilk *et al.*, "High- k Dielectrics: current Status and Materials Properties Considerations," *J. Appl Phys. (Review)* **89** (2001) 5243.
51. E.P. Gusev *et al.*, "Ultrathin High- k Gate Stacks for Advanced CMOS Devices," *Tech. Dig. IEDM* 2001, p. 451.
52. Y. Kim *et al.*, "Conventional n -MOSFET Devices Using Single Layer HfO_2 and ZrO_2 as High- k Gate Dielectrics with Polysilicon Gate Electrode," *Tech. Dig. IEDM* 2001, p. 451.
53. C. Hobbs *et al.*, "80 nm Poly-Si Gate CMOS with HfO_2 Gate Dielectric," *Tech. Dig. IEDM* 2001, p. 651.
54. R. Wallace and G.D. Wilk, "Identifying the Most Promising High- k Gate Dielectrics," *Semiconductor International*, July 2001, p. 227.
55. R. Chau and G. Marcyk, "New Transistors for 2005 and Beyond – The TeraHertz Transistor," Intel Press Release, Nov. 26, 2001.

Chapter 5

THE STRUCTURE OF DEEP-SUBMICRON MOSFETS: Retrograde-Wells; Super-Steep Retrograde Channel Doping; Drain Engineering; Punchthrough-Control Structures

In Chapter 1 we discussed the evolution of MOSFET structures down to the sub-micron technology nodes in production at the time publication of this text. In this chapter we delve further into the details of the MOSFET regions that are fabricated in such deep-submicron MOSFETs, namely: **1)** retrograde wells for CMOS twin-well technology; **2)** super-steep retrograde (SSR) channel doping profiles; **3)** drain engineering issues in deep-submicron MOSFETs; and **4)** punchthrough-control structures.

5.1 WELL-FORMATION IN DEEP-SUBMICRON CMOS

Twin-well CMOS is now the dominant CMOS technology in IC production. In twin-well CMOS each well is formed separately by implanting the well dopants into a lightly doped substrate region. Having two well implants allows each well-type to be tailored separately, permitting independent device performance adjustments for both PMOS and NMOS transistors. When first introduced, twin-well CMOS structures were fabricated by using moderate-energy implants to place both types of well dopant near the wafer surface. These dopants then had to be driven into the substrate by a long (12-24 hour), high-temperature ($>1100^{\circ}\text{C}$) diffusion process (Fig. 5-1). Such a deep drive-in step was needed to prevent punchthrough from the MOSFET drain regions at the surface to the substrate under the well. This type of CMOS-well-structure is referred to as a *diffused-well*. However, use of diffused-well structures gives rise to some problems which limits their use when CMOS is scaled below $0.5\ \mu\text{m}$:

1. Lateral (as well as vertical) diffusion occurs during the diffusion step, which has the effect of reducing packing density. For example, since the lateral diffusion is ~ 0.7 times the junction depth, a typical diffused well having a vertical junction depth of $3\text{-}4\text{-}\mu\text{m}$, results in a lateral spread of well dopant of $2\text{-}3\text{-}\mu\text{m}$. Consequently, the maximum aspect ratio of a diffused well is limited to about 1.6:1 (i.e., wells narrower than about 1.6 times their depth would intermingle with the dopant of adjacent wells).

2. If LOCOS isolation is used, boron from the *p*-well-dopant implant-step segregates into the oxide during the long, high-temperature field-oxide growth step. Compensating for this effect requires a separate field-threshold-adjust implant (also referred to as a *channel-stop-implant*), prior to the field-oxidation step. This additional step adds process complexity.
3. Diffusion of the channel-stop-implant dopant into the active regions during field oxidation adversely affects both the junction-capacitance and the turn-off characteristics of the NMOSFETs (see Vol. 3).
4. The lengthy, high-temperature drive-in-step increases process cycle time, and increases the risk of silicon wafer warpage, bow, and flatness degradation (and the likelihood of metal contamination from furnace heating elements).
5. The diffused-well profile for a particular technology node is the net result of compromises between the need to control threshold-voltage, to suppress hot-carrier effects, to control punchthrough and soft-error effects, and to provide latch-up immunity. For example, a high dopant concentration is desirable deep in the well to strengthen latch-up immunity. This cannot be achieved in a diffused-well because doping at the bottom of such a well must be lower than at the surface, and the maximum surface doping is set by limits on junction breakdown voltage and junction capacitance.

For all of the above reasons, the diffused-well approach to forming a twin-well CMOS process becomes less effective for each smaller technology node. As a result, an alternative method of forming the wells was sought. The technique adopted to replace the older diffused-well structure when CMOS technologies are scaled below about 0.5- μm involves *retrograde-well formation with high-energy ion-implant steps*.

5.1.1 Retrograde-Wells for Deep-Submicron CMOS

The medium-energy implant steps used to introduce well-dopants into the substrate in the diffused-well approach (50-100-keV), can be replaced with high-energy-implant steps (300-keV to 1-Mev). Such high-energy implants cause the peak of the implant to be located considerably deeper within the silicon substrate (at roughly 1- μm for the energies most frequently used in high-energy implant processes). Since the implant peak is now far beneath the silicon surface, the impurity concentration thus decreases as the doping profile approaches the wafer surface. Since the well-profile in this case is different from that of a conventional




Fig. 5-1 Doping profile in a conventional well formed by a shallow implant and drive-in step. diffused well (in which the doping concentration after drive-in is highest at the surface, and decreases monotonically with depth, as seen in Fig. 5-1), such deeply implanted wells are known as *retrograde-wells*.^{*} Comparison of the doping profiles in conventional and implanted *p*-well profiles (obtained by simulation) is shown in Fig. 5-2.^{2,3} The retrograde-doping-profile is retained by minimizing the temperature-cycles of later process steps (e.g., by using RTP instead of furnace anneals).

The retrograde-well approach to forming the twin-well CMOS-structure has several major advantages over the diffused-well process:

1. Much less lateral-dopant-spread occurs for a retrograde-well having the same junction depth as a diffused-well. This is because ion implantation is a more anisotropic dopant-distribution process than diffusion (i.e., the lateral-straggle for implant energies of 500-keV is only $\sim 0.7\text{-}\mu\text{m}$). In addition, little additional diffusion occurs after the implant is performed, since only a short anneal at a relatively low-temperature is needed to activate the implant. Thus, the total lateral-dopant-spread barely exceeds $1\text{-}\mu\text{m}$ after all thermal processing (compared to at least $2\text{-}\mu\text{m}$ for the same well-depth using a diffused-well process).² Figure 5-3 depicts the doping concentration profile of a high-energy implanted *p*-well. In this example, the implanted *p*-well is formed by boron implantation at 400-keV.

In addition, high-energy implanters can place dopant beneath a shallow-

^{*} In order to avoid excessive spread of the active-device electrical parameters, the surface concentration after the retrograde implant should be at least five times smaller than its final value - which will be set by subsequently performed, shallower low-dose implants specifically designed for threshold and punchthrough control.

trench-isolation oxide or a LOCOS field oxide, allowing the CMOS twin-well structure to be implanted *after* the dielectric isolation features are formed. (In diffused-wells, the well-dopants must be implanted before the field-oxide, and driven-in either before - or during - the field-oxidation step). Thus, since the high-energy implanted wells are formed after the long, high-temperature cycle needed to grow the LOCOS field-oxide, lateral-spread of the well-dopants is further reduced. (A higher threshold voltage can also be achieved in the LOCOS field-regions of the p -wells if the boron implant is done following field-oxidation, because the boron does not segregate out into the oxide during the field-oxide growth-step.¹⁾ Hence, the $7\text{-}9\text{-}\mu\text{m}$ n^+ -to- p^+ spacing required for a twin-well $1.2\text{-}\mu\text{m}$ CMOS process which uses conventional wells, can be reduced to $\sim 5\text{-}\mu\text{m}$ if retrograde wells are used instead. Such overall reduced lateral-dopant-diffusion permits higher circuit-packing-densities.

2. By combining the high-energy-implant step with the other lower-energy MOSFET channel implants (V_T -adjust and punchthrough stopper) and since minimal thermal diffusion occurs, control of dopant levels throughout the depth of the well becomes possible with fewer tradeoffs (a task that has been dubbed "Well Engineering"). This permits optimization of such key




Fig. 5-2 Simulated doping profiles in PMOS channel regions: dashed lines, lightly doped substrate; solid lines, retrograde n -well.³ (© 1982 IEEE).




Fig. 5-3 Example of the doping profile of a retrograde *p*-well (boron) implant (400 keV).

MOSFET performance characteristics as: device speed (carrier mobility and, S/D capacitance), inter-device leakage-currents, V_T -control, punch-through suppression, parasitic-transistor effects, and soft-error and latch-up resistance. That is, low surface-doping levels increase mobility and decrease capacitance. Heavier doping below the surface (retrograde doping) suppresses minority carrier collection by decreasing depletion widths; thus reducing soft errors and latchup susceptibility. This degree of flexibility in optimizing device parameters is not possible with diffused-wells.

Besides the primary benefits of increased packing-density and greater process flexibility, retrograde-wells offer the following secondary advantages:⁵

1. A retarded electric field is created in the parasitic-vertical-bipolar-transistor, thereby reducing its current gain. This affords some extra protection against latchup.
2. Susceptibility to vertical-punchthrough is reduced without having to significantly raise the surface-doping-concentration.
3. The conductivity in the bottom of the well is increased, which also provides additional resistance against latchup.
4. The shallower well depth should also make the drain of the parasitic n^+ -to- n -well (or p^+ -to- p -well) parasitic-FETs shallower. This contributes to improvements in both the short-channel threshold-roll-off-effect and the in the punchthrough characteristics of these parasitic field-region devices (see Vol. 3, Chap. 6).

5. The formation of retrograde-wells with high-energy implants results in a reduced-doping-concentration under the bottom of the source and drain regions, which reduces the source/drain-to-body junction-capacitance.

However, some concerns associated with the retrograde process should also be mentioned. First, the process requires a thick photoresist as a masking material for the high-energy implant. Typical resist thicknesses are 2.0-2.5- μm , and special exposure and development techniques are required for this process. Implant shadowing arising from the use of such thick resists must also be addressed. (We will address the challenges associated with the use of thick resists as high-energy-implant masks in more detail at the end of this section.) Questions have also been raised about the possibility that the high-energy implants could cause damage that may degrade device and circuit performance.

5.1.2 Process Integration Issues Involving the Use of Retrograde Wells

Advanced twin-well CMOS processes with both retrograde *n*- and *p*-wells (using short [~ 5 min] RTP well-drive-in steps), were reported for submicron applications as early as 1991.⁶ Further advances continued throughout the decade. Scaling CMOS to 0.5- μm and below reduces the well depths required to prevent vertical punchthrough and latchup. In turn, as device and isolation dimensions shrink with each device node, retrograde-well implant-energies for both DRAM and logic circuits are also gradually being reduced. However, the retrograde-well implants used for DRAM devices typically require higher doses than those used in logic devices (i.e., to achieve better minority-carrier suppression [soft-error rate]). This, in turn, requires a higher well-implant-energy (to avoid excessive dopant in the near-surface [channel] region). In addition, the well-depth and well-dopant-concentration can be reduced if additional, lower-energy implants are precisely located with respect to the transistor structure (to suppress punch-through of the MOSFET channels and enhance the field-isolation characteristics).

The high-energy implant step used to form retrograde-wells in deep-submicron-CMOS is typically performed together with the V_T -adjust, punchthrough, and channel stop (isolation) implants. These implants are all done in the same implanter, without removing the wafers from the implant process chamber in between (unless channel engineering implants [that use high wafer-tilt-angle for precision dopant placement] are required - see Sect. 5.4). Such a “chained” implant sequence is performed by doing the highest-energy implant first, with the lowest-energy implant being done last. This ensures that no ions traverse the end-of-range (EOR) damage of a previous implant. Note that because

of economic requirements for high equipment utilization, this sequence must be carried out in an implanter that has the capability of doing not only high-energy implants (e.g., up to about 1-MeV for the retrograde n -well implant), but also lower-energy boron implants (down to about 10-keV, for the NMOS V_T -adjust implant).

An example of a "chained implant" retrograde twin-well CMOS process is given in Ref. 7. Here, a retrograde n -well is formed by a 600-keV, $3 \times 10^{13} \text{ cm}^{-2}$ phosphorus implant. Then, a second phosphorus implant (150-keV, $4 \times 10^{12} \text{ cm}^{-2}$) is used to obtain both punchthrough prevention and intra-field isolation (channel stop), and a third phosphorus implant (70-keV, $6 \times 10^{12} \text{ cm}^{-2}$) sets the threshold voltage. In an identical manner, three selective boron implants are placed in the p -well region. The retrograde p -well implant is boron at 300-keV, $3 \times 10^{13} \text{ cm}^{-2}$. Then a punchthrough/channel-stop-implant at 150-keV, $4 \times 10^{12} \text{ cm}^{-2}$ and a threshold-adjust-implant at 30-keV, $5.5 \times 10^{12} \text{ cm}^{-2}$ are added. The process displays very good inter-well isolation characteristics, which allows a minimum p^+ -to- n^+ spacing 40% lower than the same process without retrograde wells. It also achieves very good intra-well isolation, allowing n^+ -to- n^+ (and p^+ -to- p^+) device separation of 0.5- μm , without an additional channel-stop implant.

From a manufacturing perspective, the well-formation sequence thus appears to be a single implant step, reducing manufacturing complexity and cost. Figure 5-4 compares an advanced diffused-well process with a high-energy implanted process up to gate oxidation, showing the process simplification possible with "well-engineering." Eliminating process steps has other benefits besides reducing cycle time. These include a reduction in work-in-progress (WIP) inventory, less wafer handling, and fewer defects.

The cycle-time and cost savings obtained from such a "chained-implant" sequence was assessed by SEMATECH. They sponsored a comparison of a baseline diffused-well process with a high-energy retrograde-well process at two different chip manufacturers. The high-energy processes were engineered to achieve minimum cycle-time and maximum cost savings, while maintaining the same basic device and circuit parametric data (and thus were identical to the baseline processes after gate-oxidation). Significant improvements in cycle-time, cost, and device-performance were achieved by both companies.

By chaining these implants, the doping-profile in the well-regions of the MOSFETs has a *modulated* characteristic as depicted in Fig. 5-5 (where the term "modulated" means that the doping-concentration-profile has several maxima and minima).⁷ The incorporation of such multiple implants to form a modulated well has become a firmly established processing approach in chip production.




Fig. 5-4 Fabrication sequences for: a) conventional-diffused-well and; b) high-energy-implanted-well processes.

Another issue of using high-energy implants to introduce the well and isolation dopants involves implant shadowing. That is, as shown in Fig. 5-6a, thick photoresist films must be used as masks against the high-energy implant (e.g., 2.0-2.5 μm thick). The doping asymmetry resulting from high energy implants with a small (7°) tilt angle can have significant effects on retrograde well structures and inter-well isolation. Figure 5-7 depicts the simulated doping profiles from a 1 MeV phosphorus implant with a 7° tilt.⁸ The simulation accounted for the fact that opposite corners of the photoresist will wear down and carbonize differently because of the asymmetry in the incoming ion beam. As the sidewall shape of the photoresist changes with time, this will affect the implanted profile in the silicon. The doping profiles in Fig. 5-7 clearly show a bulge of lightly doped material on the shadow side of the profile. More seriously, on the




Fig. 5-5 Modulated n -well structure for advanced devices, showing the functions of each implant.⁷

incoming side, a channel doped to 20% of the peak-concentration extends from the projected range up to the surface. Doping variations such as these can adversely affect the mobilities and junction-capacitances of the resulting devices. This will also make it harder to maintain adequate isolation structures as isolation widths scale below 400-nm. These problems can be mitigated by reducing the tilt-angle to the 2-4° range, using 0°-tilt. However, using 0°-tilt-implants is not always possible, due to channeling effects (which are severe at high energies).

An alternative solution to the implant shadowing problem during high-energy




Fig. 5-6 The geometric effects of ion implantation into a narrow active region: a) low-tilt-angle shadowing and well misalignment; b) low-tilt quad implant provides both lateral and vertical (no channeling) uniformity.




Fig. 5-7 Normalized doping profile of 1 MeV phosphorus implantation. a) On the shadow side (a) a lowly doped bulge is found (according to Monte Carlo simulation). b) On the incoming side, Monte Carlo simulation shows a trunk.⁸

7°-tilt implants is to reposition the wafers part-way through the implant process. If the wafers are repositioned four times, and 25% of the total dose is implanted with the wafer in each position (*quad implant*), all the areas of the exposed silicon surface will receive the same implant dose, eliminating the implant-shadowing problem (Fig. 5-6b). That is, well profiles are symmetric, both laterally and vertically, and shadowing effects near the surface are compensated.

A high-energy batch-implanter capable of performing low-tilt quad-implants without unloading the wafers from the disk addresses the isolation scaling problem with high productivity. Since it is not practical to scan a high-energy ion beam, implanters with fixed beams and batch end-stations using simultaneous disk spinning and scanning is the method-of-choice for process uniformity. The




Fig. 5-8 *In situ* quad implants can be run on a batch end-station with orthogonal tilt axes (designated α and β).

quad-implant capability is achieved with a disk chamber as shown in Fig. 5-8.⁹ Here the disk can be independently tilted in two orthogonal directions. Such batch high-energy implanters are sold by Axcelis Corp. Single-wafer high-energy implanters are also commercially available. A model offered by Applied Materials also permits tilting the wafer and repositioning it several times during an implant step. Higher tilt-angle control is claimed for such single-wafer high-energy implanters compared to the batch types.¹⁰

5.2 SUPERSTEEP RETROGRADE (SSR) CHANNEL DOPING PROFILES

The appropriate choice of substrate doping and engineering of doped layers under the gate are critical to optimum performance of deep-submicron MOSFETs (with respect to drain-to-source punchthrough, threshold voltage, and channel mobility). Specifically, the doping-density in the region between the source and drain must increase as the gate-length is reduced to prevent punchthrough. As shown in Fig. 5-9, the mean channel-doping-density needed to control punchthrough when gate lengths scale below about $0.13\text{-}\mu\text{m}$ begins to exceed $5 \times 10^{17}/\text{cm}^3$. However, to avoid reduction of carrier mobility in the channel, the doping at the surface must be kept below $5 \times 10^{17}/\text{cm}^3$ to obtain the universal mobility curve.¹¹ To allow the surface concentration to be kept below this value, and still have a mean doping concentration in the channel above this number, a vertical *retrograde doping concentration profile* is needed in the channel region.




Fig. 5-9 Doping density required for punchthrough control.¹¹

Assume that a lighter doped surface layer with a concentration of $1 \times 10^{17}/\text{cm}^3$ exists down to a depth X_1 (taken to be approximately $1/2$ of the source/drain junction depth X_j), and that at that depth the doping abruptly changes to the value needed for the heavily doped punchthrough-control layer. Figure 5-10 shows the scaling required for X_1 at each technology generation. Because the transition in doping concentration from the lighter doped region near the surface to the heavily doped punchthrough-control region below must occur over such a short distance, the gradient in the doping concentration must be very steep. Hence, such a doping concentration profile is termed a *super-steep retrograde* (SSR) profile.




Fig. 5-10 Typical thickness of lighter-doped layer and total number of impurity atoms for $10^{17}/\text{cm}^3$ surface doping density.¹¹

The formation of SSR channel-doping-profiles for technology nodes from $0.18\text{-}\mu\text{m}$ down to about $0.1\text{-}\mu\text{m}$ is done using ion implantation (in place of the conventional V_T -adjust implant step). In these implant processes, however, higher-mass dopants are substituted for the dopants typically used to carry out the V_T -adjust implants. That is, indium (In) is used instead of boron (B) for the NMOS devices, and either arsenic (As) or antimony (Sb) replace phosphorus (P) in PMOS devices. Heavier implant species provide steeper as-implanted profiles (due to their smaller straggle), and the heavier ions have reduced diffusivity (keeping the as-implanted profile from spreading out during subsequent thermal processes). Thus, well-profiles implanted with In and As (using implant energies in the 100-200-keV range) can be fabricated with sufficiently low doping ($\sim 5 \times 10^{16}/\text{cm}^3$) at the gate-oxide interface, and a higher peak doping level ($\sim 1 \times 10^{18}/\text{cm}^3$) 80-nm below the gate oxide. (Note that peak doping concentrations of indium cannot be made higher than about $10^{18}/\text{cm}^3$ because of the solubility limit of indium atoms in silicon.)

Figure 5-11a shows indium doping-profiles for various annealing temperatures, up to 1000°C .¹² It is evident that little change occurs in the as-implanted indium doping profile for annealing temperatures up to 1000°C , making it a promising candidate for forming SSR channel-doping-profiles. Indium implants for retrograde-channels in NMOSFETs have been reported in some cases to *improve* subthreshold-slopes relative to conventional boron implanted-channels,^{12,13} while in another case it was found to have *degraded* the subthreshold-slope.¹⁴ It is generally agreed that SSR doping-profiles are effective at reducing short-channel-effects and drain-induced-barrier-lowering, but it is not equally certain whether this translates into overall improvement in device performance (as this also depends on many other variables, including gate-oxide-thickness, gate-length, and junction-doping). Figures 5-11b and 11c, respectively, show the vertical concentration-doping-profile for an SSR and a conventional process for PMOSFETs (Sb for SSR, and P for the conventional process), and NMOSFETs (indium for SSR, and boron for the conventional process).¹⁵

The use of SSR channel-doping-profiles is entering some mainstream process flows, despite disagreements over their advantages compared to conventional channel-profiles. In late 1999, the successful fabrication of 100-nm-gate-length devices was reported. They were built using SSR channel-profiles, source/drain-extensions, and deep source/drain-regions for contact. A 100-nm-process yielded devices with $1.04\text{-mA}/\mu\text{m}$ (NMOS) and $0.46\text{-mA}/\mu\text{m}$ (PMOS) on-currents at 1.5 V with $3\text{-nA}/\mu\text{m}$ off-current. This process uses indium and arsenic as the implant




Fig. 5-11 a) SIMS data of indium profiles over a large range of annealing temperatures. Conventional and retrograde doping profiles (simulated) for b) NMOS and c) PMOS.¹²

species for the SSR-channel-doping-profiles, low-energy boron and arsenic source/drain-extensions, and high-angle pocket-implants.¹⁶

The source for indium ions in implant processes is InCl_3 , a solid material at room temperature. The production of ion beams from solid InCl_3 presents some special challenges for ion implanters. First, InCl_3 is hygroscopic (i.e., it readily absorbs moisture), and thus may require excessive outgassing if not handled properly outside of the ion-source vaporiser. In addition, although InCl_3 is a solid, it has a low melting-point. Thus, indirect heating from a second vaporiser in the ion-source may cause unintentional vaporization. Both of these effects can lead to premature loss of the source charge, as well as the problem of indium

coating in and around the source area. Finally, even during normal operation, indium tends to drift down the beamline, covering the beamline components. This creates a risk of cross-contamination, since the indium atoms can be dislodged from these surfaces if they are struck by ion beams of other species.

Two ion-implanter features can adequately suppress such effects. First, active cooling in the source eliminates indirect heating, decreasing indium-loss and excess beamline-coating. Second, an electrostatic (or other) filtering element near the end-station greatly reduces the magnitude of such cross-contamination, allowing all species to be run on a single implanter. The latest generations of single-wafer, medium-current-implanters incorporate such features.¹⁷

5.2.1 Fabricating SSR Profiles for Sub-0.1 μm MOSFETs

When gate-lengths scale below 0.1- μm , it probably will no longer be possible to create SSR channel-doping-profiles using ion implantation (even if In and As are used as the implanted species). For example, if a lightly-doped surface-layer is established for a 50-nm-generation MOSFET (with a doping concentration of $1 \times 10^{17}/\text{cm}^3$), the heavily-doped punchthrough-control layer ($10^{19}/\text{cm}^3$) will have begun at a depth of just 7-nm beneath the silicon surface. Since the width of the surface-inversion-layer is typically thinner than 7-nm, the channel electrons will still be located primarily in the lightly-doped surface-region. However, thin surface-layers with such an abrupt doping-concentration-increase cannot be fabricated with ion implantation (and its ancillary annealing processes). Other doping techniques, such as low-temperature selective-epitaxy (of perhaps Si-Ge layers¹⁹) will likely be needed for 50-nm and beyond MOSFETs.*

5.3 SOURCE/DRAIN ENGINEERING IN DEEP-SUBMICRON CMOS

In deep-submicron MOSFETs, the typical source/drain contact-structures consist of two regions: **1)** A shallow source/drain-extension-region (SDE), with a junction-depth X_j ; and **2)** A deeper contact-source/drain-region, with a junction-depth X_{jc} . As also described in Chap. 1, when MOSFETs were first designed with such two-region source/drain-structures, the first-region had lighter doping than the second-region (and it was in fact called a *lightly-doped drain (LDD)* re-

* Figure 5-10 also shows a graph of N_T (the total number of impurity atoms in the lightly doped layer) versus technology generation. For 50-nm and below, this value approaches a small number (< 10), so that for cases where the doping density is important to device operation, any device parameter depending strongly on N_T will show large statistical fluctuations from device-to-device. If all parameters depend only very weakly on N_T then the layer may as well be undoped,¹⁸ so that V_T -control relates to the positioning of the step (i.e., the increase in doping) and the doping in the heavily doped layer.

gion. This region was added to the single-region MOSFET drain-structures at about the time when MOSFETs were scaled below $1.5\text{-}\mu\text{m}$. Its function was to reduce the peak electric-field (and thus hot-electron-injection) near the drain-end of the channel. However, as MOSFETs gate-lengths were scaled to the deep-submicron regime, the power-supply voltages also had to be reduced, and this resulted in a significant decrease in the peak electric-field near the drain. Hence, the LDD region was no longer needed to suppress hot-carrier-injection effects.

However, in deep-submicron MOSFETs the SDE-region remains a part of the drain structure. But, its role now is to reduce short-channel-effects. The drain contact-region is required to accommodate the thickness of the salicide contact-layer and minimize junction-leakage. Nevertheless, the junction depth X_{jC} of the contact-region should not be larger than that needed to meet these conditions. That is, the greater the junction-depth, the larger must be the width of the sidewall-spacer. This, in turn, will result in a longer SDE-region (which increases the value of the parasitic SDE-resistance, R_{SDE}). In Sect 5.3.1.3, we will see that to enable a MOSFET to deliver improved performance as the gate length is scaled, it is critical that the source/drain contact design should minimize both the parasitic series-resistance-effects and the salicide-substrate contact-resistance. In addition, to ensure that short-channel-effects are effectively controlled as the MOSFET is scaled, both X_j and X_{jC} will also have to appropriately scaled.

Figure 5-12 shows the depths of the source/drain-region junctions and undoped channel-region as MOSFETs are scaled below 200-nm (where L_L is the lithographically-drawn gate-length), as taken from the ITRS 1999 study.²⁰ The design rules used in ITRS 2001 to calculate these same values have been relaxed slightly from those in the 1999 study: 1) the source/drain-contact junction-depth is $1.1 L_L$ ($\pm 33\%$), compared to $0.8 L_L$; 2) the source/drain-extension junction-depth is $0.55 L_L$ ($\pm 25\%$), compared to $0.4 L_L$; and 3) the undoped region near the Si/gate-oxide interface in a super-steep retrograde doped channel (SSR) is $0.3 L_L$ ($\pm 25\%$), compared to $0.2 L_L$. Creating and maintaining these ultra-shallow junctions remains a fundamental challenge for doping and metrology techniques.

In this section we will discuss two subjects related to the formation of the source/drain-structure in deep-submicron MOSFETs, namely: 1) the issues involved in keeping the value of the resistance of the drain region R_S (which is the sum of the parasitic resistance components and contact resistance), to a value that is sufficiently low to meet the requirements of scaled-MOSFET device-design, and 2) the process technology needed to form shallow SDE-junctions.




Fig. 5-12 Source/drain junction and undoped-channel depths for planar CMOS on bulk-Si.

5.3.1 Resistance of Deep-Submicron Source/Drains

In the planar MOSFET, the device-region in which transistor-action occurs is the *channel* under the gate. The current coming from the metal-interconnect lines must flow from the metal-Si-contact to the edge of the channel through the source or drain regions (Fig. 5-13). In the MOSFET, current enters the contact perpendicular to the wafer-surface, and then travels parallel to the surface in order to reach the channel. The total parasitic series-resistance, R_S , of the current path from the contact to the edge of the channel of a single-region drain (i.e., one




Fig. 5-13 Schematic drawing showing: a) current paths within the source and drain regions, of a planar MOSFET and; b) their corresponding representative series resistance components.²¹ (© 1987 IEEE).

that does not have an LDD or a SDE) can be modeled by the sum of four components;²¹

$$R_S = R_{co} + R_{sh} + R_{sp} + R_{ac} \quad (5.1)$$

where R_{co} is the *contact resistance* between the metal and the source/drain region, R_{sh} is the *sheet resistance* of the bulk region of the source and drain, R_{sp} describes the *resistance of the current lines crowding near the channel end of the source*, and R_{ac} is the *accumulation-layer resistance*.

If the MOSFET drain has an SDE, the R_{sh} component of R_S can be replaced by R_{SDE} , as indicated in Fig. 5-14, so that R_S is now given by:

$$R_S = R_{co} + R_{SDE} + R_{sp} + R_{ac} \quad (5.2)$$

In any case, the value of R_S must be viewed from the perspective of how it affects the performance of a MOSFET. Specifically, its value must be compared to that of the channel-resistance R_{sat} of the MOSFET in its ON state:

$$R_{sat} = V_{DD}/I_{Dsat} \quad (5.3)$$

When the external resistance of the source + drain regions is equal to approximately 10% of the value of R_{sat} , the saturation-drain-current I_{Dsat} is reduced by about 8%. In most MOSFET design approaches, the goal is to keep I_{Dsat} from being reduced by no more than 10% due to such series-resistance of the source and drain regions. Thus, it is useful to analyze the components of R_S , so that it can be understood what factors can be adjusted to keep the value of R_S to the value which will meet the I_{Dsat} -degradation design goal.




Fig. 5-14 Schematic drawing of the components of source or drain resistance in a deep-submicron MOSFET.

For future scaling, the value of R_{sat} (actually $R_{\text{sat}}W$, normalized per unit device width) is given by:

$$R_{\text{sat}}W \cong V_{\text{DD}}t_{\text{ox}}/(0.47v_{\text{sat}}\epsilon_{\text{ox}} [V_{\text{DD}} - V_{\text{T}}]) \cong t_{\text{ox}}/(0.376v_{\text{sat}}\epsilon_{\text{ox}}) \quad (5.4)$$

Equation 5-4 indicates that since t_{ox} will continue to be made smaller as MOSFETs are scaled, the value of $R_{\text{sat}}W$ will also decrease as the devices are scaled. This implies that the value of R_{S} will also have to be made lower with each technology node. Before we examine in detail the implications of a decreasing R_{sat} (and therefore also a decreasing R_{S}), we first need to give a more thorough discussion of the physical meaning of the parasitic resistance components of the drain contact region, namely R_{ac} , R_{sp} , and R_{SDE} .

5.3.1.1 Physical Meaning of R_{ac} , R_{sp} , and R_{SDE} : Let us discuss the physical origins of the three parasitic resistance components of the drain/source-regions, with respect to deep-submicron NMOSFET structures. Figure 5-15 depicts the doping gradient of an n^+-p junction at the source (or drain) end of an NMOSFET. The dotted lines indicate contours of constant doping concentration. We define the end of the MOSFET channel as the location where the metallurgical junction occurs (i.e., where $N_{\text{D}} = N_{\text{A}}$ at the surface). When the MOSFET is turned ON, an inversion layer is induced along the length of the channel (i.e., in the substrate-region - where for this NMOSFET the doping is p -type). However, because the gate is an equipotential region, the positive bias needed to turn the MOSFET ON, will have a different effect on the silicon region under the gate if it is doped n -type. That is, in the region where the *drain doping* overlaps under the gate edge, an accumulation-layer (instead of an inversion-layer) is formed (dark region in Fig. 5-15).

The length of the accumulation-region is determined by the point where the induced (accumulated) carrier-concentration at the surface equals the background doping level. For example, a typical bias induces $\sim 10^{19}/\text{cm}^3$ carriers in the accumulation layer while the maximum doping level in the source/drain region is in the 10^{20} - $10^{21}/\text{cm}^3$ range. Therefore, the accumulation-layer has a more negligible effect in the more heavily doped region of the drain (i.e., further away from the channel edge). Nevertheless, there is still a component of resistance due to the resistance of the accumulation-layer in series with the channel-ON-resistance, and this component is referred to as the accumulation-resistance, R_{ac} . Both the accumulation-layer and the inversion-layer have about the same thickness (which is given by X_{C} , and to which we will refer again in the discussion on R_{sp}). *In any case, for deep-submicron MOSFETs, the length of the accumulation-layer is so short, that R_{ac} does not play a significant role in causing the value of R_{S} to*




Fig. 5-15 Details of structures near the vicinity of the channel end. The dotted lines are contours of constant concentration. Dark region represents the accumulation layer.²¹ (© 1987 IEEE).

rise as the devices are scaled. Hence, we will not consider this component any further in discussing the problem of the increase in R_S as the MOSFET is scaled.

Let us consider R_{sp} next, as this parasitic resistance component does play a role in the increase of R_S as the devices are scaled in the deep-submicron regime. Qualitatively, for a non-abrupt junction (i.e., where the doping contours are spaced over some finite distance, as depicted in Fig. 5-15), R_{sp} arises because after leaving the channel, the current does not immediately spread into the bulk of the source-drain regions (where the resistance effect is given by R_{SDE}). Instead, the carriers leave the accumulation layer and spread out as they move from the thin accumulation layer into the (laterally) uniformly-doped SDE-region of the source or drain SDE (Fig. 5-16).²² This resistance component is called the spreading resistance, R_{sp} .

An analytical approximation for calculating the value of R_{sp} is given by:

$$R_{sp} \sim (2\rho/\pi W) \ln(\beta X_j/X_C) \quad (5.5)$$

where ρ is the resistivity of the SDE-region, and X_C is the inversion-/accumulation-layer thickness, and β is a constant that varies from 0.37 to 0.9 (depending on the method of derivation). For the purpose of this discussion, an intermediate value of 0.58 will be used.²¹

The value of the series-resistance component R_{SDE} of the SDE-region as shown in Fig. 5-14 can be estimated from (i.e., $R = \rho/A$):




Fig. 5-16 Schematic diagram showing the resistance component associated with the injection region where the current spreads from a thin surface layer into a uniformly doped source or drain region.²² (© 1983 IEEE)

$$R_{SDE} \cong \rho l_{SDE} / (W X_j) \quad (5.6)$$

Without resorting to a two-dimensional analysis to calculate the length of the SDE region l_{SDE} , a reasonable estimate of its value is $L_L/2$ (where L_L is the lithographically drawn gate-length). Thus, since $X_j \sim 0.55 L_L$ (as described in the introduction of this section), with scaling the ratio of l_{SDE} to the SDE junction-depth X_j will remain approximately 1.2.

The sum of R_{sp} and R_{SDE} will give the value of the parasitic series resistance component of the SDE region of the drain contact structure. That is, when Eq. 5.5 and 5.6 are added together we get:

$$(R_{sp} + R_{SDE})W \cong \rho (l_{SDE}/X_j) [1 + (2X_j/\pi l_{SDE}) \ln (\beta X_j/X_C)] \quad (5.7)$$

From Eq. 5-7 it can be seen that, in effect, R_{sp} multiplies the resistance of the SDE region by the quantity given in the brackets of Eq. 5-7. This quantity is expected to range from a factor of 2.09 at the 250-nm generation to about 1.48 at the 50-nm generation, which indicates the R_{sp} plays a significant role in the parasitic resistance of deep-submicron MOSFETs, and it would be beneficial if methods could be developed that could reduce its value.

5.3.1.2 Comparing the Resistance of the SDE Region ($R_{sp} + R_{SDE}$) to R_{sat} : With the equations derived in Sect. 5.3.1.1 it becomes possible to estimate the values of $(R_{sp} + R_{SDE})$ that will be required for MOSFETs scaled down to 50-nm. (Note that this analysis was adapted from Ref. 23.) The center curve of Fig. 5-17 shows the calculated values of the channel resistance $R_{sat}W$ (in Ω -cm) of MOSFETs from the 0.25- μ m (250-nm) node down to the 50-nm node. The upper and lower curves show what the value of $20(R_{sp} + R_{SDE})W$ would be if the SDE region had sheet resistance values of 500- Ω /sq and 1000- Ω /sq, respectively. Note that




Fig. 5-17 Allowed values of drain (or source) extension resistance considering both bulk extension resistance R_{SDE} and extension spreading resistance R_{sp} .²³

values are shown for n -channel devices, p -channel devices would be about 20% higher. In addition, $20(R_{sp} + R_{SDE})W$ is used because the source and drain contact regions each contribute to the resistance in series with $R_{sat}W$.

The data in Fig. 5-17 indicates that the sheet resistance values of $(R_{sp} + R_{SDE})$ will need to be about 650- Ω /sq for 250-nm MOSFETs and about 900- Ω /sq for 50-nm MOSFETs if the value of $20(R_{sp} + R_{SDE})W$ needed to limit the degradation in I_{Dsat} to 8-10% is to be achieved. However, since the junction-depths of the SDE-regions decrease as the gate-lengths are reduced, in order to keep the sheet-resistance-values in the 650-900- Ω /sq range, the average doping-densities in the SDE-regions will have to be increased. As shown in Fig. 5-17, the peak values of doping will have to exceed $10^{19}/\text{cm}^3$ (e.g., for the 50-nm node, the peak doping will have to be $5.5 \times 10^{19}/\text{cm}^3$).

By 2001 it was determined that junctions whose depth was 35-nm could be fabricated with 0.5-keV implants and spike-anneals, but that this was about as low as could be practically achieved (see Sect. 5.3.3). Thus, for 0.1- μm technologies, it will be possible to fabricate SDE-regions with adequately shallow junctions and sufficiently low-values of sheet-resistance. However, it is not clear if it will be possible to do this for 50-nm devices, since the junction-depth will have to be decreased to about 20-25-nm, and this will mean that the sheet resistance will have to be significantly increased above 350- Ω /sq.

Also note that the model for R_{sp} given by Eq. 5-5 does not include the effect of the steepness of the lateral-doping-concentration-gradient of the SDE-implant.

As MOSFETs are scaled below 100 nm, this effect becomes the dominant factor that controls the value of R_{sp} . We discuss this issue further in Sect. 5.3.5.

Since increasing the concentration of dopants in the shallow SDE-regions is a difficult task, other ways to reduce the value of the resistance of the SDE-regions have also been sought. From Eq. 5-6 it can be seen that if the length of the SDE region could be reduced, the value of its resistance would also be decreased. While this can be accomplished by decreasing the width of the sidewall spacer, this is not practical in the conventional deep-micron MOSFET-structure. That is, since a deep contact-region is needed (to accommodate the reacted salicide-layer, see Sect 5.3.1.3), the lateral-straggle of the deeper contact-implant would penetrate under the gate edge too far if such a narrower sidewall-spacer is used. However, as we will discuss in Sect. 5.3.2, incorporating elevated-source/drains into the MOSFET structure would permit the use of such narrow sidewall-spacers, thus allowing the resistance of the SDE-region to be made smaller.

5.3.1.3 Parasitic-Resistance R_{co} of the Deeper Contact-Region of the Drain:

Although the contact-region of the drain-structure has a deeper junction-depth than the SDE, it can also contribute significantly to the parasitic series resistance of the drain structure, namely through the *contact resistance*, R_{co} . That is, a salicide ($TiSi_2$ or $CoSi_2$) is formed on the surface of the contact-region by sputter-depositing a layer of Ti (or Co) onto the wafer. Then the Ti (or Co) is reacted with the silicon at elevated temperatures, forming the salicide layer. This salicide-layer (and the kinetics of its formation) play a role in the value of R_{co} .

A simple model for R_{co} (or $R_{co}W$) is given by:²¹




Fig. 5-18 Allowed values of drain (or source) contact-resistance.²³

$$R_{co}W \geq \rho_c/2 L_L \quad (5.8)$$

where ρ_c is the specific contact resistivity of the silicon-to-silicide interface (in $\Omega\text{-cm}^2$). This can again be compared with the channel-resistance R_{sat} . Figure 5-18 gives values of $20R_{co}W$ for a 10% contribution of (source + drain) contact resistance. To have a 10% or less contribution, the data in Fig. 5-18 indicates that ρ_c must be in the range of $10^{-7}\text{-}\Omega\text{-cm}^2$ for $0.25\text{-}\mu\text{m}$ MOSFETs, but must get down to around $4 \times 10^{-8}\text{-}\Omega\text{-cm}^2$ for 50-nm MOSFETs. It has been demonstrated that for a barrier height of about 0.5-eV , the required doping-density needed to achieve such a low value of ρ_c is above $10^{20}/\text{cm}^3$. This means that the silicon regions in contact with the silicide will have to be very-heavily doped, a condition that may not be possible to attain in 50-nm MOSFETs with conventional structures, for reasons we describe next.

When the silicide is formed on the source/drain contact-regions by the reaction of Ti (or Co) and silicon, some of the silicon in the substrate is consumed (i.e., when TiSi_2 is formed, the silicon consumed is about 75% of that of the thickness of the final silicide film, while for CoSi_2 , even more silicon is consumed – about equal to the thickness of the CoSi_2 that is formed). This has two repercussions. First, the contact-region of the drain must be deep enough so that the junction is not entirely lost as a result of the silicide-formation. To keep the implanted dopants from negating the benefits of the shallow SDE-junction (as a result of lateral-straggle that causes the implanted species to penetrate laterally under the implant-mask edge) a sufficiently wide gate-sidewall spacer must be used to mask the contact-region-implant. This impacts the resistance of the SDE-region, through an increase in l_{SDE} . Second, the silicon consumed is that nearest the surface, just where its doping concentration is the highest. The interface between the resultant silicide and the silicon is far below the initial silicon surface, where the implanted doping-concentration is considerably lower (which will impact the value of R_{co}). Furthermore, the dopant in the silicon (especially boron) is known to segregate into the silicide layer, further depleting the doping-concentration at the silicide-silicon interface. Since the contact-region of the drain cannot be made arbitrarily deep (due to the fact that lateral-straggle also increases as the projected-range of the implant is increased), it is not clear that it will be possible to make contact-regions with doping concentrations that are adequately high to achieve the required low-values of ρ_c . The use of elevated-source/drain regions (Sect. 5.3.2) would also allow a way around this obstacle.




Fig. 5-19 Schematic of elevated-source/drain contacting structure.

5.3.2 MOSFETs with Elevated-Source/Drains

One proposed method for reducing the series-resistance of the source/drain structures in deep-submicron MOSFETs is to modify the basic device structure by adding so-called *elevated* (or *raised*) *source/drains* (Fig. 5-19). In this method, the heavily-doped contact is elevated above the original substrate surface by forming a selectively-grown epitaxial-Si (or perhaps Si-Ge) layer.

The MOSFET with elevated-source/drains has several advantages for devices when they are scaled to 50-nm and beyond. First, the width of the sidewall-spacer can be made much smaller. This can greatly reduce the resistance of the SDE region by decreasing its length l_{SDE} . Second, the n^+ contact layer can be sufficiently thick to contain the silicide layer without junction-leakage problems. Third, the selective-epitaxy-layer can potentially be heavily-doped during growth to obtain a lower contact-resistance. However, two selective-epitaxy processes will be needed since both n^+ and p^+ contacts must be made. The Si-epitaxial-growth steps occur after the SDE-implant. To keep the dopant of the SDE-region from diffusing too-far under the gate-edge, the selective-epitaxial-processes will have to be carried out at sufficiently low temperatures (i.e., probably below 850°C). A technique involving such a low-temperature epitaxial-process for forming elevated-source/drains was described by Miyano *et al.*²⁴

In late-2001, Intel announced that the deep-submicron-MOSFET structure it intends to use for the next decade is designed with elevated-source/drains (and an SOI-structure that also employs a high- k dielectric [ZrO_2], SSR-channel-doping, and pocket-implants for punchthrough-control).⁵⁸

5.3.3 Shallow-Junction-Formation for Deep-Submicron Source/Drains

The main thrust for achieving shallow SDE region junction depths is to decrease the energy of the SDE-implant. For the source/drain-structures of the 0.13- μm and 0.1- μm technology nodes, single-digit keV energies are expected to be needed for the implants that will form the drain contact regions, and sub-keV energies will be needed for the SDE-region-implants.

5.3.3.1 Ultra-Low-Energy Implants: There are three reasons that reducing the energy of the implant leads to a decrease in the junction-depth. First, the projected range R_p of the implant becomes smaller as the energy is reduced. Second, the straggle and ion-channeling effects both scale with R_p (which is especially important for B implants). Third, TED that occurs during the implant-annealing step is reduced (see Sect. 5.3.3.2). It turns out that for sub-keV B-implants the channeling-effects become relatively unimportant (compared to the broadening of the implant doping profile caused by TED during the annealing step). For this reason, elaborate measures to reduce channeling (such as performing a pre-amorphization-implant prior to the low-energy SDE-implant) are not likely to be used for MOSFETs with gate lengths of 0.1- μm and smaller.

The difficulty with implementing such low-energy-implant processes in manufacturing applications is achieving the productivity that the industry has been accustomed to getting at higher-implant-energies. For example, at energies greater than 10-keV, a high-current-implanter with a beam-current between 10- and 25-mA can implant 230 wafers per hour with the high dose of $4 \times 10^{15}/\text{cm}^2$. (Note that beyond 0.18- μm , the doses of the SDE will be in the $1\text{-}2 \times 10^{15}/\text{cm}^2$ range, and the doses of the contact-regions of source/drains will be even higher.) At sub-keV energies, the maximum beam-current available on commercial implanters in the mid-1990s timeframe was in the 1-2-mA range. Even after a reduction in dose (made possible by the decreasing energy), the productivity is only fraction of what it previously was. The decreased beam-current at lower energies follows from Child's law, which states that the maximum ion-current that can be extracted from any cathode, drops off as $V^{3/2}$ where V is the extraction voltage. While this basic constraint can be somewhat circumvented (by extracting a larger current at a higher energy and then decelerating the beam

to a final lower energy; i.e., what implant vendors refer to as “decel”), the effective beam-current still decreases with the final energy. With decel, care must also be taken to minimize energy-contamination caused by ion-neutralization before (or in) the decelerating field. That is, ions neutralized while being transported in the beamline will not be counted as part of the dose. Furthermore, they will be implanted at much higher energy, possibly causing deeper junctions (thus defeating the central purpose of using an ultra-low-energy implant).

There are two commercially available high-current, low-energy-implanter configurations: 1) *batch* (or *multiwafer*) implanters; and 2) *single-wafer* implanters. Batch type implanters are sold by Axcelis (GSD/200E[®] model) and Applied Materials (Quantum LEAP[®]). A single-wafer, high-current, low-energy-implanter (with a scanned ribbon beam) is offered by Varian Semiconductor (VISta-80[®]). The vendors of the “batch” type low-energy-implanters argue that the throughput is significantly higher than for single-wafer machines. The batch systems use a fixed beam, while the single-wafer systems use a scanned beam. The tuning time for a fixed beam is always shorter than that needed for a scanned beam. Hence, the set-up time for a batch system is smaller. Capacity modeling studies have shown that fewer batch low-energy-implant-systems are required (e.g., 3 to 4 for a fab that starts 5000-wafers per week with a 0.18- μm process, versus 5 to 9 single-wafer-implanters), primarily because of the fast tuning in the batch machines. This reduces the overall capital-cost and cost-per-wafer.

The advantages claimed for the low-energy, single-wafer-implanters are the following: 1) the angle of the implant with respect to the wafer surface can be controlled more accurately in a single-wafer-implanter; 2) sputtering of metals from the spinning disk (the largest source of contamination in batch-implanters) is eliminated; and 3) a 70°-angle analyzing-magnet allows the VISta-80[®] to essentially eliminate the problem of energy contamination.

While a significant effort was being expended to improve the productivity by increasing the beam current,^{25,26} the basic capability of being able to implant at an ultra-low-energy (i.e., sub-keV) already existed by 2000. (That is, by 2000 implanters were available that could provide 4-mA at 0.2-keV.) This allowed researchers to investigate the limits of shallow SDE-junction-depths with sub-keV implants and conventional RTA methods. Drain extensions with junction-depths that meet 0.1- μm technology requirements were demonstrated.²⁷ It appears, however, that it may not be possible to improve on these results unless either the extension-resistivity-specification is significantly relaxed or new annealing technologies are developed which provide a smaller thermal budget




Fig. 5-20 Sheet resistance and source/drain junction depth expectations for CMOS transistors according to the ITRS99 study for cost and performance-focused product and gate sizes from 180 nm towards deeply-scaled devices with gates ~ 20 nm. Also shown are experimental results for sub-keV B^+ implants with “spike” RTA in CZ-Si materials.⁵⁹

and are compatible with CMOS processing. That is, in order to meet the decreased resistivity requirements of the scaled MOSFETs, it is necessary to implant a larger dose or increase the annealing temperature to activate more of the smaller dose implant. The issue is illustrated in Fig. 5-20, where the ITRS99 expectations for the source/drain-extension junction-depth and sheet-resistance are compared to experimental results for boron-doping with sub-keV B-implants and a “spike”-RTA process (with a high-temperature thermal-cycle of 1050°C for 1 sec). All of the experimental results are above the $\sim 10^{-3}\text{-}\Omega\text{-cm}$ resistivity “wall” (the dark downward-sloping line in this figure). The shaded squares and triangles in Fig. 5-20 are actual experimental data, whereas the open circles are expected results that have not yet been attained. The resistivity requirements for “high performance” MOSFETs are $\sim 10^{-4}\text{-}\Omega\text{-cm}$ for 20-nm MOSFETs.

As compared to the SDE-regions of the source/drain, higher doping-concentrations are needed for the contact source/drain-regions. This is because these regions are used to contact the silicide-layer, and high doping-concentrations help to reduce the value of R_{c0} . Since these regions are not adjacent to the channel, they do not have as great an impact on short-channel behavior as the SDE-junctions. Consequently, doses and implant-energies can be higher than those permissible for SDE-regions, even when B-implants are used.

By 2001 the trend of using lower implant energies for the SDE-implant for each generation appears to have reached a practical limit in terms of device performance (especially for *p*-channel transistors). That is, 0.5-keV boron implants appear to be the lower useful limit for shallow junctions, not just for 0.13- μm but for all technologies.²⁸ Below 0.5-keV, the implant becomes less productive, more costly, and the final junction performance (i.e., the simultaneous achievement of junction-depth and resistivity) is the same. The performance limit with a 0.5-keV boron-implant and spike-anneal is a junction-depth of about 35-nm and a sheet resistance of about 350- Ω/sq . It appears that to further reduce either value, the other must be increased.

5.3.3.2 Transient-Enhanced Diffusion: The second key reason for developing dopant implant processes with energies in the sub-keV range (besides reducing the as-implanted depth), is to minimize the transient-enhanced diffusion (TED) of the dopant. When high-energy ions enter the silicon lattice, they displace silicon atoms from their lattice sites, creating pairs of vacancies and interstitials. When the post-implant anneal is initiated, most of these interstitials and vacancies recombine, but some interstitials remain behind (in an amount about equal to the quantity of implanted atoms – most of which now occupy the sites that were formerly filled by the still-displaced silicon interstitials). The fact that each implanted atom produces about one residual interstitial after a very short anneal is called the “+1 approximation.” TED can be explained by relating its enhanced-diffusion effects to the presence of these excess interstitials for a wide range of low- and medium-dose implants, and low- and medium-energies.

The residual excess interstitials rapidly coalesce into such unstable extended-defects as {311}'s and also into more-stable extended-defects, such as dislocation loops. While this coalescence occurs because there is a lower system-energy when the interstitials populate extended-defects (compared to when they exist as individual interstitials), the defects are still metastable. Thus, they dissolve with continued annealing (especially the {311}-defects). During their dissolution they emit interstitials into the silicon. The rate at which these defects dissolve depends on the activation-energy and annealing-temperature. Nevertheless, as long as these defects exist, an interstitial supersaturation is maintained (i.e., a higher concentration of interstitials is present than would exist in the absence of the extended defects). Since boron diffuses by an interstitial mechanism, its diffusivity is enhanced by the excess interstitials - with the time-averaged diffusivity-enhancement equal to the time-averaged interstitial-supersaturation. In any case, both the interstitial-supersaturation and the

diffusivity-enhancement soon end after the defects have dissolved. The enhancement is thus transient.

The *increase* in depth of a shallow SDE-junction ΔX_j due to TED can be expressed in terms of the initial-supersaturation of interstitials and the time of the interstitial defect dissolution as:

$$\Delta X_j^2 \propto NR_p \exp [- (-1.4 \text{ eV})/kT] \quad (5.9)$$

where N is number of interstitials initially trapped in the defects (approximately equal to the implanted dose, as noted above) and R_p is the projected ion range (which is where the peak concentration of the excess interstitials is initially located). The linear dependence of N simply represents the fact that the larger the dose, the larger the supersaturation, and hence the greater the diffusivity enhancement. The linear dependence on R_p has been demonstrated experimentally. The nearer the excess interstitials are to the surface, the faster they reach the surface (where they are annihilated). The linear dependence on R_p explains why use of ultra-low-energy implants reduces TED effects. That is, if an ultra-low-energy implant is used, R_p will be small. Thus, the location of the interstitials will be closer to the surface, allowing them to escape there faster. Thus, the duration of the transient is shortened, making the value of ΔX_j smaller.²⁹ (Later work indicated that for implants below 1-keV in energy, TED is even further reduced because there is less lattice damage per ion.³⁰)

Another important dependence contained in Eq. 5-9 is the *negative* activation-energy of ΔX_j^2 , which arises from the fact that the interstitial-supersaturation due to the presence of the extended-defects is larger at a lower temperature. The negative-activation-energy implies that if the defects are annealed out at a low temperature, the final junction will be deeper than if the defects are annealed out at a higher temperature. This is one of the main reasons why the S/D anneals are currently carried out in an RTA tool rather than in a conventional batch furnace (that has a ramp-up rate of a few degrees per minute). In an RTA chamber, significantly less time is spent during the temperature ramp-up at a lower temperature (at which the diffusivity-enhancement is larger).

5.3.3.3 Rapid-Thermal-Annealing of Shallow Junctions: To form the shallowest junction possible using ultra-low-energy implantation, it is necessary to minimize the thermal-budget after implant. (Thus, as noted above, annealing such implants is carried out in RTA tools to realize good-quality shallow junctions.) In the ideal case, the as-implanted-dose would spend “zero” time at the temperature that would electrically-activate the dopants and heal the lattice damage from the implant. (Exposure to a high-temperature for a very-short time is effective

because the activation-energy for dopant-activation is typically higher than that for diffusion, thus electrical activation is favored while limiting diffusion. Reported values for boron are 5.4-eV and 3.4-eV for activation and diffusion, respectively.) Attempts to reach this ideal annealing condition have led to the development of so-called "spike" anneals, which consist of very fast ramp-up and ramp-down of temperature, with virtually zero-time at the peak temperature. Experiments have shown that the difference in the percentage-of-activation and sheet-resistance between spike-anneals and those that keep the wafer at temperature for 10-sec is negligible. On the other hand, for the 10-sec-at-temperature anneals, the junction-depth increases with temperature.⁸⁸ This indicates that spike anneals are more effective at higher peak-temperatures.

In practice, spike anneals have an effectively finite-time at temperature. Also, in reality, while ramp-up rates as fast as about 200°C/sec are possible, the ramp-down is limited to approximately 50-80°C/sec. As a result of these deviations from ideality, it is useful to determine what is a sufficiently-fast ramp-up rate. The negative-activation-energy of TED seems to indicate that as high a ramp-rate that can be attained, should be used during a spike anneal. However, experiments show that for such ultra-fast ramp-rates, the advantage gained by going from moderately fast (e.g., 100°C/sec) to ultra-fast ramp-up rates (200-400°C/sec) is relatively small for ultra-low-energy implants. Such a small advantage must be balanced against the loss of process control (e.g., across-wafer thermal-uniformity and temperature-repeatability) which inevitably occurs when such ultra-fast ramp-up-rates are used. The reason the advantage is not very great is that TED is already sufficiently minimized at 100°C/sec.³² This reduction in thermal-budget during ramp-up is negligible compared to the portion of the thermal budget which cannot be reduced (the finite-dwell-time at temperature and the relatively low ramp-down-rate).

The data shows that the largest reduction in junction-depth with increased ramp-up-rates occur for the lowest-energy-implants (see Fig. 5-21).³¹ Since TED decreases with decreasing implant-energy, it can be inferred that the advantage is primarily due to the overall thermal-budget and not just of the TED. It is therefore evident that without the ability to increase the ramp-down-rate (when it is relatively smaller than the ramp-up-rate), the advantage from increasing the ramp-up-rate will quickly saturate at ramp-up-rates greater than the ramp-down-rate. In addition, it has been determined that the ramp-rate is not as good a measure of the quality of a spike-anneal as is the time spent diffusing the dopant. That is, since about 90% of the dopant-activation occurs in the short-duration from approximately 50°C below the peak-temperature to the peak-temperature




Fig. 5-21 Junction-depth, measured at a concentration of $1 \times 10^{18}/\text{cm}^3$ after spike-annealing at various ramp-up-rates. The ramp-down-rate was the same in all cases. For both As and B the advantage from a faster ramp-up is largest for the shallowest implant. This implies that the reduction in TED (known to decrease with implant-depth) is not the dominant mechanism responsible for the larger reduction in junction-depths observed for the shallower-implants with increasing ramp-up-rates.³¹

and back to 50°C below, this interval of time is really a better specification of the quality of a spike-anneal.²⁸

Figure 5-22 is a survey of published spike-anneal data that was presented in Ref. 32. It can be seen that many of the data points are coincident, despite having been taken from different implant-and-annealing conditions (energy, dose, and ramp-rate). It is evident that more than one set of process conditions can be used to arrive at the same junction properties.

A variety of RTA-tool configurations are commercially available, including the following: **a)** linear lamps, double-sided heating; **b)** axisymmetric lamps, single-sided heating; **c)** arc lamp; **d)** hot-plate; and **e)** hot-wall RTP. Several general references are available that give detailed descriptions of these types of RTP tools.^{33,34,35} Data on shallow junctions formed with the various RTP-tool types can be found in the following references: lamp-based RTP systems (36); hot-plate (susceptor – 37); and hot-wall RTP (38).

New ways to increase the value of the electrically-active-dopant in shallow-junction regions are also being actively being researched. Some of these novel techniques include: 1) laser anneals;³⁹ 2) strain-compensation implants




Fig. 5-22 Comparison of *p*-type sheet-resistance and junction-depth data for spike-anneals using various implant-and-annealing conditions. The data set includes a 400°C/sec ramp-up-rate and 0.2-keV implant-energy. Note that all the data points fall in a rather narrow band. No one has been able to make a 30-nm junction with a 300-Ω/sq sheet-resistance using ion-implantation and conventional rapid-thermal-annealing.³²

(e.g., by adding Ge-atoms to the silicon lattice, their larger size compensates for strain caused by the smaller B atoms. This increases the solubility of the boron atoms in the silicon.);⁴⁰ and 3) using RTP-tools which have a short lamp-response-time, which increases the ramp-down-rate.⁴¹

5.3.3.4 Dopant Loss for sub-keV Implants from Self-Sputtering, Out Diffusion, and Surface Oxide: Several factors associated with ultra-low-energy implants give rise to loss of some of the species that are implanted, and they are discussed in this section. The effects that lead to such dopant loss are: self-sputtering, out-diffusion, and the presence of a surface oxide during the implant process. When the dose-loss from all three of these effects are combined, the loss can be large enough to pose a significant problem for ion-implant processes carried out at energies of 0.5-keV or lower.

The first phenomenon associated with dopant loss in ultra-low-energy implant processes is *self-sputtering*. That is, when any solid-surface (the target) is struck by an ion-beam, sputtering of atoms from the target will occur. The number of atoms sputtered for each bombarding ion rises as the energy of the ion decreases. In particular, when the ions being implanted have energies in the 0.2-1-keV range, significant sputtering of the target will occur. For example, when 0.5-




Fig. 5-23 The dose-loss due to self-sputtering depends on how much dopant has already been implanted. (a) At the start of the implant most of the sputtered atoms are silicon. (b) As the composition of the near surface layer becomes altered, with an increasing fraction of them being boron, more boron atoms are sputtered.⁵⁹

keV B-ions strike a silicon target, about one Si-atom is sputtered for every four implanted B-atoms. Since at such low-energies the implanted species also come to rest near the Si surface, some of these implanted B-atoms themselves will be subject to sputtering. In fact, it is expected that with increasing B-dose, more and more of the implanted B-atoms will be sputtered from the surface. (This phenomenon is depicted in Fig. 5-23.) Since additional B-implanted-atoms will be sputtered with increasing dose, this implies that the fraction of implanted dose that is retained in the silicon wafer will decrease with increasing dose. Given the difficulty associated with achieving a large beam-current at such low-energies, a further reduction in the retained dose is very undesirable. That is, while the dopant-loss could be compensated by increasing the implant dose, this will further decrease throughput (which is already too low).

Figure 5-24 plots the retained-dose compared with the nominal-dose for various energies.³² It indicates that at 2-keV essentially the entire dose is retained. But at implant-energies of 0.5-keV and 0.2-keV, a significant fraction of the implanted-dose has been sputtered out, with the missing fraction rising with increasing dose. For a nominal-dose of $1 \times 10^{15}/\text{cm}^2$, sputtering causes a 10% reduction in the retained dose at 0.5-keV, and a reduction of 20% of the retained dose at 0.2-keV.

If BF_2^+ is used to implant B at low-energies, the sputtering problem is expected to be even worse than if B is implanted. That is, in BF_2^+ -implantation, for each implanted B-atom that contributes to the retained dose, there are now 3 atoms (one B and 2 F) which can cause sputtering (compared to just one B-atom for an implant process that uses B^+ -ions instead). For example, for a nominal dose of $1 \times 10^{15}/\text{cm}^2$, we stated that a 0.5-keV B^+ -implant will cause a 10% reduction in retained dose. However, if a BF_2^+ implant is carried out so that the B-atom in the BF_2^+ -ion has the same energy as in the 0.5-keV B^+ -process (i.e., the BF_2^+ -ions have energies of 2.2-keV), the reduction in retained-dose increases to ~20%. The above circumstances imply that caution must be exercised when comparing junction data from the literature for different sub-keV implants or for different species. A correction needs to be applied for the different retained-doses to allow meaningful comparisons to be made.

The second effect that gives rise to dose-loss is *out-diffusion*. Out-diffusion of implanted species occurs during the annealing steps that are performed after the implant. As the projected-range R_p of the dopant is decreased (as a result of implanting at lower energies), the out-diffusion grows worse. The reduction in retained-dose after a $1000^\circ\text{C}/15\text{-sec}$ -anneal is approximately 10% for an implant energy of 0.5-keV, but increases to 15% for 0.2-keV energies.




Fig. 5-24 Retained B-dose as a function of nominal B-dose implanted into (100)-silicon wafers with an as-received native oxide. The trend lines are 3rd order polynomial spline-fits. For a nominal B-dose of $1 \times 10^{15}/\text{cm}^2$, sputtering leads to a reduction of ~10% in the retained dose at 0.5-keV, and a reduction of ~20% at 0.2-keV.⁵²

The final cause of dopant-loss in sub-keV implants is due to the presence of an *oxide on the silicon-surface during implant*. Such an oxide is often deliberately grown to protect the silicon surface from metal contamination during the implant process (see Chap. 10, Vol. 1, 2nd Ed.). While this protective oxide layer can be made quite thin, it nevertheless has a finite thickness. It is clear that as the implant energy is reduced, a larger fraction of the as-implanted dose will be located in the protective oxide. Since the oxide is stripped off at the end of the implant step, the dopant that remains in the oxide cannot contribute to the formation of the junction. Approximately 25% of the B implanted at 0.5-keV is lost by removal of a 15-nm-thick surface-oxide, while more than 40% is lost for 0.2-keV implants. With these results, it is possible to estimate the equivalent-dose needed at lower energies (such as 0.2-keV) to make up for the larger loss as compared to 0.5-keV implants. For example, it has been calculated that to successfully implant a dose of $4 \times 10^{14}/\text{cm}^2$ B-atoms at 0.2-keV into the silicon beyond the protective oxide, the beam-current would have to be as much as 60% greater than the beam-current at 0.5-keV to obtain an equivalent throughput process.³² To circumvent the oxide dose-loss problem, some ultra-low-energy implant processes are being carried out without the use of a protective oxide.

In summary, the dose-loss effects are significant for sub-keV implant processes, and the loss increases as the implant-energy is reduced. For the extreme case of 0.2-keV implants, as much as 40% of the B-dose can be lost due to the combined effects of self-sputtering, out-diffusion, and native-oxide removal for the high doses needed for an SDE-implant.

5.3.4 Effect of the Overlap of the SDE-Region and Gate-Edge on MOSFET Performance

In addition to being able to carefully set the junction-depth X_j and length of the SDE region l_{SDE} , it has also been reported that the amount of overlap of the SDE-region with the gate-edge is also critical for optimum device performance.^{42,57} That is, if the overlap of the SDE-region and the gate-edge is too great, the deep-submicron MOSFET will suffer excessive leakage (due to larger short-channel effects that arise if the channel-length is too small). Excessive leakage means that the off-state current exceeds its maximum design value (e.g., $1 \text{ nA}/\mu\text{m}$). In addition, the gate-to-(drain/source) overlap-capacitance increases, which negatively impacts device switching speed.

On the other hand, if the SDE-to-gate-edge-overlap is too small, the ON-state saturated-drain-current I_{Dsat} will decrease because the SDE-region and the end of the channel are not electrically well-coupled. Thus, an excessively-high-resist-




Fig. 5-25 Schematic of a deep-submicron MOSFET with an offset-sidewall spacer.⁵⁷

ance-region separates them (and this increases the parasitic resistance of the source/drain regions, which leads to a decrease in the value of I_{Dsat}).

Controlling the position of the edge of the SDE region with respect to the gate edge can be done in the following way. First, the implant-and-annealing processes for forming the SDE (and contact) region of the drain structure are determined, and the drain structure is formed using these process conditions. However, an offset-spacer is fabricated on the side of the gate after the gate-poly is etched (but before the SDE implant step is carried out, Fig. 5-25).⁵⁷ The width of this off-set spacer is varied from zero (no-spacer) to some upper-bound (e.g., 50-nm). Measurements are then made for the MOSFET having different offset-spacer-widths. The offset-spacer-width that yields optimum device characteristics (i.e., the best combination of off-current and I_{Dsat}) is taken to be the value that produces the correct overlap of the SDE-region and the gate edge.




Fig. 5-26 I_{Dsat} versus SDE overlap (NMOS).⁴²

The results of such a study are shown in Fig. 5-26. In this case, the effects of SDE-overlap on 0.25- μm NMOSFETs were analyzed. The arsenic-implanted SDE junction-depth X_j was measured to be 50-nm. Since the lateral diffusion of the SDE junction under the gate-edge is estimated to be 0.6-0.7 times the vertical depth (about 30-nm), minus the width of the offset spacer, the SDE-overlap for each offset spacer width can be determined. Fig. 5-26 shows that if the SDE-overlap is less than 20-nm, the value of I_{Dsat} falls off rapidly. Thus, a minimum overlap of ~20-nm is recommended by this study. Information as to how to form the offset spacer was not given, but a method (such as re-oxidizing the polysilicon gate-structure after it has been etched) is one possible way of doing so.

5.3.5 SDE-Junction Abruptness

The SDE-region must not only have the correct junction-depth, average-doping-concentration, and position under the edge of the gate, but recent studies have shown that there must also be a highly-abrupt lateral-doping-gradient at the interface of the SDE and the MOSFET channel-regions.^{43,44} Not only does such an abrupt-doping-gradient help limit the lateral-encroachment of the extension-depletion-regions into the channel, but more importantly it minimizes R_{sp} . The design rules for lateral-junction-abruptness are that the doping-falloff must be at least one decade in a distance equal to ~3% of the size of the gate-length (for a spreading-resistance less than 5% of R_{sat}). For 100-nm MOSFETs this means that the junction-abruptness must be ~3 nm/decade, which is about the profile slope of as-implanted B at 0.2-keV.⁴⁵ Since the abruptness will have to increase even further as smaller MOSFETs are designed, this implies that new techniques will have to be developed that result in final junction-doping-profiles that are even steeper than the as-implanted profiles.

The design of the implanter can play a role in the lateral-abruptness of the SDE as-implanted doping profile. That is, unlike mid- to high-energy ion-implant applications, channeling-effects are minimal for low-energy, high-current implants (because of increased channeling acceptance angle). Nevertheless, there is still a significant difference between single-wafer and batch-implanters due to implant shadowing effects. Ideally, a 0°-implant will give the most-abrupt lateral-junction because any tilt-angle larger than 0° induces shadowed areas at the vicinity of the gate pattern (leading to laterally-graded doping-profiles). If the incident beam has an angular-spread deviating from the ideal parallel beam, each of the ions having different incidence angles will make different shadows. The result is a loss of dose- and junction-abruptness at the outskirts of the gate. A single-wafer, parallel-beam-implanter minimizes the incident-angle-variations.

Spinning-disk batch-implanters use a stationary-spot ion-beam. The wafers pass through the beam due to the rotation of the disk. Such batch-implanters use a concave-shaped disk to secure wafers in their respective sites during the high-speed motion of the disk. Centrifugal force exerted on the disk surface holds them in place. Since the conical disk has a curved surface and the wafer-surface is flat, this leads to an incident-beam angle-variation across the wafer during the implant process. Depending on the dimensions of the disk, cone-angle, and wafers, this can amount to 1.5°-variation across a wafer.⁴⁶

Recently, the abruptness of the SDE-lateral-doping was measured using both scanning capacitance microscopy (SCM)⁴⁷ and scanning tunneling microscopy (STM).⁴⁸ The latter measurement detected a tail-region of dopant at the end of the doping profile, spreading from the extension-region in the horizontal direction near the gate oxide. The cause of this anomalous diffusion tail was not understood.

5.4 ANTI-PUNCHTHROUGH STRUCTURES IN DEEP-SUBMICRON CMOS

Lateral tailoring of the channel doping profile can provide some additional flexibility to control V_T and punchthrough. Recently, such lateral tailoring of the channel profile has been carried out with the use of *large-angle-tilt implanted punchthrough stopper* (LATIPS), which are also referred to as *pocket-implants* (and are depicted in Fig. 5-27). Such a pocket-implant puts additional dopants in the channel close to the source/drain-junctions for punchthrough control, and leaves much of the channel region with a lighter doping, as needed for a low V_T .^{*} The peak doping values of the pocket-implants must be somewhat larger than the doping-concentration values needed for a punchthrough-control layer that is uniform in the lateral channel direction between the source and drain.

These punchthrough-suppression pocket-implants are done after the source/drain-extension-implant (and before the formation of the spacer used to define the edge of the deeper contact-source/drain-implant). This ensures that the pocket-implant-dopant is self-aligned to the gate. The dopant is placed just below the active channel, adjacent to the source and drain, and is of the same dopant-type as the well. Precise control of the placement and dose of this implant within the transistor-structure is needed to obtain the intended enhancements. As noted

* As pointed out in Chap. 1, if an implant with a beam directed normally to the wafer surface is used to introduce dopants to create a punchthrough-control structure, instead of one whose direction is tilted at a large angle to the wafer surface, the resulting punchthrough-control structure is termed a *halo* structure. Such a halo structure is described in Chap. 1, and is depicted in Fig. 1-2b.




Fig. 5-27 MOSFET with heavily-doped pocket-implants for punchthrough-control.

above, the use of high wafer-tilt-angles when performing such pocket-implants offers an additional, controllable processing parameter for producing complex channel structures, without diffusion or additional masks. (The presence of the pocket-implanted-species also helps keep the source/drain-extension [SDE] junction-depths shallow, because they compensate some of the dopant in the SDE region [which, in effect, squeezes the SDE-junction closer to the surface].)

As introduced by Hori, high tilt-angles are needed for achieving greater




Fig. 5-28 Simulated 2-D impurity profiles of typical LATIPS structures for (a) NMOSFET with n -LDD region and; (b) Buried-channel PMOSFET.⁴⁹

lateral-penetration of the pocket-implant than the adjacent source/drain-extension implant without thermal diffusion.⁴⁹ That is, the species implanted by the pocket-implant should reside outside of the final source/drain-extension-doping-profile after implant and annealing. Typically, tilt-angles are 20°-45° from the wafer normal. Figure 5-28 shows the resulting (simulated) doping profile in the channel region and in the adjacent well of a LATIPS device.⁴⁹

To maintain device symmetry with high tilt-angle, the implants must be split into segments. Since most circuits contain transistor gates placed 90° from each other, high tilt-angle implants are typically done in four segments of equal dose ("quad-implants") with the wafer rotated 90° between segments. (As gate-widths shrink, less undercutting of the gate is required to produce the punchthrough stop effect. Consequently, tilt-angle requirements for this application are steadily decreasing below the 0.25- μm node, and are expected to reach the "low-tilt-angle" threshold of 10° by the 0.1- μm technology node.)

High-tilt-angle punchthrough-suppression-implants improve device performance. Junction-capacitance can be reduced by up to 65%; while the subthreshold slope of the device becomes steeper (which suppresses short-channel effects).⁵⁰ The dramatic improvement in punchthrough-resistance does not depend on extreme scaling of the S/D junction-depth or n -well background-doping. The reduced subthreshold-slope and junction-capacitance directly result from carefully controlled doping underneath the channel at the gate edge and the near elimination of all other undesired doping that results from less controllable doping methods.

Because of their lower-diffusivity and as-implanted-straggle, higher mass dopants can be placed more precisely in the channel. Consequently, indium (In) and antimony (Sb) are being increasingly used for this application.^{51,52} Punchthrough-stop implants were the primary production application of In and Sb in ion-implantation in the 2000 timeframe. The lower susceptibility of these species to TED also helps reduce the reverse-short-channel-effect (the slight increase in threshold-voltage with decreasing effective-channel-length that occurs before punchthrough-effects dominate the smallest channel-lengths).

One proposed structure for MOSFETs with an effective gate length (L_E) of 0.25- μm is shown in Fig. 5-29.⁵³ This device has a very heavily doped source/drain next to a very heavily doped pocket-implant. Since the gate-length is so small, the pocket-implanted-region actually doubles for the traditional retrograde-well-implant. This aggressive device design shows the challenges of doping a 25-nm MOSFET. Very-high doping levels and very-steep doping gradients are required – with a minimum of thermal processing.




Fig. 5-29 Doping contours in 25-nm PMOSFET.⁵³

An issue associated with the use of In as a pocket-implant species has recently been reported. That is, an In implant at the doses needed for the pocket-implant process causes a buried amorphous layer to form. This layer has an interface with the single-crystal silicon. The silicon at these interfaces is still crystalline, but is heavily damaged. The indium segregates to these damaged regions and becomes




Fig. 5-30 Indium SIMS profiles for $1 \times 10^{14}/\text{cm}^2$ implants at 200 keV annealed at 750°C for 2, 30, and 120 min in nitrogen. This figure shows large dose loss for indium. The depth of the defect layer (measured by XTEM) is shown (upper & lower defect layers).⁵⁴

electrically de-activated (negating its ability to provide punchthrough control).^{54,55} Figure 5-230 shows a SIMS profile of the In as-implanted, and after annealing. The loss of indium from its peak is seen. A double-implanted extension region (As + Sb) has been reported to be able to control the damaged region near the In pocket, mitigating the indium segregation and de-activation.⁵⁶

REFERENCES

1. R.D. Rung, C.J. Dell'Oca, and L.G. Walker, "A Retrograde *p*-Well for High Density CMOS," *IEEE Trans. Electron Dev.*, **ED-28**, p. 1115, 1981.
2. D.M. Brown *et al.*, "Trends in Advanced CMOS Process Technology," *Proceedings of the IEEE*, December 1986, p. 1646.
3. G.J. Hu *et al.*, "Design and Fabrication of *p*-channel FET for 1- μ m CMOS Technology," *IEDM Tech. Dig.* 1982, p. 710.
4. R. Martin and J.Y. Chen, "Optimized Retrograde *n*-Well for 1 μ m CMOS," *Proc. Custom Integ. Circuits Conf.*, 1985, p. 199.
5. J.Y. Chen, "CMOS - The Emerging Technology," *IEEE Circuits and Devices Magazine*, March 1986, p. 16.
6. Y. Mochizuki, "Special Report: High Energy Ion Implantation Technology," *Nikkei Microelectronics* (Dec. 1991), p. 92.
7. K. Tsukamoto *et al.*, "High Ion Energy Implantation for ULSI: Well Engineering and Gettering," *Solid State Technology*, June 1992, p. 35.
8. R. Wijberg *et al.*, "Strong Asymmetric Doping Profiles at Mask Edges in High-Energy Ion Implantation," *IEEE Trans. Electron Dev.*, **37-1**, January 1990, p. 79.
9. T.M. Parrill and M.J. Namaroff, "Ion Implantation Productivity for Advanced Applications," *European Semiconductor*, July 1999, p. 44.
10. B. Adibi and V. Meniailenkov, "Transistor Performance: The Impact of Implant Doping Accuracy," *Solid State Technology*, January 2001, p. 88.
11. S. Takagi *et al.*, "On the Universality of the Inversion Layer Mobility in Silicon MOSFETs: Part I-Effects of Substrate Impurity Concentration," *IEEE Trans. Electron Dev.*, **41**, 2357 (1994).
12. P. Boullion *et al.*, "Re-Examination of Indium Implantation for a Low Power 0.1 μ m Technology," *Tech. Dig. IEDM*, 1995, p. 897.
13. S.C. Williams *et al.*, "Scaling Trends for Device Performance and Reliability in Channel-Engineered NMOSFETs," *IEEE Trans. Electron Dev.*, **45**, January 1998, p. 254.
14. I. De and C.M. Osburn, "Impact of Super-Steep-Retrograde Channel Doping Profiles on the Performance of Scaled Devices," *IEEE Trans. Electron Dev.*, **46**, August 1999, p. 1711.

15. S. Venkatesan *et al.*, "Device Drive Current Degradation Observed with Retrograde Channel Profiles," *Tech. Dig. IEDM* 1995, p. 419.
16. M. Harlan and K. Petry, *Ion Implantation Technology*, 1998, June 22-26, Kyoto, Japan.
17. T. Ghani *et al.*, "100 nm Gate Length High Performance/Low Power CMOS Transistor Structure," *Tech. Dig. IEDM*, 1999, p. 415.
18. T. Mizuno, *IEEE Trans. Electron Dev.*, **47**, 756 (2000).
19. Ohguro *et al.*, "Undoped Epitaxial Si Channel in NMOSFET Grown by UHV-CVD with Preheating," *IEEE Trans. Electron Dev.*, **45**, March, 1998, p. 710.
20. International Technology Roadmap for Semiconductors, 2001 Edition, Semiconductor Industry Association, San Jose, CA.
21. K.K. Ng and W.T. Lynch, "Analysis of the Gate-Voltage-Dependent Series Resistance of MOSFETs," *IEEE Trans. Electron Dev.*, July 1986, p. 965.
22. G. Baccarani and G.A. Sai-Halasz, "Spreading Resistance in Submicron MOSFETs," *IEEE Electron Dev. Lett.*, **EDL-4**, 1983, p. 27.
23. W.C. Holton *et al.*, "Overview of Semiconductor Devices," Ch. 1 in *Handbook of Semiconductor Manufacturing Technology*, Y. Nishi and R. Doering, Eds., Marcel Dekker, New York, 2000, p. 1.
24. K. Miyano *et al.*, "Low Thermal Budget Elevated Source/Drain Technology Utilizing Novel Solid Phase Epitaxy and Selective Vapor Phase Etching," *Tech. Dig. IEDM* 2000, p. 433.
25. D.W. Duff and L.M. Rubin, "Ion Implant Equipment Challenges for 0.18 μm and Beyond," *Solid State Technology*, June 1998, p. 83.
26. T. Parrill *et al.*, "A New Era for High-Current, Low-Energy Ion Implantation," *Solid State Technology*, November 2000, p. 103.
27. H.J. Gossmann *et al.*, "Junctions for Deep-Sub-100-nm NMOS: How Far Will ion Implant Take Us?" *Symp. on Front End Processing at the Spring 2000 Meeting of the Materials Research Soc.*, April, 2000.
28. L. Peters, "Ramping the 0.13 μm Generation," *Semiconductor International*, January 2001, p. 56.
29. A. Agarwal *et al.*, "Reduction of Transient Diffusion from 1-5 keV Si^+ Ion Implantation Due to Surface Annihilation of Interstitials," *Appl. Phys. Letts.*, **71**, p. 3141 (1997).
30. A. Agarwal *et al.*, *Mat. Res. Soc. Symp. Proc.*, **568**, p. 19 (1999).
31. A. Agarwal *et al.*, "Ultra-Shallow Junction Formation Using Ion Implantation and Rapid Thermal Annealing: Physical and Practical Limits," *Abs. Mtg. Electrochem. Soc.*, Spring 2000, Abs. 526.
32. A. Agarwal *et al.*, "Ultra-Shallow Junctions by Ion Implantation and Rapid Thermal Annealing: Spike Anneals, Ramp-Rate Effects," *Mater. Res. Soc. Symp.*, **19** p. 568 (1999).

33. P.J. Timans *et al.*, "Rapid Thermal Processing," Ch. 9 in *Handbook of Semiconductor Manufacturing Technology*, Y. Nishi and R. Doering, Eds., Marcel Dekker, New York, 2000, pp. 201-86.
34. *Advances in Rapid Thermal and Integrated Processing*, F. Roozeboom Ed., Kluwer Academic Publishers, Dordrecht, NL, 1996.
35. R.B. Fair, *Rapid Thermal Processing*, Academic Press, San Diego, CA, 1993.
36. M.A. Foad and D. Jennings, "Formation of Ultra-Shallow Junctions by Ion Implantation and RTA," *Solid State Technology*, December 1998, p. 43.
37. A. Atanos *et al.*, "Susceptor-Based Rapid Thermal Processing for Ultra-Shallow Junctions," *Solid State Technology*, April 2000, p. 50.
38. M. Ameen and J. Hebb, "Implanter, RTP Systems Issues for Ultrashallow Junction Formation," *Solid State Technology*, September 2001, p. 77.
39. B. Yu *et al.*, "70-nm MOSFET with Ultra-Shallow, Abrupt, and Super-Doped S/D Extension Implanted by Laser Thermal Process (LTP)," *Tech. Dig. IEDM* 1999, p. 509.
40. S. Banerjee, "High Ramp Rate Thermal Annealing for Ultra-Shallow Junctions," *Abs. Mtg. Electrochem. Soc.*, Spring 2000, Abs. 521.
41. D.M. Camm and M. LeFrancois, "Spike Thermal Processing Using Arc Lamps," *Abs. Mtg. Electrochem. Soc.*, Spring 2000, Abs. 567.
42. S. Thompson *et al.*, "MOS Scaling: Transistor Challenges for the 21st Century," *Intel Technology Journal*, 3rd Quarter 1998.
43. C. Osburn *et al.*, "Design and Integration Considerations of End-of-the-Roadmap Ultrashallow Junctions," *J. Vac. Sci. Technol.* **B-18**, p. 338, 2000.
44. T. Ghani *et al.*, *Dig. Tech. Papers, Symp. VLSI Technol.* 2000,
45. M.I. Current *et al.*, "Process Integration Issues for Doping of Ultra-Shallow Doping Junctions," *J. Vac. Sci. Technol.* **B-18**, p. 468, 2000.
46. U. Jeong *et al.*, "Devices Dictate Control of Implant-Beam Incident Angle," *Solid State Technology*, October 2001, p. 79.
47. R.N. Kleiman *et al.*, *J. Vac. Sci. Technol.*, **B-18**, p. 2034 (2000).
48. H. Fukutome *et al.*, "Anomalous Diffusion in the Extension Region of Nanoscale MOSFETs," *Tech. Dig. IEDM*, 2001, p. 67.
49. T. Hori, "A 0.1 μm CMOS Technology with Tilt Implanted Punchthrough Stopper (TIPS)," *Tech. Dig. IEDM* 1994, p. 75.
50. M. Rodder *et al.*, "A Scaled 1.8 V, 0.18 μm Gate Length CMOS Technology: Device Design and Reliability Concerns," *Tech. Dig. IEDM* 1995, p. 415.
51. K. Miyashita *et al.*, "Optimized Halo Structure for 80-nm Physical Gate CMOS Technology with Indium and Antimony Highly Angled Ion Implantation," *Tech. Dig. IEDM* 1999, p. 645.
52. Y. Momiyama *et al.*, "Indium Tilted Channel Implantation Technology for 60 nm NMOSFET," *Dig. Tech. Papers, Symp. VLSI Technol.* 1999, p. 67.

53. Y. Taur, "25 nm CMOS Design Considerations," *Tech. Dig. IEDM*, 1998, p. 789.
54. T. Noda, "Modeling of End-of-Range (EOR) Defects for Channel Engineering," *Tech. Dig. IEDM*, 2001, p. 839.
55. T. Noda *et al.*, "Effects of End-of-Range Dislocation Loops on Transient-Enhanced Diffusion of Indium Implanted in Silicon," *J. Appl Phys.*, **88**, 4980 2000.
56. H.C.-H. Wang *et al.*, "Antimony Assisted Arsenic S/D Extension Engineering for Sub-0.1 μm NMOSFETs: A Novel Approach to Steep and Retrograde Indium Pocket Implants," *Tech. Dig. IEDM* 2001, p. 63.
57. S. Narasimha *et al.*, "High Performance Sub-40 nm CMOS Devices on SOI for the 70 nm Technology Node," *Tech. Dig. IEDM* 2001, p. 625.
58. R. Chau *et al.*, "A 50-nm Depleted Substrate CMOS Transistor (DST)," *Tech. Dig. IEDM*, 2001, p. 621.
59. M.I. Current *et al.*, "Ultrashallow Junctions or Ultrathin SOI?" *Solid State Technology*, September 2000, p. 66.

Chapter 6

ADVANCED LITHOGRAPHY I - PHOTORESISTS

Lithography is the most heavily used process technology for fabricating ICs. In 2002 some ULSI process flows use more than 20 mask levels. Thus, the entire lithography procedure is applied more than 20 times when fabricating many modern ICs. The semiconductor industry is also continuing to drive toward smaller feature sizes, and it relies on progress in lithography to help maintain this effort. Here many of the changes taking place in lithography processes in the 2001-2002 timeframe are discussed. While the basics of the lithography process are not presented in this text, such information can be found Vol. 1 (2nd Ed.) of *Silicon Processing for the VLSI Era*,¹ and elsewhere.^{2,3}

Figure 6-1 shows the lithography-scaling roadmap as it was envisioned in 1998.⁴ Not all of the predictions shown in this figure have come to pass (e.g., proximity-X-ray-lithography, predicted to be inserted into manufacturing by 2000, never got commercialized). Nevertheless, the data in the figure clearly indicates that many changes have occurred in lithography, and many more are occurring today. The purpose of this chapter (and Chap. 7) is to cover the changes depicted on the right-hand side of Fig. 6-1, including some that are not shown in this chart (e.g., 157-nm lithography, based on F₂-laser light-sources).

6.1 CHEMICALLY-AMPLIFIED DEEP-UV RESISTS FOR OPTICAL LITHOGRAPHY

As device dimensions were scaled to less than 1.0- μm , advances were occurring in both the DNQ/novolac resists and the lithography hardware. To achieve sub-wavelength resolution, advances in lithography were made (i.e., improvement in stepper optics and inspection techniques). Such progress allowed DNQ/novolac resists to continue to be used to fabricate device patterns in the sub-micron realm. Specifically, by using *i*-line illumination to replace *g*-line, by using *i*-line lenses with larger numerical aperture (NA) in the steppers, and by improving the novolac resin and DNQ materials, the resolution of *i*-line lithography kept being improved. Eventually, it became possible to print the features used in 0.35- μm CMOS technology with DNQ/novolac resists. Nevertheless, it was understood that new photoresists would be needed for the generations beyond 0.35- μm . Thus, a major industrial effort was launched in the early 1980's to develop photoresist systems for shorter wavelengths. This effort spanned about 10 years.




Fig. 6-1 Lithography Scaling Roadmap

6.1.1 248-nm DUV Photoresists

Eventually, by the early 1990s, when the $0.25\text{-}\mu\text{m}$ generation was reached (and used to make such ICs as 256-Mbit-DRAMs), it became clear that *i*-line lithography could no longer print $0.25\text{ }\mu\text{m}$ features (even when using such resolution-enhancement-techniques as phase-shift-masks and off-axis illumination). A shift from *i*-line to deep-UV illumination had to be made. Since both novolac resin and DNQ strongly absorb UV light at around 250 nm, DNQ/novolac resists cannot operate properly in the DUV region. Thus, the new resist chemistry developed during the 1980s (based on *chemical amplification* - CA) was adopted. This CA-chemistry also offered increased photospeed and contrast. Since CA-resists were compatible with DUV illumination, they became the resist materials of choice for advancing optical lithography toward higher resolution.⁵

In chemical amplification the important chemistry is not driven directly by the photons absorbed during the exposure step. Instead, the absorption of photon energy causes the decomposition of a *photoacid generator* (PAG). This causes a small amount of acid to be formed throughout the resist. (In early CA-resists such PAGs were *onium salts*.) This acid induces a cascade of chemical trans-

formations in the resist film, typically during the *post-exposure bake (PEB)* step. These transformations increase the solubility of the resist in the developer. Since the latter reactions are catalytic, the acid is regenerated after each chemical reaction. Thus, the same acid molecule can participate in further reactions. From 500-1000 chemical reactions can result from a single photon-absorption event. In summary, imaging in CA resists occurs in two steps: 1) acid generation during exposure; and 2) acid-catalyzed reactions during the PEB step.

This technology was pioneered by IBM in the early 1980s in an attempt to accommodate the low intensity of illumination produced by Hg-arc lamps at 248-nm wavelengths. Very fast resists were needed, and this led to the development of the CA reactions. Both positive- and negative-tone DUV-resists were developed. Details concerning the *chemical compositions* of these resists are described in Ref. 5. Information about the *chemical reactions* occurring during the various resist processing steps of 248-nm DUV-resists (i.e., exposure, PEB, and develop) can be found in Ref. 6.

One of the first commercially available CA-DUV-resists was a negative-tone resist (Shipley MEGAPOSIT SNR200). Its introduction allowed lithographic practitioners to gain experience with CA-resists and to witness first hand their high resolution capability. However, the SNR200-resist did not find widespread use because it is difficult to print contact holes with negative resists. Production-worthy positive-tone CA-DUV-resists soon followed, with the Shipley APEX-E resist being developed by the IBM/Shipley DUV-resist alliance. The IBM-developed CA-DUV resists have phenolic sites on poly hydroxystyrene (pHOST) which have been protected with t-butoxy-carbonate (t-BOC) groups. The IBM t-BOC resist works in positive-tone with aqueous developer, and alternately in negative-tone using an organic developer. Other major resist vendors now also offer CA-DUV-resists, including Clariant, Olin, JSR, and TOK. Positive-tone materials have become the preferred DUV resists. Some of the newer resists are compatible with TMAH developer and have been made more resistant to airborne contamination. Line/space patterns down to 165-nm, with a depth-of-focus (DOF) of 1.2- μm can be printed with such resists. Negative-tone CA-DUV-resists are also available, although not as many types are offered. Because of the improved aerial image of dark-field masks versus bright-field masks, the ability to print isolated-lines with negative resists is superior to that of positive resists. Thus, for some pattern types, negative resists are preferable. CA-DUV resists, however, are expensive. Their cost in 1998 was \$1500–\$2000 per gallon, which is about 2–3 times higher than DNQ/novolac resists. Future CA-DUV resist formulations are predicted to be even more costly.

6.1.1.1 Amine-Contamination of DUV CA Resists: While the biggest advantage of CA-resists is their high sensitivity (i.e., fast photospeed, in the range of 10–50 mJ/cm²), the catalytic nature of the CA process makes reproducibility a concern. If the catalytic chain of reactions is somehow interrupted, many of the lithographically important reactions will not occur, leading to catastrophic resist failure. That is, prior to post-exposure-bake (during which the photoacids perform the task of deprotection), these acids are susceptible to neutralization by bases.

The most common mechanism that quenches the catalytic reactions occurs as a result of *ambient contamination*.⁷ Specifically, the culprits are trace quantities (on the order of 10 ppb) of vapors of volatile base compounds (such as amines, ammonia, ammonium hydroxide, HMDS, or N-methylpyrrolidone [NMP - a common ingredient in strippers]). Such trace levels of amines in the ambient air can significantly affect the photochemistry because (as noted above) only a small quantity of photo-acid is produced by the exposure dose. If the ambient contains any of these contaminant vapors, the top surface of the resist will absorb them during the time that elapses between the exposure and post-exposure-bake (PEB) steps. These base molecules will then react with and neutralize the photo-generated acid. The surface region of the resist is now devoid of acid, and thus becomes less soluble than the acid-containing regions below. This less-soluble skin develops more slowly, resulting in the formation of a T-top structure (Fig. 6-2).




Fig. 6-2 (a) Environmental amine contamination of a chemically amplified resist, resulting in “T-top” formation after development.

This causes linewidth variations from wafer-to-wafer, as the extent of the skin formation is not controlled. In addition to airborne contamination, the acids also decay with time. Thus, any delay between exposure and PEB exacerbates the linewidth control problem. After PEB, resist susceptibility to amine contamination drops to negligible levels.

Let us elaborate on the problem of T-top formation. As noted above, the resist is most sensitive after the coated wafer is exposed in the exposure tool and transported back to the PEB/development tool, until the time it is baked (PEB). Typically the time delay between flash and post-exposure bake may be less than 3 minutes, depending on tool loading, but on occasion it may be 10 minutes or longer. A 10-minute pause can easily cause a linewidth variation on a wafer that may have just finished exposure but is not yet baked. If this event happens when a wafer is in an area where the amine contamination level has reached 5 ppb (or more), it is possible to cause a CD shift of as much as 10-20-nm. If the CD shift is great enough, changes in the resulting linewidth can cause the electrical characteristics and performance of the devices to change (possibly to the point where the device will not perform to specification and its speed or function is diminished). The length of time the wafers are exposed relative to the contamination concentration determines the potential risk to linewidth control. The effect of amine contamination on an example DUV resist is shown in Fig. 6-3 for three conditions: 1) no time delay between exposure and PEB; 2) 45-minute delay between exposure and PEB (with the wafer being held within the scanner enclosure, in which the amine concentration was about 1 ppb); and 3) 45-minute




Fig. 6-3 The effect of molecular bases on a DUV-resist is shown with: a) No delay between exposure and PEB; b) after a 45-min delay in the exposure tool; and c) after a 45-min delay in a cleanroom ambient.

delay between exposure and PEB (with the wafer being held in the cleanroom-ambient which has an ambient-amine-concentration of about 5-ppb). Significant T-topping occurs as a result of allowing the wafer to remain in the cleanroom-ambient for 45 minutes.

As shown above, the environmental contamination problem can be quite serious, as trace quantities of basic (i.e., as opposed to acidic) vapors are ubiquitous in the semiconductor fabrication ambient (typically in the 5-10-ppb range). Several methods have thus been established to combat this problem. The first involves filtration of the cleanroom air with activated charcoal. This was the practice first adopted by the industry when DUV-resists were initially being used, but it only reduces the nominal amine concentration in the cleanroom ambient to the 5-10-ppb range. (Environmental base contamination can also be neutralized and further reduced by adding weak acids to the filters.) More recently (as noted above), scanners and track systems (where the resist-coating, exposure, and development steps are performed) are housed in enclosures, and the air that enters these enclosures is purified with charcoal filtering and monitoring systems. Such airborne-amine-filtration and real-time monitoring systems are built by Extraction Systems (Franklin, MA) and other firms (see Figs. 6-4 and 6-5). According to the ITRS Roadmap, the total airborne contamination levels inside such DUV-lithography-enclosures must be kept below 1-ppb (molar) by such filtration systems as long as CA-resists are used. Another approach is to have the wafer track place the wafers in “safe holding” locations after exposure. Other ways to controlling this problem include: **a)** coating resist layers with a protective water-soluble transparent polymeric film (and removing this “sealing” film prior to development with a water rinse); **b)** incorporating stabilizing additives to the resist; and **c)** reducing the rate of absorption of contaminants by “densifying” the resists through annealing.

Nevertheless, even use of all of the above techniques is not completely effective in curing the problem of amine-poisoning of CA resists. Therefore, it is important that additional measures be employed to minimize the levels of amine in the cleanroom ambient. This is a challenging task since there are many potential sources of amines in a fab. Amine levels in wafer fab areas can easily exceed the nominal 10-ppb concentrations when small quantities of developer or adhesion promoters (HMDS) are spilled. (Note that HMDS application is an ammonia- producing process that therefore requires ample exhaustion to prevent




Fig. 6-4 Schematic of filtration units connected to photo-island clusters to avoid amine contamination of chemically amplified resists. Courtesy of Extraction Systems, Inc.

leakage into the track environment, causing amine levels within the track system enclosure to rise above 1-ppb.) Many paints, plastics, and epoxies also outgas amines. Materials that initially evolve large quantities of volatile bases, but quickly reach low-outgassing rates can be used in the fabrication of lithography tools. However, their use can be problematic in operating a wafer fab. Some materials continue to evolve amines over long periods of time and should not be used in wafer fabs, nor in the construction of lithography equipment.

6.1.1.2 Current State of 248-nm Resist Technology: Devices fabricated at 0.35- μm use a mixture of optical lithographies, including traditional *i*-line and 248-nm-DUV (the latter employing single-layer CA-resists). The conversion from *i*-line to 248-DUV was completed in the transition to 0.25- μm devices. The




Fig. 6-5 Cabinet-style chemical air filtration was added to the existing integrated filters to provide protection from possible spills and elevated room concentrations.

resolution limits for 248-nm resists continues to decrease. By adding such enhancements as phase-shifting-mask technology and/or more complex multi-layer resist schemes, the use of 248-nm-lithography is predicted to be extended to features as small as $0.13\text{-}\mu\text{m}$. In fact, some claim that positive resists for 248-nm can image down to $0.1\text{-}\mu\text{m}$ (100-nm) for isolated lines in logic applications, and 130-nm in dense arrays using the latest high-NA (0.8) scanners. (Smaller isolated lines can be imaged than can features in dense arrays because scattering-bar and OPC technologies are more readily applied to isolated structures.) However, at these critical dimension limits, it is very hard to maintain adequate process windows in a production environment and process optimization is engineering-intensive. The applications in which 248-nm will be pushed to 100-nm will therefore be very limited.

With manufacturers supplying fifth and sixth generations of 248-nm resist, these resist types are maturing rapidly. For example, their etch resistance is now comparable to *i*-line resists. The 248-nm resists are also optimized for specific challenges, resulting in resists for isolation layers, contact holes, metal lines, etc. Although such layer-specific resist specialization causes complexity in the fab line, it is mandatory in order to achieve sub-wavelength lithography.

TABLE 6-1 Linewidth Sensitivities of Commercially Available DUV KrF Resists

Resist	Supplier	Linewidth sensitivity (nm/°C)
Apex E	Shipley	16.0
UVIIHS	Shipley	7.5
UV6	Shipley	2.6
TM-461	JSR	2.6
DP-024	TOK	1.8
ARCH 2	Arch	~0

Another issue involving 248-nm DUV-resists is their sensitivity to post-exposure-bake temperature. The earliest commercially available 248-nm resists (e.g., APEX, from Shipley) exhibited large linewidth variations with fluctuations in the temperature of the PEB (16.00 nm/°C). However, as shown in Table 6-1, resist suppliers responded to industry requests to provide better linewidth control. (For example, Shipley later produced the UVII/HS resist - and thereafter the UV6 resist - which progressively improved this parameter.) However, these linewidth sensitivities have driven hot-plate specifications, since the resists with essentially no post-exposure linewidth-variation may not be universally applicable to all feature types, nor are they necessarily able to provide the best resolution.

In order to satisfy the extraordinarily tight linewidth-control requirements of today's and future processes, hot-plates must therefore exhibit excellent across-plate uniformity – significantly less than 0.5°C (range) – and must be matched to tighter levels. This is a challenge not only in terms of achieving the required capability, but it also poses a formidable metrology challenge. Resistance temperature detectors are the best available thermometers today. These are usually bonded to a silicon wafer, which is then placed on the hot plate. This placement is also difficult, since the wires must go between the wafer and the measurement electronics.

As noted above, printing isolated lines is easier than printing nested features. Consequently, contact-hole layers have rapidly become the ones that are most difficult to image (and may be the first to transfer to 193-nm). One example of how layer-specific resist specialization is being used to tackle the contact layer imaging problem is the so-called *RELACS* process.⁸ That is, this is a process developed by Mitsubishi Electronic Corp. for shrinking KrF-imaged via holes




Fig. 6-6 Process flow of RELACS.⁸ (© IEEE 1998)

from $0.2\text{-}\mu\text{m}$ to $0.1\text{-}\mu\text{m}$ using a coat, diffusion-bake-and-rinse sequence, following resist-exposure and develop. That is, after the coating step, acid from the unexposed resist diffuses into the wall of the via hole covered by the coating – and then into the coating material – during the bake step. The coating material is crosslinked by this acid (see Figs. 6-6 and 6-7). After a rinse step, some of the coating material remains behind, thereby causing the opening size of the via to shrink. Clariant AZ has licensed the materials from Mitsubishi (R200 coating and R2 developer) and commercializes the process as RELACS (Resist Enhancement Lithography Assisted by Chemical Shrink).

Once the performance of single-layer 248-nm DUV-photoresists based on pHOST chemistries becomes exhausted, bilayer-resists may be adopted to extend the 248-nm-based lithography process. Bilayer processes decouple requirements for imaging, performed by the thin (200-nm thick, or less) top resist, from needs




Fig. 6-7 The RELACS process shrinks these KrF-imaged $0.22\text{ }\mu\text{m}$ contact holes (left) to $0.11\text{ }\mu\text{m}$ (right) using a coat, diffusion bake, and rinse step after wafer patterning. (Courtesy of Clariant AZ)

for etch resistance, managed by the thick (400-1000-nm thick) bottom resist. The top layer uses standard single-layer resist imaging, and the image is transferred down anisotropically using O_2/SO_2 plasma etching. The bottom layer acts as an anti-reflecting coating (ARC), reducing the pattern-width degradation from underlying topography. Importantly, bilayer-image performance tends to be more limited by the capability of the scanner. At least one bilayer approach has been implemented in manufacturing. The CARL (chemically amplified resist lines) developed by Infineon Technologies, is being evaluated at 248-nm and 193-nm. (See Vol. 1, 2nd Ed. for more details on the CARL process.)

Another bilayer approach is being proposed for dual-damascene patterning with 248-nm lithography. Arch Chemical offers a thin imaging system (TIS-2000[®]) optimized for dual-damascene patterning. The top resist layer provides patterning and the bottom organic-layer acts as the BARC, while also planarizing via layers for trench imaging in a via-first approach (Fig. 6-8, see also Sect. 15.9.1.5).⁹ One advantage to this process is its dual use at 248-nm and 193-nm.

6.1.2 193-nm DUV Photoresists

The insertion point for 193-nm lithography is predicted to be the second-generation 0.13- μm or even 0.10- μm devices (late in 2002 or early 2003). Successful extension of 248-nm resist is stalling the 193-nm transition. In addition, the compressed timeline for arriving at the 0.13- μm node on the SIA Roadmaps is also part of the reason. That is, if there were four years allowed for developing the 0.13- μm technology, then 193-nm lithography would have a good chance of being accepted into manufacturing from the beginning of that technol-



Fig. 6-8 In the via-first damascene approach, the underlayer resist serves the purposes of planarization, BARC and uniform via fill to protect the via bottom during the trench etch. (Courtesy Arch Chemicals and IMEC)

ogy node. But, since there is not that amount of time, there is more of an emphasis being placed on extending 248-nm lithography.

At 0.13- μm there is substantial benefit to transferring to 193-nm using standard binary reticles, rather than using 248-nm and enhancing the reticles with RET. However, the decision to make this transition will depend on the maturity of 193-nm resist materials and the performance of 193-nm exposure tools with very high NA (i.e. > 0.68).¹⁰ In addition, at the 0.13- μm node, economics (rather than technology) may influence the insertion point of 193-nm lithography. That is, some customers (who manufacture a large number of parts from a single mask set) may try to extend the use of 248-nm lithography by any means possible, including the route of using more expensive reticles. Others (such as foundries, which on the average, run fewer wafers per mask) may prefer the ‘simpler’ approach of driving to a shorter (193-nm) wavelength. It is estimated that possibly 10 mask levels will require the new systems (enhanced-248-nm or 193-nm). Critical masks will include gate, active area, contact, first metal and first via..

One of the most significant aspects of 193-nm resist development is that after nearly a decade of R&D (primarily performed empirically, due to the complexity of reactions within the resist), a single superior polymer backbone material has not yet been identified (even though the insertion point of 193-nm lithography is drawing closer). That is, no single polymer platform material seems to be able to provide the best process for every application. Instead, there are three seemingly-viable resist polymer types, each exhibiting some benefits – but none of which have all the benefits needed to be used across all production lines. What is predicted to occur is that users will select different chemistry platforms for different applications.

That is, despite the fact that process engineers prefer one resist/one supplier, at 193-nm there are three useful polymer platforms: 1) *acrylates* (acrylate platforms with attached ali-cyclic structures); 2) *pure cyclic olefins*; and 3) *cyclic olefin/maleic anhydrides (COMAs)*.¹⁰ (These are all also different than the hydroxy-styrene-based resists used for 248-nm lithography.) The acrylates for example, reportedly provide the best dense-line performance (particularly with the adamantane methylacrylate chemistry developed by Fujitsu), but they generally exhibit poor etch-resistance. On the other hand, the cyclic-olefin polymers offer better etch—resistance. IBM (in collaboration with Arch Chemicals) is pursuing this group of materials (which reportedly show intrinsically higher robustness toward fairly harsh etch steps). Finally, Clariant AZ licensed a free-radical copolymer of functionalized cyclo-olefins and maleic anhydride from Hyundai. This polymer appears to be very cost-effective and may

migrate back into 248-nm to reduce resist cost.

The partial benefits that each polymer offers has caused resist suppliers to pursue multiple platforms for 193-nm resists. That is, by 2000 many resist suppliers were working on two or three of these different polymer families (whereas in 1997 each 193-nm resist-supplier had its own, single platform). In addition, a lithography consortium headed by IMEC has been established to evaluate various 193-nm resists from Arch Chemical, Clariant, JSR, and Shipley on a common lithography tool (the ASML 5500/900 scanner with integrated TEL track). This will simplify comparisons of resists whose performance is often measured under different conditions. By 1999 several promising 193-nm resists were emerging (although at that time they still remained 1-2 years from being production worthy). Nevertheless, using a single-layer 193-nm resist, a 0.6-NA scanner and alternating phase-shift mask, 70-nm gates could be patterned (Fig. 6-9).²¹

Beyond selecting the most appropriate polymer platform, resist chemists are charged with finding the photoacid generator (PAG) best able to deliver strong dissolution inhibition, high photospeeds, thermal stability, and tailorable photoacid size (the last factor correlates strongly to imaging performance).

6.1.2.1 Problems of 193-nm Resists: As noted above, the 193-nm photoresist will need to be selected by chip manufacturers in 2001-2002 to begin developing 193-nm lithographic processes. Together with the issues of selecting resists based on their polymer platform, a set of other resist performance characteristics also needs to be considered. We discuss those issues here.




Fig. 6-9 70-nm gates patterned with 193-nm resist and alternating phase-shift mask. Courtesy of Semiconductor International.²¹

The *primary performance factors* involving the still-immature 193-nm resists are those involving process latitude, namely: exposure-latitude and DOF (i.e., an exposure latitude of ~20% and a DOF of 0.5- μ m are needed at 193-nm). There are also numerous *secondary performance characteristics* including: etch-resistance; degree of linewidth variation with fluctuation in post-exposure-bake temperature; line-edge-roughness; resist-collapse; resist adhesion (lifting); resist shrinkage during irradiation with e-beams during CD inspection; and resist outgassing.

Etch resistance becomes more critical for 193-nm resists because thinner resist layers will have to be used than in previous lithography generations. Resist thickness is expected to be reduced to 400-600 nm in 193-nm (down from about 1000-nm in prior generations of lithography). The advances in etcher design and the use of high-density-plasma systems are helping to improve 193-nm resist thinning during etch steps. However, in cases of insufficient dry-etch-resistance, use of a hard-mask instead of resist-masking may need to be considered.

The *degree of linewidth-variation* in the face of post-exposure-bake temperature-fluctuation is another inherent problem of the immature 193-nm resists. By 2001 193-nm resists exhibited linewidth variations of 10 nm/°C, which is significantly higher than that exhibited by the latest generation of 248-nm resist at that time (see Sect. 6.1.1). But, the same situation existed when the early 248-nm resists were first released. The target value for 193-nm is 3 nm/°C.

Line-edge-roughness is much more pronounced at 193-nm than at 248-nm. Complex interactions occur between lithographic performance, line-edge roughness, and etch-resistance. Resist chemists are seeking the right compromise. Some researchers claim that line-edge-roughness (LER) can be reduced to the 5-7-nm range. The effect of LER on device performance is still being quantified.

Resist-collapse becomes a major issue as the resist features are brought closer together. That is, as developer and rinse water are being removed from developed wafers, surface-tension forces cause closely-spaced adjacent lines to be pulled together (Fig. 6-10). This phenomenon limits the aspect-ratio of resist features (another reason why resist films have smaller thicknesses as features are scaled). Resist-collapse becomes common when resist-feature aspect-ratios exceed about 4:1. There is some concern that resist-collapse may be one factor that could delay the deployment of 193-nm lithography.

The immature 193-nm resists are also prone to *lifting* since their formulations are not yet optimized for adhesion (as are those of *i*-line and 248-nm resists). Adhesion can be optimized with respect to wafer-temperature and HMDS-delivery for each resist type. Lifting can also be addressed by reducing the resist thickness. Using a multilayer resist is another potential remedy for resist-lifting.




Fig. 6-10 Closely spaced, high-aspect-ratio lines of resist that have collapsed after development.

The 193-nm resists also exhibit significant *shrinkage* (both in the vertical and lateral directions) when they are irradiated by electron beams (as occurs when CD inspections are performed using an SEM). Such resist shrinkage was also observed in early 248-nm resist, but modified resist formulations helped to overcome that problem.¹¹ Some 193-nm resists exhibit more shrinkage than others, but the tradeoff is that those that have better shrinkage behavior tend to have worse photospeeds and are more prone to resist collapse. Additional work is needed to make 193-nm resists able to meet all of these needs.

Another significant problem with 193-nm resists is that they *outgas organic compounds* that can then build up on scanner optics. This issue may be addressed by PAG selection or by using various additives. Aromatic fragments such as the iodobenzene liberated by iodonium salt sensitizers are among the most critical outgassing species. While the outgassing problem is evident with 248-nm systems as well, the working distance between the lenses and resist at 193-nm is shorter, and the adsorption of vapors is greater at shorter wavelengths. Thus, it is predicted that the outgassing problem will further increase for 157-nm systems.

6.1.3 157-nm DUV Photoresists

The existing deep-UV lithographic technologies and associated optical extensions combined with early 193-nm-based systems are expected to provide sufficient resolution to allow them to be used for the 130-nm device generation outlined in the 1999 SIA Roadmap. However, extension of optical lithography

beyond that point may require that 157-nm DUV-illumination systems be adopted by 2005. If this time-schedule is to be met, the first pilot-line quantities of 157-nm resist will need to be delivered to SEMATECH by the first-half of 2002 to begin process development efforts toward the 100-nm device node. Volume production capability using 157-nm illumination systems should be then become available by the 1st quarter of 2005.¹²

The question of “Will 157-nm lithography be ready by 2005?” was debated at the SPIE Microlithography Conference in March 2001. However, there was no consensus as to whether the schedule will (or even, should) be met. Nevertheless, considering that the development cycle for 248-nm DUV resist materials spanned at least 10 years (1980-1990), and the 193-nm resist development program was approximately 8 years long (1991-1999), the 157-nm resist development efforts are faced with a much more abbreviated and challenging development schedule. In addition, the cost of developing a 157-nm resist is also expected to be very high (estimated to be \$50-60M). Since such a financial burden is not feasible for any single company, the International SEMATECH formed a University-based consortium to perform fundamental research on 157-nm resists. Just as significantly, IMEC and ASML have begun a cooperative 157-nm lithography development effort, with funding support from many top device manufacturers, including AMD, Infineon, Intel, Micron, Philips, Samsung, ST Microelectronics, and UMC. The First International Symposium on 157-nm Lithography (sponsored by 43 companies), was held in Dana Point, CA in May 2000, and the Second Symposium was held in the same location in May 2001. In any case, researchers are confident that the industry will design workable resists for 157-nm lithography, but they are less sure that they will be able to do it by the 2003 deadline (i.e., set by the possibility that this will be time at which it will be necessary to pattern critical levels in the 70-nm device generation).

The biggest difficulty facing 157-nm lithography is that the illuminating radiation consists of such high-energy photons (7.9 eV). Most polymers used to make up the backbone of previous generation resists strongly absorb such high-energy photons. Thus, it is difficult to find polymers for 157-nm resists that have sufficient transparency (as well as adequate etch resistance, and good adhesion to substrates). Fortunately, however, two promising candidates for the *backbone* (or *platform*) polymers in 157-nm resists have been identified: 1) highly fluorinated hydrocarbons (fluoropolymers based on norbornane); and 2) silicon-based siloxanes. A key challenge to developing 157-nm resists based on the latter group of materials (siloxanes) is the ability to achieve a sufficiently high glass-transition temperature.

Fundamentally, the design of materials for developing 157-nm resists is identical to that used to develop resists for the previous DUV lithographic generations. That is, the materials must satisfy the following set of requirements common to all CA-photoresist materials: **1)** high transparency at the exposure wavelengths; **2)** sufficient resistance to plasma-etching processes; and **3)** functional units that are capable of undergoing efficient photochemical transformations that change their solubility in developer solutions. For positive-tone resists, this is typically accomplished by designing the matrix-resin (backbone material) with an acidic functionality that is masked by an acid labile protecting group. Strong acids generated within the exposed regions of the photoresist-film catalyze the thermolysis of the protecting groups, rendering these regions soluble in the aqueous-base-developer solutions. The resists should also have glass-transition-temperatures higher than the processing temperatures, acceptable shelf-storage lifetime, and minimum toxicological risk. A single-layer-photoresist process for imaging at 157-nm is also clearly preferred over a multilayer-resist approach.

When attempting to develop the next-generation of resists, it is often convenient to adopt a modular approach for the design of new photoresist materials. This allows the polymer design to be broken down into several functional sub-units that may be addressed in a somewhat independent fashion (Fig. 6-11).



Fig. 6-11 A modular approach in the design of new photoresist materials provides flexibility in design, but transparency among all subunits must be maintained.

Since the 248-nm and 193-nm resist materials are too-absorbing at 157-nm, and since the 157-nm resists were still in their earliest stages of development in 2001, a two-pronged approach was chosen to develop the technology of 157-nm lithography. The first prong involved using existing resists, but at a greatly reduced thickness (60-70-nm-thick). This provides a pathway for tool-testing and for developing early baseline-processes. The second-prong pursues development of the 157-nm resist itself (i.e., exploring the use of novel polymers - such as the fluorinated variations of the resins used in 248-nm resists). In these research efforts, attempts are also made to optimize the formulations and imaging conditions required to print sub-100-nm features. This is a complex task, since it is necessary to explore a variable space that includes the photoacid-generator, base, dissolution-inhibitor, base-polymer, exposure, bake, and development. Figure 6-12 shows some preliminary results of 70-100-nm-features printed using early formulations of 157-nm resists that have evolved from that development effort. Imaging is performed at 0.6-NA, 50-mJ/cm², with an alternating phase-shift-mask, using 148-nm-thick resist on a 70-nm antireflective-layer (DUV30), followed by a 60-sec 140°C PAB, a 90-sec 130°C PEB, and development for 20-sec in a 0.26-N TMAH developer. A good image quality is obtained, with sidewall angles between 85-89°.

Beyond having to meet the performance requirements for reduced line-edge-roughness, fast-photospeed, dry-etch-resistance, and solubility in aqueous-base - developer, 157-nm resists have a strong tendency to outgas materials, which settle on the lens. At 157-nm, even a monolayer of oxygen or water can significantly change the transmission of light through the lens and even attenuate light. Fluorocarbons are less of a concern than silicon dioxide, because the user can bleed oxygen into the system with the laser on, making the fluorocarbon residues volatile. With siloxanes, however, SiO₂ deposits are more difficult to remove. Attention to designing effective gas (nitrogen) flows between the wafers and lenses in 157-nm lithography tools will help combat this problem.

6.2 ANTI-REFLECTIVE COATINGS (ARCs)

Interference effects caused by the reflection of light that is transmitted through the photoresist and reflected off the substrate and back, can interfere with incoming light and cause the resist to be unevenly exposed. (See Vol. 1, 2nd Ed., p. 517-24 for a discussion of such effects.) Instead of reducing such interference effects through the modification of the resist itself (as also discussed in Vol. 1), methods that reduce reflectivity at resist interfaces can provide linewidth control with minimal loss of resist performance. That is, to dampen these reflections,

anti-reflective coatings (ARCs) can be used.¹³ By minimizing standing waves and reflective notching from substrate reflections, ARCs provide improved resolution and better CD control.

ARCs suppress the reflections either by: 1) *attenuating light* that passes through the ARC or; 2) by *matching the index of refraction* of the ARC to the resist-system at the exposure-wavelength employed (such that destructive interference of the light passing through the ARC occurs). These layers can be deposited either on top of resist layers (forming a *Top AR coating* or *TAR*), or on the surface of the wafer beneath the resist (to form a *Bottom AR Coating* or *BARC*). For 0.25- μm lithography (and below), BARCs must be able to suppress more than 99% of the substrate-reflected-light to provide sufficient CD control. Although it significantly increases the process complexity, use of *both* a BARC and a TAR have been reported for layers that require the tightest CD control (i.e., poly gate patterning).

Bottom anti-reflective coatings are materials applied between the substrate and the resist. They are used extensively in applications such as gate definition and for opening contacts, where it is important to keep tight control over critical dimensions. They are not used much at the interconnect level, since the layer of TiN typically used to control electromigration and prevent hillocking on aluminum lines has the extra benefit of being a good anti-reflective coating. As the industry goes to shorter wavelengths, the challenges of minimizing reflections increase. That is, the reflectivity of the substrate becomes higher with




Fig. 6-12 Using 157-nm exposures, phase-shift masks, and 148-nm thick resist on a 70-nm AR layer, various resist recipes resolve at linewidths of: a) and b) 80 nm; c) 100 nm; and d) 70 nm.




Fig. 6-13 Reflectivity is a function of film thickness, refractive index (n) and extinction coefficient (κ).

decreasing wavelength, and thus interference problems also become more severe. At the same time, advances such as phase-shift-masks, off-axis-illumination, and optical-proximity-correction have allowed features to be printed that are smaller than the wavelength of light. This has made the elimination of CD variations caused by reflected light to be even more critical.

BARCs reduce the problems involving reflectivity by decreasing the value of the reflection coefficient of the resist-substrate interface. They can accomplish this in two ways. First, the BARC may absorb the incident light that manages to penetrate to the bottom of the resist (*absorption*). This requires that a material with a high extinction-coefficient κ be chosen for the BARC, and/or that a thick BARC layer be used. Unfortunately, if the value of κ is too high, the reflectivity of the resist/BARC interface increases – which degrades the effectiveness of the BARC. Thus, useful values of κ are typically in the range of $0.22 \leq \kappa \leq 0.5$ in order to maintain reflectance back into the resist below 10%. For processes that used *i*-line resist, a fairly thick BARC-layer was used (60-90-nm thick, see Fig. 6-13).¹³ But DUV-lithography mandates the use of thinner resist and BARC layers because of decreased depth of focus. One of the major challenges for BARCs is maintaining a small enough reflectivity as the BARCs get thinner with decreasing feature size (see also Fig. 6-13).

Thus, a second approach which decreases the value of the reflection coefficient of the resist-substrate interface is favored for 0.25- μm lithography (and smaller). That is, a BARC material whose index of refraction and thickness match the incident light wavelength is sought (*index-matching*). To implement index-matching, a structure is formed that has an optical-path-length of $\lambda/4$ for the wavelength of light being employed. Such a $\lambda/4$ -optical-path-length will exist in a thin film (the BARC) made of a material having the correct index-of-refraction and thickness (in the range of 50-80-nm). Light strikes the BARC/resist interface, and some is reflected back toward the air/resist interface, but the remainder enters the BARC.

The light entering the index-matched BARC layer will pass through the BARC layer twice (i.e., once after reflecting from the BARC/substrate interface). These two passes through a quarter-wavelength optical-path-length will produce a light wave with a half-wavelength phase-shift directed toward the resist/BARC interface. This phase-shifted wave interferes destructively with the part of the light originally reflected from the BARC/resist interface. Thus, reflectivity at this interface is decreased. Complete destructive interference only occurs if the amplitude values of the interfering waves are identical. Tight control of BARC thickness (to ensure the two-pass optical-path-length is exactly $\lambda/2$) is an obvious requirement for index-matching by the BARC layer. If thicker BARCs can be tolerated, further reduction in reflectivity will occur by making the index-matching BARC thicker (i.e., to a two-pass optical-path-length of $3\lambda/2$).

In fact, all BARCs employ some of both the absorber and index-matching mechanisms. In any case, if the BARC is effective, little of the light incident on the resist/BARC interface is reflected back toward the resist/air interface, and as a result, the *clearing-dose swing ratio* (see Vol. 1, 2nd Ed., p. 522) is smaller. Standing-wave-effects are reduced because the smaller amplitude of the reflected light decreases the standing wave intensity. Since less light scatters off the bottom surface, the severity of notching is also mitigated. BARCs thus compensate for variations in wafer topography, substrate reflectivity, and surface characteristics. One price paid for these benefits is increased process complexity (and, of course, increased process costs, in terms of equipment and materials). For example, a separate process may be needed to remove the BARC edge-bead. Another issue which arises when BARCs are employed is that their use may also significantly extinguish the light signals that come from alignment marks (these signals arise from the scattering of light from the mark). A variety of deposition techniques have been used to deposit BARCs including spin-on, PVD, and CVD processes.

6.2.1 Organic BARCs

Spin-on organic BARCs are primarily absorber-type polymer films that contain highly absorbing dyes (introduced into the polymer at concentration levels that deliver appropriate extinction-coefficient values). They must also be non-bleaching at the exposure wavelength. Such *organic BARCs* are applied directly to the substrate to a thickness in the range of 60-120-nm. The resist is then spun on top of the BARC, using conventional track equipment. Suppliers of organic spin-on BARCs include Brewer Science, Clariant, Shipley, Hitachi, and Tokyo Ohka. Proponents of the organic approach point out that organic BARCs are advantageous in terms of cost-of-ownership, refractive-index-reproducibility, planarization-capability, film-thickness-tolerance, rework-capability, and surface-control.

Early organic BARCs were about 200-nm-thick, and were wet-etched (in a step often called “ARC open”). Since wet etching is an isotropic-removal process, the resulting undercutting of the BARC layers made them unsuitable for optical lithography smaller than 0.5- μm . Newer organic BARCs are designed to be developed by an anisotropic dry-development process using an oxygen plasma. This extends their use to DUV lithography. However, the self-planarizing nature of spin-on films does not make the dry-developing process a complete solution to the above undercutting problem. That is, when spun-on over topography, some regions of the BARC will be thicker than others, and this causes a problem when organic BARCs are dry-developed. An anisotropic dry-etch-step can be used to etch the BARC in the flat areas of the wafer, and while this may erode some of the resist thickness, it should not attack the resist laterally. However, the thicker residual-BARC-regions must still be removed, and this may be done with a second, isotropic over-etch-step. The isotropic BARC removal process will also laterally attack the resist feature, and this can give rise to linewidth-control problems. ARC-open may be carried out in a separate etch chamber prior to the oxide, metal, or poly etch, or the ARC may be etched *in-situ* prior to the film being etched. Using a separate chamber approach leads to a larger COO penalty. Hence, dry-etch-tool vendors (such as Lam Research), offer *in-situ* ARC-open processes integrated with the etch process of all film types (Al, W, poly, and oxide). Organic BARCs are typically etched with O_2 chemistries (together with appropriate additives such as Ar, He, and CF_4).

Another issue involving organic BARCs is their (in)compatibility with chemically-amplified (CA) resists. That is, the acidity levels of organic BARCs can negatively interact with CA resists (resulting in acidic or basic by-products being formed during thermal hardening of the resist). These by-products can

create an intermixing layer at the BARC/resist interface. Such intermixing must not be allowed to occur. Researchers have developed organic BARCs for KrF and ArF resists that have chromophore and cross-linkable functional groups in the same copolymer form as the photoresist to avoid this problem.¹⁴ The key difficulty of implementing the solution of closely matching the chemistry of the organic BARC to that of 197-nm resist is that by 2001 there was not yet a mature 197-nm resist. Until a baseline product is chosen, it will be hard to closely match the organic BARC and resist. Only when the industry standardizes to one or two 197-nm resists, will it be possible to apply this solution successfully.

A manufacturing-related challenge of using organic BARCs is caused by the fact that the liquid, spin-on BARC materials coat spinning bowls and coagulate in drain lines. A new material introduced by Nissan Chemicals (DUV44) reportedly uses 70% less catalyst, which results in less spin-bowl coagulation. It retains the optical properties of its predecessors so that there is minimal process variation with respect to depth of focus or exposure latitude.

6.2.2 Inorganic Dielectric BARCs

Inorganic dielectric BARCs are deposited by PECVD. These are typically films of silicon oxynitride (SiON) or silicon nitride (SiN) that function both as index-matching and absorbing BARCs. The thickness, index-of-refraction, and extinction-coefficient of such silicon-oxynitride layers can be tuned to produce an effective BARC layer. The inorganic-CVD-BARCs are thinner (30-50-nm-thick) than the organic BARC layers. These layers also conformally coat the underlying topography as a result of the CVD process. This allows the entire film to have the correct thickness (i.e., the film does not self-planarize). Inorganic BARCs have chemistries similar to the underlying layers, which can make it tricky to remove them after resist-stripping. Thus, some processes leave the inorganic BARC material in place. On the other hand, inorganic BARCs can have a much higher selectivity to the material being etched (e.g., poly-Si or Al) than can organic BARCs (or the photoresist itself). Consequently, the “ARC open” step is not as much of an issue as when an organic BARC is used. In fact, in some processes that use inorganic BARCs, no separate ARC-open step is used. A smaller overetch time is also needed to clear the BARC all over the wafer and large feature sizes than for organic BARC clearing. Dedicated production tools for depositing inorganic BARCs have been developed by such suppliers as Applied Materials and Novellus Systems.

For 193-nm lithography, the composition of the inorganic SiON films must be altered, since most silicon-based inorganic materials are opaque to 193-nm light.

The BARC films for 193-nm lithography will have to change from SiON films (which are silicon-rich films, where 40+% of the film composition is silicon) to films that are much more like an oxide. However, the PECVD process allows such tuning of the composition of silicon, oxygen, and nitrogen of the film over a relatively wide range. By adjusting the CVD process conditions, the BARC film can be tuned to be suitable for *i*-line lithography, 248-nm lithography, or 193-nm lithography.

Inorganic BARCs can cause adverse reactions between the ARC film and the photoresist (akin to the problems that can occur when organic BARCs are used). The culprits are again amine groups (NH_3) that are left on the surface of the SiON films after processing. Deep-UV resists are more sensitive to such interactions than older *i*-line and *g*-line resists. One technique to avoid this interaction is to *in-situ*-deposit a thin oxide on top of the BARC before spinning-on the resist. This oxide becomes an inert barrier between the resist and BARC and has no impact on the properties of the BARC itself. Another way of preventing such interaction is to use an oxygen treatment after the SiON film has been deposited, but before putting down the resist. This effectively removes any amine groups from the BARC surface. The Novellus PEARL[®] (Plasma-Enhanced Anti-Reflective Layer) includes an *in-situ* nitrous-oxide treatment before the wafer is taken out of the deposition chamber.

6.2.3 PVD-Deposited ARCs

The most common PVD-deposited ARCs are TiN films. TiN films act primarily as absorber-type BARCs, with TiN having a κ -value of 1.1. Their main application is for patterning Al films with *i*-line lithography. Because TiN ARCs are difficult to remove, they are normally left behind and become part of the device (where they may serve in the role of a diffusion barrier). TiN films are reactively sputter-deposited to a thickness of ~80-nm for this purpose. Their use in DUV-lithography is limited by their high-DUV reflectivity (20–30%).

6.2.4 BARCs for Dual-Damascene Applications

When BARCs need to be used with dual-damascene, low-*k*/copper interconnect systems, another set of complex challenges are encountered. The biggest obstacle is patterning transparent dielectric layers (in which the trenches and via holes of the damascene structures must be etched). These dielectric layers may lie over the rough topography of a reflective film such as copper or polysilicon. Unlike the case of applying a BARC directly onto a reflective layer (such as a poly or Al film), in this situation the intermetal dielectric is transparent. Below it are all

kinds of reflective surfaces, at multiple levels. This makes the conventional method of controlling reflection by destructive interference inadequate. That is, a reflection minimized for one local film stack may result in a high reflection for another local film stack. To solve the problem, multilayer ARCs, termed *universal ARLs (UARLs)* are deposited on the dielectric to be patterned (Fig. 6-14). Either two-layers (or sometimes even three layers) are used to create such structures. The bottom layer is opaque to UV light (and reflective), to mask the underlying oxide, while the upper layer cancels out the reflected light by destructive interference. The underlying layer has a higher index of refraction and extinction coefficient so that it is more reflective than absorbing (in the same way that poly and aluminum films behave). Such UARLs are deposited by CVD, in tools from vendors including Novellus Systems and Applied Materials. The UARL formed in the Applied Materials process is termed *Double-DARC*.[®] Note that the third layer shown in Fig. 6-14 is an oxide film to prevent chemical interaction between the first two BARC layers and the DUV resist.

6.3 PHOTORESIST PROCESSING SYSTEMS

In the early days of IC fabrication the pieces of equipment that performed the individual resist-processing steps were stand-alone tools. As each step was




Fig. 6-14 a) Conformal BARC; b) Planar BARC; c) three-layer universal AR layer (UARL).




Fig. 6-15 DUV Photo-island.

completed, the wafers would be manually carried from one tool to the next. By about 1990, these tools were integrated into resist-processing systems that automatically moved the wafers from one tool to another without human intervention. Such systems are now configured as either wafer tracks or wafer clusters. In either case, such resist-processing systems are then linked to a stepper to form an integrated stepper-track/photo-island (Fig. 6-15).¹⁵ A cassette of wafers is loaded onto the input station of the photo-island, and 30–60 minutes later they emerge as patterned wafers, ready to be sent to the next process (e.g., ion-implantation or etching).

Wafer tracks originally consisted of two side-by-side lines of resist processing tools (i.e., the prime, spin, and soft-bake modules on the line that fed the stepper, and the PEB, develop, and hard-bake modules on the other). The wafers were transferred sequentially from one module to the next using a belt transport mechanism. In today's *track systems*, the individual tools are still arranged in two lines, but a central robotic transfer shuttle moves the wafers from one tool to another, offering the capability to randomly access the tools (Fig. 6-16). In *wafer clusters* the individual resist-processing tools are arranged in a circular fashion around a central robot that moves the wafers among the tools, again allowing flexible access to each of the process stations.^{16,17} The wafer-cluster-system approach was pioneered by Texas Instruments in the mid-1980's and was introduced commercially by FSI in 1991. It has an anthropomorphic, 6-axis




Fig. 6-16 Clean Track ACT platform.[®] Courtesy of Tokyo Electron America.

wafer-handling system that provides more reach and fewer, larger robots per cluster. SVG's ProCell wafer-cluster system offers a hexagonal platform (Fig. 6-17). Wafers follow a circular path from process module to coating, stepper interface, develop cell, and back to the cassette interface. By scheduling processes with more than 40 wafers simultaneously with varying positions, time requirements and sequencing, the lithography process can be completed in 12 balanced moves. This is done with a patented synchronous scheduling algorithm called *advanced guidance system* (AGS), which controls wafer movement by calculating the optimal wafer path before movement is initiated. System-induced delays are minimized through time management that automatically builds-in scheduled intervals at user-defined non-critical steps, allowing consistent process timing.

The stepper-track (or stepper-cluster) photo-islands are among the most complex systems in a wafer fab. They may consist of up to 20 individual process tools (besides the stepper) that must all work together. At any one moment, the track may be transferring 15-20 wafers through multi-process levels, putting resist on some, developing some, and baking or chilling others. In addition to handling more wafers, the newer lithography processes require the track to perform more steps per wafer. These additional steps include: edge-bead removal,




Fig. 6-17 Pro-Cell cluster.[®] Courtesy of Silicon Valley Group.

applying anti-reflective layers, and processing multi-layer resists. Track systems must also ensure that each wafer (and each lot) has a consistent photoresist coating. The largest manufacturers of such track and cluster systems are Tokyo Electron Ltd., Dainippon Screen, FSI International, and Silicon Valley Group (roughly in that order). We will now describe some of the issues associated with the functioning of photo-islands.²⁰ They include: capacity, flexibility, reliability, cost of ownership, and environmental/safety features.

The *capacity* of the wafer track is one of its most important characteristics. Advanced wafer stepper/scanners are both fast and expensive (\$5M to \$10M). To get maximum use from the stepper/scanner, the track must be able to supply wafers as quickly as the stepper can accept them. By 2001, some stepper/scanner throughputs exceeded 100 wafers/hour (200-mm). The wafer track thus requires multiple tools for each process to keep up. For example, as many as six spinners may be needed to support one stepper.

Another critical feature is *flexibility*. The track system must be capable of being modified to meet not only today's, but also tomorrow's needs. It should be possible to add, upgrade, or replace process stations without replacing the entire system. Flexibility is so important because deep-UV resist processing is still evolving, and both hardware and software must be adaptable to "yet to be

determined” queue times, chemistry management, and process steps. However, since 200-mm tracks do not accommodate upgrades to 300-mm wafer sizes, the flexibility show-stopper will be the change to the 300-mm wafer fabrication.

The flexibility capability must also extend to the system software. The software should also be modular, so that it can be reconfigured if needed. The software must also be able to handle multiple process recipes so that an array of processes can be run on the same track (e.g., both *i*-line and DUV resists). The software must meet the SEMI SECS or GEM standards for process-tool-to-host-computer communication. In addition, the operator interface should be well designed so that chances for operator errors are minimized. Ultimately there will be an expert system in the cluster controller that will collect and analyze data from the system using statistical techniques that will determine the overall lithography process status.

The software will also have an impact on throughput. For example, if a new lot cannot be started until the previous lot has finished, the *actual* throughput will be significantly lower than the *steady-state* throughput. To eliminate this problem the software controlling the track must be able to start a new lot while the previous lot is still being processed (a procedure termed *lot cascading*). Hence, it must be possible to start a new lot as soon as the input station is empty. The software must recognize the boundary between the two lots and change the recipe when the first wafer of the new lot arrives at each processing station. Capabilities such as on-line recipe editing and graphical user interfaces also help maximize actual wafer production time.

Next, the system must be highly *reliable*. All wafer track manufacturers specify at least 95% uptime, but even this value means that the system will not be available for 24–36 hours per month. Use of “intelligent redundancy” in subsystems can improve track reliability (for example, by adding an extra hot-plate, or by having qualified standby modules).

The cost of the track system itself, its footprint, and the amount of resist and developer consumption are other factors that impact the *cost-of-ownership*. In the move from 200- to 300-mm wafer tracks, users are demanding that 300-mm tracks be no more than one-third larger than 200-mm systems. Use of vertically stacked modules should allow such system footprint goals to be met. Resist consumption is one of the major costs of operating a semiconductor fab. To control this cost, the dispense volume of resist per wafer has been decreased with time. The design of the resist pump and spinning equipment plays a major role in achieving reduced resist consumption.

The tracks must also be *clean* and *safe to operate*. Both external particles and contaminants must be suppressed, and the track tools and processes cannot generate particles. Point-of-use filtration of resists and developer liquids and advanced wafer transport techniques (that employ gentle handling of wafers) reduces particle generation. Photo-islands are also enclosed in Class-1 environmental chambers. Safety issues involve the control of toxic fumes from resist and developer solutions, and measures to ensure that wafers do not fly off the high-speed spinning chucks.

The environment within the photo-island enclosure must be strictly controlled, including the temperature, relative humidity (RH), and vibration (and for DUV resist processing, the trace quantities of amines).^{18,19} The temperature control issue is challenging because the users want an enclosed system in a small footprint. Yet they also require that the temperature throughout this volume (which contains bake modules and motors) also be uniform and tightly controlled. The RH is chosen to be some value in the range from 35–50%, but it must then be maintained at that selected value to $\pm 0.2\%$. The temperature of the resist and developer chemicals used in the system must also be well controlled.

The goal of the lithographic process is to produce resist features with consistent CDs. In fact, the acceptable CD variation is getting smaller faster than the actual CD size.²⁰ At $0.18\text{-}\mu\text{m}$ and beyond, good CD control will become the most important challenge of resist processing. Many factors (already mentioned) impact the value of the CD including the resist thickness, the use of an anti-reflection coating, and the exposure and develop processes. For example, in *i*-line lithography, across-wafer and wafer-to-wafer tolerances of $50\text{-}\text{\AA}$ were acceptable. But sub- $0.18\text{-}\mu\text{m}$ processes require $< 20\text{-}\text{\AA}$ ranges. To achieve such tighter film thickness tolerances, the track system must rigorously control cup humidity and temperature, resist temperature, resist dispense rate, and wafer temperature. (Some sub- $0.13\text{-}\mu\text{m}$ processes will require $\pm 0.1^\circ\text{C}$ temperature control and humidity within $\pm 0.2\%$.) The thermal control in baking, as well as the time elapsed between process steps, are becoming additional variables that play critical roles in determining the CD value, especially when DUV-resists are used. In DUV processes, the coating step and the PEB hot-plate-temperature are key, but so is the lag between the time PEB is finished and when the wafer goes on the chill plate. Sequences will have to be timed within 1 or 2 seconds at every step. If the system cannot ensure this transfer timing, CDs will vary from wafer to wafer. (In the past the purpose of the PEB step was to stabilize the image. Now it is the step that basically creates the image. So any variation in the PEB process can significantly impact the CDs for $0.25\text{-}\mu\text{m}$ features and below.)

REFERENCES

1. S. Wolf and R.N. Tauber, *Silicon Processing for the VLSI Era – Volume 1: Process Technology*, Lattice Press, Sunset Beach, CA, 2000, Chaps. 12 & 13.
2. H.J. Levinson, *Principles of Lithography*, SPIE Press, Bellingham WA, 2001.
3. *Microlithography: Science and Technology*, J.R. Sheats & B.W. Smith, Eds., Marcel Dekker, New York, 1998.
4. P.K. Vasudev and P.M. Zeitzoff, "Si-ULSI with a Scaled-Down Future," *IEEE Circuits & Devices*, March 1998, p. 19.
5. H. Ito, "Deep-UV Resists: Evolution and Status," *Solid State Technology*, July 1996, p. 164.
6. C. Garza *et al.*, "Photoresist Materials and Processing," in *Handbook of Semiconductor Manufacturing Technology*, Y. Nishi and R. Doering, Eds., Marcel Dekker, Inc., New York, 2000. Chapter 17, p. 515-528.
7. D. Ruede *et al.*, "The Impact of Airborne Molecular Bases on DUV Photoresists," *Solid State Technology*, August 2001, p. 63.
8. T. Toyoshima *et al.*, "0.1- μ m-Level Contact-Hole Pattern Formation with KrF Lithography by Resolution Enhancement Lithography Assisted by Chemical Shrink (RELACS)," *Tech. Dig. IEDM*, 1998, p. 333.
9. L.J. Peters, "Resist Developers Try to Beat the Clock," *Semiconductor International*, February 2001, p. 77.
10. L.J. Peters, "Resists Join the Sub-Lambda Revolution," *Semiconductor International*, September 1999, p. 68.
11. B. Su *et al.*, "Analyzing and Characterizing Resist Shrinkage," *Solid State Technology*, May 2001, p. 52.
12. "Developments in Materials for 157-nm Photoresists," *Solid State Technology*, October 2001, p. 63.
13. P. Singer, "Anti-Reflective Coatings: A Story of Interfaces," *Semiconductor International*, March 1999, p. 55.
14. L. Peters, "Progress in KrF Antireflective Coatings," *Semiconductor International*, May 2000, p. 25.
15. P. Burggraaf, "Stepper-Track Integration: Solving the Problems," *Semiconductor International*, August 1992, p. 30.
16. R. DeJule, "DUV Cluster Tools Go Mainstream," *Semiconductor International*, August 1999, p. 44.
17. M. Krishna *et al.*, "Improve Yields and Enhance CDs. With Integrated DUV Resist Track," *Solid State Technology*, October 2000, p. 135.
18. B. Demandante *et al.*, "Protect DUV Processes with Real-Time Molecular Monitoring," *Semiconductor International*, September 2000, p. 115.

19. L. Peters, "Maintaining a Clean Environment in DUV Lithography Bays," *Semiconductor International*, May 1999, p. 52.
20. A.E. Braun, "Track Systems Meet Throughput and Productivity Challenges," *Semiconductor International*, February 1998, p. 63.
21. L. Peters, "Readying Resists for the 90-nm Node," *Semiconductor International*, February 2002, p. 63.

Chapter 7

ADVANCED LITHOGRAPHY II: OPTICAL HARDWARE

In this chapter the topics related to microlithography optics and hardware pertinent to IC technology at the start of 2001 decade are discussed. These subjects include: excimer-laser light-sources; optical-alignment-tools (stepper-scanners) for the 248-, 193-, and 157-nm lithography generations; resolution-enhancement-techniques; and next-generation lithography (NGL).

7.1 EXCIMER-LASER DEEP-UV LIGHT SOURCES

Excimer lasers are used to produce the light needed for deep-UV optical lithographic exposure systems. Deep-UV laser sources will dominate what many industry experts believe will be optical lithography's final arena before an industry jump to the post-optical era. Such laser-light sources are essential enabling elements for lithography for the next three critical-dimension nodes of the industry's roadmap. The term *laser* is an acronym for *light amplification by stimulated emission of radiation*. The krypton-fluoride (KrF) excimer laser is used to produce DUV light with a wavelength of 0.248- μm (or 248-nm). Argon-fluoride (ArF) excimer lasers are employed to produce DUV light with a wavelength of 193-nm, and F_2 excimer lasers for 157-nm DUV light. No fundamental changes are necessary to allow a KrF-laser to operate as an ArF-laser, except to change the gas composition in the laser's plasma tube and the mirrors that make up the cavity.

By 2001 the KrF-excimer-laser had become the light source of choice in mainstream, high-volume, advanced IC production (i.e., for 0.35-, 0.25-, and 0.18- μm -CMOS technologies). At the same time, ArF-excimer-lasers were being installed as the light source for 193-nm stepper/scanners that were being used for advanced process development applications, as well as for some pilot-line production (i.e., for sub-0.2- μm -CMOS process-development lines). It is conjectured that ArF lasers will displace KrF between 130-nm and 100-nm, albeit not until ArF maturity is reached in production. ArF has the potential to be the dominant source down to the 100-nm to 70-nm technology-nodes. Below 100-nm, the F_2 laser appears as a possibility.¹

An *excimer* is an exotic molecule formed by one atom each of a noble gas and halogen atom. This *dimeric* molecule is bound only in a quasi-stable excited state.




Fig. 7-1 Energy diagram for a KrF excimer laser. KrF^* is formed via two reaction channels. It decays to the ground state via dissociation into Kr and F while emitting a photon at 248-nm.

That is, if the noble gas and halogen gas atoms are in the ground state they will not react, but if one (or both) are in an excited state, a chemical reaction can occur to form a *dimer*. The term “excimer” is thus a contraction of the phrase “*excited dimer*.” (Note that true dimers are molecules containing two atoms of the *same* element, but this term is also used here to describe a molecule with two different atoms.) When the excimer decays back to the ground state, the dimer falls apart into its two constituent atoms (with the emission of a DUV-photon accompanying the decay process). When such decay is stimulated by absorption of energy from another light photon, DUV-laser light is emitted by an ensemble of KrF^* dimers. The spontaneous (i.e., not stimulated) dissociation time of an excimer (e.g., KrF^*) is relatively long (i.e., in the nanosecond to microsecond range). Therefore, population inversion (higher population of the excited state than the ground state) can readily be achieved by exciting a high-pressure mixture of Kr and F gases in a high-voltage pulse discharge (see Fig. 7-1).

A capacitor (that will serve as the transient power supply to produce the plasma discharge) is first charged to 12-kV. Then it is discharged in a very short time (75 ns) across electrodes present in the laser cavity. The plasma discharge created by this injection of energy produces Kr^+ and F^- ions, and these ions then combine to form the KrF^* excimers (with the process that creates the excited population of dimers called *pumping*). The laser light is produced by stimulating this created population of excimers to decay within a very short time. Some of the excimers begin to decay spontaneously. The light they emit passes through the gas containing the excimer population, and this stimulates additional excimer decay (which creates more radiation). This is the *amplification* process alluded to

in the acronym term *laser*. The laser cavity also uses mirrors to reflect radiation back into the gas. Thus, the stimulated decay rate (and laser-light emission) continues to increase, until almost all of the excimers have undergone stimulated decay. In fact, in a properly designed laser cavity, the stimulated decay process is completed very quickly after it is initiated. Thus, the light of an excimer laser is emitted in the form of short pulses of energy (i.e., these excimer-laser sources do not emit laser-light continuously, as do continuous-emission lasers). The laser-light exits the laser cavity through one of its ends, at which a partially-reflecting surface is located. As soon as the capacitor can be charged again to a high-enough voltage (making it able to act as the excitation source for creating the discharge) the excitation, pumping, and laser-emission cycle can be repeated.

One of the biggest problems in using excimer lasers as lithographic light-sources, however, is the fact they emit their energy in such a pulsed mode. Excimer lasers with a power output that is useful for lithographic applications (2-20 W) typically produce pulses of laser energy at a rate of 200-2500 Hz, with each pulse being only 5-20-nsec in length and containing about 10-mJ of energy. Since each pulse is so short, and there is a relatively long time between pulses, the peak power within each pulse is extremely high (even when the average power of the laser appears to be quite modest). Such peak powers can cause damage to the optical coatings and materials of the optical lithography system if it is concentrated in too small an area (e.g., the stepper lens). Thus, design features must be employed to keep the power-density low enough at all points within optical elements. An increase in the repetition rate of the laser is also beneficial, since this produces the same average power with a lower power per pulse (and exposure-dose-control is also improved).

Excimer lasers are attractive as DUV light-sources for several reasons. First, KrF-lasers can deliver much more usable power at 248-nm than can a mercury-arc lamp. The radiance of the laser is several orders-of-magnitude greater than the arc lamp because the laser emits a highly-collimated beam of light, whereas the arc lamp emits light in all directions (isotropically). Excimer-lasers also have a low degree of coherence compared to most other kinds of lasers, as well as a relatively broad linewidth (which results in low temporal coherence). Low coherence is generally a desirable characteristic of a lithographic light source.

On the other hand, the 0.300-nm (300-pm) *spectral width* of the 248-nm laser is not narrow enough to satisfy the bandwidth requirements of the refractive optical systems of step-and-repeat aligners. (That is, the dispersion [the change of optical index with wavelength] of optical components in the DUV region is high. Thus, spectral bandwidths even in the picometer range, can produce significant

chromatic aberration in systems with refractive optical components. This makes it difficult or even impossible to focus and image lithographic patterns properly.) Consequently, since the lenses of these steppers have no chromatic correction, this forces the illumination source to have a spectral bandwidth of less than 0.001-nm (or < 1 -pm). It is therefore necessary to put dispersive optical elements (such as prisms and diffraction gratings) within the laser cavity to reduce the bandwidth of the KrF laser-light to this value. These elements somewhat reduce the total power of the laser, but more importantly they also decrease the stability of the power level. A feedback system must be employed to keep the center wavelength of the line-narrowed laser-light-beam constant to about the same level of accuracy as the bandwidth. This control is needed because if the laser wavelength drifts by a few thousandths of a nm, the chromatic aberrations of the lens will cause an excessive shift in the focus of the lens. For each shift of the wavelength by 1-pm (0.001-nm), the lens-focus will shift by about 0.15- μ m.

7.1.1 KrF Excimer Lasers

By 2001, excimer-laser wavelength-stability of much less than 1-pm was being achieved (i.e., ± 0.25 -pm). For example, the Cymer ELS-6010 KrF laser (introduced in 2000) has a spectral bandwidth: ≤ 0.5 -pm full-width-at-half maximum (FWHM – see Fig. 7-2a) and a 95% energy integral of ≤ 1.4 -pm (this latter specification defines the spectral range that includes 95% of the energy of the pulse, see Fig. 7-2b). Also, the repetition rate of this laser has been increased to 2500 Hz. However, beyond 180-nm lithography, even a 0.5-pm spectral bandwidth and a 95% energy integral of 1.4-pm will not be sufficiently small. These specification will need to be narrowed to < 0.4 pm and < 1 pm, respectively. Using double-pass Etalon (reflecting surface, Fig. 7-4b) optics with a 10W, 2000




Fig. 7-2 a) Definition of “full width at half maximum,” FWHM; b) Definition of 95% integral pulse bandwidth.




Fig. 7-3 Pulse energy and stability vs. repetition rate for a KrF laser running in the constant charge voltage mode.

Hz laser, laser pulses with an actual spectral bandwidth centered at 248.3-nm, a spectral bandwidth of 0.27-pm and 95% energy integral of 0.93 were produced.²

Another issue related to pulse power is exposure control. The method for controlling exposure in a stepper illuminated with a pulsed laser is to integrate the pulsed energy until the required exposure dose is reached (at which point a signal is sent to stop the laser from pulsing). To achieve a 1% control of accuracy, at least 100 pulses must be used. Early excimer lasers had lower pulse-repetition-rates (1000 Hz), and thus had slower exposure times. By doubling the pulse-repetition-rate to 2000 Hz, the delivered exposure energy within the same unit of time was also doubled, and this also cut the exposure time approximately in half. By 2002, the newest laser models have overcome this limitation (repetition-rates are up to 4000 Hz), and the exposure speeds of excimer laser steppers now match (or exceed) those of arc-lamp-illuminated systems. Photonic energy output is a related critical parameter for lithography. The recently improved output characteristics of KrF systems are such that the relationship between output power and laser repetition rate is essentially linear (Fig. 7-3).

In addition to the issue of pulsed power, excimer lasers have some other drawbacks. They are much larger than an arc-lamp illumination source, typically occupying a clean-room footprint of 2x5 feet (Fig. 7-4). The excimer laser is also expensive (\$500,000–\$1,000,000), which in 2001 added 10-20 percent to the cost of the stepper. Gas used by the stepper is also costly and toxic and the plasma cavity in which it is contained, is not sealed. Thus, it must be periodically refilled




Fig. 7-4 a) Configuration of excimer laser light source and stepper (Courtesy ASML); b) Etalon

with this gas (about every 5 days). This requires a gas-handling system that can fulfill the rigorous industrial safety requirements for toxic gases. (The interval between gas refilling has been increased by more than a factor of 10 since the earliest lasers were used for lithography, and improvement is continuing.)

The laser pulses also sputter materials onto the mirrors and windows of the cavity. Thus, they must be cleaned after a number of pulses. The laser must be shut down during such servicing. Eventually, the entire laser-cavity must be replaced (which represents the largest cost of operating an excimer laser). The number of pulses between cleanings (and replacement) has been continuously increased. In 1998, servicing was required after 1 billion pulses and laser-cavity replacement after more than 2.5-billion pulses. Since laser usage during production is about 2×10^9 pulses in a year, in 1998 window cleaning had to be done about once every six months, and laser-cavity replacement about once a year.

The laser system is also relatively inefficient in terms of electrical-power usage, and thus it consumes about 10-kW while the laser is operating. Finally, the DUV-light of the laser is very hazardous to human skin and eyes. Hence, stringent safety precautions must be enforced when maintenance work is performed on the laser. The laser enclosure and beamline must also be interlocked to prevent anyone operating the system from being exposed to the

laser-light. Nevertheless, as excimer-laser technology has matured the reliability of lasers has been greatly increased, and the frequency-of-repair rates have dramatically declined. KrF lasers are commercially available from Cymer, Inc., Lambda Physik, and Komatsu, with Cymer, Inc. at the turn of the century having the largest market share.

7.1.2 ArF Excimer Lasers

The demands of ArF-laser technology are even more stringent than those of KrF-lasers. The power output and repetition-rate must be increased, line-narrowing must be smaller, and pulse-uniformity must be improved to allow accurate dose-control. Finally, the entire set of issues dealing with accelerated degradation of materials and system components caused by 193-nm radiation must be addressed. It appears that a basic space-line resolution of less than 105-nm will be possible using ArF illumination. By 2002, Cymer introduced the Nanolith-7000™ ArF-laser with a 4-kHz rep-rate, an average power of 20-W, and high spectral purity. The optical-component degradation under 193-nm radiation was also found to be lessened as the peak-power of the laser pulse is decreased. Thus, efforts to reduce the peak-power (by increasing the pulse-width) were being pursued for ArF-lasers. Some success toward achieving this goal have been described. Progress reported by 2000 indicates that the manufacturing performance of ArF-lasers will be comparable to that exhibited by KrF-lasers currently being used in production.

7.1.3 F₂ Excimer Lasers

There are many challenges that must be met to build production-worthy F₂ excimer lasers, but these also appear to be tractable. As with the ArF-laser, reducing peak power, but increasing average power (10-40-W) will be important. F₂-lasers operating at multi-kHz pulse rates will be needed. Spectral linewidth demands at 157-nm will depend on lens design, but it seems likely that a spectral bandwidth of 0.2-pm will be required. F₂-lasers emit two bands of light (at 157.63-nm and 157.52-nm), but 87% of the energy is located at the longer wavelength. A prototype 2000-Hz F₂-laser, based on a current ArF design was described in 1999, in which single-line operation at 157.63-nm was achieved. The output of this F₂-laser scaled linearly with repetition rate. Its energy stability was better than 6% (3 σ) over 100 bursts and better than 4% over more than 80% of the burst range. Gas lifetimes appear comparable to current ArF lifetimes.

7.2 EXPOSURE TOOLS FOR DUV LITHOGRAPHY

The wafer stepper was initially commercialized by the GCA Corporation of Andover, MA. GCA's first stepper, the DSW4800 (Direct Step on the Wafer)

was equipped with a 10X reduction capability, a 0.28-NA and g-line lens that could pattern a maximum square field of 10 mm x 10 mm. The lens was supplied by Carl Zeiss of Oberkochen, Germany. The stepper had a resolution of 1.25- μ m lines and spaces over a 1.5- μ m depth-of-focus and could achieve an overlay of ± 0.7 - μ m. Its list price was about \$300,000.

Several other companies soon began selling wafer steppers, and the major suppliers today are Nikon, ASM Lithography (ASML), Canon, and Ultratech. Modern steppers have considerably greater capability than the original GCA DSW4800, but the operating principles are essentially the same. Leading-edge systems in 2001 come in the step-and-scan configuration. (The stepper and step-and-scan configurations are described in more detail in Vol. 1, 2nd Ed., Chap. 13.) The characteristics of 248-nm step-and-exposure tools are listed in Table 7-1. To show how their imaging and overlay capabilities have been improved, these are listed both for the modern step-and-scan systems and the GSW4800 in that table.

7.2.1 Exposure Tools for 248-nm Lithography

Optical lithography systems continue to reach further and further beyond their previously perceived limits. By 2001 248-nm scanners – which use a KrF-laser light-source – were routinely printing 0.18- μ m features. Industry experts believe that 248-nm lithography will get them to at least the 0.13- μ m node. The pressure to push 248-nm lithography past what had been earlier considered its limits is largely a matter of economics. Chipmakers must weigh the trade-offs between the cost of the advanced reticles necessary to extend the current wavelength, and the systems costs and risks that come with the next wavelength. Manufacturers that run large volumes of devices per reticle are more willing to put effort into the current wavelength, spending the money needed on the reticles. On the other hand, those making logic or application-specific ICs (ASICs), where only a few hundred wafers may be manufactured with a reticle set, face a much higher cost of ownership if forced to pay the price of advanced reticles. Advances in resist technology and the ability to make lenses with higher numerical aperture are two of the reasons higher resolutions are possible with 248-nm lithography.³ (Note that 248-nm resists are discussed in Chap. 6, Sect. 6.1.1.)

Lenses can now be built with higher numerical aperture (NA) and lower aberrations than was previously thought possible (Fig. 7-5). Even in 1999 it was not considered likely that lenses with an NA greater than 0.6 could be manufactured. Yet by 2001 various steppers were being introduced with even higher NA. For example, Nikon offers a stepper with a lens having an NA of 0.75, and the ASML PAS 5500/800 uses a lens with an NA of 0.8.

TABLE 7-2 Commercially Available KrF Step-and-Scan Systems - Compared to the First Commercially Available Stepper

	GCA	Canon	SVGL	Nikon	ASML
Model	DSW4800	ES3	Micrascan III+	NSR-S205C	5500/800
M:1	10×	4×	4×	4×	4×
Wavelength	436 nm	248 nm	248 nm	248 nm	248 nm
Maximum lens NA	0.28	0.73	0.60	0.75	0.80
Field size	10 mm × 10 mm	26 mm × 33 mm	26 mm × 34 mm	25 mm × 33 mm	26 mm × 33 mm
Overlay, Machine-to-itself	500 nm	25 nm	45 nm	30 nm	30 nm
Lens distortion	250 nm	20 nm	25 nm	20 nm	20 nm
Overlay, machine-to-machine	700 nm	45 nm	55 nm	45 nm	45 nm
Wafer size	3," 4," 5"	200, 300 mm	150, 200 mm	200, 300 mm	150, 200 mm
Throughput (200 mm wafers, except for GCA)	20 wafers per hour (4" wafers)	100 wafers per hour	90 wafers per hour	140 wafers per hour	120 wafers per hour

7.2.2 Exposure Tools for 193-nm Lithography

The ASML PAS 5500/900 ArF step-and-scan tool was introduced in 2001. It is based on the ASML 5000 architecture and uses a Carl Zeiss refractive Starlith 900[®] lens with CaF₂ elements for partial achromatization. The lens has an NA that is adjustable from 0.45 to 0.6. There is a large working distance from




Fig. 7-5 The 248-nm lithography tools have seen vast improvements in lens aberrations in recent years. (Courtesy of ASML)




Fig. 7-6 The ASML PAS 5500/900 step-and-scanner. (Courtesy of ASML)

the final lens element to the photoresist surface, so that the lens contamination caused by outgassing from 193-nm photoresist during exposure is minimized. Figure 7-6 shows a picture of the PAS 5500/900 ArF step-and-scan system.

Canon's 193-nm scanner the FPA-5000-AS1 (introduced in 2000) has a 0.6-NA lens, and has demonstrated 600-nm DOF and can print 130-nm lines/spaces using annular illumination. The wafer throughput is projected to be 80-90 wph if the resist sensitivity is 10-mJ/cm². Challenges include availability of CaF₂ and improvements in resist performance.⁴

SVG offered two 193-nm exposure tools in 2000, the Micrascan V model (with an NA of 0.75) and Micrascan 193 (with an NA of 0.60). Both of these scanners use a catadioptric design, which requires only 1.7 kg of CaF₂ (as opposed to the 48 kg required for the chromatic correction of a refractive system).

7.2.3 Exposure Tools for 157-nm Lithography

Amid concerns about the technical risks and cost for all next-generation lithography (NGL) technology at and below the 70-nm node, work continues to develop 157-nm lithography technology.^{5,77} This technology, however, is beset by a number of obstacles new to the evolution of lithography processes. First, the

material that has been used for the lenses and reticles of previous generations of lithography, namely fused-silica, will have to be replaced by calcium fluoride (CaF_2). Second, the optical path will need to be a purged system requiring a nitrogen environment. Third, the optical system is likely to be of a catadioptric design, since such optical systems are smaller in overall design and require smaller optical elements than do comparable refractive optical systems. For example, due to the way the design is folded, the catadioptric design is approximately one third the size and weight of an equivalent all-refractive system, and the lens elements may be half that of all refractive optics in both size and numbers. While catadioptric lens elements could range from 50 to 200 mm, all-refractive lens elements as large as 400-mm might be required, depending on design.

The beamsplitter, the heart of the catadioptric optical systems, is a cube the size of which depends on the NA. The larger the NA the larger the beamsplitter that is needed. Fabricating beamsplitters from CaF_2 is a difficult challenge. As we will describe in the next section, the handling and polishing of this thermally sensitive and easily chipped material is a delicate operation. In 1999, however, SVG (in cooperation with Schott) announced that they have been able to successfully produce a 100-mm CaF_2 cube (Fig. 7-7).⁶ Though not large enough for a 0.7-NA system, it meets the specifications for a 0.45-NA scanner.

At the First Symposium on 157-nm Lithography in 2000, ASML said it expects to ship its first 157-nm scanner in the 3rd or 4th quarter of 2003, and Canon expects to be ready about a year later. Estimates for the cost of a single 157-nm scanner range from \$12m to \$20M (for a system with a high NA).⁷



Fig. 7-7 SVGL has demonstrated the ability to grow and make a beam-splitter cube 100-mm on a side for use in its 157-nm catadioptric lithography tool. (Courtesy SVGL)




Fig. 7-8 Transmission of 10-mm-thick samples of materials used in lenses of wafer steppers.

7.2.4 Calcium Fluoride Optical Elements for DUV Lithography

Although the optical elements of lithography systems down to 248 nm can be made with fused silica, refractive optical systems at 193-nm often need to use at least some CaF_2 elements. At 157-nm, CaF_2 is virtually the only available useful transmissive material (with BaF_2 as the other possible candidate). The transmission properties of various types of optical glass are shown in Fig. 7-8. Lenses for 193-nm usually include CaF_2 as an optical material for some of their elements, especially at locations where the light intensity is especially strong. CaF_2 elements are used because damage is a concern under the high intensity levels of light delivered by excimer lasers. That is, one type of such damage is compaction of the lens material. Compaction occurring in the projection optics will degrade the image quality, and this compaction will also increase light absorption by the lens (and such increased absorption will therefore also reduce light intensity at the wafer, thereby reducing stepper throughput). Fused-silica undergoes compaction (becomes more dense) and thus also more absorbing under the intense light from excimer lasers. Consequently, CaF_2 , which seemingly does not compact because it is a stable, single-crystal, is used in the illuminator and projection optics wherever high-levels of light intensity is expected. In 193-nm steppers, the compaction of fused-silica that occurs after extensive use is sufficiently severe so that it can render 193-nm lithography unsuitable for high-resolution lithography. In the illuminators of 193-nm systems, where such high intensities occur, appreciable amounts of CaF_2 are thus needed.

However, short wavelength applications also put very stringent requirements

on materials and fabrication. To minimize susceptibility to optical damage (as well as scattering and absorption losses that degrade throughput), bulk CaF_2 must be extremely pure and homogeneous. To reduce image degradation stemming from optical fabrication errors, the component surfaces must be flat and smooth to the level of tens or hundreds of angstroms rms. CaF_2 is hygroscopic, soft, and very prone to chipping, particularly at the edges. As a result, fabrication time for CaF_2 is typically 50% to 100% longer than for glass.

Besides transparency, there are other properties that a material must have in order to be used to make optical elements for DUV exposure tools. One such property is that the material does not exhibit excessive birefringence. (*Birefringence* is the optical property of a material in which a different index of refraction exists along various crystal axes.) However, many materials do exhibit significant birefringence, and such materials are generally not suitable for use in high-resolution optical systems. For example, SiO_2 in its purely crystalline form (quartz), is not easily incorporated into lenses because it has dissimilar behavior among different optical axes. On the other hand, amorphous fused-silica is a standard optical material because its non-crystalline structure causes it to have only a small degree of birefringence. Some materials, like CaF_2 have (until recently) been thought to exhibit little *intrinsic* birefringence. However, CaF_2 can exhibit low levels of birefringence induced by mechanical stresses. This type of *extrinsic* birefringence is termed *residual-stress birefringence*.⁸

Residual-stress birefringence occurs from the mechanical stress and strain formed during the production of an optical element (for example, if there are large thermal inhomogeneities in the furnaces in which the crystals [e.g., of CaF_2] are grown). A high level of residual-stress birefringence in optical components can lead to the aberration of light rays in an imaging system, and thus affect the imaging quality of a step-and-scan system. Residual-stress birefringence currently limits the yield of CaF_2 crystals suitable for use in stepper lenses.

Recently (May 2001), it was discovered that crystalline CaF_2 does, in fact, possess *intrinsic birefringence*. Lens designers were familiar with the residual-stress birefringence in CaF_2 described above, and were prepared to compensate for this effect with relatively complex lens designs. But, intrinsic birefringence – which may inflict about 6x more birefringence – presents a more sticky problem. However, a group of technologists gathered in mid-2001 to assess the issue, and they concluded that it will not be a showstopper for 157-nm lithography. Furthermore, intrinsic birefringence is not a concern for 193-nm lithography because corrections can compensate for any effects it causes at this wavelength. While it certainly will make 157-nm lens design more complex, the fact that this

phenomenon was discovered before such lenses had been fabricated is a good thing. It also implies that lithography systems will have to manage more carefully the polarization of the light as it enters a lens.⁷⁸ The lens design software (e.g., CODE V from Optical Research Associates) will also have to be modified to compensate for intrinsic birefringence.⁹

There are also questions about whether it will be possible to supply the quantity and quality of CaF_2 needed for 157-nm lithography. Nikon plans to use its own production for some of its optics supply. While, its major supply will not come from in-house, the company plans to develop the intellectual property for CaF_2 and optical coatings to help it get the quality needed. Corning Inc. recently acquired Optovac and Tropol Corp., to beef-up its capabilities to tackle CaF_2 production. It also has a facility in North Brookfield MA for producing CaF_2 .

Note that while conventional fused-silica is not transmissive enough at 157-nm to be used as a 157-nm reticle-blank, its transmission can be improved by preparing the fused-silica with low-OH content (and by adding fluorine to the glass network). This increases the transmission to 82%, allowing fused silica to meet the International SEMATECH targets for 157-nm mask materials.⁷⁷

7.2.5 300-mm Lithography Tools

Development of 300-mm tools began in about 1995. Before the end of 1997 the first 300-mm lithography stepper was installed (the Canon FPA-3000EX3L KrF-stepper) at I300I (now International SEMATECH). Initially, vendors were advised to develop tools that could handle only 300-mm wafers, but a few tool vendors took the bridge-tool approach (which allows a tool to be used on either 200-mm or 300-mm wafers). By late 1998, however, the industry was still not ready to embrace 300-mm production. Instead it stayed with technology-driven cost-reduction at 200-mm. By 2001, 300-mm had still not been widely adopted, as the industry went into a deep downturn. Nevertheless, mature 300-mm tools were ready, but the insertion node was predicted to be 130-nm, not at the 250-nm node, as originally envisioned.

It should be noted that stepper-scanners expose each field and then step to the next one. Since there are $2\frac{1}{4}$ times as many fields on a 300-mm wafer as on a 200-mm wafer, it could take twice as long to expose one. Achieving the desired throughput requires the wafer and reticle stages to move further and faster, while the overlay and resolution demands of 130-nm (and smaller) imaging reduce the tolerable errors and vibrations. All of the exposure tool manufacturers announced new products or platforms to meet these needs.^{10,11}

ASML chose a "reaction-free-mass" concept for its new "Twinscan" platform, intended for operation both at 200-mm and 300-mm. To allow rapid acceleration of the relatively heavy wafer stages, the linear stage motors push against a counter-mass, which moves in the opposite direction, rather than against the fixed stepper frame. Since the counter-mass is free to move, it absorbs the impulse from the acceleration without inducing vibrations in the exposure tool structure. The center of gravity remains fixed, eliminating gravitational torques. The stages accelerate and decelerate according to Newton's third law, just like a rocket in vacuum (which spews reaction mass behind it). According to ASML, the new systems reduce moving-average alignment error to 3-nm and moving-standard-deviation to < 2 nm, a 10-fold improvement. The initial "Twinscan" tools were specified at 62-wph (in 2000), with throughput expected to double by 2002.

Canon chose a more conservative approach for 300-mm production, introducing a tool set that uses a high-NA KrF-scanner for critical levels, and a matching *i*-line-stepper for non-critical levels. All are designed for high throughput, specifically 88, 300-mm wph for the scanner, and 100 wph for the stepper. The matched fields allow for a mix-and-match strategy with the lowest CoO tool applied to each level. An ArF-tool is expected to be available in 2001. While Canon did not reveal its stage design, counter-masses and improved aerodynamics allow 350-mm/sec wafer speeds with overlay accuracy below 23-nm.

Nikon has had a 300-mm-capable KrF-scanner in the field since 1998 (the NSR-S203B), and the newly introduced 0.75-NA NSR-S205C promises 83 wph, along with 130-nm resolution (using RET) and < 30 -nm overlay. Nikon expected to ship 100 of these systems in 2001. The NSR-SF100 *i*-line-scanner also matches the 25x33-mm field of the excimer scanners for mix-and-match applications. A new 0.68-NA ArF-scanner was promised for 2001.

Silicon Valley Group (acquired by ASML in 2001) introduced the Micrascan IV and V systems in 2000. These incorporate innovative low-mass precision wafer stages, without interferometer retroreflector mirrors. The interferometer systems of the Micrascan IV and V are inside out, compared to previous designs. That is, the mirrors are on the frame, and the laser-beam launching and collection optics are on the vertically oriented stages. The lightweight stages allow scan speeds above 300-mm/sec. The reticle stage, however, must move 4x-faster. The quick, four wavelength HPAS alignment system has 1σ overlay accuracy of 3-nm. The 193-nm Micrascan V tools are designed to expose 130-nm CDs with standard mask illumination and 100-nm half-pitch using RETs. These tools have a large NA (0.75) and catadioptric projection lenses. The 248-nm Micrascan IV with 0.60-NA optics is intended for non-critical applications.

7.2.6 Mix-and-Match Lithography

One way to lower the cost of lithography is to use the most advanced (and thus expensive) machines only for the critical levels, and employ less-expensive tools for the less-critical levels. This has been widely practiced for many years, and is referred to as *mix-and-match lithography*.

Vendors of exposure tools generally offer both high-resolution (expensive) and lower resolution (lower cost) models. The exposure tools intended for use on those levels with relatively lower-resolution requirements are normally optimized for throughput and price (instead of resolution and overlay). Lower-NA lenses are cheaper to design and build than higher-NA lenses. Such less-expensive systems deliver high throughput by exposing larger field sizes. In addition, in the 2001 timeframe all lower-cost models are steppers (i.e., not stepper-scanners).

Another strategy for lowering the capital cost of lithography is to utilize exposure tools from several generations of technology. As exposure tools get older they can no longer image the smallest feature sizes of the next technology nodes. Yet these steppers can still be used for imaging the less critical levels. This is an effective cost-saving method since it is not necessary to purchase new tools, and those in use may have already been fully depreciated. Smaller-NA steppers are also useful for patterning implant masks (that generally have larger feature sizes, but also often thicker resist films). In such cases, high-resolution steppers may actually do an inferior job, due to their limited depth-of-focus.

While mix-and-match lithography appears economically attractive, it is not without its drawbacks. It may involve using steppers from more than one supplier, or steppers that employ dissimilar operator interfaces. This necessitates extra training for the lithography workers, and a separate spare-parts inventory for each stepper model.

7.3 RESOLUTION ENHANCEMENT TECHNOLOGIES (RETS)

By 2001 it appears that the conventional lithographic processes that have enabled the descent of the IC feature sizes over the past 30 years, are approaching the limits of their usefulness. That is, even by using the shortest possible illumination wavelength, λ , and the largest numerical aperture (NA) lenses, the last factor, k_1 , in the basic resolution equation:

$$\text{Minimum resolution} = k_1 (\lambda/\text{NA}) \quad (7.1)$$

presents a formidable obstacle. (Note that k_1 represents the measure of lithographic aggressiveness.)

That is, to obtain acceptable yield with a conventional lithography process (i.e., one which does not use any resolution enhancing techniques), the value of

k_1 is restricted to values larger than ~ 0.75 (because unacceptable image degradation occurs below this value). However, in the past two decades, various *resolution enhancement techniques (RETs)* have been developed, and their use permits lower values of k_1 to be achieved.^{12,13} These RETs include the use of anti-reflective coatings and top-surface imaging (as is discussed in Chap. 6), and off-axis-illumination (OAI), optical-proximity-correction (OPC), and phase-shift-masking (PSM), which are discussed in this section. Use of these techniques can possibly reduce k_1 from 0.75 to 0.35, which represents more than a 50% decrease in critical dimension compared to conventional lithography. Thus, we have gained the capability to print features that are one-half the size of those that can be printed with conventional lithography. Hence, by employing RETs, optical lithography has been able to maintain its vitality - allowing it to be used much longer than was ever thought possible 10 years ago.

7.3.1 Off-Axis-Illumination

Off-axis-illumination is a method for improving the resolution of a stepper without resorting to a higher NA lens or a shorter wavelength of light. The method was long employed in optical microscopes to enhance image contrast, and was introduced to microlithographers by Mack¹⁴ and Fehrs¹⁵ in 1989. Researchers at Canon, Inc.,¹⁶ and Nikon Corporation¹⁷ incorporated it into the optical systems of steppers in 1992. The off-axis-illumination technique improves the resolution capability of the stepper by modifying the direction of incidence of the illumination on the reticle. That is, it directs the beam of light from the illumination system of the stepper through the reticle in a direction that would make it strike the projection lens at the edge of the entrance pupil (rather than at the center of the projection lens entrance pupil, as is done in the conventional illumination technique). The term *off-axis-illumination* is somewhat of a misnomer. This is because conventional partially-coherent illumination also includes a range of angles of incidence on the mask, both on-axis and off-axis. Thus, when the term "off-axis-illumination" is used to describe the *post-1992 techniques*, it is intended to mean an illumination scheme *without any on-axis components*.

The principle of the new "off-axis illumination" techniques can be understood by considering the imaging process of optical lithography from a Fourier optics perspective (see, for example, Vol. 1, 2nd Ed., Chap. 13), as applied to imaging the pattern of a grating of lines and spaces. As shown in Fig. 7-9, in conventional stepper optical systems the light beam is directed from the illumination system through the reticle in a direction which would coincide with the center of the entrance pupil of the projection lens. Recall that for a grating pattern, the light is




Fig. 7-9 Principle of on-axis illumination: a) Light illuminating the mask from an on-axis direction, and the diffraction pattern from an on-axis coherently illuminated grating mask. The pattern is centered on the entrance pupil of the objective lens. b) Aperture with on-axis illumination showing the 0-order (undiffracted beam) and the two first order diffracted beams, $m = +1$ and $m = -1$.

diffracted into a set of beams which propagate away from the grating only at specific angles (corresponding to the orders of the diffracted beam). The undiffracted beam (0-order) propagates at a direction perpendicular to the reticle plane. The first-order diffracted beams ($m = +1$ and $m = -1$) propagate at angles $\theta_1 = \sin^{-1}(\lambda/p)$ and $\theta_1 = -\sin^{-1}(\lambda/p)$, respectively (see Fig. 7-9) where p is the pitch of the grating (i.e., the distance equal to the sum of the line and the space). The third-order diffracted beams propagate at larger angles than the first-order beams (i.e., $\theta_3 = \sin^{-1}[3\lambda/p]$ and $\theta_3 = -\sin^{-1}[3\lambda/p]$). Since no imaging is possible unless at least one additional beam is accepted by the lens besides the 0-order beam, the NA of the lens must be large enough to accept both the $+1$ and the -1 first order beams. For a given NA and λ , there is a minimum pitch below which the first order beams will fall outside the collection area of the lens. For this pitch and smaller, no imaging of the grating pattern is possible. An optical system that collects the three beams (0-order and $+1$ and -1 order beams) is sometimes called a system that employs *three-beam imaging*. Note that if at least the first order beams are captured within the pupil of the lens (and for the case of coherent illumination), this leads to the simple resolution limit of $0.5 \lambda/NA$, or in equivalent terms, a k_1 -limit of 0.5. For gratings with pitches below this limit, no pattern is formed by an optical system with this λ and NA, using coherent light.

If an *off-axis* (or *oblique*) illumination scheme is employed (Fig. 7-10a), such

that the illuminating beam is directed so the 0-order beam strikes the entrance pupil of the projection lens just at its edge, and only one of the other first-order beams strikes the other edge of the entrance pupil (i.e., either the $m = +1$ or the $m = -1$ beam) only two-beams are collected (hence the name *two-beam imaging*, see Fig. 7-10b). In this case the angle, θ , can have a value greater than in three-beam imaging, implying that the pitch of the grating can be smaller (and in turn a higher resolution can be achieved for an optical system employing the same NA and λ). In the extreme case of this type of off-axis illumination, a doubling of the resolution-limit capability of the imaging system is obtained, compared to a coherent fully on-axis-illumination scheme. Such resolution-enhancement is most pronounced for the case of dense-patterns of equal lines and spaces (such as occur in the regular array patterns of DRAM and SRAM interconnect lines).

Although resolution-enhancement may seem to be the primary benefit of off-axis illumination, in fact it is the impact of illumination on DOF that provides the more significant advantages. Defocus causes a phase error for each diffraction order that is proportional to the square of the radial position within the pupil. Consider the case of off-axis-illumination where the zero-order and one of the first-orders are the same distance from the center of the objective lens pupil. In this case, both the zero-order and the collected first-order will have phase errors due to defocus, but these errors will both be the same, and the relative phase difference between the zero- and first-order beams will thus be zero. Such a circumstance will result in an image that is much less prone to defocus, resulting




Fig. 7-10 Principle of off-axis illumination: a) Light illuminating the mask from an off-axis direction, and the diffraction pattern from an off-axis coherently illuminated grating mask is no longer centered on the entrance pupil of the objective lens, but is instead shifted. b) Aperture with one off-center hole that produces the illumination shown in (a).

in an important improvement in DOF. Thus, the proper choice of an off-axis illumination angle for a given equal line/space pitch will result in a dramatic increase in the DOF of that feature.

One limitation of off-axis illumination is that it does not provide the same resolution enhancement for isolated lines as it does for dense lines and spaces. This is because discrete diffraction-orders do not exist for isolated features. Instead an isolated feature generates a continuous diffraction pattern. Hence, isolated line performance is only minimally improved by off-axis illumination. When both dense and isolated features are considered together in a field, a dense-to-isolated feature-bias will arise if off-axis-illumination is employed.¹⁸ To circumvent this problem, off-axis-illumination tricks have been proposed. One involves adding small (sub-resolution) auxiliary patterns close to an isolated feature to establish the required interference effects (see Sect. 7.3.1).^{19,20,21} Another issue that must be addressed is that some illumination energy is lost because one of the 1st-order beams is not collected. As a result, it is necessary to increase the exposure time to compensate for this loss of illumination.

If the illumination of the mask only comes from one beam (that is, through an aperture with only one off-center hole, as shown in Fig. 7-10b), the +1st-order will fall completely out of the pupil, but the 0th and -1st-orders will be collected to form an image (Fig. 7-10b). However, the asymmetry between the 0th and -1st orders leads to severe telecentricity errors. Symmetry can be restored by illuminating with two sources, placed on opposite sides of the pupil, using an off-axis illumination aperture as shown in Fig. 7-11a (*dipole illumination*). This is an improvement over the single-beam aperture, but it will only improve imaging for gratings oriented in one direction. It will degrade them for gratings oriented in the perpendicular direction (see Fig. 7-11a1). Nevertheless, if geometries are oriented in only the vertical direction, such dipole illumination is optimal. *Quadrupole illumination* (Fig. 7-11b) works well when all features are oriented left-right or up-down, but distorts features of all other orientations (e.g., a line at a 45° angle). The latter limitation can often be tolerated because critical features are rarely oriented at odd angles to the sides of the chip. The *annular aperture* shown in Fig. 7-11c improves features of all orientations, but at the price of milder improvements in the resolution and DOF.

Note that a specific off-axis illumination setting will improve imaging performance for only a narrow range of pitches, but this is still an advantage for many applications, such as memories, where many structures are highly periodic.




Fig. 7-11 Different types of off-axis illumination apertures. The aperture with holes at the edges or corners - (a) and (b) - will improve lines oriented in one direction (see a1), but will degrade imaging of lines in the orthogonal direction. (c) Annular off-axis illumination aperture.²³

However, an off-axis illumination setting optimized for one pitch may work poorly for others. For patterns with more than one pitch, this becomes a problem. In such cases, an off-axis-illumination source that includes some on-axis illumination (with lower intensity than off-axis light), reportedly gives better results.²²

Off-axis-illumination is relatively easily implemented. Stepper manufacturers can provide any of the illumination-aperture types described above. A series of these apertures can even be mounted on a turret, and the particular aperture desired for any mask can be automatically supplied by the stepper control program. More sophisticated illuminators can also be used to transmit a larger fraction of the available light into the annulus of illumination.

7.3.2 Optical Proximity Correction (OPC)

The techniques developed to extend optical lithography beyond the range of conventional imaging are based on the idea that the 2-D aerial image formed by the projection lens is a structure to be optimized. One way to optimize the aerial image is to pre-compensate the reticle pattern to account for expected pattern distortion due to diffraction effects. One important consequence of diffraction is the so-called *proximity effect*, in which the exact size and shape of the features patterned on the wafer depend on their proximity to other features. These proximity effects manifest themselves in the form of distorted geometries (and in some extreme cases, even unprinted patterns). For designers, this phenomenon translates into line-width variations and other distortions that can significantly

decrease performance – or even worse - cause missing, incomplete, or shorted structures that can result in circuit failure.

One technique for determining such expected pattern-distortion involves computer simulation. That is, the 2-D aerial image of a particular reticle feature (or a group of features) is simulated by calculating the effects of diffraction on the image.²⁴ Based on the results, the reticle pattern can be altered and simulated again to determine if the change has improved the 2-D aerial image.²⁵ The reticle patterns are altered by adding (or subtracting) sub-features to the original pattern, and these features are called *optical-proximity-correction-features*. Additional aspects of the optical-proximity-correction procedure is discussed next.

One effect long observed in microlithography is that when patterns smaller than the exposure wavelength are being imaged, individual pattern features do not image independently. Instead, they interact with neighboring patterns. A simple qualitative argument for why this occurs is based on the light intensity pattern of the Airy function. That is, overlap of the secondary diffraction peaks of the Airy function with adjacent pattern features leads to increased or decreased exposure intensity at any point in the image compared to a purely geometrical image model. For example, the linewidth of isolated- and densely-grouped-lines eventually varies by a significant amount from that of the predicted linewidth (based on the pattern size on the reticle) when the feature sizes approach the



Fig. 7-12 Optical proximity effect. All pattern features are the same size on the reticle, but the final image is larger for the isolated line extension than for the densely packed lines.

wavelength of the illuminating light. However, very little difference between two such aerial images is observed if the feature sizes are large, i.e., $> 1 \mu\text{m}$. For example, assuming the use of positive photoresist, $0.35\text{-}\mu\text{m}$ -wide *isolated* lines are $0.09 \mu\text{m}$ wider than *closely spaced* $0.35\text{-}\mu\text{m}$ -wide lines (i.e., which might be part of a diffraction-grating pattern). Figure 7-12 shows an example of this effect. Since the linewidth depends on the proximity of other features, this effect is called an *optical-proximity-effect*. Such proximity-dependent linewidth variation (specifically termed *iso-dense print-bias*) may become significant in the interconnect-lines of a memory chip. That is, lines within the memory-array region of the chip would be regularly and closely spaced, but in the peripheral sense-amplifier and logic-circuitry they could be spaced farther apart. If this dimensional-difference can be predicted, the width of the chrome lines on a reticle can be adjusted to make isolated and densely-spaced printed lines on the wafer all the same width.²⁶ Such adjustments to the sizes of patterns on a reticle are termed *optical-proximity-corrections (OPC)*, and in this case such an OPC is performed as a *one-dimensional, pattern-dependent width correction* to lines on a reticle. (Note that biasing the size of features has been used historically for many years to assist in lithography-process centering and optimization, but until recently the same bias was applied to the entire reticle. On the other hand, the OPC-bias is custom-tailored for each line in its own environment.)

Originally, OPC was considered to be just a method to correct the line-size variations as a function of the proximity of other features (as described above).²⁷ However, other pattern-modification techniques have been developed to improve the images of such two-dimensional IC features as contact holes (or vias) and lines (e.g., of poly or metal). That is, corner-rounding and general loss of shape fidelity in small features is caused by the inability of the projection lens to




Fig. 7-13 Example of line shortening due to image distortion.




Fig. 7-14 A T-shaped feature (a) with dimensions near the resolution limit of the projection lens is printed as a rather featureless blob (c) on the wafer. Addition of serifs (b) brings the printed image (d) closer to the shape originally designed. Reprinted by permission of Marcel Dekker. (e) Adjustments to the linewidth can correct for the proximity of nearby features, and serifs on the end of a line can correct line shortening effects.

resolve details smaller than the diffraction limit of the lens. For example, a square contact-hole pattern with a size close to the minimum resolution limit of the optics will print more nearly like a circle. Likewise, a line (which should print with a rectangular shape - see Fig. 7-13a), instead prints as a feature with an elliptical shape (and an even shorter length). These effects have therefore also been classified as another form of optical proximity effect.

The OPC techniques used for modifying the 2-D reticle patterns to alleviate such deviations in the aerial images involve appending small, secondary patterns to the primary contact hole or short poly- and metal-line patterns. As noted above, such added-on auxiliary features are intended to be below the resolution capability of the projection optics. Several types of OPC features are employed. The most common are secondary patterns (called *serifs*) which are added to the corners of square hole patterns (as shown in Fig. 7-14b & e). They make the aerial image (and hence also the printed image) of such small contacts become more square-like. This occurs because the serifs enhance the amount of light transmitted through the corners of transparent mask features (e.g., the pattern of a contact hole being imaged in a positive resist). For short lines, serifs (together with linewidth changes) may be also added to improve the fidelity of the printed feature. The second type of OPC feature is the *line-jog*. These are used for lines that are isolated along part of their run across the wafer surface, but are near




Fig. 7-15 Sub-resolution scattering bars applied to isolated features.

other lines at other places. For such lines, incremental linewidth changes can be made to the linewidth by employing such line-jogs (see Fig. 7-14e).

A third type of OPC feature is the *scattering bar*, whose role is to improve the imaging of isolated lines. Scattering bars are lines having a sub-resolution width that are placed adjacent to isolated lines on the same pitch as dense features on the same reticle (Fig. 7-15). The purpose of scattering bars is to create a dense environment around an isolated feature. However, when properly designed, these scattering bars do not print. The isolated line thus appears dense to the projection system, but prints as a fine, isolated line.*

While OPC techniques provide significant benefits, they are not gained without some costs.¹⁸ The adoption of OPC includes the following drawbacks. First, serifs add a large number of additional features to the database of the reticle pattern. This increases the time needed to write the reticle (and therefore also its cost). Second, the sizes of the serifs are typically much smaller than the minimum feature size of the reticle, which creates problems during the inspection phase of the reticle manufacturing process. Likewise, when sub-resolution features first appeared, they represented a decrease of minimum feature sizes by factors of three and four. Such large changes in minimum feature size necessitated rapid advances in mask patterning. Third, this technique may not be feasible in all situations. That is, if the spacing between two contacts is already at

* As noted earlier, off-axis-illumination is an effective method used to enhance the patterning of periodic structures, but it provides no benefit for isolated lines.

the minimum allowed dimension, adding serifs to the square contact-hole pattern would bring parts of the two contact hole patterns to a distance below the minimally allowed value, and in such cases they cannot be used. Finally, it must be remembered that OPC is intended to correct for proximity effects. It does not actually improve the resolution or other quality metrics of the lithography process.

Since OPC is not performed until the design data are prepared for mask fabrication, OPC is typically transparent to circuit designers (although in some cases the design team may elect to get involved in deploying OPC in their layouts). However, in the first case, designers must still select a chip-manufacturer and mask-maker capable of accommodating OPC adjustments to the design. In both cases, some method must nevertheless be employed to determine which types (and where) OPC features have to be added to circuit layouts. Two approaches have been developed for carrying out this latter task.

The first is the so-called *rules-based* method. This uses a pre-determined set of rules together with a pattern-layout database program. The database program systematically determines the proximity environment of every pattern feature-edge, and then uses a lookup-table algorithm to apply the appropriate rules. These rules can generate biasing, serifs, scattering bars, etc. The rules may be developed directly from experience in the wafer fab, or they may be determined from image and resist simulations. Such rules-based approaches to determining the addition of OPC features to mask patterns are generally quite fast (requiring from several minutes to several hours on a typical workstation, per pattern level). However, the process of generating and validating the rules themselves can be a lengthy and tedious process. Since the accuracy and precision of the OPC features are completely determined by the extent and quality of the rules, this task must be effectively performed.

The second method is the so-called *model-based OPC approach*. In this case, each feature and its proximity environment are modeled by an image analysis program. A set of mathematical model parameters is used within the program to determine the appropriate corrections to the pattern layout. The model-based method is computationally intensive and may require many hours (or even days) of processing per pattern level. The model parameters are very important, but there are a limited number required. Manufacturers fabricate special test chips to generate OPC models of their lithography process. The chief advantages of the model-based approach is that the correction accuracy and precision can be readily controlled, and that corrections can be successfully applied to any sort of pattern layout. Software companies that offer OPC programs include Mentor

Graphics, Numerical Technologies (NumeriTech), and MaskTools (an ASML Company).

7.3.3 Phase-Shift Masking (PSM)

The most dramatic improvement in resolution limits imposed by diffraction involves the use of the phenomenon of *phase shifting*. For example, if a lithography process can attain a resolution of $0.3\text{-}\mu\text{m}$ using a 248-nm KrF light source with a stepper having an $\text{NA} = 0.6$, then by incorporating phase-shifting techniques on the reticle, the resolution can be improved to as much as $0.18\text{-}\mu\text{m}$. The concept of increasing the resolution of a lithographic image by modifying the optical-phase of the mask transmission was first suggested in 1982 by Levenson, Viswanathan, and Simpson.²⁹ While a number of different types of phase-shifting masks have subsequently been developed, they all employ the same basic concept, as illustrated by the original version. This concept will be used here to demonstrate the principle of *phase-shift masking* (PSM). Several references review the topic of PSMs in more detail than is provided here.^{30,31}

The phase-shifting of light as it passes through the clear part of a mask is accomplished by adding an extra layer of transmissive material to the optical path (Fig. 7-16). For PSM applications, a phase shift of 180° is usually desired, and this corresponds to an optical path-length difference of $\lambda/2$ at the stepper wavelength. Assume now that a grating (representing a *binary imaging mask*, or *BIM*, Fig. 7-17a1) is being imaged by optics with a particular numerical aperture




Fig. 7-16 The phase-shifting layer introduces a difference in optical-path-length. Here the difference is $\lambda/2$.³⁰ © IEEE (1993)




Fig. 7-17 Schematic of (a) a conventional binary mask (b) an alternating phase shift mask, (ALT PSM). The mask electric field, amplitude, and image intensity is shown for each type of mask.²⁸ Reprinted with permission of Marcel Dekker.

and partially coherent light. The (normalized) amplitude of the electric field (E -field) at the mask is either +1 or 0, as shown in Fig. 7-17a2. However, the imaging is degraded at the wafer because light from the clear areas on the mask is diffracted so that it strikes regions on the wafer that would ideally be completely dark. The nominally-dark-regions have light diffracted onto them from the clear spaces on both the right and left of them. The E -field amplitude on the wafer as a result of such diffraction is given in Fig. 7-17a3, and the light-intensity (which is the square of the E -field-amplitude) is plotted on 7-17a4.

If a phase-shifting material is placed on *alternating* clear spaces of a mask (as shown in Fig. 7-17b1), this forms a type of PSM called an *alternating-PSM*, or *ALT-PSM* (or sometimes even a *Levenson-PSM*). It should be noted that producing a phase shifter on a clear region of a mask may be done in one of two ways. In the first, an appropriate film of material can be deposited over the entire mask, and then etched away in the desired areas. In the second, the fused-silica glass itself can be etched in the appropriate clear-areas to produce recesses in the glass. The latter technique requires well-controlled etches so that recesses of the appropriate depth can be produced with only a timed etch. However, since deposition of a film different than fused-silica is not necessary, the use of this second approach to produce ALT-PSMs avoids the potential problem of the phase-shifter affecting either the light amplitude or phase.

In an ALT-PSM the light is phase-shifted by 180° when it passes through the spaces containing the PSM material, and the E -field amplitude on the mask is

shown in Fig. 7-17b2. Note that the E -field amplitude at the mask spaces containing the phase shifters is -1, but at those without a phase shifter has a value of +1. The E -field intensity imaged on the wafer using such a PSM is shown in Fig. 7-17b3, and the corresponding light intensity on Fig. 7-17b4. It can be seen that the contrast in the light-intensity distribution of the image on the wafer is greater when the PSM is used. Contrast is increased because the light diffracted into the nominally dark area from the left-clear-area will interfere destructively with the light diffracted from the right-clear-area. All types of PSMs use this same principle, in which the destructive interference of light of opposite phases is used to improve image contrast.

While ALT-PSMs give the greatest improvement in resolution for the case when closely spaced clear lines are separated on an opaque background, this type of mask is not effective for some other types of patterns. One example is the case when tightly packed features are laid-out in a pattern that resembles the stacking of bricks in a wall (Fig. 7-18). Since such a pattern has alternating rows offset from one another, it is not possible to assign a phase value to each pattern that will make it 180° out of phase with all its neighboring features. The resolution of isolated features (such as contact holes) is also not improved by ALT-PSMs. In general, non-repetitive patterns cannot be given phase assignments that meet the ALT-PSM approach.

Another problem with ALT-PSMs occurs when opaque lines are created on a clear background. At the edge where the clear area covered with a phase shifter abuts an area of clear-glass without a phase-shifter, interference between the two phases will make such boundaries print as a narrow dark line (Fig. 7-19a). A possible cure for this problem is to put another layer of material at such boundaries which shifts the phase by only 90° (see Fig. 7-19d), but in practice such a cure is not completely satisfactory. That is, it requires additional steps in an already complex reticle-fabrication process. Another approach to solve this problem involves the use of negative photoresist to produce masks for IC levels that produce line patterns. By using negative resist, if patterns on a mask which define *lines* are clear-features (and those defining spaces and field-regions are opaque, Fig. 7-20), phase-shifter material never abuts a clear area. This is one of the reasons that negative resists are again being considered for deep-submicron lithography applications that call for PSMs. A lower-cost version of ALT-PSMs (the *sidewall-chrome alternating aperture* [SCAA] PSM) specifically tailored for small production runs (< 500 wafers), was recently described by Levenson.³² In this type of PSM, the phase-shifting regions are patterned into the mask substrate before the chrome is deposited onto the mask blank. Then the chrome is pattern-




Fig. 7-18 Limitation of ALT-PSMs. There is no way to assign phases so that a 180° -phase difference occurs between adjacent transparent features. In this example, the phases have been assigned to the odd-numbered rows, but there is no way to assign phases consistently to the even rows.³⁶ Reprinted with permission of Marcel Dekker.

ed with a second exposure. To make the masks less costly, about 1000 mask blanks would have to be layed out with pre-determined phase-shift locations. Special EDA tools would then be used to lay out chips so all that all fine-features lie at these predetermined phase-shift locations. Levenson opines that this situation would be compatible with >90% of ASIC designs.

Other types of PSMs have also been developed in an attempt to overcome the drawbacks of ALT-PSMs for some applications. Before describing these other types of PSMs it should be mentioned that the various types of PSMs are grouped into so-called *strong* and *weak* PSMs. Therefore, these terms must be defined. The distinction is based on the maximum degree of improved resolution and depth of focus that each type can provide. Strong-PSMs (such as ALT-PSMs) can provide up to a 40% improvement in resolution, but a lesser improvement in depth of focus. Weak-PSMs (such as the *rim-shift-PSMs* and the *attenuated* [or *halftone*] PSMs which are described next) offer less improvement in resolution, but more improvement in depth of focus. The benefits each group offers are different, and this implies that the “best” type of PSM depends on the particular application (as described in more detail later).

One of such alternative type of PSMs is the *rim-shift-PSM*, which falls into the group of weak-PSMs. The rim-shift-PSM was developed to address the problem of overlay in PSM structures by creating a self-aligned phase-shifting structure. In the fabrication of such structures, a phase-shifter film is deposited onto the chrome layer and then resist is spun onto the reticle. The resist is then patterned by e-beam exposure and developing.

This is followed by an anisotropic etching of the phase-shifter film. Finally, the chrome film is etched isotropically so that it undercuts the phase-shifting film




Fig. 7-19 Problem at the edge of a phase-shifter at a clear boundary: (a) ALT-PSM used on lines and spaces pattern with a clear field. Dark lines will print at the boundaries between the edge of the phase shifter and non-shifted clear areas; (b) E -fields along the z -axis between C and D for light incident on the phase shifter and clear area; (c) These two E -fields interfere in the vicinity of $z = 0$, causing the intensity of the E -field there to drop, resulting in a dark line printed as shown in (a); (d) Adding an extension of phase shifting material (with $\phi = 90^\circ$) at the end of the phase-shifting region (as shown in [d]), helps mitigate the problem; (e) The amplitude of the E -fields of the light for the three phase regions versus z ; (f) Intensity of light versus z when the $\phi = 90^\circ$ extension is present. Note that the intensity drop-off is much smaller when interference occurs, and the dark line may no longer print.

(see Fig. 7-21). In rim-shift -PSMs the phase -shifting takes place only at the rim of each mask feature. As a result, such PSMs do not provide as much resolution improvement as do the ALT-PSMs. However, they do not suffer from the pattern restrictions that hinder ALT-PSMs. Thus, they can be used for arbit-




Fig. 7-20 On the left, extra resist printed by the phase edge, for positive photoresist. The right side of the figure shows what occurs with negative resist.

rary reticle patterns, including isolated features. Among the issues of concern are rim-size optimization and the lack of inspection and repair of the phase-shifting materials of the mask.

Another type of weak-PSM that can also be applied to arbitrary layout patterns is the *attenuated* (or *halftone*) PSM.^{33,34} Such *attPSMs* are fabricated by replacing the opaque part of a conventional reticle with a halftone film (i.e., one that is partially transmissive, about 10%). For example, for *i*-line-light such a film can be made from a very thin layer of chromium oxynitride or Mo-Si-ON (molybdenum silicon-oxynitride) having the proper thickness to shift the phase of the light it transmits by 180° (Fig. 7-22). While some light will pass through the halftone film, it will be too weak to expose the photoresist to the degree necessary for it to be washed away during development. But the negative amplitude of this weak phase-shifted light will destructively interfere with the non-phase-shifted light so that a useful (if weak) improvement in the resolution is achieved. The attPSMs are generally considered better than rim-shift PSMs. This




Fig. 7-21 Example of a rim-shift phase-shifting mask.




Fig. 7-22 Principle of the attenuated-PSM (attPSM).³¹ © IEEE (1993)

is because attPSMs are much easier to fabricate (since the halftone absorber layer can be patterned just as if it was the opaque layer of a conventional mask). Isolated defects (either clear or opaque) can also be repaired with conventional repair techniques. Because of their relative simplicity, attPSMs have been the first type of PSM to be adopted in commercial IC fabrication. One limitation of attPSMs is that they are themselves subject to optical-proximity-effects. One approach to reducing this problem is to combine OPC with attPSMs. The reticle in this case must be made with three tones (clear, attenuated chrome, and opaque chrome). This technique is called *ternary attenuated PSM*, and MicroUnity provides software that allows such OPC features to be designed into the attPSM reticle pattern.³⁵

Although PSMs were introduced in 1982, there was scant interest in the technique until about 1988. At that point, a large surge in research about PSMs began. While this resulted in dozens of papers dealing with this topic being published over the next ten years, PSMs were not widely introduced into production until the late 1990s. Even by 1997 only about 1% of the world's mask output contained PSMs. However, as 0.18- μm -CMOS was being moved into production in 1999 it became apparent that resolution-enhancement-techniques including PSMs would have to be used to enable optical lithography to print such small features. By 2000 attPSMs were being used extensively in manufacturing. Such weak attenuating (or halftone) PSMs were being used on 0.18- μm contact-hole levels. Strong-ALT-PSMs were being used on levels containing gates and interconnect lines. ALT-PSMs were also being used in memory circuits, in which interconnect lines are closely and regularly spaced. Reticle inspection techniques for ALT-PSMs were introduced by 1999, but repair techniques still lagged at that

time. The combination of attenuated PSMs and off-axis illumination provides an especially effective resolution-enhancement technology, as each method alone is only able to partially reduce the zero-order light component.

From the descriptions provided above – and from that of previous sections – we can see that a particular type of phase-shifting-mask or modified-illumination is applicable as a RET in specific situations, but not in others. It was noted that ALT-PSMs are effective for dense lines and spaces but not for isolated contacts. On the other hand, attPSMs are applicable for contacts and isolated features. Likewise, off-axis-illumination is found to enhance imaging of dense lines and spaces, but does not particularly improve the patterning of isolated-features. These general trends appear to be true for many of the newly developed methods of enhancing optical lithography. That is, as the improvement is restricted to specific types of features; there is no single solution for them all.

7.4 MASK ERROR FACTOR (MEF, or MEEF)

Masks generally include geometries of various dimensions. The fact that a mask contains a fairly wide range of feature sizes implies that lithographic imaging tools and resist processes should exhibit *linearity*. By this we mean that imaged patterns on the wafer should have the same size as the original patterns on the reticle (after applying the lens reduction factor). In other words, the printed features should all be approximately the size of the corresponding feature on the mask (divided by the lens reduction factor), over a wide range of feature sizes (i.e., a 4X reduction stepper should print a 10- μm -wide line on the wafer from a line on a reticle which is 40- μm wide, and it should print a 1- μm -wide line on the wafer from a 4- μm -wide line on a reticle).

However, as the printed feature sizes approach the resolution limit of the lens, *non-linearity* is found to occur.³⁷ This effect is shown in Fig. 7-23, which shows the results for a 248-nm stepper. The data in the figure indicates that linearity between the reticle-feature-size and printed-feature-size is obtained for printed-feature-sizes down to about 150% of the exposure-wavelength. That is, one can see that for the case of a 248-nm stepper, as long as the reticle dimensions are larger than 1300-nm (which is $4 \times 325 \text{ nm}$), the reticle-dimensions are transferred to the printed-features in a 4:1 ratio. However, for smaller features, the dimensions on the wafer are transferred at a ratio greater than 4:1. This means that when critical geometries are being printed, corrections on the mask must be made to account for this non-linearity. This type of print-bias is a function of feature-size, and therefore can be corrected by appropriately resizing the features on the mask.




Fig. 7-23 Transfer of features from a reticle to the wafer. The features are reduced in size by 4x for large feature size, but the reduction changes for features near the resolution limit of the lens.

Since the quality of exposure tool lenses has improved and resolution enhancement technology has provided the means to push imaging performance below the wavelength of the exposure light (i.e., to less than 100% of the exposure wavelength), the smallest features that we now expect to be able to print are in the regime where such non-linearity becomes significant. Hence, this non-linearity effect has become very important from a practical point of view.

Another consequence of the non-linear printing of features near the resolution limit of a lens is that there is a *change in the magnitude by which mask linewidth errors* are transferred by the lens. That is, for larger printed feature sizes (i.e., those which exceed about 150% of the exposure wavelength), mask errors are transferred to the printed feature in the same ratio as the lens reduction factor. For example, in a 4X lens, a 20-nm error in the reticle CD for a 400-nm (4- μ m) mask feature, would result in only a 5-nm printed error in the 1- μ m printed line (because the transfer is still linear for this feature size). However, what is implied by the data of Fig. 7-23 is that *variations in linewidth about their nominal size are not reduced by the lens reduction factor when small features are imaged*. Instead, the effective mask-dimension-error is magnified. The severity of this amplification is described by the so-called *mask error factor (MEF)*. Note that this factor is also called the *mask error enhancement factor (MEEF)*, but we will use the abbreviation MEF here. The MEF is defined as:

$$\text{MEF} = M (\Delta\text{CD}_{\text{printed}} / \Delta\text{CD}_{\text{mask}}) \quad (7.2)$$

Where M is the nominal magnification of the mask compared to the wafer image, and $\Delta CD_{\text{printed}}$ is the change in the CD of the printed feature, and ΔCD_{mask} is the change in CD on the mask. If $MEF > 1$, the errors in the mask CDs are transferred to the printed features on the wafer by an amount that is greater than would occur if $MEF = 1$, even if the mask CD gets geometrically reduced by the proper ratio (e.g., 4:1). This makes it more difficult to control wafer CDs in the presence of inevitable mask errors. For example, for the case described in the previous paragraph, the $MEF = 1$. However, if the MEF in that case was instead $= 2$, the error in the CD of the printed line would increase from 5-nm to 10-nm for an error of 20-nm on the reticle (see Fig. 7-24).

The primary factor that causes the values of MEF to rise above 1.0 is the degradation of the image contrast as the factor $(CD_{\text{printed}} \lambda / NA)$ is decreased below 0.6. In an imaging system with no aberrations and no defocus, it has been found that MEF rises to over 4 when $(CD_{\text{printed}} \lambda / NA) = 0.35$. (The 0.35 value corresponds to a resolution of 125-nm for a KrF-stepper with an NA of 0.7.) In such circumstances (i.e., if $MEF = 4$), any reticle linewidth variations will transfer 1:1 on 4X reduction exposure tools. In such cases, the entire benefit of lens reduction (whose role is to reduce the impact of reticle variations on wafer linewidth control) is completely absent.

It has been found that exposure-dose has little significant effect on the MEF . The MEF is related to the mask size and the imaging system, not the resist size.




Fig. 7-24 For a $MEF > 1$, a small CD-error on a 4X mask can transfer a larger magnitude of error onto the wafer. (Courtesy KLA-Tencor)

Therefore, reticle biasing does not really help to reduce MEF, although it may be desired for other reasons. The MEF degrades somewhat with defocus, but the degradation is small for defocus smaller than the Rayleigh unit of defocus, $\lambda/2NA$.

The most significant factor that can control the MEF is improvement in the image contrast. This improvement can be achieved in various ways, including the use of more advanced exposure tools (shorter wavelength, higher NA, better aberration control), and through the use of some of the resolution enhancement techniques. Of particular benefit, at small cost, is the use of annular or quadrupole illumination. The disadvantage is that the proximity effects tend to be emphasized and the isolated-to-dense feature bias control suffers.

The MEF also has a significant impact on reticle costs. That is, as long as $MEF = 1$, improvements in reticle linewidth control only had to match the decrease in minimum feature size (in order to keep constant the reticle contributions to wafer linewidth variations). However, as noted above, with MEF values as large as 4 now being reported, the challenges facing reticle makers have been increased. That is, multiple improvements in the quality of photomasks will be necessary to limit the effects of MEF. Even if these improvements should prove technically feasible, they will only be achieved with increased cost.

These reticle improvements include tighter CD-control and metrology, and tighter enforcement of defect inspection parameters. Characterization must be performed in each area of the wafer because MEF is not uniform (isolated lines generally have a lower MEF than do equally sized dense lines, and near the diffraction limit, contacts have $\sim 2\times$ the MEF of lines and spaces of similar width), and defects near the feature edge are magnified by MEF (just like CD errors). This creates a paradigm shift in sample size and will also require new developments in defect inspection tools. Typically, reticles have been specified with 5 to 10 measurement-sites using white light or *i*-line-metrology. However, with tighter specifications in both CD and defects, the $1\text{-}\mu\text{m}$ optical metrology limit and such small sample sizes are no longer adequate. Generally used at the wafer level, CD SEMs with resolutions $\sim 4\text{ nm}$, are now being applied to manufacturing the mask sets for $0.15\text{ }\mu\text{m}$ memory cells (whose CDs are $0.6\text{ }\mu\text{m}$ on the reticle). Inspection-tool improvements are allowing such higher resolution limits to be achieved on 5 to 15 times more sites – with overall measurement times remaining the same ($\sim 5\text{ min/mask}$). Another path toward reducing MEF, as described by Kim *et al.*,³⁸ is to widen the exposure latitude using all means available (including improving aerial image contrast with strong phase-shift masks).

7.5 EXTENDING THE LIMITS OF OPTICAL LITHOGRAPHY

In the late 1970's, the demise of optical lithography was predicted to occur when IC feature sizes reached about $1\text{-}\mu\text{m}$. Since optical lithography is being used for $0.13\text{-}\mu\text{m}$ IC technologies, this prediction was obviously incorrect. Nevertheless, some limits to optical microlithography do exist, and the consensus today is still that some other lithographic technology will replace optical lithography at a future date.

The resolution limit of optical lithography was also once considered to be about the same dimension as the wavelength of the exposure light. However, as noted in Sect. 7-3, by employing *resolution enhancement technologies* (RETs) the minimum feature size that can now be practically imaged is about 50% smaller than the exposure wavelength (e.g., $0.13\text{-}\mu\text{m}$ features can be produced with 248-nm KrF light).³⁹ As a result, the rate of shrinkage of the minimum feature size has been faster than the reduction of the exposure wavelength. (For $0.18\text{-}\mu\text{m}$ technology, KrF excimer-laser-based lithography is employed, with the KrF wavelength being 248-nm [$0.248\mu\text{m}$]).

To image $0.13\text{-}\mu\text{m}$ features without having to resort to such resolution enhancement techniques as PSM, off-axis-illumination, OPC, and multi-layer resists, however, a shorter wavelength of light is needed (e.g., ArF-excimer-laser light that has a wavelength of 193-nm). Since ArF technology (including appropriate light sources, lens materials, and resists), did not become available in time for full-scale production of $0.18\text{-}\mu\text{m}$ ICs, adoption of such RETs onto KrF has been the way that $0.18\text{-}\mu\text{m}$ technology is being manufactured. In 1999 the first generation 193-nm ArF 4:1 stepper/scanners from ASML, Canon, and SVG Lithography were installed on $0.13\text{-}\mu\text{m}$ development lines. The average price of ArF steppers is \$10-\$15 million. ArF resists from Olin, and others (based on acrylates and cyclic olefin polymer materials – see Chap. 6), were available for pilot-line use. But it appears that ArF excimer-light (or some other shorter wavelength energy source) will be needed to obtain adequate resolution with sufficient depth of focus for the next generation ($0.1\text{-}\mu\text{m}$ -CMOS). Note that even at $0.1\text{-}\mu\text{m}$, the dimension of the feature being printed is smaller than even the wavelength of ArF excimer-light. Thus, RETs will also be needed. (Another financial drawback is that ArF light appears to damage the fused-silica used for ArF lenses. Thus, the \$1.5-million lens in ArF stepper/scanners may need to be replaced after three years of use.) Since (for reasons we will describe next), it appears that the limit of optical lithography is now predicted to be $0.05\text{-}0.07\text{-}\mu\text{m}$ (50-70-nm), non-optical techniques will eventually be needed.⁴⁵ Such non-optical alternatives are considered in the next section.

We noted above that in the 1970's it was predicted that it would not be possible to use optical lithography for IC technologies below about 1 μm . There were several reasons why this estimate proved to be incorrect, as follows:

1. In the decade starting in 1985, lens-making technology made significant and unexpected advances. For example, as noted in Sect. 7.2, 0.3-NA, *g*-line lenses being manufactured in 1980 had a resolution limit of 1.25- μm and a depth-of-focus of 1.5- μm . By 1996 Nikon was offering lenses with the same NA, but with much improved performance (i.e., these Nikon *i*-line-lenses with 0.3-NA had a resolution limit of 0.7- μm and a depth of focus of 5.0- μm). The reason for this improvement was that the lenses being manufactured in the mid-1985's were not yet diffraction limited (but were still being limited by lens aberrations). By 1996, lens-making technology had improved to the degree that the lenses actually were diffraction limited. In addition, it was learned how to make lenses with much larger NA than in 1980. For example, by 2001, lenses with an NA as large as 0.8 were being offered commercially. (However, since the NA of lenses cannot exceed 1, and since diffraction-limited lenses are as perfect as they can be, it will not be possible to obtain the gains provided to optical lithography from such ingenuity and innovation in lens-making again.)
2. Optical lithography technologies were developed that could use shorter wavelengths than the mercury *g*-line (436-nm). The ability to use such shorter wavelengths not only reduced the resolution limit, but also brought with it an increased depth of focus.
3. Photoresists also were improved, allowing the k_1 values to be reduced. For example, in 1980 $k_1 = 0.8$, but by 2001, k_1 was decreased to < 0.5 .
4. The depth of focus requirements (DOF) were decreased (down to about $\pm 0.2\text{-}\mu\text{m}$), primarily due to the development of chemical-mechanical polishing (CMP).
5. Resolution enhancement technologies (RETs) were developed.

Despite these advances, there are several physical limits that are being reached that imply that the optical lithography will need to be replaced when the minimum feature sizes on ICs reach 50-70-nm. Let us list those limits, which have been stated by such industry experts as H. Levinson to justify the 50-70-nm resolution limit of optical lithography.⁴⁰

1. To get to 70-nm resolution with optical lithography, shorter wavelengths of light will be needed. UV lasers operating at 157-nm (F_2) and 126-nm (Ar_2^*), are possible illumination sources for such shorter wavelengths.

Since virtually all materials absorb strongly in the range of 20–193-nm (except for some, like calcium fluoride [CaF_2] that still transmit 157-nm and 126-nm light), it may be necessary to use all-reflective optical systems at these wavelengths. (Extreme UV [EUV] lithography, discussed in Sect.7.6.1, uses such all-reflective optical systems.) However, as discussed previously, by 1999 advances in F_2 -laser technology, in the growing of CaF_2 -crystals, and in 157-nm resist chemistry made 157-nm lithography a possible candidate to fill the 0.1- μm “lithography gap” that exists.⁴¹

However, the thermal stability of the mask-substrate material may make it impractical to go to 126-nm illumination. That is, fused-silica can be still used for the mask substrate material because it still sufficiently transparent at 157-nm. However, it becomes too absorbing just a few nanometers below 157-nm, and thus it is not a material that can be used for masks at 126-nm. For such masks, a material such as CaF_2 must be used (since CaF_2 is still sufficiently transparent at 126-nm). However, the coefficient of thermal expansion of fused-silica is much smaller than that of CaF_2 (0.5-ppm/K vs 19 ppm/K). When a reticle is being exposed with an e-beam (to create the patterns on the reticle), substantial energy is absorbed by the mask-substrate material, and this causes the temperature of the mask blank to rise. Assuming that the temperature-rise can be limited to only 0.1K, there will be a 5-nm registration error across 100-mm on a substrate made




Fig. 7-25 Diminishing returns of higher NA for higher resolution. For lens with an NA greater than 0.80 NA, each incremental increase in lens-resolving power requires disproportionately larger increases in lens diameter. The ratio represents the difference of lens diameter to resolving power at a given NA.

of fused-silica (a magnitude of mis-registration that can easily be accommodated within overlay budgets). However, if the mask blank is made of CaF_2 , the same temperature-rise will cause a mis-registration error of 100-nm across 100-mm, making it impractical to use CaF_2 as the mask substrate material. Thus, it appears that 157-nm will be the shortest wavelength that can be used for an optical lithography process.

2. As noted earlier, lenses cannot be made any more perfect than when they are diffraction limited. Thus, the remaining limitation imposed by diffraction remains and becomes dominant. In addition, it is unlikely that lithography will be carried out in a medium other than a vacuum or gas (such as air or nitrogen). This limits the NA of a lens to < 1 . Since the NA of lenses available in 2001 is already at 0.8 in the most advanced scanners, increases in NA in the future can no longer be a key driver to higher resolution that it has been in the past. Thus, the great strides of lithography due to improvements in lens fabrication are no longer possible (Fig. 7-25).³⁹

3. The decrease in depth-of-focus requirements down to $\pm 0.2\text{-}\mu\text{m}$ was brought about by the use of CMP. However, it will not be possible to reduce this requirement further, as the wafer topographies are now about as flat as they can get.

4. The degree to which optical lithography can be extended toward the 50-nm limit depends on how effectively all of the RET methods described earlier can be implemented. The ability to implement a particular RET technique also depends on the application. As an example that was described earlier, the use of off-axis-illumination is highly effective for imaging highly repetitive structures (such as those found in memories), but the same technique is of not much benefit for imaging isolated features.

In summary, there are many challenges to be met to enable optical lithography to be extended to 70-nm ($0.07\text{-}\mu\text{m}$), although there is optimism that this goal will be achieved (Fig. 7-26).⁴⁰ However, for the reasons given above, 50-nm ($0.05\text{-}\mu\text{m}$) appears to be a clear lower limit for optical lithography.⁴¹

It is also probable that a mix-and-match strategy will be employed when ICs are fabricated with features smaller than $0.1\text{-}\mu\text{m}$. That is, a non-optical lithography process may be used for the layers with the smallest minimum dimension, and optical lithography techniques for the non-critical layers. Figure 7-27 shows the relationship between resolution and exposure wavelength for various types of microlithographic technologies.⁴²




Fig. 7-26 Wavelength, NA, and k_1 for 250 nm to 50 nm resolution nodes. (Courtesy ASML)

Overlay limits are another issue to be considered with optical systems. Stage precision is the biggest practical concern, but work is reportedly being carried out to solve this problem.⁴³ Another overlay issue involves alignment target acquisition. Metal and grainy polysilicon have long presented difficulties for stepper




Fig. 7-27 Relationship between resolution and exposure wave length for various microlithographic technologies.⁴² © 1996 (IEEE).

alignment systems. More recently, additional problems have been encountered on wafers that have undergone chemical-mechanical polishing. One solution has been to align all layers to a “zero layer” having consistent alignment targets.

The best level-to-level overlay-capability of optical steppers is estimated to be about 30-nm, which will be adequate for 0.1- μm technology, but not for 0.07- μm . For 0.07- μm technology, it may be necessary to dedicate individual steppers to a particular wafer lot. This will reduce overall stepper productivity and introduce another source of additional costs.⁴⁴

7.6 NON-OPTICAL (or NEXT GENERATION) LITHOGRAPHIC TECHNOLOGIES (NGL)

In order to image features smaller than 70-nm it will probably be necessary to employ some form of non-optical technology (or *next generation lithography*, *NGL*).⁵² Two such NGL candidates will be discussed in this section: 1) extreme ultra-violet (EUV) lithography; and 2) electron-beam projection lithography (EPL). It should be noted, however, that by 2001, extreme ultra-violet (EUV) lithography had become the leading NGL technology. The others had become extinct (proximity x-ray and direct-write e-beam), or on put on the endangered species list (EPL). The EPL approach suffered a punishing blow in late-2000 when Agere Bell Laboratories cancelled its research effort. However, since it remains alive under the auspices of an IBM-Nikon led research effort, we will provide a brief description of this candidate NGL technology as well.

It should also be noted that in 2001 the consensus was that non-optical techniques were still behind the overall production capability of optical micro-lithography (especially with respect to productivity).⁴⁵ Two additional difficulties are shared by non-optical lithographic techniques: 1) the cost of a single mask is expected to be in the \$50,00–\$100,000 range; and 2) no pellicles can be mounted on the masks to protect them from particles. The latter problem makes masks for non-optical technologies much more vulnerable to particles and other defects.

7.6.1 Extreme Ultra-Violet Reflective Projection Lithography (EUV)

An attempt is being made to extend the principles of projection lithography into the soft x-ray spectrum. (The region of the spectrum with photon energies of about 100-eV and with wavelengths between 10-15-nm [or 0.01–0.015- μm] can be considered either at the low end of the x-ray spectrum (*soft x-rays*), or the short wavelength limit of the *extreme ultra-violet* spectrum [EUV].) The chief reason EUV seems to be emerging as the winner in the NGL race is that EUV demands the fewest changes in manufacturing from the current methods, and




Fig. 7-28 (a) Schematic drawing of the optics of an EUV system. (b) An artists drawing of an EUV lithography system. A laser generates EUV radiation by exciting a laser produced plasma. This radiation is collected by a multilayer condenser system. The radiation illuminates a multilayer coated reflection mask, which is imaged and demagnified onto a resist-coated wafer.⁴⁶ Reprinted with permission of Solid State Technology, published by PennWell.

therefore appears to involve the least risk. (In an industry where downtime at an average fab costs \$4 million a day, risk is not taken lightly.) For example, EUV radiation is more like light than any of the other alternatives. That is, it still involves photons, rather than electrons or ions, and the industry has grown comfortable with photons.

Furthermore, EUV photons can be focused with reflective lenses (which are actually curved mirrors). Use of these mirrors enables reduction optics to be used, which in turn allows photomasks to be fabricated with much larger dimensions than the features being imaged. Such masks are much easier to fabricate than masks containing patterns of the same size as the imaged features.

A number of interference coatings that exhibit relatively good reflectivity of such EUV light have been developed (i.e., silicon/molybdenum composites - deposited by sputtering), and they can be used to produce EUV mirrors. These coatings make it feasible to design projection systems that use all-reflective lithographic components to image patterns with EUV. The microlithographic technology based on this approach is called *extreme ultraviolet lithography*

(EUVL), or *soft x-ray projection lithography*.⁴⁷ Figure 7-28 shows a schematic of an EUV lithography system. A short survey of EUV technology is provided here. For more details, readers are referred to the excellent book by Attwood.⁵³

EUV radiation can be generated in a number of ways. *Laser plasma sources* have shown promise as EUV light sources. They utilize pulses of high-intensity laser-light (normally from a Nd-YAG laser) to strike a target material (typically a supersonic jet of xenon gas). This produces a plasma that emits light with a broadband radiation that contains a significant component of EUV radiation. Xenon gas is the most common target material because it produces relatively strong EUV radiation, and being inert, does not directly generate debris that would contaminate and degrade the EUV optics. Unfortunately, these lasers may not be robust enough to be able to provide reliable operation in a production environment.

Synchrotrons (such as those used in proximity x-ray lithography) can also serve as the source of EUV light. Their main drawback is that they are not standalone light sources. Chip makers would prefer a standalone light source. With many standalone light sources in a fab instead of one synchrotron, the risk of having to shut down an entire fab if the light source fails is avoided. Some other alternative light source technologies were reportedly under development, but by the end of 2001 public information about them was not yet available.

In any case, the EUV radiation from the light source is collected and shaped into a narrow arc by a system of mirrors coated with EUV interference films. This radiation is then used to illuminate an EUV reflection reticle. The pattern on the reticle is then de-magnified (by 4X or 5X) and imaged onto a resist-coated wafer. The entire reticle pattern is exposed onto the wafer by synchronously scanning the reticle and the wafer (i.e., a step-and-scan exposure is performed). By using Rayleigh's resolution equation, it is predicted that a resolution of 32-nm can be achieved using a wavelength of 13.4-nm in a system having an $NA = 0.25$, with a k_1 -value of 0.6. EUV lithography also offers the benefit of a large depth-of-focus for a system of such resolution (i.e., a DOF of greater than 1-micron). As noted earlier, since reduction optics are possible, many of the mask problems associated with proximity x-ray lithography are overcome.

However, there are a number of formidable challenges that must be met to make this technology practical. First, a modestly-priced, highly-reliable light source is still needed. Second, the stepper and the EUV beam-delivery system must be operated in a vacuum to prevent absorption and scattering of EUV rays. Third, the absence of transparent materials at EUV wavelengths implies that pellicles cannot be used (especially since the EUV light must pass through a

pellicle twice in the reflection optics of EUV systems). Finally, since there are no high-transmission materials in the EUV, not only must all optical elements be reflecting, so must the mask. There are numerous issues involved in the fabrication of such reflecting optical elements and masks, and these will be discussed in the following paragraphs. While all of the above challenges appear daunting, significant progress was reportedly being made by 2001 to meet them.^{55,56}

Fabrication of the reflective optical elements and masks for EUV requires a technology that can not only create surfaces with a relatively high reflectance, but that can also shape the surfaces of such reflective optical elements to extremely high optical tolerances. High mirror reflectance is important for EUV exposure tool productivity because such tools contain many reflecting surfaces (e.g., six mirrors in the projecting optics, two mirrors in the illuminator, and a reflection mask). Since the EUV light reflects nine times in such a system, the intensity of light at the wafer plane will be nearly 30% greater if each reflector has a 70% reflectance - compared to the case where each reflector has a 68% reflectance. Hence, even small increases in reflectance are significant.

Reflection occurs at interfaces between materials of different indices of refraction. However, at wavelengths below 50-nm all materials exhibit comparable indices of refraction (~ 1). Thus, it is difficult to make *single* interfaces that are good reflectors of EUV light. However, a technique that uses *multiple* interfaces can produce moderately effective EUV reflectors (i.e., with 60-70% reflectance). That is, such reflectors consist of a multilayer structure having a stack of many (e.g., 40 pairs) thin films (i.e., each with a thickness of tens of angstroms). This stack consists of alternating thin layers of high-Z and low-Z materials (where Z is the atomic number of the element being used in the film). This arrangement is used because there is a small but effective difference between the refractive indices at a high-Z/low-Z interface (see Fig. 7-29). Furthermore, by making the periodicity d of the multilayer satisfy the Bragg condition ($\lambda/2\sin\theta$), the reflected light from each interface adds to the reflected light from the other interfaces. The net effect is that by combining the small reflectivity at each interface it is possible to achieve a moderately high reflectivity overall (assuming there are a sufficient number of layers).

The materials for each layer must also be weak absorbers of EUV light, since the light must be able to penetrate to the lower levels of the film stack (which also explains the need to use as thin a film as possible for each layer). Most efforts have focused on using Mo and Si as the high-Z and low-Z materials for each layer of the EUV reflector, respectively. A 68% reflectance has been




Fig. 7-29 Principle of a multilayer reflector for EUV radiation.

achieved for reflectors made with such Mo/Si multilayers for an EUV wavelength of 13.4-nm. However, the reflectivity will need to be improved to >70% to enable high-throughput cost-effective lithography. These layers are deposited by physical vapor deposition (sputtering), and each layer must be deposited to a thickness accuracy of less than an angstrom. Note that since most elements are strong absorbers at EUV wavelengths, even sub-monolayers of contaminants can reduce mirror reflectance. As a result, mirror (and mask) contamination is an important issue for EUV lithography. Finally, these interference films must be able to withstand exposure to strong EUV radiation without damage over long periods of time.

The fabrication of the aspheric (non-spherical) mirror substrates (the curved surfaces onto which the multilayer stacks must be deposited) is difficult because of the extremely tight tolerance (i.e., better than 2-nm) on the *surface figure* of these elements. Optics producers will need new metrology techniques to measure figure and surface roughness of these mirrors to the required accuracies. It was reported by workers at the Lawrence Livermore Laboratories in March 2001 that it was taking a full year to make a mirror set for EUV at that time. Industrial insertion would require manufacturing 300 such sets/year, a daunting challenge.

The *EUV masks* are fabricated by depositing the reflecting multilayers described above, on a flat substrate. Absorbing materials are then deposited and patterned on the multilayer, completing the mask fabrication. Since nearly all materials absorb EUV radiation, various films can be used for the absorber,

including chromium, TiN, and TaN. The choice of absorber material is based on their ability to be deposited, etched, and cleaned. One of the problems of using Mo/Si multilayers on EUV masks is that they begin to significantly intermix at temperatures above 150°C. Such intermixing reduces the reflectivity of the stack. This limits the maximum process temperatures used to deposit and etch the absorber layers on EUV masks. By 2001, it was reported that EUV developers had devised a way to repair masks when defects are inadvertently incorporated during their fabrication.

Another consequence of the high absorptivity of all materials at EUV is the need for ultrathin resists (< 200-nm-thick). The resist-collapse problem that occurs when resist features have high aspect-ratios also dictates the use of thin resists (Chap. 6). However, it has been demonstrated that lithography processes suitable for manufacturing are feasible with such ultrathin resists. Moreover, resists quite similar to those used for DUV lithography appear to be suitable for EUV lithography.

EUV development is being carried out by a unique U.S. government-industry consortium known as the EUV Limited Liability Corporation (LLC). Under the terms of the agreement, three national laboratories, Sandia, Lawrence-Livermore, and Lawrence-Berkeley – are doing most of the development work, while industry members supervise and foot the bills. The core of the industry group consists of five chip makers: Intel, AMD, Infineon, Micron Technology, and Motorola. In April, 2001, the first full-scale prototype EUV lithography system was unveiled (Fig. 7-30).⁵⁴ This system, called the Engineering Test Stand (ETS) measures about 10x10x10 ft. The light source is a 1500-watt laser plasma source that generates an EUV beam with 10-W of power. (More than 50-W will be needed by the time the EUV systems reach production, as this is the power expected to be needed to allow throughputs of 70 300-mm wafers per hour.) The EUV LLC announced in March 2001 that the ETS was used to successfully print lines at 100-nm spacings. It was predicted that by the end of 2001, the ETS would be printing 70-nm lines and spaces at full field sizes. Debates are occurring at the end of 2001 as to when EUV will be ready for high-volume production. The optimists say that this will take place by 2005. Others argue that while early production units may be ready by then, high-volume manufacturing will take 2 to 3 years longer.

7.6.2 Electron Beam Projection Lithography (SCALPEL and PREVAIL)

Another NGL technique based on *e-beam projection* has been pursued (EPL). The system developed by Lucent Technologies (now Agere), is called *Scattering*




Fig. 7-30 A worker inspects the Engineering Test Stand, a full-scale prototype EUV lithography system – as assembled at Sandia National Laboratories. (Courtesy Sandia Labs).

with *Angular Limitation in Projection Electron beam Lithography* (or *SCALPEL*).^{47,48} In this approach, a special scattering mask is used to produce a high-contrast image with a technique commonly used in transmission electron microscopy. That is, an electron beam (coming down from the top of Fig. 7-31) is scanned across a special mask that consists of a thin silicon nitride (SiN) blank (100–150-nm thick) having mask patterns formed of very thin (i.e., 25–50-nm-thick) tungsten or gold features. The electrons from the scanned beam can either: 1) strike regions of the mask covered with one of the metal patterns; or 2) strike a region of the mask *not* covered with metal. Electrons striking the SiN film pass straight through it (i.e., SiN only weakly scatters the beam electrons). On the other hand, electrons striking the metal patterns are strongly scattered as they pass through the heavy metal of the mask features. Those that have passed unscattered through the silicon nitride are then focussed by a lens so that they pass through the aperture of the *back focal-plane filter*. But most of the electrons that are scattered as they travel through the metal patterns get blocked by the back focal-plane filter (and thus do not travel through its aperture). The electrons that make it through the filter aperture are demagnified and strike the wafer

surface (whereupon they form a high-contrast, 4:1-reduced image of the scattering mask).

The resolution limits of SCALPEL can be extended below $0.1\text{-}\mu\text{m}$. In addition, because the scattering patterns are so thin, the demagnification of the mask can be made small enough that chips can be fabricated with as many as 2×10^{10} pixels (defined here as a small square whose side is equal to the minimum printable linewidth). Since 1-Gigabit DRAM patterns, for example, need roughly 10^{10} lithographic pixels per chip, the SCALPEL technique is suitable for such chip designs. The thin silicon nitride mask-blank substrate is supported on a silicon wafer with periodic silicon support struts. These struts are not imaged onto the wafer since the patterns are shifted into place as they are illuminated. While the mask structure is similar to that used in x-ray masks, the silicon support struts provide greater dimensional stability of the patterns on the




Fig. 7-31 Schematic of the SCALPEL technique. Electrons (1) that hit the scatterer (the metal patterns on the mask) are strongly scattered, and most are filtered out by the aperture. Electrons traveling through the silicon nitride membrane (2, 3) are only weakly scattered and pass through the aperture. These are demagnified to form a high contrast image on the substrate. Courtesy of Lucent Technologies, Inc.

SCALPEL mask, and the use of 4:1 reduction optics makes mask fabrication of the 4:1 reduction masks simpler. The initial price of a SCALPEL system (1998) was \$8 million.

One advantage of SCALPEL over x-ray lithography is that it does not require a synchrotron orbital radiation (SOR) ring. Such an SOR ring is expensive, and is designed to be used with multiple steppers. Instead, a good e-beam source for SCALPEL is available. For SCALPEL, if another stepper is needed, only the stepper need be purchased. Another advantage is that the scanning e-beam that passes through the mask produces little heat in the thin nitride mask membrane and this reduces distortion of the imaged pattern on the wafer. Finally, SCALPEL's depth-of-focus has been measured to be ~50 times greater than for 0.25 μm optical lithography techniques. On the other hand, the traditional problems of e-beam lithography, such as low throughput, proximity effects, radiation damage, charging, and lack of a good resist are limitations of SCALPEL. Some other concerns involve keeping the membrane clean, and finding ways to repair it. A goal of producing working SCALPEL steppers that can deliver up to 50 300-mm wafer per hour at 0.13- μm resolution by 2003 has been established.

In 2001, however, EPL appeared to be losing some of its momentum, with EUV gaining support instead. Motorola dropped out of the group of companies backing EPL, and Applied Materials and ASML disbanded their eLith LLC venture that was to have commercialized the SCALPEL technology. However, several of the EPL backers remained committed to developing the approach. Agere and TI switched their allegiance to the EPL approach being developed by Nikon and IBM (as did the semiconductor companies belonging to the Selete equipment consortium in Japan). The Nikon-IBM approach is called PREVAIL. These companies argue that EPL is better-suited to small-volume ASICs than the EUV system, which requires more expensive masks. Nikon is preparing to offer the PREVAIL e-beam column for e-beam projection lithography by 2004 (and perhaps earlier).

REFERENCES

1. O. Semprez, "Excimer Lasers for Future Lithography," *Solid State Technology*, July 2000, p. 255.
2. A. Ershov *et al.*, "Feasibility Studies of Operating KrF Lasers at Ultra-Narrow Spectral Bandwidths for 0.18 μm Linewidths," *Proc. SPIE.*, Vol. 3334, Feb. 1998.

3. A. Hand, "KrF Lithography Not Finished Yet," *Semiconductor International*, February 2001 p. 58.
4. M.D. Levenson, "Is There Light at the End of NGL Tunnel?" *Solid State Technology*, May 2001, p. 51.
5. R. DeJule, "157-nm Lithography Moves Forward," *Semiconductor International*, July 2000, p. 82.
6. R. DeJule, "NGL's Critical Bridge: 157 nm," *Semiconductor International*, March 1999, p. 36.
7. A. Hand, "Ready or Not, When Will 157-nm Lithography Really be Needed?" *Semiconductor International*, May 2001, p. 42.
8. B. Wang, "Birefringence in Fused Silica and CaF₂ for Lithography," *Solid State Technology*, February 2000, p. 77.
9. A. Hand, "Intrinsic Birefringence of CaF₂ Won't Halt 157-nm Lithography," *Semiconductor International*, September 2001, p. 42.
10. "Lithography Tools for 300-mm," *Solid State Technology*, September 2000, p. 40.
11. P.M. Ware, "300-mm Lithography Enters Reality," *Semiconductor International*, July 2000, p. 128.
12. A. K.-K. Wong, *Resolution Enhancement Techniques in Optical Lithography*, SPIE Press, Bellingham, WA, 2001.
13. R. DeJule, "Update on Resolution Enhancement Techniques," *Semiconductor International*, August 2000, p. 54.
14. C.A. Mack, "Understanding Focus Effects in Submicron Optical Lithography: A Review," *Optical Engineering*, Vol. 32, No. 10 (October 1993, pp. 2350-2362).
15. C. Mack, "Optimum Stepper Performance By Image Manipulation" *KTI Microelect. Sem.* p. 209 (1989).
16. D.L. Fehrs *et al.*, "Illuminator Modification of an Optical Aligner" *KTI Microelect. Sem.* p. 217 (1989).
17. M. Noguchi *et al.*, "Subhalf Micron Lithography System with Phase-Shifting Effect," *Proc. SPIE*, Vol. 1674, p. 92, (1992).
18. W. Partlow *et al.*, "Depth-of-Focus and Resolution Enhancement for *i*-line and Deep-UV Lithography Using Annular illumination," *Proc. SPIE*, Vol. 1927, p. 137 (1993).
19. S. Asai *et al.*, *J. Vac. Sci. Technol.* **B 10**(6), 3023 (1992).
20. K. Toh *et al.*, "Three-Dimensional Simulation of Optical Lithography," *SPIE*, Vol. 1463, p. 402 (1991).
21. K. Tounai *et al.*, "Optimization of Modified Illumination for 0.25 μ m Resist Patterning," *Proc. SPIE*, Vol. 2197, p. 31 (1994).
22. T. Ogawa *et al.*, "Effective Light Source Optimization with the Modified Beam for Depth-of-Focus Enhancements," *Proc. SPIE*, Vol. 2197, p. 19 (1994).

23. H.J. Levinson and W.H. Arnold, "Optical Lithography," Chap. 1, pp. 11-138, in *Handbook of Microlithography, Micromachining, and Microfabrication*, Vol. 1, Microlithography, Ed. P.Rai-Choudhury, SPIE Optical Engineering Press, Bellingham, WA., 1997.
24. R. DeJule, "OPC Simulation," *Semiconductor International*, September 1997, p. 56.
25. C. Mack, "Evaluating Proximity effects Using 3-D Optical Lithography Simulation," *Semiconductor International*, July 1996, p. 237.
26. C.A. Mack and P.M. Kaufman, "Mask Bias in Submicron Optical Lithography," *J. Vac. Sci. Technol.*, Vol. **B6** (Nov./Dec. 1998) p. 2213.
27. N. Shamma *et al.*, "A Method of Correction of Proximity Effect in Optical Lithography," *KTI Microlithography Seminar Interface 1991*, p. 145.
28. *Microlithography: Science and Technology*, J.R. Sheats & B.W. Smith, Eds., Marcel Dekker, New York, 1998.
29. M. Levenson *et al.*, "Improving Resolution in Photolithography with a Phase-Shifting Mask," *IEEE Trans. Electron Dev.*, **ED-29**, 1828 (1982).
30. B.J. Lin, "Phase-Shifting Masks Gain an Edge," *IEEE Circuits & Devices Mag.*, March 1993, p. 28.
31. *ibid.*, Ref. 24, p. 74-82.
32. M.D. Levenson, "Strong Phase-Shift Mask Designs with Lower Cost," *Solid State Technology*, January 2001, p. 104.
33. T. Terasawa *et al.*, "Imaging Characteristics of Multi-Phase-Shifting Mask," *SPIE*, Vol. 108, 25 (1989).
34. B.J. Lin, "The Attenuated Phase-Shift Mask," *Solid State Technology*, January 1992, p. 43.
35. R. DeJule, "OPC for Attenuated Phase-Shift Masks," *Semiconductor International*, May 1998, p. 44.
36. M.S. Hibbs, "System Overview of Optical Steppers and Scanners," in *Microlithography: Science and Technology*, Eds. J.R. Sheats and B.W. Smith, Marcel Dekker, New York, 1998, Ch. 1, pp. 1-107.
37. W. Maurer *et al.*, "Pattern Transfer at $k_1 = 0.5$: Get 0.25 μm Lithography Ready for Manufacturing," *Proceeding of SPIE*, Vol. 2726, p. 113, 1996.
38. B.-G. Kim *et al.*, "Beneath the MEEF," *Solid State Technology*, August 2000, p. 107.
39. S. Okazaki, *Proc. of SPIE*, Vol. 2440, p. 18 (1995).
40. H.J. Levinson, *Principles of Lithography*, SPIE Press, Bellingham WA, 2001.
41. J.A. McClay and A.S.L. McIntyre, "157 nm Optical Lithography: The Accomplishments and the Challenges," *Solid State Technology*, June 1999, p. 57.
42. S. Okasaki, "Lithography Prospects for 0.18 μm Technology & Beyond," *Tech. Dig. IEDM*, 1996, p. 57.

43. S.A. Lis, "An Air-Turbulence Compensated Interferometer," *Proc. SPIE*, Vol. 2440, 9891 (1995).
44. *ibid.*, Ref. 23, p. 124.
65. T. Brunner, "Pushing the Limits of Lithography for IC Production," *Tech. Dig. IEDM*, 1997, p. 9.
66. A.M. Hawryluk *et al.*, "EUV Lithography," *Solid State Technology*, July 1997, p. 151.
67. S. Berger *et al.*, *SPIE Proceedings*, Vol. 2322, p. 434 (1994).
68. L.R. Harriott *et al.*, *J. Vac. Sci. Technol.*, **B14**(6), 3825 (1996).
69. P.M. Ware, "Why Optics is Forever in Lithography," *Solid State Technology*, May 2000, p. 192.
70. C. Wagner *et al.*, "The Technical Considerations of Extending Optical Lithography," *Solid State Technology*, September 2000, p. 97.
71. J.S. Petersen, "Integrated Imaging a Key Approach to Optical Lithography at 100-nm+," *Solid State Technology*, January 2001, p. 80.
72. R. DeJule, "Next Generation Lithography Tools," *Semiconductor International* March 1999, p. 48.
73. D.T. Attwood, *Soft X-rays and Extreme Ultraviolet Radiation, Principles and Applications*, Oxford University Press, 2000.
74. Hand, "EUV Lithography Makes Serious Progress," *Semiconductor International*, June 2001, p. 54.
75. J. Canning, "Challenges of Next-Generation Lithography," *Semiconductor International*, September 2000, p. 107.
76. M.D. Levenson, "Is There Light at the End of the NGL Tunnel?" *Solid State Technology*, May 2000, p. 51.
77. A.K. Bates *et al.*, "Review of Technology for 157-nm Lithography," *IBM J. Res. & Dev.*, Vol. **45**, No. 5, 2001.
78. A. Hand, "157-nm Optics Demand a Bag of Tricks," *Semiconductor International*, February 2002, p. 50.

Chapter 8

CHEMICAL MECHANICAL POLISHING (CMP)

As circuit features are scaled to submicron dimensions and additional levels are added to multilevel-interconnection schemes, the required degree of planarization is increased. In fact, the complexity of current microelectronic devices demands global planarity of the substrate after shallow-trench isolation and at all interconnect levels. Thus, such planarization needs to be implemented in both conductor and dielectric materials. In this chapter the technique of *chemical mechanical polishing* (the only known technique that provides global planarization for ULSI applications) is described. The discussion will begin by defining terms through which planarization is characterized, and then a brief recount of the evolution of planarization techniques that preceded CMP will be given. After concluding this introductory matter, the remainder of the chapter is devoted to the CMP process.

8.1 TERMINOLOGY & EVOLUTION OF PLANARIZATION PROCESSES FOR ICS

The term planarization is employed quite frequently (and often loosely) in other technical literature. Thus it is useful to define the term more completely. The example case used for this discussion is that of a dielectric layer deposited after Metal-1 is patterned (i.e., an *intermetal dielectric* [or IMD] film). In the case where no planarization exists (Fig. 8-1a), the step heights on the IMD surface closely approximate the step heights of the Metal-1-layer and the underlying topography. Furthermore, in this case the steps on the IMD surface generally also have steep slopes.

8.1.1 Defining the Degree of Planarization

The steps on the surface of the IMD can be made less severe through various planarization methods. The degree to which this can be successfully accomplished differs according to the technique used. The degree of planarization is classified according to the following qualitative planarization criteria:

1. The first degree of planarization (smoothing) involves a lessening of the step slopes at the IMD surface (Fig. 8-1b). The step heights in this case, however, are not significantly reduced in magnitude.

2. In the second degree of planarization (partial- or semi-planarization) the step heights are reduced (but not eliminated), and the slopes of the steps are also smoothed (Fig. 8-1c).

3. In the third degree of planarization (complete local-planarization), the steps at the surface of the IMD are completely eliminated wherever the spaces in the underlying topography are relatively close together (e.g., $< 10\text{-}\mu\text{m}$




Fig. 8-1 (a) through (e) - Degrees of dielectric planarization; (f) SEM of 6-metal-level interconnect structure, with complete global-planarization realized at each level.

apart), but the steps at isolated, wide features still exhibit a step (Fig. 8-1d).

4. In the fourth degree of planarization (complete global-planarization), the surface is completely planarized over arbitrary topography (Fig. 8-1e).

Figure 8-1f shows a SEM of a 6-level-metal interconnect-system in which complete global-planarization has been realized in each of the metal levels (i.e., using CMP).

A quantitative measure of the step-height-reduction, referred to as the *planarization factor*, β , is given by¹

$$\beta = 1 - (t_{\text{step}}^f / t_{\text{step}}^i) \quad (8.1)$$

where t_{step}^f and t_{step}^i are the final- and initial-step-heights, respectively. In complete-planarization cases, $\beta = 1$. If no planarization (or only smoothing) exists, then $\beta = 0$.

8.1.2 The Need for Dielectric Planarization

As the number of levels in an interconnect technology is increased, the stacking of additional layers on top of one another produces a more and more rugged topography. Consider, for example, a two-level-metal, single-poly CMOS technology. Assume the step-height of the semi-recessed field-oxide is $0.3\text{-}\mu\text{m}$, and the thicknesses of the poly and the first and second metals are 0.4- , 0.5- and $1.0\text{-}\mu\text{m}$, respectively. The maximum height of the steps on the wafer surface after each of these processes will be 0.3- , 0.7- , 1.2- , and $2.2\text{-}\mu\text{m}$, respectively (Fig. 8-2). It is apparent that the surface of the wafer must be planarized in some fashion to prevent the topography roughness from growing with each level. Without such planarization, the microscopic canyons that result on the wafer surface from stacking of device features can lead to topography conditions that would eventually reduce the yield of circuits to unacceptably small values.

A nonplanar wafer topography results in three conditions that prevent the fabrication of reliable electrical connections in multilevel interconnect systems. These conditions are as follows:

1. Poor step-coverage of metal lines as they cross over the high and steep steps. A measure of how well a film maintains its nominal thickness is expressed by the ratio of minimum thickness of a film as it crosses a step, t_s , to the nominal thickness of the film on horizontal regions, t_n (Fig. 8-3a). This property is referred to as the *step-coverage* of the film, and is expressed as the percentage of the nominal thickness that occurs at the step:

$$\text{Step coverage (\%)} = (t_s / t_n) \times 100\% \quad (8.2)$$








Fig. 8-2 As the number of levels in an interconnect technology is increased, the stacking of additional layers on top of one another produces steps of progressively greater heights.

Step coverage of 100% is ideal for a conductor, but in general the height of the step and the aspect-ratio of the features being covered impact the expected step-coverage. (The *aspect-ratio* is defined as the height-to-spacing ratio of two adjacent steps.) The greater the step-height or the aspect-ratio, the more difficult it is to attain coverage of the step without a corresponding thinning of the film that overlies it. Figure 8-3b shows an example of poor step-coverage. Hence, worse step-coverage is expected under these conditions. In addition to the step-height and aspect-ratio, step-coverage depends on two other topological-factors: the contour and slope of the step. In general, the smoother the contour of a step and the less vertical its slope, the better will be the step-coverage of an overlying film.

2. Metal stringers remain behind at the foot or sides of steep steps when anisotropic-etching is used. This condition is shown in Fig. 8-3c. In addition, the resist is typically eroded by the same gases that etch the metal. The resist must therefore be thick enough in all locations that it will not be completely removed before the etch-process is completed. If the dielectric surface has steps, in certain locations (i.e., over the upper corners of the steps in the dielectric, see Fig. 8-3d) there may not be sufficient resist thickness to survive during the time of overetch that must be used for removal of the stringers. The resist-erosion-rate during the overetch time



(a) Step Coverage (%) = $(t_s / t_n) \times (100\%)$



d)

$$t_3 > t_1 > t_2 > y$$

Fig. 8-3 a) Definition of step-coverage. b) SEM micrograph showing poor step-coverage. c) Metal stringers remain behind at the foot or sides of a steep step when anisotropic-etching is used. d) Problem of resist-thinning as film crosses underlying steps.

is also generally enhanced. Because most of the exposed-metal has been etched away, the reactant gases that were being consumed during etching of the metal are now present in greater concentrations. In cases where the resist is completely eroded at thin spots, the metal beneath the resist will be exposed to the reactive species and may be etched away to an unacceptable degree.

Even if the above two limitations could be overcome, the following obstacle would eventually force planarization to be implemented:

3. The depth-of-field limitations of submicron optical-lithography tools will require surfaces to be planar within $\pm 0.5 \mu\text{m}$. As a result, if steps larger than $0.5 \mu\text{m}$ exist on the surface of the IMD (or any other layer on the wafer), it will not be possible to pattern features in Metal-1 to the maximum resolution of the stepper. Thus, planarization will be mandatory if optical lithography is to be usable for fabricating ICs with such submicron feature sizes. (This topic is discussed in more detail in Vol.1, 2nd Ed., Chap. 13.)

Planarization of the intermetal dielectric layers is one of the chief approaches that has been taken to alleviate the problem of rough surface topography.

8.1.3 Design Rules Related to Intermetal Dielectric-Formation and Planarization Processes

The type of intermetal dielectric material, its thickness, and the method of deposition and planarization can all have an impact on the design rules that must be applied when laying out an integrated circuit with a particular multilevel-metal system. Here a two-level-metal system with an underlying poly-silicon level is considered. Assume that the topography beneath the polysilicon is completely planar. In this system, design rules dealing with the following conditions must be specified: 1) minimum polysilicon-to-Metal-1 spacing, assuming no metal overlap of the poly; 2) minimum distance between coincident edges when Metal-1 overlaps polysilicon; and 3) minimum spacing of Metal-1-to-Metal-1.

If polysilicon and Metal-1 come too close together, a gap will exist between them that will lead either to void formation in the CVD oxide PMD layer following deposition (Fig. 8-4a) or to the formation of a deep, narrow crevice that cannot be covered by the next level of metal, even after some planarization procedures have been utilized (Fig. 8-4b).

In the second case (Fig. 8-4c), if polysilicon and metal edges are coincident, the total step height may be too high for adequate coverage by Metal-2 to be achieved. Figure 8-4d illustrates the case in which the problems of coincident edges and a narrow crevice are exacerbated by their simultaneous occurrence.

In the third case, the spacing between adjacent Metal-1 lines must be large enough to prevent void or crevice formation in the deposited dielectric film. The step that exists in the LOCOS field oxide must also be considered in real situations when such design rules are being formulated. One possible way to prevent the formation of voids, crevices, and excessively high steps, is to allow




Fig. 8-4 Conditions associated with the relative spacing of polysilicon and Metal-1 that lead to layout design rules of these layers.

the spacings between Metal-1 and underlying features to be sufficiently large so any possible combination of misalignment cannot lead to the problems listed. However, this alternative is impractical, because it increases chip size and causes excessive complexity in layout design.

The trend in advanced IC designs today is toward the elimination of all such restrictive dielectric-layer-related design rules. The development focus is on dielectric planarization processes that allow all spaces between any adjacent or overlapping features (and all possible step heights), to be covered with a dielectric layer whose surface does not exhibit any voids, crevices, or excessively

high steps. Even though this is an actively pursued goal, it has not yet been attained in all processes and technologies. Various planarization approaches that have been developed along the path toward the condition in which no restrictive design rules need be invoked will be described.

8.1.4 Step-Height Reduction of Underlying Topography Alleviates the Need for Planarization

In two-level-metal processes it may be possible to avoid performing any planarization procedures with respect to the IMD if the topography underlying IMD is planarized by the process steps that precede IMD deposition. Although this approach may appear to be obsolete for ULSI circuits, several of the step-height-reduction techniques turn out to be useful for providing a planar surface under Metal-1. Such a condition will ultimately be required for three- and four-level-metal processes. The survey of planarization techniques of dielectric layers begins by considering this approach. In this section one older step-height reduction technique is described, namely *planarization through sacrificial-layer etchback*.

8.1.5 Planarization through Sacrificial-Layer Etchback

Planarization of CVD-interlevel-dielectric films can also be achieved using the *sacrificial-layer etchback technique* (Fig. 8-5). This method gained the most widespread acceptance in two-level-metal processes down to $\sim 1\text{-}\mu\text{m}$ device tech-




Fig. 8-5 Sequence of steps used in a sacrificial-layer etchback process for planarization.

nologies (and even in some reported three-level-metal bipolar processes). Using this approach, it is possible to achieve a high degree of planarization between steps that are $\sim 2\text{-}10\text{-}\mu\text{m}$ apart. With more closely-spaced features, the technique runs into problems. For more widely spaced steps, planarization is less complete. The process is carried out by first depositing the CVD film that will serve as the interlevel dielectric (ILD) or intermetal dielectric (IMD). This layer is then coated with a film that will later be etched off (sacrificed). In most cases, such sacrificial-layers are photoresists, spun-on in liquid form. Upon being baked, these liquids become solid thin films that are thick enough so they provide a film surface that is close to being flat, as shown in Fig. 8-6. As long as the feature-size is smaller than about $10\text{-}\mu\text{m}$, the degree of planarization can exceed 70% with most photoresists.

In the next step, the sacrificial-layer is first rapidly etched back in a plasma (typically, O_2 , or O_2 mixed with CF_4) until the topmost regions of the dielectric layer are just exposed (Fig. 8-5b). The etch chemistry is then modified so the sacrificial-layer material and the dielectric are etched at approximately the same




Fig. 8-6 Degree of planarization vs. various feature size for different polymers.² (© 1987 IEEE)

rate. The etch is continued under these conditions until all of the sacrificial layer has been etched away. At this point, the surface of the dielectric film is highly planarized since the profile of the sacrificial layer is transferred to the dielectric layer by the etchback procedure. The thickness of the dielectric film over underlying features (such as metal lines), may be thinner than desired after the etchback is completed. In fact, in some processes the etchback step is allowed to proceed until the Metal-1 lines are exposed. In either case, an additional layer of CVD dielectric is generally deposited in order to establish a minimum adequate thickness everywhere on the wafer surface.

8.1.5.1 Sacrificial-Etchback-Process Problems: To achieve the desired degree of planarity and final dielectric-film-thickness, very tight process control is necessary for such parameters as the magnitude of the etch-rate, the etch-rate uniformity across a wafer, end-point-detection, and oxide-thickness-uniformity under the resist layer. The resist etch-rate is sensitive to the cure cycle (especially if a high-temperature bake step [$> 150^{\circ}\text{C}$] is used to improve surface planarity), and to chamber preconditioning. In batch processes, the etch-rate is also sensitive to the number of wafers present in the chamber. Such tight process-control of a complex process is hard to maintain on a production line.

The process also requires a multitude of steps, which implies a lengthy process, and thus low-throughput. Etchback is a difficult process to successfully implement in a batch-etch mode, resulting in an even lower-throughput. Finally, if the aspect-ratio between adjacent Metal-1 lines with vertical sidewalls exceeds 0.4, voids will form when most CVD-SiO₂ layers are deposited (Fig. 8-7). These voids can trap resist and moisture, which can subsequently be released if the voids are opened during the etchback process. Opened voids will also trap metal during the Metal-2 deposition-step. It will remain in the form of metal stringers following Metal-2 patterning. Thus, this process is not feasible for Metal-1 spacings of less than $\sim 1.25\text{-}\mu\text{m}$ (unless a process is available for deposition of SiO₂ layers at low temperatures without formation of voids in high-aspect ratio spaces [e.g., PECVD TEOS films, O₃:TEOS films, or HDP CVD films]).

8.2 INTRODUCTION TO CHEMICAL MECHANICAL POLISHING (CMP)

As the number of interconnect layers in ICs has increased, the planarization of dielectric and metal layers has become more critical. In general, planarizing techniques such as the thermal flow of oxide layers, sacrificial-resist-etchback, and spin-on-glass, are inadequate for interconnect systems with more than three layers of metal. All of these techniques ultimately provide only a limited degree of smoothing and local planarization (i.e., over distances smaller than $10\text{-}\mu\text{m}$).




Fig. 8-7 (a) Diagram of void-formation due to cusping of the dielectric. (b) SEM of voids left between 1.5- μm -spaced Metal-1 lines in a 3.0- μm -thick PMD PECVD oxide.

They are not able to provide global planarization.³ Global planarization of both dielectric and metal layers, however, is possible with chemical-mechanical-polishing (CMP), a process that was pioneered at IBM in the 1980s. In this technique, high elevation features are selectively removed (i.e., material from high elevation features is removed more rapidly than material at lower elevations), resulting in topography with improved planarity (see Fig. 8-10 [in which $h_{\text{final}} \ll h_{\text{initial}}$] and Fig. 8-10b). The degree of planarization is expressed by Eqs. 8-1 and 8-3. A step-height reduction of 90–95% is achievable using CMP, yielding values of β in the 0.90–0.95 range. CMP is also capable of planarization of distances up to several millimeters, far in excess of that possible with any other technique thus far developed.⁴

Mechanical polishing, assisted by chemical action, produces such selective material removal. The process is performed by mounting the wafer face down on a carrier. The carrier is then pressed against a moving platen containing a polishing pad. The carrier itself is rotated. An abrasive-containing aqueous slurry is dripped onto the table, and centrifugal force distributes the slurry across the pad. This forms a thin colloidal layer of slurry which saturates the pad (Fig. 8-8). The combination of mechanical effects and chemical reactions results in material removal from the surface of the wafer.

CMP offers three key advantages for fabricating sub-micron ICs. First, for logic devices (such as microprocessors and ASICs), CMP makes it possible to achieve high manufacturing yields and high device speeds with multilevel interconnects having up to eight levels of metal. By planarizing IC topography, CMP avoids the problem of metal thinning over steep topographies in multi-level interconnect structures. Second, memory devices (such as DRAMs) benefit from CMP even though they use interconnect systems with only two levels of metal. For memories, the flat wafer surface after CMP increases the depth-of-focus budget available for lithography (see Chap. 13, Vol. 1, 2nd Ed.). This allows memory-circuit designers to employ smaller critical dimensions, thus reducing chip sizes without decreasing yield. Smaller chip sizes provide a significant cost advantage in the competitive realm of DRAM manufacture. Third, CMP is paradoxically capable of reducing (rather than increasing) defect-density.

Because CMP has become an enabling technology for allowing ICs to be further scaled, the applications of CMP have become pervasive. For example, by 2000, stacked-capacitor DRAMs have upwards of 9 polishing steps, and microprocessors may incorporate as many as 16 polishing steps. As a result, the manufacturability aspects of CMP (namely, the overall cost per CMP step - expressed in terms of \$/wafer/polish step) become as important as CMP yield.

In the remainder of this chapter the following topics will be discussed; **a)** the terminology used to characterize CMP processes; **b)** the history of CMP; **c)** the mechanisms involved in CMP of oxides and metals; **d)** CMP equipment and consumables; and **e)** the details of CMP for various materials; and **f)** the challenges facing CMP processing. The latter include: inadequate understanding of the polishing mechanisms, low throughput, inadequate reliability of the polishing tools, degradation of removal-rate with usage-time of a polishing pad,




Fig. 8-8 Schematic of a rotary-table chemical-mechanical-polishing system.

non-uniformity of film-thickness-removal across the wafer, high cost of ownership, and high defect density.

8.3 THE TERMINOLOGY USED TO CHARACTERIZE CMP PROCESSES

Before beginning the discussion of the details of the CMP process, it is useful to define the metrics used to characterize the CMP process itself. This discussion is begun by listing the goals desired in a CMP process. They are:

1. The CMP process should have the ability to selectively reduce the step heights of features in the film being polished (i.e., a high degree-of-planarization must be possible);
2. Good planarity across a die (highest spot to lowest spot should be less than 150-nm);
3. Good film thickness uniformity within the wafer ($\pm 2-5\%$, 1σ);
4. High removal rates (100–140-nm/min), for high throughput and low cost-of-ownership;
5. Uniform removal rates from wafer-to-wafer;
6. Good selectivity and/or good endpoint technology to avoid under-polishing or over-polishing;
7. The CMP process should not add excessive defects (e.g., for 0.18- μm CMOS, fewer than 0.125-particles/ cm^2 with a size larger than 0.06- μm are allowed at each mask level);
8. The overall cost of a CMP process should be as low as possible (expressed in \$/wafer for each CMP process which is conducted).

While it is useful to list these goals in the qualitative manner as given above, the metrics for characterizing a CMP process can also be expressed in quantifiable form. These quantifiable forms are presented next.

8.3.1 CMP Removal-Rate (RR)

The *removal-rate* (RR) describes how rapidly a CMP process removes material from a non-patterned wafer (Fig. 8-9). This quantity is measured by performing a CMP process on a planarized, unpatterned wafer for a specific time, and determining how much material has been polished away. Generally speaking, the RR should be high so that the CMP process can be completed quickly enough to allow a satisfactory throughput. The RR is quantitatively expressed as follows:

$$\text{RR} = \Delta T/t \quad (8.3)$$




Fig. 8-9 Definition of *removal-rate* (RR).

where ΔT is the thickness of material removed in time t . RR is most frequently expressed in units of $\text{\AA}/\text{min}$.

8.3.2 The Degree of Planarization (DOP)

In the ideal case, after CMP the surface should be completely planarized (see Fig. 8-1). The quantity that describes how well the CMP process meets this ideal is the *degree of planarization* (%DOP). The %DOP (see Fig. 8-10a) is quantitatively expressed as:

$$\%DOP = [(H_d^i - H_d^f)/H_d^i] \times 100\% \quad (8.4)$$

where H_d^i is the height of feature being polished prior to carrying out the CMP step, and H_d^f is the height of the feature after the completion of the polishing step. Note that when the value of the %DOP is 100% this indicates that the feature has been completely planarized. Figure 8-11b shows a wafer surface on which the %DOP is 100% (complete global-planarization). Figure 8-11a shows a wafer surface on which the CMP process has not produced complete planarization (%DOP < 100%).

8.3.3 Within-Die Non-Uniformity (WIDNU)

The rate at which material is removed by CMP within a die may not be uniform. Such *within-die non-uniformity* (WIDNU) is quantitatively defined as the *standard deviation of the film thickness within a die*, σ_{WID} , divided by the *average value* of all “ n ” film-thickness measurements within the die, $\bar{x}_{\text{WID}}$:




Fig. 8-10 Definition of *degree of planarization (DOP)*.

$$WIDNU = \sigma_{WID} / \bar{x}_{WID} \quad (8.5)$$

Note that σ_{WID} is the standard deviation of measurements within the die of some specific thickness, depending on the type of thickness non-uniformity being specified (e.g., the thickness variation of the oxide in the field between metal lines in an otherwise planarized oxide surface, see Fig. 8-11), and it is expressed quantitatively by:

$$\sigma_{WID} = \sqrt{[(x_1 - x_{WID})^2 + \dots + (x_n - x_{WID})^2]/(n - 1)} \quad (8.6)$$

where $x_1 \dots x_n$ are particular measurements on a die. Two examples of effects that cause WIDNU are shown in Figs. 8-12 and 8-13, respectively.

In Fig. 8-12c the step heights after CMP have not been reduced by the same amount within a die. Specifically, narrow, isolated-features tend to be planarized to a greater degree than wide, isolated-features, or narrow, densely-spaced-features. This form of WIDNU is termed *pattern-dependent-planarization*. The causes of such pattern-dependent-planarization are described in Sect. 8.5.3.2.




Fig. 8-11 a) Surface on which complete global-planarization has been achieved; b) Surface on which complete global-planarization has not been achieved.

In Fig. 8-13c, although the step heights of the oxide within a die (as shown in Fig. 8-13a) have been completely planarized, some film has been eroded in regions between the steps to a degree that the oxide surface is not planar throughout the die. This causes the distance from the top of the oxide to the planarized substrate surface below the oxide to differ within the die. This form of WIDNU is known as *dishing*, and the effects that cause such dishing are described later.




Fig. 8-12 Effect #1 that causes *within-die non-uniformity* (WIDNU).




Fig. 8-13 Effect #2 that causes *within-die non-uniformity*, WIDNU (dishing).

8.3.4 Within-Wafer Non-Uniformity (WIWNU)

The *within-wafer non-uniformity* (WIWNU) is defined as the *standard deviation of the film thickness within a wafer*, σ_{WIW} , divided by the *average value* of all "n" film thickness measurements on that same wafer, $\bar{x}_{WIW}$.

$$WIWNU = \sigma_{WIW} / \bar{x}_{WIW} \quad (8.7)$$

Note that σ_{WIW} is the standard deviation of measurements within the wafer of some specific thickness, depending on the type of thickness non-uniformity being specified (e.g., the thickness variation of the distance between the otherwise planarized surface of the oxide and the surface of the planarized substrate below, see Fig. 8-14), and it is expressed quantitatively by:

$$\sigma_{WIW} = \sqrt{[(x_1 - \bar{x}_{WIW})^2 + \dots + (x_n - \bar{x}_{WIW})^2] / (n - 1)} \quad (8.8)$$

where $x_1 \dots x_n$ are particular measurements on a wafer. Two examples of WIWNU are shown in Fig. 8-15.

In Fig. 8-15a the surface of the oxide after CMP is shown to be globally planarized across the entire wafer. However, the distance from the surface of the oxide to the planarized surface of the substrate below is non-uniform across the wafer. An example of two effects that can lead to such WIWNU are: 1) If the thickness of the substrate (wafer) itself is non-uniform, and the CMP process is performed with a completely rigid pad, this will cause WIWNU (see Sect.

$$\bar{x}_{WIW} = (x_1 + x_2 + x_3 + x_4) / 4$$

$$WIWNU = \frac{\sigma_{WIW}}{\bar{x}_{WIW}}$$




Fig. 8-14 Definition of *within-wafer non-uniformity* (WIWNU).

8.12.2); and 2) In rotary CMP polishing tools, WIWNU can be caused by the relationship between the angular rotation velocities of the wafer carrier and the polishing pad platen. This topic is discussed in Sect. 8.5.

Another effect that gives rise to a special type of WIWNU is shown in Fig. 8-15b. This figure shows that the wafer surface after CMP has an edge bead of material, caused by a smaller removal rate of material by CMP near the edge of the wafer. This topic is described further in Sect. 8.6.2.1.

8.3.5 Wafer-to-Wafer Non-Uniformity (WTWNU)

The *wafer-to-wafer non-uniformity* (WTWNU) is defined as the *standard deviation of the film thickness from wafer-to-wafer*, σ_{WTW} , divided by the




Fig. 8-15 a) Example of one type of WIWNU; b) Example of a second type of WIWNU caused by the *edge-bead-effect*.

average value of all the measurements of the film thickness measurements taken over all n wafers, $\bar{x}_{\text{WTW}}$.

$$\text{WTWNU} = \sigma_{\text{WTW}} / \bar{x}_{\text{WTW}} \quad (8.9)$$

Note that σ_{WTW} is the standard deviation of measurements from wafer-to-wafer for “ n ” wafers of some specific thickness, depending on the type of thickness non-uniformity being specified (e.g., the thickness variation of the distance between the otherwise planarized surface of the oxide and the surface of the planarized substrate below, see Fig. 8-16), and it is expressed quantitatively by:

$$\sigma_{\text{WTW}} = \sqrt{[(x_1 - \bar{x}_{\text{WTW}})^2 + \dots + (x_n - \bar{x}_{\text{WTW}})^2] / (n - 1)} \quad (8.10)$$

where $x_1 \dots x_n$ are particular measurements on a wafer. An example of WTWNU is shown in Fig. 8-16. Two of the many causes of WTWNU include pad-aging (see Sect. 8.6.7), and slurry inconsistency from batch-to-batch (see Sect. 8.6.3).

8.3.6 Efficiency of Planarization (EOP)

When an oxide is deposited over a metal line, enough oxide over the metal line must exist after the CMP step to minimize electrical cross-talk and parasitic capacitance between metal layers. This oxide thickness is determined by the IC designer. The CMP process-engineer must set up the CMP process so that after CMP is completed the oxide minimally meets the designers’ requirements. The *efficiency of planarization* of a CMP process has an impact on the process integration choices that must be made to ensure that the minimum oxide thick-




Fig. 8-16 Definition of *wafer-to-wafer non-uniformity* (WTWNU).

ness remains after CMP. The *efficiency of planarization* (%EOP) is expressed as:

$$\%EOP = [(T_r - T_d) / T_r] \times 100\% \quad (8.11a)$$

where T_r is the dielectric thickness removed by the CMP process on top of a feature (e.g., a metal line) and T_d is the oxide-thickness-loss at the center of a wide space between metal lines (see Fig. 8-17). The ideal case would be a CMP process with an %EOP = 100%. If this occurs, that means that complete planarization is achieved without the erosion of any oxide in the center of the wide space between metal lines. However, the %EOP is generally not 100%, and thus some erosion of the oxide between metal lines usually occurs.

It is the task of the CMP process engineer to determine how much total oxide must be deposited prior to the CMP step to ensure that the oxide on the metal lines is at least as thick as that specified by the IC designer. This thickness quantity is normally determined during tool setup, but it is useful to have an expression which allows the CMP engineer a way to estimate the correct value prior to performing the experimental task itself.

To allow the CMP engineer to calculate this thickness value more easily, the %EOP expression given by Eq. 8-11a is rewritten using different parameters. That is, Eq. 8-11a provides an expression for %EOP that makes it easier to visualize the concept of %EOP, but using it makes it cumbersome to calculate the required oxide deposition-thickness. Therefore, another expression is used instead of Eq. 8-11a for the deposited-oxide-thickness calculation. This alternate relationship is given as Eq. 8-11b (see Figs. 8-17c and 8-17d)

$$\%EOP = [H_{\text{metal}} / (T_{\text{total}} - T_{\text{cov}})] \times 100\% \quad (8.11b)$$

where H_{metal} is the height of the metal line being covered by the oxide, T_{total} is the total amount of the oxide film deposited over the metal line prior to CMP, and T_{cov} is the target amount of oxide that should remain over the metal line (as specified by the IC designer). Equation 8-11b is then rearranged to allow T_{total} to be determined:

$$T_{\text{total}} = (H_{\text{metal}} / \%EOP) + T_{\text{cov}} \quad (8.12)$$

As an example, if the %EOP is 50%, and $H_{\text{metal}} = 0.5\text{-}\mu\text{m}$, and T_{cov} is specified as $0.5\text{-}\mu\text{m}$, then using Eq. 8-12 (with $EOP = \%EOP/100\% = 50\%/100\% = 0.5$), then the amount of oxide that would have to be deposited prior to the CMP process that would result in $0.5\text{-}\mu\text{m}$ of oxide over the metal lines after CMP would be $T_{\text{total}} = 1.5\text{-}\mu\text{m}$.

The least-expensive process involves depositing the smallest thickness of oxide (and this would occur if %EOP was 100%, corresponding to a $T_{\text{total}} = 1.0\text{-}$

$$\%EOP = [H_{\text{metal}} / (T_{\text{total}} - T_{\text{cov}})] \times 100\%$$




Fig. 8-17 The basic CMP process is one of reducing film-thickness selectivity over the wafer, ending with improved planarity. Here that metric is defined as *efficiency of planarization* (EOP).

μm). Thus, it can be seen that if the %EOP can be increased, the overall IC fabrication cost associated with forming the planarized oxide film over the metal steps will be reduced. For example, if %EOP could be increased to 80% (from 50%), Eq. 8-12 would predict that the $T_{\text{total}} = 1.1\text{-}\mu\text{m}$.

8.4 THE HISTORY OF CMP

The early history of CMP was chronicled by Fury.⁵ He recounts that the process of chemical-mechanical-polishing originated at IBM in 1983. Research and development on CMP was exclusively performed within IBM until 1988. During those five years IBM closely guarded all information about the process. By the late-1980s several factors changed their secretive attitude. First, Intel microprocessors were selected for IBM's PC product line, and IBM decided to share some CMP data to help improve Intel's interconnect technology. Second, at that time the DRAM market was dominated by Japanese manufacturing companies. IBM was wary of having to rely entirely on foreign suppliers for such a critical component of its computer systems. Hence, they elected to help

strengthen a domestic DRAM supplier (Micron Technology, Inc.) by teaching them about the CMP process. Information about CMP was included in the process for the 4-MB DRAM that IBM sold to Micron Technology in the mid-1980s. In 1988, IBM agreed to disclose to SEMATECH its process scheme for multi-level interconnects, although they did not give all the details on CMP. They did, however, provide one of their CMP polishing tools (a Si-wafer polishing-tool sold by Westech, and marketed later as the IPEC Model 372, shown in Fig. 8-18). Motorola was introduced to CMP through the Power-PC microprocessor project, a joint venture between IBM, Motorola, and Apple Computer. In 1989 IBM published the first paper which publicly discussed the CMP of oxide films.⁶ These events initiated the rapid proliferation of CMP throughout the IC industry.

The spread of CMP was hastened by other events, chiefly the downsizing of IBM from 1990–94. Many engineers with expertise in CMP left IBM and went to work for other IC companies who were seeking to implement the technology. The effort at SEMATECH involved improving the CMP tool-performance and reliability. Their work with Westech tools led to the development of the early popular CMP-tools, sold later as the IPEC 372 and 472 models. (Westech was acquired by IPEC.)

Although early development of CMP was centered in the U.S., worldwide efforts soon got underway. Polishing tools were initially offered by companies that had been building machines for polishing silicon wafers (Speedfam and Strasbaugh, as well as IPEC [Westech]). Overseas suppliers soon joined them (e.g., Ebara and Cybeq from Japan, and Wolters from Europe). Eventually the




Fig. 8-18 The Speedfam 372 CMP tool.

larger semiconductor equipment vendors entered the market. Applied Materials introduced its tool in 1996, and Lam Research acquired On-Trak Systems, another commercial CMP vendor. The large number of vendors gave rise to some consolidation as well (an example of which was the merger of Speedfam and IPEC in 1999).

CMP was the fastest growing IC process technology of the 1990s, and it was also the most rapidly growing segment of the semiconductor process equipment market in that time frame. From 1995 to 1997 sales tripled, reaching \$520 million in 1997. Sales were expected to exceed \$1 billion by 2000.⁷ The number of CMP polishing steps per year was also estimated to reach 125 million by that date. The first application of CMP was the planarization of dielectric films (mainly CVD oxide), but the number of applications has increased. Currently it is being used to planarize metal films (including tungsten, aluminum, and copper), as well as oxides and low-*k* dielectric films. By the end of the century, CMP had evolved from being a cleanroom-engineers' nightmare, to a critical process technology without which the production of ULSI chips with multilevel-interconnects might not be possible.

8.5 MODELING THE MECHANISMS OF CMP

The mechanisms of CMP are quite complex, and differ for each type of film being polished. Many variables also impact the removal rate, including: film type, pressure (force applied to the polishing pad), velocity, temperature, slurry feed rate, type of polishing motion, slurry particle size, pad hardness, and pad conditioning. The pressing need for production-worthy CMP capabilities forced early researchers to ignore the complexity of the process and go straight to an empirical trial-and-error approach. But, to logically optimize a CMP process, a more fundamental understanding of the mechanical and chemical forces at work is needed. While a complete understanding of CMP mechanisms has not yet been achieved, some insight has been gained. A brief introduction as to what is known about CMP mechanisms is presented here, divided into three categories: **1)** the mechanical aspects of material removal by CMP (Preston's Equation); **2)** the chemical and mechanical effects that cause planarization of oxides by CMP; and **3)** the chemical and mechanical effects that cause planarization of metals by CMP.

8.5.1 The Mechanical Aspects of Silicon Dioxide Removal by CMP: (Preston's Law)

The CMP process for planarizing films in ULSI devices evolved from the technology of chemical-mechanical-polishing used to produce silicon wafers. That is, CMP in the Si wafering process is used to: 1) remove residual sawing and grinding damage that occurs when single-crystal silicon ingots are sliced into wafers; and 2) enhance the flatness (planarity) of the bare, starting-wafer surface.

However, the CMP process used in the Si wafering procedure differs significantly in two ways from the oxide-CMP process used to planarize oxide-layers a ULSI IC:

1. The oxide-CMP process is much more exacting than the Si-wafering CMP process. That is, the thickness of material removed in the CMP step of wafering is on the order of $10\text{-}\mu\text{m} \pm 0.1\text{ }\mu\text{m}$. However, the thickness of material removed in the oxide-CMP processes is only on the order of $0.5\text{-}\mu\text{m} \pm 0.01\text{ }\mu\text{m}$ (i.e., about 5% of the thickness of the material removed in Si wafer polishing). Thus, the degree of control in oxide-CMP processes is much higher than that needed for Si wafer polishing.

2. When a *bare Si wafer is being polished*, the process involves oxidizing the Si surface with a chemical in the slurry solution, and then the slurry particles abrade away this oxide. That is, the CMP of Si wafers is carried out with a slurry containing fine slurry particles dispersed in a solution that *oxidizes the bare-Si wafer*. This is the *chemical component* of the CMP process. The abrasion of this oxide by the slurry-particles is the *mechanical component* of the process. The abrasive process exposes the Si beneath the oxide to the chemical in the slurry, which re-oxidizes the exposed Si, and so on. In fact, the abrasion of the oxide performs two functions: **a)** The polishing process is continued long enough so that the damaged region near the Si surface from sawing and grinding is eventually consumed by the oxidation and abrasion sequence; and **b)** Since the abrasion occurs more rapidly on “high” spots on the wafer surface, these “high” spots are eroded more rapidly than the “low” areas. Thus, the wafer-surface becomes flatter (more planar).

However, when an oxide is being polished in a ULSI IC (a process that is carried out in such applications as the CMP of the trench-oxide in shallow-trench-isolation structures (STI), and the CMP-step used to planarize the inter-level dielectric [ILD] and inter-metal dielectric [IMD] layers), the material to be polished *is already an oxide*. Hence, the

mechanism employed to polish the Si wafer (i.e., chemically oxidizing the Si surface, and mechanically abrading it away), is not an operative mechanism in oxide-CMP. A discussion of what are believed to be the phenomena that govern the removal of oxide films in oxide-CMP follows.

In 1997 Tomozawa stated that, like optical-glass polishing, much of the oxide CMP process was still an art rather than a technology. To qualify as a technology, the basic mechanisms of a process must be understood, allowing it to be logically optimized. However, at the time Tomozawa made his comment, the basic mechanisms of oxide CMP were not yet well understood.⁸ The descriptions provided in this section briefly summarize what is known about the phenomena associated with oxide-CMP. Since silicon oxides used in IC fabrication are a form of glass, oxide-CMP is a specialized form of the glass polishing technology used to produce optical lenses. Thus, some aspects of oxide-CMP can be understood from the long history of glass polishing (which generally have been derived from trial-and-error, rather than from a fundamental understanding of the process). Optical-glass and SiO₂-films-on-Si-wafers are polished with a slurry consisting of abrasive silica particles (whose hardness is about equal to that of the oxide) suspended in an aqueous alkaline solution (typically KOH or NH₄OH, diluted in DI-water).

An empirical relationship that models the optical-glass-polishing removal-rate, RR, of flat-glass regions (defined as the thickness of glass removed per unit time), was developed by Preston, and is known as *Preston's equation* or *Preston's Law*.⁹ This law states that the RR is proportional to the applied-pressure P and linear-velocity v at which a polishing pad moves relative to the optical-glass specimen, or:

$$RR = K_p P v \quad (8.13)$$

where K_p (*Preston's constant*) is a proportionality constant that is independent of pressure and velocity. The same law appears to apply to the rate of removal of oxide by CMP. (Typical values of P and v in CMP processes are 7-psi, and 30-40-ft/min, respectively.)

Note that Preston's equation describes the relationship between the RR of oxide and *mechanical effects*. (That is, mechanical effects are those caused the application of physical forces on a substance, namely in Preston's equation, the pressure exerted on the oxide and the relative velocity between the glass and the polishing-pad.) The Preston equation predicts that oxide-RR is linearly proportional to P and v , but gives no insight into other phenomena (i.e., such physical

and chemical factors as the glass-temperature, the chemical nature of the polishing medium, the hardness of the glass, etc). These effects are all put into the Preston constant, K_p , which contains the influence of such phenomena as glass hardness, Young's modulus, the polishing slurry, and the composition and hardness of the polishing pads. Despite the fact that Preston's equation sheds no light *per se*, on how these other phenomena impact RR, it is still a model that provides useful predictability concerning oxide-CMP. Hence, it is informative to discuss some further issues related to this equation.

The most important criticism of the Preston equation is that it was formulated empirically rather than from first principles (i.e., it was not mathematically derived from a physical model of the glass-polishing process). Several authors have proposed equations from first principles that predict the dependency of oxide RR on pressure and velocity, including Brown and Cook (1984),¹⁰ Liu *et al.* (1995),¹¹ Runnels and Eyman (1994),¹² Tseng (1997),¹³ and Zhao and Shi (1999).¹⁴ A critical review of the evolution of these models is found in Shinn *et al.*¹⁵

Many of the models (and supporting experimental evidence) indicate that the dependence of oxide-RR in CMP on pressure and velocity is not a simple linear relationship. Recent work has proposed multiple variations of Preston's equation of the form:

$$RR = K_p v^\beta p^\alpha \quad (8.14)$$

Where α and β are adjustable parameters dependent on the system to be polished. The values of these coefficients must be experimentally determined.

In the model of oxide RR of Zhao and Shi (which is the first model that also includes the effect of pad and wafer hardness), the RR demonstrates a sub-linear dependence on pressure given by:

$$RR = K_p v P^{2/3} \quad (8.15)$$

Figure 8-19 shows experimental data demonstrating the dependence of RR for oxide films.¹⁶ Zhao and Shi also found that the pressure dependence of RR significantly influences planarization efficiency and pattern-density dependence. For instance, not all slurry particles in contact with a wafer necessarily remove material efficiently. A particle rolling against the surface removes little material, yet a particle held firmly by the pad slides against the wafer surface, changing the surface structurally and chemically. Sliding and removing requires a minimum local pressure, giving a revised polishing rate of:

$$RR = K_p v (P^{2/3} - P_{th}^{2/3}) \quad \text{when } (P \geq P_{th}) \quad (8.16)$$

and

$$RR = 0 \quad \text{when } (P \leq P_{th}) \quad (8.17)$$




Fig. 8-19 Experimental data correlates well with the $P^{2/3}$ dependence of removal-rate on applied pressure.¹⁶

where P_{th} is the threshold pressure. In addition, they found that planarization efficiency also improves with P_{th} (Fig. 8-20), requiring less material removal to achieve a given planarization result.¹⁶

8.5.1.1 Model that Treats WIWNU Effects In Rotary-CMP Tools Based on Preston's Law:

One of the limitations of CMP is that within-wafer-non-uniformities (WIWNU) occur, as defined in Sect. 8.3.4. The Preston equation states that the oxide-RR is linearly proportional to the *linear velocity* of the pad with respect to the oxide-surface being polished. Thus, one way to reduce such WIWNU is to ensure that the same linear velocity is experienced by all areas of the wafer. In rotary-CMP tools, the wafer carrier rotates, as does the platen that holds the polishing pad. If the pad did not rotate, and only the carrier rotated about its axis, the oxide-RR at center of the wafer would drop to zero, since there would be no relative motion between the wafer and the pad at that point. In addition, the RR would increase radially from the center to the edge of the wafer.




Fig. 8-20 Increasing the threshold pressure improves planarization efficiency for various final step heights (500-nm initial step height).¹⁶




Fig. 8-21 Plan view of a single-carrier single-platen rotary-polisher, showing relative rotary motions of both the carrier and the platen.

Now assume that the platen and the wafer carrier both rotate. In this case (referring to Fig. 8-21), it can be noted that the centers-of-rotation of the wafer-carrier and the platen are offset from one another. If the wafer-carrier and the platen have the same rotational frequency, and are rotating in the same direction, point B of the outside edge of the wafer in that figure experiences zero relative velocity, and the point A on the inside edge of the wafer experiences the greatest relative speed of the surface of the wafer to the pad. Thus, the instantaneous removal rate at the edge of the wafer is greatest when the edge is directly between the two centers (point A), and zero when in the extreme position (point B). However, since all points on the edge of the wafer pass through points A and B at a constant frequency, the time-average RR at the edges will be the same as at the center of the wafer. Thus, it is the average-radius from the center of the platen, r_{av} , that defines the distance the wafer travels and the average speed of travel, S_t , for purposes of the total film removed and RR calculations:

$$S_t = 2 \pi r_{av} f (\text{rpm}) \quad (8.18)$$

In practice, within-wafer-non-uniformity of RR is observed in rotary-CMP tools (e.g., WIWNU). One form of such WIWNU is a spoke-like pattern due to vibration harmonics. Driving the carrier in rotational synchronization with the platen usually causes the worst vibrations. Hence, the wafer-carrier is usually driven at a constant difference in frequency to the platen. Since the correct wafer-carrier rotational-frequency for perfect circular symmetry is not known, it must be experimentally determined.

8.5.2 Models Which Describe Factors that Impact Oxide-RR in CMP Through the Preston Constant

There are many factors that impact the oxide-RR in CMP besides the applied pressure and velocity. These are expressed in Preston's Law by changes in the Preston constant. Here two models are given that have been proposed to explain the dependence of oxide-RR on other phenomena besides pressure and velocity.

8.5.2.1 Impact on the Oxide-RR from the Electrochemical Interactions Between the Slurry Particles and the Oxide Surface: A model was proposed by Cook in which he postulated that a mechanism for oxide-removal by CMP involved contact-mediated reactions with the solvent (water).¹⁷ That is, local events in CMP may be considered to be the approach to contact of two opposing asperities: 1) pad plus adhering particle; and 2) the oxide surface. Asperity-contact causes reactions in the vicinity of the contact, and these result in mass removal from the oxide. The depth and width of the swath removed is determined by the size of the slurry particle and the chemical-reaction-rate, which is largely controlled by the interaction force between the contacting surfaces. The length of the swath gives an indication of the duration of the asperity contact.

For the case where the slurry particle and the surface are of the same material (as occurs in oxide-CMP with a silica-based slurry), the forces due the Zeta-potential act to repel the silica particles from the oxide surface, while the Van-der-Waals forces cause the oxide surface to attract the slurry particles (see Sect. 8.7.1 for a discussion of the Zeta-potential and the Van-der-Waals forces). The curve that graphs the force-versus-distance for such a case of opposing forces between the particles and the wafer-surface exhibits a maximum repulsion at some characteristic separation distance. This may be perceived as an activation-energy-barrier for closest approach. The particle must thus have a kinetic-energy greater than this activation-energy-barrier in order for direct contact to occur between the slurry particle and the oxide-surface. A reduction in this activation-energy-barrier should result in a higher probability of contact, and therefore cause an increase in oxide-RR.

Based on this model, Cook suggested that an increase in RR could be achieved by using a slurry whose particles were different than that of the oxide (e.g., use CeO_2 slurry particles instead of silica), and in which the Zeta-potential had a value that caused the slurry particle and the oxide to attract one another. This would strongly increase the probability of contact between the slurry particle and the oxide-surface and thus increase RR.

8.5.2.2 Dependence of Oxide-RR in CMP on Dielectric Hardness: Dielectric materials vary in hardness from the very-hard and inelastic silicon-nitride, to softer dielectrics such as doped-oxides and spin-on-dielectrics (SODs). The RR of dielectrics has been found to increase with a decrease in their hardness. Figure 8-22 shows that as the hardness of fluorinated-silicate-glass (FSG) is decreased, the RR increases.¹⁸ (The hardness of the FSG in this study was decreased by increasing the concentration of fluorine that is incorporated in the oxide.) In another work, the RR of PSG and BPSG was studied as a function of the P-concentration in a P-doped oxide-film, and as a function of the B- and P-doping in a BPSG oxide film (Fig. 8-23).¹⁹ Higher doping is seen to cause the RR to increase. This is correlated with oxide hardness, since the incorporation of P_2O_3 and B_2O_5 into an SiO_2 -network causes a softening of these oxide-films.

8.5.3 Models Which Describe Chemical-Mechanical Phenomena that Give Rise to Planarization Phenomena Associated With CMP of Oxides

Various models have been proposed to explain how chemical phenomena act in concert with the mechanical forces affecting oxide-RR (as expressed by Preston's Law). These models also provide insight as to why oxide-CMP can selectively remove the "up-regions" of an oxide film on wafers faster than the "down-




Fig. 8-22 A linear relationship exists between the CMP-removal-rate and the hardness and elastic modulus of F- SiO_2 . Removal-rate, hardness, and elastic modulus are all normalized with respect to those parameters of undoped TEOS-oxides.¹⁸




Fig. 8-23 a) Removal-rate of PSG as a function of phosphorus-concentration: pressure 4-psi, table speed: 40-rpm, carrier speed: 643-rpm; b) Removal rates of P-doped oxides and B-doped oxides as a function of P- and B-doping-concentration in the oxide.¹⁹

regions" (thereby allowing planarization of the film to occur). Some ideas from these models are discussed in this section.

Izumitani proposed that optical-glass-polishing "proceeds by the formation of a hydrated-layer by means of a chemical-reaction between the glass-surface and water and then the removal of this hydrated-layer by the abrasive particles."²⁰ This proposed mechanism is consistent with the observation that the polishing-rate is extremely low without the presence of water to cause the hydration. (Polishing with a slurry of silica-particles in a non-aqueous solution [e.g., in oil] exhibits substantially lower polishing rates.) The hydrated-layer that thus forms on the oxide-surface generally has a much lower hardness and mechanical strength than the SiO_2 beneath it. Therefore, plastic-deformation results in mechanical removal of the hydrated-layer (by a plowing effect) when it is rubbed by the abrasive particles.

The same type of mechanism is expected for oxide-CMP. Removal of the oxide takes place by a combination of mechanical and chemical action, using an abrasive slurry dispersed in alkaline solution (Fig. 8-24). Since silica-particles are used in the slurry of oxide CMP, they have about the same hardness as the SiO_2 . Thus, the unreacted SiO_2 is not appreciably removed (nor damaged) by the plowing effect when it is rubbed by the silica particles in the slurry. However, the silica-slurry-particles still cause the oxide to plastically deform. This deformation




Fig. 8-24 Depiction of polishing-pad compression and localized pressures applied to topographic features. Pressures are greatest at the top-leading-edges of steps, and are lowest in the wakes of the steps.

is likely to be assisted by frictional heating. It has been determined that oxide readily undergoes hydration (water entry) if it is plastically deformed by a diamond indenter. When entered by water, the hardness and mechanical strength of the oxide is generally decreased. Thus, during CMP, it seems that hydration of the oxide film surface is caused by the plastic deformation of the oxide by the abrasive particles. The degree of deformation is increased as the pressure of these particles on the surface is increased, and by frictional heating. The softer hydrated-layer is then removed by the plowing action of the abrasive particles, which increases as the linear-velocity of the polishing pad is increased. These conclusions are substantiated by Preston's Law. The properties of the pad also appear to play an important role in CMP. It is probable that the polishing pad has to be soft enough to grip the abrasive particles, but hard enough to transmit the pressure to the oxide. It is generally agreed that some sort of chemical mechanism (such as SiO_2 -dissolution) is a cofactor in causing oxide-CMP. Various chemical processes have been proposed.²¹ The larger polishing rate in higher-pH slurry is often cited as evidence for silica-dissolution.

8.5.3.1 Model of the Mechanism that Produces Planarization of Steps In Oxide

CMP: While the above model gives some insight into how oxide is polished with a silica-based slurry, it does not address the issue of how planarization of the oxide by such polishing is achieved. To obtain planarization of a film with topography, the surfaces of elevated features ("up-areas") must be eroded faster than those at lower elevations ("down-areas"). The selective removal of material in "up-areas" is empirically observed to depend on many factors, including the

feature dimensions, the structure (and surface condition) of the polishing pad, and the height of the step being removed

It is important to note that the case being discussed here involves the CMP of an oxide layer that proceeds only until the oxide surface is planarized, and that the surface of the wafer after the CMP step is *homogeneous* (i.e., only oxide is exposed over the entire wafer surface at the conclusion of the CMP step, as shown in Fig. 8-25a). This differs from the case when a film is polished until it is removed from the surface in some regions, but is allowed to remain in recessed regions of the wafer surface after the CMP step. In that case (which is described in a later paragraph), the wafer surface is *heterogeneous*, insofar as some exposed areas of the wafer contain the polished film residing in recesses, and others contain material that underlaid the film that was polished (Fig. 8-25b). Note that in the second case, the CMP process is essentially a *blanket-removal-process of a planar film* because the film being removed is already roughly planar when the CMP process is started.




Fig. 8-25 The process of removing material by CMP falls into two categories: a) Removing homogeneous material and stopping while the removal of the surface film is incomplete (e.g., planarization of an ILD oxide); b) Removing deposited material, but continuing until all material is entirely removed on some regions of the wafer surface, while in other regions it remains recessed below the surface (e.g., Cu-damascene feature formation by CMP).

Selective removal of material that protrudes above the surrounding topography (as shown for the case of Fig. 8-25a) is thought to arise in part from the compliant nature of the polishing pads.²² Figure 8-24 depicts the localized compression occurring within a pad as features on the wafer surface are driven across it. The pad applies pressure to the wafer surface through the slurry, with the largest pressures being exerted where the pad is most compressed. Higher pressure is applied to elevated regions (“up-areas” - Fig. 8-26) and the leading edges of the features that are moving against the compressed pad, compared to lower-lying regions (“down-areas”) and trailing edges.²³ The difference in local applied pressure causes the material removal rate to be fastest at the upper corner of the leading edge of a step. Figure 8-27 shows how a feature would be planarized as the leading edge is eroded away as a function of time during a CMP process. (In the next section it will be demonstrated how this phenomenon - in concert with wafer rotation during polishing - causes smaller features to be rounded-off and polished-aster than wider features.)

As the steps erode, the “down-areas” are exposed to increasing pressure, and the removal-rate there increases (approaching that of the “up-areas”). As this happens, the rate of step-height-reduction decreases toward zero. In the latter stages of the polishing process the selectivity is so low that small residual steps remain, and in practice cannot be fully removed by continued polishing.

In the second case described above (Fig. 8-25b), the material of the blanket-deposited layer is removed non-selectively by CMP. This non-selective removal continues until all of the film is polished away from the areas of the substrate, and only film material remains in the trenches. However, if the CMP process is continued beyond that point, material within the trenches will continue to be removed. This removal will be greater in wide trench areas than in narrower trenches. The result of such removal from wide trenches gives rise to a CMP problem called *dishing*. The phenomenon of dishing and methods developed to mitigate it are also discussed in other parts of the book. In Sect. 8.12.1, the general aspects of dishing are covered, and the impact of dishing effects on the fabrication shallow-trench-isolation structures is found in Chap. 9. Chapters 15 and 16 provide additional information on the impact of dishing on Cu-CMP and on the CMP processes used to polish inlaid metal lines in damascene processes.

8.5.3.2 Pattern-Dependence of the Planarization Rate in CMP Processes: The degree of planarization (DOP) of features for the CMP processes depicted by Fig. 8-17a has been found to depend on the feature sizes and the density of features within a region of a die. This DOP dependency on feature size and pattern density is one cause of WIDNU. The reasons for such WIDNU are described here.




Fig. 8-26 Cross section of conformal dielectric on patterned metal, showing the “up-regions” and “down-regions” of the dielectric film.

The first question to answer is why narrow, isolated-features tend to planarize faster than wide isolated features. From Fig. 8-27 we see that the leading edge of a step will be removed as a function of time in an oxide CMP process. However, in a process in which the wafer carrier is rotating, all top edges of the feature being polished become the “leading edge” as the feature is rotated by the carrier. As a result, the entire feature is planarized according to the sequence shown in Fig. 8-28a. If the feature is wide, the leading edges will be polished away, as shown in Fig. 8-28b, but the material in the center of the wide feature will not be polished as quickly as material at the feature edges. As a result, wider, isolated-features will planarize more slowly than narrow, isolated features. This will cause such WIDNU as shown in Fig. 8-13.




Fig. 8-27 A depiction of how the leading edge of a feature of an oxide step (i.e., the edge that is pressed against the pad by the combined movements of the carrier and platen), is eroded by CMP.




Fig. 8-28 Schematic cross-section of a narrow and wide feature of oxide being polished by CMP, as a function of time. Since the leading edges are polished most rapidly (and the feature continually rotates, so that all edges become the leading edge for the same amount of time), the narrow feature is planarized more rapidly than the wide feature.

The next question is: Why are densely-spaced narrow features planarized more slowly than isolated, narrow features? As first discussed by Burke,²⁴ the time required to planarize an "up-area" structure as shown in Fig. 8-26 (or to reduce its height to some fraction of its initial value) is dependent on the "down-area" adjacent to it. Specifically, the time to planarize a step depends on the width of the "up-area," the width of the "down-areas" between "up-areas," and the ability of the polishing-pad to rigidly span that distance between "up-areas." The stiffer the pad, the more rigid the span - and the slower the rate of material removal from "down-areas." This gives good planarization. The softer the pad, the less able it is to bridge larger distances. Thus, more material is removed by softer pads in "down-areas" between adjacent "up-areas." This gives poorer planarization. When features to be polished are separated by distances greater than the leveling-distance of the pad, there is no selectivity between "up-areas" and "down-areas," and planarization does not occur. In practice, some selectivity in RR occurs between "up-" and "down-areas," but this selectivity is not complete. Ideally, the leveling-distance of a pad should be large enough to planarize the widest "down-areas" on a chip. On the other hand, the greater the leveling-distance, the more a pad will respond to wafer-scale non-flatness parameters, such as TLV and bow. This results in non-uniformity of the polished film thickness across the wafer (a subject discussed in more detail in Sect. 8.12.2).

In summary, planarization will occur most slowly for step heights in an oxide over the largest or densest interconnect structures adjacent to wide unpatterned

field areas, scribe lines, and wafer edges. It will occur most rapidly for step heights in the oxide over smaller arrays and narrow, isolated features. It is also necessary to specify an acceptable degree of planarization, because in the latter stages of the CMP process, material is removed nearly as fast from “down-areas” as from “up areas.” Step heights no longer decrease at appreciable rates.

Like metal-CMP processes, oxide-CMP in a production environment is often a multi-step process. When in-line endpoint-detection is employed (as will be discussed in Sect. 8.6.9), two or more polishing steps may be needed to obtain the correct oxide thickness. In addition, a separate final-polish (or buff) procedure is frequently used to provide light polishing and to remove slurry particles and small wafer-defects. A small amount of oxide can also be buffed away with this buffing procedure (typically 30–40-nm), which aids in removing defects (especially residual slurry particles and the small scratches created by the primary polish). Use of a buff procedure is one of the reasons why CMP can actually *reduce* defect-densities (including eliminating some types of defects created in other processes), rather than increase them.²⁵

8.5.4 Metal-CMP Mechanisms

The mechanisms involved in the CMP of metals which cause planarization of the metal film surface, follow a relatively simple three-step sequence proposed by Kaufman.²⁶ This three-step sequence is as follows (Fig. 8-29):




Fig. 8-29 Schematic representation of the model of CMP of metal films.²⁶

1. A passivation layer (e.g., an oxide of the metal) is chemically formed on both the “up-areas” and “down-areas” of the metal film, due to the oxidation potential of the solution. (For effective polishing, it must be possible to both oxidize the metal and closely match the hardness of the slurry abrasive to the hardness of the material being removed.)
2. This freshly formed oxide film is softer than the metal itself and is mechanically removed from the “up-areas” by the pad/abrasive. (While the “down-areas” are not contacted due to the partial flexibility of the pad.)
3. The corrosive nature of the slurry re-grows the passive film on the “up-ares,” while the corrosive elements are blocked from the metal in the “down-areas” by the passivation film.

The “up-areas” are continually corroded and polished until the pad flexibility allows it to contact the “down-areas.” At that point, the planarization process again depends on the hardness of the pad and the down-force applied to the wafer. Thus, the corrosion properties of the slurry are chosen to convert the metal surface into a film that is soft enough to be abraded by the pad-plus-abrasive-material, yet hard and impermeable enough to prevent outright etching of the metal.

The goal is to find slurries with just the right combination of chemical and abrasive aggressiveness to produce high removal-rates, good-planarity, local-uniformity, and high-selectivity. Although the metal-CMP-model is simple to understand, successfully carrying out the above process for specific metals can be challenging. The slurry’s chemical-composition tends to play a more important role in metal-CMP than in dielectric-CMP. As a result, it is possible to achieve fairly high metal-to-oxide selectivity (e.g., 120:1 for tungsten to silicon dioxide). However, the slurry solution may also etch the metal-oxide that is formed. A careful balance between etching and oxidation must therefore be maintained. If etching dominates, then the metal will etch isotropically and planarization will not be obtained. The metal-deposition-step may also have to be modified to prevent metal deposition near the wafer edge. Otherwise, metal residue may re-main on the wafer’s beveled edge after CMP, causing yield and reliability problems.

Pourbaix diagrams are often used to identify which pH-range is most ideal for CMP of metals.²⁷ *Pourbaix diagrams* are graphical representations of the domains of stability for different oxidation states of metals in aqueous solutions with respect to pH and electrochemical potential (i.e., contour maps in a solution potential versus pH). For example, the Pourbaix diagram for W (shown in Fig. 8-30) indicates that in order to form an un-dissolved protective WO_3 layer over the W, the pH of the solution should be below 4, and have a slightly positive oxida-




Fig. 8-30 Tungsten solubility versus solution-pH (Pourbaix) diagram.²⁷

tion potential. For this reason, most tungsten slurries have a low pH, typically with pH-values between 2 and 3.

Unlike oxide CMP processes (whose purpose is to remove a specific amount of the dielectric layer), the metal-CMP processes require some degree of overpolish to ensure that metal is completely removed from field areas. The challenge here is to optimize such overpolish so that process time and oxide loss are minimized (i.e., to maximize throughput), while compensating for any non-uniformities from prior steps (and without causing any new uniformity problems from dishing or erosion).

It should also be mentioned that one aspect which makes metal-CMP processes easier to control than oxide-CMP processes, is that commercially available endpoint methods are much more sensitive for metal CMP. That is, metal-CMP processes are carried out by polishing-back blanket-metal-layers until all of the metal on the wafer surface is removed (but the metal in the via holes or within the trenches remains). Once the metal on the top surface is removed, the underlying oxide in the field is exposed. Consequently, this endpoint is easier to detect by monitoring a variety of phenomena associated with the clearing of the metal over the oxide, such as: **a)** a change in surface reflectivity; **b)** a change in surface temperature; or **c)** a change in the torque of the platens or wafer carrier (due to the different frictional coefficients of the materials being polished). In any case, the optimum metal-CMP process would have a clear endpoint-signal -followed by a short overpolish step (to remove any

metal remaining in dished areas of the wafer, or in surface scratches). The result should be a surface in which the metal and the barrier-layer is completely removed, with a minimum of the underlying dielectric being eroded, and where a minimum amount of dishing is produced.

8.6 CMP EQUIPMENT

There are number of different tools and consumables used in a complete CMP process, including:

1. CMP polishing tools;
2. Slurries;
3. Pads;
4. Slurry distribution systems;
5. Endpoint detection systems;
6. Cleaning tools;
7. Metrology tools.

These items are described in the following sections.

8.6.1 CMP Polishing Tools

The basic polishing tool used for CMP evolved from the machines used to polish bare-Si-substrate-surfaces. When the idea for CMP was first conceived at IBM, they purchased silicon polishing tools (used by wafer manufacturers) from Westech (now SpeedFam-IPEC) and Strasbaugh. The basic configuration of the wafer-polisher was retained, but the tools were modified to make them suitable for developing CMP. As mentioned earlier, in such polishers the wafer is mounted upside down on a wafer-carrier, and the carrier is pressed downward against a polishing pad (Figs. 8-31 and 8-32). Both the wafer carrier and polishing pad are rotated. Slurry is dripped onto the polishing pad, and it becomes saturated with slurry. The pad thus drags slurry beneath the rotating wafer carrier, where it can polish the wafer surface (as described earlier in the section on mechanisms of CMP). The first polishers adapted for CMP had a single wafer-carrier.

The CMP-polisher differs from the wafer-polishing tool in a number of ways. In polishing silicon-wafers, several tens-of-microns of material are removed, while the CMP-process removes only about $0.5\text{--}1.0\text{-}\mu\text{m}$ of material. The uniformity of material removal across a wafer in CMP is also much more stringent than in silicon-wafer polishing ($\pm 0.5\text{--}0.1\text{-nm}$ for CMP). Furthermore, CMP-tools require a higher-level of automation, throughput, reliability, and critical process-parameter-control. Thus, despite more than 30 years of experience in silicon-wafer polishing, new processes and equipment had to be developed by the IC industry for carrying out CMP.




Fig. 8-31 Schematic diagram of a wafer being polished by CMP.

The Westech and Strasbaugh polishers first used by IBM were also the tools that found widest use in the early CMP processes. IBM provided to SEMATECH one of these silicon-wafer polishing tools from Westech. This tool was used by SEMATECH to launch a program that focused on improving the tool's ability to do CMP on the thin films encountered in VLSI structures, and to increase the tool reliability. The results of this program were used in designing the IPEC model 472®-CMP-tool, which achieved wide adoption for CMP applications during the mid-1990's. Figure 8-33 shows a plan view of an IPEC Avanti 776® polisher, a modified version of the 472 tool.

8.6.1.1 CMP Polishing-Tool Configurations: While early CMP tools used a single wafer-carrier, more recent designs contain multiple-carriers (and multiple-platens). This increases the throughput of the polisher and allows multi-step CMP processes to be carried out on a single tool. The classes of CMP polishing tools can be categorized according to the manner in which motion between the wafer-carrier and polishing table is produced. These categories are as follows:

1. *Rotary CMP Tools* (in which both the table [or platen] and the carrier rotate);
2. *Orbital CMP Tools* (in which the carrier rotates, but the table moves in an orbital path);
3. *Linear CMP Tools* (in which the carrier rotates and the table moves in linear path);
4. *Fixed Table CMP tools* (in which the table is stationary, but the carrier moves in an orbital path).

Table 8-1 lists some commercial CMP polishing tools and categories into which they fall.

8.6.1.2 Rotary CMP Tools: Figure 8-32a shows a schematic of a single-carrier/single-platen *rotary CMP tool*. The motion between the wafers and the pad is created by the rotation of the platen together with the rotation of the wafer-carrier. (The carrier also holds the wafer face down, and applies a downward force against the surface of the pad mounted on the rotating platen.) The pad is afixed to the flat table by a waterproof-adhesive. The following tools are examples of rotary-motion CMP tools with multiple wafer-carriers: Strasbaugh Symphony,[®] which has four wafer-carriers and three platens (Fig. 8-34); SpeedFam-IPEC Auriga[®] which has five wafer-carriers and two platens (for primary and secondary polishing, Fig. 8-35); Cybeq Nano-Tech-Isoplanar-8000[®] which has six-wafer carriers; and Applied Materials Mirra[®] with four wafer-carriers and three platens (each with an *in-situ* pad-conditioning arm, Fig. 8-36). In the Mirra,[®] a central spindle transports the wafer-carriers from one platen to the next. A three-platen-configuration (such as is available on the Symphony[®] and the Mirra[®]) permits three-step CMP-processes to be performed on a single tool.





Fig. 8-32 CMP tool configurations: a) Rotary tool; b) Linear tool.

TABLE 8-1 Classification of Some CMP Polishers

Vendor & Model	Table motion-number	Carrier type-number	Built-in endpoint methods ¹	Special features
	Established	Polishers		
AMAT Mirra	Rotary-3	BB-CRRC-4	Red laser reflectometer	Sequential use of 3 tables
Cybeq 8000	Rotary-1	BB-CRRC-6		
IPEC 372/472	Rotary-2	FBC/NRRC-1	Absolute temperature	Sequential use of 2 tables
IPEC 676	Orbital-4	BB-CRRC-4		Parallel tool
IPEC 776	Orbital-4	BB-CRRC-4		Ditto, Integrated Ontrak scrubber
Speedfam/Auriga	Rotary-1	FB-NRRC-5	Visible light reflectometer	
Strasbaugh/6DS-SP	Rotary-1 or 2	FB-NRRC-2		2 carrier size buffing platens, optional 2nd table
Strasbaugh/Symphony	Rotary-3	FB-CRRC-4		
	Developing	Polishers		
Lam/Teres-	Linear-2	?-2		Fluid bearing platen
Ontrak/Synergy	Integrated Cleaner			Disposable 3-M
Obsidian	Fixed-1	Orbital, BBC?-1		slurryless pad

8.6.1.3 Orbital CMP Tools: In *orbital CMP tools*, the wafer-carrier rotates in the same manner as in the rotary CMP tools. The platen, however, executes an orbital path about the center of the rotating carrier (instead of rotating about its own central axis (Fig. 8-37). In this approach the removal-rate-non-uniformity problem encountered in rotary CMP tools is circumvented. This occurs because the travel distance of all loci on the wafer surface relative to loci on the platen surface are equivalent. Another advantage of this tool configuration is that it uses a platen with a smaller radius than that needed in a rotary polisher. As a result, the footprint of the polisher can be significantly reduced. Orbital CMP tools are sold by IPEC-Speedfam in their AvantGaard 676,[®] AvantGaard776,[®] and Momentum[®] models. Figure 8-38 shows the SpeedFam-IPEC Momentum,[®] which has four wafer carriers and four platens.

8.6.1.4 Linear CMP Tools: CMP tools that have a pad in the form of a continuous belt (that moves in the same fashion as a treadmill) are also available. The pad is thus moved past the rotating wafer carrier in a linear (rather than rotary) motion (*linear CMP tools*). These tools offer the potential benefits of higher linear



linear speeds 400–500-ft/min (versus 34-ft/min in rotary CMP tools), harder pad materials, and reduced polishing-pressure (i.e., because the polish rate can be maintained at a high value with reduced applied pressure, as a result of increased pad velocity). This type of tool may be able to produce better planarization of oxides in a shorter time and reduce the problem of dishing in CMP (see Sect. 8.12). Linear CMP tools are offered by Lam Research (Teres® Fig. 8-39), Apex, and Doosan. The Teres® has two linear polishing belts, and one station with a rotating platen (for carrying out buffing or cleaning steps). The wafer carriers move independently from one station to another. The Teres® also employs an *air bearing* beneath the polishing belt. This allows the pressure distribution across the wafers to be profiled. At a given pressure and speed, adjustments to the pressure-distribution profile can be made to significantly reduce film-thickness non-uniformities (Sect. 8.12). The removal-rate non-uniformity problem encountered in rotary CMP tools is also circumvented in linear CMP tools. Improved planarization efficiencies (i.e., less oxide needs to be deposited to achieve complete planarity) have also been claimed for this configuration.

Petitioner Samsung Ex-1012, 0377




Fig. 8-34 Schematic drawing of the Symphony[®] CMP tool. Courtesy of Strasbaugh Corp.

see Fig. 8-41). This tool also employs a slurry-less pad supplied by the 3M Corp. The pad material is mounted on a roller (akin to a roll of paper towels). After each wafer is polished, the roll is advanced to remove the used pad-surface. This makes a new segment of pad material available to polish the next wafer (roll-to-roll transport of the slurry-free pad). Applied Materials acquired Obsidian in 2000, but by the end of 2000, the tool had not yet been commercially released.

8.6.1.6 300-mm CMP Tools: Many semiconductor equipment manufacturers are readying CMP polishing tools for 300-mm wafers. By mid-2000 more than a dozen CMP equipment manufacturers have exhibited or announced intentions to participate in the 300-mm market.²⁷ It is reported that most 300-mm CMP tools are capable of reaching the performance capabilities of the 200-mm tools. However, challenges remain with respect to the issues of consumables costs, integration of metrology, and full automation. In some cases a reduction in consumables cost is being achieved. For example, in the Speedfam-IPEC 300-mm polishing tool, slurry use is increased by only 20% over that needed in the 200-mm tool, whereas the area of the wafer being polished is increased by a factor of 2.25. This has a net positive effect on the CoO. Edge exclusion zones of 3-mm or less are also reportedly being achieved on these tools.

8.6.2 Wafer Carriers in CMP Polishing Tools (and the CMP Edge Effect)

In Fig. 8-42 the wafer is shown mounted on the carrier. The traditional wafer carrier consists of a circular plate (chuck) within a pocket (which holds the




Fig. 8-35 Detailed view of the SpeedFam-IPEC Auriga® five-carrier polishing tool. Courtesy of SpeedFam-IPEC, Inc.




Fig. 8-36 Architecture of the Mirra® three-platen CMP tool. Courtesy of Applied Materials, Inc.

wafer), attached to a rod by a gimbal (Fig. 5-43)). Downward force is applied to the plate by the rod during polishing. The depth of the pocket in which the wafer resides is chosen to allow the top-surface of the wafer to extend beyond the pocket, permitting its surface to be polished. Instead of the wafer being directly in contact with the steel chuck, a backing film is sandwiched between the wafer and the chuck. This film provides elasticity. Without a flexible backing film, any




Fig. 8-37 Schematic drawing of orbital platen motion polisher.



Fig. 8-38 Photograph of the Momentum,¹⁰ an orbital platen motion polisher. Courtesy of SpeedFam-IPEC, Inc.

defect or particle on the chuck (or the back of the wafer) will cause a thin spot in the film being polished. In addition, the possibility of wafer breakage is




Fig. 8-39 Schematic drawing of the Teres® linear CMP tool. Courtesy Lam Research, Inc.




Fig. 8-40 Schematic drawing of orbital carrier-motion with indexing pad.

increased. Early backing films were merely thin foam layers. They did little to lessen the polish-performance-dependency on the variations of wafer-thickness or flatness. In order to more fully compensate for wafer-to-wafer variations in flatness and film-thickness, much development work has been done to improve the wafer-carrier design.




Fig. 8-41 Fixed-table with roll-to-roll pad. Carrier rotates and also executes linear motion.




Fig. 8-42 Schematic drawing of the components of a CMP wafer-carrier.

Two key design elements in the improved wafer-carriers are:

1. The retaining-ring;
2. The wafer-leveling mechanism.

The primary function of the *retaining-ring* is to prevent the wafer from slipping out of the pocket when high down-force and high-speeds are used. Wafer retention can be maintained even with an average down-force of about 2-psi if the retaining-ring extends past the mid-thickness of the wafer. To keep the retaining-ring surface from being polished, some wafer-carriers may keep the retaining-ring about 100-microns off the pad surface. Wafer-carriers with such rings are termed *non-contact retaining-ring carriers* (NRRC). In NRRCs there is no pressure applied to the pad by this ring. The other type of retaining-ring




Fig. 8-43 Carrier being subjected to gimballing down force.




Fig. 8-44 Comparison of: a) film-backed/non-contact retaining-ring carrier (FB-NRRC); and b) bladder-backed/contact retaining-ring carrier (BB-CRRC); c) distribution of pressure profile at wafer edge for FB-NRRC.

design causes the retaining-ring to contact the pad. Hence, carriers with these rings are called *contact retaining-ring carriers* (CRRC). The CRRC also has the capability of varying the down-force on the wide (typically 10-25 mm-wide) bearing surface of the ring. Wafer-carriers used in some polishing tools (e.g., Applied Materials' Mirra® and Strasbaugh's Symphony®) are designed with a retaining-ring that can apply variable pressure to the pad.²⁸ This allows the pad profile at the wafers edge to be controlled. A smaller edge-exclusion zone on the wafer can therefore be used (2-3 mm).

Wafer leveling by the wafer-carrier is accomplished by backing the wafer with: 1) a compressible film (i.e., *film back carrier*, FBC); 2) a pneumatic bladder (*bladder-backed carrier*, BBC); or 3) a lip-sealed air bearing (*air-backed carrier*, ABC).

The earliest wafer carriers were FBC-NRRC (Fig. 8-44a). Perforations in the backing film and the flat surface plate are used to vacuum-attach the wafer to the carrier during transport. The backing film acts as a cushion to distribute the down

force evenly to the wafer. Early backing films were chemically-impregnated felt materials that had to be applied by hand, but they were only useful for about 25 wafers. Newer backing films (such as the DF200, the WB, and the R200 films) last about 200-800 wafers. (The reason backing films wear out is that they are compressed and de-compressed each time they are used. At some point, the film will lose its ability to recover and takes a “set.”) In FBC-NRRCs the pad pressure at the edge of the wafer is not well controlled, and the polishing rate of the film is decreased at the wafer’s edge. Hence, a wider edge-exclusion ring of 5-7-mm must be enforced for wafers with such carriers.

The second type of wafer-carrier is the BBC-design (Fig. 8-44b). In the BBC a rubber inner-tube-style bladder is substituted for the backing film. The chamber created by the bladder can be alternately vacuumed or pressurized. When the carrier brings the wafer into contact with the platen, first pressure is applied to the retaining-ring bladder (with a sufficient down force to clamp the wafer within the retaining-ring). Next, the wafer-bladder may be vented or pressurized. Usually the platen is stationary when the wafer-carrier retaining-ring makes contact and the wafer-bladder is vented until the wafer-carrier comes to speed. Then the wafer-bladder is pressurized. Since the wafer “floats” on the bladder bubble, global and local planarity of the wafer surface is accomplished without gimbaling the wafer-carrier to the head of the tool.

The air-backed wafer-carrier (ABC) functions much like the BBC. However, instead of a bladder to contain the air pressure (or vacuum) behind the wafer, it has a compliant lip-seal around the backside edge of the wafer. However, the seal is not easy to maintain, and slurry particles can enter and contaminate the backside of the wafer. As a result, ABC types have not yet been commercialized.

8.6.2.1 CMP Edge-Effect

The removal-rate of material by CMP should ideally be uniform across the wafer (i.e., the WIWNU should = 0). However, for various reasons, non-uniformity of material removal within a wafer is generally observed. One of the most common forms of WIWNU is the *CMP edge-effect*, in which the removal-rate is much smaller at the edge of the wafer, leaving an edge-bead of material at the conclusion of the CMP process. Figure 8-45 shows two typical thickness profiles of wafers polished by two different polishers, along a wafer-diameter. In both cases, an edge-bead, 100-200-nm high, exists after the polishing step. This edge-bead will generally render devices fabricated in that area inoperable. As a result, devices fabricated within a region near the edge of the wafer are considered to be excluded as candidates for working die, and this ring near the edge of the wafer




Fig. 8-45 Edge effect observed in CMP.

is termed the *exclusion ring* (Fig. 8-46). In current polishers, the exclusion ring is 3-mm wide. However, as wafer sizes are increased, the number of die at the wafer's edges keeps increasing (Table 8-2).²⁹ In order to obtain more yielding die per wafer, methods to further reduce the edge exclusion ring are being pursued.

The edge-bead-effect is attributed to the pad-deformation-profile and the pressure-distribution near the edge of the wafer. As a result, this effect can be significantly reduced by optimizing the pressure distribution at the edge of the wafer, primarily through the use of contact-retaining-ring-carriers (CRRC). The bulk physical properties of the polishing pad (such as its hardness, flexibility, compressibility, energy-absorption, and rebound) also all influence the width of




Fig. 8-46 Exclusion ring.

TABLE 8-2 Edge Die Count versus Wafer Diameter

Wafer diameter	Total wafer die count	Edge die count	Edge die percentage	Max edge revenue (\$B)
300 mm	515	107	21%	2.76
200 mm	217	69	32%	1.78
150 mm	115	48	42%	1.24
127 mm	71	38	53%	1.00
100 mm	43	26	60%	0.68
76 mm	21	16	76%	0.43

the exclusion ring. Pad materials that provide the hardness necessary for planarization (but remain compliant enough to transfer dynamic contact-pressure more evenly), will deliver improved edge-exclusion. New materials for polishing pads and sub-pads have been designed to improve the uniformity of contact.³⁰

8.6.3 CMP Consumables (Slurries)

Slurries consist of small, abrasive particles (generally inorganic oxides) of specific shape and size (typically 10–100-nm) suspended in an aqueous solution. The abrasive particles have roughly the same hardness as the film being polished. Reagent chemicals, such as acids, bases, surfactants, buffers, corrosion inhibitors, and complexing agents, are also added to the solution, depending upon the material to be polished. The slurry parameters that impact the polishing-rate include the chemical composition of the slurry solution (and its pH) and the concentration (in wt %) of the solid-particles in the slurry. Also important are the shape, size, and size distribution of the slurry-particles. An automatic slurry feeding system is used to ensure uniform wetting of the polishing pad and proper delivery of the slurry. Slurries are marketed by a number of suppliers, the largest of which is Cabot Corp. More slurry vendors are entering the market, including Rodel Inc., Fujimi Inc., Olin Microelectronic Materials, Praxair Surface Technologies, and EKC Technology, Inc.

The goal for each CMP process is to find a slurry that produces high removal-rates, good-planarity, local-film-uniformity, and high-selectivity. Also important are the ease with which the slurry can be cleaned from the wafer, the aggressiveness with which it attacks the polishing equipment, its storage stability, and the cost of disposing of the slurry waste. From a manufacturability perspective, consistency is a critical issue. That is, slurries have tended to exhibit quite a lot of variability from batch-to-batch. In the future, suppliers will be

expected to deliver slurry that has the same performance consistently. If this can be done, the need for monitor wafers will be significantly reduced, allowing the cost of the CMP process to be decreased.

The shelf-life of slurry is also an important characteristic. This determines how long a slurry can be stored before use after manufacture. Some slurries need to be kept within a specific temperature-range during shipping and storage to maintain their performance. The shorter the shelf-life of the slurry, the narrower the window in which it can be used, and inventory-control becomes important. An ideal shelf life for slurries is at least one year.

As CMP technology has evolved, slurry technology has therefore also had to progress to keep pace with the demanding requirements of the industry. Today's CMP slurries are increasingly tailored for specific process applications (like STI or Cu interconnects) as well as for specific polishing tools or other consumables (i.e., pads). Some of these issues have been discussed in Sect. 8.5.2, and others will be addressed in Sect. 8.11. The remaining slurry topics are considered here.

One other aspect of slurry management should also be pointed out. Slurries tend to dry rapidly on a wafer after leaving the wet environment of the polishing table. Once a slurry dries, it is very difficult (if not impossible), to remove all the slurry particles from a wafer surface. To prevent this from occurring, wafers are




Fig. 8-47 a) SEM of fumed-silica slurry-particles. Courtesy Rodel; b) Fumed-silica formation.

rinsed while still on the pad, and then quickly transported into wet-cleaning tanks to remove the slurry. In fabs that do not use polishing tools with integrated cleaning systems, logistical difficulties may delay the transport of wafers from the polisher to the cleaning system, inviting the above problem.

8.6.3.1 Slurries for Oxide-CMP: Slurries for oxide-CMP traditionally consisted of colloidal-silica or fumed-silica suspended in an alkaline solution (typically potassium-hydroxide [KOH] or ammonium-hydroxide [NH₄OH], diluted in DI-water). The first generation of slurries for oxide-CMP contained fumed-silica abrasives, and they still retain a large fraction of the market share. Fumed-silica is manufactured as a dry powder by the oxidation of silicon tetrachloride (SiCl₄) at high temperature in a flame (see Fig. 8-47). The powder must be dispersed and blended into the final slurry. The fact that the fumed-silica must be mixed is inconvenient, and adds cost. The average selling price of fumed-silica slurries in 1998 was \$10-\$15 per gallon. Figure 8-47 also shows a SEM of fumed-silica slurry particles.³¹

Colloidal-silica slurries have entered the market as an alternative to fumed-silica. Colloidal-silica is manufactured by the hydrolysis of sodium-silicate (or other silicates). This is followed by an ion-exchange to reduce the sodium levels for IC applications. (Early on, colloidal-silica was avoided due to the possibility of sodium contamination, but improvements in this aspect of colloidal-silica processing have opened the door for its adoption.) Colloidal-silica is prepared directly in solution, thus avoiding most of the handling problems of fumed-silica. Its microstructure is a distribution of spherical particles (see Fig. 8-48).³² Colloidal-silica slurries also tend to be more stable and less prone to agglomeration than fumed-silica slurries. In addition, their more uniform size




Fig. 8-48 SEM of colloidal-silica slurry particles. Courtesy of Fujimi Corporation




Fig. 8-49 SEM of cerium oxide slurry particles. Courtesy of Fujimi Corporation.

distribution makes it less likely that they will cause microscratches. The cost of colloidal-silica slurries is about 20% higher than that of fumed-silica slurries (\$18 versus \$15 per gallon). The use of colloidal-silica slurries has rapidly increased (replacing fumed-silica slurries), and they find use in STI, ILD, and polysilicon CMP processes.

The solids content of oxide-CMP slurries is 5-35-wt%, and the pH is between 9.0–11.0. By controlling pH within this range, agglomeration is minimized. CMP slurries generally contain few chemical additives. As mentioned above, these few typically consist of: **1)** an alkaline chemical to provide colloidal stability (i.e., to prevent slurry-particle-agglomeration) and to increase oxide removal rates; and **2)** a buffering agent (used to keep the pH constant throughout the slurry volume and over time). The polishing rate of oxide increases with: **1)** increasing pH; **2)** increasing slurry particle concentration; and **3)** increasing particle size.

Slurries for oxide-CMP based on other abrasives than silica have also been introduced in recent years. Ceria-slurries (CeO_2 -based) have been formulated for STI and ILD applications, although ceria is difficult to manufacture at small particle sizes. A self-stopping, dishing-free process using a ceria-slurry was reported by Nojo.³³ Ceria-slurries exhibit a higher removal rate at a much lower pH than silica-slurries (e.g., at a pH of 6 to 7). Ceria-slurries have been adopted for STI-CMP because of their high-selectivity to oxide over nitride (as high as 250:1). Ceria particles can also be blended with silica particles in a slurry. The addition of silica helps keep ceria particles in suspension. In 1998, the average selling price of ceria-slurries was \$18 to \$20 per gallon. Figure 8-49 shows cerium oxide (CeO_2) particles.³⁴

Zirconia-based slurries (ZrO_2) have been investigated for use in low- k -dielectric-CMP, especially the CMP of non-fluorinated polyarylene ethers (e.g.,

FLARE™, from Honeywell, see Chap. 14). Zirconia is harder than silica but softer than alumina. Manganese-oxide slurries (MnO_2) have also been studied for the direct polishing of low- k dielectrics (and for the CMP of W). It was reported that the deep scratches formed with CMP using a conventional silica-based slurry were reduced from a 20-nm depth to a 2-nm depth by the use of a MnO_2 -based slurry. Residual MnO_2 slurry particles can also be removed using H_2O_2 with a pH of 6, which does not attack the fluoro-carbon low- k material being polished (e.g., a poly-AE layer, FLARE®).³⁵

8.6.3.2 Slurries for Metal-CMP: Slurries for metal-CMP applications typically have more constituents than do oxide slurries. Besides the *oxidizer* (e.g., ferric-nitrate and hydrogen-peroxide), and a buffer agent, they may contain: **1)** a *surfactant* (to assist in keeping the slurry particles dispersed, see Sect. 8.7.1.4); **2)** a *complexing agent* (used to facilitate the removal of metal from surfaces, especially in the case of copper); **3)** *corrosion inhibitors* (e.g., benzotriazole [BTA] in Cu slurries to permit the use of acidic slurries); and **4)** *additives to change the selectivity to other films*. The oxidizer is often separated from the abrasive for reasons of colloidal stability or shelf life. In the year 2000 time-frame, choosing and balancing all of these constituents still makes the formulation of metal-CMP slurries as much an art as a science.

Metal-CMP slurries typically use alumina particles suspended in various liquids (depending on the specific metal being polished). Alumina slurries are preferred because they exhibit higher metal-removal-rates and higher selectivity to the oxide ILD-layers (> 20:1, metal-to-oxide). The alumina particles may be fabricated either by a fumed process similar to silica, or by precipitation from aluminum hydroxide.

The pH range of metal-CMP slurries is low (e.g., pH = 1.0-5.0 for W-CMP alumina slurries, and pH = 3.0- 9.0 for Cu-CMP alumina slurries). As noted in the previous section, silica particles in oxide-slurries can be kept well dispersed for relatively long periods of time by controlling the pH of the slurry (giving them a long shelf-life). However, alumina-based slurries have traditionally exhibited the drawback of poor colloidal stability. This causes slurry particle agglomerates to form. Such clumps produce unacceptable microscratches in the films being polished. Recently, improvements have been made in the colloidal stability of alumina based slurries.³⁶ Nevertheless, to overcome this problem from another direction development of slurries based on other particle types (e.g., cerium oxide and zirconium oxide particles) for metal-CMP has been pursued. In 1998, the cost of alumina slurries was between \$25 and \$30 per gallon.

8.6.3.3 Multi-Step Slurries: When carrying out a metal-CMP process (e.g., W or Cu) two materials must be polished (i.e., the main metal, and the underlying barrier [or glue] layer). This CMP-step can be carried out with a process that uses one slurry, or two slurries. While the one-slurry process is simpler, it has not been possible to restrict the problems of dishing and erosion to the necessary degree with such a process. Hence, the two-slurry approach has been adopted. That is, for Cu-CMP, the first slurry removes the bulk of the Cu in the field areas, while the second removes the barrier (e.g., Ta or TaN) from the field areas. These two-step CMP processes significantly reduce the copper dishing and erosion effects. (Generally, the formulations of these slurries still remains proprietary). Use of a CMP-tool with multiple-platens also facilitates the manufacturability of such two-step CMP processes.

8.6.4 Slurry Distribution Systems

Slurry management (i.e., mixing, storage, distribution, and dispensing) is another key issue of a CMP process. Reliable *slurry distribution systems* (SDS) are an increasingly important component of the overall CMP-equipment-set. It is critical that the user of a CMP system view the SDS as an integral part of the CMP manufacturing process, and treat it with as much care as a polisher is given. This will greatly minimize process variations, ensure smooth functioning of manufacturing, and reduce unscheduled downtime.

Slurry management is challenging for a number of reasons.³⁷ Precise mixing and consistent batch blends are necessary to achieve the repeatability demanded by process engineers. The slurry consists of particles in a liquid, and they must be kept suspended in it in a homogeneous state. However, these particles will agglomerate into clumps unless steps are taken to suppress this tendency. (The main source of surface deformations in CMP is generally believed to be the presence of undetected coarser-size particles in the CMP slurry.)³⁸ The slurry-pH plays a role in the dispersion of silica particles. As is described in more detail in the section *CMP Cleaning*, at a pH above 7.5 the silica particles acquire sufficient surface charge to generate electrostatic repulsion, and this effectively keeps the slurry well dispersed.³⁹ (Above a pH of 10.7, however, the particles dissolve and form a silicate.) In addition, from the time the raw slurry is introduced into the SDS it is also critical that a blanket of humidified air be provided over the slurry to prevent agglomeration in the dispense system. Finally, slurries for Cu- and W-CMP require constant re-circulation to maintain particle suspension. (It is typically recommended that a minimum flow-rate of 1-m/sec be used for re-circ-




Fig. 8-50 Slurry distribution system.

ulation). Slurries have a finite shelf-life (after which the agglomerate-level becomes excessive). This shelf-life ranges from less than one week to about one month. Filtering is therefore necessary to prevent any agglomerates (which might have formed during that time), from reaching the wafer being polished.

Slurry handling in an SDS is a delicate task and care must be exercised to prevent "damaging" the slurry. That is, the slurry must not be subjected to excessive shear (which could cause the slurry to agglomerate), or to insufficient shear (which would permit slurry settling). The SDS must also be regularly maintained. Such maintenance involves periodic cleaning out and flushing of the system (as well as the polisher).

The SDS must continuously provide slurry to a number of polishers in a sustained manufacturing production environment (i.e., 24 hours a day, seven days a week, and in high volumes). The pH and solids-content of the slurry must be monitored in-line to ensure consistency. Furthermore, since slurries are abrasive particles contained in chemically aggressive liquids, they present a harsh environment to the components of the distribution system. That is, pumps, piping, valves, and measurement apparatus in contact with slurry, can be stressed to the point of failure in a short period of time. Nevertheless, bulk slurry

distribution systems have been designed to handle these conditions. These systems are sophisticated pieces of equipment, far more advanced than other bulk-delivery systems. Figure 8-50 shows the schematic layout of an SDS, and Fig. 8-51 shows the actual pieces of equipment in an SDS. Such SDS systems are available from vendors including: Mega Systems & Chemicals and FSI International. These vendors supply detailed recommendations regarding design and maintenance of SDS, piping, mixing, and dilution procedures, filtration of the slurry, filter changeouts, and re-circulation of the slurry.

8.6.5 Environment, Safety, and Handling Issues of CMP Slurries

As CMP further moves into large scale IC production, the disposal of spent slurry, CMP process by-products, and metal contaminants (i.e., material removed from the wafer surface) become important issues.

Slurry also always contains aggressive chemicals. In some cases these chemicals are highly toxic. Furthermore, the material removed by a CMP process ends up in the expended slurry and the rinse water. Some IC fabs estimate that CMP processes may come to consume 30-40% of the total water utilized in IC manufacturing. The issue of purification and disposal of this waste water (or




Fig. 8-51 Schematic of a slurry management-system with metrology, auto-dosing and filtration.

recycling), becomes more critical as new materials such as copper, gold, and tantalum become adopted in IC manufacturing. For example, copper is a known toxin in water. Therefore, fabs require waste-water treatment systems to recycle the drain water of CMP processes. The most common limits for waste streams are those for Total Suspended Solids (TSS), heavy metals (like copper, chromium, zinc, and nickel), pH, and total organic content (TOC).⁴⁰

The slurry particles are suspended particles in a solution, and hence they can be removed from the waste water by a process of *flocculation* (i.e., a process by which the dispersed slurry particles are caused to clump together to form larger clusters of matter [i.e., to flock]) followed by filtration. Flocculation involves adding a flocculent and adjusting the pH to a level where the flocculent works best. The slurry particles then agglomerate and settle out of suspension. After the solids are separated, the next step involves ion removal. Either ion-exchange or reverse-osmosis may be used to do this. Note that as slurry volumes go up, they will generate huge amounts of solid waste, estimated at 100,000-400,000 pounds per year, per typical fab, and this solid waste must also be disposed of safely. A decrease in slurry consumption by the CMP-processes will be needed to reduce this waste-disposal burden.

Some companies are also examining the issue of reusing the water from a polisher. That is, while a polisher is in an idle (or pad-wet) mode, there is a continuous stream of DI-water that is used to keep all parts of the polisher wet and reduce the possibility of formation of dry particles. This water generally retains a high purity level and offers the potential of recycle and reuse, thus reducing the waste-treatment-costs for CMP.

One suggested method of reducing slurry consumption is to re-cycle the slurry. In one study of re-using slurry, KOH-based fumed-silica slurry was used to polish a PECVD-TEOS film. The slurry was then captured after being flushed from the CMP tool. By adding new slurry and adjusting the pH to compensate for the decreased solids content and pH, the slurry appeared to be capable of re-use up to six times, while maintaining roughly equal removal rates.⁴¹ In a more comprehensive slurry-recycling process, the slurry-waste would be treated by the following processes: filtration, oxidizer-replenishment, removal of metals, and replenishment of buffers and other necessary additives. The task of slurry recycling (and eventual disposal) could be carried out by the slurry manufacturer. On the other hand, it has also been discussed that the slurry could be leased by the end user, and that it would be sent back to the slurry manufacturer after use for regeneration. The concept of slurry re-use is fraught with a number of

difficult challenges, and is today still in its infancy. The issues of co-operation and development between the end-users and suppliers still need to be addressed before this process becomes an accepted procedure.

8.6.6 CMP Consumables (Polishing Pads)

Pads and slurries are the consumables of a CMP process. Historically, the polishing tools were considered to be the technology's major contributors. But consumables are now being recognized as being equally important. With a new group of consumables being made available, some customers select the slurries first, then review their compatibility with existing tools, and based on the results, select a polishing tool. The importance of CMP consumables is expected to increase with the advent of Cu-CMP and low-*k*-CMP. The general characteristics of polishing pads are described here.

Polishing pads are made of either: 1) polyurethane-impregnated felts; or 2) closed-cell cast and sliced polyurethane (with filler material to control hardness). Urethane is utilized because urethane chemistry allows the pad characteristics to be tailored to meet specific mechanical property needs. Table 8-3 lists the important properties of five polishing pads (all manufactured by Rodel). A thorough discussion of the mechanical properties and the surface roughness of CMP pads is found in pp. 68-83 of Ref. 42.

The pads made from impregnated felts are more porous and can carry a larger volume of water or slurry, due to the basic fiber structure of felt. The Rodel Suba

TABLE 8-3 Rodel Polyurethane Pad Properties

Pad	Specific Gravity	Compressibility	Hardness	Type
Politex Supreme Suba IV	<i>Not available</i> 0.3	High 15%	Soft 61 (Shore A)	Micro porous felt Urethane impregnated polyester felt
Suba 500	0.34	7%	72 (Shore A)	Urethane impregnated polyester felt
IC-1000	0.63–0.85	2.25%	57 (Shore D)	Rigid micro porous cast polyurethane
IC-1400	Top layer IC- 1000, bottom layer foam	0.7%–7%	Flexible	Equal to stacked IC1000/Suba IV




Fig. 8-52 a) Schematic of polishing pad; b) SEM of a new Rodel Suba IV® Pad. Courtesy of Rodel Inc.

IV pads are made of polyurethane impregnated polyethylene felt (Fig. 8-52), which shows a SEM of the surface of a new Suba IV pad.⁴³ They are classified as *soft-polish pads*, and exhibit greater compressibility than the closed-cell polyurethane types. The Rodel Politex pad is also made from a flexible felt-like material, and it is classified as a *finishing pad*, used to buff wafers with water and other chemicals to remove particles and reduce scratch defects.

The Rodel IC-1000 pads are micro-porous, filled, cast pads that have low compressibility (Fig. 8-53).⁴⁴ Pores make up about 30% of the volume of the pad, and the average diameter of a pore is about 30-nm. Such micro-porous, cast pads are classified as *hard-polish pads*. The IC-1000 pad has been the most widely used pad for oxide-CMP processes. The Rodel IC-1400 is a hybrid pad. While there is no consensus, it is generally agreed that the hardness and porosity




Fig. 8-52 SEM of a new Rodel 1000 IC Pad. Courtesy of Rodel Inc.




Fig. 8-54 Photograph of polishing pads, showing pad perforations. Courtesy of Rodel Inc.

of the pad are important parameters and that the pad plays a crucial (but still poorly understood) role in determining the final polish results. However, there is no single physical property of a polish pad that is known to lead to good quality for all CMP tools and consumable sets. Polishing pads are supplied by a number of vendors, with Rodel Corp. having the largest market share. Other suppliers of pads include Thomas West, Freudenberg, Fujimi, and Teijin.

In many CMP applications, two pads are simultaneously used, because a hard pad gives better local (within die) planarity, but a softer pad gives better uniformity of material removal across the entire wafer. Using a combination of two pads provides a compromise between these extremes. For example a hard IC-1000 pad is mounted onto a softer Suba-IV pad to form a stacked pad. On the other hand, the IC-1400 is a single molded pad. That is, it is an IC-1000 pad molded to a more porous backing pad that simulates the compressibility of the Suba-IV pad.

As shown in Figures 8-54 and 8-55, the surface of the pad is either cut with concentric-grooves or contains perforations 1-mm-wide and 250- μm -deep punched into the pad. These grooves (or perforations) form channels to help transport the slurry between the pad and wafer. Pores present on the pad surface also aid in slurry transport.

The desired goal of cost-of-ownership for CMP pads has been identified as less than \$0.05 per wafer. The cost of closed-cell polyurethane pads is high (\$0.06-\$0.10/ cm^2). Thus, for a 200-mm CMP rotary tool (which requires a 300-mm diameter pad) the initial cost for the pad is about \$50. For a 300-mm CMP tool, the pad must have a diameter of 510-550-mm, and the cost of the pad is about \$125. To achieve a CoO for the pad of less than \$0.05 per wafer, the




Fig. 8-55 Polishing pad cross-section, showing grooves in pad surface.

smaller pad (i.e., for 200-mm wafers) must polish 800 wafers, and the pad for the 300-mm CMP tool must polish 2500 wafers before being discarded.⁴⁵

8.6.7 Pad Conditioners

One crucial aspect of CMP is the state of the surface of the pad. That is, surface roughness and porosity determine: 1) slurry transport to the wafer surface; 2) material transport away from the wafer surface; and 3) the contact area of the pad to the wafer surface. As a result, unless the surface of a pad is continuously maintained in the optimal state of roughness and porosity, removal-rates can vary with time. In fact, a decrease in removal-rate has been most commonly observed (approximately logarithmic with time).⁴⁶ For example, starting with a new pad, the removal-rate can drop from 210-nm/min to 75-nm/min after only 50 wafers have been polished. This effect occurs because during the polishing process the surface of the pad rapidly undergoes plastic deformation so that the surface becomes smoother and the pores become filled with pad material (Fig. 8-56). This phenomenon has been termed *glazing*. Such glazing is undesirable, since as the pores of the pad become closed, slurry delivery is decreased to the wafer surface, and reduced polishing rates result. In addition, large waste-particles can become embedded in the pad and cause scratches.




Fig. 8-56 Surface of a glazed pad (Rodel's Suba IV[®] pad) after polishing.




Fig. 8-57 Schematic drawing of pad conditioning. Reprinted with permission of Solid State Technology. Published by PennWell.

A consistent (and rapid) removal rate is necessary for production-worthy CMP processes. This can be achieved by a process that refreshes the surface of the pad, and this technique is called *pad conditioning*. Figures 8-57 and 8-58 show a typical conditioning process in which the pad-conditioner (a disk whose surface is embedded with a diamond grit) sweeps back-and-forth across the rotating pad to restore the pad to its required surface planarity and surface roughness. The pad-conditioning process also opens the pores of the pad by forming micro-scratches on the pad surface. An example of what the pad-conditioning process accomplishes is shown in Fig. 8-59, which contains SEM micrographs of the




Fig. 8-58 Diamond embedded ring pad conditioner.