




US 20120099822A1

(19) **United States**(12) **Patent Application Publication**
Kuffel et al.(10) **Pub. No.: US 2012/0099822 A1**(43) **Pub. Date: Apr. 26, 2012**(54) **OPTICAL COMMUNICATION CONNECTOR**(52) **U.S. Cl. 385/78**(57) **ABSTRACT**(75) Inventors: **Gregory L. Kuffel**, Plainfield, IL (US); **Joel D. Kwasny**, Romeoville, IL (US)(73) Assignee: **PANDUIT CORP.**, Tinley Park, IL (US)(21) Appl. No.: **12/909,974**(22) Filed: **Oct. 22, 2010****Publication Classification**(51) **Int. Cl.**
G02B 6/36 (2006.01)

In accordance with the following description, an optical communication connector includes a ferrule having retractable alignment pins that are actuable between an extended position and a retracted position. For example, the connector may include an inner housing assembly having optical fibers and an outer housing positioned over the inner housing assembly. The outer housing is shaped to be removable from the inner housing assembly, which has a movable pin clamp mechanically coupled to alignment pins for aligning the connector with another connector. The pin clamp may be slid from a first position (corresponding to a male gender) to a second position (corresponding to a female gender). Separately or in combination with changing gender, the polarity of a communication connector may be changed due to its inclusion of an asymmetric polarity-changing feature that is actuable by an installer to change a polarity of the communication connector. Such a feature may be actuated by being moved from a first position to a second position relative to the communication connector.






FIG.1
(prior art)




FIG.2




FIG.3




FIG.4




FIG.5




FIG. 6




FIG. 7




FIG.8




FIG.9




FIG.10




FIG. 11




FIG. 12




FIG.13




FIG.14




FIG. 15




FIG. 16




FIG.17




FIG.18




FIG.19




FIG.20




FIG.21




FIG.22

OPTICAL COMMUNICATION CONNECTOR

FIELD

[0001] The present invention relates generally to communication connectors, and more particularly, to an optical communication connector having a configurable polarity and/or gender.

BACKGROUND

[0002] As optical cabling technology continues to improve, bringing higher transmission speeds and better reliability, existing data centers typically must decide whether to upgrade their infrastructures to embrace the newer technology. This involves a cost-benefit analysis to determine whether the benefits to be derived from the upgrade outweigh the costs of the upgrade.

[0003] One cost to consider is the extent of the upgrade. An extensive upgrade, such as replacing an entire infrastructure, is likely to be more costly (in equipment costs and installation man-hours) than a less-extensive upgrade, such as swapping out a limited number of components with upgraded components that are able to interface with the existing infrastructure. A data center will typically attempt to reuse existing cabling infrastructure when possible, in order to lessen costs.

[0004] Another cost relates to the complexity of each component upgrade. When an upgrade is undertaken, an installer must install the upgraded component so that it interfaces properly with any installed network equipment and intermediate links. This may include matching transmission-speed capabilities, polarity, and/or gender of cables and/or connectors. An increase in the complexity of network equipment, cabling, and connectors may be accompanied by a corresponding increase in the complexity of the installation.

[0005] Yet another cost relates to the number of unique parts that must be ordered and installed. This cost is closely related to complexity. An upgrade that requires many unique parts (such as cables and connectors) results in a more complicated Bill of Material (BOM). In turn, an installer must transport and install each of these unique parts. A larger number of unique parts is likely to increase the risk of a part being installed at an incorrect location (e.g. a part installed with a reversed polarity).

[0006] Thus, an optical communication connector that assists in reducing the cost of an upgrade and/or that assists in simplifying the upgrade would be desirable.

SUMMARY

[0007] In accordance with the following description, an optical communication connector includes a ferrule having retractable alignment pins that are actuable between an extended position and a retracted position. For example, the connector may include an inner housing assembly having optical fibers and an outer housing positioned over the inner housing assembly. The outer housing is shaped to be removable from the inner housing assembly, which has a movable pin clamp mechanically coupled to alignment pins for aligning the connector with another connector. The pin clamp may be slid from a first position (corresponding to a male gender) to a second position (corresponding to a female gender).

[0008] The inner housing assembly preferably has a stop surface that defines the first position corresponding to the male gender and the second position corresponding to a female gender. Furthermore, the movable pin clamp prefer-

ably has a deflectable tab that may be slid relative to the stop surface from the first position to the second position to change the gender of the connector.

[0009] In one embodiment, the outer housing is structured (e.g. with a slot through which the pin clamp can be accessed) so that the pin clamp can be actuated without removing the outer housing.

[0010] Another feature described herein relates to changing the polarity of a connector. The outer housing preferably has a polarity key disposed thereon. When the outer housing is rotated 180-degrees along an axis orthogonal to a front face of the connector's ferrule, the polarity key is correspondingly rotated from a first position to a second position, where the first position corresponds to a first polarity and the second position corresponds to a second polarity. The inner housing assembly preferably has at least two recessed features that are each shaped to accept the polarity key when the outer housing is slid over the inner housing assembly.

[0011] Generally, the polarity of a communication connector may be changed due to its inclusion of an asymmetric polarity-changing feature that is actuable by an installer to change a polarity of the communication connector. Such a feature may be actuated by being moved from a first position to a second position relative to the communication connector.

BRIEF DESCRIPTION OF THE DRAWINGS

[0012] The above-mentioned and other features and advantages, and the manner of attaining them, will become more apparent and the technology will be better understood by reference to the following description of one or more embodiments taken in conjunction with the accompanying drawings, wherein:

[0013] FIG. 1 illustrates a simplified block diagram showing an example of a typical cross connect system;

[0014] FIG. 2 illustrates a simplified block diagram showing an example of a typical upgraded version of the same cross connect system;

[0015] FIG. 3 is an upper left perspective view of an MPO connector (an example of an optical connector) in the Male orientation;

[0016] FIG. 4 is an upper left perspective view of an MPO connector (an example of an optical connector) in the Female orientation;

[0017] FIG. 5 is an upper left perspective view of a portion of a Male-oriented MPO connector with the outer housing removed;

[0018] FIG. 6 is a cross-sectional side view of the portion of the MPO connector shown in FIG. 5, showing the retractable pin clamp in the first (Male) position;

[0019] FIG. 7 is a cross-sectional side view of the portion of the MPO connector shown in FIG. 5, showing the retractable pin clamp in the second (Female) position;

[0020] FIG. 8 is a flow diagram illustrating a method for changing a gender of an optical connector from male to female, according to an embodiment;

[0021] FIG. 9 is a flow diagram illustrating a method for changing a gender of an optical connector from female to male, according to an embodiment;

[0022] FIG. 10 is a simplified schematic diagram illustrating a transceiver mapping of two connectors communicating over eight of twelve provided fiber channels;

[0023] FIG. 11 is a simplified plan view of a Type-A patch cord/connector cable;

[0024] FIG. 12 is a simplified plan view of a Type-B patch cord/connector cable;

[0025] FIG. 13 is an upper left perspective view of a connector in accordance with a preferred embodiment;

[0026] FIG. 14 is an upper left perspective view of a partially disassembled connector in accordance with a preferred embodiment;

[0027] FIG. 15 is an upper left perspective view of a connector in accordance with a preferred embodiment;

[0028] FIG. 16 is an upper left perspective front view of an inner housing assembly and an outer housing of a partially disassembled connector in accordance with a preferred embodiment;

[0029] FIG. 17 is a rear perspective view illustrating a back side of the outer housing (i.e. opposite the polarity key) according to a preferred embodiment;

[0030] FIG. 18 is a flow diagram illustrating a method for changing a polarity of an optical connector, according to an embodiment;

[0031] FIG. 19 is a flow diagram illustrating a method for changing a gender and a polarity of an optical connector, according to an embodiment;

[0032] FIG. 20 is a perspective view of an alternative embodiment of a connector according to the present invention, showing an outer housing separated from an inner housing assembly;

[0033] FIG. 21 is a side view of the embodiment of FIG. 20, showing an outer housing separated from an inner housing assembly; and

[0034] FIG. 22 is a perspective view of the embodiment of FIG. 20, with the outer housing latched to the inner housing assembly.

[0035] Corresponding reference characters indicate corresponding parts throughout the several views. The exemplification set out herein illustrates one or more preferred embodiments of the invention, and such exemplification is not to be construed as limiting the scope of the invention in any manner.

DETAILED DESCRIPTION

Example Implementation Context

[0036] To provide context for much of the discussion herein, FIGS. 1 and 2 set forth an example, based on Method A in the “Optical Fiber Cabling Components Standard,” Edition C, Telecommunications Industries Association, Jun. 1, 2008 (TIA-568-C.3), of a typical cross connect system 100 (FIG. 1) and a typical upgraded version of the same cross connect system 200 (FIG. 2).

[0037] As can be seen with reference to FIG. 1, first network equipment 102 communicates with second network equipment 104 through an optical communication path comprising a series of ports, cables, and cassettes. Starting from left to right in FIG. 1, the first network equipment 102 has an LC transceiver port 106 that connects through a first LC equipment cord 114 to a first cassette 116. A first MPO (Multi-fiber Push-On) patchcord/trunk cable 110 links the first cassette 116 to a second cassette 118. An LC cross connect cord 120 connects the second cassette 118 to a third cassette 122. A second MPO patchcord/trunk cable 112 links the third cassette 122 to a fourth cassette 124. A second LC equipment cord 126 connects the fourth cassette 124 to the second network equipment 104 through its LC transceiver port 108.

[0038] The LC transceiver ports 106 and 108, the LC equipment cords 114 and 126, the LC cross connect cord 120, and cassettes 116, 118, 122, and 124 interface with one another via LC connectors. LC connectors are small form-factor fiber connectors that use a 1.25 mm diameter ceramic ferrule in a standard RJ-45 telephone plug housing (in either a simplex or duplex configuration). In the example shown, the cassettes 116, 118, 122, and 124, which serve as junction points, include LC ports on a front side (for interfacing with the LC equipment cords 114 and 126 and cross connect cord 120) and MPO ports on a rear side (for interfacing with the MPO patchcord/trunk cables 110 and 112). The illustrated patchcord/trunk cables 110 and 112 are Female MPO—Female MPO of Type A, which interface with Male MPO ports on the rear side of the cassettes 116, 118, 122, and 124. In both FIGS. 1 and 2, “F” stands for “Female MPO,” while “M” stands for “Male MPO” (with alignment pins).

[0039] For purposes of discussion, we will assume that the MPO patchcord/trunk cables 110 and 112 are permanent links to be reused in a proposed upgrade to the example system 100. The LC components are to be upgraded to MPO components, which include/support communications over multiple fibers (e.g. up to 24 strands). Such an upgrade may be to implement 40G data rates, for example. Thus, as shown in FIG. 2, the MPO patchcord/trunk cables 110 and 112 are still present in the upgraded version 200 of the example. The choice of components and reused parts for the example of FIGS. 1 and 2 is completely arbitrary and other configurations and upgrades may utilize the teachings described herein.

[0040] As can be seen with reference to FIG. 2, first upgraded network equipment 202 includes a parallel optics transceiver with an MPO port 206 to interface via an MPO patchcord/trunk cable 214 to a first FAP (Fiber Adapter Panel) 216. The first FAP 216 is linked to a second FAP 218 through the first reused MPO patchcord/trunk cable 110 to a second FAP 218. The second FAP 218 is linked through a second MPO patchcord/trunk cable 220 to a third FAP 222. The third FAP 222 is linked to a fourth FAP 224 through the second reused MPO patchcord/trunk cable 112. The fourth FAP 224 is linked through a third MPO patchcord/trunk cable 226 to a parallel optics transceiver with an MPO port 208 on second upgraded network equipment 204.

[0041] Comparing FIGS. 1 and 2, as a result of the upgrade from the example 100 to the upgraded version 200, first and second network equipment 102 and 104 has been upgraded to first and second upgraded network equipment 202 and 204 having respective parallel optics MPO transceiver ports. The first LC equipment cord 114 has been upgraded to a Female MPO—Male MPO patchcord/trunk cable—Type A 214. The second LC cross connect cord 120 has been upgraded to a Male MPO—Male MPO patchcord/trunk cable—Type A 220. The second LC equipment cord 126 has been upgraded to a Female MPO—Male MPO patchcord/trunk cable—Type B 226. The cassettes 116, 118, 122, and 124 have been upgraded to FAPs 216, 218, 222, and 224 with respective MPO adapters. As previously mentioned, the MPO patchcord/trunk cables 110 and 112 are permanent links that were reused in the example upgrade.

[0042] Thus, a BOM (Bill of Material) for the above upgrade would list three distinct MPO-MPO cable assemblies (not including the existing, reused cables 110 and 112):

[0043] Cable 214: Female MPO—Male MPO patchcord/trunk cable—Type A

[0044] Cable 220: Male MPO—Male MPO patchcord/trunk cable—Type A

[0045] Cable 226: Female MPO—Male MPO patchcord/trunk cable—Type B.

Overview

[0046] In accordance with one or more embodiments described herein, an installer can change a gender of an optical communication connector, such as an MPO patchcord/trunk cable connector, from male to female (or visa versa) by removing an outer housing and retracting (or extending) alignment pins corresponding to the gender of the cable. As a result, few unique component types are required. This will simplify the BOM, since there are fewer part number variations, due to the same cables (possibly with different length) being used. In addition, installation is made easier, since parts are more generic and can be adapted as needed for particular parts of the installation. The installer can conveniently change the gender of the connector in the field.

[0047] In accordance with one or more embodiments described herein, an installer can change a polarity of an optical communication connector, such as an MPO patchcord/trunk cable connector, from a first polarity to a second polarity by reversing a configuration of a polarity key. Thus, a single component can be used for either polarity, which reduces the number of unique component types required for a typical installation, simplifies the BOM, and makes installation easier.

[0048] The above-summarized retractable alignment pins and reversible polarity key may be implemented separately or in combination.

Retractable Alignment Pins

[0049] As can be seen with reference to FIG. 3, an MPO connector 300 (an example of an optical connector) in the male orientation includes an inner housing assembly 400, an outer housing 500, a ferrule 600, and alignment pins 602 extending outward from the ferrule 600, which contains optical fibers for communication. Similarly, FIG. 4 shows the MPO connector 300 in the female orientation, with the alignment pins 602 retracted into alignment pin cavities 604. The same MPO connector 300 can thus be used in both the male and female orientation by respectively extending or retracting the alignment pins 602.

[0050] FIG. 5 shows a portion of the MPO connector 300 with the outer housing 500 removed to expose a retractable pin clamp 402. The retractable pin clamp 402 is mechanically coupled (preferably fixed) to the alignment pins 602 through the ferrule 600. The retractable pin clamp 402 preferably includes one or more tabs 404, each with a hole 406 for engagement by a tool. One or more spacers 407 situated in the inner housing assembly 400 includes one or more corresponding stop surfaces 408, adjacent to the one or more tabs 404, to define a first position (a male position) and a second position (female position) for the retractable pin clamp 402. FIGS. 6 and 7 are cross-sectional side views of the portion of the MPO connector 500 shown in FIG. 5, showing the retractable pin clamp 402 in the first and second positions, respectively, according to a preferred embodiment.

[0051] The process for changing the gender of the connector will now be described with reference to FIGS. 5-7, which show a preferred embodiment in which the retractable pin clamp 402 has two tabs 404, each having a hole 406 and the

spacer 407 has two stop surfaces 408. After removing the outer housing 500 from the MPO connector 300, an installer may slide the retractable pin clamp 402 along a z-axis 410 that is orthogonal to a front face 412 of the ferrule 600 to cause the alignment pins 602 to move between the male configuration and the female configuration. To do so, the installer deflects the tabs 404 inward (toward each other) by engaging the two holes 406 with a tool (such as a pliers-like tool having two pegs that mate with the two holes 406) and sliding the retractable pin clamp 402 (and coupled alignment pins 602) along the z-axis 410 between the first position (male position) and the second position (female position). The installer releases the tool to lock the retractable pin clamp 402 into position along the z-axis 410 on the other side of the stop surfaces 408. The installer may then reinstall the outer housing 500, so that the connector is ready for mating to an opposite gender connector.

[0052] In other embodiments of the invention, tools are not necessary to effect the gender change. For example, referring to FIG. 5, the hole 406 can be replaced with a post for fingertip actuation.

[0053] The first position (male position) and second position (female position) are defined by the dimensions of the stop surfaces 408, and in particular, by the z-axis length between the stop surfaces 408. Preferably, this length should be greater than approximately twice the extended length of one of the alignment pins 602 relative to the front face 412 of the ferrule 600. This ensures that two oppositely-gendered connectors 300 will be able to interface completely, so that the extended alignment pins 602 of the male connector 300 are fully engaged within the corresponding cavities 604 housing the retracted alignment pins 602 of the female connector 300. In addition to setting the distance through which the alignment pins 602 are extended and retracted with the stop surfaces 408, the spacer 407 also helps transfer a load from a spring 606 to the ferrule 600 to isolate the retractable pin clamp 402.

[0054] While the above description pertains to a preferred implementation of a connector having a changeable gender, other implementations are also possible. For example, one example implementation utilizes only a single tab 404 that is deflected to move below a single stop surface 408. Another example implementation utilizes more than two tabs 404 and/or more than two stop surfaces 408. In yet another example implementation, rather than being fixed to the alignment pins 602, the retractable pin clamp 402 is coupled to the alignment pins 602 by some other type of mechanical linkage that causes the alignment pins 602 to extend or retract by a larger displacement than the displacement of the actuated retractable pin clamp 402. In yet another alternative implementation, the stop surfaces 408 are not part of the inner housing assembly 400. Many other alternatives are possible for implementing the connector as claimed herein.

[0055] FIGS. 8 and 9 are flow diagrams illustrating methods 1800 and 1900 for changing a gender of an optical connector, such as the connector 300 described above, from male to female and from female to male, respectively.

[0056] In the method 1800, an installer removes the outer housing 500 from the connector 300, as shown in block 1802. The installer deflects inward one or more tabs 404 on the retractable pin clamp 402, as shown in block 1804, and slides the retractable pin clamp 402 from a male position to a female position, causing the alignment pins 602 to retract into the ferrule 600, as shown in block 1806. The installer releases the

tabs, as shown in block **1808**, and replaces the outer housing **500**, as shown in block **1810**. The method **1900** differs from the method **1800** only in block **1906**, in which the installer slides the retractable pin clamp **402** from a female position to a male position, causing the alignment pins **602** to extend out of the ferrule **600**. Blocks **1902**, **1904**, **1908**, and **1910** in the method **1900** correspond respectively to blocks **1802**, **1804**, **1808**, and **1810** in the method **1800**. In methods according to embodiments of the present invention, the connector assembly remains intact, and the fibers within the connector are not exposed to damage or handling during reconfiguration.

Reversible Polarity Key

[0057] In addition to gender, another parameter to be considered by an installer during an upgrade is the polarity of a connector. The polarity may be considered separately or in combination with the gender, depending on the specific type (e.g. mechanical configuration) of optical connector.

[0058] In order to utilize a parallel optics transceiver with an MPO port, there must be at least one Type-B MPO-MPO patchcord in the link, assuming connectivity Method A is utilized per the "Optical Fiber Cabling Components Standard," Edition C, Telecommunications Industries Association, Jun. 1, 2008 (TIA-568-C.3), which is incorporated by reference herein in its entirety. FIGS. **10-12** are provided for clarification. FIG. **10** is a simplified schematic diagram illustrating a transceiver mapping of two connectors communicating over eight of twelve provided fiber channels. FIGS. **11** and **12** are simplified plan views of respective Type-A and Type-B patch cords/connector cables. As can be seen with reference to FIGS. **10-12**, including at least one Type-B MPO-MPO patchcord in the link effectively routes channel **1** to channel **12**, channel **2** to channel **11**, channel **3** to channel **10**, and channel **4** to channel **9**, which effectively routes transmit (Tx) to receive (Rx). Fiber numbers **9** through **12** of transceiver **700a** transmit (Tx) one or more communication signals to fiber numbers **1** through **4** of transceiver **700b**, which receive (Rx) the corresponding signal(s) across these four fibers. Fiber numbers **1** through **4** of transceiver **700a** receive (Rx) signal(s) from fiber numbers **9** through **12** of transceiver **700b**, which transmit (Tx) the corresponding signal(s) across these four fibers. The fiber scheme shown and described with reference to FIGS. **10-12** is compatible with the "Transceiver MPO Connector" transmit/receive configuration established by the POP4 MSA "Four Channel Pluggable Optical Transceiver Multi-Source Agreement" industry technical specification, which is incorporated by reference herein in its entirety.

[0059] The polarity keys **800** shown in FIGS. **11** and **12** will be discussed below, in conjunction with FIGS. **13-17**. In essence, the polarity keys **800** provide a mechanical means for identifying the polarity and for ensuring proper interfacing between adjoining connectors.

[0060] Changing the polarity of one connector in a patchcord effectively changes it from Type-A to Type-B, or vice versa. As will be described in detail below, an installer can change the polarity of an optical communication connector, such as an MPO patchcord/trunk cable connector, from a first polarity to a second polarity by reversing a configuration of a polarity key. Thus, a single component can be used for either polarity, which reduces the number of unique component types required for a typical installation, simplifies the BOM, and makes installation easier. For an installation involving a plurality of patchcords, only one type of patchcord needs to

be ordered, and during installation, it does not matter where each cable end is located, since the polarity can be changed as needed. Further, the connector interior (including the fiber and ferrule), is not exposed to damage during the polarity changing operation.

[0061] FIGS. **13-17** are perspective views illustrating a connector **300** and associated components, in both assembled and partially disassembled configurations. In these figures, like reference numerals refer to like components.

[0062] A polarity key **800** is integrated into the outer housing **500**. For example, the outer housing **500** may have the polarity key **800** integrally formed therein. Alternatively, the polarity key **800** may be a separate piece that is attached to the outer housing **500** by an appropriate fastener or adhesive.

[0063] The polarity key **800** includes, at its base, a polarity key tab **802**. Formed opposite the polarity key tab **802** and integrated into (integrally formed in or separately fastened to) the outer housing **500** is a blank tab **804**. The polarity key tab **802** and the blank tab **804** extend outward, along the z-axis **410**. Unlike the polarity key tab **802**, the blank tab **804** does not include a polarity key, and instead serves as a filler, thus, effectively being an absence of the polarity key **802**, as will be described below.

[0064] The inner housing assembly **400** includes two symmetric recessed features **806**, one on either side of where the ferrule **600** is located in the inner housing assembly **400**. The recessed features **806** are shaped and configured to accept the polarity key tab **802** (and associated polarity key **800**) and the blank tab **804**. According to a preferred embodiment, the polarity of the connector **300** is reversed by removing and rotating the outer housing **500** 180-degrees around the z-axis **410** of the ferrule **600** and reinstalling the outer housing **500** into the assembly **400**. The polarity key tab **802** and blank tab **804** fit into the recessed features **806** opposite of where they were before the 180-degree rotation. As a result, only the outer housing **500** is removed. The inner housing assembly **400** is not removed, which prevents disturbing the sensitive spring **606**, ferrule **600**, optical fiber, and spring push assembly **810**. Removing the inner housing assembly **400** would also expose the optical fibers, which is undesirable.

[0065] The preferably symmetric design of the inner housing assembly **400** allows the outer housing **500** to be flipped and reinstalled for polarity-changing. As illustrated in FIG. **16**, the recessed features **806** on the inner housing assembly **400** help the installer to locate and secure the geometries of the polarity key tab **802** and the blank tab **804** on the outer housing **500**. Sidewalls **812** on the polarity key **800** and/or polarity key tab **802** interface with corresponding polarity key sidewall retainers **814** to control movement of the polarity key tab **802** and blank key tab **804** in the x-axis direction **414**. Similar sidewalls are placed on the blank tab **804**. To control movement of the polarity key tab **802** in the y-axis direction **416**, the polarity key tab **802** and blank key tab preferably both include planar protrusions **816** that are overlapped by protrusion retainers **818** located on the inner housing assembly **400** as part of the recessed features **806**. The protrusion retainers **818** thus serve as guides along which the outer housing **500** may slide via its polarity key tab **802** and blank tab **804**, as illustrated in FIGS. **13-16**.

[0066] FIG. **17** is a rear perspective view illustrating a back side of the outer housing **500** (i.e. opposite the polarity key **800**) according to a preferred embodiment. The outer housing **500** includes two compression springs **820** located on compression spring alignment posts **824** in respective compres-

sion spring wells **822**. Small crush ribs **826** are located on the alignment posts **824**. During assembly, the compression springs **820** are pressed over the crush ribs **826** around the alignment posts **824** and are thus held in place by interference with the crush ribs **826**. Stop posts **828** on the exterior of the inner housing assembly **400** interface with the compression spring wells **822** when the outer housing **500** is assembled onto the inner housing assembly **400**. The stop posts **828** provide a surface for the compression springs **820** to act (compress) against, to force the outer housing forward (toward the ferrule endpiece). Ribs **831** of the outer housing engage with detents **833** of the inner housing assembly **400** to prevent the compression spring from separating the outer housing **500** from the inner housing assembly **400**.

[0067] FIG. **18** is a flow diagram illustrating a method **2800** for changing a polarity of an optical connector, such as the connector **300** described above. In the method **2800**, an installer removes the outer housing **500** from the connector **300**, as shown in block **2802**. The installer rotates the outer housing 180-degrees around the z-axis (orthogonal to the front face of the ferrule **600**), as shown in block **2804**, and replaces the outer housing **500**, as shown in block **2806**.

[0068] FIG. **19** is a flow diagram illustrating a method **2900** for changing a gender and a polarity of an optical connector, such as the connector **300** described above. In the method **2900**, an installer removes the outer housing **500** from the connector **300**, as shown in block **2902**. The installer deflects inward one or more tabs **404** on the retractable pin clamp **402**, as shown in block **2904**, and slides the retractable pin clamp **402** to appropriate gender position (male or female, as defined by location relative to the stop surface(s) **408**), causing the alignment pins **602** to retract into or extend out of the ferrule **600**, as appropriate, as shown in block **2906**. The installer releases the tabs **404**, as shown in block **2908**. The installer then rotates the outer housing **500** 180-degrees around the z-axis (orthogonal to the front face of the ferrule **600**), as shown in block **2910**, and replaces the outer housing **500**, as shown in block **2912**.

[0069] FIG. **20** is a perspective diagram of another embodiment of the present invention, in which the outer housing **2000** latches to an inner housing assembly **2001** using deflecting latch flaps **2002** provided on the outer housing **2000** and latch ramps **2004** provided on the inner housing assembly **2001**. FIG. **21** is a side view of this embodiment. The location of the polarity key **800** can be swapped between the top and bottom of the connector by flipping the outer housing before attaching the outer housing **2000** to the inner housing assembly **2001**. FIG. **22** is a perspective view of an assembled connector of this embodiment. In this embodiment, the outer housing **2000** can be unlatched by squeezing the outer housing from the sides. Clearance along the sides of the outer housing **2000** then allows the top and bottom portions of the outer housing to bow outwardly, allowing unlatching.

[0070] While this invention has been described as having a preferred design, the present invention can be further modified within the spirit and scope of this disclosure. This application is therefore intended to cover any variations, uses, or adaptations of the invention using its general principles. Further, this application is intended to cover such departures from the present disclosure as come within known or customary practice in the art to which this invention pertains and which fall within the limits of the appended claims.

1. An optical communication connector, comprising a ferrule having retractable alignment pins that are actuatable between an extended position and a retracted position.

2. The optical communication connector of claim 1,

wherein in the extended position, the alignment pins are extended a first displacement from a front face of the ferrule, thereby causing the connector to be in a male gender configuration, and

wherein in the retracted position, the alignment pins are retracted into alignment pin cavities in the ferrule by a distance greater than or equal to the first displacement, thereby causing the connector to be in a female gender configuration.

3. The optical communication connector of claim 1, wherein actuation of the alignment pins between the extended position and the retracted position is effected using a pin clamp that is mechanically coupled to the alignment pins.

4. The optical communication connector of claim 3, wherein the pin clamp is fixedly attached to the alignment pins.

5. The optical communication connector of claim 3, wherein the pin clamp is coupled to the alignment pins through a mechanical linkage that causes the alignment pins to move by a larger displacement than that of the pin clamp, when the pin clamp is displaced.

6. The optical communication connector of claim 3, wherein the pin clamp includes at least one feature that may be engaged by a tool to effect actuation of the alignment pins between the extended position and the retracted position.

7. The optical communication connector of claim 6, wherein the pin clamp includes at least one tab, and wherein the at least one feature comprises at least one hole located on the tab.

8. The optical communication connector of claim 3, wherein the pin clamp includes at least one tab comprising a post for manual engagement by a user.

9. The optical communication connector of claim 3, further comprising at least one spacer having at least one stop surface, wherein the pin clamp is slidable between a first position and second position corresponding respectively to the extended position and the retracted position, and wherein the first and second positions are defined by the at least one stop surface on the at least one spacer.

10. The optical communication connector of claim 3, further comprising at least one spacer having a stop surface, wherein the pin clamp comprises a tab that, upon being deflected, allows the pin clamp to move below the stop surface.

11. The optical communication connector of claim 3, wherein the pin clamp comprises two pin clamps, wherein each pin clamp comprises at least one tab that can be deflected to allow the pin clamp to move below a stop surface on a spacer located on the connector.

12. The optical communication connector of claim 1, further comprising a polarity key having a configuration that can be altered to change a polarity of the connector.

13. The optical communication connector of claim 12, wherein the configuration of the polarity key is altered by rotating the polarity key in relation to the connector.

14. The optical communication connector of claim 12, wherein the polarity key is located on an outer housing of the connector, and wherein the outer housing can be rotated around an axial length of the connector to effect the change in polarity.

15. The optical communication connector of claim 14, wherein the polarity key includes a polarity key tab and a blank tab 180-degrees opposite the polarity key tab on the outer housing, wherein the polarity key tab and the blank tab mechanically interface with features on the connector, and wherein rotation of the housing relative to the axial length effects the change in polarity.

16. The optical communication connector of claim 1, wherein the connector is an MPO connector.

17. An optical communication connector, comprising:
an inner housing assembly having optical fibers disposed therein; and

an outer housing disposed over the inner housing assembly, the outer housing shaped to be removable from the inner housing assembly;

wherein the inner housing assembly comprises a movable pin clamp mechanically coupled to alignment pins for aligning the connector with another connector, wherein the pin clamp may be slid from a first position to a second position, and wherein the first position corresponds to a male gender and the second position corresponds to a female gender.

18. The optical communication connector of claim 17, further comprising a ferrule through which the optical fibers and alignment pins pass,

wherein in the first position, the alignment pins are extended a first displacement along a z-axis orthogonal to a front face of the ferrule, and

wherein in the second position, the alignment pins are retracted into alignment pin cavities in the ferrule by a distance greater than or equal to the first displacement along the z-axis orthogonal to the front face of the ferrule.

19. The optical communication connector of claim 17, wherein the pin clamp is fixedly attached to the alignment pins.

20. The optical communication connector of claim 17, wherein the pin clamp is coupled to the alignment pins through a mechanical linkage that causes the alignment pins to move by a larger displacement than that of the pin clamp, when the pin clamp is displaced.

21. The optical communication connector of claim 17, wherein the pin clamp includes at least one feature that may be engaged by a tool to effect actuation of the alignment pins between the first position and the second position.

22. The optical communication connector of claim 17, wherein the inner housing assembly comprises at least two stop surfaces to limit movement of the pin clamp to a length between the first and second positions.

23. The optical communication connector of claim 22, wherein the at least two stop surfaces are located on one or more spacers on the inner housing assembly.

24. The optical communication connector of claim 22, wherein the pin clamp comprises a tab that, upon being deflected, allows the pin clamp to move past one of the at least two stop surfaces.

25. The optical communication connector of claim 17, wherein the inner housing assembly comprises a plurality of spacers having stop surfaces to constrain sliding movement of the pin clamp to a length bound by the first position and the second position.

26. The optical communication connector of claim 17, wherein the pin clamp is designed to be slid only when the outer housing is removed.

27. The optical communication connector of claim 17, wherein the pin clamp comprises two pin clamps located on opposite sides of the inner housing assembly, wherein each pin clamp comprises at least one tab that can be deflected to allow the pin clamp to move below a stop surface on a spacer located on the inner housing assembly.

28. The optical communication connector of claim 17, wherein the outer housing comprises a polarity key configured so that a polarity of the connector is defined based on how the outer housing is installed.

29. The optical communication connector of claim 18, wherein the outer housing comprises a polarity key tab and a blank tab located opposite the polarity key tab, wherein the polarity key tab has a polarity key formed thereon to define a polarity of the connector, wherein the polarity key tab and the blank tab are shaped to fit in respective first and second recessed features located on opposite sides of the inner housing assembly, and wherein the polarity of the connector can be changed by rotating the outer housing around the z-axis so that the polarity key tab fits in the second recessed feature and the blank key tab fits in the first recessed feature.

30. The optical communication connector of claim 29, wherein the first and second recessed features include guides along which the polarity key tab and the blank tab of the outer housing may slide along the z-axis as the outer housing is installed onto the inner housing assembly.

31. The optical communication connector of claim 30, wherein the polarity key tab and the blank tab each have planar protrusions spanning outward from their centers, and wherein the recessed features of the inner housing assembly each have protrusion retainers.

32. The optical communication connector of claim 30, further comprising a latch mechanism to secure the outer housing to the inner housing assembly.

33. The optical communication connector of claim 17, wherein the connector is an MPO connector.

34. An optical communication connector, comprising:

an inner housing assembly that houses a plurality of optical fibers disposed in a ferrule, wherein the inner housing assembly has a stop surface that defines a first position corresponding to a male gender and a second position corresponding to a female gender; and

a movable pin clamp disposed in the inner housing assembly, wherein the pin clamp has a deflectable tab that may be slid relative to the stop surface from the first position to the second position to change the gender of the connector.

35. The optical communication connector of claim 34, further comprising an outer housing for installation over the inner housing assembly, wherein the outer housing covers the movable pin clamp.

36. The optical communication connector of claim 35, wherein the outer housing comprises a polarity key disposed on one of a plurality of outside edges of the outer housing to define a polarity of the connector, wherein the polarity is defined based on which of two installation modes the outer housing is installed, wherein the first installation mode differs from the second installation mode in how the outer housing is rotated relative to the inner housing assembly during installation of the outer housing onto the inner housing assembly.

37. The optical communication connector of claim 36, wherein in the first installation mode, the outer housing is rotated 180 degrees opposite from in the second installation

mode, thereby causing the polarity key to correspondingly be rotated 180 degrees relative to the inner housing assembly.

38. An optical communication connector, comprising:
an inner housing assembly having a ferrule with optical fibers disposed therein; and
an outer housing shaped to slide over the inner housing assembly;
wherein the outer housing has a polarity key disposed thereon, and wherein the outer housing may be rotated 180-degrees along an axis orthogonal to a front face of the ferrule to cause the polarity key to be rotated from a first position to a second position, wherein the first position corresponds to a first polarity and the second position corresponds to a second polarity, and wherein the inner housing assembly has at least two recessed features, each being shaped to accept the polarity key when the outer housing is slid over the inner housing assembly.

39. A communication connector, comprising a polarity-changing feature actuable by an installer to change a polarity of the communication connector, the polarity-changing feature being an asymmetric feature that may be actuated by being moved from a first position to a second position relative to the communication connector.

40. A fiber adapter panel having a plurality of optical communication connectors, at least one of which comprises:
an inner housing assembly having optical fibers disposed therein; and

an outer housing disposed over the inner housing assembly, the outer housing shaped to be removable from the inner housing assembly;

wherein the inner housing assembly comprises a movable pin clamp mechanically coupled to alignment pins for aligning the connector with another connector, wherein the pin clamp may be slid from a first position to a second position, and wherein the first position corresponds to a male gender and the second position corresponds to a female gender.

41. An optical communication cable comprising at least one end terminated at an optical communication connector, the optical communication connector comprising:

an inner housing assembly having optical fibers disposed therein; and

an outer housing disposed over the inner housing assembly, the outer housing shaped to be removable from the inner housing assembly;

wherein the inner housing assembly comprises a movable pin clamp mechanically coupled to alignment pins for aligning the connector with another connector, wherein the pin clamp may be slid from a first position to a second position, and wherein the first position corresponds to a male gender and the second position corresponds to a female gender.

* * * * *