US007936392B2

(12) **United States Patent**
Ng et al.

(10) **Patent No.: US 7,936,392 B2**
(45) **Date of Patent: May 3, 2011**

(54) **IMAGING ARRANGEMENTS AND METHODS THEREFOR**

(75) Inventors: **Yi-Ren Ng**, Mountain View, CA (US); **Patrick M. Hanrahan**, Portola Valley, CA (US); **Marc S. Levoy**, Stanford, CA (US); **Mark A. Horowitz**, Menlo Park, CA (US)

(73) Assignee: **The Board of Trustees of the Leland Stanford Junior University**, Palo Alto, CA (US)

(*) Notice: Subject to any disclaimer, the term of this patent is extended or adjusted under 35 U.S.C. 154(b) by 670 days.

(21) Appl. No.: **11/576,438**

(22) PCT Filed: **Sep. 30, 2005**

(86) PCT No.: **PCT/US2005/035189**

§ 371 (c)(1),
(2), (4) Date: **Jun. 6, 2007**

(87) PCT Pub. No.: **WO2006/039486**

PCT Pub. Date: **Apr. 13, 2006**

(65) **Prior Publication Data**

US 2007/0252074 A1 Nov. 1, 2007

Related U.S. Application Data

(60) Provisional application No. 60/647,492, filed on Jan. 27, 2005, provisional application No. 60/615,179, filed on Oct. 1, 2004.

(51) **Int. Cl.**
G03B 13/00 (2006.01)
H04N 5/232 (2006.01)

(52) **U.S. Cl.** **348/349**; 348/350

(58) **Field of Classification Search** 348/345–356
See application file for complete search history.

(56) **References Cited**

U.S. PATENT DOCUMENTS

725,567	A	4/1903	Ives
4,383,170	A	5/1983	Takagi et al.
4,661,986	A	4/1987	Adelson
4,694,185	A	9/1987	Weiss
5,076,687	A	12/1991	Adelson

(Continued)

FOREIGN PATENT DOCUMENTS

DE 19624421 A1 6/1996

(Continued)

OTHER PUBLICATIONS

Edward H. Adelson and John Y.A. Wang, "Single Lens Stereo with a Plenoptic Camera", Feb. 1992, IEEE, vol. 14, No. 2, pp. 99-106.*

(Continued)

Primary Examiner — Tuan Ho
Assistant Examiner — Anthony J Daniels
(74) *Attorney, Agent, or Firm* — Courtney IP Law

(57) **ABSTRACT**

Image data is processed to facilitate focusing and/or optical correction. According to an example embodiment of the present invention, an imaging arrangement collects light data corresponding to light passing through a particular focal plane. The light data is collected using an approach that facilitates the determination of the direction from which various portions of the light incident upon a portion of the focal plane emanate from. Using this directional information in connection with value of the light as detected by photosensors, an image represented by the light is selectively focused and/or corrected.

14 Claims, 35 Drawing Sheets



U.S. PATENT DOCUMENTS

5,282,045	A	1/1994	Mimura et al.	
5,610,390	A *	3/1997	Miyano	250/216
5,748,371	A	5/1998	Cathey, Jr. et al.	
5,757,423	A	5/1998	Tanaka et al.	
6,023,523	A	2/2000	Cohen et al.	
6,028,606	A	2/2000	Kolb et al.	
6,097,394	A	8/2000	Levoy et al.	
6,201,899	B1	3/2001	Bergen	
6,320,979	B1	11/2001	Melen	
6,483,535	B1	11/2002	Tamburrino et al.	
6,577,342	B1	6/2003	Webster	
6,842,297	B2	1/2005	Dowski, Jr. et al.	
7,034,866	B1 *	4/2006	Colmenarez et al.	348/211.12
2002/0159030	A1	10/2002	Frey et al.	
2003/0117511	A1	6/2003	Belz et al.	
2003/0156077	A1	8/2003	Balogh	
2005/0080602	A1	4/2005	Snyder et al.	

FOREIGN PATENT DOCUMENTS

WO	WO 00/22566		4/2000
WO	WO 03/052465	A2	6/2003
WO	WO 2006/039486	A3	4/2006

OTHER PUBLICATIONS

Paul Haeberli, "A Multifocus Method for Controlling Depth of Field", Oct. 1994, http://www.graficaobscura.com/depth/index.html.*

J. Jackson et al. "Selection of a Convolution Function for Fourier Inversion Using Gridding." *IEEE Transactions on Medical Imaging*, Sep. 1991. vol. 10, No. 3, pp. 473-478.

T. Naemura et al. "3-D Computer Graphics based on Integral Photography." *Optics Express*, Feb. 12, 2001. vol. 8, No. 2, pp. 255-262.

F. Okano et al. Three-dimensional video system based on integral photography. *Optical Engineering*, Jun. 1999. vol. 38, No. 6, pp. 1072-1077.

E. Adelson et al. "Single Lens Stereo with a Plenoptic Camera." *IEEE Translation on Pattern Analysis and Machine Intelligence*, Feb. 1992. vol. 14, No. 2, pp. 99-106.

M. Levoy et al. "Light Field Rendering." *SIGGRAPH 96 Proceeding*, 1996. pp. 31-42.

A. Isaksen et al. "Dynamically Reparameterized Light Fields." *SIGGRAPH 2000*, Computer Graphics Proceedings. 10 pgs.

A. Agarwala et al. "Interactive Digital Montage." *ACM SIGGRAPH 2004*, vol. 23, No. 3, pp. 292-300.

P. Haeberli. "A Multifocus Method for Controlling Depth of Field." *GRAPHICAObscura*, 1994, pp. 1-3.

Herbert E. Ives, "Optical properties of a Lippman lenticulated sheet," J. Opt. Soc. Am. 21, 171 (1931).

Vaish et al., "Using plane + parallax for calibrating dense camera arrays", in Proceedings CVPR, 2004, pp. 2-9.

Wilburn et al., "High Performance Imaging using Large Camera Arrays", ACM Transactions on Graphics (TOG), vol. 24, Issue 3 (Jul. 2005), Proceedings of ACM SIGGRAPH 2005, pp. 7.

Jin-Xiang Chai et al., "Plenoptic Sampling", ACM SIGGRAPH 2000, Annual Conference Series, 2000, pp. 307-318.

Dowski et al., "Wavefront coding: A modern method of achieving high performance and/or low cost imaging systems" SPIE Proc. vol. 3779 (1999).

Tanida et al., "Thin observation module by bound optics (TOMBO): concept and experimental verification" Applied Optics 40, 11 (Apr. 2001), pp. 1806-1813.

Lippmann, "Reversible Prints", Communication at the French Society of Physics, Journal of Physics, 7, 4, Mar. 1908, pp. 821-825.

Sokolov, "Autostereoscopy and Integral Photography by Professor Lippmann's Method", 1911, pp. 23-29.

Gortler et al., "The lumigraph" SIGGRAPH 96, pp. 43-54 (1996).

* cited by examiner


100
150
160
Preview Processor
Preview Image
Preview Arrangement
170
Preview Screen
190
Imaging Arrangement
180
Image Sensor
Photosensor Array 130
Microlens Array 120
122
Main Lens 110
s
d
Subject 105
107
106
140
Sensor data processing circuitry

FIG. 1


230
Viewfinder Display
235
Input Device
250
Communication Link
260
Computer
Low-resolution Image Data
Image Capture Request
220
Signal Processor
222
Low-resolution Image Processor
224
Compression Processor
226
Ray-direction Processor
Image Data
Raw Data
Raw Data
240
Data Storage
Sensor Data
210
Image Sensor Arrangement
212
Microlens/ photosensor chip
214
Integrated processing circuit

FIG. 2


310
Capture digital image data
320
Is preview image desired?
yes
330
Generate preview image
no
340
Process and compress raw data
350
Extract light ray data
360
Retrieve ray-mapping data
370
Implement ray-mapping data with extracted light ray data to synthesize a re-sorted image

FIG. 3


410
Receive preview request with raw sensor image data
420
Select center pixel from each microlens image in the raw sensor image data
430
Form high depth of field image with selected pixels
440
Downsample high depth-of-field image and generate preview image data
450
Send generated preview image data to viewfinder display
460
Display image with generated preview image data

FIG. 4


510
Receive raw image data from sensor array
520
Is coloring desired?
yes
530
Demosaic color filter array values to produce color at sensors
no
540
Is rectification and alignment desired?
yes
550
Rectify and align microlens images with photosensor array
no
560
Is interpolation desired?
yes
570
Interpolate pixel values to integral number of pixels associated with each microlens
no
580
Compress processed raw image data and present for synthesis processing

FIG. 5


610
Receive raw image data from photosensor array
620
Is refocusing desired?
yes
630
Refocus image data
no
640
Is image correction desired?
yes
650
Correct image data
no
660
Generate resultant image using processed image data

FIG. 6

FIG. 7


710
Select virtual focal plane for refocusing an image portion
720
Select pixel of a virtual image for the virtual focal plane
730
Is correction desired?
yes
740
For selected lens positions, calculate the value of a virtual light ray passing between the pixel and the lens position
no
750
Add the sum of light ray values for each lens position for the virtual focal plane to determine a total value for selected pixel
730
Is normalization desired?
yes
740
Divide by fraction of light rays summed for pixel that were within the bounds of the input light field
no
760
Additional pixels for refocusing?
yes
no
770
Combine pixel data to generate a refocused virtual image


810
Compute a set of images refocused at different focal depths in a particular scene
820
For each pixel in a final virtual image to be computed, determine a pixel from the set of images that has the highest local contrast
830
Assemble together the pixels having the highest local contrast into the final virtual image

FIG. 8


910
Select a pixel in a final virtual image to be computed
920
Estimate the depth of a nearest object for a light ray traced from the selected pixel into a scene through the center of the lens
930
Compute the selected pixel's value in an image refocused at the estimated depth
940
Additional pixels to process?
yes
no
950
Use the computed values for the selected pixels to create the final virtual image

FIG. 9


Microlens
Array 1020
Main Lens 1010
Photosensor
Array 1030
1022
1023

FIG. 10


Ray Sensor
1130
u
x
Main Lens 1110
Ray in camera 1120
v
y
Photosensor value in
microlens image 1140
Microlens image 1150 in
array of microlens images
Image 1170 read from
photosensor array
Closeup 1180 of image 1170

FIG. 11



FIG. 12



FIG. 13A



FIG. 13B



Closup

FIG. 14A

Closup

FIG. 14B

Closup

FIG. 14C


Cone of desired world rays 1530 computed from 1525
Ideal thin main lens 1520
Virtual film 1510
1501
Cone of desired camera rays 1525 to produce image value for 1501

FIG. 15


Ray sensor 1640
Cone of desired world rays 1630
Real main lens 1650
1651

FIG. 16

FIG. 17A

FIG. 17B

FIG. 17C



FIG. 18A



FIG. 18B



FIG. 18C



FIG. 19A



FIG. 19B



FIG. 19C



FIG. 19D



FIG. 19E



FIG. 19F


Input 4D Light Field 2010
4D Fourier transform
4D Fourier transform 2020 of light field
Extract 2D slices (one for each desired focal depth)
2D slices (2030) of 4D Fourier transform
Inverse 2D Fourier transform
Refocused photographs 2040

FIG. 20



FIG. 21A



FIG. 21B


2210
Receive input discrete 4D light field
2215
Is aliasing reduction desired?
yes
2220
Pad light field with obrder of zero values
no
2230
Modulate by reciprocal of the inverse 4D Fourier transform of 4D resampling filter
2225
Is rolloff correction desired?
340
yes
no
2250
Receive desired focal depth of refocused image
2240
Compute 4D Fourier transform
2260
Is aliasing reduction desired?
yes
2280
Extract 2D slice for desired depth using 4D resampling filter and oversampling
no
2270
Extract 2D slice for desired depth using 4D resampling filter
2283
Compute inverse 2D Fourier transform
2275
Compute inverse 2D Fourier transform
2286
Crop to central portion with non-oversampled size
2290
Finished refocusing?
no
yes
2295
Done

FIG. 22


Subject 2310
2301
Main lens 2330
Partial occluder 2320
Rays 2340 blocked by occluder and to be disregarded
Ray Sensor 2350

FIG. 23



FIG. 24A



FIG. 24B



FIG. 24C


Virtual aperture 2520
Rays 2540 to be combined to produce image value at 2550
Main lens 2510
3D point 2550 corresponding to output pixel value
Ray sensor 2570
Virtual lens plane 2530
Virtual film 2560

FIG. 25


Virtual aperture 2620
Virtual film 2660
Virtual lens plane 2630

FIG. 26



FIG. 27


2890
Imaging Arrangement
Main Lens 2810
Light ray
Sensor 2820
Subject 2805

FIG. 28


2910
Receive database containing, for each output image pixel, the set of ideal world rays to be summed to produce an output image pixel value
2920
Receive specifications of real main lens optics used to physically direct light rays to light ray sensor
2925
Choose output image pixel
2930
For a chosen output image pixel, computationally trace ideal world rays though main lens optics to light ray sensor to determine how much various ray sensor values contribute to that pixel's final value
2940
For each ray sensor value, add to a database how much it contributes as a weight associated with chosen output image pixel
2950
More output image pixels to process?
yes
no
2960
Return database of weights associated with each output image pixel and each ray sensor value

FIG. 29


3010
Receive database containing, for each output image pixel, the set of ray sensor values and associated weights
3020
Receive ray sensor values for one exposure of imaging system
3025
Choose output image pixel
3030
For each ray sensor value in set associated with chosen pixel, multiply each ray sensor value by weight in database, and add to sum
3040
Set output image pixel value as sum
3050
More output image pixels to process?
yes
no
3060
Return output image

FIG. 30



FIG. 31A



FIG. 31B



FIG. 31C



FIG. 31D


Virtual aperture function 3210
Output image 3200
Output pixel 3201
Output pixel 3251
Virtual aperture function 3250

FIG. 32


3310
Receive light ray sensor data
3320
User selects region of output image
3330
User selects image formation procedure
3340
User alters parameters for image procedure
3350
Produce visualization of current output image for user
3360
User done editing current image portion?
no
yes
3370
User done editing image?
no
yes
3380
Save output image

FIG. 33


3410
Choose output image pixel
3420
Refocus pixel at a plurality of focal depths, and, for each depth, measure the homogeneity of the rays that are combined to pixel value
3430
Retain pixel value with highest homogeneity of rays
3440
More pixels to process?
yes
no
Done

FIG. 34


3510
Receive light ray sensor data
3520
Extract set of sub-aperture images, where each sub-aperture image consists of a single pixel from each microlens image
3530
Optionally translate each sub-aperture image in the imaging plane and composite together to bring a desired focal plane into focus

FIG. 35

IMAGING ARRANGEMENTS AND METHODS THEREFOR

RELATED PATENT DOCUMENTS

This patent application is the national stage filing under 35 U.S.C. 371 of International Application No. PCT/US2005/035189 filed on Sep. 30, 2005, which claims benefit under 35 U.S.C. §119(e) of U.S. Provisional Application Ser. No. 60/615,179 filed on Oct. 1, 2004; and of U.S. Provisional Application Ser. No. 60/647,492 filed on Jan. 27, 2005.

FEDERALLY-SPONSORED RESEARCH AND DEVELOPMENT

This invention was made with Government support under contract 0085864 awarded by the National Science Foundation. The U.S. Government has certain rights in this invention.

FIELD OF THE INVENTION

The present invention relates generally to imaging applications, and more specifically to processing image data to focus and/or correct the image data.

BACKGROUND

Imaging applications such as those involving cameras, video cameras, microscopes, telescopes and more have generally been limited in the amount of light that is collected. That is, most imaging devices do not record most of the information about light distribution entering the device. For example, conventional cameras such as digital still cameras and video cameras do not record most of the information about the light distribution entering from the world. In these devices, collected light is often not amenable to manipulation for a variety of approaches, such as for focusing at different depths (distances from the imaging device), correcting for lens aberrations or manipulating an angle of view.

For still-imaging applications, typical imaging devices capturing a particular scene generally focus upon a subject or object in the scene, with other parts of the scene left out of focus. For video-imaging applications, similar problems prevail, with a collection of images used in video applications failing to capture scenes in focus.

Many imaging applications suffer from aberrations with the equipment (lenses) used to collect light. Such aberrations may include, for example, spherical aberration, chromatic aberration, distortion, curvature of the light field, oblique astigmatism and coma. Correction for aberrations has typically involved the use of corrective optics, when tend to add bulk, expense and weight to imaging devices. In some applications benefiting from small-scale optics, such as camera phones and security cameras, the physical limitations associated with the applications make it undesirable to include additional optics.

Difficulties associated with the above have presented challenges to imaging applications, including those involving the acquisition and altering of digital images.

SUMMARY

The present invention is directed to overcoming the above-mentioned challenges and others related to imaging devices and their implementations. The present invention is exemplified in a number of implementations and applications, some of which are summarized below.

According to an example embodiment of the present invention, a light is detected with directional information characterizing the detected light. The directional information is used with the detected light to generate a virtual image, corresponding to one or both of a refocused image and a corrected image.

According to another example embodiment of the present invention, two or more subjects at different focal depths in a scene are imaged, with portions of the scene corresponding to each subject focused at different focal planes. Light from the scene is focused upon a physical focal plane and detected, together with information characterizing the direction from which the light arrived at particular locations on the physical focal plane. For at least one subject that is located at a depth of field that is not focused upon the physical focal plane, a virtual focal plane that is different than the physical focal plane is determined. Using the detected light and directional characteristics thereof, portions of the light corresponding to a focused image of the at least one subject upon the virtual focal plane are collected and added to form a virtual focused image of the at least one subject.

According to another example embodiment of the present invention, a scene is digitally imaged. Light from the scene that is passed to different locations on a focal plane is detected, and the angle of incidence of the light detected at the different locations on the focal plane is detected. A depth of field of a portion of the scene from which the detected light came is detected and used together with the determined angle of incidence to digitally re-sort the detected light. Depending upon the application, the re-sorting includes refocusing and/or correcting for lens aberrations.

The above summary of the present invention is not intended to describe each illustrated embodiment or every implementation of the present invention. The figures and detailed description that follow more particularly exemplify these embodiments.

BRIEF DESCRIPTION OF THE DRAWINGS

The invention may be more completely understood in consideration of the detailed description of various embodiments of the invention that follows in connection with the accompanying drawings, in which:

FIG. **1** is a light ray capturing and processing arrangement, according to an example embodiment of the present invention;

FIG. **2** is an optical imaging device, according to another example embodiment of the present invention;

FIG. **3** is a process flow diagram for image processing, according to another example embodiment of the present invention;

FIG. **4** is a process flow diagram for generating a preview image, according to another example embodiment of the present invention;

FIG. **5** is a process flow diagram for processing and compressing image data, according to another example embodiment of the present invention;

FIG. **6** is a process flow diagram for image synthesis, according to another example embodiment of the present invention;

FIG. **7** is a process flow diagram for image refocusing, according to another example embodiment of the present invention;

FIG. **8** is a process flow diagram for extending the depth of field in an image, according to another example embodiment of the present invention;

FIG. **9** is a process flow diagram for another approach to extending the depth of field in an image, according to another example embodiment of the present invention;

FIG. **10** illustrates one example approach to separating light rays, according to another example embodiment of the present invention;

FIG. **11** illustrates an approach to the mapping of sensor pixel locations to rays in the L(u,v,s,t) space with respect to data collected, according to another example embodiment of the invention;

FIG. **12** illustrates several images refocused at different depths, according to another example embodiment of the present invention;

FIG. **13**A shows an imaging configuration in 2D, according to another example embodiment of the present invention;

FIG. **13**B shows a cone of rays from a 3D point summed for a pixel, according to another example embodiment of the present invention;

FIGS. **14**A-**14**C show an approach to computing images with different depths of field, according to another example embodiment of the present invention;

FIG. **15** illustrates an approach to the tracing of rays from a 3D point on a virtual film plane, according to another example embodiment of the present invention;

FIG. **16** shows an approach to finding the value of light, according to another example embodiment of the present invention;

FIG. **17**A shows an ideal 512×512 photograph, according to another example embodiment of the present invention;

FIG. **17**B shows an image that would be produced with an f/2 bi-convex spherical lens, according to another example embodiment of the present invention;

FIG. **17**C shows an image computed using an image correction approach, according to another example embodiment of the present invention;

FIGS. **18**A-**18**C illustrate the tracing of light rays common in color imaging systems, according to another example embodiment of the present invention;

FIGS. **19**A-**19**F illustrate approaches to implementing a mosaic array, according to another example embodiment of the present invention;

FIG. **20** is a process flow diagram of computational approaches to refocusing in a Fourier domain, according to another example embodiment of the present invention;

FIG. **21**A shows a triangle filter approach, according to another example embodiment of the present invention;

FIG. **21**B shows a Fourier transformation of the triangle filter approach; according to another example embodiment of the present invention;

FIG. **22** is process flow diagram of an approach to refocusing in a frequency domain, according to another example embodiment of the present invention;

FIG. **23** shows a set of rays which pass through a desired focal point, according to another example embodiment of the present invention;

FIGS. **24**A-B show differing views of a portion of a microlens array, according to another example embodiment of the present invention;

FIG. **24**C illustrates images that appear on a photosensor, according to another example embodiment of the present invention;

FIG. **25** illustrates an example embodiment of the present invention, in which a virtual image is computed as it would have appeared on virtual film;

FIG. **26** shows an approach to manipulating a virtual lens plane, according to another example embodiment of the present invention;

FIG. **27** illustrates that the virtual film may take any shape, according to another example embodiment of the present invention;

FIG. **28** shows an imaging arrangement; according to another example embodiment of the present invention;

FIG. **29** is a process flow diagram for pre-computing a database of weights associated with each output image pixel and each ray sensor value, according to another example embodiment of the present invention;

FIG. **30** is a process flow diagram for computing an output image using a database of weights, according to another example embodiment of the present invention;

FIGS. **31**A-D illustrate various scalar functions which are selectively implemented as a virtual aperture function, according to another example embodiment of the present invention;

FIG. **32** shows a virtual aperture function which varies from pixel to pixel; according to another example embodiment of the present invention;

FIG. **33** is a process flow diagram of a user selecting a region of an output image, editing an image portion and saving the output image, according to another example embodiment of the present invention;

FIG. **34** is a process flow diagram for extending the depth of field in an image, according to another example embodiment of the present invention; and

FIG. **35** is a process flow diagram for computing a refocused image from received light ray sensor data, according to another example embodiment of the present invention.

While the invention is amenable to various modifications and alternative forms, specifics thereof have been shown by way of example in the drawings and will be described in detail. It should be understood, however, that the intention is not to limit the invention to the particular embodiments described. On the contrary, the intention is to cover all modifications, equivalents, and alternatives falling within the spirit and scope of the invention.

DETAILED DESCRIPTION

The present invention is believed to be useful for a variety of different types of devices, and the invention has been found to be particularly suited for electronic imaging devices and applications. While the present invention is not necessarily limited to such applications, various aspects of the invention may be appreciated through a discussion of various examples using this context.

According to an example embodiment of the present invention, a four-dimensional (4D) light field (e.g., the light traveling along each ray in a region such as free space) is detected using an approach involving the determination of the amount and direction of light arriving at a sensor located at a focal plane. The two-dimensional position of light in the focal plane is detected, together with information characterizing the direction from which the light arrived at particular locations in the plane. With this approach, the directional lighting distribution arriving at different locations on the sensor are determined and used to form an image. In various discussions herein, the assembly or assemblies implemented for sensing and/or measuring of a light field are referred to as a "light ray sensor," or a "ray sensor."

In one application, an approach similar to the above is implemented using an imaging system having optics and sensors that sample the space of light rays that are incident on an imaging plane, with computational functionality that renders images from the set of measured rays in different ways. Each of the optics, sensors and computational functionality is

implemented using a variety of approaches, in combination or distinctly, depending upon the implementation. For example, a camera having lenses (optics) that focus an image upon a photosensor array (sensors) located at an imaging plane can be used to sample the space of light rays. An output from the photosensor array is used with computational functions (e.g., at a processor internal and/or external to the camera) to render images, such as by computing photographs that are focused at different depths or with different depths of field, and/or computationally correcting lens aberrations to produce higher quality images.

In another example embodiment, optics and sensor components of an imaging system direct rays of light onto sensor elements such that each sensor element senses a set of rays including rays emanating from specific directions. In many applications, this set of rays is a bundle of rays that is localized in both space and direction. For many applications, this bundle of rays will converge to a single geometric ray of light as the optics and sensor resolutions increase. In this regard, various portions of the description herein refer to the values sensed by the sensor elements as "rays of light" or "light rays" or simply "rays," even though in general they may not be limited to geometric rays.

Turning now to the figures, FIG. **28** shows an imaging arrangement **2890**, according to another example embodiment of the present invention. The imaging arrangement **2890** includes a main lens **2810**, and a light ray sensor that measures the value of light arriving at different locations on the sensor and from difference incident directions. In this context, measuring the value of light may be implemented by detecting light arriving at different locations at the sensor, together with characteristics of that light such as intensity to generate a value.

FIG. **1** shows an imaging system **100**, according to another example embodiment of the present invention. The imaging system **100** includes an imaging arrangement **190** having a main lens **110**, a microlens array **120** and a photosensor array **130**. In this case, the microlens array **120** and photosensor array **130** implement a light ray sensor. Although FIG. **1** illustrates a particular main lens **110** (single element) and particular microlens array **120**, those skilled in the art will recognize that a variety of lenses and/or microlens arrays (currently available or developed in the future) are selectively implemented with a similar approach by, for example, replacing the shown main lens and/or microlens array.

Rays of light from a single point on a subject **105** in an imaged scene are brought to a single convergence point on the focal plane of the microlens array **120**. For instance, when the imaged point on the subject **105** is at a distance from the main lens that is conjugate to the distance from the microlens array to the main lens, the dimension "d" is about equal to the dimension "s" as shown. A microlens **122** at this convergence point separates these rays of light based on the direction of the light, creating a focused image of the aperture of the main lens **110** on the photosensors underneath the microlens.

The photosensor array **130** detects light incident upon it and generates an output that is processed using one or more of a variety of components. In this application, the output light data is passed to sensor data processing circuitry **140**, which uses the data together with positional information about each photosensor providing the data in generating an image of the scene (e.g., including subjects **105**, **106** and **107**). The sensor data processing circuitry **140** is implemented, for example, with a computer or other processing circuit selectively implemented in a common component (e.g., a chip) or in different components. In one implementation, a portion of the sensor data processing circuitry **140** is implemented in the imaging arrangement **390**, with another portion of implemented in an external computer. Using the detected light (and, e.g., characteristics of the detected light) together with a known direction from which the light arrived at the microlens array (as computed using a known location of each photosensor), the sensor data processing circuitry **140** selectively refocuses and/or corrects light data in forming an image (where refocusing may be correcting). Various approaches to processing detected light data are described in detail below, with and without reference to other figures. These approaches may be selectively implemented with the sensor data processing circuitry **140** consistent with the above.

Different portions of the imaging system **100** are selectively implemented in a common or separate physical arrangement, depending upon the particular application. For example, when implemented with a variety of applications, the microlens array **120** and the photosensor array **130** are combined into a common arrangement **180**. In some applications, the microlens array **120** and the photosensor array **130** are coupled together on a common chip or other circuit arrangement. When implemented with a hand-held device such as a camera-like device, the main lens **110**, microlens array **120** and photosensor array **130** are selectively combined into a common imaging arrangement **190** integrated with the hand-held device. Furthermore, certain applications involve the implementation of some or all of the sensor data processing circuitry **140** in a common circuit arrangement with the photosensor array **130** (e.g., on a common chip).

In some applications, the imaging arrangement **100** includes a preview arrangement **150** for presenting a preview image to a user capturing images. The preview arrangement is communicatively coupled to receive image data from the photosensor array **130**. A preview processor **160** processes the image data to generate a preview image that is displayed on a preview screen **170**. In some applications, the preview processor **160** is implemented together with the image sensor **180**, on a common chip and/or in a common circuit. In applications where the sensor data processing circuitry **140** is implemented with the photosensor array **130** as discussed above, the preview processor **160** is selectively implemented with the sensor data processing circuitry **140**, with some or all of the image data collected by the photosensor array **130** used to generate the preview image.

The preview image may be generated using relatively fewer computational functions and/or less data than that used to generate a final image. For instance, when implemented with a hand-held imaging device such as a camera or cell phone, a preview image that does not effect any focusing or lens correction may be sufficient. In this regard, it may be desirable to implement processing circuitry that is relatively inexpensive and/or small to generate the preview image. In such applications, the preview processor generates the image at a relatively low-computational cost and/or using less data, for example by using the first extended depth of field computational method as described above.

The imaging system **100** is implemented in a variety of manners, depending upon the application. For instance, while the microlens array **120** is shown with several distinguishable microlenses by way of example, the array is generally implemented with a multitude (e.g., thousands or millions) of microlenses. The photosensor array **130** generally includes a relatively finer pitch than the microlens array **120**, with several photosensors for each microlens in the microlens array **120**. In addition, the microlenses in the microlens array **120** and the photosensors in the photosensor array **130** are gener-

ally positioned such that light passing via each microlens to the photosensor array does not overlap light passed via adjacent microlenses.

In various applications, the main lens **110** is translated along its optical axis (as shown in FIG. **1**, in a horizontal direction) to focus on a subject of interest at a desired depth "d" as exemplified between the main lens and an example imaging subject **105**. By way of example, light rays from a single point on the subject **105** are shown for purposes of this discussion. These light rays are brought to a single convergence point at microlens **122** on the focal plane of the microlens array **120**. The microlens **122** separates these rays of light based on direction, creating a focused image of the aperture of the main lens **110** on a set of pixels **132** in the array of pixels underneath the microlens. FIG. **10** illustrates one example approach to separating light rays, such that all rays emanating from a point on a main lens **1010** and arriving anywhere on the surface of the same microlens (e.g., **1022**) are directed by that microlens to converge at the same point on a photosensor (e.g., **1023**). This approach shown in FIG. **10** may, for example, be implemented in connection with FIG. **1** (i.e., with the main lens **1010** implemented for main lens **110**, with microlens array **1020** implemented for microlens array **120**, and with photosensor array **1030** implemented for photosensor array **130**).

The image that forms under a particular microlens in the microlens array **122** dictates the directional resolution of the system for that location on the imaging plane. In some applications, directional resolution is enhanced by facilitating sharp microlens images, with the microlenses focused on the principal plane of the main lens. In certain applications the microlenses are at least two orders of magnitude smaller than the separation between the microlens array and the main lens **110**. In these applications, the main lens **110** is effectively at the microlenses' optical infinity; to focus the microlenses, the photosensor array **130** is located in a plane at the microlenses' focal depth.

The separation "s" between the main lens **110** and the microlens array **120** is selected to achieve a sharp image within the depth of field of the microlenses. In many applications, this separation is accurate to within about $\Delta x_p \cdot (f_m/\Delta x_m)$, where Δx_p is the width of a sensor pixel, f_m is the focal depth of the microlenses and Δx_m is the width of the microlenses. In one particular application, Δx_p is about 9 microns, f_m is about 500 microns and. Δx_m is about 125 microns, with the separation between the microlens array **120** and the photosensor array **130** being accurate to about 36 microns.

The microlens array **120** is implemented using one or more of a variety of microlenses and arrangements thereof. In one example embodiment, a plane of microlenses with potentially spatially varying properties is implemented as the microlens array **120**. For example, the microlens array may include lenses that are homogeneous and/or inhomogeneous, square in extent or non-square in extent, regularly distributed or non-regularly distributed, and in a pattern than is repeating or non-repeating, with portions that are optionally masked. The microlenses themselves may be convex, non-convex, or have an arbitrary profile to effect a desired physical direction of light, and may vary in profile from microlens to microlens on the plane. Various distributions and lens profiles are selectively combined. These various embodiments provide sampling patterns that are higher spatially (correspondingly lower angularly) in some regions of the array, and higher angularly (correspondingly lower spatially) in other regions. One use of such data facilitates interpolation to match desired spatial and angular resolution in the 4D space.

FIG. **24**A illustrates a view (line of sight perpendicular to the plane) of a portion of a microlens array, according to another example embodiment of the present invention. The microlenses are square-shaped and regularly distributed in an array.

FIG. **24**B illustrates a view of a portion of a microlens array, according to another example embodiment of the present invention. The microlens plane distribution is not regular or repeating, and the microlenses are arbitrarily shaped.

FIG. **24**C illustrates images that appear on the photosensor in connection with another example embodiment of the present invention, using a distribution such as that shown in FIG. **24**A with a convex profile and a main lens having a circular aperture.

In other example embodiments, a regular mosaic of larger and smaller microlenses is used. In one implementation, the resulting photosensor data is interpolated to provide a homogeneous sampling that has the maximum spatial and angular resolutions of a microlens or microlenses in the mosaic.

FIGS. **19**A-**19**F illustrate approaches to implementing a mosaic array such as that described above, in connection with one or more example embodiments of the present invention. FIG. **19**A is an overhead view of a plane showing example relative sizes and arrangement of the microlenses. FIG. **19**B is an illustration of the shape of the images that form on the photosensor array after projection through each microlens in FIG. **19**A. FIG. **19**C is a cross-sectional view of the array in FIG. **19**A, illustrating that the microlenses have the same f-number and their focal points share a common plane. This requires that the smaller microlenses are positioned closer to the focal plane than the larger ones. This causes the images of the main lens that appear underneath each microlens to be large without overlapping, and all appear in-focus on a photosensor that is placed at the plane containing the focal points.

FIG. **19**D shows a cross-sectional view of the microlenses shown in FIGS. **19**A and **19**C implemented in a full imaging arrangement containing a main lens **1910**, a mosaic microlens array **1920** and photosensor arrangement **1930**, according to another example embodiment of the present invention. Note that although the diagram has been shown with several microlenses and several pixels per microlens, the actual number of microlenses and pixels is selected using a variety of approaches, such as by determining the resolution requirements of the given application and implementing appropriate numbers of each.

FIG. **19**E is a Cartesian ray diagram representing the space of rays starting at u on the main lens **1910** and terminating at s on the microlens array **1920** (the space of rays is shown in 2D for clarity, although the full space of rays is 4D). The set of rays that are summed by each photosensor (labeled A-P) in FIG. **19**C is shown on the Cartesian ray diagram in FIG. **19**D. In the full 4D space of rays, each photosensor integrates a 4D box of rays. The 4D boxes for photosensors under the larger microlenses have half the width (twice the resolution) in the (u, v) directional axes, and twice the width (half the resolution) in the (x, y) spatial axes compared to photosensors under the smaller microlenses.

In another example embodiment, photosensor values are interpolated to a regular grid so that the resolution in all axes matches the maximum resolution in all axes. FIG. **19**F illustrates such an approach, wherein the boxes of rays that represent each photosensor value are split by interpolating nearby box values. In the 2D ray space illustrated, each box is split into two, but in the 4D space, each box is split into four (split into two along each of its two longer sides). In some embodiments, the interpolated values are computed by ana-

lyzing the nearby values. In another embodiment, the interpolation is implemented as a weighted sum of the values of the original, unsplit boxes in a neighborhood of the desired value.

In some applications, the weighting is implemented in a manner that depends on a decision function based on the values in a neighborhood. For example, the weighting may interpolate along the axes that are least likely to contain an edge in the 4D function space. The likelihood of an edge near that value can be estimated from the magnitude of the gradient of the function values at those locations, as well as the components of the Laplacian of the function.

In another example embodiment, each of the microlenses (e.g., in the array **1920** of FIG. **19**D or similar) is tilted inwards so that their optical axes are all centered on the main lens aperture. This approach reduces aberrations in the images that form under microlenses towards the edges of the array.

Referring again to FIG. **1**, the aperture sizes of the main lens **110** and of the microlenses in the microlens array **120** (e.g., the effective sizes of the opening in the lenses) are also selected to meet specific applications in which the imaging arrangement **100** is implemented. In many applications, the relative aperture sizes are selected so that collected images are as large as possible without overlapping (i.e., such that light does not undesirably overlap onto an adjacent photosensor). This approach is facilitated by matching the f-numbers (focal ratios; i.e., the ratio of the aperture to the effective focal length of the lens) of the main lens and the microlenses. In this instance, the effective focal length, in terms of the f-number, for the main lens **110** is the ratio of the diameter of the aperture of the main lens to the distance "s" between the main lens **110** and the microlens array **120**. In applications in which the principal plane of the main lens **110** is translated relative to the plane at which the microlens array **120** is located, the aperture of the main lens is selectively modified so as to maintain the ratio and thus the size of the images forming under each microlens in the microlens array. In some applications, different main lens aperture shapes such as a square aperture are used to achieve desirable (e.g., efficient) packing of the array of images under the microlens array on the photosensor surface.

The following discussion refers to a general application of the imaging arrangement **100** of FIG. **1**, in connection with one or more example embodiments of the present invention. Considering a two-plane light field "L" inside the imaging arrangement **100**, L(u,v,s,t) denotes the light traveling along a light ray that intersects the main lens **110** at (u, v) and that intersects the plane of the microlens array **120** at (s,t). Assuming ideal microlenses in the microlens array **120** and ideal photosensors (e.g., pixels) on aligned grids in the photosensor array **130**, all the light that passes to a photosensor also passes through its square parent microlens in the microlens array **120**, and through the photosensor's conjugate square on the main lens **110**. These two square regions on the main lens **110** and microlens specify a small four-dimensional box in the light field, and the photosensor measures the total amount of light in the set of rays represented by this box. Correspondingly, each photosensor detects such a four-dimensional box in the light field; the light field detected by the photosensor array **130** thus is a box-filtered, rectilinear sampling of L(u, v,s,t).

FIG. **11** illustrates an approach to the mapping of sensor pixel locations to rays in the L(u,v,s,t) space with respect to data collected, according to another example embodiment of the invention. The approach shown in FIG. **11** and discussed herein may be applicable, for example, to FIG. **1** with each photosensor in the photosensor array **130** corresponding to a sensor pixel. Image **1170** in the bottom right is a downsampling of raw data read from a ray sensor (photosensor) **1130**, with the circular image **1150** that forms under one microlens circled. Image **1180** in the bottom left is a close-up representation of a portion of the raw data around the circled microlens image **1150**, with one photosensor value **1140** circled within the microlens image. Since this circular image **1150** is an image of the lens aperture, the location of the selected pixel within the disk provides the (u, v) coordinates of the starting position of the illustrated ray **110** on the main lens. The location of the microlens image **1150** within the sensor image **1170** provides the (x, y) coordinates of the ray **1120**.

Although the mapping of sensor elements to rays is discussed with respect to the figures (and other example embodiments), values associated with the various sensor elements are selectively represented by the value of the set of rays that is directed through optics to each particular sensor element. In the context of FIG. **1**, each photosensor in the photosensor array can thus be implemented to provide a value that represents a set of light rays directed via the main lens **110** and microlens array **120** to the photosensor. That is, each photosensor generates an output in response to the light incident upon the photosensor, and the position of each photosensor, relative to the microlens array **120**, is used to provide directional information about the incident light.

In one example embodiment, the resolution of the microlens array **120** is selected to match a particular application's desired resolution for final images. The resolution of the photosensor array **130** is selected so that each microlens covers as many photosensors as required to match the desired directional resolution of the application, or the finest resolution of photosensors that may be implemented. In this regard, the resolution of the imaging system **100** (and other systems discussed herein) is selectively tailored to particular applications, with considerations such as the type of imaging, cost, complexity and available equipment used to arrive at a particular resolution.

Once image data is captured via optics and sensors (e.g., using imaging arrangement **190** in FIG. **1**), a variety of computational functions and arrangements are implemented to selectively process the image data. In one example embodiment of the present invention, different sets of photosensors capture these separated light rays from each microlens and pass information about the captured light rays to a computational component such as a processor. Images of the scene are computed from the set of measured light rays.

In the context of FIG. **1**, sensor data processing circuitry **140** is implemented to process the image data and compute images of the scene including subjects **105**, **106** and **107**. In some applications, a preview arrangement **150** is also implemented to generate a preview image using a preview processor **160**, with the preview image displayed on a preview screen **170**. The previous processor **160** is selectively implemented with the sensor data processing circuitry **140**, with a preview image generated in a manner not inconsistent, for example, with approaches discussed below.

In another embodiment, for each pixel in an image output from a sensor arrangement, the computational component weights and sums a subset of the measured rays of light. In addition, the computational component may analyze and combine a set of images computed in the manner described above, for example, using an image compositing approach. Although the present invention is not necessarily limited to such applications, various aspects of the invention may be appreciated through the discussion of several specific example embodiments of such a computational component.

In connection with various example embodiments, image data processing involves refocusing at least a portion of an image being captured. In some embodiments, an output image is generated in the context of a photograph focused on desired elements of a particular scene. In some embodiments, the computed photograph is focused at a particular desired depth in the world (scene), with misfocus blur increasing away from the desired depth as in a conventional photograph. Different focal depths are selected to focus upon different subjects in the scene.

FIG. **12** illustrates several images **1200**-**1240** refocused at different depths, computed from a single light field measured in accordance with another example embodiment of the present invention. The approach shown in FIG. **12** may, for example, be implemented using an imaging arrangement such as that shown in FIG. **1**.

FIGS. **13**A and **13**B show a refocusing approach, according to another example embodiment of the present invention. This approach may be implemented, for example, with a computational/processor component of an imaging system, such as the sensor data processing circuitry **140** in FIG. **1**. Each output pixel (e.g., **1301**) from an imaging arrangement corresponds to a three-dimensional (3D) point (e.g., **1302**) on a virtual film plane **1310**. This virtual film plane **1310** is located behind a main lens **1330**, where the plane **1310** is optically conjugate to the desired focal plane in the world (not shown). That is, the virtual film plane **1310** is located at a position at which a film plane would desirably be located to capture a simple two-dimensional (2D) image (e.g., the position is comparable to the position at which a photographic film would be located with a conventional camera in order to capture a 2D image). By separating light by direction (e.g., using the microlens array **120** of FIG. **1**), the light arriving at the virtual film plane **1310** can be selectively computed. In this regard, the value for the output pixel **1301** is computed by summing the cone of light rays **1320** that converge on the corresponding 3D point **1302**. Values for these rays are gleaned from the data collected by the ray sensor **1350**. FIG. **13**A shows an imaging configuration in 2D for visual simplicity. In FIG. **13**B, a cone of rays **1330** from the 3D point **1340** is summed for the same pixel **1301**, with the chosen world focal depth if closer to the main lens.

In some embodiments, the required light ray values do not correspond exactly to the discrete sample locations captured by the ray sensor. In some embodiments, the light ray value is estimated as a weighted sum of selected close sample locations. In some implementations, this weighting approach corresponds to a four-dimensional filter kernel that reconstructs a continuous four-dimensional light field from the discrete sensor samples. In some implementations, this four-dimensional filter is implemented with a four-dimensional tent function corresponding to quadrilinear interpolation of the 16 nearest samples in the four dimensional space.

FIG. **35** is a process flow diagram for computing a refocused image from received light ray sensor data, according to another example embodiment of the present invention. At block **3520** a set of sub-aperture images is extracted from light ray sensor data **3510**, where each sub-aperture image consists of a single pixel under each microlens image where the pixels are at the same relative position under its microlens. At block **3530**, the set of sub-aperture images is combined to produce the final output image. The sub-aperture images are optionally translated relative to one another and composited to bring a desired plane into focus.

In another example embodiment, darkening associated with pixels near a border of an output image is mitigated. For instance, with the pixels near the border of an output image, some required rays may not have been captured in the measured light field (they may exceed the spatial or directional bounds of the imaging arrangement, such as the microlens array **120** and photosensor array **130** in FIG. **1**). For applications in which this darkening is undesirable, the pixel values are normalized by dividing a value associated with the pixels (e.g., as captured by a photosensor array) by the fraction of rays that are actually found in the measured light field.

As discussed above, a variety of different computational approaches are chosen for different applications. The following discussion addresses various such approaches. In some applications, reference is made to figures, and in other applications, the approaches are discussed generally. In each of these applications, the particular approaches may be implemented using a computational-type component, such as the sensor data processing circuitry **140** shown in FIG. **1**.

In another example embodiment, an imaging methodology for each output pixel for a particular imaging system corresponds to a virtual camera model in which a virtual film is rotated or deformed, arbitrarily and/or selectively, and a virtual main lens aperture is correspondingly moved and modified in size as appropriate. By way of example, FIG. **25** illustrates an example embodiment in which a virtual image is computed as it would have appeared on virtual film **2560** if it had been present behind a virtual lens aperture **2520** of arbitrary size on a virtual lens plane **2530** that is permitted to be non-coincident with the physical main lens plane **2510**. The value of the pixel corresponding to point **2550** on the virtual film **2560** is computed by summing the rays passing through the virtual aperture **2520** and converging on point **2550**, which are found by their intersection point and incident direction on ray sensor **2570**.

FIG. **26** shows an approach to manipulating a virtual lens plane, according to another example embodiment of the present invention. A virtual lens plane **2630** and/or virtual film plant **2660** selectively tilted, relative to a physical main lens or other reference. An image computed using this approach has a resulting world focal plane that is not parallel to the imaging plane.

In another example embodiment, as exemplified in FIG. **27**, the virtual film **2560** need not be planar, but may take any shape.

A variety of approaches involve selective implementation of different apertures. In one example embodiment, the virtual aperture on the virtual lens plane is a generally circular hole, and in other example embodiments, the virtual aperture is generally non-circular and/or is implemented with multiple distinct regions of any shape. In these and other embodiments, the notion of "virtual aperture" can be generalized, and in some applications, corresponds to an approach involving the processing of light data to correspond to light that would be received via a selected "virtual" aperture.

In various embodiments, a virtual aperture approach is implemented with a pre-determined but arbitrary function on a virtual lens plane. FIGS. **31**A-**31**D illustrate various scalar functions that are selectively implemented as the virtual aperture function in connection with one or more example embodiments. The various functions include, for example, smoothly varying values (as exemplified in FIG. **31**B), implementing a plurality of distinct regions (as exemplified in FIG. **31**A), and taking on negative values (as exemplified in FIG. **31**D). To compute the value of a point on a virtual film, all rays that start at different points on the virtual lens and converge on the point on the virtual film are weighted by the virtual aperture function and summed. In various other embodiments, the final value is computed with an arbitrary computational function that depends on the ray values. For example, the compu-

tational function may not correspond to a weighting by a virtual aperture function, but may contain discontinuous program branches depending on the value of test functions computed on the ray values.

In other example embodiments, as may be implemented in combination with the other example embodiments described herein, a method of computing output pixels is chosen independently. For example, in one example embodiment, parameters including the orientation of a virtual lens plane and the size of the virtual aperture are varied continuously for each output pixel. In another example, as illustrated in FIG. **32**, the virtual aperture function used to integrate rays for each output pixel is varied from pixel to pixel. In an output image **3200**, pixel **3201** uses virtual aperture function **3210** and pixel **3251** uses virtual aperture function **3250**.

In another example embodiment, a virtual aperture function varies from pixel to pixel. In one specific embodiment, the function is chosen to mask out rays from undesired portions of a particular scene, such as an undesired object in the foreground.

In another example embodiment, a human user chooses virtual aperture parameters interactively, with light data processed in accordance with the selections. FIG. **33** is a process flow diagram showing one such example embodiment. In the first block **3310**, the process receives data from a light ray sensor. In block **3320**, a user selects a region of an output image; in block **3330** a user selects an image formation method; and in block **3340**, the user alters parameters for the selected method and visually examines a computed image of the scene at block **3350** (for example on a computer monitor). Block **3360** checks if the user is done editing the image portion, and if not returns to block **3330**. Block **3370** checks whether the user is done choosing portions of the image to edit, and if not returns to block **3320**. If editing is complete, block **3380** saves the final edited image.

In another example embodiment, an image with extended depth of field is computed by focusing on more than one subject at the same time. In one implementation, the depth of field of the output image is extended by simulating conventional photographic imaging with a stopped-down (reduced size) main lens aperture. For each output pixel, an evaluation is performed using the rays of light that would have converged at the output pixel through an aperture (on the virtual lens plane) that is smaller than the aperture used in ray sensing.

In one implementation involving the example system **100** shown in FIG. **1**, the depth of field is extended by extracting a photosensor value under each microlens image, where each photosensor is located at the same relative position within each microlens image. With respect to FIG. **1**, extending the depth of field produces an image in which not only the subject **105** is in focus (due to the correlation between the distances "d" and "s") but also objects at a different depth, such as subjects **106** and **107**, which may otherwise be blurry due to misfocus. This approach to extending the depth of field, coupled with optional downsampling of the resulting image, is computationally efficient. This approach is selectively implemented in applications where noise generated with the image is tolerable, such as where the image generated is for preview purposes (e.g., for display at the preview screen **170** in FIG. **1**). FIG. **4**, discussed below, is further directed to approaches to the generation of a preview image.

FIGS. **14**A and **14**B illustrate an approach to computing images with different depths of field, in connection with one or more example embodiments. FIG. **14**A shows an image and close-up computed with refocusing. Note that the face in the close-up is blurry due to shallow depth of field. The middle row of FIG. **14**B shows the final image computed with an extended depth of field approach such as that described in the previous paragraph.

FIG. **8** is a process flow diagram for another computational approach to extending the depth of field in an image, according to another example embodiment of the present invention. At block **810**, a set of images refocused at all focal depths in a particular scene is refocused. At block **820** and for each pixel, a pixel is determined from a set of images that has the highest local contrast. At block **830**, the pixels having the highest local contrast are assembled into a final virtual image. With this approach, a desirable signal-to-noise ratio (SNR) can be obtained, using a relatively high number of pixels (e.g., relative to selecting a single pixel (photosensor) for each microlens in a microlens array). Referring to FIG. **14**C, the example image shown is produced using an approach similar to that described in connection with FIG. **8** and exhibits relatively low image noise.

In one alternative embodiment, a minimum set of refocused images to compute is defined as follows, in terms of the distance between a virtual film plane for each refocused image and the principal plane of the main lens via which the light for the image is passed to the virtual film plane. A minimum distance is set at the focal length of the main lens, and the maximum distance set at the conjugate depth for the closest object in the scene. The separation between each virtual film plane is no more than $\Delta x_m f/A$, where Δx_m is the width of a microlens, f is the separation between the main lens and the microlens array, and A is the width of the lens aperture.

In another example embodiment, refocused images are combined to produce an extended depth of field image at each final pixel to retain the pixel that is best focused in any of the set of refocused images. In another embodiment pixels to retain are chosen by enhancing the local contrast and coherence with neighboring pixels. For general information regarding imaging, and for specific information regarding approaches to imaging involving enhancing local contrast, reference may be made to Agarwala, A., Dontcheva, M., Agrawala, M., Drucker, S., Colburn, A., Curless, B., Salesin, D., Cohen, M., Interactive Digital Photomontage, in ACM Transactions on Graphics, 23, 3 (2004), 292-300, which is fully incorporated herein by reference.

In another example embodiment of the present invention, an extended depth of field image is computed as follows. For each output image pixel, a refocusing computation is performed at the pixel to focus at different depths. At each depth, a measure of the homogeneity of the rays that converge is computed. The depth that produces the (relative) maximum homogeneity is chosen and kept for that pixel value. With this approach, where an image pixel is in focus, all of its rays originate from the same point in the scene and thus are likely to have similar color and intensity.

Although the measure of homogeneity can be defined in various ways, for many applications, the following measure of homogeneity is used: for each color component of each ray, the squared difference of that color intensity is computed from the corresponding color component of the central ray (the ray that arrives at the pixel at an angle closest to the optical axis of the main lens). All of these squared differences are summed, and the homogeneity is taken to be the reciprocal of the sum.

FIG. **34** is a process flow diagram for extending the depth of field in an image, according to another example embodiment of the present invention. At block **3410**, a pixel is selected in a virtual image to be computed. At block **3420**, the pixel is refocused at a plurality of focal depths, and the homo-

geneity of the rays that are combined to refocus at each depth is computed. At block **3430**, the refocused pixel value associated with the highest homogeneity of rays that are combined is retained as the final output image pixel value. The process continues at block **3440** until all pixels are processed.

In another example embodiment, the above process is adapted so that the selection of final pixel values takes into account the neighboring pixel values, and the homogeneity of the associated rays that are combined to compute those pixel values.

In other example embodiments of the present invention, the depth of field is extended by focusing each pixel on the depth of the closest object in that direction. FIG. **9** is a process flow diagram for extending the depth of field in an image, according to one such example embodiment. At block **910**, a pixel is selected in a final virtual image to be computed. At block **920**, the depth of a nearest object is estimated for a light ray (or set of light rays) traced from the selected pixel into a scene through the center of the lens.

At block **930**, the selected pixel's value is computed in an image refocused at the estimated depth. If additional pixels are desirably processed at block **940**, another pixel is selected at block **910** and the process continues at block **920** for the newly-selected pixel. When no additional pixels are desirably processed at block **940**, the computed values for each selected pixel are used to create the final virtual image.

In some embodiments involving the extension of the depth of field, a value at each output pixel is computed by disregarding light rays that originate at depths closer than the depth of a desired object to mitigate or eliminate artifacts such as those generally referred to as "blooming" or "halo" artifacts around the borders of objects closer to the lens. By way of example, FIG. **23** illustrates the set of rays that pass through a desired focal point **2301** in the world on a subject of interest **2310**. Some of these rays are occluded from the main lens by object **2320**, and these correspond to the light rays **2340** that are detected by ray sensor **2350** but disregarded in computing an image value for point **2301**. In some embodiments, rays to be disregarded are detected by a mismatch with the color of the central ray. In some embodiments the resulting pixel value is normalized by dividing by the fraction of rays that are not disregarded. These embodiments may be used in isolation or combination with each other and any other embodiments, including those directed to extending the depth of field.

As discussed above, light data is processed in accordance with various example embodiments to focus and/or correct images. A variety of approaches to the latter correction approach are discussed as follows. In some of these embodiments, aberrations are corrected by tracing rays through the actual optical elements of the optics (e.g., lens or lenses) used in capturing the rays, and mapping the traced rays to particular photosensors capturing the light. Light data is rearranged, using knownd defects exhibited by the optics as well as the known position of the sensors detecting the light.

In one correction-type embodiment, the world of rays that contribute to each pixel as formed through idealized optics is computed for each pixel on a film of a synthesized photograph. In one implementation, these rays are computed by tracing rays from the virtual film location back through the ideal optics into the world. FIG. **15** illustrates an approach to the tracing of rays from a 3D point **1501** on a virtual film plane **1510** through an ideal thin main lens **1520** out into a cone of world rays **1530**, in connection with one such example embodiment. In some implementations, the set of desired rays **1525** may not necessarily correspond to direction through a real lens, but may correspond to any set of rays that are to be weighted and summed to produce a desired image value.

FIG. **16** shows an approach to finding the value of light traveling along ideal rays for a particular application, in connection with another example embodiment. These values are computed by tracing desired ideal world rays **1630** through a real main lens **1650**, having a single element with spherical interfaces, used to physically direct the real world light rays to the ray sensor **1640** at the time the rays are measured (detected). In this embodiment, the rays that ideally converge to a single 3D point (**1601**) do not converge, representing a defect of lenses with spherical interfaces called spherical aberration. The ray sensor **1640** provides individual values for each of the aberrated rays (such as **1651**), which are used to correct for the spherical aberration.

FIGS. **17**A-**17**C illustrate example results using a computer simulation with an approach to lens correction. The image in FIG. **17**A is an ideal 512×512 photograph (as seen through perfect optics). The image in FIG. **17**B is an image that would be produced with a real f/2 bi-convex spherical lens, which has loss in contrast and blurring. The image in FIG. **17**C is a photograph computed using an approach to image correction described above, using an optics and sensor arrangement facilitating 10×10 directional (u, v) resolution at each of 512×512 microlenses.

In another example embodiment of the present invention, chromatic aberrations are corrected in a main lens used to capture an image. Chromatic aberration is caused by the divergence of rays of light as they are physically directed through optics because of differences in the physical direction dependent on the wavelength of light. The incoming rays are traced through the actual optics, taking into account the wavelength-dependent refraction of light that occurs in the actual optics. In some applications, each color component of the system is traced separately based on the primary wavelength.

In another example embodiment, each of the red, green and blue components common in color imaging systems is traced separately, as illustrated in FIG. **18**A. The green world light rays are computationally traced back into the imaging system to produce green rays **1830**, and to determine where they intersect a color ray sensor **1810** and at what direction they intersect the color ray sensor **1810**. Similarly, FIG. **18**B illustrates computationally tracing the desired blue world light rays **1820**, which are refracted to a greater extent than the green light rays. FIG. **18**C illustrates computationally tracing the desired red world light rays **1830**, which are refracted to a lesser extent than the green light rays. The values for each ray are computed from the values from the ray sensor **1810** using, for example, approaches discussed in connection with other example embodiments described herein. The light field values for each ray are integrated to calculate the corrected image value for each particular film pixel. For some applications, chromatic aberration is ameliorated by refocusing each color channel on the plane at which its wavelengths best come into focus.

The desired light rays may not converge exactly on one of the discrete ray values sampled by the ray sensor. In some embodiments, the value to be used for such rays is computed as a function of the discrete ray values. In some embodiments, this function corresponds to a weighted sum of the value of discrete rays in a neighborhood of the desired light ray. In some implementations, this weighted sum corresponds to a 4D convolution of the discrete sample values with a predetermined convolution kernel function. In other implementations, the weighting may correspond to a quadrilinear interpolation from the 16 nearest neighbors. In still other

implementations, the weighting may correspond to a cubic or bicubic interpolation from the 16 nearest neighbors.

It is worth noting that example correction processes have been described in terms of ray-tracing for conceptual simplicity; a variety of other approaches are implemented with correction. In one embodiment, for each desired output pixel, the set of photosensor values that contribute are pre-computed along with their relative weights. As described above, these weights are a property of a number of factors that may include the optics, sensor, desired set of rays to be weighted and summed for each output pixel and desired light field reconstruction filter. These weights are pre-computed, selectively using ray-tracing, and stored. A corrected image is formed by weighting and adding the appropriate sensed light field values for each output pixel.

FIG. **29** and FIG. **30** illustrate other example embodiments for use in connection with the above correction approach. FIG. **29** is a process flow diagram for pre-computing a database of weights associated with ray (light) sensors and an output pixel value associated with each ray sensor. In the first two blocks **2910** and **2920**, a data set (e.g., in a database) is received for a desired image formation process consisting (for each output image pixel) of a set of ideal world light rays to be summed to produce an output image pixel value, and a specification for real main lens optics used to physically direct light rays to a light ray sensor. At block **2925**, an image pixel is chosen. For the output value of this pixel, the associated set of world rays is computationally traced at block **2930** through a virtual representation of the main lens optics to the ray sensor. This results in a set of weights to be applied to each ray sensor value to compute the output pixel value. These values are stored in an output database in block **2940**. Block **2950** checks whether all pixels have been processed, returning to block **2925** if not. If all pixels have been processed, the final block **2960** saves the completed database.

FIG. **30** is a flow diagram for a process that computes an output image using a database of weights that may have been computed by a process as in FIG. **29**. In block **3010** and **3020**, the process receives the database and a set of ray sensor values captured with the main lens optics used in computing the database. At block **3025**, a pixel in the output image is selected, so that its final image value may be computed. For the selected pixel, block **3030** uses the database to find the set of ray sensor that contributes and their weights. In block **3040**, each sensor value given in **3020** is weighted and added to a sum for that image pixel value. At block **3050**, a check is performed to see whether all image pixels have been processed. If not, the process returns to block **3025**, and if so, the output image is saved at block **3060**.

In a variety of example embodiments, light data is processed in the frequency domain, with certain approaches directed to computational approaches to refocusing that operate in the Fourier domain. FIG. **20** is a flow diagram illustrating one such approach, in connection with another example embodiment. The input to the algorithm is a discrete 4D light field **2010**, which we will refer to as L(s,t,u,v), representing the ray starting at (u, v) on a main lens and terminating at (s, t) on a microlens plane (e.g., from the main lens **110** and terminating at a plane of the microlens array **120** of FIG. **1**). The first step is to compute the discrete 4D Fourier transform **2020** of the light field. The 4D Fourier transform value at (k_s, k_t, k_u, k_v), let us call this value M(k_s, k_t, k_u, k_v) is defined by the following equation:

$$M(k_s,k_t,k_u,k_v)=\iiiint L(s,t,u,v)\exp(-2\pi\sqrt{-1}\cdot(sk_s+tk_t+uk_u+vk_v))dsdtdudv, \quad (1)$$

where the exp function is the exponential function, $\exp(x)=e^x$. In some embodiments the discrete light field is sampled on a rectilinear grid in the 4D space, and the Fourier transform is computed with the Fast Fourier Transform (FFT) algorithm.

The next step, which is executed once for each depth at which we wish to refocus the image, is to extract appropriate 2D slices **2030** of the 4D Fourier transform, and compute the inverse 2D Fourier transforms of the extracted slices, which are photographs focused at different depths **2040**. The inverse 2D Fourier transform, g(x, y), for a function G(k_x, k_y) is defined by the following equation:

$$g(x,y)=\iint G(k_x,k_y)\exp(2\pi\sqrt{-1}\cdot(xk_x+yk_y))dk_xdk_y. \quad (2)$$

The values on the extracted 2D slice are determined by the depth at which we want to refocus. Considering the conjugate plane (on the image-side of the lens) for the desired world focal plane, when the separation between this conjugate plane and the main lens is D and the separation between the microlens plane and the main lens is F, then the value of the extracted 2D slice at coordinates (k_x,k_y) is given by

$$G(k_x,k_y)=1/F^2\cdot M(k_x(1-D/F),k_y(1-D/F),k_xD/F,k_yD/F). \quad (3)$$

Using various approaches, artifacts that result from discretization, resampling and Fourier transformation are selectively ameliorated. In general signal-processing terms, when we sample a signal it is replicated periodically in the dual domain. When we reconstruct this sampled signal with convolution, it is multiplied in the dual domain by the Fourier transform of the convolution filter. In this regard, the original, central replica is isolated, eliminating all other replicas. A desirable filter is a 4D sinc function, sinc(s)sinc(t)sinc(u)sinc(v), where sinc(x)=sin(πx)/(πx); however, this function has infinite extent.

In various approaches, finite-extent filters are used with frequency-domain processing; such filters may exhibit defects, which are selectively mitigated. FIG. **21**A illustrate these defects with respect to a specific 1D filter, with corresponding discussion below directed to mitigation or such defects. FIG. **21**A represents a triangle filter approach implemented with in linear interpolation in 1D (or as the basis for a 4D quadrilinear filter). FIG. **21**B shows the Fourier transform of the triangle filter approach, which is not of unit value within the band-limit (see **2010**), and which gradually decays to smaller fractional values as the frequency increases. In addition, the filter is not truly band-limited, containing energy at frequencies outside the desired stop-band (**2020**).

The first defect described above leads to "rolloff artifacts," which can lead to a darkening of the borders of computed photographs. Decay in the filter's frequency spectrum with increasing frequency means that the spatial light field values, which are modulated by this spectrum, also "roll off" to fractional values towards the edges.

The second defect described above involves aliasing artifacts in computed photographs, which are related to energy at frequencies above the band-limit. The non-zero energy that extends beyond the band-limit means that the periodic replicas are not fully eliminated, leading to two kinds of aliasing. First, the replicas that appear parallel to the slicing plane appear as 2D replicas of the image encroaching on the borders of the final photograph. Second, the replicas positioned perpendicular to this plane are projected and summed onto the image plane, creating ghosting and loss of contrast.

In an example embodiment, correction for rolloff-type defects as described above is eliminated by multiplying the input light field by the reciprocal of the filter's inverse Fourier spectrum, to nullify the effect introduced during resampling. In this example embodiment, multiplication is performed

prior to taking the 4D Fourier transform in the pre-processing step of the algorithm. While it corrects rolloff error, pre-multiplication may accentuate the energy of the light field near its borders, maximizing the energy that folds back into the desired field of view as aliasing.

Three methods of suppressing aliasing artifacts—oversampling, superior filtering and zero-padding—are used individually or in combination in various example embodiments described below. Oversampling within the extracted 2D slice increases the replication period in the spatial domain. This means that less energy in the tails of the in-plane replicas will fall within the borders of the final photograph. Increasing the sampling rate in one domain leads to an increase in the field of view in the other domain. Aliasing energy from neighboring replicas falls into these outer regions, which is cropped away to isolate the original, central image of interest.

Another approach to mitigating aliasing is directed to a finite-extent filter that approximates a perfect spectrum (as would be exhibited via use of an ideal filter) as closely as possible. In an example embodiment, a 4D Kaiser-Bessel separable function, kb4(s,t,u,v)=kb(s)kb(t)kb(u)kb(v), is used as the filter, where

$$kb(x)=1/W\cdot I_0(P\cdot\sqrt{1-(2x/W)^2}) \quad (4)$$

In this equation, I_0 is the standard zero-order modified Kaiser-Bessel function of the first kind, W is the width of the desired filter, and P is a parameter that depends on W. In this example embodiment, W values are 5, 4.5, 4.0, 3.5, 3.0, 2.5, 2.0 and 1.5, and the P values are, respectively, 7.4302, 6.6291, 5.7567, 4.9107, 4.2054, 3.3800, 2.3934, and 1.9980. For general information regarding aliasing, and for specific information regarding approaches to mitigating aliasing in connection with one or more example embodiments of the present invention, reference may be made to Jackson J. I., Meyer C. H., Nishimura, D. G. and Macovski, A., 1997, Selection of convolution function for Fourier inversion using gridding. IEEE Transactions on Medical Imaging, 10, 3, 473-478, which is fully incorporated herein by reference. In one implementation, widths "W" of less than about 2.5 are implemented to achieve desirable image quality.

In another example embodiment, aliasing is mitigated by padding a light field with a small border of zero values before pre-multiplication and taking its Fourier transform. This pushes energy slightly further from the borders, and minimizes the amplification of aliasing energy by the pre-multiplication for rolloff correction.

FIG. **22** is a flow diagram showing an approach to refocusing in the frequency domain using various corrections described above, according to another example embodiment of the present invention. At block **2210**, a discrete 4D light field is received. In the pre-processing phase, which occurs once per input light field, block **2215** checks if aliasing reduction is desired, and if so executes block **2220**, which pads the light field with a small border (e.g., 5% of the width in that dimension) of zero values. At block **2225** a check is performed to determine whether rolloff correction is desired, and if so, the light field is modulated at block **2230** by the reciprocal of the Fourier transform of the resampling filter. In the final block of the pre-processing phase, the 4D Fourier transform of the light field is computed at block **2240**.

In the refocusing phase, which occurs once per desired focal depth, the process receives a desired focal depth of refocused image at block **2250**, such as through the direction of a user. At block **2260**, a check is performed to determine whether aliasing reduction is desired. If not, block **2270** extracts a 2D slice of the Fourier transform of the light field, with a desired 4D rsampling filter, where the trajectory of the 2D slice corresponds to the desired focal depth; and block **2275** computes an inverse 2D Fourier transform of the extracted slice and moves to block **2290**. If aliasing reduction was desired at block **2260**, the process moves to block **2280**, at which a 2D slice with desired 4D resampling filter and oversampling (e.g. 2× oversampling in each of the two dimensions) is extracted. At block **2283**, the slice's inverse 2D Fourier transform is computed, and the resulting image is cropped to the original size without oversampling at block **2286**, after which the process moves to block **2290**. At block **2290**, a check is performed to determine whether refocusing is complete. If not, another focal depth is chosen at block **2250** and the process proceeds as described above. If refocusing is complete, the process exits at block **2295**.

The asymptotic computational complexity of this frequency-domain algorithm is less than refocusing by explicitly summing rays as described for the alternate embodiment above. Assume that the input discrete light field has N samples in each of its four dimensions. Then the computational complexity of the algorithm that explicitly sums rays is O (N^4) for refocusing at each new depth. The computational complexity of the frequency-domain algorithm is O (N^2 log N) for refocusing at each new depth, dominated by the cost of the inverse 2D Fourier transform. However, the pre-processing step costs O (N^4 log N) for each new light field dataset.

In another example embodiment, the captured light rays are optically filtered. Although not limited to such applications, some examples of such filters are neutral density filters, color filters, polarizing filters. Any filter currently existing or that may be developed in the future may be used to effect a desired filtering of the rays of light. In one implementation, the light rays are optically filtered in groups or individually, so that each group or individual ray is filtered differently. In another implementation, a filtering is applied by the use of a spatially-varying filter attached to a main lens. In one example application, a gradient filter such as a neutral-density gradient filter is used to filter light. In another implementation, spatially varying filters are used in front of one or more of a ray sensor, a microlens array or a photosensor array. Referring to FIG. **1** by way of example, one or more such filters are selectively placed in front of one or more of the main lens **110**, microlens array **120** and photosensor array **130**.

In another example embodiment of the present invention, a computational component such as a processor is programmed to selectively choose rays to combine in computing output pixels in order to effect a desired net filtering for that pixel value. By way of example, consider embodiments involving an optical neutral gradient density filter at the main lens, each image of the lens aperture that appears under a microlens is weighted by the filter gradient across its extent. In one implementation, output images are computed by selecting a photosensor under each microlens at the point of the gradient that matches the desired level of neutral-density filtering for that output image pixel. For example, to produce an image in which every pixel is filtered to a large extent, every pixel value is set to the value of the photosensor under the corresponding microlens that is at the extreme end of the gradient corresponding to maximum filtering.

FIG. **2** is a data-flow diagram showing an approach to processing images in connection with other example embodiments of the present invention. An image sensor arrangement **210** collects image data using microlens/photosensor chip arrangement **212** in a manner similar, for example, to the microlens array **120** and photosensor array **130** shown in FIG. **1** and described above. The image sensor arrangement **210**

optionally includes an integrated processing circuit **214** bearing certain processing circuitry to prepare collected image data for transfer.

Sensor data created at the image sensor arrangement **210** is passed to a signal processor **220**. The signal processor includes a low-resolution image processor **222** and one or both of a compression processor **224** and a (light) ray-direction processor **226**; each of these processors is selectively implemented separately or functionally with a common processor, depending upon the application. Furthermore, each of the processors shown in FIG. **2** is selectively programmed with one or more processing functions described in connection with other figures or elsewhere herein. The signal processor **220** is optionally implemented in a common device or component with the image sensor arrangement **210**, such as on a common circuit and/or in a common image device.

The low-resolution image processor **222** uses sensor data received from the image sensor arrangement **210** to generate low-resolution image data, which is sent to a viewfinder display **230**. An input device **235**, such as a pushbutton on a camera or video camera, sends an image capture request to the signal processor **220** requesting, for example, the capture of a particular image displayed in the viewfinder display **230** and/or to initiate video imaging where so implemented.

In response to the image capture request or as otherwise directed, the signal processor **220** uses the sensor data captured by the image sensor arrangement **210** to generate processed sensor data. In some applications, the compression processor **224** is implemented to generate compressed raw data for transfer to a data storage arrangement **240** (e.g., memory). Such raw data is then selectively processed at the signal processor **220** and/or at an external computer **260** or other processing device, implementing ray-direction processing such as that implemented with the ray-direction processor **226**, which is discussed further below.

In certain applications, the ray-direction processor **226** is implemented to process the sensor data received at the signal processor **220** to rearrange the sensor data for use in generating focused and/or corrected image data. The ray-direction processor **226** uses one or both of sensor data received from the image sensor arrangement **210** and raw data sent to the data storage arrangement **240**. In these applications, the ray-direction processor **226** uses ray-mapping characteristics of the particular imaging device (e.g., camera, video camera or mobile telephone) in which the image sensor arrangement **210** is implemented to determine a rearrangement of light rays sensed with the microlens/photosensor chip **212**. Image data created with the ray-direction processor **226** is sent to the data storage arrangement **240** and/or to a communication link **250** for use in a variety of applications, such as in streaming image data or otherwise sending image data to a remote location.

In some applications, the integrated processing circuit **214** includes some or all of the processing functionality of the signal processor **220** by implementing, for example, a CMOS-type processor or other processor with appropriate functionality. For instance, the low-resolution image processor **222** is selectively included with the integrated processing circuit **214**, with the low-resolution image data sent directly to the viewfinder display **230** from the image sensor arrangement **210**. Similarly, the compression processor **224**, or functionality similar thereto, is selectively implemented with the integrated processing circuit **214**.

In some applications, computation of final images may be performed on the integrated processing circuit **214** (e.g. in some digital still cameras that output only final images). In other applications, the image sensor arrangement **210** may simply transmit the raw light ray data, or a compressed version of these data, to an external computational device, such as a desktop computer. Computation of final images from these data is then performed on the external device.

FIG. **3** is a flow diagram for a method for processing image data, according to another example embodiment of the present invention. At block **310**, image data is captured at a camera or other imaging device, using a main lens or a lens stack with a microlens/photosensor array such as that shown in FIG. **1**. If a preview image is desired at block **320**, the preview image is generated at block **330** using, for example, a viewfinder or other type of display. The preview image is displayed, for example, in a viewfinder of a camera or video camera, using a subset of the captured image data.

Raw data from the photosensor array is processed and compressed for use at block **340**. Light ray data is extracted from the processed and compressed data at block **350**. This extraction involves, for example, detecting a bundle or set of light rays incident upon a particular photosensor in the photosensor array. Ray mapping data is retrieved at block **360** for the imaging arrangement in which the image data is captured. The ray-mapping data and the extracted light ray data is used to synthesize a re-sorted image at block **370**. For example, the extraction, mapping and synthesis blocks **350-370** are selectively implemented by determining a bundle of light rays for a particular pixel of a scene for which the light rays were collected, and integrating the energy of the light rays to synthesize a value for the particular pixel. In some applications, the ray mapping data is used to trace light rays for each particular pixel through actual lenses used to acquire the image data. For example, by determining an appropriate set of rays to add together in order to focus upon a selected subject at a particular focal depth at block **370**, the rays can be re-sorted to arrive at a focused image. Similarly, by determining a proper arrangement of rays to correct for conditions such as lens aberrations in the imaging device, the rays can be re-sorted to generate an image relatively free of characteristics relating to the aberrations or other condition.

A variety of approaches are selectively used to generate preview images for camera-type and other applications. FIG. **4** is a process flow diagram for generating such a preview image, according to another example embodiment of the present invention. The approach shown in FIG. **4** and discussed below may be implemented, for example, in connection with the generation of a preview image at block **330** of FIG. **3**.

A preview instruction with raw sensor image data is received at block **410**. At block **420**, a center pixel is selected from each microlens image in the raw sensor image data. The selected center pixels are collected to form a high depth-of-field image at block **430**. At block **440**, the high depth-of-field image is downsampled to a resolution amenable for use in a viewfinder display. Referring to FIG. **2** by way of example, such downsampling is selectively performed at one or more of the image sensor arrangement **210** or the signal processor **220**. The generated preview image data is sent to the viewfinder display at block **450**, and at block **460**, the viewfinder displays an image with the preview image data.

FIG. **5** is a process flow diagram for processing and compressing image data, according to another example embodiment of the present invention. The approach shown in FIG. **5** and discussed below may be implemented, for example, in connection with the processing and compressing of image data at block **340** of FIG. **3**. When implemented with an arrangement as shown in FIG. **2**, the approach shown in FIG. **5** may, for example, be implemented at one or both of the image sensor arrangement **210** and the signal processor **220**.

At block **510**, raw image data is received from a sensor array. If coloring is desired at block **520**, color filter array values are demosiaced at block **530** to produce color at the sensors. If rectification and alignment is desired at block **540**, microlens images are rectified and aligned with the photosensor array at block **550**. If interpolation is desired at block **560**, pixel values are interpolated at block **570** to an integral number of pixels associated with each microlens. At block **580**, the processed raw image data is compressed and presented for synthesis processing (e.g., to form a refocused and/or corrected image).

FIG. **6** is a process flow diagram for image synthesis, according to another example embodiment of the present invention. The approach shown in FIG. **6** and discussed below may be implemented, for example, in connection with the image synthesis approach shown at block **370** of FIG. **3** and discussed further below.

At block **610**, raw image data is received from a photosensor array. If refocusing is desired at block **620**, image data is refocused at block **630** using, e.g., approaches discussed herein for selectively re-sorting light represented by the raw image data. If image correction is desired at block **640**, image data is corrected at block **650**. In various applications, image correction at block **650** is carried out before or concurrently with refocusing at block **630** in applications where both refocusing and image correction is desirable. A resultant image is generated at block **660** using processed image data including refocused and corrected data, where applicable.

FIG. **7**A is a process flow diagram for image refocusing with a lens arrangement, according to another example embodiment of the present invention. The approach shown in FIG. **7** and discussed below may be implemented, for example, in connection with the refocusing of image data at block **630** in FIG. **6**.

At block **710**, a virtual focal plane for refocusing an image portion is selected. At block **720**, a pixel of a virtual image for the virtual focal plane is selected. If correction (e.g., for lens aberration) is desired at block **730**, the value of a virtual light ray (or virtual set of light rays) passing between the selected pixel and each particular lens position is calculated at block **740**. In one application, this calculation is facilitated by computing the conjugate light ray that would fall upon the selected pixel and tracing that ray through the path in the lens arrangement.

At block **750**, the sum of light ray (or virtual set of light ray) values for each lens position for the particular focal plane are added to determine a total value for the selected pixel. In some applications, the sum added at block **750** is a weighted sum, wherein certain light rays (or set of light rays) are given greater weight than others. If there are additional pixels for refocusing at block **760**, another pixel is selected at block **720** and the process continues until no further pixels are desirably refocused. After the pixels have been refocused, the pixel data is combined at block **770** to generate a refocused virtual image at the virtual focal plane selected in block **710**. The refocusing approaches involving some or all of blocks **720**, **730**, **740** and **750** in FIG. **7** are carried out via more specific functions for a variety of applications.

The sensor data processing circuitry implemented with one or more example embodiments described herein includes one or more microprocessors, Application-Specific Integrated Circuits (ASICs), digital signal processors (DSPs), and/or programmable gate arrays (for example, field-programmable gate arrays (FPGAs)), depending upon the implementation. In this regard, sensor data processing circuitry may be any type or form of circuitry whether now known or later developed. For example, the sensor data processing circuitry may include a single component or a multiplicity of components (microprocessors, ASICs and DSPs), either active and/or passive, which are coupled together to implement, provide and/or perform a desired operation/function/application.

In various applications, the sensor data processing circuitry performs or executes one or more applications, routines, programs and/or data structures that implement particular methods, tasks or operations described and/or illustrated herein. The functionality of the applications, routines or programs are selectively combined or distributed in certain applications. In some applications, the applications, routines or programs are implemented by sensor (or other) data processing circuitry using one or more of a variety of programming languages, whether now known or later developed. Such programming languages include, for example, FORTRAN, C, C++, Java and BASIC, whether compiled or uncompiled code, selectively implemented in connection with one or more aspects of the present invention.

The various embodiments described above are provided by way of illustration only and should not be construed to limit the invention. Based on the above discussion and illustrations, those skilled in the art will readily recognize that various modifications and changes may be made to the present invention without strictly following the exemplary embodiments and applications illustrated and described herein. For instance, such changes may include implementing the various optical imaging applications and devices in different types of applications, increasing or decreasing the number of rays collected per pixel (or other selected image area), or implementing different algorithms and/or equations than the examples described to assemble or otherwise process image data. Other changes may involve using coordinate representations other than or in addition to Cartesian coordinates, such as polar coordinates. Such modifications and changes do not depart from the true spirit and scope of the present invention.

What is claimed is:

1. A method for digitally imaging a scene, the method comprising: generating photosensor image data in response to detecting light rays incident on a physical focal plane using a photosensor array, having a plurality of photosensors, wherein the plurality of photosensors simultaneously detect the light rays from the scene that are incident on a microlens array and passed to different locations on the physical focal plane; determining an angle of incidence of the light rays incident at different locations on the physical focal plane using the photosensor image data; and generating a virtual output image which corresponds to the scene by selectively combining the photosensor image data based on the angle of incidence of the light rays, such that at least a selected portion of the image is refocused via the selective combination of photosensor image data representing different ones of the light rays.

2. The method of claim **1**, wherein generating a virtual an output image comprises forming an image having at least a portion thereof focused at a virtual focal plane that is different than the physical focal plane.

3. The method of claim **2**, wherein generating a virtual output image further comprises:

determining a set of light rays from the detected light rays that make up the at least a portion of the image focused at a virtual focal plane that is different than the physical focal plane; and

combining the determined set of light rays to form the portion of the output image focused at the virtual focal plane.

4. The method of claim **1**, wherein combining the determined set of light rays further comprises correcting for conditions of optics used in detecting the light.

5. The method of claim **1**, wherein combining the determined set of light rays further comprises correcting for lens aberration.

6. A digital imaging system for generating a virtual image of a scene, wherein the virtual image includes a plurality of pixels, the system comprising:

a photosensor array, having a plurality of photosensors, configured to detect light including a plurality of light rays from the scene, wherein each photosensor, in response to detecting the light incident thereon, generates light data, the photosensor array further configured to detect a set of the plurality of light rays that concurrently arrive at the particular portion of the physical focal plane at different angles of incidence;

an optics arrangement, having a physical focus, configured to direct light rays from the scene to the photosensor array via a physical focal plane; and

processing circuitry to compute a pixel value of each pixel of the virtual image by combining light data from selected photosensors based on angles of incidence of the light rays detected by each photosensor, as characterized by the location of each photosensor relative to the physical focal plane, the virtual image having a virtual focus and a virtual focal plane that are respectively different from the physical focus and the physical focal plane.

7. The system of claim **6**, wherein the optics arrangement includes a microlens array, the microlens array including a plurality of microlenses, each microlens being configured to separate light rays incident upon the microlens and to direct the separated rays to a predetermined plurality of photosensors in the photosensor array.

8. The system of claim **7**, wherein the processing circuitry further determines the angles of incidence of light upon each photosensor using a position of each photosensor relative to the microlens.

9. The system of claim **6**, wherein the processing circuitry further determines a focus depth of a subject in the scene from which the light rays emanate, and uses the focus depth and the angles of incidence to compute the virtual image focused upon a virtual focal plane that is different from the physical focal plane.

10. The system of claim **6**, wherein the processing circuitry is further configured to:

determine an angle of incidence of the detected light rays as characterized by the location of each photosensor detecting the light, and

map a path of the detected light rays through the system using the angles of incidence of the detected light rays.

11. The system of claim **6**, wherein the optics arrangement includes a microlens array having a plurality of microlenses, each microlens being associated with a plurality of the photosensors and configured to direct light rays from the optics arrangement onto the associated plurality of photosensors.

12. The system of claim **6**, wherein the processing circuitry is configured to combine the light data from selected photosensors based on data indicative of a virtual focal plane and the angles of incidence of the light rays detected by each photosensor, to generate a virtual image of the scene having the virtual focus at the virtual focal plane.

13. The system of claim **6**, wherein:

the optics arrangement is configured to project light from the scene onto the physical focal plane with a physical depth of field, and

the processing circuitry is configured to generate the virtual image of the scene by combining light data from selected photosensors, based on a selected virtual depth of field and the angles of incidence of the light rays detected by each photosensor, to generate a virtual image of the scene having the selected virtual depth of field, the selected virtual depth of field being different from the physical depth of field.

14. The system of claim **6**, wherein:

the optics arrangement is configured to project light from the scene onto the physical focal plane with a physical depth of field, and

the processing circuitry is configured to generate the virtual image of the scene by combining light data from selected photosensors, based on a selected virtual depth of field and the angles of incidence of the light rays detected by each photosensor, to provide a virtual image of the scene having the selected virtual depth of field, the selected virtual depth of field being greater than the physical depth of field.

* * * * *

UNITED STATES PATENT AND TRADEMARK OFFICE

CERTIFICATE OF CORRECTION

PATENT NO. : 7,936,392 B2
APPLICATION NO. : 11/576438
DATED : May 3, 2011
INVENTOR(S) : Ng et al.

It is certified that error appears in the above-identified patent and that said Letters Patent is hereby corrected as shown below:

Column 25, line 1 and line 4, the claim reference numeral "1", each occurrence, should read -3-.

Signed and Sealed this
First Day of May, 2012

David J. Kappos

David J. Kappos
Director of the United States Patent and Trademark Office