

HE-SIG-B Structure

Date: 2015-07-11

Authors:

Name	Affiliation	Address	Phone	Email
Joonsuk Kim	Apple	1 Infinite Loop Cupertino, CA 95014 USA		joonsuk@apple.com
Aon Mujtaba				mujtaba@apple.com
Guoqing Li				guoqing_li@apple.com
Eric Wong				ericwong@apple.com
Chris Hartman				chartman@apple.com
Robert Stacey	Intel	2111 NE 25th Ave, Hillsboro OR 97124, USA	+1-503-724-893	robert.stacey@intel.com
Po-Kai Huang				po-kai.huang@intel.com
Qinghua Li				qinghua.li@intel.com
Xiaogang Chen				xiaogang.c.chen@intel.com
Chitto Ghosh				chittabrata.ghosh@intel.com
Rongzhen Yang				rongzhen.yang@intel.com
Laurent cariou				laurent.cariou@intel.com

Authors (continued)

Name	Affiliation	Address	Phone	Email
Yakun Sun	Marvell	5488 Marvell Lane, Santa Clara, CA, 95054	408-222-2500	yakunsun@marvell.com
Hongyuan Zhang				hongyuan@marvell.com
Lei Wang				Leileiw@marvell.com
Liwen Chu				liwenchu@marvell.com
Jinjing Jiang				jinjing@marvell.com
Yan Zhang				yzhang@marvell.com
Rui Cao				ruicao@marvell.com
Sudhir Srinivasa				sudhirs@marvell.com
Saga Tamhane				sagar@marvell.com
Mao Yu				my@marvell..com
Edward Au	Broadcom			edwardau@marvell.com
Hui-Ling Lou				hlou@marvell.com
Ron Porat				rporat@broadcom.com
Matthew Fischer				mfischer@broadcom.com
Sriram Venkateswaran				
Leo Montreuil				
Andrew Blanksby				
Vinko Erceg				

Authors (continued)

Name	Affiliation	Address	Phone	Email
Peter Loc	Huawei			peterloc@iwirelesstech.com
Le Liu		F1-17, Huawei Base, Bantian, Shenzhen	+86-18601656691	liule@huawei.com
Jun Luo		5B-N8, No.2222 Xinqinqiao Road, Pudong, Shanghai		jun.l@huawei.com
Yi Luo		F1-17, Huawei Base, Bantian, Shenzhen	+86-18665891036	Roy.luoyi@huawei.com
Yingpei Lin		5B-N8, No.2222 Xinqinqiao Road, Pudong, Shanghai		linyngpei@huawei.com
Jiyong Pang		5B-N8, No.2222 Xinqinqiao Road, Pudong, Shanghai		pangjiyong@huawei.com
Zhigang Rong		10180 Telesis Court, Suite 365, San Diego, CA 92121 NA		zhigang.rong@huawei.com
Rob Sun		303 Terry Fox, Suite 400 Kanata, Ottawa, Canada		Rob.Sun@huawei.com
David X. Yang		F1-17, Huawei Base, Bantian, Shenzhen		david.yangxun@huawei.com
Yunsong Yang		10180 Telesis Court, Suite 365, San Diego, CA 92121 NA		yangyunsong@huawei.com
Zhou Lan		F1-17, Huawei Base, Bantian, SHenzhen	+86-18565826350	Lanzhou1@huawei.com
Junghoon Suh		303 Terry Fox, Suite 400 Kanata, Ottawa, Canada		Junghoon.Suh@huawei.com
Jiayin Zhang		5B-N8, No.2222 Xinqinqiao Road, Pudong, Shanghai	+86-18601656691	zhangjiayin@huawei.com

Authors (continued)

Name	Affiliation	Address	Phone	Email
Albert Van Zelst	Qualcomm	Straatweg 66-S Breukelen, 3621 BR Netherlands		allert@qti.qualcomm.com
Alfred Asterjadhhi		5775 Morehouse Dr. San Diego, CA, USA		aasterja@qti.qualcomm.com
Bin Tian		5775 Morehouse Dr. San Diego, CA, USA		btian@qti.qualcomm.com
Carlos Aldana		1700 Technology Drive San Jose, CA 95110, USA		caldana@qca.qualcomm.com
George Cherian		5775 Morehouse Dr. San Diego, CA, USA		gcherian@qti.qualcomm.com
Gwendolyn Barriac		5775 Morehouse Dr. San Diego, CA, USA		gbarriac@qti.qualcomm.com
Hemanth Sampath		5775 Morehouse Dr. San Diego, CA, USA		hsampath@qti.qualcomm.com
Menzo Wentink		Straatweg 66-S Breukelen, 3621 BR Netherlands		mwentink@qti.qualcomm.com
Richard Van Nee		Straatweg 66-S Breukelen, 3621 BR Netherlands		rvannee@qti.qualcomm.com
Rolf De Vegt		1700 Technology Drive San Jose, CA 95110, USA		rolfv@qca.qualcomm.com
Sameer Vermani		5775 Morehouse Dr. San Diego, CA, USA		svverman@qti.qualcomm.com
Simone Merlin		5775 Morehouse Dr. San Diego, CA, USA		smerlin@qti.qualcomm.com
Tevfik Yucek		1700 Technology Drive San Jose, CA 95110, USA		tyucek@qca.qualcomm.com
VK Jones		1700 Technology Drive San Jose, CA 95110, USA		vkjones@qca.qualcomm.com
Youhan Kim		1700 Technology Drive San Jose, CA 95110, USA		youhank@qca.qualcomm.com

Authors (continued)

Name	Affiliation	Address	Phone	Email
Kiseon Ryu	LG Electronics	19, Yangjae-daero 11gil, Seocho-gu, Seoul 137- 130, Korea		kiseon.ryu@lge.com
Jinyoung Chun				jiny.chun@lge.com
Jinsoo Choi				js.choi@lge.com
Jeongki Kim				jeongki.kim@lge.com
Giwon Park				giwon.park@lge.com
Dongguk Lim				dongguk.lim@lge.com
Suhwook Kim				suhwook.kim@lge.com
Eunsung Park				esung.park@lge.com
HanGyu Cho				hg.cho@lge.com
Thomas Derham	Orange			thomas.derham@orange.com
Brian Hart	Cisco Systems	170 W Tasman Dr, San Jose, CA 95134		brianh@cisco.com
Pooya Monajemi				pmonajem@cisco.com

Authors (continued)

Name	Affiliation	Address	Phone	Email
Fei Tong	Samsung	Innovation Park, Cambridge CB4 0DS (U.K.)	+44 1223 434633	f.tong@samsung.com
Hyunjeong Kang		Maetan 3-dong; Yongtong-Gu Suwon; South Korea	+82-31-279-9028	hyunjeong.kang@samsung.com
Kaushik Josiam		1301, E. Lookout Dr, Richardson TX 75070	(972) 761 7437	k.josiam@samsung.com
Mark Rison		Innovation Park, Cambridge CB4 0DS (U.K.)	+44 1223 434600	m.rison@samsung.com
Rakesh Taori		1301, E. Lookout Dr, Richardson TX 75070	(972) 761 7470	rakesh.taori@samsung.com
Sanghyun Chang		Maetan 3-dong; Yongtong-Gu Suwon; South Korea	+82-10-8864-1751	s29.chang@samsung.com
Yasushi Takatori	NTT	1-1 Hikari-no-oka, Yokosuka, Kanagawa 239-0847 Japan		takatori.yasushi@lab.ntt.co.jp
Yasuhiko Inoue				inoue.yasuhiko@lab.ntt.co.jp
Yusuke Asai				asai.yusuke@lab.ntt.co.jp
Koichi Ishihara				ishihara.koichi@lab.ntt.co.jp
Akira Kishida				kishida.akira@lab.ntt.co.jp
Akira Yamada	NTT DOCOMO	3-6, Hikinooka, Yokosuka- shi, Kanagawa, 239-8536, Japan		yamadaakira@nttdocomo.com
Fujio Watanabe		3240 Hillview Ave, Palo Alto, CA 94304		watanabe@docomoinnovations.com
Haralabos Papadopoulos				hpapadopoulos@docomoinnovations.com

Authors (continued)

Name	Affiliation	Address	Phone	Email
James Yee	Mediatek	No. 1 Dusing 1 st Road, Hsinchu, Taiwan	+886-3-567-0766	james.yee@mediatek.com
Alan Jauh				alan.jauh@mediatek.com
Chingwa Hu				chingwa.yu@mediatek.com
Frank Hsu				frank.hsu@mediatek.com
Thomas Pare	Mediatek USA	2860 Junction Ave, San Jose, CA 95134, USA	+1-408-526-1899	thomas.pare@mediatek.com
ChaoChun Wang				chaochun.wang@mediatek.com
James Wang				james.wang@mediatek.com
Jianhan Liu				Jianhan.Liu@mediatek.com
Tianyu Wu				tianyu.wu@mediatek.com
Russell Huang				russell.huang@mediatek.com
Bo Sun	ZTE	#9 Wuxing duan, Xifeng Rd, Xi'an, China		Sub.bol@zte.com.cn
Kaiying Lv				lv.kaiying@zte.com.cn
Yonggang Fang				yfang@zttex.com
Ke Yao				Yao.ke5@zte.com.cn
Weimin Xing				Xing.weimin@zte.com.cn

Discussion on HE-SIG B Structure

- The current SFD [1] defines HE-SIG-B as follows:
 - Downlink HE MU PPDU shall include HE-SIG-B field, and the number of OFDM symbols of HE-SIG-B field is variable.
 - NOTE—The HE-SIG-B field includes information required to interpret HE MU PPDU, and detail is TBD.
 - HE-SIG-B shall use a DFT period of 3.2 μ s and subcarrier spacing of 312.5 kHz.
- Background
 - The structure of HE-SIG-B has to be defined with following details
 - How to sort the contents in sequence
 - Encoding sequence is discussed in another presentation [4]
 - For wider bandwidth than 20MHz, how to arrange over frequency bands
 - What information to be signaled
 - In this presentation, we propose a HE-SIG-B structure

Topic 1: Duplicate or Non-duplicate

- HE SIG-A is proposed to have 2 OFDM symbol [2]
 - HE SIG-A is duplicated over operating bandwidth, like 11n/ac
 - HE SIG-B exists only for DL-MU
- For MU, contents in HE SIG-A and HE SIG-B can be separated as follows:
 - HE SIG-A can deliver the information about the PPDU to all STAs
 - STAs do not know about the operating bandwidth yet; so better to be duplicated
 - HE SIG-B sends the information for designated receiving STAs for MU operation
- The remaining question is whether we have duplicated part in HE SIG-B if there is any
 - We may not need another duplicated portion in HE SIG-B, given that HE SIG-A has 48~52 information bits
 - Unless we are lack of number of bits in HE SIG-A to be fully duplicated, we do not need to duplicate any OFDM symbol of HE SIG-B over full bandwidth


Topic 2: Common & User-specific

- There are some information, which needs to be decoded by a group of STAs, as common information for DL-MU
 - For example, Resource Unit (RU) allocation needs to be decoded, not by only one specific STA, but by a group of STAs
 - A group includes TBD number of STAs. It can be all or a subset of designated receiving STAs.
 - Those information may not be necessary for the other group of STAs when it is signaled for a subset of STAs
- Common information for a group of receiving STAs can be signaled at once
 - These information may need to be located up front in HE SIG-B, before user-specific information (MCS, Nsts etc. for each user)
 - If the group is a subset of STAs, those information is better to be aligned with the designated group of receiving STAs, so that decoding error does not affect for other group of receiving STAs, in terms of sub-bands
 - We can minimize the impact of OBSS interference, which may occupy some of sub-bands

Common Field in SIG-B


- The information for non-designated STAs to avoid the further unnecessary decoding process can be included in L-SIG & HE SIG-A
- HE SIG-B includes control signaling for recipients of DL-MU PPDU
 - The common field in HE SIG-B has the information which is needed for recipients in common
 - E.g., RU allocation is common information to all or sub-set of recipients
 - The user-specific field in HE SIG-B has the information for a specific user, which is not needed for other users

User-specific Field in HE SIG-B



- User-specific field consists of multiple sub-fields
- Per-STA information, one specific subfield may deliver some information for a specific STA, which may not be useful for some other STAs
 - i.e., Information is isolated between designated receiving STAs
- The boundary between common & user-specific field is in the bit-level, not OFDM symbol boundary

* 20MHz is an example



- Information in SIG-B common field is shared between users within the same sub-band channel
 - E.g., Resource Unit Allocation
- Common/User specific signaling applies to the same sub-band channel
 - In this way, signaling in corrupted sub-band channel does not affect on decoding the PPDU in another sub-band channel
 - We can isolate the signaling to operate the OFDMA PPDU, so that partial interference does not corrupt the whole OFDMA PPDU reception

RU Allocation

- In MU (OFDMA or MIMO (SDMA)) operation, there are many combinations of RUs per bandwidth. Possible RUs [3], depending on the size of operating bandwidth, are
 - 26, 52, 106, 242, 484, 996 and 996 x 2 data tones
- Receiving STAs need to know which RU needs to be decoded for themselves in HE SIG-B
- These RU allocation mapping is better to be up front, at common field, in HE SIG-B, because
 - Signaling for RU allocation for all receiving STAs can save the overhead, than individual signaling per STA, and
 - Receiver can prepare for decoding accordingly with early identified RU structure
- We propose to include RU allocation information in the common field of HE SIG-B
 - How to signal RU allocation is TBD

Summary

- We propose the HE signal field structure as follows
 - HE SIG-B does not have any OFDM symbol that is fully duplicated over the operating BW
 - Some part of an OFDM symbol may be duplicated if necessary
 - In HE SIG-B, which exists for DL-MU PPDU
 - We need to signal the control information for designated receiving STAs
 - For DL-MU, we need following information
 - Resource allocation (OFDMA or MU-MIMO)
 - Per-STA information, e.g.,
 - STA-ID
 - MCS
 - Nsts
 - We propose to have two fields in SIG-B
 - Common field, where RU allocation info is included
 - User-specific field, where per-STA info belongs to

Straw poll #1

- Do you agree to add to 11ax SFD that HE SIG-B does NOT have any OFDM symbol duplicated in each 20 MHz of the PPDU bandwidth?

Straw poll #2

- Do you agree to add to 11ax SFD that HE SIG-B has the common field followed by the user-specific field, where
 - The common field includes the information for all of designated STAs to receive the PPDU in corresponding bandwidth
 - The user-specific field consists of multiple sub-fields that do not belong to the common field, where one or multiple of those sub-fields are for each designated receiving STA
 - The boundary between the common & the user-specific field is in the bit-level, not the OFDM symbol-level

Straw poll #3

- Do you agree to add to 11ax SFD that the common field in HE SIG-B contains Resource Unit (RU) allocation?

Reference

- [1] 11-15-0132-06-00ax-spec-framework
- [2] 11-15-0822-00-00ax-HE-SIG-A-Structure
- [3] 11-15-0330-04-00ax-OFDMA-numerology-and-structure
- [4] 11-15-0873-00-00ax-HE-SIG-B-encoding-structure