



US008041881B2

(12) **United States Patent**
Rajan et al.

(10) **Patent No.:** **US 8,041,881 B2**
(45) **Date of Patent:** **Oct. 18, 2011**

(54) **MEMORY DEVICE WITH EMULATED CHARACTERISTICS**

(75) Inventors: **Suresh Natarajan Rajan**, San Jose, CA (US); **Keith R. Schakel**, San Jose, CA (US); **Michael John Sebastian Smith**, Palo Alto, CA (US); **David T. Wang**, San Jose, CA (US); **Frederick Daniel Weber**, San Jose, CA (US)

(73) Assignee: **Google Inc.**, Mountain View, CA (US)

(*) Notice: Subject to any disclaimer, the term of this patent is extended or adjusted under 35 U.S.C. 154(b) by 35 days.

(21) Appl. No.: **11/762,010**

(22) Filed: **Jun. 12, 2007**

(65) **Prior Publication Data**

US 2008/0056014 A1 Mar. 6, 2008

Related U.S. Application Data

(63) Continuation-in-part of application No. 11/461,420, filed on Jul. 31, 2006.

(51) **Int. Cl.**
G06F 12/00 (2006.01)

(52) **U.S. Cl.** **711/103; 711/104**

(58) **Field of Classification Search** **711/103, 711/104, 105, 110**

See application file for complete search history.

(56) **References Cited**

U.S. PATENT DOCUMENTS

3,800,292 A 3/1974 Curley et al.
4,069,452 A 1/1978 Conway et al.

4,323,965 A	4/1982	Johnson et al.	
4,334,307 A	6/1982	Bourgeois et al.	
4,345,319 A	8/1982	Bernardini et al.	
4,392,212 A	7/1983	Miyasaka et al.	365/230
4,525,921 A	7/1985	Carson et al.	
4,566,082 A	1/1986	Anderson	
4,592,019 A	5/1986	Huang et al.	365/78
4,646,128 A	2/1987	Carson et al.	
4,698,748 A	10/1987	Juzswik et al.	364/200
4,706,166 A	11/1987	Go	
4,710,903 A	12/1987	Hereth et al.	365/194
4,764,846 A	8/1988	Go	
4,780,843 A	10/1988	Tietjen	364/900
4,794,597 A	12/1988	Ooba et al.	
4,796,232 A	1/1989	House	365/189
4,841,440 A	6/1989	Yonezu et al.	364/200
4,862,347 A	8/1989	Rudy	
4,884,237 A	11/1989	Mueller et al.	365/63

(Continued)

FOREIGN PATENT DOCUMENTS

DE 102004051345 5/2006

(Continued)

OTHER PUBLICATIONS

Kellerbauer "Die Schnelle Million," with translation, "The quick million."

(Continued)


Primary Examiner — Vu A Le

(74) *Attorney, Agent, or Firm* — Fish & Richardson P.C.

(57) **ABSTRACT**

A memory subsystem is provided including an interface circuit adapted for communication with a system and a majority of address or control signals of a first number of memory circuits. The interface circuit includes emulation logic for emulating at least one memory circuit of a second number.

25 Claims, 18 Drawing Sheets



U.S. PATENT DOCUMENTS

4,887,240 A	12/1989	Garverick et al.	361/222	5,752,045 A	5/1998	Chen	395/750
4,888,687 A	12/1989	Allison et al.		5,757,703 A	5/1998	Merritt et al.	365/189
4,899,107 A	2/1990	Corbett et al.	324/158	5,760,478 A	6/1998	Bozso et al.	
4,912,678 A	3/1990	Mashiko		5,761,703 A	6/1998	Bolyn	711/106
4,922,451 A	5/1990	Lo et al.		5,781,766 A	7/1998	Davis	395/552
4,935,734 A	6/1990	Austin	340/825.83	5,787,457 A	7/1998	Miller et al.	
4,937,791 A	6/1990	Steele et al.		5,798,961 A	8/1998	Heyden et al.	365/52
4,956,694 A	9/1990	Eide		5,802,010 A	9/1998	Zagar et al.	365/233
4,982,265 A	1/1991	Watanabe et al.		5,802,395 A	9/1998	Connolly et al.	
4,983,533 A	1/1991	Go		5,802,555 A	9/1998	Shigeeda	711/106
5,025,364 A	6/1991	Zellmer		5,812,488 A	9/1998	Zagar et al.	365/233
5,072,424 A	12/1991	Brent et al.	365/189	5,831,833 A	11/1998	Shirakawa et al.	
5,083,266 A	1/1992	Watanabe	395/275	5,831,931 A	11/1998	Manning	365/233
5,104,820 A	4/1992	Go et al.		5,831,932 A	11/1998	Merritt et al.	365/233
5,220,672 A	6/1993	Nakao et al.	395/750	5,834,838 A	11/1998	Anderson	257/697
5,241,266 A	8/1993	Ahmad et al.	324/158	5,835,435 A	11/1998	Bogin et al.	365/227
5,252,807 A	10/1993	Chizinsky	219/390	5,838,165 A	11/1998	Chatter	
5,257,233 A	10/1993	Schaefer	365/227	5,838,177 A	11/1998	Keeth	327/108
5,278,796 A	1/1994	Tillinghast et al.	365/211	5,841,580 A	11/1998	Farmwald et al.	365/194
5,282,177 A	1/1994	McLaury	365/230	5,843,799 A	12/1998	Hsu et al.	438/6
5,332,922 A	7/1994	Oguchi et al.	257/723	5,843,807 A	12/1998	Burns	
5,347,428 A	9/1994	Carson et al.		5,845,108 A	12/1998	Yoo et al.	395/551
5,384,745 A	1/1995	Konishi et al.	365/230.03	5,850,368 A	12/1998	Ong et al.	365/238
5,388,265 A	2/1995	Volk	395/750	5,859,792 A	1/1999	Rondeau et al.	365/52
5,390,334 A	2/1995	Harrison		5,860,106 A	1/1999	Domen et al.	711/137
5,408,190 A	4/1995	Wood et al.	324/765	5,870,347 A	2/1999	Keeth et al.	365/230
5,432,729 A	7/1995	Carson et al.	365/63	5,870,350 A	2/1999	Bertin et al.	
5,448,511 A	9/1995	Paurus et al.	365/52	5,872,907 A	2/1999	Griess et al.	
5,453,434 A	9/1995	Albaugh et al.	514/397	5,875,142 A	2/1999	Chevallier	365/212
5,467,455 A	11/1995	Gay et al.	395/281	5,878,279 A	3/1999	Athenes	
5,483,497 A	1/1996	Mochizuki et al.		5,884,088 A	3/1999	Kardach et al.	395/750
5,498,886 A	3/1996	Hsu et al.	257/213	5,901,105 A	5/1999	Ong et al.	365/230
5,502,333 A	3/1996	Bertin et al.		5,903,500 A	5/1999	Tsang et al.	365/189.05
5,502,667 A	3/1996	Bertin et al.	365/51	5,905,688 A	5/1999	Park	365/227
5,513,135 A	4/1996	Dell et al.		5,907,512 A	5/1999	Parkinson et al.	365/195
5,513,339 A	4/1996	Agrawal et al.		5,915,105 A	6/1999	Farmwald et al.	395/309
5,519,832 A	5/1996	Warchol		5,915,167 A	6/1999	Leedy	
5,526,320 A	6/1996	Zagar et al.	365/233	5,917,758 A	6/1999	Keeth	365/189.05
5,530,836 A	6/1996	Busch et al.	395/477	5,923,611 A	7/1999	Ryan	365/233
5,550,781 A	8/1996	Sugawara et al.		5,924,111 A	7/1999	Huang et al.	
5,559,990 A	9/1996	Cheng et al.	395/484	5,926,435 A	7/1999	Park et al.	365/233
5,561,622 A	10/1996	Bertin et al.	365/51	5,929,650 A	7/1999	Pappert et al.	324/763
5,563,086 A	10/1996	Bertin et al.		5,943,254 A	8/1999	Bakeman, Jr. et al.	365/72
5,566,344 A	10/1996	Hall et al.	395/800	5,946,265 A	8/1999	Cowles	365/233
5,581,498 A	12/1996	Ludwig et al.	365/63	5,949,254 A	9/1999	Keeth	326/87
5,581,779 A	12/1996	Hall et al.	395/800	5,953,215 A	9/1999	Karabatsos	361/767
5,590,071 A	12/1996	Kolor et al.	365/149	5,953,263 A	9/1999	Farmwald et al.	365/194
5,598,376 A	1/1997	Merritt et al.	365/230	5,954,804 A	9/1999	Farmwald et al.	710/36
5,604,714 A	2/1997	Manning et al.	365/230	5,956,233 A	9/1999	Yew et al.	361/760
5,606,710 A	2/1997	Hall et al.	395/800	5,962,435 A	10/1999	Mao et al.	514/63
5,608,262 A	3/1997	Degani et al.		5,963,429 A	10/1999	Chen	
5,610,864 A	3/1997	Manning	365/193	5,963,463 A	10/1999	Rondeau et al.	365/52
5,623,686 A	4/1997	Hall et al.	395/800	5,963,464 A	10/1999	Dell et al.	365/52
5,627,791 A	5/1997	Wright et al.	365/222	5,963,504 A	10/1999	Manning	365/233
5,640,337 A	6/1997	Huang et al.	364/578	5,966,724 A	10/1999	Ryan	711/105
5,640,364 A	6/1997	Merritt et al.	365/233	5,966,727 A	10/1999	Nishino	711/127
5,652,724 A	7/1997	Manning	365/189	5,969,996 A	10/1999	Muranaka et al.	365/189.01
5,654,204 A	8/1997	Anderson	438/15	5,973,392 A	10/1999	Senba et al.	
5,661,677 A	8/1997	Rondeau et al.	365/63	5,995,424 A	11/1999	Lawrence et al.	
5,661,695 A	8/1997	Zagar et al.	365/233	5,995,443 A	11/1999	Farmwald et al.	365/233
5,668,773 A	9/1997	Zagar et al.	365/233	6,001,671 A	12/1999	Fjelstad	
5,675,549 A	10/1997	Ong et al.	365/233	6,002,613 A	12/1999	Cloud et al.	365/189
5,680,342 A	10/1997	Frankeny	365/52	6,002,627 A	12/1999	Chevallier	365/212
5,682,354 A	10/1997	Manning	365/233	6,014,339 A	1/2000	Kobayashi et al.	365/233
5,692,121 A	11/1997	Bozso et al.		6,016,282 A	1/2000	Keeth	365/233
5,692,202 A	11/1997	Kardach et al.	395/750	6,026,050 A	2/2000	Baker et al.	365/233
5,696,732 A	12/1997	Zagar et al.	365/233	6,029,250 A	2/2000	Keeth	713/400
5,702,984 A	12/1997	Bertin et al.		6,032,214 A	2/2000	Farmwald et al.	710/129
5,703,813 A	12/1997	Manning et al.	365/189	6,032,215 A	2/2000	Farmwald et al.	710/129
5,706,247 A	1/1998	Merritt et al.	365/233	6,034,916 A	3/2000	Lee	365/233
RE35,733 E	2/1998	Hernandez et al.		6,034,918 A	3/2000	Farmwald et al.	365/233
5,717,654 A	2/1998	Manning	365/233	6,035,365 A	3/2000	Farmwald et al.	710/129
5,721,859 A	2/1998	Manning	397/421	6,038,195 A	3/2000	Farmwald et al.	365/233
5,724,288 A	3/1998	Cloud et al.	365/193	6,038,673 A	3/2000	Benn et al.	713/323
5,729,503 A	3/1998	Manning	365/233	6,044,032 A	3/2000	Li	365/230
5,729,504 A	3/1998	Cowles	365/236	6,047,073 A	4/2000	Norris et al.	
5,742,792 A	4/1998	Yanai et al.		6,047,344 A	4/2000	Kawasumi et al.	710/107
5,748,914 A	5/1998	Barth et al.	395/285	6,053,948 A *	4/2000	Vaidyanathan et al.	703/14
				6,069,504 A	5/2000	Keeth	327/108

6,070,217 A	5/2000	Connolly et al.	710/131	6,457,095 B1	9/2002	Volk	711/105
6,073,223 A	6/2000	McAllister et al.	711/167	6,459,651 B1	10/2002	Lee et al.	365/233
6,075,730 A	6/2000	Barth et al.	365/191	6,473,831 B1	10/2002	Schade	711/115
6,075,744 A	6/2000	Tsern et al.	365/230	6,476,476 B1	11/2002	Glenn	
6,078,546 A	6/2000	Lee	365/233	6,480,929 B1	11/2002	Gauthier et al.	711/105
6,079,025 A	6/2000	Fung	713/323	6,487,102 B1	11/2002	Halbert et al.	365/51
6,084,434 A	7/2000	Keeth	326/87	6,489,669 B2	12/2002	Shimada et al.	
6,088,290 A	7/2000	Ohtake et al.	365/233	6,490,161 B1	12/2002	Johnson	
6,091,251 A	7/2000	Wood et al.	324/755	6,493,789 B2	12/2002	Ware et al.	711/105
RE36,839 E	8/2000	Simmons et al.	326/93	6,496,440 B2	12/2002	Manning	365/230
6,101,152 A	8/2000	Farmwald et al.	365/233	6,496,897 B2	12/2002	Ware et al.	711/105
6,101,564 A	8/2000	Athenes et al.		6,498,766 B2	12/2002	Lee et al.	365/233
6,101,612 A	8/2000	Jeddeloh	713/401	6,510,097 B2	1/2003	Fukuyama	365/230.03
6,108,795 A	8/2000	Jeddeloh	713/401	6,510,503 B2	1/2003	Gillingham et al.	711/167
6,111,812 A	8/2000	Gans et al.	365/233	6,512,392 B2	1/2003	Fleury et al.	324/765
6,134,638 A	10/2000	Olarig et al.	711/167	6,521,984 B2	2/2003	Matsuura	
6,154,370 A	11/2000	Degani et al.	361/761	6,526,471 B1	2/2003	Shimomura et al.	711/5
6,166,991 A	12/2000	Phelan	365/233	6,526,473 B1	2/2003	Kim	
6,182,184 B1	1/2001	Farmwald et al.	710/129	6,526,484 B1	2/2003	Stacovsky et al.	711/158
6,199,151 B1	3/2001	Williams et al.		6,545,895 B1	4/2003	Li et al.	365/52
6,208,168 B1	3/2001	Rhee	326/83	6,546,446 B2	4/2003	Farmwald et al.	710/305
6,216,246 B1	4/2001	Shau	714/763	6,553,450 B1	4/2003	Dodd et al.	711/105
6,222,739 B1	4/2001	Bhakta et al.	361/790	6,560,158 B2	5/2003	Choi et al.	365/226
6,226,709 B1	5/2001	Goodwin et al.		6,563,337 B2	5/2003	Dour	326/30
6,233,192 B1	5/2001	Tanaka	365/222	6,563,759 B2	5/2003	Yahata et al.	365/233
6,233,650 B1	5/2001	Johnson et al.		6,564,281 B2	5/2003	Farmwald et al.	710/305
6,240,048 B1	5/2001	Matsubara	365/233	6,564,285 B1	5/2003	Mills et al.	711/103
6,243,282 B1	6/2001	Rondeau et al.	365/52	6,574,150 B2	6/2003	Suyama et al.	365/189
6,252,807 B1	6/2001	Suzuki et al.	365/193	6,584,037 B2	6/2003	Farmwald et al.	365/233
6,260,097 B1	7/2001	Farmwald et al.	710/129	6,587,912 B2	7/2003	Leddige et al.	711/5
6,260,154 B1	7/2001	Jeddeloh	713/401	6,590,822 B2	7/2003	Hwang et al.	365/222
6,262,938 B1	7/2001	Lee et al.	365/233	6,594,770 B1	7/2003	Sato et al.	713/320
6,266,285 B1	7/2001	Farmwald et al.	365/194	6,597,616 B2	7/2003	Tsern et al.	365/222
6,266,292 B1	7/2001	Tsern et al.	365/230	6,597,617 B2	7/2003	Ooishi et al.	365/222
6,274,395 B1	8/2001	Weber	438/14	6,614,700 B2	9/2003	Dietrich et al.	365/194
6,279,069 B1	8/2001	Robinson et al.	711/103	6,618,267 B1	9/2003	Dalal et al.	
6,295,572 B1	9/2001	Wu	710/131	6,618,791 B1	9/2003	Dodd et al.	711/105
6,298,426 B1	10/2001	Ajanovic	711/172	6,621,760 B1	9/2003	Ahmad et al.	365/233
6,304,511 B1	10/2001	Gans et al.	365/233	6,630,729 B2	10/2003	Huang	
6,307,769 B1	10/2001	Nuxoll et al.	365/63	6,631,086 B1	10/2003	Bill et al.	365/185.09
6,314,051 B1	11/2001	Farmwald et al.	365/233	6,639,820 B1	10/2003	Khandekar et al.	365/63
6,317,352 B1	11/2001	Halbert et al.	365/52	6,646,939 B2	11/2003	Kwak	365/219
6,317,381 B1	11/2001	Gans et al.	365/233	6,650,588 B2	11/2003	Yamagata	365/222
6,324,120 B2	11/2001	Farmwald et al.	365/233	6,650,594 B1	11/2003	Lee et al.	365/233
6,326,810 B1	12/2001	Keeth	326/83	6,657,634 B1	12/2003	Sinclair et al.	
6,327,664 B1	12/2001	Dell et al.	713/323	6,657,918 B2	12/2003	Foss et al.	365/233
6,330,683 B1	12/2001	Jeddeloh	713/401	6,657,919 B2	12/2003	Foss et al.	365/233
6,336,174 B1	1/2002	Li et al.		6,658,016 B1	12/2003	Dai et al.	
6,338,108 B1	1/2002	Motomura	710/110	6,658,530 B1	12/2003	Robertson et al.	711/115
6,338,113 B1	1/2002	Kubo et al.	711/105	6,659,512 B1	12/2003	Harper et al.	
6,341,347 B1	1/2002	Joy et al.	712/228	6,664,625 B2	12/2003	Hiruma	
6,343,042 B1	1/2002	Tsern et al.	365/222	6,665,224 B1	12/2003	Lehmann et al.	365/222
6,353,561 B1	3/2002	Funyu et al.	365/195	6,665,227 B2	12/2003	Fetzer	365/229
6,356,105 B1	3/2002	Volk	326/30	6,668,242 B1	12/2003	Reynov et al.	
6,356,500 B1	3/2002	Cloud et al.	365/226	6,674,154 B2	1/2004	Minamio et al.	
6,362,656 B2	3/2002	Rhee	326/87	6,683,372 B1	1/2004	Wong et al.	
6,363,031 B2	3/2002	Phelan	365/233	6,684,292 B2	1/2004	Piccirillo et al.	
6,378,020 B2	4/2002	Farmwald et al.	710/129	6,697,295 B2	2/2004	Farmwald et al.	365/233
6,381,188 B1	4/2002	Choi et al.	365/222	6,701,446 B2	3/2004	Tsern et al.	713/501
6,381,668 B1	4/2002	Lunteren	711/5	6,705,877 B1	3/2004	Li et al.	
6,389,514 B1	5/2002	Rokicki		6,708,144 B1	3/2004	Merryman et al.	703/14
6,392,304 B1	5/2002	Butler	257/777	6,710,430 B2	3/2004	Minamio et al.	
6,414,868 B1	7/2002	Wong et al.	365/51	6,711,043 B2	3/2004	Friedman et al.	
6,418,034 B1	7/2002	Weber et al.	361/790	6,713,856 B2	3/2004	Tsai et al.	
6,421,754 B1	7/2002	Kau et al.		6,714,891 B2	3/2004	Dendinger	702/132
6,424,532 B2	7/2002	Kawamura		6,724,684 B2	4/2004	Kim	365/233
6,426,916 B2	7/2002	Farmwald et al.	365/233	6,731,527 B2	5/2004	Brown	365/63
6,429,029 B1	8/2002	Eldridge et al.	438/14	6,742,098 B1	5/2004	Halbert et al.	
6,430,103 B2	8/2002	Nakayama et al.	365/230.03	6,744,687 B2	6/2004	Koo et al.	365/226
6,437,600 B1	8/2002	Keeth	326/86	6,747,887 B2	6/2004	Halbert et al.	365/51
6,438,057 B1	8/2002	Ruckerbauer	365/222	6,751,113 B2	6/2004	Bhakta et al.	365/63
6,442,698 B2	8/2002	Nizar	713/320	6,751,696 B2	6/2004	Farmwald et al.	710/305
6,445,591 B1	9/2002	Kwong		6,754,129 B2	6/2004	Khatri et al.	365/226
6,452,826 B1	9/2002	Kim et al.	365/51	6,754,132 B2	6/2004	Kyung	365/233
6,452,863 B2	9/2002	Farmwald et al.	365/233	6,757,751 B1	6/2004	Gene	710/36
6,453,400 B1	9/2002	Maesako et al.	711/167	6,762,948 B2	7/2004	Kyun et al.	365/51
6,453,402 B1	9/2002	Jeddeloh	711/167	6,765,812 B2	7/2004	Anderson	365/51
6,453,434 B2	9/2002	Delp et al.		6,766,469 B2	7/2004	Larson et al.	
6,455,348 B1	9/2002	Yamaguchi		6,771,526 B2	8/2004	LaBerge	365/63

6,772,359 B2	8/2004	Kwak et al.	713/500	7,093,101 B2	8/2006	Aasheim et al.	711/207
6,779,097 B2	8/2004	Gillingham et al.	711/167	7,103,730 B2	9/2006	Saxena et al.	711/156
6,785,767 B2	8/2004	Coulson	711/112	7,119,428 B2	10/2006	Tanie et al.	
6,791,877 B2	9/2004	Miura et al.	365/185	7,120,727 B2	10/2006	Lee et al.	711/5
6,795,899 B2	9/2004	Dodd et al.	711/137	7,126,399 B1	10/2006	Lee	327/261
6,799,241 B2	9/2004	Kahn et al.	711/105	7,127,567 B2	10/2006	Ramakrishnan et al.	
6,801,989 B2	10/2004	Johnson et al.	711/167	7,133,960 B1	11/2006	Thompson et al.	711/5
6,807,598 B2	10/2004	Farmwald et al.	710/305	7,136,978 B2	11/2006	Miura et al.	711/165
6,807,655 B1	10/2004	Rehani et al.	716/4	7,149,145 B2	12/2006	Kim et al.	365/233
6,816,991 B2	11/2004	Sanghani	714/733	7,149,824 B2	12/2006	Johnson	710/35
6,819,602 B2	11/2004	Seo et al.	365/193	7,173,863 B2	2/2007	Conley et al.	365/189
6,819,617 B2	11/2004	Hwang et al.	365/222	7,200,021 B2	4/2007	Raghuram	365/51
6,820,163 B1	11/2004	McCall et al.	710/310	7,205,789 B1	4/2007	Karabatsos	326/30
6,820,169 B2	11/2004	Wilcox et al.	711/105	7,210,059 B2	4/2007	Jeddeloh	
6,826,104 B2	11/2004	Kawaguchi et al.	365/222	7,215,561 B2	5/2007	Park et al.	
6,839,290 B2	1/2005	Ahmad et al.	365/193	7,218,566 B1	5/2007	Totolos, Jr. et al.	
6,845,027 B2	1/2005	Mayer et al.		7,224,595 B2	5/2007	Dreps et al.	365/63
6,845,055 B1	1/2005	Koga et al.	365/229	7,228,264 B2	6/2007	Barrenscheen et al.	703/23
6,847,582 B2	1/2005	Pan	365/233	7,231,562 B2	6/2007	Ohlhoff et al.	
6,850,449 B2	2/2005	Takahashi	365/222	7,233,541 B2	6/2007	Yamamoto et al.	365/230.03
6,862,202 B2	3/2005	Schaefer	365/52	7,234,081 B2	6/2007	Nguyen et al.	
6,862,249 B2	3/2005	Kyung	365/233	7,243,185 B2	7/2007	See et al.	
6,862,653 B1	3/2005	Dodd et al.	711/105	7,245,541 B2	7/2007	Janzen	365/198
6,873,534 B2	3/2005	Bhakta et al.	365/63	7,254,036 B2	8/2007	Pauley et al.	361/721
6,878,570 B2	4/2005	Lyu et al.		7,266,639 B2	9/2007	Raghuram	711/115
6,894,933 B2	5/2005	Kuzmenka et al.	365/189	7,269,042 B2	9/2007	Kinsley et al.	365/52
6,898,683 B2	5/2005	Nakamura	711/167	7,269,708 B2	9/2007	Ware	711/203
6,908,314 B2	6/2005	Brown	439/68	7,274,583 B2	9/2007	Park et al.	
6,912,778 B2	7/2005	Ahn et al.	29/852	7,277,333 B2	10/2007	Schaefer	
6,914,786 B1	7/2005	Paulsen et al.		7,286,436 B2	10/2007	Bhakta et al.	365/230
6,917,219 B2	7/2005	New	326/41	7,289,386 B2	10/2007	Bhakta et al.	365/230
6,922,371 B2	7/2005	Takahashi et al.	365/227	7,296,754 B2	11/2007	Nishizawa et al.	235/492
6,930,900 B2	8/2005	Bhakta et al.	365/51	7,299,330 B2	11/2007	Gillingham et al.	711/167
6,930,903 B2	8/2005	Bhakta et al.	365/63	7,302,598 B2	11/2007	Suzuki et al.	
6,938,119 B2	8/2005	Kohn et al.	711/105	7,307,863 B2	12/2007	Yen et al.	365/63
6,943,450 B2	9/2005	Fee et al.		7,317,250 B2	1/2008	Koh et al.	
6,944,748 B2	9/2005	Sanches et al.		7,363,422 B2	4/2008	Perego et al.	711/105
6,947,341 B2	9/2005	Stubbs et al.		7,366,947 B2	4/2008	Gower et al.	
6,951,982 B2	10/2005	Chye et al.		7,379,316 B2	5/2008	Rajan	365/63
6,952,794 B2	10/2005	Lu		7,386,656 B2	6/2008	Rajan et al.	711/103
6,961,281 B2	11/2005	Wong et al.	365/230	7,392,338 B2	6/2008	Rajan et al.	711/103
6,968,416 B2	11/2005	Moy	710/310	7,408,393 B1	8/2008	Jain et al.	703/25
6,968,419 B1	11/2005	Holman	711/5	7,409,492 B2	8/2008	Tanaka et al.	711/103
6,970,968 B1	11/2005	Holman	711/5	7,414,917 B2	8/2008	Ruckerbauer et al.	
6,980,021 B1	12/2005	Srivastava et al.	326/30	7,428,644 B2	9/2008	Jeddeloh et al.	
6,986,118 B2	1/2006	Dickman	716/8	7,437,579 B2	10/2008	Jeddeloh et al.	713/300
6,992,501 B2	1/2006	Rapport	326/30	7,441,064 B2	10/2008	Gaskins	
6,992,950 B2	1/2006	Foss et al.	365/233	7,457,122 B2	11/2008	Lai et al.	
7,000,062 B2	2/2006	Perego et al.	711/5	7,464,225 B2	12/2008	Tsern	711/115
7,003,618 B2	2/2006	Perego et al.	711/5	7,472,220 B2	12/2008	Rajan et al.	711/103
7,003,639 B2	2/2006	Tsern et al.	711/154	7,474,576 B2	1/2009	Co et al.	
7,007,095 B2	2/2006	Chen et al.		7,480,147 B2	1/2009	Hoss et al.	
7,007,175 B2	2/2006	Chang et al.	713/300	7,480,774 B2	1/2009	Ellis et al.	
7,010,642 B2	3/2006	Perego et al.	711/5	7,496,777 B2	2/2009	Kapil	713/324
7,010,736 B1	3/2006	Teh et al.	714/733	7,515,453 B2	4/2009	Rajan	365/63
7,024,518 B2	4/2006	Halbert et al.	711/115	7,532,537 B2	5/2009	Solomon et al.	365/230
7,026,708 B2	4/2006	Cady et al.		7,539,800 B2	5/2009	Dell et al.	
7,028,215 B2	4/2006	Depew et al.		7,573,136 B2	8/2009	Jiang et al.	
7,028,234 B2	4/2006	Huckaby et al.	714/710	7,580,312 B2	8/2009	Rajan et al.	
7,033,861 B1	4/2006	Partridge et al.	438/109	7,581,121 B2	8/2009	Barth et al.	
7,035,150 B2	4/2006	Streif et al.	365/194	7,581,127 B2	8/2009	Rajan et al.	
7,043,599 B1	5/2006	Ware et al.	711/106	7,590,796 B2	9/2009	Rajan et al.	
7,045,396 B2	5/2006	Crowley et al.		7,599,205 B2	10/2009	Rajan	
7,045,901 B2	5/2006	Lin et al.		7,606,245 B2	10/2009	Ma et al.	
7,046,538 B2	5/2006	Kinsley et al.	365/52	7,609,567 B2	10/2009	Rajan et al.	
7,053,470 B1	5/2006	Sellers et al.		7,613,880 B2	11/2009	Miura et al.	
7,053,478 B2	5/2006	Roper et al.		7,619,912 B2	11/2009	Bhakta et al.	
7,058,776 B2	6/2006	Lee	711/167	7,724,589 B2	5/2010	Rajan et al.	
7,058,863 B2	6/2006	Kouchi et al.	714/718	7,730,338 B2	6/2010	Rajan et al.	
7,061,784 B2	6/2006	Jakobs et al.	365/51	7,761,724 B2	7/2010	Rajan et al.	
7,061,823 B2	6/2006	Faue et al.	365/230	2001/0000822 A1	5/2001	Dell et al.	711/170
7,066,741 B2	6/2006	Burns et al.		2001/0003198 A1	6/2001	Wu	
7,075,175 B2	7/2006	Kazi et al.	257/678	2001/0011322 A1	8/2001	Stolt et al.	
7,079,396 B2	7/2006	Gates et al.		2001/0021106 A1	9/2001	Weber et al.	
7,079,441 B1	7/2006	Partsche et al.	365/226	2001/0021137 A1	9/2001	Kai et al.	365/222
7,079,446 B2	7/2006	Murtagh et al.	365/233	2001/0046129 A1	11/2001	Broglia et al.	
7,085,152 B2	8/2006	Ellis et al.	365/149	2001/0046163 A1	11/2001	Yanagawa	
7,085,941 B2	8/2006	Li	713/300	2002/0002662 A1	1/2002	Olarig et al.	
7,089,438 B2	8/2006	Raad	713/322	2002/0004897 A1	1/2002	Kao et al.	

2002/0015340 A1	2/2002	Batinovich		2004/0139359 A1	6/2004	Samson et al.	713/320
2002/0019961 A1	2/2002	Blodgett	714/718	2004/0125635 A1	7/2004	Kuzmenka	365/51
2002/0034068 A1	3/2002	Weber et al.		2004/0133736 A1	7/2004	Kyung	711/105
2002/0038405 A1	3/2002	Leddige et al.	711/115	2004/0145963 A1	7/2004	Byon	365/233
2002/0041507 A1	4/2002	Woo et al.	365/51	2004/0151038 A1	8/2004	Ruckerbauer et al.	365/200
2002/0051398 A1	5/2002	Mizugaki	365/222	2004/0174765 A1	9/2004	Seo et al.	365/233
2002/0060945 A1	5/2002	Ikeda		2004/0177079 A1	9/2004	Gluhovsky et al.	707/100
2002/0064073 A1	5/2002	Chien	365/200	2004/0178824 A1	9/2004	Pan	326/93
2002/0064083 A1	5/2002	Ryu et al.	365/233	2004/0184324 A1	9/2004	Pax	365/189
2002/0089831 A1	7/2002	Forthun		2004/0186956 A1	9/2004	Perego et al.	711/115
2002/0089970 A1	7/2002	Asada et al.		2004/0188704 A1	9/2004	Halbert et al.	257/145
2002/0094671 A1	7/2002	Distefano et al.		2004/0196732 A1	10/2004	Lee	365/233
2002/0121650 A1	9/2002	Minamio et al.		2004/0205433 A1	10/2004	Gower et al.	
2002/0121670 A1	9/2002	Minamio et al.		2004/0208173 A1	10/2004	Di Gregorio	370/360
2002/0124195 A1	9/2002	Nizar	713/320	2004/0225858 A1	11/2004	Brueggen	
2002/0129204 A1	9/2002	Leighnor et al.		2004/0228166 A1	11/2004	Braun et al.	365/154
2002/0145900 A1	10/2002	Schaefer	365/52	2004/0228196 A1	11/2004	Kwak et al.	
2002/0165706 A1	11/2002	Raynham	703/25	2004/0228203 A1	11/2004	Koo	365/233
2002/0167092 A1	11/2002	Fee et al.		2004/0230932 A1	11/2004	Dickmann	716/10
2002/0172024 A1	11/2002	Hui et al.		2004/0236877 A1	11/2004	Burton	
2002/0174274 A1	11/2002	Wu et al.	710/100	2004/0250989 A1	12/2004	Im et al.	
2002/0184438 A1	12/2002	Usui	711/106	2004/0256638 A1	12/2004	Perego et al.	257/200
2003/0002262 A1	1/2003	Benisek et al.	361/728	2004/0257847 A1	12/2004	Matsui et al.	365/63
2003/0011993 A1	1/2003	Summers et al.		2004/0260957 A1	12/2004	Jeddeloh et al.	713/300
2003/0016550 A1	1/2003	Yoo et al.		2004/0264255 A1	12/2004	Royer	365/189.01
2003/0021175 A1	1/2003	Tae Kwak	365/219	2004/0268161 A1	12/2004	Ross	713/300
2003/0026155 A1	2/2003	Yamagata		2005/0018495 A1	1/2005	Bhakta et al.	365/199
2003/0026159 A1	2/2003	Frankowsky et al.		2005/0021874 A1	1/2005	Georgiou et al.	709/250
2003/0035312 A1	2/2003	Halbert et al.		2005/0024963 A1	2/2005	Jakobs et al.	365/202
2003/0039158 A1	2/2003	Horiguchi et al.	365/200	2005/0027928 A1	2/2005	Avraham et al.	711/103
2003/0041295 A1	2/2003	Hou et al.		2005/0028038 A1	2/2005	Pomaraniski et al.	714/42
2003/0061458 A1	3/2003	Wilcox et al.	711/167	2005/0034004 A1	2/2005	Bunker et al.	
2003/0061459 A1	3/2003	Aboulenein et al.		2005/0036350 A1	2/2005	So et al.	365/63
2003/0093614 A1	5/2003	Kohn et al.	711/105	2005/0041504 A1	2/2005	Perego et al.	365/222
2003/0101392 A1	5/2003	Lee	714/718	2005/0044303 A1	2/2005	Perego et al.	711/5
2003/0105932 A1	6/2003	David et al.	711/167	2005/0044305 A1	2/2005	Jakobs et al.	711/105
2003/0117875 A1	6/2003	Lee et al.	365/226	2005/0047192 A1	3/2005	Matsui et al.	365/145
2003/0123389 A1	7/2003	Russell et al.		2005/0071543 A1	3/2005	Ellis et al.	711/106
2003/0126338 A1	7/2003	Dodd et al.	710/305	2005/0078532 A1	4/2005	Ruckerbauer et al.	365/199
2003/0127737 A1	7/2003	Takahashi		2005/0081085 A1	4/2005	Ellis et al.	714/5
2003/0131160 A1	7/2003	Hampel et al.	710/22	2005/0099834 A1	5/2005	Funaba et al.	365/63
2003/0145163 A1	7/2003	Seo et al.	711/106	2005/0102590 A1	5/2005	Norris et al.	714/719
2003/0158995 A1	8/2003	Lee et al.	711/105	2005/0105318 A1	5/2005	Funaba et al.	365/63
2003/0164539 A1	9/2003	Yau		2005/0108460 A1	5/2005	David	
2003/0164543 A1	9/2003	Kheng Lee		2005/0127531 A1	6/2005	Tay et al.	
2003/0182513 A1	9/2003	Dodd et al.	711/137	2005/0132158 A1	6/2005	Hampel et al.	711/167
2003/0183934 A1	10/2003	Barrett		2005/0135176 A1	6/2005	Ramakrishnan et al.	
2003/0189868 A1	10/2003	Riesenman et al.	365/226	2005/0138267 A1	6/2005	Bains et al.	711/100
2003/0189870 A1	10/2003	Wilcox	365/233	2005/0138304 A1	6/2005	Ramakrishnan et al.	
2003/0191888 A1	10/2003	Klein	711/105	2005/0139977 A1	6/2005	Nishio et al.	257/686
2003/0191915 A1	10/2003	Saxena et al.	711/160	2005/0141199 A1	6/2005	Chiou et al.	361/704
2003/0200382 A1	10/2003	Wells et al.	711/106	2005/0149662 A1	7/2005	Perego	711/5
2003/0200474 A1	10/2003	Li	713/320	2005/0152212 A1	7/2005	Yang et al.	365/233
2003/0205802 A1	11/2003	Segaram et al.		2005/0156934 A1	7/2005	Perego et al.	
2003/0206476 A1	11/2003	Joo	365/222	2005/0166026 A1	7/2005	Ware et al.	711/167
2003/0217303 A1	11/2003	Chua-Eoan et al.	713/600	2005/0193163 A1	9/2005	Perego	711/105
2003/0223290 A1	12/2003	Park et al.	365/200	2005/0194676 A1	9/2005	Fukuda et al.	
2003/0227798 A1	12/2003	Pax	365/189	2005/0194991 A1	9/2005	Dour et al.	326/30
2003/0229821 A1	12/2003	Ma	714/8	2005/0195629 A1	9/2005	Leddige et al.	365/51
2003/0230801 A1	12/2003	Jiang et al.		2005/0201063 A1	9/2005	Lee et al.	
2003/0231540 A1	12/2003	Lazar et al.	365/222	2005/0204111 A1	9/2005	Natarajan	711/167
2003/0231542 A1	12/2003	Zaharinova-Papazova et al.	365/226	2005/0207255 A1	9/2005	Perego et al.	365/222
2003/0234664 A1	12/2003	Yamagata		2005/0210196 A1	9/2005	Perego et al.	711/115
2004/0016994 A1	1/2004	Huang		2005/0223179 A1	10/2005	Perego et al.	711/154
2004/0027902 A1	2/2004	Ooishi et al.	365/222	2005/0224948 A1	10/2005	Lee et al.	257/686
2004/0034732 A1	2/2004	Valin et al.	714/4	2005/0232049 A1	10/2005	Park	
2004/0034755 A1	2/2004	LaBerge et al.		2005/0235119 A1	10/2005	Sechrest et al.	711/158
2004/0037133 A1	2/2004	Park et al.	365/202	2005/0235131 A1	10/2005	Ware	711/203
2004/0044808 A1	3/2004	Salmon et al.	710/8	2005/0237838 A1	10/2005	Kwak et al.	365/222
2004/0047228 A1	3/2004	Chen	365/232	2005/0243635 A1	11/2005	Schaefer	365/227
2004/0057317 A1	3/2004	Schaefer	365/222	2005/0249011 A1	11/2005	Maeda	365/222
2004/0064647 A1	4/2004	DeWhitt et al.		2005/0259504 A1	11/2005	Murtugh et al.	365/233
2004/0064767 A1	4/2004	Huckaby et al.	714/710	2005/0263312 A1	12/2005	Bolken et al.	
2004/0083324 A1	4/2004	Rabinovitz et al.		2005/0265506 A1	12/2005	Foss et al.	375/376
2004/0088475 A1	5/2004	Streif et al.	711/105	2005/0269715 A1	12/2005	Yoo	
2004/0100837 A1	5/2004	Lee		2005/0278474 A1	12/2005	Perersen et al.	711/5
2004/0117723 A1	6/2004	Foss	714/805	2005/0281096 A1	12/2005	Bhakta et al.	
2004/0123173 A1	6/2004	Emberling et al.	714/733	2005/0281123 A1	12/2005	Bell et al.	365/230
				2005/0283572 A1	12/2005	Ishihara	711/118

FOREIGN PATENT DOCUMENTS

OTHER PUBLICATIONS

Wu et al., "eNVy: A Non-Volatile, Main Memory Storage System," to appear in ASPLOS VI.

"Using Two Chip Selects to Enable Quad Rank," IP.com PriorArtDatabase, copyright IP.com, Inc. 2004.

"BIOS and Kernel Developer's Guide (BKDG) for AMD Family 10h Processors," AMD, 31116 Rev 3.00, Sep. 7, 2007.

Skerlj et al., "Buffer Device for Memory Modules (DIMM)" Qimonda 2006, p. 1.

Copy of Written Opinion from PCT Application No. PCT/US06/24360 mailed on Jan. 8, 2007.

Copy of Preliminary Report on Patentability from PCT Application No. PCT/US06/24360 mailed on Jan. 10, 2008.

Copy of Written Opinion from International PCT Application No. PCT/US06/34390 mailed on Nov. 21, 2007.

Copy of International Search Report from PCT Application No. PCT/US06/34390 mailed on Nov. 21, 2007.

Office Action from U.S. Appl. No. 11/461,427 mailed on Sep. 5, 2008.

Final Office Action from U.S. Appl. No. 11/461,430 mailed on Sep. 8, 2008.

Notice of Allowance from U.S. Appl. No. 11/474,075 mailed on Nov. 26, 2008.

Office Action from U.S. Appl. No. 11/474,076 mailed on Nov. 3, 2008.

Office Action from U.S. Appl. No. 11/524,811 mailed on Sep. 17, 2008.

Non-final Office Action from U.S. Appl. No. 11/461,430 mailed on Feb. 19, 2009.

Final Office Action from U.S. Appl. No. 11/461,435 mailed on Jan. 28, 2009.

Non-final Office Action from U.S. Appl. No. 11/461,437 mailed on Jan. 26, 2009.

Non-final Office Action from U.S. Appl. No. 11/939,432 mailed on Feb. 6, 2009.

Wu et al., "eNVy: A Non-Volatile, Main Memory Storage System," ASPLOS-VI Proceedings—Sixth International Conference on Architectural Support for Programming Languages and Operating Systems, San Jose, California, Oct. 4-7, 1994. SIGARCH Computer Architecture News 22(Special Issue Oct. 1994).

Form AO-120 as filed in US Patent No. 7,472,220 on Jun. 17, 2009.

German Office Action From German Patent Application No. 11 2006 002 300.4-55 Mailed Jun. 5, 2009 (With Translation).

Non-Final Office Action From U.S. Appl. No. 11/461,430 Mailed Feb. 19, 2009.

Final Office Action From U.S. Appl. No. 11/461,435 Mailed Jan. 28, 2009.

Non-Final Office Action From U.S. Appl. No. 11/461,437 Mailed Jan. 26, 2009.

Non-Final Office Action From U.S. Appl. No. 11/461,441 Mailed Apr. 2, 2009.

Non-Final Office Action From U.S. Appl. No. 11/611,374 Mailed Mar. 23, 2009.

Non-Final Office Action From U.S. Appl. No. 11/762,010 Mailed Mar. 20, 2009.

Non-Final Office Action From U.S. Appl. No. 11/939,432 Mailed Feb. 6, 2009.

Non-Final Office Action From U.S. Appl. No. 12/111,819 Mailed Apr. 27, 2009.

Non-Final Office Action From U.S. Appl. No. 12/111,828 Mailed Apr. 17, 2009.

Fang et al., W. Power Complexity Analysis Of Adiabatic SRAM, 6th Int. Conference On ASIC, vol. 1, Oct. 2005, pp. 334-337.

Pavan et al., P. A Complete Model Of E2PROM Memory Cells For Circuit Simulations, IEEE Transactions On Computer-Aided Design Of Integrated Circuits And Systems, vol. 22, No. 8, Aug. 2003, pp. 1072-1079.

German Office Action From German Patent Application No. 11 2006 001 810.8-55 (With Translation).

Final Rejection From U.S. Appl. No. 11/461,437 Mailed Nov. 10, 2009.

Final Rejection from U.S. Appl. No. 11/762,010 Mailed Dec. 4, 2009.

Non-Final Rejection from U.S. Appl. No. 11/672,921 Mailed Dec. 8, 2009.

Non-Final Rejection from U.S. Appl. No. 11/672,924 Mailed Dec. 14, 2009.

Non-Final Rejection from U.S. Appl. No. 11/929,225 Mailed Dec. 14, 2009.

Non-Final Rejection from U.S. Appl. No. 11/929,261 Mailed Dec. 14, 2009.

Notice of Allowance From U.S. Appl. No. 11/611,374 Mailed Nov. 30, 2009.

Notice of Allowance From U.S. Appl. No. 11/939,432 mailed Dec. 1, 2009.

Notice of Allowance From U.S. Appl. No. 12/111,819 Mailed Nov. 20, 2009.

Notice of Allowance From U.S. Appl. No. 12/111,828 Mailed Dec. 15, 2009.

Great Britain Office Action from GB Patent Application No. GB0800734.6 Mailed Mar. 1, 2010.

Final Office Action from U.S. Appl. No. 11/461,420 Mailed Apr. 28, 2010.

Notice of Allowance from U.S. Appl. No. 11/553, 372 Mailed Mar. 12, 2010.

Notice of Allowance from U.S. Appl. No. 11/553,399 Mailed Mar. 22, 2010.

Non-Final Office Action from U.S. Appl. No. 11/588,739 Mailed Dec. 29, 2009.

Notice of Allowance from U.S. Appl. No. 11/611,374 Mailed Apr. 5, 2010.

Non-Final Office Action from U.S. Appl. No. 11/828,181 Mailed Mar. 2, 2010.

Non-Final Office Action from U.S. Appl. No. 11/828,182 Mailed Mar. 29, 2010.

Final Office Action from U.S. Appl. No. 11/858,518 Mailed Apr. 21, 2010.

Non-Final Office Action from U.S. Appl. 11/929,432 Mailed Jan. 14, 2010.

Non-Final Office Action from U.S. Appl. No. 11/929,571 Mailed Mar. 3, 2010.

Non-Final Office Action from U.S. Appl. No. 11/929,631 Mailed Mar. 3, 2010.

Non-Final Office Action from U.S. Appl. No. 11/929,636 Mailed Mar. 9, 2010.

Non-Final Office Action from U.S. Appl. No. 11/929,655 Mailed Mar. 3, 2010.

Notice of Allowance from U.S. Appl. No. 11/939,432 Mailed Dec. 1, 2009.

Non-Final Office Action from U.S. Appl. No. 11/939,432 Mailed Apr. 12, 2010.

Notice of Allowance from U.S. Appl. No. 12/111,819 Mailed Mar. 10, 2010.

Non-Final Office Action from U.S. Appl. No. 12/507,682 Mailed Mar. 8, 2010.

Examination Report from GB Intellectual Property Office Dated Mar. 1, 2010.

Final Office Action from U.S. Appl. No. 11/461,435 Dated May 13, 2010.

Final Office Action from U.S. Appl. No. 11/515,167 Dated Jun. 3, 2010.

Notice of Allowance from U.S. Appl. No. 11/515,223 Dated Jul. 30, 2010.

Final Office Action from U.S. Appl. No. 11/553,390 Dated Jun. 24, 2010.

Notice of Allowance from U.S. Appl. No. 11/611,374 Dated Jul. 19, 2010.

Final Office Action from U.S. Appl. No. 11/672,921 Dated Jul. 23, 2010.

Final Office Action from U.S. Appl. No. 11/702,960 Dated Jun. 21, 2010.

Notice of Allowance from U.S. Appl. No. 11/763,365 Dated Jun. 29, 2010.

Final Office Action from U.S. Appl. No. 11/929,500 Dated Jun. 24, 2010.

Office Action from U.S. Appl. No. 12/574,628 Dated Jun. 10, 2010.

Supplemental European Search Report and Search Opinion issued Sep. 21, 2009 in European Application No. 07870726.2, 8 pages.

Wu et al., "eNVy: A Non-Volatile, Main Memory Storage System", ASPLOS-VI Proceedings, Oct. 4-7, 1994, pp. 86-97.

Buffer Device for Memory Modules (DIMM), IP.com Prior Art Database, <URL: <http://ip.com/IPCOM/000144850>>, Feb. 10, 2007, 1 pg.

German Office Action from German Patent Application No. 11 2006 002 300.4-55 Dated May 11, 2009 (With Translation).

Great Britain Office Action from GB Patent Application No. GB0803913.3 Dated Mar. 1, 2010.

International Preliminary Examination Report From PCT Application No. PCT/US07/016385 Dated Feb. 3, 2009.

Search Report and Written Opinion From PCT Application No. PCT/US07/03460 Dated on Feb. 14, 2008.

Non-Final Office Action from U.S. Appl. No. 11/461,420 Dated Jul. 23, 2009.

Notice of Allowance from U.S. Appl. No. 11/461,430 Dated Sep. 10, 2009.

Non-Final Office Action from U.S. Appl. No. 11/461,435 Dated Aug. 5, 2009.

Non-Final Office Action from U.S. Appl. No. 11/515,167 Dated Sep. 25, 2009.

Non-Final Office Action from U.S. Appl. No. 11/515,223 Dated Sep. 22, 2009.

Non-Final Office Action from U.S. Appl. No. 11/538,041 Dated Jun. 10, 2009.

Non-Final Office Action from U.S. Appl. No. 11/553,372 Dated Jun. 25, 2009.

Notice of Allowance from U.S. Appl. No. 11/553,372 Dated Sep. 30, 2009.

Notice of Allowance from U.S. Appl. No. 11/553,372 Dated Aug. 4, 2010.

Non-Final Office Action from U.S. Appl. No. 11/553,390 Dated Sep. 9, 2009.

Non-Final Office Action from U.S. Appl. No. 11/553,399 Dated Jul. 7, 2009.

Notice of Allowance from U.S. Appl. No. 11/553,399 Dated Oct. 13, 2009.

Notice of Allowance from U.S. Appl. No. 11/553,399 Dated Dec. 3, 2010.

Notice of Allowance from U.S. Appl. No. 11/611,374 Dated Sep. 15, 2009.

Notice of Allowance from U.S. Appl. No. 11/611,374 Dated Oct. 29, 2010.

Final Office Action from U.S. Appl. No. 11/672,924 Dated Sep. 7, 2010.

Non-Final Office Action from U.S. Appl. No. 11/702,960 Dated Sep. 25, 2009.

Non-Final Office Action from U.S. Appl. No. 11/702,981 Dated Mar. 11, 2009.

Non-Final Office Action from U.S. Appl. No. 11/702,981 Dated Aug. 19, 2009.

Non-Final Office Action from U.S. Appl. No. 11/762,013 Dated Jun. 5, 2009.

Notice of Allowance from U.S. Appl. No. 11/762,013 Dated Aug. 17, 2010.

Notice of Allowance from U.S. Appl. No. 11/762,013 Dated Dec. 7, 2010.

Non-Final Office Action from U.S. Appl. No. 11/763,365 Dated Oct. 28, 2009.

Notice of Allowance from U.S. Appl. No. 11/763,365 Dated Oct. 20, 2010.

Non-Final Office Action from U.S. Appl. No. 11/855,805 Dated Sep. 21, 2010.

Non-Final Office Action from U.S. Appl. No. 11/858,518 Dated Aug. 14, 2009.

Non-Final Office Action from U.S. Appl. No. 11/858,518 Dated Sep. 8, 2010.

Final Office Action from U.S. Appl. No. 11/929,225 Dated Aug. 27, 2010.

Final Office Action from U.S. Appl. No. 11/929,261 Dated Sep. 7, 2010.

Final Office Action from U.S. Appl. No. 11/929,286 Dated Aug. 20, 2010.

Notice of Allowance from U.S. Appl. No. 11/929,320 Dated Sep. 29, 2010.

Final Office Action from U.S. Appl. No. 11/929,403 Dated Aug. 31, 2010.

Final Office Action from U.S. Appl. No. 11/929,417 Dated Aug. 31, 2010.

Final Office Action from U.S. Appl. No. 11/929,432 Dated Aug. 20, 2010.

Final Office Action from U.S. Appl. No. 11/929,450 Dated Aug. 20, 2010.

Notice of Allowance from U.S. Appl. No. 11/929,483 Dated Oct. 7, 2010.

Non-Final Office Action from U.S. Appl. No. 11/929,500 Dated Oct. 13, 2009.

Final Office Action from U.S. Appl. No. 11/929,631 Dated Nov. 18, 2010.

Final Office Action from U.S. Appl. No. 11/929,655 Dated Nov. 22, 2010.

Notice of Allowance from U.S. Appl. No. 11/939,432 Dated Sep. 24, 2009.

Non-Final Office Action from U.S. Appl. No. 11/939,440 Dated Sep. 17, 2010.

Non-Final Office Action from U.S. Appl. No. 11/941,589 Dated Oct. 1, 2009.

Notice of Allowance from U.S. Appl. No. 11/941,589 Dated Oct. 25, 2010.

Non-Final Office Action from U.S. Appl. No. 12/057,306 Dated Oct. 8, 2010.

Non-Final Office Action from U.S. Appl. No. 12/203,100 Dated Dec. 1, 2010.

Non-Final Office Action from U.S. Appl. No. 12/769,428 Dated Nov. 8, 2010.

Non-Final Office Action from U.S. Appl. No. 12/838,896 Dated Sep. 3, 2010.

Final Office Action from U.S. Appl. No. 11/939,440 Dated May 19, 2011.

Final Office Action from U.S. Appl. No. 11/855,805, Dated May 26, 2011.

Search Report From PCT Application No. PCT/US10/038041 Dated Aug. 23, 2010.

Non-Final Office Action from U.S. Appl. No. 11/461,437 Dated Jan. 4, 2011.

Notice of Allowance from U.S. Appl. No. 11/515,223 Dated Feb. 4, 2011.

Non-Final Office Action from U.S. Appl. No. 11/553,372 Dated Jan. 5, 2011.

Final Office Action from U.S. Appl. No. 11/588,739 Dated Dec. 15, 2010.

Final Office Action from U.S. Appl. No. 11/828,182 Dated Dec. 22, 2010.

Non-Final Office Action from U.S. Appl. No. 11/855,826 Dated Jan. 13, 2011.

Notice of Allowance from U.S. Appl. No. 11/939,432 Dated Feb. 18, 2011.

Notice of Allowance from U.S. Appl. No. 12/144,396 Dated Feb. 1, 2011.

Non-Final Office Action from U.S. Appl. No. 12/816,756 Dated Feb. 7, 2011.

Notice of Allowance from U.S. Appl. No. 11/762,013 Dated Feb. 23, 2011.

Notice of Allowance from U.S. Appl. No. 11/929,500 Dated Feb. 24, 2011.

Notice of Allowance from U.S. Appl. No. 11/763,365 Dated Mar. 1, 2011.

Final Office Action from U.S. Appl. No. 12/574,628 Dated Mar. 3, 2011.

Final Office Action from U.S. Appl. No. 11/929,571 Dated Mar. 3, 2011.

Notice of Allowance from U.S. Appl. No. 11/611,374 Dated Mar. 4, 2011.

Notice of Allowance from U.S. Appl. No. 11/929,483 Dated Mar. 4, 2011.

Notice of Allowance from U.S. Appl. No. 11/553,399 Dated Mar. 18, 2011.

Final Office Action from U.S. Appl. No. 12/507,682 Dated Mar. 29, 2011.

Non-Final Office Action from U.S. Appl. No. 11/929,403 Dated Mar. 31, 2011.

Non-Final Office Action from U.S. Appl. No. 11/929,417 Dated Mar. 31, 2011.

Notice of Allowance from U.S. Appl. No. 12/838,896 Dated Apr. 19, 2011.

Notice of Allowance from U.S. Appl. No. 11/702,981 Dated Apr. 25, 2011.

Notice of Allowance from U.S. Appl. No. 11/702,981 Dated Mar. 10, 2011.

Notice of Allowance from U.S. Appl. No. 11/929,320 Dated May 5, 2011.

* cited by examiner




FIG. 1




FIG. 2




FIG. 3




FIG. 4




FIG. 5




FIG. 6




FIG. 7




FIG. 8




FIG. 9




FIG. 10




FIG. 11




FIG. 12




FIG. 13




FIG. 14




FIG. 15




FIG. 16




FIG. 17




FIG. 18

1

MEMORY DEVICE WITH EMULATED CHARACTERISTICS

RELATED APPLICATION

This application is a continuation-in-part of commonly-assigned U.S. patent application Ser. No. 11/461,420 entitled "System and Method for Simulating a Different Number of Memory Circuits" filed Jul. 31, 2006 by Rajan, et al., which is incorporated by reference as if fully set forth herein.

BACKGROUND OF THE INVENTION

1. Technical Field of the Invention

This invention relates generally to digital memory such as used in computers, and more specifically to organization and design of memory modules such as DIMMs.

2. Background Art

Digital memories are utilized in a wide variety of electronic systems, such as personal computers, workstations, servers, consumer electronics, printers, televisions, and so forth. Digital memories are manufactured as monolithic integrated circuits ("ICs" or "chips"). Digital memories come in several types, such as dynamic random access memory (DRAM), static random access memory (SRAM), flash memory, electrically erasable programmable read only memory (EEPROM), and so forth.

In some systems, the memory chips are coupled directly into the system such as by being soldered directly to the system's main motherboard. In other systems, groups of memory chips are first coupled into memory modules, such as dual in-line memory modules (DIMMs), which are in turn coupled into a system by means of slots, sockets, or other connectors. Some types of memory modules include not only the memory chips themselves, but also some additional logic which interfaces the memory chips to the system. This logic may perform a variety of low level functions, such as buffering or latching signals between the chips and the system, but it may also perform higher level functions, such as telling the system what are the characteristics of the memory chips. These characteristics may include, for example, memory capacity, speed, latency, interface protocol, and so forth.

Memory capacity requirements of such systems are increasing rapidly. However, other industry trends such as higher memory bus speeds, small form factor machines, etc. are reducing the number of memory module slots, sockets, connectors, etc. that are available in such systems. There is, therefore, pressure for manufacturers to use large capacity memory modules in such systems.

However, there is also an exponential relationship between a memory chip's capacity and its price. As a result, large capacity memory modules may be cost prohibitive in some systems.

What is needed, then, is an effective way to make use of low cost memory chips in manufacturing high capacity memory modules.

SUMMARY

A memory subsystem is provided including an interface circuit adapted for communication with a system and a majority of address or control signals of a first number of memory circuits. The interface circuit includes emulation logic for emulating at least one memory circuit of a second number.

BRIEF DESCRIPTION OF THE DRAWINGS

FIG. 1 shows a system coupled to multiple memory circuits and an interface circuit according to one embodiment of this invention.

2

FIG. 2 shows a buffered stack of DRAM circuits each having a dedicated data path from the buffer chip and sharing a single address, control, and clock bus.

FIG. 3 shows a buffered stack of DRAM circuits having two address, control, and clock busses and two data busses.

FIG. 4 shows a buffered stack of DRAM circuits having one address, control, and clock bus and two data busses.

FIG. 5 shows a buffered stack of DRAM circuits having one address, control, and clock bus and one data bus.

FIG. 6 shows a buffered stack of DRAM circuits in which the buffer chip is located in the middle of the stack of DRAM chips.

FIG. 7 is a flow chart showing one method of storing information.

FIG. 8 shows a high capacity DIMM using buffered stacks of DRAM chips according to one embodiment of this invention.

FIG. 9 is a timing diagram showing one embodiment of how the buffer chip makes a buffered stack of DRAM circuits appear to the system or memory controller to use longer column address strobe (CAS) latency DRAM chips than is actually used by the physical DRAM chips.

FIG. 10 shows a timing diagram showing the write data timing expected by DRAM in a buffered stack, in accordance with another embodiment of this invention.

FIG. 11 is a timing diagram showing how write control signals are delayed by a buffer chip in accordance with another embodiment of this invention.

FIG. 12 is a timing diagram showing early write data from a memory controller or an advanced memory buffer (AMB) according to yet another embodiment of this invention.

FIG. 13 is a timing diagram showing address bus conflicts caused by delayed write operations.

FIG. 14 is a timing diagram showing variable delay of an activate operation through a buffer chip.

FIG. 15 is a timing diagram showing variable delay of a precharge operation through a buffer chip.

FIG. 16 shows a buffered stack of DRAM circuits and the buffer chip which presents them to the system as if they were a single, larger DRAM circuit, in accordance with one embodiment of this invention.

FIG. 17 is a flow chart showing a method of refreshing a plurality of memory circuits, in accordance with one embodiment of this invention.

FIG. 18 shows a block diagram of another embodiment of the invention.

DETAILED DESCRIPTION

The invention will be understood more fully from the detailed description given below and from the accompanying drawings of embodiments of the invention which, however, should not be taken to limit the invention to the specific embodiments described, but are for explanation and understanding only.

FIG. 1 illustrates a system 100 including a system device 106 coupled to an interface circuit 102, which is in turn coupled to a plurality of physical memory circuits 104A-N. The physical memory circuits may be any type of memory circuits. In some embodiments, each physical memory circuit is a separate memory chip. For example, each may be a DDR2 DRAM. In some embodiments, the memory circuits may be symmetrical, meaning each has the same capacity, type, speed, etc., while in other embodiments they may be asymmetrical. For ease of illustration only, three such memory circuits are shown, but actual embodiments may use any plural number of memory circuits. As will be discussed

below, the memory chips may optionally be coupled to a memory module (not shown), such as a DIMM.

The system device may be any type of system capable of requesting and/or initiating a process that results in an access of the memory circuits. The system may include a memory controller (not shown) through which it accesses the memory circuits.

The interface circuit may include any circuit or logic capable of directly or indirectly communicating with the memory circuits, such as a buffer chip, advanced memory buffer (AMB) chip, etc. The interface circuit interfaces a plurality of signals **108** between the system device and the memory circuits. Such signals may include, for example, data signals, address signals, control signals, clock signals, and so forth. In some embodiments, all of the signals communicated between the system device and the memory circuits are communicated via the interface circuit. In other embodiments, some other signals **110** are communicated directly between the system device (or some component thereof such as a memory controller, an AMB, or a register) and the memory circuits, without passing through the interface circuit. In some such embodiments, the majority of signals are communicated via the interface circuit, such that $L > M$.

As will be explained in greater detail below, the interface circuit presents to the system device an interface to emulated memory devices which differ in some aspect from the physical memory circuits which are actually present. For example, the interface circuit may tell the system device that the number of emulated memory circuits is different than the actual number of physical memory circuits. The terms "emulating", "emulated", "emulation", and the like will be used in this disclosure to signify emulation, simulation, disguising, transforming, converting, and the like, which results in at least one characteristic of the memory circuits appearing to the system device to be different than the actual, physical characteristic. In some embodiments, the emulated characteristic may be electrical in nature, physical in nature, logical in nature, pertaining to a protocol, etc. An example of an emulated electrical characteristic might be a signal, or a voltage level. An example of an emulated physical characteristic might be a number of pins or wires, a number of signals, or a memory capacity. An example of an emulated protocol characteristic might be a timing, or a specific protocol such as DDR3.

In the case of an emulated signal, such signal may be a control signal such as an address signal, a data signal, or a control signal associated with an activate operation, precharge operation, write operation, mode register read operation, refresh operation, etc. The interface circuit may emulate the number of signals, type of signals, duration of signal assertion, and so forth. It may combine multiple signals to emulate another signal.

The interface circuit may present to the system device an emulated interface to e.g. DDR3 memory, while the physical memory chips are, in fact, DDR2 memory. The interface circuit may emulate an interface to one version of a protocol such as DDR2 with 5-5-5 latency timing, while the physical memory chips are built to another version of the protocol such as DDR2 with 3-3-3 latency timing. The interface circuit may emulate an interface to a memory having a first capacity that is different than the actual combined capacity of the physical memory chips.

An emulated timing may relate to latency of e.g. a column address strobe (CAS) latency, a row address to column address latency (tRCD), a row precharge latency (tRP), an activate to precharge latency (tRAS), and so forth. CAS latency is related to the timing of accessing a column of data. tRCD is the latency required between the row address strobe

(RAS) and CAS. tRP is the latency required to terminate an open row and open access to the next row, tRAS is the latency required to access a certain row of data between an activate operation and a precharge operation.

The interface circuit may be operable to receive a signal from the system device and communicate the signal to one or more of the memory circuits after a delay (which may be hidden from the system device). Such delay may be fixed, or in some embodiments it may be variable. If variable, the delay may depend on e.g. a function of the current signal or a previous signal, a combination of signals, or the like. The delay may include a cumulative delay associated with any one or more of the signals. The delay may result in a time shift of the signal forward or backward in time with respect to other signals. Different delays may be applied to different signals. The interface circuit may similarly be operable to receive a signal from a memory circuit and communicate the signal to the system device after a delay.

The interface circuit may take the form of or incorporate, or be incorporated into, a register, an AMB, a buffer, or the like, and may comply with Joint Electron Device Engineering Council (JEDEC) standards, and may have forwarding, storing, and/or buffering capabilities.

In some embodiments, the interface circuit may perform operations without the system device's knowledge. One particularly useful such operation is a power-saving operation. The interface circuit may identify one or more of the memory circuits which are not currently being accessed by the system device, and perform the power saving operation on those. In one such embodiment, the identification may involve determining whether any page (or other portion) of memory is being accessed. The power saving operation may be a power down operation, such as a precharge power down operation.

The interface circuit may include one or more devices which together perform the emulation and related operations. The interface circuit may be coupled or packaged with the memory devices, or with the system device or a component thereof, or separately. In one embodiment, the memory circuits and the interface circuit are coupled to a DIMM.

FIG. 2 illustrates one embodiment of a system **200** including a system device (e.g. host system **204**, etc.) which communicates address, control, clock, and data signals with a memory subsystem **201** via an interface.

The memory subsystem includes a buffer chip **202** which presents the host system with emulated interface to emulated memory, and a plurality of physical memory circuits which, in the example shown, are DRAM chips **206A-D**. In one embodiment, the DRAM chips are stacked, and the buffer chip is placed electrically between them and the host system. Although the embodiments described here show the stack consisting of multiple DRAM circuits, a stack may refer to any collection of memory circuits (e.g. DRAM circuits, flash memory circuits, or combinations of memory circuit technologies, etc.).

The buffer chip buffers communicates signals between the host system and the DRAM chips, and presents to the host system an emulated interface to present the memory as though it were a smaller number of larger capacity DRAM chips, although in actuality there is a larger number of smaller capacity DRAM chips in the memory subsystem. For example, there may be eight 512 Mb physical DRAM chips, but the buffer chip buffers and emulates them to appear as a single 4 Gb DRAM chip, or as two 2 Gb DRAM chips. Although the drawing shows four DRAM chips, this is for ease of illustration only; the invention is, of course, not limited to using four DRAM chips.

5

In the example shown, the buffer chip is coupled to send address, control, and clock signals **208** to the DRAM chips via a single, shared address, control, and clock bus, but each DRAM chip has its own, dedicated data path for sending and receiving data signals **210** to/from the buffer chip.

Throughout this disclosure, the reference number **1** will be used to denote the interface between the host system and the buffer chip, the reference number **2** will be used to denote the address, control, and clock interface between the buffer chip and the physical memory circuits, and the reference number **3** will be used to denote the data interface between the buffer chip and the physical memory circuits, regardless of the specifics of how any of those interfaces is implemented in the various embodiments and configurations described below. In the configuration shown in FIG. **2**, there is a single address, control, and clock interface channel **2** and four data interface channels **3**; this implementation may thus be said to have a “1A4D” configuration (wherein “1A” means one address, control, and clock channel in interface **2**, and “4D” means four data channels in interface **3**).

In the example shown, the DRAM chips are physically arranged on a single side of the buffer chip. The buffer chip may, optionally, be a part of the stack of DRAM chips, and may optionally be the bottommost chip in the stack. Or, it may be separate from the stack.

FIG. **3** illustrates another embodiment of a system **301** in which the buffer chip **303** is interfaced to a host system **304** and is coupled to the DRAM chips **307A-307D** somewhat differently than in the system of FIG. **2**. There are a plurality of shared address, control, and clock busses **309A** and **309B**, and a plurality of shared data busses **305A** and **305B**. Each shared bus has two or more DRAM chips coupled to it. As shown, the sharing need not necessarily be the same in the data busses as it is in the address, control, and clock busses. This embodiment has a “2A2D” configuration.

FIG. **4** illustrates another embodiment of a system **411** in which the buffer chip **413** is interfaced to a host system **404** and is coupled to the DRAM chips **417A-417D** somewhat differently than in the system of FIG. **2** or **3**. There is a shared address, control, and clock bus **419**, and a plurality of shared data busses **415A** and **415B**. Each shared bus has two or more DRAM chips coupled to it. This implementation has a “1A2D” configuration.

FIG. **5** illustrates another embodiment of a system **521** in which the buffer chip **523** is interfaced to a host system **504** and is coupled to the DRAM chips **527A-527D** somewhat differently than in the system of FIGS. **2** through **4**. There is a shared address, control, and clock bus **529**, and a shared data bus **525**. This implementation has a “1A1D” configuration.

FIG. **6** illustrates another embodiment of a system **631** in which the buffer chip **633** is interfaced to a host system **604** and is coupled to the DRAM chips **637A-637D** somewhat differently than in the system of FIGS. **2** through **5**. There is a plurality of shared address, control, and clock busses **639A** and **639B**, and a plurality of dedicated data paths **635**. Each shared bus has two or more DRAM chips coupled to it. Further, in the example shown, the DRAM chips are physically arranged on both sides of the buffer chip. There may be, for example, sixteen DRAM chips, with the eight DRAM chips on each side of the buffer chip arranged in two stacks of four chips each. This implementation has a “2A4D” configuration.

FIGS. **2** through **6** are not intended to be an exhaustive listing of all possible permutations of data paths, busses, and buffer chip configurations, and are only illustrative of some ways in which the host system device can be in electrical contact only with the load of the buffer chip and thereby be

6

isolated from whatever physical memory circuits, data paths, busses, etc. exist on the (logical) other side of the buffer chip.

FIG. **7** illustrates one embodiment of a method **700** for storing at least a portion of information received in association with a first operation, for use in performing a second operation. Such a method may be practiced in a variety of systems, such as, but not limited to, those of FIGS. **1-6**. For example, the method may be performed by the interface circuit of FIG. **1** or the buffer chip of FIG. **2**.

Initially, first information is received (**702**) in association with a first operation to be performed on at least one of the memory circuits (DRAM chips). Depending on the particular implementation, the first information may be received prior to, simultaneously with, or subsequent to the instigation of the first operation. The first operation may be, for example, a row operation, in which case the first information may include e.g. address values received by the buffer chip via the address bus from the host system. At least a portion of the first information is then stored (**704**).

The buffer chip also receives (**706**) second information associated with a second operation. For convenience, this receipt is shown as being after the storing of the first information, but it could also happen prior to or simultaneously with the storing. The second operation may be, for example, a column operation.

Then, the buffer chip performs (**708**) the second operation, utilizing the stored portion of the first information, and the second information.

If the buffer chip is emulating a memory device which has a larger capacity than each of the physical DRAM chips in the stack, the buffer chip may receive from the host system's memory controller more address bits than are required to address any given one of the DRAM chips. In this instance, the extra address bits may be decoded by the buffer chip to individually select the DRAM chips, utilizing separate chip select signals (not shown) to each of the DRAM chips in the stack.

For example, a stack of four x4 1 Gb DRAM chips behind the buffer chip may appear to the host system as a single x4 4 Gb DRAM circuit, in which case the memory controller may provide sixteen row address bits and three bank address bits during a row operation (e.g. an activate operation), and provide eleven column address bits and three bank address bits during a column operation (e.g. a read or write operation). However, the individual DRAM chips in the stack may require only fourteen row address bits and three bank address bits for a row operation, and eleven column address bits and three bank address bits during a column operation. As a result, during a row operation (the first operation in the method **702**), the buffer chip may receive two address bits more than are needed by any of the DRAM chips. The buffer chip stores (**704**) these two extra bits during the row operation (in addition to using them to select the correct one of the DRAM chips), then uses them later, during the column operation, to select the correct one of the DRAM chips.

The mapping between a system address (from the host system to the buffer chip) and a device address (from the buffer chip to a DRAM chip) may be performed in various manners. In one embodiment, lower order system row address and bank address bits may be mapped directly to the device row address and bank address bits, with the most significant system row address bits (and, optionally, the most significant bank address bits) being stored for use in the subsequent column operation. In one such embodiment, what is stored is the decoded version of those bits, in other words, the extra bits may be stored either prior to or after decoding.

The stored bits may be stored, for example, in an internal lookup table (not shown) in the buffer chip, for one or more clock cycles.

As another example, the buffer chip may have four 512 Mb DRAM chips with which it emulates a single 2 Gb DRAM chip. The system will present fifteen row address bits, from which the buffer chip may use the fourteen low order bits (or, optionally, some other set of fourteen bits) to directly address the DRAM chips. The system will present three bank address bits, from which the buffer chip may use the two low order bits (or, optionally, some other set of two bits) to directly address the DRAM chips. During a row operation, the most significant bank address bit (or other unused bit) and the most significant row address bit (or other unused bit) are used to generate the four DRAM chip select signals, and are stored for later reuse. And during a subsequent column operation, the stored bits are again used to generate the four DRAM chip select signals. Optionally, the unused bank, address is not stored during the row operation, as it will be re-presented during the subsequent column operation.

As yet another example, addresses may be mapped between four 1 Gb DRAM circuits to emulate a single 4 Gb DRAM circuit. Sixteen row address bits and three bank address bits come from the host system, of which the low order fourteen address bits and all three bank address bits are mapped directly to the DRAM circuits. During a row operation, the two most significant row address bits are decoded to generate four chip select signals, and are stored using the bank address bits as the index. During the subsequent column operation, the stored row address bits are again used to generate the four chip select signals.

A particular mapping technique may be chosen, to ensure that there are no unnecessary combinational logic circuits in the critical timing path between the address input pins and address output pins of the buffer chip. Corresponding combinational logic circuits may instead be used to generate the individual chip select signals. This may allow the capacitive loading on the address outputs of the buffer chip to be much higher than the loading on the individual chip select signal outputs of the buffer chip.

In another embodiment, the address mapping may be performed by the buffer chip using some of the bank address signals from the host system to generate the chip select signals. The buffer chip may store the higher order row address bits during a row operation, using the bank address as the index, and then use the stored address bits as part of the DRAM circuit bank address during a column operation.

For example, four 512 Mb DRAM chips may be used in emulating a single 2 Gb DRAM. Fifteen row address bits come from the host system, of which the low order fourteen are mapped directly to the DRAM chips. Three bank address bits come from the host system, of which the least significant bit is used as a DRAM circuit bank address bit for the DRAM chips. The most significant row address bit may be used as an additional DRAM circuit bank address bit. During a row operation, the two most significant bank address bits are decoded to generate the four chip select signals. The most significant row address bit may be stored during the row operation, and reused during the column operation with the least significant bank, address bit, to form the DRAM circuit bank address.

The column address from the host system memory controller may be mapped directly as the column address to the DRAM chips in the stack, since each of the DRAM chips may have the same page size, regardless any differences in the capacities of the (asymmetrical) DRAM chips.

Optionally, address bit A[10] may be used by the memory controller to enable or disable auto-precharge during a column operation, in which case the buffer chip may forward that bit to the DRAM circuits without any modification during a column operation.

In various embodiments, it may be desirable to determine whether the simulated DRAM circuit behaves according to a desired DRAM standard or other design specification. Behavior of many DRAM circuits is specified by the JEDEC standards, and it may be desirable to exactly emulate a particular JEDEC standard DRAM. The JEDEC standard defines control signals that a DRAM circuit must accept and the behavior of the DRAM circuit as a result of such control signals. For example, the JEDEC specification for DDR2 DRAM is known as JESD79-2B. If it is desired to determine whether a standard is met, the following algorithm may be used. Using a set of software verification tools, it checks for formal verification of logic, that protocol behavior of the simulated DRAM circuit is the same as the desired standard or other design specification. Examples of suitable verification tools include: Magellan, supplied by Synopsys, Inc. of 700 E. Middlefield Rd., Mt. View, Calif. 94043; Incisive, supplied by Cadence Design Systems, Inc., of 2655 Sealy Ave., San Jose, Calif. 95134; tools supplied by Jasper Design Automation, Inc. of 100 View St. #100, Mt. View, Calif. 94041; Verix, supplied by Real Intent, Inc., of 505 N. Mathilda Ave. #210, Sunnyvale, Calif. 94085; 0-In, supplied by Mentor Graphics Corp. of 8005 SW Boeckman Rd., Wilsonville, Oreg. 97070; and others. These software verification tools use written assertions that correspond to the rules established by the particular DRAM protocol and specification. These written assertions are further included in the code that forms the logic description for the buffer chip. By writing assertions that correspond to the desired behavior of the emulated DRAM circuit, a proof may be constructed that determines whether the desired design requirements are met.

For instance, an assertion may be written that no two DRAM control signals are allowed to be issued to an address, control, and clock bus at the same time. Although one may know which of the various buffer chip/DRAM stack configurations and address mappings (such as those described above) are suitable, the verification process allows a designer to prove that the emulated DRAM circuit exactly meets the required standard etc. If, for example, an address mapping that uses a common bus for data and a common bus for address, results in a control and clock bus that does not meet a required specification, alternative designs for buffer chips with other bus arrangements or alternative designs for the sideband signal interconnect between two or more buffer chips may be used and tested for compliance. Such sideband signals convey the power management signals, for example.

FIG. 8 illustrates a high capacity DIMM 800 using a plurality of buffered stacks of DRAM circuits 802 and a register device 804, according to one embodiment of this invention. The register performs the addressing and control of the buffered stacks. In some embodiments, the DIMM may be an FB-DIMM, in which case the register is an AMB. In one embodiment the emulation is performed at the DIMM level.

FIG. 9 is a timing diagram illustrating a timing design 900 of a buffer chip which makes a buffered stack of DRAM chips mimic a larger DRAM circuit having longer CAS latency, in accordance with another embodiment of this invention. Any delay through a buffer chip may be made transparent to the host system's memory controller, by using such a method. Such a delay may be a result of the buffer chip being located electrically between the memory bus of the host system and the stacked DRAM circuits, since some or all of the signals

9

that connect the memory bus to the DRAM circuits pass through the buffer chip. A finite amount of time may be needed for these signals to traverse through the buffer chip. With the exception of register chips and AMBs, industry standard memory protocols may not comprehend the buffer chip that sits between the memory bus and the DRAM chips. Industry standards narrowly define the properties of a register chip and an AMB, but not the properties of the buffer chip of this embodiment. Thus, any signal delay caused by the buffer chip may cause a violation of the industry standard protocols.

In one embodiment, the buffer chip may cause a one-half clock cycle delay between the buffer chip receiving address and control signals from the host system memory controller (or, optionally, from a register chip or an AMB), and the address and control signals being valid at the inputs of the stacked DRAM circuits. Data signals may also have a one-half clock cycle delay in either direction to/from the host system. Other amounts of delay are, of course, possible, and the half-clock cycle example is for illustration only.

The cumulative delay through the buffer chip is the sum of a delay of the address and control signals and a delay of the data signals. FIG. 9 illustrates an example where the buffer chip is using DRAM chips having a native CAS latency of i clocks, and the buffer chip delay is j clocks, thus the buffer chip emulates a DRAM having a CAS latency of $i+j$ clocks. In the example shown, the DRAM chips have a native CAS latency **906** of four clocks (from $t1$ to $t5$), and the total latency through the buffer chip is two clocks (one clock delay **902** from $t0$ to $t1$ for address and control signals, plus one clock delay **904** from $t5$ to $t6$ for data signals), and the buffer chip emulates a DRAM having a six clock CAS latency **908**.

In FIG. 9 (and other timing diagrams), the reference numbers **1**, **2**, and/or **3** at the left margin indicate which of the interfaces correspond to the signals or values illustrated on the associated waveforms. For example, in FIG. 9: the "Clock" signal shown as a square wave on the uppermost waveform is indicated as belonging to the interface **1** between the host system and the buffer chip; the "Control Input to Buffer" signal is also part of the interface **1**; the "Control Input to DRAM" waveform is part of the interface **2** from the buffer chip to the physical memory circuits; the "Data Output from DRAM" waveform is part of the interface **3** from the physical memory circuits to the buffer chip; and the "Data Output from Buffer" shown in the lowermost waveform is part of the interface **1** from the buffer chip to the host system.

FIG. 10 is a timing diagram illustrating a timing design **1000** of write data timing expected by a DRAM circuit in a buffered stack. Emulation of a larger capacity DRAM circuit having higher CAS latency (as in FIG. 9) may, in some implementations, create a problem with the timing of write operations. For example, with respect to a buffered stack of DDR2 SDRAM chips with a read CAS latency of four clocks which are used in emulating a single larger DDR2 SDRAM with a read CAS latency of six clocks, the DDR2 SDRAM protocol may specify that the write CAS latency **1002** is one less than the read CAS latency. Therefore, since the buffered stack appears as a DDR2 SDRAM with a read CAS latency of six clocks, the memory controller may use a buffered stack write CAS latency of five clocks **1004** when scheduling a write operation to the memory.

In the specific example shown, the memory controller issues the write operation at $t0$. After a one clock cycle delay through the buffer chip, the write operation is issued to the DRAM chips at $t1$. Because the memory controller believes it is connected to memory having a read CAS latency of six clocks and thus a write CAS latency of five clocks, it issues the write data at time $t0+5=t5$. But because the physical

10

DRAM chips have a read CAS latency of four clocks and thus a write CAS latency of three clocks, they expect to receive the write data at time $t1+3=t4$. Hence the problem, which the buffer chip may alleviate by delaying write operations.

The waveform "Write Data Expected by DRAM" is not shown as belonging to interface **1**, interface **2**, or interface **3**, for the simple reason that there is no such signal present in any of those interfaces. That waveform represents only what is expected by the DRAM, not what is actually provided to the DRAM.

FIG. 11 is a timing illustrating a timing design **1100** showing how the buffer chip does this. The memory controller issues the write operation at $t0$. In FIG. 10, the write operation appeared at the DRAM circuits one clock later at $t1$, due to the inherent delay through the buffer chip. But in FIG. 11, in addition to the inherent one clock delay, the buffer chip has added an extra two clocks of delay to the write operation, which is not issued to the DRAM chips until $t0+1+2=t3$. Because the DRAM chips receive the write operation at $t3$ and have a write CAS latency of three clocks, they expect to receive the write data at $t3+3=t6$. Because the memory controller issued the write operation at $t0$, and it expects a write CAS latency of five clocks, it issues the write data at time $t0+5=t5$. After a one clock delay through the buffer chip, the write data arrives at the DRAM chips at $t5+1=t6$, and the timing problem is solved.

It should be noted that extra delay of j clocks (beyond the inherent delay) which the buffer chip deliberately adds before issuing the write operation to the DRAM is the sum j clocks of the inherent delay of the address and control signals and the inherent delay of the data signals. In the example shown, both those inherent delays are one clock, so $j=2$.

FIG. 12 is a timing diagram illustrating operation of an FB-DIMM's AMB, which may be designed to send write data earlier to buffered stacks instead of delaying the write address and operation (as in FIG. 11). Specifically, it may use an early write CAS latency **1202** to compensate the timing of the buffer chip write operation. If the buffer chip has a cumulative (address and data) inherent delay of two clocks, the AMB may send the write data to the buffered stack two clocks early. This may not be possible in the case of registered DIMMs, in which the memory controller sends the write data directly to the buffered stacks (rather than via the AMB). In another embodiment, the memory controller itself could be designed to send write data early, to compensate for the j clocks of cumulative inherent delay caused by the buffer chip.

In the example shown, the memory controller issues the write operation at $t0$. After a one clock inherent delay through the buffer chip, the write operation arrives at the DRAM at $t1$. The DRAM expects the write data at $t1+3=t4$. The industry specification would suggest a nominal write data time of $t0+5=t5$, but the AMB (or memory controller), which already has the write data (which are provided with the write operation), is configured to perform an early write at $t5-2=t3$. After the inherent delay **1203** through the buffer chip, the write data arrive at the DRAM at $t3+1=t4$, exactly when the DRAM expects it—specifically, with a three-cycle DRAM Write CAS latency **1204** which is equal to the three-cycle Early Write CAS Latency **1202**.

FIG. 13 is a timing diagram **1300** illustrating bus conflicts which can be caused by delayed write operations. The delaying of write addresses and write operations may be performed by a buffer chip, a register, an AMB, etc. in a manner that is completely transparent to the memory controller of the host system. And, because the memory controller is unaware of this delay, it may schedule subsequent operations such as

11

activate or precharge operations, which may collide with the delayed writes on the address bus to the DRAM chips in the stack.

An example is shown, in which the memory controller issues a write operation **1302** at time **t0**. The buffer chip or AMB delays the write operation, such that it appears on the bus to the DRAM chips at time **t3**. Unfortunately, at time **t2** the memory controller issued an activate operation (control signal) **1304** which, after a one-clock inherent delay through the buffer chip, appears on the bus to the DRAM chips at time **t3**, colliding with the delayed write.

FIGS. **14** and **15** are a timing diagram **1400** and a timing diagram **1500** illustrating methods of avoiding such collisions. If the cumulative latency through the buffer chip is two clock cycles, and the native read CAS latency of the DRAM chips is four clock cycles, then in order to hide the delay of the address and control signals and the data signals through the buffer chip, the buffer chip presents the host system with an interface to an emulated memory having a read CAS latency of six clock cycles. And if the tRCD and tRP of the DRAM chips are four clock cycles each, the buffer chip tells the host system that they are six clock cycles each in order to allow the buffer chip to delay the activate and precharge operations to avoid collisions in a manner that is transparent to the host system.

For example, a buffered stack that uses 4-4-4 DRAM chips (that is, CAS latency=4, tRCD=4, and tRP=4) may appear to the host system as one larger DRAM that uses 6-6-6 timing.

Since the buffered stack appears to the host system's memory controller as having a tRCD of six clock cycles, the memory controller may schedule a column operation to a bank six clock cycles (at time **t6**) after an activate (row) operation (at time **t0**) to the same bank. However, the DRAM chips in the stack actually have a tRCD of four clock cycles. This gives the buffer chip time to delay the activate operation by up to two clock cycles, avoiding any conflicts on the address bus between the buffer chip and the DRAM chips, while ensuring correct read and write timing on the channel between the memory controller and the buffered stack.

As shown, the buffer chip may issue the activate operation to the DRAM chips one, two, or three clock cycles after it receives the activate operation from the memory controller, register, or AMB. The actual delay selected may depend on the presence or absence of other DRAM operations that may conflict with the activate operation, and may optionally change from one activate operation to another. In other words, the delay may be dynamic. A one-clock delay (**1402A**, **1502A**) may be accomplished simply by the inherent delay through the buffer chip. A two-clock delay (**1402B**, **1502B**) may be accomplished by adding one clock of additional delay to the one-clock inherent delay, and a three-clock delay (**1402C**, **1502C**) may be accomplished by adding two clocks of additional delay to the one-clock inherent delay. A read, write, or activate operation issued by the memory controller at time **t6** will, after a one-clock inherent delay through the buffer chip, be issued to the DRAM chips at time **t7**. A preceding activate or precharge operation issued by the memory controller at time **t0** will, depending upon the delay, be issued to the DRAM chips at time **t1**, **t2**, or **t3**, each of which is at least the tRCD or tRP of four clocks earlier than the **t7** issuance of the read, write, or activate operation.

Since the buffered stack appears to the memory controller to have a tRP of six clock cycles, the memory controller may schedule a subsequent activate (row) operation to a bank a minimum of six clock cycles after issuing a precharge operation to that bank. However, since the DRAM circuits in the stack actually have a tRP of four clock cycles, the buffer chip

12

may have the ability to delay issuing the precharge operation to the DRAM chips by up to two clock cycles, in order to avoid any conflicts on the address bus, or in order to satisfy the tRAS requirements of the DRAM chips.

In particular, if the activate operation to a bank was delayed to avoid an address bus conflict, then the precharge operation to the same bank may be delayed by the buffer chip to satisfy the tRAS requirements of the DRAM. The buffer chip may issue the precharge operation to the DRAM chips one, two, or three clock cycles after it is received. The delay selected may depend on the presence or absence of address bus conflicts or tRAS violations, and may change from one precharge operation to another.

FIG. **16** illustrates a buffered stack **1600** according to one embodiment of this invention. The buffered stack includes four 512 Mb DDR2 DRAM circuits (chips) **1602** which a buffer chip **1604** maps to a single 2 Gb DDR2 DRAM.

Although the multiple DRAM chips appear to the memory controller as though they were a single, larger DRAM, the combined power dissipation of the actual DRAM chips may be much higher than the power dissipation of a monolithic DRAM of the same capacity. In other words, the physical DRAM may consume significantly more power than would be consumed by the emulated DRAM.

As a result, a DIMM containing multiple buffered stacks may dissipate much more power than a standard DIMM of the same actual capacity using monolithic DRAM circuits. This increased power dissipation may limit the widespread adoption of DIMMs that use buffered stacks. Thus, it is desirable to have a power management technique which reduces the power dissipation of DIMMs that use buffered stacks.

In one such technique, the DRAM circuits may be opportunistically placed in low power states or modes. For example, the DRAM circuits may be placed in a precharge power down mode using the clock enable (CKE) pin of the DRAM circuits.

A single rank registered DIMM (R-DIMM) may contain a plurality of buffered stacks, each including four x4 512 Mb DDR2 SDRAM chips and appear (to the memory controller via emulation by the buffer chip) as a single x4 2 Gb DDR2 SDRAM. The JEDEC standard indicates that a 2 Gb DDR2 SDRAM may generally have eight banks, shown in FIG. **16** as Bank **0** to Bank **7**. Therefore, the buffer chip may map each 512 Mb DRAM chip in the stack to two banks of the equivalent 2 Gb DRAM, as shown; the first DRAM chip **1602A** is treated as containing banks **0** and **1**, **1602B** is treated as containing banks **2** and **4**, and so forth.

The memory controller may open and close pages in the DRAM banks based on memory requests it receives from the rest of the host system. In some embodiments, no more than one page may be able to be open in a bank at any given time. In the embodiment shown in FIG. **16**, each DRAM chip may therefore have up to two pages open at a time. When a DRAM chip has no open pages, the power management scheme may place it in the precharge power down mode.

The clock enable inputs of the DRAM chips may be controlled by the buffer chip, or by another chip (not shown) on the R-DIMM, or by an AMB (not shown) in the case of an FB-DIMM, or by the memory controller, to implement the power management technique. The power management technique may be particularly effective if it implements a closed page policy.

Another optional power management technique may include mapping a plurality of DRAM circuits to a single bank of the larger capacity emulated DRAM. For example, a buffered stack (not shown) of sixteen x4 256 Mb DDR2 SDRAM chips may be used in emulating a single x4 4 Gb

13

DDR2 SDRAM. The 4 Gb DRAM is specified by JEDEC as having eight banks of 512 Mbs each, so two of the 256 Mb DRAM chips may be mapped by the buffer chip to emulate each bank (whereas in FIG. 16 one DRAM was used to emulate two banks).

However, since only one page can be open in a bank at any given time, only one of the two DRAM chips emulating that bank can be in the active state at any given time. If the memory controller opens a page in one of the two DRAM chips, the other may be placed in the precharge power down mode. Thus, if a number p of DRAM chips are used to emulate one bank, at least $p-1$ of them may be in a power down mode at any given time; in other words, at least $p-1$ of the p chips are always in power down mode, although the particular powered down chips will tend to change over time, as the memory controller opens and closes various pages of memory.

As a caveat on the term "always" in the preceding paragraph, the power saving operation may comprise operating in precharge power down mode except when refresh is required.

FIG. 17 is a flow chart 1700 illustrating one embodiment of a method of refreshing a plurality of memory circuits. A refresh control signal is received (1702) e.g. from a memory controller which intends to refresh an emulated memory circuit. In response to receipt of the refresh control signal, a plurality of refresh control signals are sent (1704) e.g. by a buffer chip to a plurality of physical memory circuits at different times. These refresh control signals may optionally include the received refresh control signal or an instantiation or copy thereof. They may also, or instead, include refresh control signals that are different in at least one aspect (format, content, etc.) from the received signal.

In some embodiments, at least one first refresh control signal may be sent to a first subset of the physical memory circuits at a first time, and at least one second refresh control signal may be sent to a second subset of the physical memory circuits at a second time. Each refresh signal may be sent to one physical memory circuit, or to a plurality of physical memory circuits, depending upon the particular implementation.

The refresh control signals may be sent to the physical memory circuits after a delay in accordance with a particular timing. For example, the timing in which they are sent to the physical memory circuits may be selected to minimize an electrical current drawn by the memory, or to minimize a power consumption of the memory. This may be accomplished by staggering a plurality of refresh control signals. Or, the timing may be selected to comply with e.g. a tRFC parameter associated with the memory circuits.

To this end, physical DRAM circuits may receive periodic refresh operations to maintain integrity of data stored therein. A memory controller may initiate refresh operations by issuing refresh control signals to the DRAM circuits with sufficient frequency to prevent any loss of data in the DRAM circuits. After a refresh control signal is issued, a minimum time tRFC may be required to elapse before another control signal may be issued to that DRAM circuit. The tRFC parameter value may increase as the size of the DRAM circuit increases.

When the buffer chip receives a refresh control signal from the memory controller, it may refresh the smaller DRAM circuits within the span of time specified by the tRFC of the emulated DRAM circuit. Since the tRFC of the larger, emulated DRAM is longer than the tRFC of the smaller, physical DRAM circuits, it may not be necessary to issue any or all of the refresh control signals to the physical DRAM circuits simultaneously. Refresh control signals may be issued separately to individual DRAM circuits or to groups of DRAM

14

circuits, provided that the tRFC requirements of all physical DRAMs has been met by the time the emulated DRAM's tRFC has elapsed. In use, the refreshes may be spaced in time to minimize the peak current draw of the combination buffer chip and DRAM circuit set during a refresh operation.

FIG. 18 illustrates one embodiment of an interface circuit such as may be utilized in any of the above-described memory systems, for interfacing between a system and memory circuits. The interface circuit may be included in the buffer chip, for example.

The interface circuit includes a system address signal interface for sending/receiving address signals to/from the host system, a system control signal interface for sending/receiving control signals to/from the host system, a system clock signal interface for sending/receiving clock signals to/from the host system, and a system data signal interface for sending/receiving data signals to/from the host system. The interface circuit further includes a memory address signal interface for sending/receiving address signals to/from the physical memory, a memory control signal interface for sending/receiving control signals to/from the physical memory, a memory clock signal interface for sending/receiving clock signals to/from the physical memory, and a memory data signal interface for sending/receiving data signals to/from the physical memory.

The host system includes a set of memory attribute expectations, or built-in parameters of the physical memory with which it has been designed to work (or with which it has been told, e.g. by the buffer circuit, it is working). Accordingly, the host system includes a set of memory interaction attributes, or built-in parameters according to which the host system has been designed to operate in its interactions with the memory. These memory interaction attributes and expectations will typically, but not necessarily, be embodied in the host system's memory controller.

In addition to physical storage circuits or devices, the physical memory itself has a set of physical attributes.

These expectations and attributes may include, by way of example only, memory timing, memory capacity, memory latency, memory functionality, memory type, memory protocol, memory power consumption, memory current requirements, and so forth.

The interface circuit includes memory physical attribute storage for storing values or parameters of various physical attributes of the physical memory circuits. The interface circuit further includes system emulated attribute storage. These storage systems may be read/write capable stores, or they may simply be a set of hard-wired logic or values, or they may simply be inherent in the operation of the interface circuit.

The interface circuit includes emulation logic which operates according to the stored memory physical attributes and the stored system emulation attributes, to present to the system an interface to an emulated memory which differs in at least one attribute from the actual physical memory. The emulation logic may, in various embodiments, alter a timing, value, latency, etc. of any of the address, control, clock, and/or data signals it sends to or receives from the system and/or the physical memory. Some such signals may pass through unaltered, while others may be altered. The emulation logic may be embodied as, for example, hard wired logic, a state machine, software executing on a processor, and so forth.

CONCLUSION

When one component is said to be "adjacent" another component, it should not be interpreted to mean that there is

15

absolutely nothing between the two components, only that they are in the order indicated.

The physical memory circuits employed in practicing this invention may be any type of memory whatsoever, such as: DRAM, DDR DRAM, DDR2 DRAM, DDR3 DRAM, SDRAM, QDR DRAM, DRDRAM, FPM DRAM, VDRAM, EDO DRAM, BEDO DRAM, MDRAM, SGRAM, MRAM, IRAM, NAND flash, NOR flash, PSRAM, wetware memory, etc.

The physical memory circuits may be coupled to any type of memory module, such as: DIMM, R-DIMM, SO-DIMM, FB-DIMM, unbuffered DIMM, etc.

The system device which accesses the memory may be any type of system device, such as: desktop computer, laptop computer, workstation, server, consumer electronic device, television, personal digital assistant (PDA), mobile phone, printer or other peripheral device, etc.

The various features illustrated in the figures may be combined in many ways, and should not be interpreted as though limited to the specific embodiments in which they were explained and shown.

Those skilled in the art, having the benefit of this disclosure, will appreciate that many other variations from the foregoing description and drawings may be made within the scope of the present invention. Indeed, the invention is not limited to the details described above. Rather, it is the following claims including any amendments thereto that define the scope of the invention.

What is claimed is:

1. A memory apparatus for use with a host system, the memory apparatus comprising:

a plurality of memory circuits;

one or more first components of a first type, each of the one or more first components being electrically couplable to the host system; and

one or more second components of a second type different from the first type, each of the one or more second components being electrically couplable to the host system, the first and second components being operable to present to the host system a simulated memory circuit where there is a difference in at least one aspect between the simulated memory circuit and at least one of the plurality of memory circuits,

wherein each memory circuit of the plurality of memory circuits is electrically coupled to at least one of the one or more first components of the first type and to at least one of the one or more second components of the second type, where the one or more first components and the one or more second components are further operable to identify at least one of the plurality of memory circuits that is not being accessed and to perform a power-saving operation on the at least one of the plurality of memory circuits identified as not being accessed.

2. The memory apparatus of claim 1, where the one or more first components are operable to present a control interface between the host system and the plurality of memory circuits, and

the one or more second components are operable to present a data interface between the host system and the plurality of memory circuits.

3. The memory apparatus of claim 2, where the first type is a register and the second type is a buffer.

4. The memory apparatus of claim 2, where the control interface is configured to send and receive control, command and clock signals, and the data interface is configured to send and receive data signals.

16

5. The memory apparatus of claim 1, where the plurality of memory circuits comprise a stack of dynamic random access memory (DRAM) circuits and are coupled to a dual-inline memory module (DIMM).

6. The memory apparatus of claim 5, where the DIMM is a registered DIMM (R-DIMM).

7. The memory apparatus of claim 5, where the stack further includes the one or more second components of the second type.

8. The memory apparatus of claim 5, where the stack comprises a plurality of address, control and clock buses.

9. The memory apparatus of claim 5, where the stack comprises a single shared address, control and clock bus coupled to each of the plurality of memory circuits in the stack.

10. The memory apparatus of claim 5, where the stack comprises a shared data bus coupled to two or more of the plurality of memory circuits.

11. The memory apparatus of claim 5, where the stack comprises a plurality of data buses, each of the plurality of data buses being coupled to two or more of the plurality of memory circuits.

12. The memory apparatus of claim 5, where the stack comprises a plurality of data buses, each of the plurality of data buses being respectively coupled to a different one of the plurality of memory circuits.

13. The memory apparatus of claim 5, where the one or more second components are packaged separately from the plurality of memory circuits.

14. The memory apparatus of claim 5, where the one or more second components are packaged together with the plurality of memory circuits.

15. The memory apparatus of claim 1, where the power-saving operation comprises placing the at least one memory circuit identified as not being accessed in a precharge power down mode.

16. The memory apparatus of claim 15, where the one or more first components and the one or more second components are operable to place the at least one memory circuit identified as not being accessed in a precharge power down mode by controlling a clock enable input of the at least one identified memory circuit.

17. The memory apparatus of claim 1, where the one or more first components and the one or more second components are operable to identify the at least one of the plurality of memory circuits as not being accessed based on a number of open pages in at least one memory circuit of the plurality of memory circuits.

18. The memory apparatus of claim 1, where the one or more second components of the second type comply with a JEDEC standard and have forwarding, storing, or buffering capabilities.

19. The memory apparatus of claim 1, where the difference in at least one aspect comprises a signal difference where the signal is associated with a mode register operation.

20. The memory apparatus of claim 1, where the first and second components are electrically coupled to each of the memory circuits in a stack and where the stack includes a shared address, control and clock bus coupled to each of the plurality of memory circuits.

21. The memory apparatus of claim 1, where the difference in at least one aspect comprises a number of banks.

22. The memory apparatus of claim 21, where the plurality of memory circuits has eight banks and the simulated memory circuit has four banks or two banks.

17

23. The memory apparatus of claim 1, where the difference in at least one aspect includes a number of row-address signals.

24. The memory apparatus of claim 1, where the first components and second components are operable to perform the power saving operation by controlling a clock-enable pin of at least one of the plurality of memory circuits.

18

25. The memory apparatus of claim 1, where the first components and second components are further operable to select one or more of the plurality of memory circuits by generating one or more chip select signals and to perform an operation on the one or more selected memory circuits.

* * * * *