

(12) **Patent Application Publication**
TAKANO et al.

(43) **Pub. Date:** **Jan. 17, 2019**

(52) U.S. Cl.

CPC **G02B 6/3825** (2013.01); **G02B 6/387**
(2013.01); **G02B 6/3873** (2013.01); **G02B**
6/4292 (2013.01); **G02B 6/4228** (2013.01);
G02B 6/3893 (2013.01)

(71) Applicant: **SENKO Advanced Components, Inc.,**
Marlborough, MA (US)

(72) Inventors: **Kazuyoshi TAKANO**, Southborough, MA (US); **Jimmy Jun-Fu CHANG**, Worcester, MA (US)

(57) **ABSTRACT**

(21) Appl. No.: 16/035,691

(22) Filed: **Jul. 15, 2018**


Related U.S. Application Data

(60) Provisional application No. 62/532,710, filed on Jul. 14, 2017, provisional application No. 62/549,655, filed on Aug. 24, 2017, provisional application No. 62/588,276, filed on Nov. 17, 2017.

Publication Classification

(51) **Int. Cl.**
G02B 6/38 (2006.01)
G02B 6/42 (2006.01)

An optical connector holding two or more LC-type optical ferrules is provided. The optical connector includes an outer body, an inner front body accommodating the two or more LC-type optical ferrules, ferrule springs for urging the optical ferrules towards a mating receptacle, and a back body for supporting the ferrule springs. The outer body and the inner front body are configured such that four LC-type optical ferrules are accommodated in a small form-factor pluggable (SFP) transceiver footprint or eight LC-type optical ferrules are accommodated in a quad small form-factor pluggable (QSFP) transceiver footprint. A mating receptacle (transceiver or adapter) includes a receptacle hook and a housing with an opening that accommodates the receptacle hook in a flexed position as the optical connector makes connection with the mating receptacle by introducing the receptacle hook into an optical receptacle hook recess.






FIG. 1A
(Prior Art)




FIG. 1B
(Prior Art)




FIG. 1C
(Prior Art)

FIG. 1D
(Prior Art)




FIG. 2A
(Prior Art)

FIG. 2B
(Prior Art)




FIG. 2D
(Prior Art)






FIG. 2C
(Prior Art)











FIG. 5















FIG. 9












FIG. 14A




FIG. 14B




FIG. 14C




FIG. 15A









FIG. 15B












FIG. 20






FIG. 21A








FIG. 23A




FIG. 23B




FIG. 24




FIG. 25A




FIG. 25B




FIG. 26




FIG. 27A




FIG. 27B




FIG. 28A

FIG. 28B




FIG. 29A




FIG. 29B




FIG. 29C




FIG. 29D




FIG. 29E




FIG. 30




FIG. 31






FIG. 32A








FIG. 33B




FIG. 34B

FIG. 34A




FIG. 34C




FIG. 35B




FIG. 35A




FIG. 35C





FIG. 36A






FIG. 37




FIG. 38





FIG. 39






FIG. 41





FIG. 42B

FIG. 42A






FIG. 44A




FIG. 44B




FIG. 44C




FIG. 45




FIG. 46




FIG. 47





FIG. 48








FIG. 50





ULTRA-SMALL FORM FACTOR OPTICAL CONNECTORS

CROSS-REFERENCE TO RELATED APPLICATIONS

[0001] This application claims priority to U. S Provisional Patent Application Ser. Nos. 62/532,710 filed Jul. 14, 2017, 62/549,655 filed Aug. 24, 2017, and 62/588,276 filed Nov. 17, 2018, the disclosures of which are incorporated by reference herein.

FIELD OF THE INVENTION

[0002] The present disclosure relates generally to ultra-small form factor optical connectors and related connections within adapters and optical transceivers.

BACKGROUND

[0003] The prevalence of the Internet has led to unprecedented growth in communication networks. Consumer demand for service and increased competition has caused network providers to continuously find ways to improve quality of service while reducing cost.

[0004] Certain solutions have included deployment of high-density interconnect panels. High-density interconnect panels may be designed to consolidate the increasing volume of interconnections necessary to support the fast-growing networks into a compacted form factor, thereby increasing quality of service and decreasing costs such as floor space and support overhead. However, room for improvement in the area of data centers, specifically as it relates to fiber optic connections, still exists. For example, manufacturers of connectors and adapters are always looking to reduce the size of the devices, while increasing ease of deployment, robustness, and modifiability after deployment. In particular, more optical connectors may need to be accommodated in the same footprint previously used for a smaller number of connectors in order to provide backward compatibility with existing data center equipment. For example, one current footprint is known as the small form-factor pluggable transceiver footprint (SFP). This footprint currently accommodates two LC-type ferrule optical connections. However, it may be desirable to accommodate four optical connections (two duplex connections of transmit/receive) within the same footprint. Another current footprint is the quad small form-factor pluggable (QSFP) transceiver footprint. This footprint currently accommodates four LC-type ferrule optical connections. However, it may be desirable to accommodate eight optical connections of LC-type ferrules (four duplex connections of transmit/receive) within the same footprint.

[0005] In communication networks, such as data centers and switching networks, numerous interconnections between mating connectors may be compacted into high-density panels. Panel and connector producers may optimize for such high densities by shrinking the connector size and/or the spacing between adjacent connectors on the panel. While both approaches may be effective to increase the panel connector density, shrinking the connector size and/or spacing may also increase the support cost and diminish the quality of service.

[0006] In a high-density panel configuration, adjacent connectors and cable assemblies may obstruct access to the individual release mechanisms. Such physical obstructions

may impede the ability of an operator to minimize the stresses applied to the cables and the connectors. For example, these stresses may be applied when the user reaches into a dense group of connectors and pushes aside surrounding optical fibers and connectors to access an individual connector release mechanism with his/her thumb and forefinger. Overstressing the cables and connectors may produce latent defects, compromise the integrity and/or reliability of the terminations, and potentially cause serious disruptions to network performance.

[0007] While an operator may attempt to use a tool, such as a screwdriver, to reach into a dense group of connectors and activate a release mechanism, adjacent cables and connectors may obstruct the operator's line of sight, making it difficult to guide the tool to the release mechanism without pushing aside the adjacent cables. Moreover, even when the operator has a clear line of sight, guiding the tool to the release mechanism may be a time-consuming process. Thus, using a tool may not be effective at reducing support time and increasing the quality of service.

SUMMARY OF THE INVENTION

[0008] An optical connector holding two or more LC-type optical ferrules is provided. The optical connector includes an outer body, an inner front body accommodating the two or more LC-type optical ferrules, ferrule springs for urging the optical ferrules towards a mating receptacle, and a back body for supporting the ferrule springs. The outer body and the inner front body are configured such that four LC-type optical ferrules are accommodated in a small form-factor pluggable (SFP) transceiver footprint or eight LC-type optical ferrules are accommodated in a quad small form-factor pluggable (QSFP) transceiver footprint. A mating receptacle (transceiver or adapter) includes a receptacle hook and a housing with an opening that accommodates the receptacle hook in a flexed position as the optical connector makes connection with the mating receptacle by introducing the receptacle hook into an optical receptacle hook recess.

BRIEF DESCRIPTION OF THE DRAWINGS

[0009] FIG. 1A is a perspective view of a prior art standard 6.25 mm pitch LC connector SFP;

[0010] FIG. 1B is a perspective view of a prior art standard 6.25 mm pitch LC adapter;

[0011] FIG. 1C is a top view of the prior art adapter of FIG. 1B;

[0012] FIG. 1D is a front view of the prior art adapter of FIG. 1B, showing the 6.25 mm pitch;

[0013] FIG. 2A is a perspective view of a prior art LC duplex connector;

[0014] FIG. 2B is a perspective view of a prior art LC duplex connector with a remote release pull tab;

[0015] FIG. 2C is a top view of a prior art LC connector used in the embodiments shown in FIGS. 2A and 2B;

[0016] FIG. 2D is a side view of the prior art LC connector of FIG. 2C;

[0017] FIG. 3 is an exploded view of one embodiment of a connector;

[0018] FIG. 4 is a perspective view of one embodiment of a connector;

[0019] FIG. 5 is a perspective view of one embodiment of a connector with the outer housing removed from the front body.

[0020] FIG. 6 is a perspective view of one embodiment of a duplex connector;

[0021] FIG. 7 is a perspective view of another embodiment of a duplex connector;

[0022] FIG. 8 is a perspective view of one embodiment of a quad connector;

[0023] FIG. 9 is another perspective view of one embodiment of a quad connector;

[0024] FIG. 10 shows various embodiments of adapter types;

[0025] FIG. 11A is a side view of a connector connected to an adapter;

[0026] FIG. 11B is a side view of a connector being removed from an adapter;

[0027] FIG. 12A is a side view of the outer housing of a connector being removed;

[0028] FIG. 12B is a perspective view of a transparent outer housing of a connector showing the front body;

[0029] FIG. 13 is a perspective view of one embodiment of a quad connector inserted into a corresponding adapter;

[0030] FIGS. 14A-C are illustrative examples of cable management using various embodiments of connectors;

[0031] FIG. 15A-B are illustrative examples of cable management using multiple fiber strands per jacket;

[0032] FIG. 16 is an illustrative example of using a cable management system using multiple fiber strands per jacket.

[0033] FIG. 17 is another illustrative example of using a cable management system using multiple fiber strands per jacket.

[0034] FIGS. 18A-B are various views of one embodiment of a MT connector.

[0035] FIGS. 19A-D are illustrative examples of possible alternative connector designs.

[0036] FIG. 20 shows moving two connectors from a duplex connector to two simplex connectors.

[0037] FIG. 21A is an exploded view of a micro optical connector according to an embodiment.

[0038] FIG. 21B is a perspective view of the assembled micro optical connector of FIG. 21A.

[0039] FIG. 22 is a front view of the micro optical connector of FIG. 21B showing overall connector dimensions and ferrule pitch.

[0040] FIG. 23A is a cross-sectional view of the micro optical connector of FIG. 21B latched into the adapter of FIG. 24.

[0041] FIG. 23B is a cross-sectional view of the micro optical connectors of FIG. 21B unlatched from the adapter of FIG. 24.

[0042] FIG. 24 is an exploded view of an adapter for the micro optical connectors of FIG. 21B.

[0043] FIG. 25A is a cross-sectional view of the adapter of FIG. 24, assembled.

[0044] FIG. 25B is a cross-sectional side view of the adapter housing of FIG. 24.

[0045] FIG. 26 is a front view of the assembled adapter of FIG. 24.

[0046] FIG. 27A is an isometric view of the front body of the micro optical connector of FIG. 21A.

[0047] FIG. 27B is a right side view of the front body of FIG. 27A.

[0048] FIG. 28A is an isometric view of the back body of the micro optical connector of FIG. 21A.

[0049] FIG. 28B is a side view of the back body of FIG. 28A.

[0050] FIG. 29A is an isometric view of the outer housing of the micro optical connector of FIG. 21A.

[0051] FIG. 29B is a front view of the outer housing of FIG. 29A.

[0052] FIG. 29C is a cross-sectional view of the outer housing of FIG. 29A showing the top of an orientation protrusion.

[0053] FIG. 29D is an inner view of the outer housing of FIG. 29A;

[0054] FIG. 29E is an inner view of the outer housing of FIG. 29A.

[0055] FIG. 30 is a side view of an adapter hook of the adapter of FIG. 24.

[0056] FIG. 31 is an isometric view of the adapter of FIG. 24 assembled with the micro optical connectors of FIG. 21B.

[0057] FIG. 32A is cross-sectional view of a prior art connector showing a latch gap.

[0058] FIG. 32B is a cross-sectional view of the micro optical connector of FIG. 21B latched (left) and unlatched (right) within the adapter of FIG. 24, assembled.

[0059] FIG. 33A depicts the micro optical connector of FIG. 21B in a QSFP footprint, depicting dimensions in millimeters.

[0060] FIG. 33B depicts the micro optical connectors of FIG. 21B in an SFP footprint, depicting dimensions in millimeters.

[0061] FIG. 34A-34C depicts adapter hooks interacting with the micro optical connectors of FIG. 21B before (FIG. 34A), during (FIG. 34B), and after (FIG. 34C) latching.

[0062] FIG. 35A-FIG. 35C depicts the micro optical connector of FIG. 21B side flap operation before (FIG. 35A), during (FIG. 35B), and after (FIG. 35C) latching.

[0063] FIG. 36A depicts plural micro optical connectors in a transceiver.

[0064] FIG. 36B is a front view of the transceiver of FIG. 36A.

[0065] FIG. 37 is an exploded view of a micro optical connector according to a further embodiment.

[0066] FIG. 38 is an isometric view of a front body of the micro optical connector of FIG. 37.

[0067] FIG. 39 is an isometric view of a back body of the micro optical connector of FIG. 37.

[0068] FIGS. 40A, 40B, and 40C depict a technique for reversing polarity of the optical connector of FIG. 37.

[0069] FIG. 41 is an exploded view of a micro optical connector according to a further embodiment.

[0070] FIG. 42A is an isometric view of the front body of the micro optical connector of FIG. 41.

[0071] FIG. 42B is a side view of the front body of FIG. 42A.

[0072] FIG. 43 is an isometric view of the back body of the micro optical connector of FIG. 41.

[0073] FIGS. 44A, 44B, and 44C are isometric views of the outer housings that may be used with any of the micro optical connectors of FIGS. 21A, 37, and 41.

[0074] FIG. 45 is an exploded view of an adapter according to a further embodiment.

[0075] FIG. 46 is a cross-section of the adapter of FIG. 45, assembled.

[0076] FIG. 47 is an exploded view of a connector according to another embodiment.

[0077] FIG. 48 is an isometric view of the back body and the back post of the connector of FIG. 47.

[0078] FIG. 49 is a cross-section of the back post of FIG. 47 assembled with optical fibers.

[0079] FIG. 50 is a front view of the connector of FIG. 47.

[0080] FIG. 51 is an isometric view of the boot of the connector of FIG. 47.

[0081] FIG. 52 is a front view of the adapter of FIG. 45.

DETAILED DESCRIPTION

[0082] This disclosure is not limited to the particular systems, devices and methods described, as these may vary. The terminology used in the description is for the purpose of describing the particular versions or embodiments only, and is not intended to limit the scope.

[0083] As used in this document, the singular forms “a,” “an,” and “the” include plural references unless the context clearly dictates otherwise. Unless defined otherwise, all technical and scientific terms used herein have the same meanings as commonly understood by one of ordinary skill in the art. Nothing in this disclosure is to be construed as an admission that the embodiments described in this disclosure are not entitled to antedate such disclosure by virtue of prior invention. As used in this document, the term “comprising” means “including, but not limited to.”

[0084] The following terms shall have, for the purposes of this application, the respective meanings set forth below.

[0085] A connector, as used herein, refers to a device and/or components thereof that connects a first module or cable to a second module or cable. The connector may be configured for fiber optic transmission or electrical signal transmission. The connector may be any suitable type now known or later developed, such as, for example, a ferrule connector (FC), a fiber distributed data interface (FDDI) connector, an LC connector, a mechanical transfer (MT) connector, a square connector (SC) connector, a CS connector, or a straight tip (ST) connector. The connector may generally be defined by a connector housing body. In some embodiments, the housing body may incorporate any or all of the components described herein.

[0086] A “fiber optic cable” or an “optical cable” refers to a cable containing one or more optical fibers for conducting optical signals in beams of light. The optical fibers can be constructed from any suitable transparent material, including glass, fiberglass, and plastic. The cable can include a jacket or sheathing material surrounding the optical fibers. In addition, the cable can be connected to a connector on one end or on both ends of the cable.

[0087] Various embodiments described herein generally provide a remote release mechanism such that a user can remove cable assembly connectors that are closely spaced together on a high density panel without damaging surrounding connectors, disrupting transmissions through surrounding connectors, and/or the like. Various embodiments also provide narrow-pitch LC duplex connectors and narrow-width multi-fiber connectors, for use, for example, with future narrow-pitch LC SFPs and future narrow width SFPs. The remote release mechanisms allow use of the narrow-pitch LC duplex connectors and narrow-width multi-fiber connectors in dense arrays of narrow-pitch LC SFPs and narrow-width multi-fiber SFPs.

[0088] FIG. 1A shows a perspective view of a prior art standard 6.25 mm pitch LC connector SFP 100. The SFP 100 is configured to receive a duplex connector and provides two receptacles 102, each for receiving a respective LC connector.

The pitch 104 is defined as the axis-to-axis distance between the central longitudinal axes of each of the two receptacles 102. FIG. 1B shows a perspective view of a prior art standard 6.25 mm pitch LC adapter 106. The adapter 106 is also configured to receive a duplex connector, and provides two receptacles 108, each for receiving a respective LC connector. FIG. 1C is a top view of the adapter 106 of FIG. 1B. The pitch of the adapter 106 is defined similarly to that of the SFP 100, as the axis-to-axis distance between the central longitudinal axes of each of the two receptacles 108, as illustrated in FIG. 1D, which shows a front view of the adapter 106.

[0089] FIG. 2A shows a prior art LC duplex connector 200 that may be used with the conventional SFP 100 and the conventional adapter 106. The LC duplex connector 200 includes two conventional LC connectors 202. FIG. 2B shows another prior art LC duplex connector 204 having a remote release pull tab 206, and including two conventional LC connectors 208. As shown, the remote release pull tab includes two prongs 210, each configured to couple to the extending member 212 of a respective LC connector 208. FIGS. 2C and 2D show top and side views, respectively, of the conventional LC connector 208, having a width of 5.6 mm, and further showing the extending member 212.

[0090] As discussed herein, current connectors may be improved by various means, such as, for example, reducing the footprint, increasing the structural strength, enabling polarity changes, etc. Various embodiments disclosed herein offer improvements over the current state of the art, as will be further discussed below.

[0091] In some embodiments, as shown in FIG. 3, a connector 300 may comprise various components. Referring to FIG. 3, an illustrative embodiment of a connector 300 is shown in an exploded view to display detail. In some embodiments, and as discussed further herein, a connector 300 may have an outer housing 301, a front body 302, one or more ferrules 303, one or more ferrule flanges 304, one or more springs 305, a back body 306, a back post 307, a crimp ring 308, and a boot 309. In some embodiments, the back body 306 may comprise one or more protrusions 306.1 which may interlock with a window/cutout 302.1 in the front body 302. This may allow for the back body 306 and the front body 302 to be securely fastened together around the ferrule(s) 303, ferrule flange(s) 304, and the spring(s) 305. The elements of FIG. 3 are configured such that two optical connectors having four LC-type optical ferrules may be accommodated in a small form-factor pluggable (SFP) transceiver footprint or at least two optical connectors having a total of eight LC-type optical ferrules may be accommodated in a quad small form-factor pluggable (QSFP) transceiver footprint.

[0092] Referring now to FIG. 4, an embodiment is shown wherein the connector 400 is assembled. In some embodiments, the assembled connector may have an outer housing 401, a front body 402 positioned within the outer housing, one or more ferrules 403, one or more ferrule flanges (not shown), one or more springs (not shown), a back body 406, a back post (not shown), a crimp ring (not shown), a boot 409, and a push-pull tab 410. In some embodiments, the connector may have one or more latching mechanisms made up of a window 412 on the outer housing 401 near the push-pull tab 410 and a protrusion 413 on the front body. The latching mechanism made up of the window 412 and protrusion 413 securely attaches the outer housing 401 to the

front body 402. In a further embodiment, the outer housing 401 may have a recess 411 to receive a locking tab or locking mechanism from an adapter (depicted in FIG. 13, below). The recess 411 of the outer housing 401 is used to interlock with an adapter (depicted in FIG. 13, below) or transceiver receptacle to secure the connector into the adapter. As would be understood by one skilled in the art, the push-pull tab 410 enables removal of the connector from a receptacle without requiring additional tools. Alternatively, the push-pull tab may be eliminated and the connector removed manually. In one or more further embodiments, the outer housing 401 may also have a key 414. The key 414 may keep the connector in a given orientation when inserted into a receptacle such as an adapter or transceiver.

[0093] FIG. 5 depicts a procedure for changing the polarity of the optical connectors of the present disclosure. As shown in FIG. 5, in some embodiments, the latching mechanism of the connector 500 may be made up of two main parts: a window (not visible) and one or more protrusions 513. As illustrated in FIG. 5, the outer housing 501 can slide on to or be removed from the front body 502 by disengaging the latching mechanisms formed by the protrusion 513 exiting through the window, whereby it contacts a rear wall of the window (refer to FIG. 4 for an illustrated example of the outer housing being attached to the front body via the latching mechanism). In some embodiments, the push-pull tab 510 may be permanently attached to the outer housing 501, as shown.

[0094] The front body 502 may be removed from the outer housing 501, rotated 180° as indicated by arrow 520, and re-inserted into the outer housing. This allows for a change in the polarity of the front body 502, as shown by the arrow diagram in FIG. 5, and therefore the ferrules can switch quickly and easily without unnecessarily risking the delicate fiber cables and ferrules.

[0095] In some embodiments, it may be beneficial to connect two or more connectors together to increase structural integrity, reduce the overall footprint, and cut manufacturing costs. Accordingly, as shown in FIG. 6, a connector 600 may in some embodiments, utilize an outer housing 601 that is capable of holding two front bodies 602. Various other embodiments are disclosed herein, and it should be noted that the embodiments disclosed herein are all non-limiting examples shown for explanatory purposes only.

[0096] Accordingly, although the embodiment shown in FIG. 6 utilizes a duplex outer housing 601, additional or alternative embodiments may exist with more capacity, for example, six or eight optical connectors within a single outer housing. As shown in FIG. 6, in some embodiments, the outer housing 601 may accept two front bodies 602, each with two separate ferrules 603. As shown, the front body(s) 602 may securely fasten to the outer housing 601 via the latching mechanism 612 and 613. In additional embodiments, the push-pull tab 610 may be modified, as shown, such that a single tab can be used to free the two or more connectors from an adapter. As illustrated in FIG. 6, the uni-body push-pull tab 610 and the outer housing 601 may have two windows 612 with which to receive multiple protrusions 613 of the front body(s) 602. As discussed herein the recesses 611 of the outer housing 601 are used to secure the connectors to an adapter (depicted in FIG. 13 below). In one or more further embodiments, the connectors may have individual back bodies 606 and boots 609 (i.e., one back body/boot per front body) as shown.

[0097] Alternatively, in some embodiments, such as that shown in FIG. 7, the connector 700 may have a single boot 709 and a duplex (i.e., uni-body) back body 706 instead of individual back bodies (e.g., such as shown in FIG. 6). In some embodiments, the duplex back body 706 may have different dimensions than that of the individual back bodies of FIG. 6, such as, for example, they may be longer to accommodate the need for routing the fiber after it exits the boot 709. As with other embodiments discussed herein, the connector shown in FIG. 7 may also include an outer housing (e.g., duplex outer housing) 701, one or more ferrules 703, at least one latching mechanism formed by the protrusion (not shown) exiting through one or more windows 712, and a push-pull tab 710.

[0098] As stated, it may be beneficial to connect two or more connectors together to increase structural integrity, reduce the overall footprint, and cut manufacturing costs. Accordingly, similar to FIG. 6, FIG. 8 shows a connector 800 that may, in some embodiments, utilize an outer housing 801 that is capable of holding multiple (e.g., four) front bodies 802.

[0099] As shown in FIG. 8, some embodiments may have an outer housing 801 able to accept up to four front bodies 802, each with one or more ferrules 803. As shown, each front body 802 may securely fasten to the outer housing 801 via the latching mechanism 812 and 813. In additional embodiments, the push-pull tab 810 may be modified such that a single tab can be used to remove the up to four connectors from an adapter. As illustrated in FIG. 8, the push-pull tab 810 may include four recesses 811, which as discussed herein are used to secure the connector to a receptacle such as an adapter (shown in FIG. 13, below) or the front receptacle portion of a transceiver. In one or more further embodiments, the connectors may have individual back bodies 806 and boots 809 (i.e., one back body/boot per front body) as shown.

[0100] Similar to FIG. 8, FIG. 9 shows an embodiment where the outer housing 901 is able to accept up to four front bodies 902, each with one or more ferrules 903. As shown, each front body 902 may securely fasten to the outer housing 901 via the latching mechanism 912 and 913. In additional embodiments, the push-pull tab 910 may be modified such that a single tab can be used to remove the up to four CS connectors from an adapter. As illustrated in FIG. 9, the push-pull tab 910 may include four recesses 911, which as discussed herein are used to secure the connector to an adapter (shown in FIG. 13, below) or the optical receptacle portion of a transceiver. The FIG. 9 embodiment may utilize a single back body 906 and a single boot 909. In one or more further embodiments, the connectors may have individual back bodies 906 and boots 909 (i.e., one back body/boot for all four front bodies) as shown.

[0101] In another aspect, the present disclosure provides method for reconfiguring optical cables in which the outer housings of the connectors may be removed and the remaining portion of the assembled connector is inserted into a housing having a larger or smaller capacity. For example, the outer housings of plural two-ferrule capacity housings may be removed and the connector inner body and associated components inserted into a second outer housing that has either a four-ferrule or eight-ferrule capacity. Alternatively, an outer housing with a four-ferrule capacity may be removed and the inner bodies and associated components are inserted into two second outer housings, each of the two

second housings having a two-ferrule capacity. Similarly, an outer housing with an eight-ferrule capacity may be removed and replaced by two four-ferrule capacity housing or a four-ferrule capacity and two two-ferrule capacity housings. In this manner, cables may be flexibly reconfigured to match the capacity of a mating optical-electrical component such as a transceiver. This aspect of the present disclosure is demonstrated in connection with FIG. 10.

[0102] Referring now to FIG. 10, various embodiments may exist such as a single housing 1001 which receives a single connector 1002. Additional embodiments may also exist, such as a duplex housing 1003 which receives two connectors 1004 and/or a quad housing 1005 which may receive up to four connectors 1006. It should be understood by one skilled in the art that various other embodiments may exist that are not explicitly shown. For example, a housing with the capacity for 5, 6, 7, 8, 9, 10 or more connectors may be utilized for various embodiments disclosed herein. As shown below, it is desirable to have flexible housing configurations so that connectors may be grouped and ungrouped between optical and optoelectronic components such as adapters and transceivers.

[0103] Alternatively, in some embodiments the connector may utilize one or more duplex back bodies with a single boot, similar to that shown in FIG. 7. Thus, similar to FIG. 7, an embodiment may allow for a further reduced footprint, less cabling, and easier maintenance of the connector. Accordingly, one or more embodiments may have an outer housing that may accept up to four front bodies, each with one or more ferrules. In some embodiments, each front body may securely fasten to the outer housing via a latching mechanism. In additional embodiments, the push-pull tab may be modified such that a single tab can be used to free the up to four front bodies from an adapter. The push-pull tab may include four openings with which to receive multiple locking tabs of the outer housing. As discussed herein the locking tabs of the outer housing are used to secure the connectors to an adapter (shown in FIG. 13) or the optical receptacle portion of a transceiver.

[0104] In further embodiments, the connector may utilize a single uni-body back body with a single boot (i.e., as shown in FIG. 9). Thus, an embodiment may allow for a further reduced foot print, less cabling, and easier maintenance of the connector. Accordingly, one or more embodiments may have an outer housing that may accept up to four front bodies, each with one or more ferrules. Each front body may securely fasten to the outer housing via the latching mechanism as discussed herein. In additional embodiments, the push-pull tab may be modified such that a single tab can be used to remove up to four connectors from an adapter. The push-pull tab may include four openings with which to receive multiple locking tabs of the outer housing. As discussed herein the locking tabs of the outer housing are used to secure the connectors to an adapter.

[0105] The optical connectors of the present disclosure are all configured to be received in a receptacle. As used herein, the term “receptacle” relates generically to a housing that receives an optical connector. A receptacle includes both optical adapters, that is, components that mate two or more optical connectors, and transceivers, which include an optical receptacle to hold connectors that are to communicate with an optoelectronic component (e.g., a component that converts optical signals to electrical signals). As shown in FIG. 11A, in one embodiment 1100A, the outer housing

1101 may comprise one or more recesses 1111. As discussed and shown herein, the one or more recesses may allow for a receptacle 1114 to securely connect to the connector 1100A. Accordingly, in some embodiments, the receptacle 1114 may have a receptacle hook 1115, which is flexible and can secure the connector 1100A into the receptacle via latching onto the wall of the recess 1111, as shown. This latching takes place when the outer housing 1101 is pushed forward into the receptacle. The sloped portions of the outer housing 1101 allow the receptacle hook 1115 to slide up and over the front of the outer housing thereby securing the connector 1100A into the receptacle.

[0106] Additionally or alternatively, in some embodiments, such as that shown in FIG. 11B, a connector 1100B may be removed from a receptacle 1114 by pulling the connector away from the adapter as indicated by the directional arrow. In some embodiments, the force may be applied by a user via the push-pull tab 1110. Alternatively, when a push-pull tab is not present, the connector may still be manually removed from a receptacle. As shown in FIG. 11B, as the connector 1100B is removed from the receptacle 1114, the flexible receptacle hooks 1115 separate and slide up the slope of the end of the connector and allow for removal of the connector from the receptacle.

[0107] Referring now to FIGS. 12A and 12B, as discussed herein and previously shown in FIG. 5, the front body 1202 can be removed from the outer housing 1201. In some embodiments, a portion of the outer body 1201 can be flexibly extended away from the front body 1202 as shown by the arrows in FIG. 12A. As discussed herein, in some embodiments, the front body 1202 may comprise a protrusion 1213 which interlocks with a window (not shown) on the outer housing 1201. Accordingly, when force is applied to the outer housing 1201 in a manner that removes the one or more protrusions 1213 from the one or more windows (not shown, see FIG. 4), the front body 1202 may be removed from the outer housing.

[0108] Referring now to FIG. 13, an embodiment 1300 is shown in which the connector (not shown in its entirety) is inserted into a receptacle such as adapter 1314. In this specific non-limiting example, the connector is similar to that shown in FIG. 8 (i.e., comprising four front bodies each with their own back body 1306 and boot 1309). However, unlike FIG. 8, the embodiment shown here utilizes four individual push-pull tabs 1310 instead of a duplex push-pull tab system which manipulates two latching tabs per push-pull tab to allow the connector to be removed from the adapter 1314.

[0109] Various benefits and details have been discussed herein with regard to the connectors and their modularity (e.g., to include multiple connectors into a single housing). In addition to the reduced footprint, structural improvements, and cost reduction, various embodiments herein may also be beneficial with regard to reducing the burden of cabling in a data center environment. Illustrative embodiments shown in FIGS. 14A through 14C depict cable configurations that may be used to reduce the complexity of optical cables in a compact environment. Note that any of the optical connectors described in this disclosure may be used in these embodiments, including the optical connectors of FIGS. 21B, 37, and 41, to be discussed in detail below. FIG. 14A shows two duplex cables similar to the cable shown in FIG. 6. In some embodiments, one or more detachable clips 1401 may be attached to two or more zip

cables to prevent the zip cables from detaching. This allows for two or more cables to be bundled and reduce the risk of entanglement with additional cables. FIG. 14B is an illustrative example of how easily an embodiment can separate into two individual connectors by unbinding the cables and thus quickly and easily creating two independent fiber optic channels that can move and be connected independently. FIG. 14C shows an embodiment in which a duplex connector like that of FIGS. 6 and 14A is connected to two separate individual connectors. Through the variable housing configurations depicted above in FIG. 10, the cable of FIG. 14A can be reconfigured as the cables of either 14B or FIG. 14C.

[0110] In addition to binding existing fiber cables, some embodiments herein may utilize a new four fiber zip cable. Referring now to FIG. 15A, a conventional zip cable (i.e., one with a single fiber strand 1520 per jacket 1521) is shown in comparison with an embodiment in which two fibers 1522 per jacket 1523 are utilized. It should be understood that this is merely a non-limiting example. In some embodiments, multiple fibers may be included per jacket, such as, for example, four fibers per jacket in order to utilize the single boot 909 and uni-body rear body 906 of the connector shown in FIG. 9.

[0111] A specific example using multi-strand cables is shown in FIG. 16 for illustrative purposes only. It should be understood that numerous alternatives and modifications are possible, such as, for example, that shown in FIGS. 18A-18B and FIGS. 19A-19D. As shown, a switch (e.g., 100G switch) 1630 is shown with a transceiver (e.g., 100G transceiver) 1631. The transceiver 1631 has a receptacle to receive duplex connectors 1632. From each of the two duplex connectors 1632, a four fiber cable 1633 extends to connect to various other connectors and transceivers. In some embodiments, as discussed herein, a clip (e.g., detachable clip) 1640 may connect two or more cables (e.g., 1633) to ensure the zip cables do not come apart. As shown, one four fiber cable 1633 is split into two two-fiber cables 1634, which are then each attached to a single simplex connector 1635 and placed into a transceiver (e.g., 25G transceiver) 1636. As further shown, one of the four fiber cables 1637 is connected to a single duplex connector 1638, which is then inserted into another transceiver (e.g., 50G transceiver) 1639.

[0112] An additional or alternative embodiment is shown in FIG. 17. As shown, one or more switches (e.g., 400G switches) 1730 and 1732 are shown each with a transceiver (e.g., 400G transceiver) 1731 and 1733. The first transceiver 1731 has a receptacle that is receiving two simplex (single) connectors 1734 and one duplex (dual) connector 1735. From each of the two simplex connectors 1734, a two fiber cable 1736 extends to connect to various other connectors and transceivers. Similar to FIGS. 14 and 16, some embodiments may have a clip (e.g., detachable clip) 1740 that may connect two or more cables (e.g., 1736, 1738, etc.) to ensure the zip cables do not come apart. From the duplex connector 1735 a four-fiber cable 1737 is split into two two-fiber cables 1738, which are then each attached to a single simplex connector each and placed into a transceiver (e.g., 400G transceiver).

[0113] Accordingly, embodiments described herein allow for improvements over the current state of the art. By way of specific example, connectors generally have three types of fixed cables. Moreover, some cables may be bifurcated. As such, the cable cannot be split once installed and the polarity

of the cables cannot be changed. Alternatively, the embodiments discussed herein may allow a user to change from a four-way to a 2-Duplex, to a 4-simplex connector, etc. (e.g., FIG. 20). Moreover, as discussed herein, the individual connectors can be split into individual connectors anytime, even after deployment. Additionally, the polarity can be changed within the connectors easily in a manner that does not risk damage to the one or more ferrules and fibers, as discussed above. It should also be noted that the depicted connectors are used herein merely for illustrative purposes, and that various other connectors may be used in any embodiment (e.g., an MT connector, such as that shown in FIGS. 18A-18B, and the optical connectors of FIGS. 21, 37, and 41).

[0114] FIGS. 18A-18B depict an optical connector including an MT ferrule 1810 in a housing that is substantially similar to the housing 301 of FIG. 3. As with the embodiment of FIG. 3, the various features of the connector are configured such that two optical connectors having two MT-type optical ferrules may be accommodated in a small form-factor pluggable (SFP) transceiver footprint or at least four optical connectors having a total of four MT-type optical ferrules may be accommodated in a quad small form-factor pluggable (QSFP) transceiver footprint.

[0115] FIGS. 19A-19D show alternative embodiments of the optical connectors of FIG. 3 in which the push-pull tabs are not integrated with the optical connector housing. As seen in FIGS. 19A-19B, a push-pull tab 1930 is a separable element from a connector housing. The push-pull tab 1930 actuates a latch 1910 for inserting and extracting the connector from an adapter or transceiver. An alternative latching mechanism is depicted in FIGS. 19C-19D. Latch 1950 includes a notch that is actuated by push-pull tab 1960.

[0116] FIG. 20 depicts the disassembly of a four-connector housing (two duplex connectors in a single housing) into two duplex connectors. This may be performed in changing, for example, a connector as shown in FIG. 14A to a connector as shown in FIG. 14C. In FIG. 20, an optical connector 2000 is depicted including a housing 2010 that houses two duplex connectors (four optical fibers). The housing 2010 is removed, leaving the two duplex connectors 2020. Two housings 2030 are then provided and two individual duplex connectors 2040 are then created from the initial single housing connector 2000. This reconfigurable housing simplifies cable management, for example, when optical cables are interconnected between lower-speed transceivers and higher-speed transceivers as seen in FIG. 16.

[0117] FIG. 21A depicts an embodiment of an optical connector 2100, shown in exploded view while 21B depicts the optical connector 2100 in an assembled view. Optical connector 2100 may include an outer housing 2110, a front body 2115, one or more ferrules 2122, one or more ferrule flanges 2124, one or more springs 2125, a back body 2130, a back post 2135, a crimp ring 2140, and a boot 2145. The outer housing 2110 may include a longitudinal bore for accommodating the front body 2115 and a ferrule assembly 2120, a connector alignment key 2105 used during interconnection, a connector flap 2103 and an optional pull tab 2107 to facilitate removal of the connector 2100 when connected in a dense array of optical connectors. Optionally, the ferrules may be LC-type ferrules having an outer diameter of 1.25 mm.

[0118] In prior art optical connectors, an inner enclosed housing was used in place of open front body 2115. Front

body **2115** includes top and bottom portions but no side-walls, termed “open sidewalls” in this embodiment. By using front body **2115**, space occupied by the prior art inner housing sidewalls becomes available to increase the density of optical connectors within a given footprint, an advantage over prior art connectors. It was determined that the outer housing **2110**, combined with the front body **2115**, provided sufficient mechanical strength and ferrule protection, advantageously providing the space for additional optical connectors. Removal of sidewalls increases available space by 1-2 millimeters.

[0119] Note that, in this embodiment, the outer housing is configured to hold two optical ferrules **2122**. Typically, two optical ferrules may be used in a “transmit” and “receive” pairing of optical fibers, called a duplex connector. However, the outer housing may be configured to hold more or fewer optical ferrules including a single optical ferrule, multiples of single optical ferrules, or multiple pairs of optical ferrules, depending upon the application. Further, the front body **2115** may be removed from the outer housing **2110** and the front body placed in a larger outer housing with other front bodies to form a larger optical connector in a manner to be discussed in more detail below. In particular, two front bodies may be used with a four-ferrule outer housing or four front bodies may be used with an eight-ferrule outer housing.

[0120] Turning to FIGS. **29A** and **29B**, isometric and front views of the outer housing **2110** are shown. As seen in the front view of FIG. **29B** and the cross-sectional view of FIG. **29C**, connector orientation protrusions **2910** are provided within the interior of the outer housing **2110**. Connector protrusion **2910** is further seen in the inner view of the housing, FIG. **29E**. When the front body is inserted within the longitudinal bore **2101** of outer housing **2110**, the outer housing connector flap **2103** locks the outer housing **2110** to the front body **2115** in the following manner. As the front body **2115** is inserted into the outer housing **2110**, the outer housing locking surface **2114**, best seen in FIG. **27C**, engages the connector orientation protrusion **2910**, seen in an inside view of the outer housing in FIG. **29D**, labelled as “Flap A”, flexing the connector flap **2103** outwardly from the outer housing body **2110**, depicted in the inset of FIG. **29C**. The flap protrusion mating location is indicated as “mating place B” in FIG. **29D**. Once the locking surface **2114** passes beyond the orientation protrusion, the connector flap returns to its original position (FIG. **29A**), and the protrusion **2910** engages locking surface **2114** and any withdrawal of the front body assembly from the outer housing **2110** is prevented as the proximal end face of the connector flap **2103** is stopped by protrusion **2910**.

[0121] FIGS. **35A-35C** depict the sequence of operations to remove an assembled front body from the outer housing in order to reverse polarity or to aggregate plural connectors in a multi-connector housing. To separate the front body from the outer housing, the connector flap **2103** is flexed outward using a finger or a tool, as depicted in FIG. **35B**. Flexing the connector flap **2103** outwardly causes the protrusion **2910** to disengage from the front body's outer housing locking surface **2114**, permitting the front body/ferrule assembly **2115** to be removed from the outer housing. This may be performed when it is desired to reverse the polarity of the connector (to be discussed below) or when desiring to aggregate plural connectors into a larger connector housing as discussed above. The separated components

are depicted in FIG. **35C**, that is, front body **2115** with the ferrule assembled therein and outer housing **2110**.

[0122] In some embodiments, the back body **2130** may comprise one or more protrusions or hooks **2134**, best seen in FIGS. **28A** and **28B**, which may interlock with a back body hook window/cutout **2119** in the front body **2115**. This may allow for the back body **2130** and the front body **2115** to be securely fastened together around the ferrule(s) **2122**, ferrule flange(s) **2124**, and the spring(s) **2125**. The back body **2130** includes a cable bore **2820**, spring guides **2132**, and side protrusions **2810**.

[0123] During assembly, the ferrule flanges **2124** fit into ferrule flange alignment slots **2117** (see FIGS. **27A** and **27B**) adjacent the ferrule openings **2116** of the front body **2115**, compressing the springs **2125** (preload) which are positioned along front body spring holders **2118**. The ends of the springs **2125** are secured on spring guides **2132** (FIGS. **28A**, **28B**) of back body **2130** by spring tension. As seen in the assembled cross-sectional views of FIGS. **23A** and **23B**, the springs **2125** are positioned to urge the ferrules **2122** into contact with mating connectors or transceiver optics, ensuring minimum insertion loss. As further seen in FIGS. **27A** and **27B**, the front body includes a receptacle hook recess **2710** with a receptacle hook retainer surface **2720** the receiver a receptacle hook when mating with an adapter or with a transceiver receptacle, as shown in further detail below.

[0124] Further reductions in connector size may be obtained by reducing the size of springs **2125**, see FIG. **21**. By using a maximum spring outer diameter of 2.5 mm, the pitch of the ferrules, that is to say, the spacing between adjacent ferrules, may be reduced to 2.6 mm when coupled with the removal of inner housing walls and walls separating adjacent ferrules. This advantage is best seen in FIG. **22** which depicts the front of connector **2100** showing overall connector dimensions and ferrule pitch. The connector size 4.2×8.96×30.85 mm (excluding optional pull tab **2107** and connector alignment key **2105**) with a ferrule pitch of 2.6 mm.

[0125] As best seen in FIG. **21B**, the outer housing **2110** and the front body **2115** together provide a receptacle hook ramp **2940** (on the outer housing) used to guide a receptacle hook into a receptacle hook recess **2170** (in the front body **2115**), also shown in FIGS. **27A** and **27B** (receptacle hook recess **2710** and receptacle hook retainer surface **2720**). The receptacle hook, to be discussed in more detail below, may be from an adapter or a transceiver to secure the optical connector **2100** thereto.

[0126] The optical connectors **2100** may be used in a variety of connection environments. In some applications, the optical connectors **2100** will mate with other optical connectors. Typically, this mating will occur with a receptacle such as an adapter or optical transceiver receptacle. An exemplary adapter **2400** depicted in FIG. **24** in an exploded view and depicted in FIG. **31** having four mating pairs of optical connectors **2100** latched therein. In other applications, as when an optical signal is to be converted to an electrical signal, the micro optical connectors **2100** will mate with an optical receptacle in a transceiver **3600** as shown in FIG. **36**. Typically, transceiver **3600** may be found in a data center, switching center, or any other location where optical signals are to be converted to electrical signals. Transceivers are often a part of another electrical device such as a switch or a server, as is known in the art.

Although much of the connection operation of this embodiment will be described with respect to an adapter, **2400**, it is understood that substantially similar mechanical retention mechanisms are positioned within the receptacle of transceiver **3600** so that any description of connector retention in adapter **2400** applies in a substantially similar way to retention of an optical connector within transceiver **3600**. An example of a transceiver optical receptacle is depicted in FIG. **36B** (holding optical connectors **2100**); as seen in FIG. **36B**, the connection environment is substantially similar to one-half of an adapter **2400**.

[0127] Turning to FIG. **24**, further size reductions in the overall optical assembly of connectors plus adapter or connectors plus transceiver may be obtained through various connection mechanisms to be described with respect to the adapter **2400** but also apply to optical connection features within the front end of transceiver **3600**. The adapter **2400** includes an adapter housing **2402** having an adapter alignment assembly **2430** positioned therein. The adapter alignment assembly **2430** includes alignment sleeves **2410** positioned within alignment sleeve openings **2440** of alignment sleeve holders **2442**. The adapter alignment assembly further includes receptacle hooks **2302** that will grip optical connectors **2100** through front body connector hook recess **2710** of FIG. **21B**. As seen in FIG. **30**, receptacle hooks **2302** include an inner surface **3110**. The adapter housing **2402** further includes connector alignment slots **2403** that mate with connector alignment key **2105** of FIG. **21A**. The connectors **2100** are received through connector opening **2405** of the adapter housing **2402** which also includes flex tab **2401**, cutout **2456**, mount plate **2452** and panel hook **2490**. To assemble the adapter alignment assembly **2430** in the adapter housing **2402**, adapter housing hooks **2432** are provided. Adapter housing hooks **2432** are received in housing adapter hook openings.

[0128] It should be understood that above description of connection mechanisms with respect to adapter **2400** may be applied in a substantially similar way with respect to the receptacle of transceiver **3600**. Particularly, the receptacle of transceiver **3600** may include a receptacle housing having a receptacle alignment assembly positioned therein. The receptacle alignment assembly includes alignment sleeves positioned within alignment sleeve openings of alignment sleeve holders. The receptacle alignment assembly further includes receptacle hooks that will grip optical connectors **2100** through front body connector hook recess **2710** of FIG. **21B**. As seen in FIG. **30**, receptacle hooks **2302** include an inner surface **3110**. The receptacle housing further includes connector alignment slots that mate with connector alignment key of FIG. **21A**. The connectors **2100** are received through connector opening of the receptacle housing which also includes flex tab, cutout, mount plate and panel hook. To assemble the receptacle alignment assembly in the receptacle housing, receptacle housing hooks are provided. Receptacle housing hooks are received in housing receptacle hook openings.

[0129] To further reduce the size of optical connectors and associated mating components, the adapter housing **2402** includes receptacle hook openings **2420**, seen in FIGS. **25A** and **25B**. Receptacle hook openings **2420** accommodate the clearance required by receptacle hooks **2302** when they flex upwards prior to latching with connectors **2100**. The interaction of the receptacle hooks **2302**, having slanted inner surfaces **3110**, with the receptacle hook openings **2420** is

best seen in FIGS. **32B** and **34A-C**. Prior to latching (FIG. **34A**), the receptacle hook **2302** is in an unflexed condition within the receptacle (adapter or transceiver). As the connector **2100** is inserted into the adapter housing **2402** or the transceiver, the receptacle ramp **2490** pushes against the receptacle hook inner surfaces **3110**, flexing receptacle hook **2302** into the receptacle hook opening **2420**. Without providing the opening, additional clearance would need to be provided to accommodate the flexing of the receptacle hook **2302**. This additional required clearance is depicted in the prior art connector/adapter of FIG. **32A**. As seen in FIG. **32A**, a connector latch gap **3210** must be provided in the prior art to accommodate the prior art connector hooks, increasing the overall footprint of the prior art connector/adapter assembly. By providing receptacle hook openings **2420** in the present disclosure, approximately 2.25 mm of valuable footprint real estate is obtained which may be used to increase connector density.

[0130] Another improvement in adapter size is obtained by removing prior art adapter walls between adjacent connectors. This is best seen in the front view of an assembled adapter **2400** shown in FIG. **26**. As seen, pairs of ferrule alignment sleeves **2410** are separated only by connector gap **2610** with a 4.35 mm pitch between adjacent connectors. The adapter size is 19.0×10.71×32.5 mm (excluding the adapter flange **2460**). Also seen in FIG. **26** is the connector alignment slot **2403**, alignment sleeve holder **2442**, and a front view of receptacle hooks **2302**.

[0131] FIG. **31** depicts an assembled adapter **2400** with four pairs of mating connectors **2100** latched therein. Note that in the latched position, receptacle hooks **2302** do not extend into receptacle hook openings **2420**. This is further visible in the cross-sectional view of an assembled adapter **2400** of FIG. **25A**. Connector alignment keys **2105** are positioned within connector alignment slots **2403**. As seen in the cross-sectional view of FIG. **23A**, the push-pull tab **2017** may extend beyond the connector boot **2145** providing clearance to easily grip the tab and remove a connector. Also seen in FIG. **31** is adapter flex tab **2401** and panel hook **2490** for interaction with racks or other equipment.

[0132] Through the various features described above, the density of optical connectors **2100** that may be provided in the standard transceiver footprint connector spaces may be doubled. For example, in a small form factor pluggable (SFP) footprint of 14×12.25 mm, two connectors **2100** having four LC-type ferrules **2122** of 1.25 mm outer diameter may be accommodated as seen in FIG. **33B**. Similarly, in a quad small form factor pluggable (QSFP) footprint of 13.5×19 mm, four connectors **2100** having a total of eight LC-type ferrules **2122** may be accommodated as seen in FIG. **33A**. Further, by providing the connectors in transmit and receive pairs, greater flexibility in optical routing is obtained, as demonstrated by previous FIGS. **16** and **17**.

[0133] Turning to FIG. **37**, another embodiment of an optical connector is depicted. In this embodiment, the last two digits of each element correspond to the similar elements in the optical connector of FIG. **21A** et seq. In FIG. **37**, connector **3700** may include an outer housing **3710**, a front body **3715**, one or more ferrules **3722**, one or more ferrule flanges **3724**, one or more springs **3725**, a back body **3730**, a back post **3735**, a crimp ring **3740** (depicted with an optional heat shrink tube extending therefrom), and a boot **3745**. The outer housing **3710** may include a longitudinal bore **3701** for accommodating the front body **3715** and

ferrules 3722, a connector alignment key 3705 used during interconnection, a connector flap 3703 and an optional pull tab 3707 to facilitate removal of the connector 3700 when connected in a dense array of optical connectors. Optionally, the ferrules may be LC-type ferrules having an outer diameter of 1.25 mm.

[0134] In FIG. 38 an isometric view of the front body 3715 is depicted. In this embodiment, the back body hook cutout 3819 has been moved forward, advantageously strengthening the assembled connector in side load environments. An alignment tab 3895 is provided for mating with a receiving recess on the back body. The receptacle hook recess 3910 operates in a substantially similar manner to the recess of FIG. 21A, described above. A ferrule flange alignment slot 3817 is also provided.

[0135] In FIG. 39, the back body 3730 is depicted, showing alignment tab recess 3997 for receiving alignment tab 3895. The front body hook 3934, for interconnecting in back body hook cutout 3819, extends outwardly from the main portion of the back body through extended hook arm 3996. Through the extended hook arm 3996 and the alignment tab 3895, breakage during side loads is reduced as the load is redistributed more evenly across the entire connector, reducing stress on the backpost.

[0136] As seen in FIGS. 40A-40C, the assembled front body 3715 may be removed from the outer housing 3710, rotated 180° as indicated by the arrow (FIG. 40B), and re-inserted into the outer housing (FIG. 40C). This allows for a change in the polarity of the front body 3715, and therefore the ferrules can switch quickly and easily without unnecessarily risking the delicate fiber cables and ferrules. As described previously with respect to FIGS. 35A-35C, connector flap 3703 is flexed outward to release the front body from the outer housing.

[0137] Turning to FIG. 41, another embodiment of an optical connector is depicted. In this embodiment, the last two digits of each element correspond to the similar elements in the micro optical connectors of FIG. 21A and FIG. 37. In FIG. 41, connector 4100 may include an outer housing 4110, a front body 4115, one or more ferrules 4122, one or more springs 4125, a back body 4130, a crimp ring 4140, and a boot 4145. The outer housing 4110 may include a connector flap 4103 and an optional pull tab 4107 to facilitate removal of the connector 4100 when connected in a dense array of optical connectors. Optionally, the ferrules may be LC-type ferrules having an outer diameter of 1.25 mm.

[0138] As seen in FIG. 42A, the front body 4015 in this embodiment includes a middle wall 4260 interposed between the ferrules and springs when the front body is assembled. This middle wall reduces the possibility of the springs becoming entangled with each other, binding the connector and breaking the optical fibers. The front body 4015 also includes an alignment cut out guide 4625, seen in the side view of FIG. 42B. The alignment cut out guides the back body 4030 into the front body 4015 during assembly of the connector, and also further reduces the side load that leads to connector breakage or disconnection of the front body and the back body 4030.

[0139] Back body 4030, depicted in an enlarged view in FIG. 43, includes an alignment guide 4377 that fits into the alignment cut out guide 4265 of FIG. 42B. The wall structure 4378 also stops the front body to prevent over-compressing the springs and provides strength under a side load.

[0140] Various modifications to the outer housing, depicted in FIGS. 44A-44C, may be used with any of the optical connectors depicted in FIGS. 21, 37, and 41 or earlier embodiments. In FIG. 44A, the push-pull tab 3707 may include a release recess 4473. Release recess 4473 permits insertion of a tool or fingernail to remove the connector from an adapter or transceiver, without disturbing adjacent connectors. Similarly, FIG. 44B depicts a release hole 4499 in push-pull tab 3707 to permit insertion of an extraction tool to remove the connector from an adapter or transceiver. FIG. 44C shows a modified connector flap 3703 with an increased cutout size of 1 mm to make it easier to insert a tool or a finger to flex the flap 3703 and remove the front body assembly when making a polarity change or aggregating the front body with other front bodies in a larger outer housing.

[0141] Another embodiment of an adapter/transceiver receptacle is depicted in FIG. 45. Unlabeled elements are substantially similar to elements depicted in FIG. 24. In this FIG., adapter housing hooks 4532 can be seen along with receptacle hooks 4502. Turning to the cross-sectional view of the assembled adapter in FIG. 46, the engagement of these elements may be seen.

[0142] Another embodiment of an optical connector 4700 is depicted in FIG. 47. The optical connector of FIG. 47 includes outer housing 4710, front body 4715, ferrules 4722, springs 4725, back body 4730, backpost 4735, crimp ring 4740, and boot 4745. Here, the emphasis is on the back body, 4730. A more detailed view of the back body 4730 is presented in FIG. 48. In this embodiment, the backpost flange has a substantially rectangular shape in order to narrow the overall connector profile by approximately 0.5 mm. Back post overmolding 4859 accommodates the back post flange 4857 and reduces the potential for back post breakage. The back wall 4853 is extended in length to 3 mm from 1.5 mm to improve the sideload strength of the overall connector. The crimp ring positioning 4855 is inversed from earlier embodiments to improve holding of aramid fiber from an optical fiber cable, improving cable retention of the back post.

[0143] Many advantages are achieved by the backpost of FIG. 48. In addition to increased connector strength, a longer fiber path 4901 is provided as shown in FIG. 49. This longer fiber path, approximately 1.5 mm longer than in previous embodiments, allows for a gentler curve as the fibers are split from the fiber optic cable, improving insertion and return loss of the fibers. In FIG. 49, the back wall 4853 can be seen as a portion of the back body 4730.

[0144] In view of the various modifications of this embodiment, FIG. 50 depicts a connector 4700 front view showing overall reduced connector width of 3.85 mm. Such a size reduction permits 4 optical connectors (a total of 8 ferrules) to be accommodated in a transceiver or connector footprint of 16 mm (including tolerances). Thus, the connectors of the present invention may be used to connect 8 LC-ferrule-housed fibers in a QSFP footprint.

[0145] To further decrease the space required by the optical connectors, a side thickness reduction may be carried out on the boot of connector 4700. Side thickness reduction 5103, depicted in FIG. 51, narrows the thickness of the boot on either side, reducing the space required by the boot to the 3.85 mm profile of connector 4700. Thus four connectors will fit in the QSFP transceiver footprint. This footprint is shown in the adapter front view of FIG. 52—as noted above, the front view of an adapter and that of a transceiver are

substantially similar from the optical perspective. In FIG. 52, the adapter inner wall is reduced from 17.4 mm to 16 mm. All of the modifications set forth in the FIG. 47 et seq. embodiment make it possible for the four connectors to fit in the profile of FIG. 52.

[0146] In the above detailed description, reference is made to the accompanying drawings, which form a part hereof. In the drawings, similar symbols typically identify similar components, unless context dictates otherwise. The illustrative embodiments described in the detailed description, drawings, and claims are not meant to be limiting. Other embodiments may be used, and other changes may be made, without departing from the spirit or scope of the subject matter presented herein. It will be readily understood that the aspects of the present disclosure, as generally described herein, and illustrated in the Figures, can be arranged, substituted, combined, separated, and designed in a wide variety of different configurations, all of which are explicitly contemplated herein.

[0147] The present disclosure is not to be limited in terms of the particular embodiments described in this application, which are intended as illustrations of various aspects. Many modifications and variations can be made without departing from its spirit and scope, as will be apparent to those skilled in the art. Functionally equivalent methods and apparatuses within the scope of the disclosure, in addition to those enumerated herein, will be apparent to those skilled in the art from the foregoing descriptions. Such modifications and variations are intended to fall within the scope of the appended claims. The present disclosure is to be limited only by the terms of the appended claims, along with the full scope of equivalents to which such claims are entitled. It is to be understood that this disclosure is not limited to particular methods, reagents, compounds, compositions or biological systems, which can, of course, vary. It is also to be understood that the terminology used herein is for the purpose of describing particular embodiments only, and is not intended to be limiting.

[0148] With respect to the use of substantially any plural and/or singular terms herein, those having skill in the art can translate from the plural to the singular and/or from the singular to the plural as is appropriate to the context and/or application. The various singular/plural permutations may be expressly set forth herein for sake of clarity.

[0149] It will be understood by those within the art that, in general, terms used herein, and especially in the appended claims (for example, bodies of the appended claims) are generally intended as “open” terms (for example, the term “including” should be interpreted as “including but not limited to,” the term “having” should be interpreted as “having at least,” the term “includes” should be interpreted as “includes but is not limited to,” et cetera). While various compositions, methods, and devices are described in terms of “comprising” various components or steps (interpreted as meaning “including, but not limited to”), the compositions, methods, and devices can also “consist essentially of” or “consist of” the various components and steps, and such terminology should be interpreted as defining essentially closed-member groups. It will be further understood by those within the art that if a specific number of an introduced claim recitation is intended, such an intent will be explicitly recited in the claim, and in the absence of such recitation no such intent is present. For example, as an aid to understanding, the following appended claims may contain usage of the

introductory phrases “at least one” and “one or more” to introduce claim recitations. However, the use of such phrases should not be construed to imply that the introduction of a claim recitation by the indefinite articles “a” or “an” limits any particular claim containing such introduced claim recitation to embodiments containing only one such recitation, even when the same claim includes the introductory phrases “one or more” or “at least one” and indefinite articles such as “a” or “an” (for example, “a” and/or “an” should be interpreted to mean “at least one” or “one or more”); the same holds true for the use of definite articles used to introduce claim recitations. In addition, even if a specific number of an introduced claim recitation is explicitly recited, those skilled in the art will recognize that such recitation should be interpreted to mean at least the recited number (for example, the bare recitation of “two recitations,” without other modifiers, means at least two recitations, or two or more recitations). Furthermore, in those instances where a convention analogous to “at least one of A, B, and C, et cetera” is used, in general such a construction is intended in the sense one having skill in the art would understand the convention (for example, “a system having at least one of A, B, and C” would include but not be limited to systems that have A alone, B alone, C alone, A and B together, A and C together, B and C together, and/or A, B, and C together, et cetera). In those instances where a convention analogous to “at least one of A, B, or C, et cetera” is used, in general such a construction is intended in the sense one having skill in the art would understand the convention (for example, “a system having at least one of A, B, or C” would include but not be limited to systems that have A alone, B alone, C alone, A and B together, A and C together, B and C together, and/or A, B, and C together, et cetera). It will be further understood by those within the art that virtually any disjunctive word and/or phrase presenting two or more alternative terms, whether in the description, claims, or drawings, should be understood to contemplate the possibilities of including one of the terms, either of the terms, or both terms. For example, the phrase “A or B” will be understood to include the possibilities of “A” or “B” or “A and B.”

[0150] In addition, where features or aspects of the disclosure are described in terms of Markush groups, those skilled in the art will recognize that the disclosure is also thereby described in terms of any individual member or subgroup of members of the Markush group.

[0151] As will be understood by one skilled in the art, for any and all purposes, such as in terms of providing a written description, all ranges disclosed herein also encompass any and all possible subranges and combinations of subranges thereof. Any listed range can be easily recognized as sufficiently describing and enabling the same range being broken down into at least equal halves, thirds, quarters, fifths, tenths, et cetera. As a non-limiting example, each range discussed herein can be readily broken down into a lower third, middle third and upper third, et cetera. As will also be understood by one skilled in the art all language such as “up to,” “at least,” and the like include the number recited and refer to ranges which can be subsequently broken down into subranges as discussed above. Finally, as will be understood by one skilled in the art, a range includes each individual member. Thus, for example, a group having 1-3 cells refers

to groups having 1, 2, or 3 cells. Similarly, a group having 1-5 cells refers to groups having 1, 2, 3, 4, or 5 cells, and so forth.

[0152] Various of the above-disclosed and other features and functions, or alternatives thereof, may be combined into many other different systems or applications. Various presently unforeseen or unanticipated alternatives, modifications, variations or improvements therein may be subsequently made by those skilled in the art, each of which is also intended to be encompassed by the disclosed embodiments.

1. A reconfigurable optical connector for holding two or more LC-type optical ferrules, comprising:

- a removable outer housing having a longitudinal bore;
- at least one inner front body removably received in the outer housing longitudinal bore, the inner front body supporting two LC-type optical ferrules, the inner front body comprising top and bottom portions with open sidewalls, the inner front body further comprising a receptacle hook recess configured to receive a receptacle hook from a mating receptacle;
- ferrule springs for urging the optical ferrules towards the mating receptacle; and
- a back body for supporting the ferrule springs.

2. The reconfigurable optical connector of claim 1, further comprising a flap in the outer housing having a retainer on the inner side thereof for holding the front body to the outer housing.

3. The reconfigurable optical connector of claim 1, further comprising a wall in the front body for separating the ferrule springs from each other.

4. The reconfigurable optical connector of claim 1, further comprising a push-pull tab on the outer housing for inserting or removing the optical connector from a mating component.

5. The reconfigurable optical connector of claim 4, wherein the push-pull tab includes a recess or a release hole for insertion of a finger or a release tool.

6. The reconfigurable optical connector of claim 1, wherein the inner front body includes an alignment tab for aligning with a receiving recess on the back body.

7. The reconfigurable optical connector of claim 1, wherein the outer housing is configured to hold four LC-type optical ferrules in two inner bodies.

8. The reconfigurable optical connector of claim 1 wherein the outer housing is configured to hold eight LC-type optical ferrules in four inner bodies.

9. An optical cable terminating in the reconfigurable optical connector of claim 1.

10. A method of reconfiguring an optical cable, comprising:

providing the optical cable of claim 9;

removing the outer housing;

inserting the inner front body, ferrules, ferrule springs, and back body into at least one second outer housing, the second outer housing having greater or lesser optical ferrule capacity than the outer housing.

11. The method of reconfiguring an optical cable according to claim 10, wherein the outer housing has a two-ferrule capacity and the second outer housing has a four-ferrule or eight-ferrule capacity.

12. The method of reconfiguring an optical cable according to claim 10, wherein the outer housing has a four-ferrule capacity and the at least one second outer housing comprises two second housings, each of the two second housings having a two-ferrule capacity.

13. The method of reconfiguring an optical cable according to claim 10, wherein the outer housing has an eight-ferrule capacity and the at least one second outer housing comprises four second housings, each of the four second housings having a two-ferrule capacity.

14. The method of reconfiguring an optical cable according to claim 10, wherein the outer housing has an eight-ferrule capacity and the at least one second outer housing comprises two second housings, each of the two second housings having a four-ferrule capacity.

15. The method of reconfiguring an optical cable according to claim 10, wherein the outer housing has an eight-ferrule capacity and the at least one second outer housing comprises three second housings, one of the three second housings having a four-ferrule capacity and two of the three second housings having a two-ferrule capacity.

16. In an optical connector holding two or more LC-type optical ferrules having an outer body, an inner front body accommodating the two or more LC-type optical ferrules, ferrule springs for urging the optical ferrules towards a mating connection, and a back body for supporting the ferrule springs, the improvement comprising configuring the outer body and the inner front body such that two optical connectors having four LC-type optical ferrules are accommodated in a small form-factor pluggable (SFP) transceiver footprint.

17. In an optical connector holding two or more LC-type optical ferrules having an outer body, an inner front body accommodating the two or more LC-type optical ferrules, ferrule springs for urging the optical ferrules towards a mating connection, and a back body for supporting the ferrule springs, the improvement comprising configuring the outer body and the inner front body such that at least two optical connectors having a total of eight LC-type optical ferrules are accommodated in a quad small form-factor pluggable (QSFP) transceiver footprint.

* * * * *